INFORMATION TO USERS

The most advanced technology has been used to photograph and reproduce this manuscript from the microfilm master. UMI films the text directly from the original or copy submitted. Thus, some thesis and dissertation copies are in typewriter face, while others may be from any type of computer printer.

The quality of this reproduction is dependent upon the quality of the copy submitted. Broken or indistinct print, colored or poor quality illustrations and photographs, print bleedthrough, substandard margins, and improper alignment can adversely affect reproduction.

In the unlikely event that the author did not send UMI a complete manuscript and there are missing pages, these will be noted. Also, if unauthorized copyright material had to be removed, a note will indicate the deletion.

Oversize materials (e.g., maps, drawings, charts) are reproduced by sectioning the original, beginning at the upper left-hand corner and continuing from left to right in equal sections with small overlaps. Each original is also photographed in one exposure and is included in reduced form at the back of the book.

Photographs included in the original manuscript have been reproduced xerographically in this copy. Higher quality 6" x 9" black and white photographic prints are available for any photographs or illustrations appearing in this copy for an additional charge. Contact UMI directly to order.

University Microfilms International
A Bell & Howell Information Company
300 North Zeeb Road, Ann Arbor, MI 48106-1346 USA
313/761-4700 800/521-0600

Order Number 9035272

**Dual control of linear stochastic systems with unknown
parameters**

Chen, Rong, Ph.D.

Case Western Reserve University, 1990

U·M·I
300 N. Zeeb Rd.
Ann Arbor, MI 48106

DUAL CONTROL OF LINEAR STOCHASTIC SYSTEMS WITH UNKNOWN PARAMETERS

by
RONG CHEN

**Submitted in partial fulfillment of the requirements
for the Degree of Doctor of Philosophy**

Thesis Advisor: Kenneth A. Loparo

**Department of Systems Engineering
CASE WESTERN RESERVE UNIVERSITY
MAY 1990**

CASE WESTERN RESERVE UNIVERSITY

GRADUATE STUDIES

We hereby approve the thesis of

RONG CHEN

candidate for the Ph. D.

degree.*

Signed:

Kenneth A. Aspin
(Chairman)

N. Sreenivas

Prof. J. C. H.
John M. Philpott

Date April 26, 1990

*We also certify that written approval has
been obtained for any proprietary material
contained therein.

I grant to Case Western Reserve University the right to use this work, irrespective of any copyright, for the University's own purposes without cost to the University or to its students, agents and employees. I further agree that the University may reproduce and provide single copies of the work, in any format other than in or from microforms, to the public for the cost of reproduction.

Rong Chen

DUAL CONTROL OF LINEAR STOCHASTIC SYSTEMS WITH UNKNOWN PARAMETERS

ABSTRACT

by

RONG CHEN

Closed loop control of linear stochastic control system with unknown parameters is studied by using a dual control approach. For control problems with either imperfect state observations or parameter uncertainties, the control signal to the system can actively influence the knowledge about the state of the system or about the parameters of the system. The dual controller is designed to regulate the state or output of the system to reach a certain goal and actively probe the system to obtain more information about the unknown system parameters. At each stage, the cost functional associated with the system objective is decomposed into a certainty equivalence cost and a dual cost. The active learning feature of the (dual) control explicitly accounts for the reduction of the dual cost, which measures the uncertainty of the system. An approximation technique is used to obtain a recursive closed form solution of the equations of functional dynamic programming. The dual control algorithm developed reduces the overall cost. Moreover, the algorithm is shown to be the best affine dual controller and it is very simple to implement. In certain

situations, using an appropriate dual cost approximation, the computational overhead for the algorithm is minimum, and real-time control applications are practical.

Dedicated to Mom

ACKNOWLEDGEMENTS

My sincere appreciation goes to my thesis advisor Professor K. Loparo, for suggesting this challenging research topic, for his time, guidance and encouragement which are invaluable to me in the completion of this thesis.

I would like to thank Professors H. Chizeck, N. Sreenath, and S. Phillips who served in my thesis committee and gave many suggestions.

Finally, I would like to thank my wife and my family for their patience, understanding, support and encouragement throughout the time of my study. I will always be grateful to them.

TABLE OF CONTENTS

Chapter 1: Introduction	1
1.1 General Overview	1
1.2 Previous Works	5
Chapter 2: Mathematical Formulation	11
2.1 Concept of Controls	11
2.2 Problem Statement	19
2.3 Mathematical Preliminary	22
Chapter 3: Two Stage Dual Control Problem	27
3.1 The Performance Function	27
3.2 The Dual Control Policy	36
Chapter 4: Finite Horizon Dual Control Problem	52
4.1 Dual Cost Evaluation, Two-mode Case	52
4.2 Approximation of the Dual Cost	62
4.3 The Dual Control Algorithm	67
4.4 Multi-mode Dual Control System	71
4.5 Systems with All Parameters Unknown	73
4.6 Convergence of the <i>a posteriori</i> Probabilities	78
4.7 Best Affine Suboptimal Control Theorem	86

Chapter 5: Simulations	91
5.1 A Simple Example	91
5.2 Conditions for Dual Control	98
5.3 Near Minimum Dual Cost Control	110
5.4 Error from Dual Cost Approximation	122
Chapter 6: Conclusion	134
References	136

LIST OF FIGURES

Figure		Page
3.1	Dual Cost as Function of Control, Same Initial States	38
3.2	Dual Cost as Function of Control, Diff. Initial States	47
4.1(a)	Integral in Eq(4.52), Observation Mean Apart	83
4.1(b)	Integral in Eq(4.52), Observation Mean Close	84
5.1	Cost-to-go as Function of Control	94
5.2	CE as Function of Control	95
5.3	Dual Cost as Function of Control	96
5.4	Cost-to-go as Function of Control, State Weighting Varies .	101
5.5	CE Cost as Function of Control, State Weighting Varies . .	102
5.6	Dual Cost as Function of Control, State Weighting Varies .	103
5.7	Total Cost and CE Cost vs Control	104
5.8(a)	Cost-to-go, Local Minimum of Dual Cost Is Not Low . . .	111
5.8(b)	Dual Cost, Local Minimum of Dual Cost Is Not Low	112
5.9(a)	Cost-to-go, Local Minimum Varies as C_1 Varies, $C_2 = -0.1$.	115
5.9(b)	Cost-to-go, Local Minimum Varies as C_1 Varies, $C_2 = 0.1$.	116
5.10(a)	Illustration of the Near Minimum Dual Cost Control	118
5.10(b)	Comparison of Dual Cost and the Approximation	125

Figure	Page
5.11(a) Error of Dual Cost at CE Control, $C_i C_j > 0$	127
5.11(b) Error of Dual Cost at Dual Control, $C_i C_j > 0$	128
5.11(c) Error of Dual Cost at CE Control, $C_i C_j < 0$	129
5.11(d) Error of Dual Cost at Dual Control, $C_i C_j < 0$	130
5.12(a) Dual Control Converges to Optimal Dual Cost Control . . .	131
5.12(b) Dual Cost Converges to Optimal Dual Cost	132
5.12(c) Dual Control Total Cost Converges to Optimal Total Cost .	133

LIST OF TABLES

Table		Page
5.1	Comparison of CE and Dual Control Cost, 2-stage Problem . .	98
5.2	Comparison of CE and Dual Control Cost, 5-stage Problem . .	99
5.3	A 10-stage System That Needs Dual Control	109
5.4	A 10-stage System That Does Not Need Dual Control . . .	109
5.5	Comparison of Dual and Near Minimum Dual Controls . .	121

CHAPTER ONE

Introduction

1.1 General Overview

Stochastic optimal control problems have been extensively studied by control engineers. Since the dynamics of many systems can change abruptly, for example, resulting from disturbances in the process or component failures, the objective is to have the controllers adapt and make appropriate changes in the control law so that the closed-loop systems can achieve satisfactory performances under varying circumstances.

Except for a few situations, the optimal control problem for a stochastic system with unknown parameters is not explicitly solvable. The difficulty arises because identification and regulation are often competing control objectives. Such a difficulty is often related to the so called “separation property”. Roughly speaking, the separation property refers to the case when the optimal controller design can be decomposed into two independent problems: a state estimation problem to determine the “best” estimate of the states from the observed outputs, and the design of an “optimal” feedback control law as a function of the state estimates. In this situation, the estimation and the feedback control are designed separately. Of course, the controller design may depend on the uncertainties of the estimated system parameters.

Stochastic control problems do not have, generally, the separation property, i.e. the estimator and controller cannot be designed separately, and the concept of dual control is important. The control is doing two tasks simultaneously, while controlling or regulating the system, it is also improving the estimates of unknowns and reducing uncertainty. Such a complication inevitably makes the analysis much more difficult and generally the solutions are either extremely complicated, or unsolvable, even for rather simple cases.

In situations where the separation property does not hold, suboptimal control strategies are derived such that (i) they closely approximate the optimal control; (ii) are easily implemented in the real process. Most of the suboptimal controllers which have been proposed, do not consider the interaction between the identification and the control. This means that the control laws are not designed to facilitate the identification. The control strategies are usually designed to minimize some control error recognizing that the parameters are uncertain. Reducing uncertainty through learning is not active but "accidental", or passive. In a *dual controller* there is, however, an interaction between the identification and the control in the sense that the controller must compromise between a control action and a probing action for active learning. The interaction is obtained by considering that the future uncertainties of the parameters are functions of the control signals applied to the system. The performance function, which has to be minimized contains some information of the future observation process through the conditional statistics of the

observations. A sufficient set of statistics for the problem may not be finite dimensional, this makes the implementation of more complicated on-line control difficult and sophisticated dual controllers as practical solutions to real control problems must deal with the “curse of dimensionality” inherent in dynamic programming.

This work discusses the dual control for the class of linear stochastic systems with unknown parameters, which have the dual effect of the control. A dual control algorithm is developed which can be easily implemented and also provides good performance.

The method is to decompose the cost functional into a certainty equivalence cost and a dual cost at each stage. The active learning feature of the dual control is represented by the reduction of the dual cost, thereby reducing the uncertainty of the system. An approximation technique is used to obtain a recursive closed form solution of the functional equations of dynamic programming. With an appropriate dual cost approximation, the computational complexity can be reduced to make the algorithm practical. Finally, the error which results from the approximation is analyzed and situations when the dual controller is required in order to obtain a significant improvement of performance of the system over the Certainty Equivalence controllers are discussed. Simulations show that the proposed dual control algorithm gives nearly optimal control. Future research directions on the dual control are also discussed.

Why is the dual control so important? When estimates of system parameters or the state are not sufficiently accurate, the certainty equivalence control law may give very poor performance, since the controller is designed based on incorrect knowledge about the system. The principle of dual control, on the other hand, takes into account the "quality" of the estimates and attempts to reconcile short term regulation objectives and long term objectives for reducing future uncertainty. Therefore, dual control finds its importance in applications where the knowledge of the control system structure can not be learned well enough with the usual certainty equivalence controller. Active learning is particularly important in problems where incipient failure detection is important.

Existing dual controller designs, implemented using numerical methods or approximations, are usually too complicated to be practical. Therefore, the additional expenses of synthesizing a dual controller design will outgrow the possible benefits, and potential applications of such techniques will not be attempted.

The contribution of this work is to develop a simple and efficient approach of dual controller design, that is, a one-step-ahead closed-loop feedback control strategy. The approach is not only simple, but also efficient since it is the best possible affine control strategy. The proposed dual control algorithm is much simpler than other existing dual control algorithm in the literature.

1.2 Previous Works

In some instances, the dual controller can have superior properties when compared to non-dual controllers, and it is desirable to find solutions for the dual control problem.

The formal solution of the dual control problem has been known for many years (Fel'dbaum 1960, Aoki 1967), the solution, however, leads to a functional equation, which generally is difficult or even impossible to solve, due to the fact that the conditional distribution of the state and estimated parameters is not necessarily Gaussian. The optimal control is generally nonlinear and the resulting control law can not be obtained in closed form. Implementation often requires a look-up control table to determine the values of control for each stage.

A number of papers have studied examples in order to gain some understanding of dual controllers. For example, Florentine (1962) solved the first order system with the control gain unknown but fixed, given an *a priori* distribution, the state is completely known, and the resulting optimal control law after three steps is obtained as a control table. It shows better performance than that a one-step optimizing controller.

Other numerically solved problems include Jacobs and Langdon (1970), Schwartz and Steigletz (1971), Griffiths and Loparo (1985) and Åström and Wittenmark (1971). The examples of optimal dual control can be used to

evaluate other different suboptimal controllers, and to study the dual property of the optimal control law, i.e., the interaction between the estimation and the control requires a compromise between probing and regulation. The interaction results from the future uncertainties of the system and the system states.

Gorman and Zaborszky (1968) and Grammaticos and Horowitz (1970) discussed the special cases where the state is measurable, the poles of the system are known, but zeros are unknown. The solution is given in terms of the standard Riccati equation and the solution of a set of differential or difference equations.

Some intuitive suboptimal dual controllers are developed to avoid the turn-off phenomenon caused by cautiousness. The covariance matrix of the parameter estimates cause the controller to be cautious when the estimates are poor. When the estimates are poor the magnitude of control effort can become very small. In this case, the controller will not excite the system and the estimates in the future may not improve, and the cautious operation of the controller continues. The control can be turned off for some period of time until the noise excites the system and better estimates are achieved. A method used by Wieslander And Wittenmark (1971), and Jacobs and Patchell (1972) is to add a perturbation to a non-dual controller to excite the system in order to obtain better estimation. Hughs and Jacobs (1974) designed a controller which incorporates a logic switch to prevent the control signal from becoming too small. However, these controllers do not possess the active (or intentional)

probing function which is inherent from the interaction of estimation and control.

Alster and Belanger (1974) considered a one-step ahead minimization problem, subject to a constraint on the trace of the one-step ahead information matrix, such that the controller can maintain good parameter identification using a trade-off between regulation and the identification error covariance. Wittenmark (1975) used a similar approach, by adding a weighted function of the one-step ahead error covariance to the loss function; the identification cost is introduced into the total cost and the problem is numerically solved. However, in many situations, for example, in the jump LQG problem, an identification cost appears naturally in the cost-to-go function as discussed in Casiello and Loparo (1989). Therefore, an additional identification cost is only an approximation of the true identification cost which results from the original problem formulation.

Another method (Milito, 1982) of introducing an identification cost to the cost-to-go of dynamic programming is to include the weighted covariance of the innovations process. The resulting controller is easy to implement and its performance is compared with the certainty equivalence controller and a cautious controller.

In Padilla *et al.* (1979), the control takes into account the accuracy of the estimation and redistributes the estimation effort through the design of a weighting matrix. The problem formulation incorporates an estimation cost

function which depends on the sensitivity of the states, or output with respect to the unknown parameters.

Chan and Zarrop (1985) incorporated system output variance in to the cost function using a self-tuning regulator procedure, to introduce uncertainty of parameter estimation to the controller design, to improve performance. In Casiello and Loparo (1985), the quadratic cost function of a jump linear system was decomposed into trajectory part and learning part, an identification feedback based on the learning part was introduced in such a way that it reduces the identification cost in order to minimize the overall cost.

In Tse (1973a), more general systems were analyzed. The system is modelled by nonlinear dynamics with nonlinear observations, the method developed attempts to maintain the closed-loop feature of the control, hence the dual property, by approximating the future trajectory by a nominal trajectory up to the second order. The future observation program and the associated statistics are evaluated along the nominal trajectory and the cost-to-go can be decomposed into deterministic, cautious and probing costs. The probing cost is a function of the one-step ahead covariance of the future state, and the covariance of the state estimates at remaining stages propagate deterministically, that is, along the nominal future trajectory fixed at the current deterministic values. A numerical solution admits a one-step dual control.

An algorithm was presented in Tse (1973b) for linear system with unknown parameters, where the parameter is governed by a known Markov process

and the cost is quadratic, using the approach of Tse (1973a). The speed of parameter convergence and the computational load were also discussed via simulations.

Dersin (1981) analytically compared the properties of the suboptimal dual controller presented by Tse (1973a) with those of the optimal control, for a simple scalar system, where the states were perfectly known, the dynamics evolve noise free, but the system parameters are Gaussian white noises with known covariances. Without the possibility of improving estimation, however, the analysis of Tse's suboptimal control may not be meaningful.

In closed-loop control system the impact on future uncertainties is explicitly accounted for (Tse, 1973a). The open-loop feedback approach (e.g., Dreyfus, 1964; Aoki, 1967; Bar-Shalom, 1969; Curry, 1969; Deshpande et al, 1973; Spang, 1965; Tse, 1972) does not have the dual control property, i.e. there is no active learning to improve future estimates and the stochastic system performance may be seriously deteriorated by such controllers (Witsenhausen 1971; Tse 1973a).

In Patchell and Jacobs (1971), the properties of separation, neutrality and certainty equivalence have been studied and the relationships between these properties were discussed, in the context that the design of optimal control may be simplified for systems having these properties. They suggested that neutrality may be sufficient for certainty equivalence. As uncertainty in stochastic systems can be considered in the form of irreducible uncertainty, such

as noises, and reducible uncertainty such as unknown parameters and states (Jacobs, 1964), the control has the inevitable task to reduce the uncertainty in controlling the system. Being aware of this, a good or optimal controller should actively perform such a dual function, passive controllers leave the work to filtering only (Fel'dbaum, 1965).

From the viewpoint of separation between filtering and controller design, the idea was first discussed by Gunkel and Franklin (1963), Joseph and Tou (1961), Stratonovich (1962) and Striebel (1965), and defined by Wonham (1968). A separation theorem was proved for a certain class of neutral systems.

The only result on the connection between the neutrality of the system and the certainty equivalence property was reported by Bar-Shalom and Tse (1974). They showed that for systems of linear dynamics with white process noise, nonlinear measurement, and quadratic cost, neutrality is equivalent to certainty equivalence. In general, neutrality is not sufficient for certainty equivalence, an example worked out by Athans (1977) is illustrative. In this example, no uncertainties can be reduced by control, but the optimal control differs from the certainty equivalence control in the sense that it also considers the uncertainties of unknowns, while certainty equivalence assumed the uncertainties were zero. Hence, the optimal control is a cautious control. In this example, the optimal control also had the separation property, since no filtering was needed. Thus certainty equivalence implies separation and neutrality.

CHAPTER TWO

Mathematical Formulation

2.1 Concept of Controls

In this section we discuss the concept of dual control and other associated concepts, as well as their definitions in order to better understand the dual control problem.

(1) Consider the following general stochastic control problem

$$x(t+1) = f(t, x(t), u(t), v(t)) \quad t = 0, 1, 2, \dots \quad (2.1)$$

where state $x(t) \in R^n$, control $u(t) \in R^m$, process noise $v(t) \in R^n$. The measurements are generated according to

$$y(t) = h(t, x(t), w(t)) \quad t = 0, 1, 2, \dots \quad (2.2)$$

where observation $y(t) \in R^p$, and measurement noise $w(t) \in R^p$.

We use the notation given below to represent eqs(2.1)-(2.2)

$$x_{t+1} = f_t(x_t, u_t, v_t) \quad t = 0, 1, 2, \dots$$

$$y_t = h_t(x_t, w_t) \quad t = 0, 1, 2, \dots$$

The initial state x_0 , and the noises v_t and w_t are random variables defined on the probability space $(\Omega, \mathcal{F}, \mathcal{P})$. The random variables are measurable with

respect to $\omega \in \Omega$, $\mathcal{F}$ denotes a σ -field and $\mathcal{P}$ is a probability measure defined on $\mathcal{F}$.

Denote

$$\begin{aligned} X_0^N &= \{x_i\}_{i=0}^N \\ U_0^{N-1} &= \{u_i\}_{i=0}^{N-1} \\ Y^t &= Y^t(\omega, U_0^{N-1}) = \{y_i\}_{i=0}^t \quad 0 \leq t < N. \end{aligned}$$

The performance of the control system is measured by the cost function J which is to be minimized

$$J = E\{V^N(X_0^N, U_0^{N-1})\} \quad (2.3)$$

where $V : R^n \times R^m \rightarrow R^1$, i.e., we seek the optimal control sequence U_0^{N-1} such that

$$J(U_0^{N-1,*}) \leq J(U_0^{N-1}) \quad \text{for all } U_0^{N-1} \in U$$

where U is the admissible set of controls defined as the class of all non-anticipatory control laws, i.e. for all $u \in U$

$$u(t) = u(t, Y^t, U_0^{t-1}) \quad t = 0, 1, \dots, N-1 \quad (2.4)$$

Denote the dynamics by

$$D = f_t(\cdot, \cdot, \cdot)_{t=0}^{N-1} \quad t = 0, 1, \dots, N-1$$

and the measurement by

$$M^t = h_t(\cdot, \cdot)_{i=0}^t \quad t = 0, 1, \dots, N-1,$$

the statistics of the information set is characterized by the joint probability law of random variables $(x_0, v_0, \dots, v_{n-1}, w_0, \dots, w_{n-1})$

$$S^t = dP(x_0, v_0, \dots, v_{n-1}, w_0, \dots, w_t)$$

The definition of an admissible control, u_t , requires that it be a (Y^t, U^{t-1}) measurable functional. Here, D , M^t and S^t are assumed given. The stochastic control problem is then well defined (Bertsekas 1976).

(2) In the following, the concepts associated with the various types of information patterns in stochastic control (Witsenhausen, 1971) are discussed.

(i) The open-loop control: the controller does not use any measurement at all. It can be written as

$$u_t^{OL} = u_t^{OL}(V^N, D, S^0) \quad t = 0, 1, \dots, N-1 \quad (2.5)$$

hence it is a mapping of knowledge of the initial state and system dynamics only.

(ii) The feedback control: the controller uses the knowledge of the past and present information, but knowledge about future measurements is not considered. It may be written as

$$u_t^F = u_t^F(V^N, D, M^t, S^t, Y^t, U^{t-1}) \quad t = 0, 1, \dots, N-1 \quad (2.6)$$

For example, one form of feedback control is the so called open-loop optimal feedback control (OLOF), which *assumes that no future observations will be available*, that is, the controller assumes that operation in the future will be open-loop.

(iii) Closed-loop control: this includes two types of controls,

a) Closed-loop control: the knowledge that the loop will stay closed through the end of process is fully used, *the controller knows that future observations will be made* and then causally anticipates all the future observations. It is in the form

$$u_t^{CL} = u_t^{CL}(V^N, D, M^{N-1}, S^{N-1}, Y^t, U^{t-1}) \quad t = 0, 1, \dots, N-1 \quad (2.7)$$

Compare with OLOF control, they differ in the use of knowledge about the future observations.

b) m -measurement feedback control (Curry 1969): the loop will stay closed for the next m stages, the control then uses the knowledge about the next m observations. It can be considered to be a partially closed-loop policy

$$u_t^{mF} = u_t^{mF}(V^N, D, M^{t+m}, S^{t+m}, Y^t, U^{t-1}) \quad t = 0, 1, \dots, N-1 \quad (2.8)$$

when $t > N-1-m$, $u_t^{mF} = u_t^{CL}$.

From this classification, the admissible optimal control u_t^* is the closed-loop control u_t^{CL} and all other types may be considered to be suboptimal controls if they are not equivalent to the closed-loop control u_t^{CL} .

Denote the minimum of the costs associated with the above control policies by

$$J^*(u^{OL}), J^*(u^F), J^*(u^{CL}) \text{ and } J^*(u^{mF}),$$

respectively. It is obvious that

$$J^*(u^{CL}) \leq J^*(u^{OL}) \quad (2.9)$$

simply because the class of controllers that do not take into account the measurements is a strict subset of the class of admissible controllers U .

It can also be shown (Bertsekas, 1976) that the relationship between the minimum costs for the various control policies is

$$J^*(u^{CL}) \leq J^*(u^{mF}) \leq J^*(u^F) \leq J^*(u^{OL}). \quad (2.10)$$

(3) The following concepts about the dual aspects of control are given.

Let the states include the unknown parameters of the system, then the stochastic optimal feedback control is some function $u_t \in U$ of information available at time t . We consider the case where v_t and w_t are mutually independent random variables, independent of x_0 .

Under certain conditions (Cramer 1946, §15.4; Wilks 1962, §5.5), the distribution of a random variable can be uniquely determined by its moments. Suppose this is true for our problem, then the conditional probability of the state

$$P(x_t | Y^t, U^{t-1}) \quad t = 0, 1, \dots, N-1 \quad (2.11)$$

can be described by its conditional mean

$$E(x_t|Y^t, U^{t-1}) \quad t = 0, 1, \dots, N-1 \quad (2.12)$$

and its higher conditional moments

$$M_t^r(x_t|Y^t, U^{t-1}) \quad \text{for } r = 2, 3, \dots \quad t = 0, 1, \dots, N-1. \quad (2.13)$$

These are often referred to as "sufficient statistics".

Let the cost functional J be given in the additive form

$$J = E\{V_N(x_N) + \sum_{t=0}^{N-1} V_t(x_t, u_t)\}. \quad (2.14)$$

From Stochastic Dynamic Programming (Aoki, 1969), at time t , the cost-to-go which is to be minimized is

$$J_t = E\{V_N(x_N) + \sum_{k=t}^{N-1} V_k(x_k, u_k)\} \quad (2.15)$$

and the optimal feedback control law can be written as

$$u_t^* = u_t(P(x_t|Y^t, U^{t-1}))$$

or

$$u_t^* = u_t(E(x_t|Y^t, U^{t-1}), M_t^r(x_t|Y^t, U^{t-1}), r > 1). \\ t = 0, 1, \dots, N-1 \quad (2.16)$$

Definition of Certainty Equivalence. A stochastic control problem has the certainty equivalence property if the functional form of the optimal

control law is the same as that of the optimal feedback control law of an equivalent deterministic problem. If the equivalent deterministic optimal feedback control law is

$$u_t^* = u_D(x_t)$$

then the certainty equivalent law is

$$u_t^* = u_D(E\{x_t|Y^t, U^t\}). \quad t = 0, 1, \dots, N-1 \quad (2.17)$$

Definition of Separation Property. (Witsenhausen, 1971) A stochastic control system has the separation property if the optimal control can be written as

$$u_t^* = u_t(F_t(Y^t, U^{t-1})) \quad t = 0, 1, \dots, N-1 \quad (2.18)$$

where F_t denotes filtering, and the design of the filtering algorithm is independent of controller design.

Remark. Certainty equivalence (CE) means that the filter maps the system information to the conditional mean only, because the CE control law does not take into account other statistics of filter output.

Definition of Neutrality. A stochastic control problem is neutral if the rate of change in uncertainty about the random variables is independent of the control. A well known measure of uncertainty is the negative of the entropy of the distribution on the probability space Ω

$$H = - \int_{\Omega} P \ln P \, d\Omega$$

where P is the density function of the probability distribution. If H is independent of U^{t-1} for all t , the problem is then neutral. For a Gaussian random variable,

$$H = \frac{1}{2} \ln |R| + \text{constant}$$

where R is the covariance of the random variable.

A corresponding concept is the "dual effect" of the control.

Definition of Neutrality of Control at Time t . Denote the r -th central moment of the i -th component of the state at time s $x_{s,i}$, $s > t$, conditioned on the σ -field generated by (Y^t, U^{t-1}) by

$$\begin{aligned} & M_{s|i}^r(Y^s, U^{s-1}) \\ &= E\{[x_{s,i}(\omega, U^{s-1}) - E\{x_{s,i}(\omega, U^{s-1}) | Y^s, U^{s-1}\}]^r | Y^s, U^{s-1}\} \end{aligned} \quad (2.19)$$

if

$$E\{M_{s|i}^r | Y^t, U^{t-1}\} \quad (2.20)$$

is independent of

$$U_t^{s-1} = \{u_t, u_{t+1}, \dots, u_{s-1}\}$$

for all i , $t \leq s \leq N-1$, for all $r \geq 2$, then u_t is said to be neutral or to have no dual effect. If (2.20) depends on U_t^{s-1} , then u_t is said to have *dual effect*, or to have the *dual property*.

Definition of Stochastic Neutral Control Systems. A stochastic control system is said to be neutral if all its optimal controls u_t , $0 \leq t \leq N-1$ are neutral.

In other words, if there exists at least one t , such that the optimal control at t has *dual effect*, then the control system is a dual control system, or a non-neutral control systems.

It is well known that only the class of closed-loop controls which incorporate the knowledge about the future observations, have an active learning property, since the control knows that future observations are to be made, there is always room to improve the estimation of the unknowns and reduce the uncertainty.

Otherwise, the controls which do not take this into consideration are passive learning controls. For example, the certainly equivalence control is a passive controller.

2.2 Problem Statement

The control problem for a discrete-time linear system with a finite set of unknown parameters, or a general unknown parameter system with the unknown parameters quantized into a finite (discrete) subset of the parameter space is given next:

The dynamics of the plant and the measurement system are described by

$$x(k+1) = A(r, k)x(k) + B(r, k)u(k) + v(k) \quad (2.21)$$

$$y(k) = C(r, k)x(k) + w(k) \quad (2.22)$$

where x is an n -dimensional state vector, u is an m -dimensional control input, and $A(r, k)$, $B(r, k)$ and $C(r, k)$ are matrices of appropriate dimensions, which are functions of the unknown mode parameter r . The vectors $x(0)$, $v(k)$, $w(k)$ are samples of mutually independent white Gaussian random sequences of appropriate dimensions, with statistics which are possibly functions of the unknown parameter r ,

$$x(0) \sim N(x_0, P_0(r))$$

$$v(k) \sim N(0, CovV(r, k))$$

$$w(k) \sim N(0, CovW(r, k)).$$

$[A(r_i, k), B(r_i, k), C(r_i, k)]$ is assumed to be a minimal realization for each mode $r_i = \{1, 2, \dots, s\}$.

The number of unknown modes s is a finite integer, $2 \leq s < \infty$. Each value of r is associated with a particular realization of the system, and all the realizations are distinct.

The uncertainty about r is described by the *a priori* probabilities:

$$p_i(0) = \Pr(r = r_i), \quad \sum_{i=1}^s p_i(0) = 1 \quad (2.23)$$

Denote the smallest σ algebra generated by the sequence of observations up to time t and the sequence of past control history by

$$I^k \triangleq \sigma\{y(0), y(1), \dots, y(k), u(0), u(1), \dots, u(k-1)\} \quad (2.24)$$

then the admissible control is

$$u(k) = u_k(I^k), \quad k = 0, 1, \dots, N-1$$

where u_k is a Borel measurable function for the fixed end point control problem.

Let U_k be the admissible control set at time k . Then, the problem is to select a sequence of control functions $\{u_k^*\}_{k=0}^{N-1}$ such that

$$J(\{u_k^*\}_{k=0}^{N-1}) \leq J(\{u_k\}_{k=0}^{N-1}) \quad \text{for all } u_k \in U_k, \quad k = 0, 1, \dots, N-1$$

where the cost performance criterion is

$$J(\{u_k\}_{k=0}^{N-1}) = V_N(x(N)) + E\left\{\sum_{k=0}^{N-1} V_k(u_k(I^k), x(k))\right\} \quad (2.25)$$

Let the cost-to-go at each stage be a quadratic function,

$$\begin{aligned} & V_N(x(N)) + \sum_{k=0}^{N-1} V_k(u_k(I^k), x(k)) \\ &= x^T(N)Q(r, N)x(N) + \sum_{k=0}^{N-1} [x^T(k)Q(r, k)x(k) + u^T(k)R(r, k)u(k)] \end{aligned}$$

hence

$$\begin{aligned} J &= E\{x^T(N)Q(r, N)x(N) \\ &\quad + \sum_{k=0}^{N-1} x^T(k)Q(r, k)x(k) + u^T(k)R(r, k)u(k)\} \end{aligned} \quad (2.26)$$

where

$$Q(r, k) = Q^T(r, k) \geq 0$$

$$R(r, k) = R^T(r, k) > 0$$

the superscript T denotes the transpose of a matrix, and the mathematical expectation E is taken with respect to the primitive random variables.

Applying the Principle of Optimality, the optimal solution may be formulated via Stochastic Dynamic Programming (Aoki, 1969), with an optimal cost function based on the information state I^k ,

$$J_k(I^k) = \min_{u(k) \in U_k} E\{x^T(k)Q(r, k)x(k) + u^T(k)R(r, k)u(k) + J_{k+1}(I^{k+1}) | I^k\} \quad k = 0, 1, \dots, N-1 \quad (2.27)$$

$$J_N(I^N) = 0.$$

2.3 Mathematical Preliminaries

(1) Kalman Filters

From now on, the subscript i and the subscript k will denote the dependence on the mode r_i , and the stage k , e.g., $A_{i,k} = A(r_i, k)$, $\hat{x}_{i,k} = E(x_k | I^k, r = r_i)$, and $p_{i,k} = \Pr(r = r_i | I^k)$, etc.

When the parameters in eqs(2.21) and (2.22) are given for each mode r , the system for each mode is in fact an ordinary linear Gaussian control system. Therefore the Kalman filter (Kalman and Bucy, 1961) is applicable to the system when the mode is fixed.

For each mode r , the one-step-ahead distribution of state x_{k+1} is Gaussian with the predicted conditional mean at time $k+1$ given I^k and its covariance

$$m_{i,k+1} = A_{i,k}\hat{x}_{i,k} + B_{i,k}u_k \quad (2.28)$$

$$P'_{i,k+1} = A_{i,k}P_{i,k}A_{i,k}^T + CovV \quad (2.29)$$

The state estimate at time $k + 1$ and its covariance are updated according to

$$\hat{x}_{i,k+1} = m_{i,k+1} + K_{i,k+1}(y_{k+1} - \hat{y}_{i,k+1}) \quad (2.30)$$

$$P_{i,k+1} = P'_{i,k+1} - K_{i,k+1}C_{i,k+1}P'_{i,k+1} \quad (2.31)$$

where the predicted observation measurement and its covariance are

$$\hat{y}_{i,k+1} = C_{i,k+1}m_{i,k+1} \quad (2.32)$$

$$M_{i,k+1} = C_{i,k+1}P'_{i,k+1}C_{i,k+1}^T + CovW \quad (2.33)$$

The Kalman filter gain matrix is determined by

$$K_{i,k+1} = P'_{i,k+1}C_{i,k+1}M_{i,k+1}^{-1} \quad (2.34)$$

$$P_{i,0} = P_0(r_i) \quad (2.35)$$

Eqs(2.28) to (2.35) will be used in the following chapters and correspond to a bank of parallel Kalman filters each tuned to a particular mode r_i , $i = 1, 2, \dots, s$.

(2) Distribution of State

The *a priori* uncertainty about r is described by

$$p_{i,0} = \Pr(r = r_i), \quad \sum_{i=1}^s p_{i,0} = 1$$

The *a posteriori* probabilities $p_i(k)$, $i = 1, 2, \dots, s$ are obtained by successive application of Bayes rule

$$\begin{aligned} p_{i,k+1} &= \Pr(r = r_i | I^{k+1}) \\ &= \frac{p(y_{k+1} | r_i, I^k) p_{i,k}}{\sum_{j=1}^s p(y_{k+1} | r_j, I^k) p_{j,k}}, \quad \text{for } i = 1, 2, \dots, s. \end{aligned} \quad (2.36)$$

From the total probability law, the density function of the probability distribution of the state x_k is a sum of Gaussians, with weighting of each possible mode r ,

$$\begin{aligned}\Pr(x_k | I^k) &= \sum_{i=1}^s p_{i,k} \Pr(x_k | r = r_i, I^k) \\ &= \sum_{i=1}^s p_{i,k} g(x_k, \hat{x}_{i,k}, P_{i,k})\end{aligned}\quad (2.37)$$

where $g(x, \hat{x}, P)$ indicates a Gaussian density function with mean $\hat{x}$ and covariance P . The density function of the probability distribution of the state is no longer Gaussian.

The conditional expectation of the state at time k is

$$\begin{aligned}\hat{x}_k &= E\{x_k | I^k\} \\ &= \int_{\mathbf{R}} x_k d\Pr(x_k | I^k) \\ &= \sum_{i=1}^s p_{i,k} \hat{x}_{i,k} \quad \text{for all } k\end{aligned}\quad (2.38)$$

The uncertainty of the state estimate $\hat{x}_k$ is given by the conditional covariance of the state, P_k .

We have the identity

$$\hat{x}_{i,k} \hat{x}_{j,k} = \frac{1}{2} \hat{x}_{i,k}^2 + \frac{1}{2} \hat{x}_{j,k}^2 - \frac{1}{2} (\hat{x}_{i,k} - \hat{x}_{j,k})^2 \quad (2.39)$$

then

$$\begin{aligned}
\left(\sum_{i=1}^s p_{i,k} \hat{x}_{i,k}\right)^2 &= \left(\sum_{i=1}^s p_{i,k} \hat{x}_{i,k}\right) \left(\sum_{j=1}^s p_{j,k} \hat{x}_{j,k}\right) \\
&= \sum_{i=1}^s \sum_{j=1}^s p_{i,k} p_{j,k} (\hat{x}_{i,k} \hat{x}_{j,k}) \\
&= \sum_{i=1}^s \sum_{j=1}^s p_{i,k} p_{j,k} \left(\frac{1}{2} \hat{x}_{i,k}^2 + \frac{1}{2} \hat{x}_{j,k}^2 - \frac{1}{2} (\hat{x}_{i,k} - \hat{x}_{j,k})^2\right) \\
&= \sum_{i=1}^s p_{i,k} \hat{x}_{i,k}^2 - \frac{1}{2} \sum_{i=1}^s \sum_{j=1}^s p_{i,k} p_{j,k} (\hat{x}_{i,k} - \hat{x}_{j,k})^2. \tag{2.40}
\end{aligned}$$

Next we evaluate

$$\begin{aligned}
E\{x_k^2 \mid I^k\} &= \sum_{i=1}^s p_{i,k} E\{x_k^2 \mid I^k, r = r_i\} \\
&= \sum_{i=1}^s p_{i,k} (\hat{x}_{i,k}^2 + P_{i,k}) \tag{2.41}
\end{aligned}$$

The covariance of state at time k is

$$\begin{aligned}
P_k &= E\{(x_k - \hat{x}_k)^2 \mid I^k\} \\
&= E\{x_k^2 \mid I^k\} - (E\{x_k \mid I^k\})^2 \\
&= \sum_{i=1}^s p_{i,k} (\hat{x}_{i,k}^2 + P_{i,k}) - \left(\sum_{i=1}^s p_{i,k} \hat{x}_{i,k}\right)^2 \\
&= \sum_{i=1}^s p_{i,k} (\hat{x}_{i,k}^2 + P_{i,k}) - \sum_{i=1}^s p_{i,k} \hat{x}_{i,k}^2 \\
&\quad + \frac{1}{2} \sum_{i=1}^s \sum_{j=1}^s p_{i,k} p_{j,k} (\hat{x}_{i,k} - \hat{x}_{j,k})^2 \\
&= \sum_{i=1}^s p_{i,k} P_{i,k} + \frac{1}{2} \sum_{i=1}^s \sum_{j=1}^s p_{i,k} p_{j,k} (\hat{x}_{i,k} - \hat{x}_{j,k})^2 \tag{2.42}
\end{aligned}$$

Note that $\hat{x}_{i,k}$ and $\hat{x}_{j,k}$ are functions of u_{k-1} , by the definition of the neutrality of control in section 2.1, the control of the system under consideration

is not a neutral control system, i.e., the control has the dual effect: the covariance of the state at time k , $E\{M_{k|k,i}^2 \mid I^k\}$, depends on u_{k-1} via the system dynamics.

Thus, we can decompose the state covariance P_k into two parts: (i) the first term of eq(2.42), $\sum_{i=1}^s p_{i,k} P_{i,k}$, which is independent of u_{k-1} , and (ii) the second term of eq(2.42), which depends u_{k-1} . We call the second part

$$\frac{1}{2} \sum_{i=1}^s \sum_{j=1}^s p_{i,k} p_{j,k} (\hat{x}_{i,k} - \hat{x}_{j,k})^2 \quad (2.43)$$

the *dual covariance of state* at time k (Casiello and Loparo, 1985).

The presence of the control dependent term in the covariance of the state estimates makes the problem a nontrivial stochastic dynamic programming problem, it will be illuminating first to study the two-stage version, which clearly displays the dual role of control in non-neutral systems.

CHAPTER THREE

Two Stage Dual Control Problem

3.1 The Performance Function

In this chapter, we discuss a two-stage ($N = 2$) control problem for a single input single output scalar model given by eqs(2.21), (2.22) and (2.26).

The performance criterion is

$$\begin{aligned} & \min_{\{u_0, u_1, \dots, u_{N-1}\}} J \\ &= \min_{\{u_0, u_1, \dots, u_{N-1}\}} E\{x_N^T Q_{r,N} x_N + \sum_{k=0}^{N-1} x_k^T Q_{r,k} x_k + u_k^T R_{r,k} u_k\} \end{aligned} \quad (3.1)$$

$$= \min_{\{u_0, u_1, \dots, u_{N-1}\}} E\{Q_{r,N} x_N^2 + \sum_{k=0}^{N-1} Q_{r,k} x_k^2 + R_{r,k} u_k^2\} \quad (3.2)$$

Without loss of generality, let's assume the state weighting $Q_{r,k} = Q_k$, and the control penalty $R_{r,k} = R_k$, i.e., they do not depend on the parameter r . Also, assume that system parameters $A_{i,k}$, $B_{i,k}$ and $C_{i,k}$ are unknown but constant.

At the terminal stage,

$$J_N = E\{Q_N x_N^2 \mid I^N\} \quad (3.3)$$

$$= Q_N(\hat{x}_N^2 + P_N) \quad (3.4)$$

$$= Q_N \sum_{i=1}^s p_{i,N}(\hat{x}_{i,N}^2 + P_{i,N}) \quad (3.5)$$

where

$$\hat{x}_{i,N} = E\{x_N \mid I^N, r = r_i\}$$

$$P_{i,N} = E\{(x_N - \hat{x}_{i,N})^2 \mid I^N, r = r_i\}$$

are the conditional mean and conditional covariance of state given the system is in mode r_i .

Denote the conditional probability density of the observation at time $k+1$, given information up to the present time k and mode status r_i by,

$$\begin{aligned} g_{i,k+1} &= P(y_{k+1} \mid r_i, I^k) \\ &= g(y_{k+1}, \hat{y}_{i,k+1}, M_{i,k+1}) \\ &= \frac{1}{\sqrt{2\pi M_{i,k+1}}} \exp\left(-\frac{1}{2} \frac{(y_{k+1} - \hat{y}_{i,k+1})^2}{M_{i,k+1}}\right) \end{aligned}$$

and probability distribution function of observation at $k+1$ conditioned on information up to present time k

$$\begin{aligned} P(y_{k+1} \mid I^k) &= \sum_{i=1}^s p_{i,k+1} P(y_{k+1} \mid r_i, I^k) \\ &= \sum_{i=1}^s p_{i,k+1} g_{i,k+1}. \end{aligned}$$

the cost-to-go at stage $N-1$ is

$$\begin{aligned} E\{J_N \mid I^{N-1}\} &= E\{Q_N \sum_{i=1}^s p_{i,N} (\hat{x}_{i,N}^2 + P_{i,N}) \mid I^{N-1}\} \quad (3.6) \\ &= Q_N \sum_{i=1}^s p_{i,N-1} \int_{-\infty}^{+\infty} \left[\frac{g_{i,N}}{P(y_N \mid I^{N-1})} \right. \\ &\quad \cdot [A_i \hat{x}_{i,N-1} + B_i u_{N-1} + K_{i,N} (y_N - \hat{y}_{i,N})]^2 \\ &\quad \left. + \frac{g_{i,N}}{P(y_N \mid I^{N-1})} P_{i,N} \right] P(y_N \mid I^{N-1}) dy_N \end{aligned}$$

$$\begin{aligned}
&= Q_N \sum_{i=1}^s p_{i,N-1} (A_i \hat{x}_{i,N-1} + B_i u_{N-1})^2 \\
&\quad + 2 Q_N \sum_{i=1}^s p_{i,N-1} K_{i,N} (A_i \hat{x}_{i,N-1} + B_i u_{N-1}) \\
&\quad \cdot \int_{-\infty}^{+\infty} g_{i,N}(y_N - \hat{y}_{i,N}) dy_N \\
&\quad + Q_N \sum_{i=1}^s p_{i,N-1} K_{i,N}^2 \int_{-\infty}^{+\infty} g_{i,N}(y_N - \hat{y}_{i,N})^2 dy_N \\
&\quad + Q_N \sum_{i=1}^s p_{i,N-1} P_{i,N} \\
&= Q_N \sum_{i=1}^s p_{i,N-1} [(A_i \hat{x}_{i,N-1} + B_i u_{N-1})^2 \\
&\quad + P_{i,N} + K_{i,N}^2 M_{i,N}]. \tag{3.7}
\end{aligned}$$

The last equation uses

$$\begin{aligned}
\int_{-\infty}^{+\infty} g_{i,N}(y_N - \hat{y}_{i,N}) dy_N &= 0 \\
\int_{-\infty}^{+\infty} g_{i,N}(y_N - \hat{y}_{i,N})^2 dy_N &= M_{i,N}.
\end{aligned}$$

The cost at stage $N - 1$ is equal to

$$J_{N-1} = E\{Q_{N-1} x_{N-1}^2 + R_{N-1} u_{N-1}^2 \mid I^{N-1}\} + E\{J_N \mid I^{N-1}\} \tag{3.8}$$

$$\begin{aligned}
&= Q_{N-1} \sum_{i=1}^s p_{i,N-1} \hat{x}_{i,N-1}^2 + R_{N-1} u_{N-1}^2 + Q_{N-1} \sum_{i=1}^s p_{i,N-1} P_{i,N-1} \\
&\quad + Q_N \sum_{i=1}^s p_{i,N-1} (A_i \hat{x}_{i,N-1} + B_i u_{N-1})^2 \\
&\quad + Q_N \sum_{i=1}^s p_{i,N-1} P_{i,N} + Q_N \sum_{i=1}^s p_{i,N-1} K_{i,N}^2 M_{i,N} \tag{3.9}
\end{aligned}$$

$$\begin{aligned}
&= (Q_{N-1} \sum_{i=1}^s p_{i,N-1} \hat{x}_{i,N-1}^2 + Q_N \sum_{i=1}^s p_{i,N-1} A_i^2 \hat{x}_{i,N-1}^2) \\
&\quad + 2Q_N \sum_{i=1}^s p_{i,N-1} A_i \hat{x}_i B_i u_{N-1} + (R_{N-1} + Q_N \sum_{i=1}^s p_{i,N-1} B_i^2) u_{N-1}^2 \\
&\quad + Q_{N-1} \sum_{i=1}^s p_{i,N-1} P_{i,N-1} + Q_N \sum_{i=1}^s p_{i,N-1} P_{i,N} \\
&\quad + Q_N \sum_{i=1}^s p_{i,N-1} K_{i,N}^2 M_{i,N}
\end{aligned} \tag{3.10}$$

With u_{N-1} unconstrained J_{N-1} convex, the optimal control u_{N-1} satisfies

$$\frac{\partial J_{N-1}}{\partial u_{N-1}} = 0. \tag{3.11}$$

Then we have

$$\begin{aligned}
u_{N-1} &= -(R_{N-1} + Q_N \sum_{i=1}^s p_{i,N-1} B_i^2)^{-1} (Q_N \sum_{i=1}^s p_{i,N-1} A_i B_i \hat{x}_i) \\
&= -\phi_{N-1} (Q_N \sum_{i=1}^s p_{i,N-1} A_i B_i \hat{x}_i)
\end{aligned} \tag{3.12}$$

where

$$\phi_{N-1} \triangleq -(R_{N-1} + Q_N \sum_{i=1}^s p_{i,N-1} B_i^2)^{-1}. \tag{3.13}$$

With the control u_{N-1} given by (3.12), the cost at stage $N-1$ is equal to

$$\begin{aligned}
J_{N-1} &= Q_{N-1} \sum_{i=1}^s p_{i,N-1} \hat{x}_{i,N-1}^2 + Q_N \sum_{i=1}^s p_{i,N-1} A_i^2 \hat{x}_{i,N-1}^2 \\
&\quad - \phi_{N-1} (Q_N \sum_{i=1}^s p_{i,N-1} A_i B_i \hat{x}_i)^2 + Q_{N-1} \sum_{i=1}^s p_{i,N-1} P_{i,N-1} \\
&\quad + Q_N \sum_{i=1}^s p_{i,N-1} P_{i,N} + Q_N \sum_{i=1}^s p_{i,N-1} K_{i,N}^2 M_{i,N}.
\end{aligned} \tag{3.14}$$

In the following, let us assume that

$$A_i = A \quad \text{and} \quad B_i = B, \quad \text{for all } i \quad (3.15)$$

i.e., the parameters A and B are known, eq(3.12) becomes

$$u_{N-1} = -(R_{N-1} + Q_N B^2)^{-1} Q_N A B \left(\sum_{i=1}^s p_{i,N-1} \hat{x}_{i,N-1} \right) \quad (3.16)$$

$$= -L_{N-1} \hat{x}_{N-1} \quad (3.17)$$

where $\hat{x}_{N-1}$ and L_{N-1} are defined as

$$\hat{x}_{N-1} = \sum_{i=1}^s p_{i,N-1} \hat{x}_{i,N-1} \quad (3.18)$$

$$L_{N-1} = (R_{N-1} + Q_N B^2)^{-1} Q_N A B. \quad (3.19)$$

Note that u_{N-1} (3.17) is the same as the certainty equivalent control law.

The optimal cost at stage $N-1$ is then

$$\begin{aligned} J_{N-1} &= (Q_{N-1} + Q_N A^2) \sum_{i=1}^s p_{i,N-1} \hat{x}_{i,N-1}^2 \\ &\quad - \phi_{N-1} (Q_N A B)^2 \left(\sum_{i=1}^s p_{i,N-1} \hat{x}_{i,N-1} \right)^2 \\ &\quad + Q_{N-1} \sum_{i=1}^s p_{i,N-1} P_{i,N-1} + Q_N \sum_{i=1}^s p_{i,N-1} P_{i,N} \\ &\quad + Q_N \sum_{i=1}^s p_{i,N-1} K_{i,N}^2 M_{i,N} \\ &= \sum_{i=1}^s p_{i,N-1} \{ [Q_{N-1} + Q_N A^2 - L_{N-1}^2 (R_{N-1} + Q_N B^2)] \hat{x}_{i,N-1}^2 \\ &\quad + [Q_{N-1} P_{i,N-1} + Q_N P_{i,N} + Q_N K_{i,N}^2 M_{i,N}] \} \\ &\quad + \frac{1}{2} L_{N-1}^2 (R_{N-1} + Q_N B^2) \\ &\quad + \sum_{i=1}^s \sum_{j=1}^s p_{i,N-1} p_{j,N-1} (\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2. \end{aligned} \quad (3.20)$$

The first term of (3.20) is a sum of quadratic function, analogous to the cost in the standard LQG problem, the second term of (3.20) is an additional cost, it is proportional to the dual covariance of the state estimates (see eq(2.43)).

The last term on the right hand side of eq(3.20) follows from the identity (2.40)

$$\begin{aligned} \left(\sum_{i=1}^s p_{i,N-1} \hat{x}_{i,N-1} \right)^2 &= \sum_{i=1}^s p_{i,N-1} \hat{x}_{i,N-1}^2 \\ &\quad - \frac{1}{2} \sum_{i=1}^s \sum_{j=1}^s p_{i,N-1} p_{j,N-1} (\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2. \end{aligned} \quad (3.21)$$

To decompose J_{N-1} into a certainty equivalence (CE) cost and dual cost, rewrite equation (3.20) in the form

$$\begin{aligned} J_{N-1} &= \sum_{i=1}^s p_{i,N-1} J_{i,N-1} + J_{N-1}^{dual} \\ &\triangleq J_{N-1}^{CE} + J_{N-1}^{dual}. \end{aligned} \quad (3.22)$$

Here the CE cost is a weighted sum of quadratic functions of the conditional state estimates.

$$\begin{aligned} J_{N-1}^{CE} &= \sum_{i=1}^s p_{i,N-1} J_{i,N-1} \\ J_{i,N-1} &= [Q_{N-1} + Q_N A^2 - L_{N-1}^2 (R_{N-1} + Q_N B^2)] \hat{x}_{i,N-1}^2 \\ &\quad + [Q_{N-1} P_{i,N-1} + Q_N P_{i,N} + Q_N K_{i,N}^2 M_{i,N}]. \end{aligned} \quad (3.23)$$

The dual cost component in the cost-to-go at stage $N - 1$ is due to the dual covariance of state at time $N - 1$, that is,

$$J_{N-1}^{dual} = \frac{1}{2} L_{N-1}^2 (R_{N-1} + Q_N B^2) \cdot \sum_{i=1}^s \sum_{j=1}^s p_{i,N-1} p_{j,N-1} (\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2. \quad (3.24)$$

Let

$$S_{N-1} = Q_{N-1} + S_N A^2 - L_{N-1}^2 (R_{N-1} + S_N B^2) \quad (3.25)$$

$$s_{i,N-1} = s_{i,N} + Q_{N-1} P_{i,N-1} + S_N K_{i,N}^2 M_{i,N} \quad (3.26)$$

where

$$s_{i,N} = S_N P_{i,N} \quad \text{and} \quad S_N = Q_N.$$

Then eq(3.23) becomes

$$J_{i,N-1} = S_{N-1} \hat{x}_{i,N-1}^2 + s_{i,N-1} \quad (3.27)$$

and from eq(3.22), the total cost at $N - 1$, is

$$J_{N-1} = \sum_{i=1}^s p_{i,N-1} (S_{N-1} \hat{x}_{i,N-1}^2 + s_{i,N-1}) + J_{N-1}^{dual}. \quad (3.28)$$

At stage $N - 2$ the cost-to-go is

$$\begin{aligned} & E\{J_{N-1} \mid I_{N-2}\} \\ &= E\left\{\sum_{i=1}^s p_{i,N-1} (S_{N-1} [A\hat{x}_{i,N-2} + Bu_{N-2} + K_{i,N-1}(y_{N-1} - \hat{y}_{i,N-1})]^2 \right. \\ &\quad \left. + s_{i,N-1}) + J_{N-1}^{dual} \mid I^{N-2}\right\} \end{aligned} \quad (3.29)$$

$$\begin{aligned} &= \sum_{i=1}^s p_{i,N-2} (S_{N-1} (A\hat{x}_{i,N-2} + Bu_{N-2})^2 \\ &\quad + S_{N-1} K_{i,N-1}^2 M_{i,N-1} + s_{i,N-1}) + E\{J_{N-1}^{dual} \mid I^{N-2}\}. \end{aligned} \quad (3.30)$$

Define the coefficient of the dual cost at $N - 1$,

$$G_{N-1} \triangleq \frac{1}{2} L_{N-1}^2 (R_{N-1} + Q_N B^2). \quad (3.31)$$

Now the dual cost at stage $N - 1$ conditioned on information up to $N - 2$ is

$$\begin{aligned} & E\{J_{N-1}^{dual} \mid I^{N-2}\} \\ &= E\{G_{N-1} \sum_{i=1}^s \sum_{j=1}^s p_{i,N-1} p_{j,N-1} (\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 \mid I_{N-2}\} \\ &= G_{N-1} \sum_{i=1}^s \sum_{j=1}^s p_{i,N-2} p_{j,N-2} \\ & \quad \cdot \int_{-\infty}^{+\infty} \frac{g_{i,N-1} g_{j,N-1}}{P(y_{N-1} \mid I^{N-2})} (\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 dy_{N-1}. \end{aligned} \quad (3.32)$$

Then the cost at stage $N - 2$ is equal to

$$\begin{aligned} J_{N-2} &= E\{Q_{N-2} x_{N-2}^2 + R_{N-2} u_{N-2}^2 \mid I^{N-2}\} \\ & \quad + E\{J_{N-1} \mid I^{N-2}\} \end{aligned} \quad (3.33)$$

$$\begin{aligned} &= Q_{N-2} \sum_{i=1}^s p_{i,N-2} \hat{x}_{i,N-2}^2 + Q_{N-2} \sum_{i=1}^s p_{i,N-2} P_{i,N-2} \\ & \quad + R_{N-2} u_{N-2}^2 + E\{J_{N-1} \mid I^{N-2}\} \end{aligned} \quad (3.34)$$

$$= \sum_{i=1}^s p_{i,N-2} J_{i,N-2} + E\{J_{N-1}^{dual} \mid I^{N-2}\} \quad (3.35)$$

$$= J_{N-2}^{CE} + J_{N-2}^{dual}, \quad (3.36)$$

where the CE cost at stage $N - 2$ is

$$J_{N-2}^{CE} = \sum_{i=1}^s p_{i,N-2} J_{i,N-2} \quad (3.37)$$

$$J_{i,N-2} = [Q_{N-2}\hat{x}_{i,N-2}^2 + S_{N-1}(A\hat{x}_{i,N-2} + Bu_{N-2})^2 + R_{N-2}u_{N-2}^2] + s_{i,N-2} \quad (3.38)$$

$$s_{i,N-2} = s_{i,N-1} + Q_{N-2}P_{i,N-2} + S_{N-1}K_{i,N-1}^2 M_{i,N-1} \quad (3.39)$$

As in eq(3.32), the dual cost at stage $N - 2$ is

$$\begin{aligned} J_{N-2}^{dual} &= E\{J_{N-1}^{dual} | I^{N-2}\} \\ &= G_{N-1} \sum_{i=1}^s \sum_{j=1}^s p_{i,N-2} p_{j,N-2} \\ &\quad \cdot \int_{-\infty}^{+\infty} \frac{g_{i,N-1} g_{j,N-1}}{P(y_{N-1} | I^{N-2})} (\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 dy_{N-1}. \end{aligned} \quad (3.40)$$

This is the cost associated with the dual covariance of the state at $N - 1$.

At stage $N - 2$, we can no longer apply the same approach to solve the optimization problem of (3.40) as we did at stage $N - 1$. Additional term, the dual cost, appears in the cost-to-go at stage $N - 2$, and it is a highly nonlinear function of the control.

At stage $N - 1$, since the control to be applied is the last control action, no benefit can be obtained from the reduction of the uncertainty, therefore, there is no need to probe the system. As the result, the optimal control at stage $N - 1$ is the CE control. However, at stage $N - 2$, active probing can improve the estimates of the unknowns in the system and realize a reduction in the cost at $N - 1$, the dual effect of control occurs here.

3.2 The Dual Control Policy

For the two-stage dual control problem, the overall cost is given by eqs(3.36)-(3.40). The optimal control problem can not solve analytically, because of the difficulty in the mathematical form of the dual cost resulting from the *a posteriori* probabilities $p_{i,N-1}$. We need to investigate the properties of the dual cost in order to find an approach to the solution of the problem.

In this section, some technical results regarding the behavior of the dual cost are given. These will serve as the basis for a dual control policy for the two-stage control problem.

For the moment, we discuss the two-mode case, and at the end of the section, it will be shown that the solution of the general multi-mode case ($s \geq 2$) may be obtained by solving a fixed set of two-mode subproblems.

Theorem 3.1. *Assume that A, B are known, the number of possible modes of the system $s = 2$, and*

$$\hat{x}_{i,N-2} = \hat{x}_{j,N-2}, \quad i \neq j,$$

i.e., the modes are indistinguishable in the mean for the initial state. Then the dual cost at stage $N - 2$ is symmetric about the point $-\frac{A}{B}\hat{x}_{N-2}$, i.e.,

$$J_{N-2}^{dual}(u_{N-2}) = J_{N-2}^{dual}(-2\frac{A}{B}\hat{x}_{N-2} - u_{N-2}). \quad (3.41)$$

Fig. 3.1 illustrates the symmetry of the dual cost as a function of the control.

Proof. From eq(3.40)

$$J_{N-2}^{dual}(u_{N-2}) = G_{N-1} \sum_{i=1}^s \sum_{j=1}^s p_{i,N-2} p_{j,N-2} \cdot \int_{-\infty}^{+\infty} \frac{g_{i,N-1} g_{j,N-1}}{P(y_{N-1} | I^{N-2})} (\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 dy_{N-1}$$

Let

$$u' = -2\frac{A}{B}\hat{x}_{N-2} - u''$$

we show for each $y' \in (-\infty, \infty)$, there is a $y'' = -y'$, such that

$$(y - \hat{y}_i)^2 \Big|_{\substack{y=y' \\ u=u'}} = (y - \hat{y}_i)^2 \Big|_{\substack{y=y'' \\ u=u''}}$$

and

$$(\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 \Big|_{\substack{y=y' \\ u=u'}} = (\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 \Big|_{\substack{y=y'' \\ u=u''}} .$$

It is straightforward from eqs(2.32) and (2.28) that

$$\begin{aligned} (y - \hat{y}_i)^2 \Big|_{\substack{y=y' \\ u=u'}} &= [y' - C_i(A\hat{x} + Bu')]^2 \\ &= [y' - C_i(A\hat{x} + B(-2\frac{A}{B}\hat{x} - u''))]^2 \\ &= [y' - C_i(-A\hat{x} - Bu'')]^2 \\ &= [y' + C_i(A\hat{x} + Bu'')]^2 \\ &= [y'' - C_i(A\hat{x} + Bu'')]^2 \\ &= (y - \hat{y}_i)^2 \Big|_{\substack{y=y'' \\ u=u''}} . \end{aligned}$$

FIG. 3.1

Figure 3.1. Dual cost as a function of control, initial state estimates are the same. The dual cost is symmetric about the local minimum dual cost control.

The subscripts have been omitted for notational simplicity.

Similarly, from eqs(2.30) and (2.28),

$$\begin{aligned}
 (\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 \Big|_{\substack{y=y' \\ u=u'}} &= [(K_i - K_j)y' - (K_i C_i - K_j C_j)(A\hat{x} + Bu')]^2 \\
 &= [(K_i - K_j)y'' - (K_i C_i - K_j C_j)(A\hat{x} + Bu'')]^2 \\
 &= (\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 \Big|_{\substack{y=y'' \\ u=u''}}.
 \end{aligned}$$

From these two equalities, the result

$$J_{N-2}^{dual}(u_{N-2}) = J_{N-2}^{dual}\left(-2\frac{A}{B}\hat{x}_{N-2} - u_{N-2}\right)$$

is immediate. □

Corollary 3.2. *Under the same conditions as Theorem 3.1, we have a local minimum of the dual cost at*

$$u_{N-2} = -\frac{A}{B}\hat{x}_{N-2}. \quad (3.42)$$

Proof. This is directly from Theorem 3.1. □

Note that the local minimum dual cost control is a linear feedback control, but it is certainly not the same as the CE control. In the following, we give the relationship between the local minimum dual cost control and the CE control.

Theorem 3.3. *Under the same conditions as Theorem 3.1, at stage $N - 2$, the dual control gain, i.e., the associated dual control yielding minimum dual cost, is greater than the Certainty Equivalence (CE) control gain. More specifically,*

$$\left| \frac{A}{B} \right| > \left| \frac{S_{N-1}BA}{R_{N-2} + S_{N-1}B^2} \right| \quad (3.43)$$

Proof. Since $S_{N-1} > 0$, and $R_{N-2} > 0$ and B is finite, then we have

$$\begin{aligned} \left| \left(\frac{R_{N-2}}{S_{N-1}B^2} + 1 \right) B \right| &> |B| \\ \left| \frac{R_{N-2}}{S_{N-1}B} + B \right| &> |B| \\ \left| \frac{1}{A} \right| \cdot \left| \frac{R_{N-2} + S_{N-1}B^2}{S_{N-1}B} \right| &> \left| \frac{1}{A} \right| \cdot |B| \\ \left| \frac{R_{N-2} + S_{N-1}B^2}{S_{N-1}BA} \right| &> \left| \frac{B}{A} \right| \\ \left| \frac{S_{N-1}BA}{R_{N-2} + S_{N-1}B^2} \right| &< \left| \frac{A}{B} \right|. \end{aligned}$$

□

Theorem 3.3 states that a larger control signal is applied when the dual control formulation is used, that is, the system is actively probed.

The cost-to-go at $N - 2$ is the sum of the CE cost and the dual cost, as given in eqs(3.36)-(3.40); although the dual cost reaches a global minimum as $u \rightarrow \pm\infty$ (see Fig. 3.1). However, because of the convexity of the CE cost, the CE cost is unbounded as $u \rightarrow \pm\infty$, consequently the global minimum of

the total cost-to-go can not be at $u = \pm\infty$. In the neighborhood of the local minimum of dual cost, as given in eq(3.42) the global minimum might exist.

The previous discussion dealt with the very special situation where the initial state estimates are the same. In general, this condition is not satisfied, next we give a result that does not have this restriction.

Theorem 3.4. Assume that A, B are known and the number of modes $s = 2$. Let $C_i = \min(C_1, C_2) = \gamma$ ($C_j \neq 0, j \neq i$), $CovW = q|\gamma|$, where q is a finite positive real number. When $\gamma \rightarrow 0$, we have (i) the dual cost

$$J_{N-2}^{dual} \approx \frac{\sqrt{2\pi M_{i,N-1}} G_{N-1} p_{i,N-2} p_{j,N-2} g_{j,N-1}}{p_{i,N-2} + \sqrt{2\pi M_{i,N-1}} p_{j,N-2} g_{j,N-1}} \cdot (\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 \Big|_{y_{N-1}=\hat{y}_{i,N-1}} \quad (3.44)$$

where

$$\begin{aligned} (\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 \Big|_{y_{N-1}=\hat{y}_{i,N-1}} &= [A(1 - K_{j,N-1}C_i)\hat{x}_{i,N-2} \\ &\quad - A(1 - K_{j,N-1}C_j)\hat{x}_{j,N-2} - K_{j,N-1}(C_i - C_j)Bu_N - 2]^2, \end{aligned}$$

(ii) the global minimum of the dual cost is

$$u_{N-2} = \pm\infty,$$

and (iii) the local minimum

$$u_{N-2}(i) \approx -\frac{A}{B} \frac{(K_{j,N-1}C_i - 1)\hat{x}_{i,N-2} - (K_{j,N-1}C_j - 1)\hat{x}_{j,N-2}}{K_{j,N-1}(C_i - C_j)}$$

for $C_i \neq C_j$, $K_{j,N-1} \neq 0$.

Proof. Under the conditions, we have the covariance of the observation conditioned on mode r_i ,

$$M_{i,N-1} = (C_{i,N-1}^2 P'_{i,N-1} + CovW) \rightarrow 0$$

where $CovW \rightarrow 0$ as $\gamma \rightarrow 0$. The Kalman filter gain for mode r_i is

$$\begin{aligned} K_{i,N-1} &= P'_{i,N-1} C_{i,N-1} M_{i,N-1}^{-1} \\ &= P'_{i,N-1} \gamma (\gamma^2 P'_{i,N-1} + q\gamma)^{-1} \\ &= P'_{i,N-1} (\gamma P'_{i,N-1} + q)^{-1} \rightarrow \frac{P'_{i,N-1}}{q} \neq 0, \end{aligned}$$

as $\gamma \rightarrow 0$, and

$$\exp\left(-\frac{1}{2} \frac{(y_{N-1} - \hat{y}_{i,N-1})^2}{M_{i,N-1}}\right) \rightarrow 1, \quad \text{for } y_{N-1} \neq \hat{y}_{i,N-1}$$

as $\gamma \rightarrow 0$. Let

$$\Delta M_{i,N-1} \triangleq \frac{\sqrt{2\pi M_{i,N-1}}}{2} \tag{3.44a}$$

then as $M_{i,N-1} \rightarrow 0$, as $\gamma \rightarrow 0$,

$$g_{i,N-1} \approx \begin{cases} \frac{1}{\sqrt{2\pi M_{i,N-1}}}, & \text{for } |y_{N-1} - \hat{y}_{i,N-1}| \leq \Delta M_{i,N-1}; \\ 0, & \text{otherwise.} \end{cases}$$

That is, formally, as $\gamma \rightarrow 0$,

$$g_{i,N-1} \rightarrow \delta(y_{N-1} - \hat{y}_{i,N-1})$$

where $\delta(t)$ is the unit impulse function (distribution) defined by

$$\int_{-\epsilon}^{\epsilon} \delta(t) dt = 1, \quad \epsilon > 0, \quad \epsilon \text{ is infinitely small.}$$

As $M_{i,N-1} \rightarrow 0$, in the interval $[\hat{y}_{i,N-1} - \Delta M_{i,N-1}, \hat{y}_{i,N-1} + \Delta M_{i,N-1}]$, y can be approximated by the constant $\hat{y}_{i,N-1}$, then from eq(3.40), the dual cost is

$$\begin{aligned} J_{N-2}^{dual} &= G_{N-1} p_{i,N-2} p_{j,N-2} \\ &\quad \cdot \int_{-\infty}^{+\infty} \frac{g_{i,N-1} g_{j,N-1}}{P(y_{N-1} | I^{N-2})} (\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 dy_{N-1} \\ &= G_{N-1} p_{i,N-2} p_{j,N-2} \\ &\quad \cdot \int_{-\infty}^{+\infty} \frac{g_{i,N-1} g_{j,N-1}}{p_{i,N-2} g_{i,N-1} + p_{j,N-2} g_{j,N-1}} \\ &\quad \cdot (\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 dy_{N-1} \\ &\approx G_{N-1} p_{i,N-2} p_{j,N-2} \\ &\quad \cdot \int_{\hat{y}_{i,N-1} - \Delta M_{i,N-1}}^{\hat{y}_{i,N-1} + \Delta M_{i,N-1}} \frac{\frac{1}{\sqrt{2\pi M_{i,N-1}}} g_{j,N-1}}{p_{i,N-2} \frac{1}{\sqrt{2\pi M_{i,N-1}}} + p_{j,N-2} g_{j,N-1}} \\ &\quad \cdot (\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 dy_{N-1} \\ &= G_{N-1} p_{i,N-2} p_{j,N-2} \\ &\quad \cdot \int_{\hat{y}_{i,N-1} - \Delta M_{i,N-1}}^{\hat{y}_{i,N-1} + \Delta M_{i,N-1}} \frac{g_{j,N-1}}{p_{i,N-2} + \sqrt{2\pi M_{i,N-1}} p_{j,N-2} g_{j,N-1}} \\ &\quad \cdot (\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 dy_{N-1} \\ &\approx \frac{\sqrt{2\pi M_{i,N-1}} G_{N-1} p_{i,N-2} p_{j,N-2} g_{j,N-1}}{p_{i,N-2} + \sqrt{2\pi M_{i,N-1}} p_{j,N-2} g_{j,N-1}} \\ &\quad \cdot (\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 \Big|_{y_{N-1} = \hat{y}_{i,N-1}} \end{aligned}$$

This proves (i).

From (i), let $g_{j,N-1} = 0$, we have $u_{N-2} = \pm\infty$, direct substitution in eq(3.32) gives (ii).

From (i), let

$$(\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 \Big|_{y_{N-1}=\hat{y}_{i,N-1}} = 0$$

we have (iii). □

Under the conditions of Theorem 3.4, one mode (mode i) becomes distinct from the other mode, since the conditional probability density function of the predicted observation for mode i becomes an impulse function. In this case, the dual cost integral is easily computed; this can be use to approximate the dual cost.

The formula(3.44) helps in the understanding of the properties of the dual cost, since the integral form in eq(3.40) is less apparent. The dual cost approximation obtained in eq(3.44) indicates that as the noise level in the observations increases, the uncertainty in the states of the system also increases.

Another property of the dual cost is that the term

$$g_{i,N-1}(\hat{y}_{i,N-1}) = \frac{1}{\sqrt{2\pi M_{i,N-1}}} \exp\left(-\frac{1}{2} \frac{(y_{N-1} - \hat{y}_{i,N-1})^2}{M_{i,N-1}}\right)$$

representing the amount of discrimination of the mean of the observation process in different modes, and the term

$$(\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 \Big|_{y_{N-1}=\hat{y}_{i,N-1}},$$

representing the difference of the state estimates for different modes, both affect the uncertainty at next stage, but they can be conflicting.

The control applied at stage $N - 2$ affects the future uncertainties through both the predicted observation and states estimate differences. In the dual cost, large discrimination of the observations helps in separating the different modes, hence reducing the uncertainty. Large discriminations in the state estimates also reduces uncertainty, but as eq(3.44) indicates, the discrimination of the observations in different modes contribute more than the discrimination of the state estimates in different modes to reducing the dual cost.

This property makes the dual cost highly nonlinear. The task of solving the dual control problem can be considered finding the a compromise between the regulation and identification (discrimination) objectives of the control.

(ii) & (iii) are the results of trying to achieve such balance. In other situations, the dual cost increases (see Fig. 3.2).

Remark. Here, the impulse approximation of the conditional density functions for the observation at the next stage $y_{i,N-1}$ and $y_{j,N-1}$, differs from that of Wenk and Bar-Shalom (1980). Wenk and Bar-Shalom assumed that the covariances of the conditional density functions for the observation at the next stage are the same for all modes, i.e., $M_{i,N-1} = M_{j,N-1} = \lambda$ (see Wenk and Bar-Shalom (1980), page 705). Under their assumption, therefore, the

conditional density functions become impulse functions for all modes, we do not make this assumption.

Remark. Theorem 3.4 is based on the approximation of dual cost. If no approximation is used, then the global minimum $u_{N-2} = \pm\infty$ can be verified (Casiello, 1985) and the local minimum dual cost won't be zero, as in a typical example shown in Fig. 3.2.

Because the initial state estimates of each mode are distinct from each other, we do not have the simple form of the local minimum dual cost control given in eq(3.42). However, eq(3.44) (iii) can be further approximated into the form of eq(3.42).

Corollary 3.5. *Under the same conditions as Theorem 3.4, we have the approximate local minimum dual control*

$$u_{N-2}(i) \approx -\frac{A}{B}\hat{x}_{i,N-2} \quad (3.45)$$

where the index i is such that $C_i = \min(C_1, C_2)$.

Proof. Since $CovW \rightarrow 0$, as $\gamma \rightarrow 0$, from eq(2.29), (2.33) and eq(2.34), with $C_i \rightarrow 0$, we have

$$CovW \ll M_{j,N-1} = C_j P'_{j,N-1} C_j^T + CovW$$

$$C_j K_{j,N-1} = \frac{C_j P'_{j,N-1} C_j^T}{C_j P'_{j,N-1} C_j^T + CovW} \rightarrow 1,$$

FIG. 3.2

Figure 3.2. Dual cost as a function of control, initial state estimates are different. The local minimum dual cost is not zero.

as $\gamma \rightarrow 0$, then

$$K_{j,N-1}C_j - 1 \rightarrow 0$$

$$K_{j,N-1}(C_i - C_j) \rightarrow K_{j,N-1}C_i - 1$$

as $\gamma \rightarrow 0$. Hence

$$\begin{aligned} u_{N-2}(i) &= -\frac{A}{B} \frac{(K_{j,N-1}C_i - 1)\hat{x}_{i,N-2} - (K_{j,N-1}C_j - 1)\hat{x}_{j,N-2}}{K_{j,N-1}(C_i - C_j)} \\ &\approx -\frac{A}{B} \hat{x}_{i,N-2}. \end{aligned}$$

□

Note that Corollary 3.2 is a special case of Corollary 3.5. The local minimum control of the dual cost is approximately the same as when the initial state estimates were indistinguishable. As $\hat{x}_{i,N-2} = \hat{x}_{j,N-2}$, eq(3.44) becomes (3.42).

In the above, we assumed the system under consideration has only two possible modes, this assumption is however very often unrealistic. we generalize the previous results to systems with more than two possible modes.

Theorem 3.6. Assume that A, B are known, number of modes $s > 2$. Let $C_i = \min(C_i, C_j) = \gamma$, i and j represent each possible pair of modes, $\frac{s!}{2(s-2)!}$ in number, ($C_j \neq 0, j \neq i$), $CovW = q|\gamma|$, q is a finite positive real number. Then as $\gamma \rightarrow 0$, we have the approximation

$$J_{N-2}^{dual} \approx \sum_{i=1}^s \sum_{j=1}^s J_{N-2}^{dual}(i, j) \quad (3.46)$$

where the pairwise dual cost is

$$J_{N-2}^{dual}(i, j) = G_{N-1} p_{i,N-2} p_{j,N-2} \int_{-\infty}^{+\infty} \frac{g_{i,N-1} g_{j,N-1}}{p_{i,N-2} g_{i,N-1} + p_{j,N-2} g_{j,N-1}} \cdot (\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 dy_{N-1}. \quad (3.47)$$

Proof. From eq(3.40)

$$\begin{aligned} J_{N-2}^{dual}(u_{N-2}) &= G_{N-1} \sum_{i=1}^s \sum_{j=1}^s p_{i,N-2} p_{j,N-2} \\ &\quad \cdot \int_{-\infty}^{+\infty} \frac{g_{i,N-1} g_{j,N-1}}{P(y_{N-1} | I^{N-2})} (\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 dy_{N-1} \\ &= G_{N-1} \sum_{i=1}^s \sum_{j=1}^s p_{i,N-2} p_{j,N-2} \\ &\quad \cdot \int_{-\infty}^{+\infty} \psi_{i,j} \frac{g_{i,N-1} g_{j,N-1}}{p_{i,N-2} g_{i,N-1} + p_{j,N-2} g_{j,N-1}} \\ &\quad \cdot (\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 dy_{N-1} \end{aligned}$$

where

$$\psi_{i,j} = \frac{p_{i,N-2} g_{i,N-1} + p_{j,N-2} g_{j,N-1}}{P(y_{N-1} | I^{N-2})}$$

Using the approximation,

$$g_{i,N-1} \rightarrow \delta(y_{N-1} - \hat{y}_{i,N-1}), \quad \text{as } M_{i,N-1} \rightarrow 0$$

then we find

$$\psi_{i,j} = \frac{p_{i,N-2} g_{i,N-1} + p_{j,N-2} g_{j,N-1}}{P(y_{N-1} | I^{N-2})} \rightarrow \begin{cases} 1, & \text{for } y_{N-1} = \hat{y}_{i,N-1}; \\ \alpha, & \text{for } y_{N-1} \neq \hat{y}_{i,N-1} \end{cases}$$

where $0 < \alpha < 1$, and

$$\frac{g_{i,N-1}g_{j,N-1}}{p_{i,N-2}g_{i,N-1} + p_{j,N-2}g_{j,N-1}} \rightarrow \begin{cases} \neq 0, & \text{for } y_{N-1} = \hat{y}_{i,N-1}; \\ = 0, & \text{for } y_{N-1} \neq \hat{y}_{i,N-1} \end{cases}$$

Therefore, $\psi_{i,j} \approx 1$ and

$$J_{N-2}^{dual} \approx \sum_{i=1}^s \sum_{j=1}^s J_{N-2}^{dual}(i, j).$$

□

Theorem 3.4 and Theorem 3.6 suggest that for the two-stage dual control problem, the dual control at the initial stage can be obtained as follows:

- (i) Compute the local minimum dual cost control according to (3.44) and the CE control.
- (ii) Evaluate the total cost using the dual control, and the total cost when using the CE control applied.
- (iii) Compare the two costs, choose the one that is smaller, the associated control is the control policy to be applied at this stage.

This method takes the advantage of the dual cost property so that all possible control values (in our problem $u \in \mathbb{R}$) are reduced to two controls: the CE control and the local minimum dual cost control. Clearly, the dual control here is a closed-loop control. At the initial stage, the control has the dual effect and it looks for future observations at only the next stage (one step), it is a closed-loop and 1-measurement feedback control. (see (2.7) and

(2.8)). The local minimum dual cost control is found by the formula (3.44), the reduction of the dual cost using the local minimum dual cost control can yield a reduction of the total cost-to-go, as will be illustrated in the examples in chapter 5. (Example 5.1)

Apparently, the global minimum dual cost controls $u \rightarrow \pm\infty$ are not included in the consideration, as $u \rightarrow \pm\infty$, the CE cost becomes infinite, this is of practical significance.

CHAPTER FOUR

Finite Horizon Dual Control Problem

In the last chapter, we investigated the dual control problem by focusing on properties of the dual cost, and the local minimum dual cost control was found. The corresponding dual control algorithm was developed. In order to apply the same technique to the general finite horizon dual control problem, it is necessary to have a recursive form of the stochastic dynamic programming solution to the problem. As time propagates backwards from the terminal time to the initial time, the evaluation of cost-to-go, which includes the future knowledge of the system unknowns, is a formidable computational task. This problem will be treated in the first section of this chapter.

Because the dual cost accumulates as the time progresses, the dual cost is treated as a sum of dual costs. An approximation obtained by its truncating an integral will be developed in section 4.2.

Then, a dual control algorithm will be developed, the convergence of the algorithm will be discussed and it will be shown that the one-step-ahead dual control is the best affine suboptimal control.

4.1 Dual Cost Evaluation, Two-mode Case

The description of the dual cost and the CE cost at each stage are formulated in this section.

The approach is to use the dynamic programming scheme in the same manner as before to stage $N - 3$. From eq(3.36) we have

$$J_{N-2} = J_{N-2}^{CE} + J_{N-2}^{dual} \quad (4.1)$$

where

$$\begin{aligned} J_{N-2}^{CE} = & \sum_{i=1}^s p_{i,N-2} [Q_{N-2} \hat{x}_{i,N-2}^2 + S_{N-1} (A \hat{x}_{i,N-2} + B u_{N-2})^2 \\ & + R_{N-2} u_{N-2}^2] + \sum_{i=1}^s p_{i,N-2} s_{i,N-2} \end{aligned} \quad (4.2)$$

$$s_{i,N-2} = s_{i,N-1} + Q_{N-2} P_{i,N-2} + S_{N-1} K_{i,N-1}^2 M_{i,N-1} \quad (4.3)$$

To find the optimal control for the CE cost, from convexity, u unconstrained,

$$\frac{\partial J_{N-2}^{CE}}{\partial u_{N-2}} = 0$$

yields the optimal control for the CE cost

$$u_{N-2}^{CE} = -L_{N-2} \hat{x}_{N-2} \quad (4.4)$$

with

$$\begin{aligned} \hat{x}_{N-2} &= \sum_{i=1}^s p_{i,N-2} \hat{x}_{i,N-2} \\ L_{N-2} &= (R_{N-2} + S_{N-1} B^2)^{-1} S_{N-1} A B. \end{aligned}$$

In order to derive recursive expression of the dual cost at stage $N - 3$, we assume u_{N-2}^{CE} is applied at stage $N - 2$, and compute the optimal CE cost

$$\begin{aligned} J_{N-2}^{CE}(u_{N-2}^{CE}) &= (Q_{N-2} + S_{N-1}A^2) \left(\sum_{i=1}^s p_{i,N-2} \hat{x}_{i,N-2}^2 \right) \\ &\quad - L_{N-2}^2 (R_{N-2} + S_{N-1}B^2) \\ &\quad \left(\sum_{i=1}^s p_{i,N-2} \hat{x}_{i,N-2} \right)^2 + \sum_{i=1}^s p_{i,N-2} s_{i,N-2}. \end{aligned} \quad (4.5)$$

Using the identity,

$$\begin{aligned} \left(\sum_{i=1}^s p_{i,N-2} \hat{x}_{i,N-2} \right)^2 &= \sum_{i=1}^s p_{i,N-2} \hat{x}_{i,N-2}^2 \\ &\quad - \frac{1}{2} \sum_{i=1}^s \sum_{j=1}^s p_{i,N-2} p_{j,N-2} (\hat{x}_{i,N-2} - \hat{x}_{j,N-2})^2 \end{aligned} \quad (4.6)$$

Eq(4.5) becomes

$$\begin{aligned} J_{N-2}^{CE}(u_{N-2}^{CE}) &= S_{N-2} \left(\sum_{i=1}^s p_{i,N-2} \hat{x}_{i,N-2}^2 \right) + \sum_{i=1}^s p_{i,N-2} s_{i,N-2} \\ &\quad + G_{N-2} \sum_{i=1}^s \sum_{j=1}^s p_{i,N-2} p_{j,N-2} (\hat{x}_{i,N-2} - \hat{x}_{j,N-2})^2 \end{aligned} \quad (4.7)$$

where

$$\begin{aligned} S_{N-2} &= Q_{N-2} + S_{N-1}A^2 - L_{N-2}^2 (R_{N-2} + S_{N-1}B^2) \\ &= Q_{N-2} + S_{N-1}A^2 - 2G_{N-2} \\ G_{N-2} &= \frac{1}{2} L_{N-2}^2 (R_{N-2} + S_{N-1}B^2) \end{aligned} \quad (4.8)$$

Note that this is the CE cost at stage $N - 2$ when u^{CE} is applied.

Also $J_{N-2}^{CE}(u_{N-2}^{CE})$ can be further decomposed into two parts:

$$J_{N-2}^{CE}(u_{N-2}^{CE}) = c'_{N-2} + c''_{N-2} \quad (4.9)$$

where

$$\begin{aligned} c'_{N-2} &= \sum_{i=1}^s p_{i,N-2} (S_{N-2} \hat{x}_{i,N-2}^2 + s_{i,N-2}) \\ c''_{N-2} &= G_{N-2} \sum_{i=1}^s \sum_{j=1}^s p_{i,N-2} p_{j,N-2} (\hat{x}_{i,N-2} - \hat{x}_{j,N-2})^2. \end{aligned} \quad (4.10)$$

At stage $N - 3$, the cost-to-go is a sum of three costs,

$$\begin{aligned} E\{J_{N-2} \mid I^{N-3}\} &= E\{c'_{N-2} \mid I^{N-3}\} + E\{c''_{N-2} \mid I^{N-3}\} \\ &\quad + E\{J_{N-2}^{dual} \mid I^{N-3}\}. \end{aligned} \quad (4.11)$$

The first term of eq(4.11) is in the form of the standard LQG cost-to-go, the CE cost. The second term of eq.(4.11) is

$$\begin{aligned} &E\{c''_{N-2} \mid I^{N-3}\} \\ &= G_{N-2} \sum_{i=1}^s \sum_{j=1}^s p_{i,N-2} p_{j,N-2} \\ &\quad \cdot \int_{-\infty}^{+\infty} \frac{g_{i,N-2} g_{j,N-2}}{\Pr(y_{N-2} \mid I^{N-3})} (\hat{x}_{i,N-2} - \hat{x}_{j,N-2})^2 dy_{N-2} \end{aligned} \quad (4.12)$$

and is a cost associated with the dual covariance of the state at $N - 2$.

From eq(3.40), the third term of eq.(4.11) is

$$\begin{aligned} &E\{J_{N-2}^{dual} \mid I^{N-3}\} \\ &= \int_{-\infty}^{+\infty} \left\{ G_{N-1} \sum_{i=1}^s \sum_{j=1}^s p_{i,N-1} p_{j,N-1} \right. \\ &\quad \cdot \int_{-\infty}^{+\infty} \frac{g_{i,N-1} g_{j,N-1}}{\Pr(y_{N-1} \mid I^{N-2})} (\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 dy_{N-1} \Big\} \\ &\quad \Pr(y_{N-2} \mid I^{N-3}) dy_{N-2} \end{aligned} \quad (4.13)$$

$$\begin{aligned}
&= G_{N-1} \sum_{i=1}^s \sum_{j=1}^s p_{i,N-3} p_{j,N-3} \int_{-\infty}^{+\infty} \left\{ \frac{g_{i,N-2} g_{j,N-2}}{\Pr(y_{N-2} \mid I^{N-3})} \right. \\
&\quad \cdot \left. \int_{-\infty}^{+\infty} \frac{g_{i,N-1} g_{j,N-1}}{\Pr(y_{N-1} \mid I^{N-2})} (\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 dy_{N-1} \right\} dy_{N-2} \quad (4.14)
\end{aligned}$$

and is the dual cost propagated from stage $N-2$ to stage $N-3$, and it is the cost associated with the dual covariance of the state at $N-1$. The sum of the last two terms is associated with the dual covariance of the state from stage $N-2$ to $N-1$, we will refer to this sum as the dual cost at stage $N-3$, J_{N-3}^{dual} ,

$$J_{N-3}^{dual} \triangleq E\{c_{N-2}'' \mid I^{N-3}\} + E\{J_{N-2}^{dual} \mid I^{N-3}\} \quad (4.15)$$

Then the dual cost is given by

$$\begin{aligned}
J_{N-3}^{dual} &= \sum_{i=1}^s \sum_{j=1}^s p_{i,N-3} p_{j,N-3} \int_{-\infty}^{+\infty} \frac{g_{i,N-2} g_{j,N-2}}{\Pr(y_{N-2} \mid I^{N-3})} \\
&\quad \cdot \{G_{N-2} (\hat{x}_{i,N-2} - \hat{x}_{j,N-2})^2 \\
&\quad + G_{N-1} \cdot \int_{-\infty}^{+\infty} \frac{g_{i,N-1} g_{j,N-1}}{\Pr(y_{N-1} \mid I^{N-2})} \\
&\quad \cdot (\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 dy_{N-1} \} dy_{N-2}. \quad (4.16)
\end{aligned}$$

In the following, we will derive a recursive decomposition of the functional equation for the cost in the stochastic dynamic programming procedure at each stage k , $0 \leq k \leq N-2$. The decomposition will include the CE cost and the dual cost in closed form, for the multi-stage control problem.

It is worthwhile noting that in order to obtain a decomposition of the cost functional at each stage k , because the cost-to-go is very complicated, we assume that future controls will be CE controls.

We have the main result of this section:

Theorem 4.1. Assume that at stage k , $0 \leq k \leq N-2$ the CE control policies $u_t = u_t^{CE}$, $k+1 \leq t \leq N-1$ are applied as the future controls, then the cost from k to the terminal stage can be decomposed into CE cost and dual cost, J_k^{CE} and J_k^{dual} respectively,

$$J_k = J_k^{CE} + J_k^{dual} \quad (4.17)$$

where

$$\begin{aligned} J_k^{CE} = & (Q_k + S_{k+1}A^2) \left(\sum_{i=1}^s p_{i,k} \hat{x}_{i,k}^2 \right) + 2ABS_{k+1}u_k \left(\sum_{i=1}^s p_{i,k} \hat{x}_{i,k} \right) \\ & + (R_k + S_{k+1}B^2)u_k^2 + \sum_{i=1}^s p_{i,k} s_{i,k} \end{aligned} \quad (4.18)$$

$$\begin{aligned} J_k^{dual} = & \sum_{i=1}^s \sum_{j=1}^s p_{i,k} p_{j,k} \int_{-\infty}^{+\infty} \frac{g_{i,k+1} g_{j,k+1}}{\Pr(y_{k+1} | I^k)} \left[G_{k+1}(\hat{x}_{i,k+1} - \hat{x}_{j,k+1})^2 \right. \\ & + \int_{-\infty}^{+\infty} \frac{g_{i,k+2} g_{j,k+2}}{\Pr(y_{k+2} | I^{k+1})} \left[G_{k+2}(\hat{x}_{i,k+2} - \hat{x}_{j,k+2})^2 \right. \\ & + \dots \\ & + \int_{-\infty}^{+\infty} \frac{g_{i,N-2} g_{j,N-2}}{\Pr(y_{N-2} | I^{N-3})} \left[G_{N-2}(\hat{x}_{i,N-2} - \hat{x}_{j,N-2})^2 \right. \\ & + \int_{-\infty}^{+\infty} \frac{g_{i,N-1} g_{j,N-1}}{\Pr(y_{N-1} | I^{N-2})} G_{N-1}(\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 \\ & \left. \left. \left. dy_{N-1} \right] dy_{N-2} \dots \right] dy_{k+2} \right] dy_{k+1} \end{aligned} \quad (4.19)$$

with

$$S_{k+1} = Q_{k+1} + S_{k+2}A^2 - L_{k+1}^2(R_{k+1} + S_{k+2}B^2) \quad (4.20)$$

$$s_{i,k} = s_{i,k+1} + Q_k P_{i,k} + S_{k+1} K_{i,k+1}^2 M_{i,k+1}$$

$$G_{k+1} = \frac{1}{2} L_{k+1}^2 (R_{k+1} + S_{k+2}B^2) \quad \text{for } 0 \leq k+1 \leq N-1. \quad (4.21)$$

Proof. By induction, first at stage $N - 2$, we have eqs(4.1), (4.2) and (3.40). At stage $N - 3$, we have the result in eq(4.16) and

$$\begin{aligned}
J_{N-3}^{CE} &= E\{Q_{N-3}x_{N-3}^2 + R_{N-3}u_{N-3}^2 \mid I^{N-3}\} + E\{c'_{N-2} \mid I^{N-3}\} \\
&= E\{Q_{N-3}x_{N-3}^2 + R_{N-3}u_{N-3}^2 \mid I^{N-3}\} \\
&\quad + E\left\{\sum_{i=1}^s p_{i,N-2}(S_{N-2}\hat{x}_{i,N-2}^2 + s_{i,N-2}) \mid I^{N-3}\right\} \\
&= Q_{N-3} \sum_{i=1}^s p_{i,N-3}\hat{x}_{i,N-3}^2 + Q_{N-3} \sum_{i=1}^s p_{i,N-3}P_{i,N-3} \\
&\quad + R_{N-3}u_{N-3}^2 + E\left\{\sum_{i=1}^s p_{i,N-2}(S_{N-2}[A\hat{x}_{i,N-3} + Bu_{N-3} \right. \\
&\quad \left. + K_{i,N-2}(y_{N-2} - \hat{y}_{i,N-2})]^2 + s_{i,N-2}) \mid I^{N-3}\right\} \\
&= Q_{N-3} \sum_{i=1}^s p_{i,N-3}\hat{x}_{i,N-3}^2 + Q_{N-3} \sum_{i=1}^s p_{i,N-3}P_{i,N-3} \\
&\quad + R_{N-3}u_{N-3}^2 + \sum_{i=1}^s p_{i,N-3}(S_{N-2}(A\hat{x}_{i,N-3} + Bu_{N-3})^2 \\
&\quad + S_{N-2}K_{i,N-2}^2 M_{i,N-2} + s_{i,N-2}) \\
&= (Q_{N-3} + S_{N-2}A^2)\left(\sum_{i=1}^s p_{i,N-3}\hat{x}_{i,N-3}^2\right) \\
&\quad + 2ABS_{N-2}u_{N-3}\left(\sum_{i=1}^s p_{i,N-3}\hat{x}_{i,N-3}\right) \\
&\quad + (R_{N-3} + S_{N-2}B^2)u_{N-3}^2 + \sum_{i=1}^s p_{i,N-3}s_{i,N-3}
\end{aligned}$$

where

$$s_{i,N-3} = s_{i,N-2} + Q_{N-3}P_{i,N-3} + S_{N-2}K_{i,N-2}^2 M_{i,N-2}.$$

Now assume that at stage $k + 1$, we have

$$J_{k+1} = J_{k+1}^{CE} + J_{k+1}^{dual}$$

where

$$\begin{aligned} J_{k+1}^{CE} &= (Q_{k+1} + S_{k+2}A^2) \left(\sum_{i=1}^s p_{i,k+1} \hat{x}_{i,k+1}^2 \right) \\ &\quad + 2ABS_{k+2}u_{k+1} \left(\sum_{i=1}^s p_{i,k+1} \hat{x}_{i,k+1} \right) \\ &\quad + (R_{k+1} + S_{k+2}B^2)u_{k+1}^2 + \sum_{i=1}^s p_{i,k+1}s_{i,k+1} \\ J_{k+1}^{dual} &= \sum_{i=1}^s \sum_{j=1}^s p_{i,k+1}p_{j,k+1} \\ &\quad \cdot \int_{-\infty}^{+\infty} \frac{g_{i,k+2}g_{j,k+2}}{\Pr(y_{k+2} \mid I^{k+1})} \left[G_{k+2}(\hat{x}_{i,k+2} - \hat{x}_{j,k+2})^2 \right. \\ &\quad + \int_{-\infty}^{+\infty} \frac{g_{i,k+3}g_{j,k+3}}{\Pr(y_{k+3} \mid I^{k+2})} \left[G_{k+3}(\hat{x}_{i,k+3} - \hat{x}_{j,k+3})^2 \right. \\ &\quad + \dots \\ &\quad + \int_{-\infty}^{+\infty} \frac{g_{i,N-2}g_{j,N-2}}{\Pr(y_{N-2} \mid I^{N-3})} \left[G_{N-2}(\hat{x}_{i,N-2} - \hat{x}_{j,N-2})^2 \right. \\ &\quad + \int_{-\infty}^{+\infty} \frac{g_{i,N-1}g_{j,N-1}}{\Pr(y_{N-1} \mid I^{N-2})} G_{N-1}(\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 \\ &\quad \left. dy_{N-1} \right] dy_{N-2} \dots \left. dy_{k+3} \right] dy_{k+2} \end{aligned}$$

with

$$S_{k+2} = Q_{k+2} + S_{k+3}A^2 - L_{k+2}^2(R_{k+2} + S_{k+3}B^2)$$

$$s_{i,k+1} = s_{i,k+2} + Q_{k+1}P_{i,k+1} + S_{k+2}K_{i,k+2}^2M_{i,k+2}$$

$$G_{k+2} = \frac{1}{2}L_{k+2}^2(R_{k+2} + S_{k+3}B^2).$$

Then at stage k , when u_{k+1}^{CE} is to be applied,

$$\begin{aligned}
J_{k+1}^{CE}(u_{k+1}^{CE}) &= (Q_{k+1} + S_{k+2}A^2) \left(\sum_{i=1}^s p_{i,k+1} \hat{x}_{i,k+1}^2 \right) \\
&\quad - L_{k+1}^2 (R_{k+1} + S_{k+2}B^2) \left(\sum_{i=1}^s p_{i,k+1} \hat{x}_{i,k+1} \right)^2 \\
&\quad + \sum_{i=1}^s p_{i,k+1} s_{i,k+1} \\
&= S_{k+1} \left(\sum_{i=1}^s p_{i,k+1} \hat{x}_{i,k+1}^2 \right) + \sum_{i=1}^s p_{i,k+1} s_{i,k+1} \\
&\quad + G_{k+1} \sum_{i=1}^s \sum_{j=1}^s p_{i,k+1} p_{j,k+1} (\hat{x}_{i,k+1} - \hat{x}_{j,k+1})^2 \\
&= c'_{k+1} + c''_{k+1}
\end{aligned}$$

with

$$\begin{aligned}
c'_{k+1} &= \sum_{i=1}^s p_{i,k+1} (S_{k+1} \hat{x}_{i,k+1}^2 + s_{i,k+1}) \\
c''_{k+1} &= G_{k+1} \sum_{i=1}^s \sum_{j=1}^s p_{i,k+1} p_{j,k+1} (\hat{x}_{i,k+1} - \hat{x}_{j,k+1})^2,
\end{aligned}$$

and S_{k+1} is given in (4.20). We find the CE cost at stage k ,

$$\begin{aligned}
J_k^{CE} &= E\{Q_k x_k^2 + R_k u_k^2 \mid I^k\} + E\{c'_{k+1} \mid I^k\} \\
&= E\{Q_k x_k^2 + R_k u_k^2 \mid I^k\} \\
&\quad + E\left\{ \sum_{i=1}^s p_{i,k+1} (S_{k+1} \hat{x}_{i,k+1}^2 + s_{i,k+1}) \mid I^k \right\} \\
&= Q_k \sum_{i=1}^s p_{i,k} \hat{x}_{i,k}^2 + Q_k \sum_{i=1}^s p_{i,k} P_{i,k} + R_k u_k^2 \\
&\quad + E\left\{ \sum_{i=1}^s p_{i,k+1} (S_{k+1} [A \hat{x}_{i,k} + B u_k \right. \\
&\quad \left. + K_{i,k+1} (y_{k+1} - \hat{y}_{i,k+1})]^2 + s_{i,k+1}) \mid I^k \right\}
\end{aligned}$$

$$\begin{aligned}
&= Q_k \sum_{i=1}^s p_{i,k} \hat{x}_{i,k}^2 + Q_k \sum_{i=1}^s p_{i,k} P_{i,k} + R_k u_k^2 \\
&\quad + \sum_{i=1}^s p_{i,k} (S_{k+1} (A \hat{x}_{i,k} + B u_k)^2 + S_{k+1} K_{i,k+1}^2 M_{i,k+1} + s_{i,k+1}) \\
&= (Q_k + S_{k+1} A^2) \left(\sum_{i=1}^s p_{i,k} \hat{x}_{i,k}^2 \right) + 2AB S_{k+1} u_k \left(\sum_{i=1}^s p_{i,k} \hat{x}_{i,k} \right) \\
&\quad + (R_k + S_{k+1} B^2) u_k^2 + \sum_{i=1}^s p_{i,k} s_{i,k} = \text{eq}(4.18).
\end{aligned}$$

And the dual cost at stage k is given by

$$\begin{aligned}
J_k^{dual} &= E\{c''_{k+1} \mid I^k\} + E\{J_{k+1}^{dual} \mid I^k\} \\
&= \int_{-\infty}^{+\infty} \sum_{i=1}^s \sum_{j=1}^s p_{i,k+1} p_{j,k+1} G_{k+1}(\hat{x}_{i,k+1} - \hat{x}_{j,k+1})^2 \Pr(y_{k+1} \mid I^k) dy_{k+1} \\
&\quad + \int_{-\infty}^{+\infty} \sum_{i=1}^s \sum_{j=1}^s p_{i,k+1} p_{j,k+1} \\
&\quad + \int_{-\infty}^{+\infty} \frac{g_{i,k+2} g_{j,k+2}}{\Pr(y_{k+2} \mid I^{k+1})} \left[G_{k+2}(\hat{x}_{i,k+2} - \hat{x}_{j,k+2})^2 \right. \\
&\quad + \int_{-\infty}^{+\infty} \frac{g_{i,k+3} g_{j,k+3}}{\Pr(y_{k+3} \mid I^{k+2})} \left[G_{k+3}(\hat{x}_{i,k+3} - \hat{x}_{j,k+3})^2 \right. \\
&\quad + \dots \\
&\quad + \int_{-\infty}^{+\infty} \frac{g_{i,N-2} g_{j,N-2}}{\Pr(y_{N-2} \mid I^{N-3})} \left[G_{N-2}(\hat{x}_{i,N-2} - \hat{x}_{j,N-2})^2 \right. \\
&\quad + \int_{-\infty}^{+\infty} \frac{g_{i,N-1} g_{j,N-1}}{\Pr(y_{N-1} \mid I^{N-2})} G_{N-1}(\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 \\
&\quad \left. dy_{N-1} \right] dy_{N-2} \dots \left. dy_{k+3} \right] dy_{k+2} \Pr(y_{k+1} \mid I^k) dy_{k+1}
\end{aligned}$$

$$\begin{aligned}
&= \sum_{i=1}^s \sum_{j=1}^s p_{i,k} p_{j,k} \int_{-\infty}^{+\infty} \frac{g_{i,k+1} g_{j,k+1}}{\Pr(y_{k+1} | I^k)} \left[G_{k+1}(\hat{x}_{i,k+1} - \hat{x}_{j,k+1})^2 \right. \\
&\quad + \int_{-\infty}^{+\infty} \frac{g_{i,k+2} g_{j,k+2}}{\Pr(y_{k+2} | I^{k+1})} \left[G_{k+2}(\hat{x}_{i,k+2} - \hat{x}_{j,k+2})^2 \right. \\
&\quad + \dots \\
&\quad + \int_{-\infty}^{+\infty} \frac{g_{i,N-2} g_{j,N-2}}{\Pr(y_{N-2} | I^{N-3})} \left[G_{N-2}(\hat{x}_{i,N-2} - \hat{x}_{j,N-2})^2 \right. \\
&\quad + \int_{-\infty}^{+\infty} \frac{g_{i,N-1} g_{j,N-1}}{\Pr(y_{N-1} | I^{N-2})} G_{N-1}(\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 \\
&\quad \left. dy_{N-1} \right] dy_{N-2} \dots \left. dy_{k+2} \right] dy_{k+1} = \text{eq(4.19)},
\end{aligned}$$

with S_{k+1} , $s_{i,k}$ and G_{k+1} defined by eqs(4.20) and (4.21).

Then the total cost at stage k is found

$$\begin{aligned}
J_k &= E\{Q_k x_k^2 + R_k u_k^2 + J_{k+1} | I^k\} \\
&= J_k^{CE} + J_k^{dual} = \text{eq(4.17)},
\end{aligned}$$

hence the theorem is proved. □

Remark. J_k^{dual} (eq(4.19)) represents an additional cost incurred using the CE control strategy for a non-neutral system.

4.2 Approximation of the Dual Cost

Theorem 4.1 gives a recursive decomposition of the cost functional at each stage, but it is still difficult to calculate the dual cost in general. The major difficulty to the solution of the dual control problem results from the propagation of the dual cost through the backward dynamic programming

procedure. Even though the 1-measurement strategy is used, the dual cost in the cost-to-go is in a recursive form which can not, however, be evaluated analytically. An approximation should be used to evaluate the dual cost, using the multiple integral given by (4.19). In this section, we will investigate the possibility of approximating the dual cost at each stage using the results derived in section 4.1.

Examine eq(4.19), the dual cost at each stage is the sum of two costs, each associated with the dual covariance of the state from stage $k + 1$ to $N - 1$, that is, the current control signal to be applied will affect future uncertainties, quantified in terms of the dual covariance of state estimates. The covariance of the state estimates at stage $k + 1$ appears as the term

$$\sum_{i=1}^s \sum_{j=1}^s p_{i,k} p_{j,k} \int_{-\infty}^{+\infty} \frac{g_{i,k+1} g_{j,k+1}}{P(y_{k+1} | I^k)} G_{k+1}(\hat{x}_{i,k+1} - \hat{x}_{j,k+1})^2 dy_{k+1}$$

and the covariance of state estimates at stage $k + 2$ appears as the term

$$\begin{aligned} & \sum_{i=1}^s \sum_{j=1}^s p_{i,k} p_{j,k} \int_{-\infty}^{+\infty} \frac{g_{i,k+1} g_{j,k+1}}{P(y_{k+1} | I^k)} \\ & \cdot \int_{-\infty}^{+\infty} \frac{g_{i,k+2} g_{j,k+2}}{P(y_{k+2} | I^{k+1})} G_{k+2}(\hat{x}_{i,k+2} - \hat{x}_{j,k+2})^2 dy_{k+2} dy_{k+1} \end{aligned}$$

and so forth.

As will be shown in next section, as the *a posteriori* probabilities converge, the dual effect of the control becomes smaller and smaller, the main dual impact of the effect will be on enhancing the learning for the next stage. This property of the dual cost suggests that the priority of the dual control should

be to improve the system identification and state estimates as early as possible. This agrees with the intuition that the earlier the unknowns of the system are identified or estimated, the more confidence about the system parameters and states we have, the better performance we can achieve by using an controller designed on more accurate information. As it will be shown in section 4.6, as the *a posteriori* probabilities of the mode converges to their true value, either 0 or 1, assuming one of the modes represents the real system, the smaller the dual cost term becomes, (the dual cost is proportional to the product of the *a posteriori* probability pairs). This indicates that a truncated dual cost of (4.19) can be reasonably a good approximation, this is expressed in the following theorem.

Theorem 4.2. Assume that A, B are known, number of modes $s = 2$. Let $C_i = \min(C_1, C_2) = \gamma$ ($C_j \neq 0, j \neq i$), $CovW = q|\gamma|$, q is a finite positive real number. Then as $\gamma \rightarrow 0$, at stage k , the dominating, i.e., the major part of the dual cost is at the next stage, the rest terms of the dual cost are negligible.

$$\begin{aligned}
 J_k^{dual} &\approx E\{c''_{k+1} | I^k\} \\
 &\sum_{i=1}^s \sum_{j=1}^s p_{i,k} p_{j,k} \int_{-\infty}^{+\infty} \frac{g_{i,k+1} g_{j,k+1}}{P(y_{k+1} | I^k)} G_{k+1}(\hat{x}_{i,k+1} - \hat{x}_{j,k+1})^2 dy_{k+1} \\
 &\text{for } 0 \leq k \leq N - 2.
 \end{aligned} \tag{4.22}$$

Proof. Under the conditions, we have the covariance of observation conditioned on mode r_i , $M_{i,k+1} \rightarrow 0$, as $\gamma \rightarrow 0$, (see eq(2.33)), thus

$$g_{i,k+1} \rightarrow \delta(y_{k+1} - \hat{y}_{i,k+1}),$$

as $\gamma \rightarrow 0$. Then, the *a posteriori* probabilities for mode r_i and r_j are

$$p_{i,k+1} = \frac{p_{i,k} g_{i,k+1}}{p_{i,k} g_{i,k+1} + p_{j,k} g_{j,k+1}} \rightarrow \begin{cases} 1, & \text{for } y_{k+1} = \hat{y}_{i,k+1}; \\ 0, & \text{for } y_{k+1} \neq \hat{y}_{i,k+1}. \end{cases}$$

$$p_{j,k+1} = \frac{p_{j,k} g_{j,k+1}}{p_{i,k} g_{i,k+1} + p_{j,k} g_{j,k+1}} \rightarrow \begin{cases} 0, & \text{for } y_{k+1} = \hat{y}_{i,k+1}; \\ 1, & \text{for } y_{k+1} \neq \hat{y}_{i,k+1}. \end{cases}$$

as $\gamma \rightarrow 0$, respectively, we have

$$p_{i,k+1} p_{j,k+1} \rightarrow 0 \quad \text{for all } y_{k+1} \quad (4.22a)$$

and eq.(4.19) becomes

$$J_k^{dual} \rightarrow E\{c''_{k+1} \mid I^k\} \quad \text{for } 0 \leq k \leq N-2. \quad (4.22b)$$

as $\gamma \rightarrow 0$. The theorem is proved. $\square$

Theorem 4.2 is equivalent to saying that at stage k , $J_{k+1} \approx J_{k+1}^{CE}$. That is, the nearest future uncertainty represents mainly the future uncertainties. At the next stage, the dual cost can be neglected. Note that Theorem 4.2 allows us to use the same technique in evaluating the dual cost as in the last chapter.

Theorem 4.3. Assume that A, B are known, number of modes $s = 2$. Let $C_i = \min(C_1, C_2) = \gamma$ ($C_j \neq 0, j \neq i$), $CovW = q|\gamma|$, q is a finite positive real number. When $\gamma \rightarrow 0$, then

$$J_k^{dual} \approx \frac{\sqrt{2\pi M_{i,k+1}} G_{k+1} p_{i,k} p_{j,k} g_{j,k+1}}{p_{i,k} + \sqrt{2\pi M_{i,k+1}} p_{j,k} g_{j,k+1}} \cdot (\hat{x}_{i,k+1} - \hat{x}_{j,k+1})^2 \Big|_{y_{k+1}=\hat{y}_{i,k+1}} \quad (4.23)$$

where

$$\begin{aligned} (\hat{x}_{i,k+1} - \hat{x}_{j,k+1})^2 \Big|_{y_{k+1}=\hat{y}_{i,k+1}} &= [A(1 - K_{j,k+1} C_i) \hat{x}_{i,k} \\ &\quad - A(1 - K_{j,k+1} C_j) \hat{x}_{j,k} - K_{j,k+1} (C_i - C_j) B u_k]^2 \end{aligned} \quad (4.24)$$

Proof. Similar to the proof of Theorem 3.4 □

Summing up the results, we circumvented the technical difficulties of the multiple integral in the representation of the dual cost, through approximation. The important point is that by using this approach, we can find the dual control law that is actively probing the system and improve the future unknowns as will be presented in the next section.

4.3 The Dual Control Algorithm

Theorem 4.4. *The optimal control for the CE cost is*

$$u_k^{CE} = -L_k \hat{x}_k, \quad \text{for } 0 \leq k \leq N-1. \quad (4.25)$$

with

$$\hat{x}_k = \sum_{i=1}^s p_{i,k} \hat{x}_{i,k} \quad (4.25a)$$

$$L_k = (R_k + S_{k+1} B^2)^{-1} S_{k+1} A B. \quad (4.25b)$$

Under the conditions of Theorem 4.3, the local minimum control for the dual cost is

$$u_k^{dual}(i) = -\frac{A}{B} \frac{(K_{j,k+1} C_i - 1) \hat{x}_{i,k} - (K_{j,k+1} C_j - 1) \hat{x}_{j,k}}{K_{j,k+1} (C_i - C_j)},$$

for $0 \leq k \leq N-1.$ (4.26)

Proof. Eq(4.25) is a direct result of eq(4.18). Proof of (4.26) is similar to that of Theorem 3.4 (iii). □

Note that the global minimum of the dual cost occurs when the controls $u_k = \pm\infty$. These are ruled out as the global minimum control since at $u_k = \pm\infty$, $J_k^{CE} \rightarrow \infty$, and this is of course not practical in any case.

Analogous to the dual control algorithm for the two-stage dual control problem presented in chapter three, we now propose the following dual control algorithm for the multi-stage finite horizon dual control problem.

The algorithm for the one-step dual control problem for unknown observation parameter systems is given as follows:

Step 1. At stage k , compute u_k using eq(4.25) and (4.26), u_k^{CE} and u_k^{dual} , respectively.

Step 2. Calculate $J_k(u_k^{CE})$ and $J_k(u_k^{dual})$ according to eq(4.17) to eq(4.21).

Step 3. Compare $J_k(u_k^{CE})$ and $J_k(u_k^{dual})$. If

$$J_k(u_k^{CE}) > J_k(u_k^{dual}) \quad \text{then } u_k = u_k^{dual} \quad \text{is applied}$$

otherwise

$$J_k(u_k^{CE}) \leq J_k(u_k^{dual}) \quad \text{then } u_k = u_k^{CE} \quad \text{is applied}$$

Step 4. Advance stage from k to $k + 1$. Go to Step 1.

Remarks of the algorithm. (1) The underlying principle of Step 3 is: We know CE cost minimum and dual cost minimum separately, but we do not know how the minimum of the total cost is achieved as the combination of the two costs. We can, however, compare and determine the lower of the total cost.

(2) The algorithm is of the 1-measurement closed-loop type control, the approximation is in the value of the dual cost in the cost-to-go. Theorem 4.2 says that the 1-measurement closed-loop control can be nearly as good as the

closed-loop control. The importance of the dual cost approximation lies in the fact that it makes the computation possible.

(3) The algorithm has the following advantages:

1. Eliminates numerical search. The dual cost and the dual control are evaluated using closed form formulas as for the CE cost and the CE control.
2. Guarantees at each stage better performance over the certainty equivalence control considering the one-step ahead cost.
3. Simple to implement.

(4) In the development of the algorithm, it is noted that the choice of future control being CE control is "artificial" in the sense that it may not actually be applied in the future, unless the CE control is a nearly optimal control as will be discussed in the next chapter, or the system becomes a neutral system. Once the *a posteriori* probabilities converge to their true values, it is only used to approximate the cost-to-go. This approximation can be very close to the optimal cost-to-go, that is, the controls in the future will practically be CE controls.

(5) Lower and upper bounds on the performance of the algorithm can be analyzed as follows.

Theorem 4.4. *The lower bound of the algorithm above is*

$$\inf J_k = J_k^{CE} + \sum_{i=1}^s \sum_{j=1}^s p_{i,k} p_{j,k} \cdot \int_{-\infty}^{+\infty} \frac{g_{i,k+1} g_{j,k+1}}{P(y_{k+1} | I^k)} G_{k+1}(\hat{x}_{i,k+1} - \hat{x}_{j,k+1})^2 dy_{k+1} \quad (4.27a)$$

and J_k is bounded from above by

$$\begin{aligned} \sup J_k = & S_k \left(\sum_{i=1}^s p_{i,k} \hat{x}_{i,k}^2 \right) + \sum_{i=1}^s p_{i,k} s_{i,k} + G_k \sum_{i=1}^s \sum_{j=1}^s p_{i,k} p_{j,k} (\hat{x}_{i,k} - \hat{x}_{j,k})^2 \\ & + \sum_{i=1}^s \sum_{j=1}^s p_{i,k} p_{j,k} \int_{-\infty}^{+\infty} \frac{g_{i,k+1} g_{j,k+1}}{P(y_{k+1} | I^k)} \left[G_{k+1}(\hat{x}_{i,k+1} - \hat{x}_{j,k+1})^2 \right. \\ & + \int_{-\infty}^{+\infty} \frac{g_{i,k+2} g_{j,k+2}}{P(y_{k+2} | I^{k+1})} \left[G_{k+2}(\hat{x}_{i,k+2} - \hat{x}_{j,k+2})^2 \right. \\ & + \dots \\ & + \int_{-\infty}^{+\infty} \frac{g_{i,N-2} g_{j,N-2}}{P(y_{N-2} | I^{N-3})} \left[G_{N-2}(\hat{x}_{i,N-2} - \hat{x}_{j,N-2})^2 \right. \\ & + \int_{-\infty}^{+\infty} \frac{g_{i,N-1} g_{j,N-1}}{P(y_{N-1} | I^{N-2})} G_{N-1}(\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 \\ & \left. dy_{N-1} \right] dy_{N-2} \dots \left. dy_{k+2} \right] dy_{k+1} \Big|_{u_k = -L_k \hat{x}_k}. \end{aligned} \quad (4.27b)$$

Proof. From eq(4.22b) we immediately have the lower bound when $p_{i,k+2}$, $0 \leq k \leq N$ goes to the true value $p_{i,k+2} \rightarrow \Lambda_{i^*}$, at stage k , where Λ is an indicator function. The upper bound is obtained when u_k^{CE} is applied to the system at stage k , then (4.28) is direct result of Theorem 4.1 (Also refer to Theorem 4.9). $\square$

The lower bound (4.27) is reached at stage k once $p_{i,k+2}$ converges to the true value. The upper bound must be evaluated numerically.

As will be seen in the next chapter, the lower bound and the upper bound are useful in the comparison of the algorithm with the optimal control and the CE control solutions.

4.4 Multi-mode Dual Control System

The results and algorithm in previous sections can be extended to the multi-mode cases, where more than two possible modes for system parameters occur.

Theorem 4.5. *Assume that A, B are known, number of modes $s > 2$. Let $C_i = \min(C_i, C_j) = \gamma$, i and j represent each possible pair of modes, ($C_j \neq 0, j \neq i$), $CovW = q|\gamma|$, q is a finite positive real number. When $\gamma \rightarrow 0$, then at stage k , we have the approximation of the dual cost*

$$J_k^{dual} \approx \sum_{i=1}^s \sum_{j=1}^s J_k^{dual}(i, j) \quad (4.28)$$

where the pairwise dual cost is

$$J_k^{dual}(i, j) = G_{k+1} p_{i,k} p_{j,k} \int_{-\infty}^{+\infty} \frac{g_{i,k+1} g_{j,k+1}}{p_{i,k} g_{i,k+1} + p_{j,k} g_{j,k+1}} (\hat{x}_{i,k+1} - \hat{x}_{j,k+1})^2 dy_{k+1}. \quad (4.29)$$

Proof. Similar to the proof of Theorem 3.6, using the result of Theorem 4.2, and note that

$$p_{j,k+1} = \frac{p_{j,k}g_{j,k+1}}{p_{i,k}g_{i,k+1} + p_{j,k}g_{j,k+1}} \rightarrow \begin{cases} 0, & \text{for } y_{k+1} = \hat{y}_{i,k+1}; \\ \lambda, & \text{for } y_{k+1} \neq \hat{y}_{i,k+1} \end{cases}$$

where λ is a nonzero number, $0 < \lambda \leq 1$. Therefore, eq(4.22a) also holds for the case when $s > 2$. □

The algorithm in section 4.3 is then modified according to Theorem 4.5 as follows:

- Step 1. At stage k , compute u_k using eq(4.25) and (4.26), u_k^{CE} and $u_k^{dual}(i, j)$, respectively, where $u_k^{dual}(i, j)$ is the dual control for the pairwise dual cost associated with each pair of modes i and j .
- Step 2. Calculate $J_k(u_k^{CE})$ and each $J_k(u_k^{dual}(i, j))$ according to eq(4.17) to eq(4.21).
- Step 3. Compare $J_k(u_k^{CE})$ and all $J_k(u_k^{dual}(i, j))$. Choose the control that yields the minimum cost J_k as the control policy to be applied at stage k .
- Step 4. Advance stage from k to $k + 1$. Go to Step 1.

4.5 Systems with All Parameters Unknown

All the previous discussions and results assume that the plant dynamics parameters are known, and only the observation coefficient is to be identified. This assumption seriously limits the application of the algorithm. It is necessary to extend the results to systems that may have all the parameters unknown.

Examine the cost-to-go at each stage. As in section 3.1, we have at the terminal stage, the cost functional

$$\begin{aligned} J_N &= E\{Q_{r,N}x_N^2 + R_{r,N}u_N^2\} \\ &= Q_N \sum_{i=1}^s p_{i,N}(\hat{x}_{i,N}^2 + P_{i,N}) \end{aligned} \quad (4.30)$$

At stage $N-1$, (see eq(3.14))

$$\begin{aligned} J_{N-1} &= Q_{N-1} \sum_{i=1}^s p_{i,N-1} \hat{x}_{i,N-1}^2 + Q_N \sum_{i=1}^s p_{i,N-1} A_i^2 \hat{x}_{i,N-1}^2 \\ &\quad - \phi_{N-1} (Q_N \sum_{i=1}^s p_{i,N-1} A_i B_i \hat{x}_i)^2 + Q_{N-1} \sum_{i=1}^s p_{i,N-1} P_{i,N-1} \\ &\quad + Q_N \sum_{i=1}^s p_{i,N-1} P_{i,N} + Q_N \sum_{i=1}^s p_{i,N-1} K_{i,N}^2 M_{i,N} \end{aligned} \quad (4.31)$$

$$\begin{aligned} &= Q_{N-1} (\sum_{i=1}^s p_{i,N-1} \hat{x}_{i,N-1}^2) + Q_N (\sum_{i=1}^s p_{i,N-1} A_i^2 \hat{x}_{i,N-1}^2) \\ &\quad - \phi_{N-1} Q_N^2 (\sum_{i=1}^s p_{i,N-1} A_i B_i \hat{x}_i^2) + \sum_{i=1}^s p_{i,N-1} s_{i,N-1} \\ &\quad + \frac{1}{2} \phi_{N-1} Q_N^2 \sum_{i=1}^s \sum_{j=1}^s p_{i,N-1} p_{j,N-1} A_i B_i A_j B_j \\ &\quad \cdot (\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 \end{aligned} \quad (4.32)$$

$$= J_{N-1}^{CE} + J_{N-1}^{dual}. \quad (4.33)$$

The cost can be decomposed into the CE cost and the dual cost, where the CE cost is

$$\begin{aligned} J_{N-1}^{CE} = & Q_{N-1} \left(\sum_{i=1}^s p_{i,N-1} \hat{x}_{i,N-1}^2 \right) + Q_N \left(\sum_{i=1}^s p_{i,N-1} A_i^2 \hat{x}_{i,N-1}^2 \right) \\ & - \phi_{N-1} Q_N^2 \left(\sum_{i=1}^s p_{i,N-1} A_i B_i \hat{x}_i^2 \right) + \sum_{i=1}^s p_{i,N-1} s_{i,N-1} \end{aligned} \quad (4.34)$$

and the dual cost is

$$\begin{aligned} J_{N-1}^{dual} = & \frac{1}{2} \phi_{N-1} Q_N^2 \sum_{i=1}^s \sum_{j=1}^s p_{i,N-1} p_{j,N-1} A_i B_i A_j B_j \\ & \cdot (\hat{x}_{i,N-1} - \hat{x}_{j,N-1})^2 \end{aligned} \quad (4.35)$$

where

$$\phi_{N-1} \triangleq -(R_{N-1} + Q_N \sum_{i=1}^s p_{i,N-1} B_i^2)^{-1} \quad (4.36)$$

$$s_{i,N-1} = s_{i,N} + Q_{N-1} P_{i,N-1} + S_N K_{i,N}^2 M_{i,N} \quad (4.37)$$

$$s_{i,N} = S_N P_{i,N} \quad \text{and} \quad S_N = Q_N.$$

From eq(4.34),

$$\begin{aligned} J_{N-1}^{CE} = & Q_{N-1} \left(\sum_{i=1}^s p_{i,N-1} \hat{x}_{i,N-1}^2 \right) + Q_N \left(\sum_{i=1}^s p_{i,N-1} A_i^2 \hat{x}_{i,N-1}^2 \right) \\ & - \phi_{N-1} Q_N^2 \left(\sum_{i=1}^s p_{i,N-1} A_i B_i \hat{x}_i^2 \right) + \sum_{i=1}^s p_{i,N-1} s_{i,N-1} \\ = & \sum_{i=1}^s p_{i,N-1} (Q_{N-1} + Q_N A_i^2 - \phi_{N-1} Q_N^2 A_i B_i) \hat{x}_{i,N-1}^2 \\ & + \sum_{i=1}^s p_{i,N-1} s_{i,N-1} \end{aligned} \quad (4.38)$$

$$= \sum_{i=1}^s p_{i,N-1} S_{i,N-1} \hat{x}_{i,N-1}^2 + \sum_{i=1}^s p_{i,N-1} s_{i,N-1} \quad (4.39)$$

where

$$S_{i,N-1} = Q_{N-1} + S_{i,N}A_i^2 - \phi_{N-1}S_{i,N}^2A_iB_i \quad (4.40)$$

$$S_{i,N} = Q_N$$

Recall in section 3.1, we assumed that $A_i = A_j$ and $B_i = B_j$ in order to have a recursive computation of $S_{i,k}$ for $0 \leq k \leq N-1$. Now we want to relax these conditions, but since $S_{i,N-1}$ is a nonlinear function of the *a posteriori* probability $p_{i,N-1}$, $i = 1, 2 \dots s$, the analysis for J_{N-1}^{CE} in the previous sections can not be applied here, and direct mathematical manipulation in closed form is not possible. Therefore, we need to find an approximation to $S_{i,N-1}$ so that recursive generation of $S_{i,N-2}$, $S_{i,N-3}$ and so on can be obtained.

One method to approximate the weighting function of the optimal cost functional $S_{i,N-1}$ is to linearize $S_{i,N-1}$. Consider each

$$S_{i,N-1} = f_i(p_1, p_2, \dots, p_{s-1}), \quad i = 1, 2, \dots, s$$

to be a surface in an $(s-1)$ dimensional Euclidian space.* That is

$$f_i(p_1, p_2, \dots, p_{s-1}) - S_{i,N-1} = 0$$

Then the "tangent plane" $\tilde{S}_{i,N-1}$ to $S_{i,N-1}$ is defined at the point $p_k = (p_{1,k}, p_{2,k}, \dots, p_{s,k})^T$ by

$$f_{p_{N-1}} \big|_{p_{N-1}=p_k} (p_{N-1} - p_k) - [\tilde{S}_{i,N-1} - S_{i,N-1}(p_k)] = 0$$

* since $\sum_{i=1}^s p_{i,k} = 1$, $S_{i,k}$ has only $s-1$ independent *a posteriori* probability variables.

where $f_{p_{N-1}}|_{p_{N-1}=p_k}$ is the Jacobian of $f_{i,N-1}$ with respect to p_{N-1} evaluated at p_k . that is

$$\tilde{S}_{i,N-1} = S_{i,N-1}(p_k) + f_{p_{N-1}}|_{p_{N-1}=p_k}(p_{N-1} - p_k) \quad (4.41)$$

We can however use the zero-order term of (4.41), since $\tilde{S}$ as a linear function of p_k prevents analytical evaluation of $E\{J_{N-1}^{CE}|I^{N-2}\}$. Let

$$\tilde{S}_{i,N-1} = S_{i,N-1}(p_{N-2}), \quad (4.42)$$

then from eq(4.39), the CE cost part in the cost-to-go at stage $N - 2$ is a quadratic, convex function of the state and the control:

$$\begin{aligned} E\{J_{N-1}^{CE}|I^{N-2}\} &= \int_{-\infty}^{+\infty} \left[\sum_{i=1}^s p_{i,N-1} \tilde{S}_{i,N-1} \hat{x}_{i,N-1}^2 P(y_{N-1} | I^{N-2}) \right. \\ &\quad \left. + \sum_{i=1}^s p_{i,N-2} s_{i,N-1} \right] dy_{N-1} \\ &= \int_{-\infty}^{+\infty} \sum_{i=1}^s p_{i,N-2} \frac{g_{i,N-1}}{P(y_{N-1} | I^{N-2})} \tilde{S}_{i,N-1} \hat{x}_{i,N-1}^2 \\ &\quad \cdot P(y_{N-1} | I^{N-2}) dy_{N-1} + \sum_{i=1}^s p_{i,N-2} s_{i,N-1} \\ &= \sum_{i=1}^s p_{i,N-2} \tilde{S}_{i,N-1} \int_{-\infty}^{+\infty} g_{i,N-1} \hat{x}_{i,N-1}^2 dy_{N-1} \\ &\quad + \sum_{i=1}^s p_{i,N-2} s_{i,N-1} \\ &= \sum_{i=1}^s p_{i,N-2} \tilde{S}_{i,N-1} \int_{-\infty}^{+\infty} g_{i,N-1} [A_i \hat{x}_{i,N-2} + B_i u_{N-2} \\ &\quad + K_{i,N-1} (y_{N-1} - \hat{y}_{i,N-1})]^2 dy_{N-1} + \sum_{i=1}^s p_{i,N-2} s_{i,N-1} \end{aligned}$$

$$\begin{aligned}
&= \sum_{i=1}^s p_{i,N-2} \tilde{S}_{i,N-1} (A_i \hat{x}_{i,N-2} + B_i u_{N-2})^2 \\
&\quad + \sum_{i=1}^s p_{i,N-2} \tilde{S}_{i,N-1} K_{i,N-1} M_{i,N-1} \\
&\quad + \sum_{i=1}^s p_{i,N-2} s_{i,N-1}. \tag{4.43}
\end{aligned}$$

Note that $\tilde{S}_{i,k}$ is different from $S_{i,k}$ in the sense that $\tilde{S}_{i,k}$ depends on the current value of the *a posteriori* probabilities, and can not be precomputed off-line, it must be evaluated at each stage after the *a posteriori* probability vector is updated.

We are then able to use the feedback type control to preserve the convexity of the CE cost at each stage. We note, the derivations of (4.43) resemble those in Chapter 3, therefore, we have the analysis analogous to that in the previous sections for the CE cost J_k^{CE} . Also the dual cost J_{N-1}^{dual} of (4.35) is in a form similar to eq(3.24), where A and B are known parameters, suggesting that the properties of the dual cost are preserved for the more general system. Therefore, although the problem is more general, it is always possible to use some method to approximate the system using a simple formulation. The cost-to-go may be decomposed into the CE type cost and the dual cost which contains extra information about future unknowns, that the CE control law ignores. We can use the same approach as we did for the simpler case.

Thus, the analysis of the dual cost and CE cost applies here to eq(4.35) and eq(4.43), i.e., Theorem 3.1 to Theorem 4.5 are valid with appropriate modifications.

Consequently, the proposed algorithm can be easily modified to be used on more general systems, with all parameters dependent on the unknown mode r .

4.6 Convergence of the *a posteriori* Probabilities

The previously proposed dual control algorithm assumes that the *a posteriori* probabilities converge to their true values. We want to show that this is indeed true, and further more, we will also show that the convergence rate of the *a posteriori* probabilities depends on the control applied at each stage.

Definition 4.1. Let $(\Omega, \mathcal{F}, \mathcal{P})$ be a probability space with an increasing family of σ -algebras $\{\mathcal{F}_t\}$, $t \in T$ is given, where $T = \{0, 1, \dots\}$. $\mathcal{F}_t \subset \mathcal{F}_s$, $t < s$. Let $\{X_t\}$ be a real valued stochastic process such that

- (i) $E|X_t| < \infty$
- (ii) X_t is $\mathcal{F}_t$ measurable
- (iii) $E\{X_s \mid \mathcal{F}_t\} = X_t$ almost surely $t < s$

then $\{X_t\}$ is said to be a martingale adapted to σ -algebra $\{\mathcal{F}_t\}$.

To verify that $\{p_{i,t}\}$ is a martingale adapted to the appropriate σ -algebra $\{\mathcal{F}_t\}$ generated by the information, we use the set-up: the sample space is $\mathbb{R}$, σ -algebra $\{\mathcal{F}_t\}$ is given by $\{I^t\}$, where $\{I^t\}$ is defined in (2.4). $\mathcal{P}$ is a probability measure defined on the σ -algebra $\{\mathcal{F}_t\}$.

(i) and (ii) are obvious.

$$\begin{aligned}
E\{p_{i,t+1} \mid I^t\} &= \int_{-\infty}^{+\infty} p_{i,t+1} d\mathcal{P} \\
&= \int_{-\infty}^{+\infty} p_{i,t+1} dP(y_{t+1} \mid I^t) \\
&= \int_{-\infty}^{+\infty} \frac{p_{i,t} g_{i,t+1}}{P(y_{t+1} \mid I^t)} P(y_{t+1} \mid I^t) dy_{t+1} \\
&= \int_{-\infty}^{+\infty} p_{i,t} g_{i,t+1} dy_{t+1} \\
&= p_{i,t} \quad \text{almost surely}
\end{aligned}$$

with respect to Lebesgue measure. Since

$$E\{X_s \mid \mathcal{F}_t\} = E\{E\{X_s \mid \mathcal{F}_{s-1}\} \mid \mathcal{F}_t\} = E\{X_{s-1} \mid \mathcal{F}_t\}$$

by induction,

$$E\{p_{i,s} \mid I^t\} = p_{i,t} \quad \text{almost surely} \quad \text{for all } t < s \quad (4.44)$$

with respect to Lebesgue measure. Hence, $\{p_{i,t}\}$ is a martingale with respect to $\{I^t\}$ on the underlying probability space $(\mathbb{R}, \mathcal{F}, \mathcal{P})$.

In the following, we state two well known theorems without proof.

Theorem 4.6. (Doob, 1953) *Let $\{X_t, \mathcal{F}_t\}$ be a martingale with respect to $(\Omega, \mathcal{F}, \mathcal{P})$, then there exists a random variable X such that*

$$\lim_{t \rightarrow \infty} X_t = X \quad \text{almost surely} \quad (4.45)$$

and

$$E|X| < \infty. \quad (4.46)$$

Theorem 4.7. (Zero-or-one Law, Lévy, 1935)* Let Λ_B be the indicator function, i.e.,

$$\Lambda_B(\omega) = \begin{cases} 1, & \omega \in B; \\ 0, & \omega \notin B. \end{cases} \quad (4.47)$$

where B is an element of the σ -algebra $\mathcal{F}_\infty = \lim_{t \rightarrow \infty} \mathcal{F}_t$, i.e., $B \in \mathcal{F}_\infty$, then

$$\lim_{t \rightarrow \infty} \Pr(B \mid \mathcal{F}_t) = \Lambda_B \quad \text{almost surely} \quad (4.48)$$

From Theorem 4.6 and Theorem 4.7, using the property of a martingale, we have the immediate result on the convergence of the *a posteriori* probabilities of mode r_i .

Theorem 4.8. The *a posteriori* probabilities for the system (2.1) given by eq.(2.7) converge with probability one to the true mode

$$\lim_{k \rightarrow \infty} \Pr(r = r_i \mid I^{k+1}) = \Lambda_{i*} \quad \text{almost surely} \\ i = 1, 2, \dots, s \quad (4.49)$$

* Other versions see e.g., Doob(1953), and Loève(1960).

where Λ is the indicator function, i^* is the true mode value for r .

Note that, as a matter of fact, the convergence theorem is independent of the control signals applied to the system. That is, no matter what control law is used, the *a posteriori* probabilities will always converge to their true values. The speed of convergence, nevertheless, depends on the control signals applied, as was pointed out by Saridis and Dao (1972). It was thought that the active learning adaptive control would force the *a posteriori* probabilities to converge more rapidly than the passive learning controls.

The proof of the Theorem for the particular problem has also been given by Saridis and Dao(1972), Anderson and Moore(1979).

Next we investigate the dependence of convergence rate of the *a posteriori* probabilities on the control policy.

For $s = 2$ case, first consider

$$\begin{aligned} \Delta p_{i,k} &\triangleq |p_{i,k+1} - p_{i,k}| \\ &= \left| \frac{p_{i,k} g_{i,k+1}}{P(y_{k+1} | I^k)} - p_{i,k} \right| \end{aligned} \quad (4.50)$$

$$\begin{aligned} &= p_{i,k} \left| \frac{g_{i,k+1} - \sum_{j=1}^s p_{j,k} g_{j,k+1}}{\sum_{j=1}^s p_{j,k} g_{j,k+1}} \right| \\ &= p_{i,k} \left| \frac{g_{i,k+1} - p_{i,k} g_{i,k+1} - p_{j,k} g_{j,k+1}}{p_{i,k} g_{i,k+1} + p_{j,k} g_{j,k+1}} \right| \\ &= p_{i,k} \left| \frac{(1 - p_{i,k}) g_{i,k+1} - p_{j,k} g_{j,k+1}}{p_{i,k} g_{i,k+1} + p_{j,k} g_{j,k+1}} \right| \\ &= p_{i,k} p_{j,k} \frac{|g_{i,k+1} - g_{j,k+1}|}{P(y_{k+1} | I^k)}. \end{aligned} \quad (4.51)$$

The convergence rate of the *a posteriori* probabilities can be measured by

$$\begin{aligned}
 & E\{|p_{i,k+1} - p_{i,k}| \mid I^k\} \\
 &= \int_{-\infty}^{+\infty} p_{i,k} p_{j,k} \frac{|g_{i,k+1} - g_{j,k+1}|}{P(y_{k+1} \mid I^k)} P(y_{k+1} \mid I^k) dy_{k+1} \\
 &= p_{i,k} p_{j,k} \int_{-\infty}^{+\infty} |g_{i,k+1} - g_{j,k+1}| dy_{k+1}
 \end{aligned} \tag{4.52}$$

the value of the integral on the right hand side of the above expression is depicted in Figure 4.1.

The shaded area in Fig. 4.1 is the value of the integral which is a function of u_k , since it depends on $|\hat{y}_{i,k+1} - \hat{y}_{j,k+1}|$, the distance between the two predictions of the output corresponding to each of the two modes:

$$|\hat{y}_{i,k+1} - \hat{y}_{j,k+1}| = |C_i(A_i \hat{x}_{i,k} + B_i u_k) - C_j(A_j \hat{x}_{j,k} + B_j u_k)|, \tag{4.53}$$

as long as $C_i B_i - C_j B_j \neq 0$. Therefore, we have shown that the convergence rate of the *a posteriori* probabilities depends on the control policy: the magnitude of control is unbounded for obtaining the largest convergence rate of the *a posteriori* probabilities.

The two-mode statement on the convergence rate of *a posteriori* probability can be extended to multi-mode systems based on a similar argument as used in section 4.4.

Observation.

(i) Obviously, $u_k = \pm\infty \Rightarrow \max |\hat{y}_{i,k+1} - \hat{y}_{j,k+1}|$. This implies that when the control is infinitely large, it drives the probability distribution of future

FIG. 4.1(a)

Figure 4.1(a). Integral of difference in Gaussian density function, observation expectations are apart.

FIG. 4.1(b)

Figure 4.1(b). Integral of difference in Gaussian density function, observation expectations are close.

observations in different modes far apart, hence the different modes are completely distinguishable from each other. The convergence to the true values is achieved immediately. The convergence rate of the *a posteriori* probability is maximized as $u_k \rightarrow \pm\infty$.

(ii) Interestingly, if we let

$$|\hat{y}_{i,k+1} - \hat{y}_{j,k+1}| = 0,$$

that is, eq(4.53) becomes minimum, the modes overlap which is in the worst case for mode separation, this control results in poor learning of the system mode. The control which has this property is

$$u_k = -\frac{C_i A_i \hat{x}_{i,k} - C_j A_j \hat{x}_{j,k}}{C_i B_i - C_j B_j},$$

when $A_i = A_j = A$, $B_i = B_j = B$ and $\hat{x}_{i,k} = \hat{x}_{j,k} = \hat{x}_k$, we have

$$u_k = -\frac{A}{B} \hat{x}_k = \text{eq}(3.42)$$

(compare with eq(3.42) where the subscript $N-2$ is replaced by k), i.e., the local minimum dual control for the dual cost causes the *a posteriori* probabilities to converge the slowest. This contradicts the perception that the dual control, or the active learning control policy, would *always* cause the *a posteriori* probabilities to converge faster than other passive learning control policies.

The uncertainty of the state estimate includes both $p_{i,k}, p_{j,k}$ and $(x_{i,k} - x_{j,k})^2$, therefore, it is not necessary to have a faster reduction in the uncertainty of the mode, to reduce the uncertainty in the state estimates.

Of course, it is possible to formulate the problem such that the uncertainty of the system mode represents the future uncertainties, hence the speed of convergence of the *a posteriori* probabilities can be optimized.

4.7 Best Affine Suboptimal Control Theorem

While it is known that for general stochastic control problems the optimal control is of the closed-loop type, that is, the controller should know that the control loop will be closed to the end of control horizon and take advantage of the future statistics of the system (section 2.1), no analytical solution of the optimal control can be obtained because of the “curse of dimensionality”. Therefore, suboptimal solutions to the problem are sought. Of the class of dual controllers i.e. the active learning controllers, there are two classes of dual controls: affine policies and non-affine policies. Because the non-affine policies generally require a numerical solution because they are not recursive in nature, the class of affine policies is more practical and receives more attention from the applications perspective.

Generally, the affine controllers are simple and easy to implement, recursive solutions can be found. In this work, the dual control algorithm is achieved by the 1-measurement (one-step-ahead) closed-loop control, and it is of the affine control type as will be shown next. The question now is when the control policies are restricted to the class of affine policies, whether this controller is the best affine controller or it would be possible to improve the

performance by using m -measurement closed-loop controls, with $m \leq 2$. The following theorem shows that the one-step-ahead closed-loop control is the best affine control law.

By the principle of optimality, and the results of Theorem 4.2, the one-step-ahead dual control, being the best affine control policies, is also a nearly optimal control so long as the *a posteriori* probabilities converge rapidly. When the *a posteriori* probabilities do not converge rapidly, it is conjectured from the formulation of the dual cost that the result of Theorem 4.2 should be true, that is, the dual cost in the cost-to-go dominates at the next stage.

Theorem 4.9. *The best affine controller is the one-step dual controller.*

Proof. The proof consists of four parts.

(a) *$(k + 1)$ -step dual controller has smaller optimal cost than k -step dual controller.*

For the set of controls U_0 using available information I^k up to time k , without using future observations, there is a strict superset U_1 , which includes the controls using $P(y_{k+1} | I^k)$, the next future observation in addition to the available information I^k that U_0 uses.

Let $\tilde{J}_0$ be the performance cost associated with the class of controls U_0 , and $\tilde{J}_1$ be the performance cost associated with the class of controls U_1 . Denote

$$\tilde{J}_0^* = \inf_{u \in U_0} (\tilde{J}_0)$$

and

$$\tilde{J}_1^* = \inf_{u \in \mathcal{U}_1} (\tilde{J}_1)$$

then we have

$$\tilde{J}_1^* \leq \tilde{J}_0^*.$$

Note that $\tilde{J}_0^*$ is the cost using an open loop feedback control policy.

In a similar manner we have

$$\tilde{J}_{k+1}^* \leq \tilde{J}_k^* \leq \dots \leq \tilde{J}_0^*.$$

(b) *one-step dual control is affine in the state estimate.*

For the one-step dual control policy at stage k , CE control policies will be applied to the future stages $k+1, k+2, \dots, N-1$, i.e., $u_{k+1} = u_{k+1}^{CE}$, $u_{k+2} = u_{k+2}^{CE}, \dots, u_{N-1} = u_{N-1}^{CE}$, then the optimal control at k can be written as

$$\bar{u}_k^* = u_k^{CE} + \Delta u_k,$$

where the perturbation term Δu_k is the difference between $\bar{u}_k^*$ and u_k^{CE} . Since

$$u_k^{CE} = -L_k \hat{x}_k,$$

therefore,

$$\bar{u}_k^* = -L_k \hat{x}_k + \Delta u_k$$

which is affine in the state estimate.

(c) *two-step and more-step dual controls are non-affine.*

Since the dual cost in the cost-to-go is non-quadratic in the state estimate, from the dynamic programming solution to the problem, two-step dual control becomes non-affine in the state estimate, so are more-step dual controls.

(d) from (a), one-step dual control is better than CE control or non-dual controls, this concludes the proof. $\square$

Theorem 4.9 serves as the basis of a general guideline for designing not only simple, but the best possible suboptimal controller to the general nonlinear control systems, within the class of affine control policies.

In this chapter, first the cost-to-go in the stochastic dynamic programming problem at each stage has been successfully decomposed into a CE cost and dual cost, assuming that the observation loop is closed at the next stage. The dual cost appears to be a sum of dual costs of each future stage. It has been shown that the dual cost at the next immediate stage dominates the future uncertainties. The same approach for the two stage problem has been adopted in developing the dual control algorithm for the finite horizon dual control problem, based on the dual cost properties. The algorithm proposed has the advantage that all the computations can be done in analytical form, no numerical evaluation will be necessary for the problem under consideration. The algorithm is extremely simple to implement. At this moment, however, only the local dual cost control is compared with CE control, the controls

may fall out of the range of global optimality. As will be discussed in the next chapter, improvements can be achieved by the inclusion of other possible controls.

The convergence of the algorithm is also investigated. For the first time, to the author's knowledge, it is been shown that the dual control may not necessarily result in faster convergence of the *a posteriori* probabilities, this indicates that depending on the formulation of the problem, the dual control improves the state estimates, but does not necessarily improve the mode identification, compared with certainty equivalence control policies.

This problem alone can be a research subject of the representation and the interpretation of future information in dual control systems.

As the one-step-ahead dual control is of the 1-measurement closed-loop type, it has been shown that such a control policy is optimal policy in the class of affine policies.

Necessary extensions were given to the finite horizon multi-mode linear stochastic system with all parameters unknown. As the dual control problem is very difficult by its nature, attempts in an analytical error study regarding the approximation, were not successful. Simulations are therefore very helpful in illustrating the errors which can result from the use of approximations. Examples of the dual control algorithm will be provided in the next chapter.

CHAPTER FIVE

Simulations

In this chapter, we illustrate through the use of examples, by the proposed dual controller to verify the properties of the dual cost and the dual controller, and to compare the dual controller with the certainty equivalence controller. It is found that the dual control algorithm can achieve nearly optimal control performance. Furthermore, we use the simulations to provide more insight into the role of the dual cost. The errors introduced by the approximation used in the algorithm are also studied. Simulations show that the algorithm behaves extremely well in the sense that it approaches the optimal control. The situations when the dual control shows significant improvement in performance over the certainty equivalence control for a non-neutral control system are analyzed and the dependence on the state weighting and the control energy penalty in the performance functional are studied.

Improvements in the proposed dual control algorithm can be made by expanding the control set. The simulation shows that improvements to further lower the cost when the local minimum control of the dual cost does not yield an optimal solution to the problem.

5.1 A Simple Example

A simple scalar two-stage linear system is considered. The simplicity of

the problem allows us to derive the optimal solution numerically and also to further understand the complications of dual control.

Example 5.1. The system is described by (5.1) and (5.2):

$$x_{k+1} = 0.8 x_k + u_k + v_k \quad (5.1)$$

$$y_k = C(r)x_k + w_k \quad k = 0, 1 \quad (5.2)$$

i.e., only the parameter in the observation matrix C is unknown,

$$C(r) = \begin{cases} 1, & \text{for } r = r_1; \\ 0.1, & \text{for } r = r_2. \end{cases}$$

The dynamic noise and observation noise are described by

$$v_t \sim N(0, 9)$$

$$w_t \sim N(0, 1)$$

respectively. The initial state has different distributions for each mode:

$$x_{1,0} \sim N(20, 4)$$

$$x_{2,0} \sim N(22, 4).$$

The performance functional to be minimized is

$$J = 0.0002(x_0^2 + x_1^2 + u_0^2 + u_1^2) + 0.9998x_2^2, \quad (5.3)$$

the terminal cost is heavily weighted in the overall cost.

The *a priori* probabilities are $p_{1,0} = 0.5$, $p_{2,0} = 0.5$.

To find the true optimal control and the optimal cost, the problem is numerically solved. The cost functional vs. control is depicted in Fig. 5.1.

The optimal control is

$$u_0^* = -17.629$$

and the optimal cost is

$$J(u_0^*) = 12.7643,$$

It is noted that the CE control yields almost the worst performance in this control range, but the dual control can improve the dual cost actively, resulting in a lot lower cost.

Fig. 5.2 and Fig. 5.3 show the decomposed costs: CE cost and dual cost respectively.

The CE cost (Fig. 5.2) is the well known quadratic function of the control, the optimal control and the cost using the CE control are obtained trivially, the CE control and the CE cost are

$$u_0^{CE} = -10.436,$$

$$J(u_0^{CE}) = 13.7801$$

The dual cost (Fig. 5.3) is a bimodal nonlinear function of the control. As Theorem 3.4 has shown, $u_0 = \pm\infty$ are the global minimum dual cost controls.

FIG. 5.1

Figure 5.1. Cost-to-go as a function of control.

FIG. 5.2

Figure 5.2. CE cost as a function of control.

Figure 5.3. Dual cost as a function of control.

Large control magnitudes separates the modes of the system and increase the signal-to-noise ratio, hence promote learning. This reduces the uncertainty of the system to a minimum, the dual cost becomes zero, the system essentially becomes a deterministic system.

As less control energy is used, the magnitude of the input signal to the system decreases and the reduction of the future uncertainty is diminished and the dual cost becomes large. Even though the discrimination of the observation process corresponding to the different modes is reduced, the uncertainty of the state estimates decreases.

The dual control obtained by eq(3.44) and the dual cost are

$$u_0^{dual} = -17.754$$

$$J(u_0^{dual}) = 12.7649$$

respectively.

u_0^{dual} is a local minimum dual cost control, the minimum total cost is in the neighborhood of u_0^{CE} or u_0^{dual} .

We can see that the suboptimal control u_0^{dual} is very close to the optimal control, and the dual control suboptimal cost is very close to the optimal cost.

In the subsequent simulation, 800 Monte Carlo runs were performed for the two-stage control problem, using dual control and CE control, for the systems with only the observation parameter unknown, the DUL control (Deshpande,

et al. , 1973) is equivalent to the CE control (see chapter 3). The results are listed in Table 5.1:

Algorithm	Sample Mean Cost	Sample Std Deviation
Optimal Control	12.9217	16.7839
Dual Control	12.9446	16.7987
DUL Control	13.9060	18.4041

Table 5.1

Table 5.1 is consistent with the results given in Fig. 5.1.

5.2 Conditions for Dual Control

It was found by experience that when there is heavy terminal state penalty and the control period is relatively short the actively learning control, or dual control is expected to have a significant improvement over the passive learning, or certainty equivalence control(see, e.g., Wenk and Bar-Shalom 1980). The question is when it is worthwhile to use the dual control vs. the CE control? No result has been reported on this aspect of the problem in past research work.

In following examples, we do not use the optimal cost with all known parameters comparisons with the new algorithm. Instead, we use the lower bound derived in section 4.3 to calculate the optimal cost, although it is still not achievable in general, it is a better reference than the known parameter

optimal cost for the purpose of comparison. For the two-stage control problem as shown in Example 5.1, the lower bound is exactly the optimal cost.

Example 5.2. The system parameters are the same as in example 5.1, but this is a 5-stage control problem, the performance index is given by

$$J = 0.0002 \sum_{k=0}^4 (x_k^2 + u_k^2) + 0.9998x_5^2$$

The problem is then almost identical to the problem in Example 5.1, except the control horizon is 3 stages longer. 200 simulation runs for the 5-stage control problem were performed. Table 5.2 gives the comparison of the dual control performance and the DUL control performance. The dual control execution time using the approximation method is not much longer than that of the CE control. *

Algorithm	Mean Cost	Std Deviation	CPU Time
Optimal Control	14.4405	—	—
Dual Control	15.7434	20.6279	38 sec
DUL Control	15.8040	20.7069	24 sec

Table 5.2

Compare with the example of the 2-stage problem, the result shows that less improvement is achieved from using the dual control for this 5-stage control problem.

* Intel 80286 12MHz CPU time

The weighting for each stage in the performance functional for the system in Example 5.1 are altered, Q_k from 0.0002 to 0.5 for all $k < N$ and $Q_N = 1 - Q_k$ i.e., early stages have great impacts on the state cost penalty. We see from Fig. 5.4, Fig. 5.5 and Fig. 5.6, as the terminal state deviation from the origin becomes less important, the dual property almost disappears!

Again, examine Fig. 5.1 and Fig. 5.2, we found that (Fig. 5.7, total cost and CE cost vs. control) the possible improvement from using dual control (or using the optimal control) is at most

$$\frac{\max(\text{Dual Cost})}{\min(\text{CE Cost})} \approx \frac{1.05}{12.74} \approx 8.24\% \quad (5.4)$$

We define

$$\text{MDCII} = \frac{\text{Dual Cost}}{\text{CE Cost}} \Big|_{u=u^{CE}} = \frac{J^{dual}(u^{CE})}{J^{CE}(u^{CE})} \times 100\% \quad (5.5)$$

as the Maximum Dual Control Improvement Index (MDCII), then the possible improvement a dual control can provide is no more than MDCII.

MDCII is related to the “dual control condition”. Practically, MDCII serves as an upper bound of the additional cost from using CE control in a non-neutral control system. See Theorem 4.4, eq(4.27b) can be used in the evaluation of MDCII.

When comparing different control algorithms, one should keep in mind what level of MDCII the system has at each stage. This determines whether

FIG. 5.4

Figure 5.4. Cost-to-go as a function of control, state weighting varies. The values are in logarithm. The curves of $Q_k = 0.5$ and $Q_k = 0.05$ are reduced by 0.8 and 0.2 respectively to fit into picture.

FIG. 5.5

Figure 5.5. CE cost as a function of control, state weighting varies. The values are in logarithm. The curves of $Q_k = 0.5$ and $Q_k = 0.05$ are reduced by 0.8 and 0.2 respectively to fit into picture.

FIG. 5.6

Figure 5.6. Dual cost as a function of control, state weighting varies.

FIG. 5.7

Figure 5.7. Total cost and CE cost vs. control.

the CE control is “sufficiently” optimal, that is, whether there is much improvement that can be derived from more expensive controllers.

Examine Fig. 5.4 and Fig. 5.5, we found that the CE control and the optimal control for the problems with less terminal state penalties, for example, the system with $Q_k = 0.5$ and $Q_N = 0.5$, are very close to each other since the cost functional is almost quadratic in control. This implies that the dual control could not provide more *active* learning than a passive learning CE control can. If we take a closer look at the system, in terms of MDCII, we found that the system is indeed not “dual”, i.e., a CE control would suffice.

Statement 5.1. *Dual Control is meaningful at stage k , i.e. MDCII defined as in (5.5) is sufficiently large, only if G_{k+1} is relatively large compared with $\frac{\partial J_k^{CE}}{\partial u_k}$. More specifically,*

$$S_{k+2} \gg S_{k+1} \quad (5.6)$$

at stage k , where S_{k+1} is defined in eq(4.20).

Proof. The derivative of CE cost J_k^{CE} with respect to control u_k is

$$\frac{\partial J_k^{CE}}{\partial u_k} = 2ABS_{k+1} \left(\sum_{i=1}^s p_{i,k} \hat{x}_{i,k} \right) + 2(R_k + S_{k+1}B^2)u_k \quad (5.7)$$

$$\sim (R_k + S_{k+1}B^2) \quad (5.8)$$

and considering eq(4.23), the derivative of dual cost J_k^{dual} with respect to control u_k is

$$\frac{\partial J_k^{dual}}{\partial u_k} \sim G_{k+1}p_{j,k} \quad (5.9)$$

Roughly speaking, relatively large S_{k+1} would imply that $\frac{\partial J_k^{CE}}{\partial u_k}$ is greater than $\frac{\partial J_k^{dual}}{\partial u_k}$, implying the increase in the CE cost would nullify the decrease in the dual cost, i.e., the active learning feature of dual control, is negligible.

From eq(4.21),

$$G_{k+1} = \frac{1}{2}(R_{k+1} + S_{k+2}B^2)^{-1}A^2B^2S_{k+2}^2 \quad (5.10)$$

since for example, assuming that A and B are fixed, $G_{k+1} \rightarrow 0$ only if $S_{k+2} \rightarrow 0$, given R_{k+1} is finite.

Therefore, if the decrease in the dual cost is greater than the increase in the CE cost, it is necessary that

$$S_{k+2} \gg S_{k+1}.$$

□

Next it will be shown how the weighting factors of the cost at each stages affects the dual property of a control system.

Rewrite the Riccati Equations (4.20) and (4.25b),

$$S_k = (A - BL_k)^2 S_{k+1} + Q_k + L_k^2 R_k \quad (5.11)$$

$$L_k = (R_k + S_{k+1}B^2)^{-1} S_{k+1}AB \quad (5.12)$$

Assume

$$R_{k+2} \ll S_{k+3}B^2 \quad \text{for all } k \quad (5.13)$$

we have

$$L_{k+2} \approx \frac{A}{B} \quad (5.14)$$

$$A - BL_{k+2} \approx 0 \quad (5.15)$$

First, (5.14) implies the CE control is approximately equal to the dual control (see eq(3.42)), since the penalty on the control energy is very small, the CE control strategy would spend more control energy, thus *passive learning* dual effect.

Assume (5.13) holds, and also

$$R_{k+2} \rightarrow 0 \quad (5.16)$$

$$Q_{k+2} \rightarrow 0, \quad (5.17)$$

then from (5.11) and (5.15), we find that $S_{k+2} \rightarrow 0$. This tells us when the weightings at the stage after the next stage ($k+2$), Q_{k+2} and R_{k+2} are relatively small, at this stage (k), the system does not have significant dual property by Statement 5.1.

In order to have significant dual property, S_{k+1} should be small, by the same argument as above, we find that R_{k+1} and Q_{k+1} must both be small, that is, we need

$$R_{k+1} << S_{k+2}B^2 \quad \text{for all } k \quad (5.18)$$

and

$$R_{k+1} \rightarrow 0 \quad (5.19)$$

$$Q_{k+1} \rightarrow 0 \quad (5.20)$$

Not all of the equations (5.15), (5.16) and (5.17) can hold simultaneously.

Hence, if

$$R_{k+1} = R_{k+2} \quad (5.21)$$

$$Q_{k+1} = Q_{k+2} \quad \text{for } 0 \leq k+1 \leq N-1, \quad (5.22)$$

then the system does not have the dual property (MDCII is not sufficiently large) at stage k . The CE control would do approximately as well as the optimal control can do.

For large S_{k+2} at stage k , the system has significant dual property, if R_{k+2} is large, the dual control would foresee that using future controls is costly (CE control is likely to be applied at stage $k+2$), thus more control effort is applied early in order to have better probing and learning; if Q_{k+2} is large, the dual control sees that there is an immediate need to drive the state to the origin quickly, requiring more accurate state estimates, an active control for probing.

Next we present an example where the situations just mentioned arise, the dual control can significantly reduce the performance cost.

Example 5.3. For a 10-stage control problem, (1) if the state at the second stage is heavily weighted, $Q_2 = 0.9998$, otherwise $Q_k = 0.0002$ and

$Q_N = 0.9998$, all other parameters are as in Example 5.1. Then, the control at the initial stage has significant dual property. The results of 200 Monte Carlo runs are listed in Table 5.3. We found that the system needs the dual control.

Algorithm	Mean Cost	Std Deviation	CPU Time
Optimal Control	27.2710	—	—
Dual Control	30.3578	30.1637	41 sec
DUL Control	32.7296	32.5672	23 sec

Table 5.3

(2) consider the same system as in (1), but all $Q_k = 0.0002$ and $Q_N = 0.9998$. The results of 200 runs are given in Table 5.4. We found that the CE control suffices.

Algorithm	Mean Cost	Std Deviation	CPU Time
Optimal Control	14.6335	—	—
Dual Control	16.2613	25.1600	39 sec
DUL Control	16.2613	25.1600	23 sec

Table 5.4

The optimal cost compared in the tables in the example is the lower bound for the cost derived in section 4.3, which is less than the optimal cost for this example, and is not attainable by any admissible control.

Therefore, when a general dual control system is considered, one should be aware of what the possible improvements are when using a dual controller.

They can be either significant or negligible, depending on the control systems parameters and the performance functional. The criterion in Statement 5.1 can be used for judging whether it is necessary, or desirable to use a dual control strategy instead of just a certainty equivalence control strategy. For the unknown observation coefficient problem, the inequality (5.6) can be pre-computed off-line, but for a general system with all the parameters unknown, this must be done on-line because of the dependency of $\tilde{S}_k$ on the *a posteriori* probabilities at each stage. It must be re-evaluated when new observations become available. , refer to (4.42). Equation (5.6) can be used conceptually for general systems.

5.3 Near Minimum Dual Cost Control

Another situation worth mentioning is shown in Fig. 5.8. This is a two-stage dual control problem, the same as the one in section 5.1, but with unknown parameter $C(r_i) \in \{1, -0.1\}$ (compare with Fig. 5.1, where $C(r_i) \in \{1, 0.1\}$). The minimum cost is at $u_0 \approx -2.0$, which implies the optimal control can be in neither the neighborhood of u_0^{CE} nor that of u_0^{dual} . This is because the local minimum of dual cost is still too large.

This indicates that turning off the control can have a lower cost since at $u_0 \approx -2.0$, the information about the future unknowns increases, as the magnitude of control increases, more future information can be lost. The control determines the system may not be appropriately excited, and it exercises more caution.

FIG. 5.8(a)

Figure 5.8(a). Cost-to-go as a function of control, local minimum of the dual cost is not small.

FIG. 5.8(b)

Figure 5.8(b). Dual cost as a function of control, local minimum of the dual cost is not small.

Recall Theorem 4.3, eq(4.23), eq(4.24), if we substitute the local minimum control (eq(3.45))

$$u'_k = -\frac{A}{B}\hat{x}_{i,k}$$

into

$$J_k^{dual} \approx G_{k+1}P_{j,k}g_{j,k+1}(\hat{x}_{i,k+1} - \hat{x}_{j,k+1})^2 \Big|_{y_{k+1}=\hat{y}_{i,k+1}}$$

we obtain

$$J_k^{dual}(u'_k) \approx G_{k+1}P_{j,k}g_{j,k+1}[A(\hat{x}_{i,k} - \hat{x}_{j,k})(1 - C_iK_{j,k+1})]^2 \quad (5.23)$$

The dual cost level depends on the value of

$$|1 - C_iK_{j,k+1}| \quad (5.24)$$

Since

$$C_iK_{j,k+1} = C_iP'_{j,k+1}C_{j,k+1}(P'_{j,k+1}C_{j,k+1}^2 + CovW)^{-1} \quad (5.25)$$

and we know $P'_{j,k+1}$ and $(P'_{j,k+1}C_{j,k+1}^2 + CovW)^{-1}$ are positive, then the sign of $C_iK_{j,k+1}$ is determined by the sign of the product C_iC_j . That is, if C_i and C_j have the same sign, and as $CovW \rightarrow 0$.

$$C_iK_{j,k+1} \rightarrow \left| \frac{C_i}{C_j} \right| \quad (5.26)$$

$C_iK_{j,k+1}$ is positive, and

$$|1 - C_iK_{j,k+1}| \rightarrow \left| \frac{1 - C_i}{C_j} \right| = \left| \frac{C_j - C_i}{C_j} \right| \quad (5.27)$$

tends to decrease, then $J_k^{dual}(u_k^{dual})$ decreases.

But if the signs of C_i and C_j are not the same,

$$C_i K_{j,k+1} \rightarrow -\left|\frac{C_i}{C_j}\right|$$

is negative, and $|1 - C_i K_{j,k+1}|$ tends to increase, then $J_k^{dual}(u_k^{dual})$ increases.

One should be careful when using the dual control method. The optimal control may not be in the neighborhood of u_k^{dual} or that of u_k^{CE} in such a situation.

When the dual cost is like the one shown in Fig. 5.8(b), and as in Fig. 5.9, where C_i or C_j varies, we may have a large dual cost at the CE control. Then, the other alternatives (e.g. Fig. 5.8(a)) for the minimum of the total cost will be the two controls located near the tails of the dual cost curve. Their values are near the minimum of the dual cost ($= 0$), as $u_k \rightarrow \pm\infty$. We call these controls the “near minimum dual cost controls”. The question is how to determine where the near minimum dual cost controls are from information like

$$J_k^{dual}(u_k) \leq \varepsilon, \quad k = 0, 1, \dots, N-2$$

where ε is a positive parameter.

Observation 5.2. *A near minimum dual cost controls is symmetric to a local minimum dual cost control about its corresponding local maximum dual cost control. As illustrated in Fig. 5.10(a), the near minimum dual cost control*

FIG. 5.9(a)

Figure 5.9(a). Cost-to-go as a function of control, local minimum dual cost varies as C_1 varies, $C_2 = -0.1$

FIG. 5.9(b)

Figure 5.9(b). Cost-to-go as a function of control, local minimum dual cost varies as C_1 varies, $C_2 = 0.1$

u^{nmin} is an image of the local minimum dual cost control u^{dual} about the corresponding maximum dual cost control u^{max} .

Let us first find the maximum dual cost controls. By Theorem 4.3, eq(4.23), under the conditions that $C_i = \min(C_i, C_j) = \gamma$ ($C_j \neq 0$, $j \neq i$), $CovW = q|\gamma|$, q is a finite nonzero real number, when $\gamma \rightarrow 0$, at time k , $M_{i,k+1} \rightarrow 0$, eq(4.23) is approximated by

$$\begin{aligned} J_k^{dual} &\approx \tilde{J}_k^{dual} \\ &= \sqrt{2\pi M_{i,k+1}} G_{i,k+1} p_{j,k} g_{j,k+1} (\hat{x}_{i,k+1} - \hat{x}_{j,k+1})^2 \Big|_{y_{k+1}=\hat{y}_{i,k+1}} \end{aligned} \quad (5.28)$$

(if $p_{i,k} = 0$, we have otherwise $J_k^{dual} = 0$)

Take the partial derivative of $\tilde{J}_k^{dual}$ with respect to u_k ,

$$\begin{aligned} \frac{\partial}{\partial u_k} \tilde{J}_k^{dual} &= \sqrt{2\pi M_{i,k+1}} B G_{i,k+1} p_{j,k} g_{j,k+1} \\ &\quad \cdot \frac{1}{M_{j,k+1}} (C_j - C_i) (\hat{x}_{i,k+1} - \hat{x}_{j,k+1}) \\ &\quad \cdot [(\hat{x}_{i,k+1} - \hat{x}_{j,k+1})(\hat{y}_{i,k+1} - \hat{y}_{j,k+1}) \\ &\quad + 2K_{j,k+1} M_{j,k+1}] \Big|_{y_{k+1}=\hat{y}_{i,k+1}} \end{aligned} \quad (5.29)$$

Note that $(\hat{x}_{i,k+1} - \hat{x}_{j,k+1}) \Big|_{y_{k+1}=\hat{y}_{i,k+1}} = 0$ gives the central local minimum dual cost control as in Theorem 4.3. Let

$$\begin{aligned} &[(\hat{x}_{i,k+1} - \hat{x}_{j,k+1})(\hat{y}_{i,k+1} - \hat{y}_{j,k+1}) \\ &\quad + 2K_{j,k+1} M_{j,k+1}] \Big|_{y_{k+1}=\hat{y}_{i,k+1}} = 0 \end{aligned} \quad (5.30)$$

FIG. 5.10(a)

Figure 5.10(a). Illustration of the near minimum dual cost control. The near minimum dual cost control u^{min} is an image of the local minimum dual cost control u^{dual} about the corresponding maximum dual cost control u^{max} .

The left hand side of eq(5.30) is a quadratic function of u_k , we can solve this equation and obtain the maximum dual cost controls.

Substitute eq(4.24) into eq(5.30). After certain algebraic manipulations, eq(5.30) becomes

$$a_k u_k^2 + b_k u_k + c_k = 0 \quad (5.31)$$

where

$$\begin{aligned} a_k &= -K_{j,k+1}(C_i - C_j)^2 B^2 \\ b_k &= AB(C_i - C_j)[(\hat{x}_{i,k} - \hat{x}_{j,k}) - 2K_{j,k+1}(C_i \hat{x}_{i,k} - C_j \hat{x}_{j,k})] \\ c_k &= A^2(C_i \hat{x}_{i,k} - C_j \hat{x}_{j,k})[(\hat{x}_{i,k} - \hat{x}_{j,k}) - K_{j,k+1}(C_i \hat{x}_{i,k} - C_j \hat{x}_{j,k})] \\ &\quad + 2K_{j,k+1}M_{j,k+1}. \end{aligned} \quad (5.32)$$

Solving eq(5.31), we have the near maximum dual cost controls

$$\begin{aligned} u_k^{max} &= \frac{-A[K_{j,k+1}(C_i \hat{x}_{i,k} - C_j \hat{x}_{j,k}) - (\hat{x}_{i,k} - \hat{x}_{j,k})]}{BK_{j,k+1}(C_i - C_j)} \\ &\quad + \frac{-A(\hat{x}_{i,k} - \hat{x}_{j,k}) \mp \sqrt{A^2(\hat{x}_{i,k} - \hat{x}_{j,k})^2 + 8K_{j,k+1}^2 M_{j,k+1}}}{2BK_{j,k+1}(C_i - C_j)}. \end{aligned} \quad (5.33)$$

By eq(4.26), u_k^{max} can be written as

$$\begin{aligned} u_k^{max} &= u_k^{dual} + \\ &\quad \frac{-A(\hat{x}_{i,k} - \hat{x}_{j,k}) \mp \sqrt{A^2(\hat{x}_{i,k} - \hat{x}_{j,k})^2 + 8K_{j,k+1}^2 M_{j,k+1}}}{2BK_{j,k+1}(C_i - C_j)}. \end{aligned} \quad (5.34)$$

Let

$$\Delta u_{k,1} = \frac{-A(\hat{x}_{i,k} - \hat{x}_{j,k}) - \sqrt{A^2(\hat{x}_{i,k} - \hat{x}_{j,k})^2 + 8K_{j,k+1}^2 M_{j,k+1}}}{2BK_{j,k+1}(C_i - C_j)} \quad (5.35)$$

and

$$\Delta u_{k,2} = \frac{-A(\hat{x}_{i,k} - \hat{x}_{j,k}) + \sqrt{A^2(\hat{x}_{i,k} - \hat{x}_{j,k})^2 + 8K_{j,k+1}^2 M_{j,k+1}}}{2BK_{j,k+1}(C_i - C_j)} \quad (5.36)$$

then

$$\begin{aligned} u_{k,1}^{max} &= u_k^{dual} + \Delta u_{k,1} \\ u_{k,2}^{max} &= u_k^{dual} + \Delta u_{k,2}. \end{aligned} \quad (5.37)$$

By Observation 5.2, the near minimum dual cost controls are

$$\begin{aligned} u_k^{nmin} &= u_k^{dual} + \\ &\quad \frac{-A(\hat{x}_{i,k} - \hat{x}_{j,k}) \mp \sqrt{A^2(\hat{x}_{i,k} - \hat{x}_{j,k})^2 + 8K_{j,k+1}^2 M_{j,k+1}}}{BK_{j,k+1}(C_i - C_j)}. \end{aligned} \quad (5.38)$$

or

$$u_{k,1}^{nmin} = u_k^{dual} + 2\Delta u_{k,1}.$$

$$u_{k,2}^{nmin} = u_k^{dual} + 2\Delta u_{k,2}.$$

For the example as shown by Fig. 5.8, by eq(5.38) we can find the near minimum dual cost controls,

$$u_0^{nmin} = -25.3948, \quad \text{and} \quad -6.8967$$

and we see $u_0^{nmin} = -6.8967$ is the best choice of the control.

These near minimum dual cost controls can be used in addition to the central local minimum dual cost control u_k^{dual} in the algorithm proposed in section 4.3, this will result in even better performance. Table 5.5 illustrates this for a 5-stage dual control problem, where $C_2 = -0.1$, $Q_k = 0.0002$, $Q_2 = Q_N = 0.9998$ and all other parameters are as in Example 5.1.

Algorithm	Mean Cost	Std Deviation	CPU Time
Near Min Dual	25.5221	24.5394	24.5 sec
Dual Control	27.1992	25.2075	19.5 sec
DUL Control	28.7297	27.8259	12.0 sec

Table 5.5

Next we need to show analytically that Observation 5.2 is true, i.e., each near minimum dual cost control is symmetric to the central local minimum dual cost control about each local maximum dual cost control.

Proof of Observation 5.2. Let

$$u' = 2u_{k,\ell}^{max} - u'' \quad \ell = 1, 2 \quad (5.39)$$

that is u' and u'' are symmetric about $u_{k,\ell}^{max}$. We want to show

$$\tilde{J}_k^{dual}(u') \approx \tilde{J}_k^{dual}(u'') \quad (5.40)$$

subject to

$$\begin{aligned} |u' - u_{k,\ell}^{max}| &\leq \Delta u_{k,\ell} & \ell = 1, 2 \\ |u'' - u_{k,\ell}^{max}| &\leq \Delta u_{k,\ell} & \ell = 1, 2 \end{aligned} \quad (5.41)$$

where $\tilde{J}_k^{dual}$ is given by eq(5.28).

Substitute eq(5.39) in to the left hand side of eq(5.40), it should be possible to obtain the right hand side of eq(5.40), a detailed proof is left for future work.

5.4 Error from Dual Cost Approximation

When an approximation is made to the dual cost evaluation, we are concerned about the error incurred from the approximation. If the error is reasonably small, the method used will result in a good approximation, hence near optimal control policies. Of course, our objective is to achieve the optimal performance provided that the algorithm is simple and efficient. i.e., ideally we want

$$J(\{u_k^{dual}\}_{k=0}^{N-1}) - J(\{u_k^*\}_{k=0}^{N-1}) \rightarrow 0 \quad (5.42)$$

Because the performance index is a continuous function of control, if we have

$$|u_k^{dual} - u_k^*| \rightarrow 0 \quad \text{for all } k \quad (5.43)$$

then eq(5.42) can be obtained.

Let J_k^u denote an upper bound of the dual cost, J_k^l a lower bound of the dual cost. If the lower bound and the upper bound satisfy

$$J_k^l \leq J_k^{dual} \leq J_k^u$$

and

$$J_k^l \leq \tilde{J}_k^{dual} \leq J_k^u$$

where $\tilde{J}$ is given in eq(4.23) and the conditions in Theorem 4.3 are met, we have

$$|J_k^u - J_k^l| = \theta(\gamma),$$

where $\theta(\gamma) \rightarrow 0$, as $\gamma \rightarrow 0$, then the approximation of the dual cost is a reasonable, and useful one.

Let the lower bound be

$$J_k^l = G_{k+1} p_{i,k} p_{j,k} \int_{-\infty}^{+\infty} \frac{g_{i,k+1} g_{j,k+1}}{p_{i,k} g_{i,k+1} + p_{j,k}} (\hat{x}_{i,k+1} - \hat{x}_{j,k+1})^2 \quad (5.44)$$

and the upper bound be

$$J_k^u = G_{k+1} p_{j,k} \int_{-\infty}^{+\infty} g_{j,k+1} (\hat{x}_{i,k+1} - \hat{x}_{j,k+1})^2, \quad (5.45)$$

since we have the inequalities:

$$\begin{aligned} \frac{g_{i,k+1} g_{j,k+1}}{p_{i,k} g_{i,k+1} + p_{j,k}} &\leq \frac{g_{i,k+1} g_{j,k+1}}{p_{i,k} g_{i,k+1} + p_{j,k} g_{j,k+1}} \leq \frac{g_{i,k+1} g_{j,k+1}}{p_{i,k} g_{i,k+1} + 0} \\ &= \frac{g_{j,k+1}}{p_{i,k}} \end{aligned}$$

we have

$$J_k^l \leq J_k^{dual} \leq J_k^u.$$

The difference between the lower and upper bounds is

$$\begin{aligned} J_k^u - J_k^l &= G_{k+1} p_{i,k} p_{j,k} \int_{-\infty}^{+\infty} \left[\frac{g_{j,k+1}}{p_{i,k}} - \frac{g_{i,k+1} g_{j,k+1}}{p_{i,k} g_{i,k+1} + p_{j,k}} \right] (\hat{x}_{i,k+1} - \hat{x}_{j,k+1})^2 \\ &= G_{k+1} p_{j,k}^2 \int_{-\infty}^{+\infty} \frac{g_{j,k+1}}{p_{i,k} g_{i,k+1} + p_{j,k}} (\hat{x}_{i,k+1} - \hat{x}_{j,k+1})^2 \quad (5.46) \end{aligned}$$

This integral can not be solved analytically.

Let the integrand in eq(5.46) be denoted by

$$h(y_{k+1}) = \frac{g_{j,k+1}}{p_{i,k}g_{i,k+1} + p_{j,k}}(\hat{x}_{i,k+1} - \hat{x}_{j,k+1})^2 \quad (5.47)$$

Then,

$$\lim_{M_{i,k+1} \rightarrow 0} h(y_{k+1}) = \begin{cases} 0, & \text{for } y_{k+1} = \hat{y}_{i,k+1}; \\ g_{j,k+1}(\hat{x}_{i,k+1} - \hat{x}_{j,k+1})^2, & \text{otherwise.} \end{cases} \quad (5.48)$$

Note that $g_{i,k+1} \rightarrow \delta(y_{k+1} - \hat{y}_{i,k+1})$, as $M_{i,k+1} \rightarrow 0$.

From eq(5.48), eq(5.46) is a quadratic function of u_k ,

$$\begin{aligned} \lim_{M_{i,k+1} \rightarrow 0} (J_k^u - J_k^l) &= G_{k+1}p_{j,k}^2(K_{i,k+1} - K_{j,k+1})^2 M_{j,k+1} \\ &\quad + [m_{i,k} - m_{j,k} - K_{i,k+1}(\hat{y}_{i,k+1} - \hat{y}_{j,k+1})]^2 \end{aligned} \quad (5.49)$$

This can not be used for error analysis, because J_k^u is a quadratic function of u_k , and is not a tight upper bound.

An analytical error study was not possible, so a numerical analysis for the error of the approximation in the dual control problem was established using simulations.

An example is given in Fig. 5.10(b), the data is same as in Example 5.1. When $M_{1,k+1} = 14.56$, $M_{2,k+1} = 4.04$, the dual cost is compared with the approximation.

Fig. 5.11(a) and (b) show the errors of the dual cost at the CE control and at the dual control, respectively, when $C_i C_j > 0$. Fig. 5.11(c) and (d)

FIG. 5.10(b)
($M1 = 14.56$, $M2 = 4.04$)

Figure 5.10(b). Comparison of the dual cost with the approximation.

show the errors for $C_i C_j < 0$. We see the error curves converge to zero as the approximation converges. The error curve for CE control when $C_2 = -0.1$ (Fig. 5.11(c)) suggests that the convergence curve is not necessarily monotone.

The error of the dual cost approximation is not as important as the error of the dual control from the optimal control. We want to establish the convergence of the dual control to the optimal control, as stated in eqs(5.42) and (5.43).

Fig. 5.12 gives simulation results for the convergence of the dual control algorithm using the system in Example 5.1, the central local minimum of the dual cost yields the combined minimum total cost. It shows that as the approximation of the dual control converges, the dual control converges to the optimal dual cost control.

Fig. 5.12(a) shows the dual control converges to the optimal dual cost control as the covariance goes to zero. Fig. 5.12(b) presents the convergence of the dual cost with the dual control to the optimal dual cost. Finally, the convergence of the total cost with the dual control to the optimal total cost is given in Fig. 5.12(c). The two curves are almost identical.

The simulation evidence indicates that the dual control algorithm is indeed nearly optimal. The algorithm exhibits reasonable convergence properties and provides a practical solution to the dual control problem, with acceptable system performance.

FIG. 5.11 (a)

Figure 5.11(a). Errors of dual cost at the CE control, $C_i C_j > 0$.

FIG. 5.11 (b)

Figure 5.11(b). Errors of dual cost at the dual control, $C_i C_j > 0$.

FIG. 5.11 (c)

Figure 5.11(c). Errors of dual cost at the CE control, $C_i C_j < 0$.

FIG. 5.11 (d)

Figure 5.11(d). Errors of dual cost at the dual control, $C_i C_j < 0$.

FIG. 5.12(a)

Figure 5.12(a). Convergence of the dual control to the optimal dual cost control.

FIG. 5.12(b)

Figure 5.12(b). Convergence of the dual cost with the dual control to the optimal dual cost.

FIG. 5.12(c)

Figure 5.12(c). Convergence of the total cost with the dual control to the optimal total cost.

CHAPTER SIX

Conclusion

The closed loop dual control problem is well known for its complexity and the infeasibility for real-time applications. Numerical solutions are not practical, even with today's high speed digital computers. This work proposes a practical dual control algorithm. First, the cost-to-go in the performance functional is decomposed recursively in to a certainty equivalence cost and a dual cost, at each stage. The dual cost is shown to be a sum of costs each associated with the dual covariance of state from the current stage to the end of the control horizon. A technique of approximation of the decomposed dual cost was presented for determining the optimal control laws for a class of dual control systems. The method considers the dual cost as dominating the increases or decreases in the cost-to-go. The dual cost is appropriately expressed in terms of filter variables in algebraic form. Then the resulting optimal control problem is solved in the usual way. The dual control problem for linear stochastic systems with unknown parameters is approximately solved in closed form. The suboptimal algebraic solution is very close to the optimal solution. It has been shown that this type of dual controller is the best in the class of affine controllers. The algorithm is the simplest dual control algorithm which has appeared in the literature and it can be applied to a broad range of control systems. The method has been demonstrated through a number of examples.

Illustrative examples demonstrate that not all dual control systems (non-neutral control systems, Bar-Shalom and Tse, 1974) have sufficient dual property to circumvent active probing, i.e., such control systems only require a certainty equivalence control solution, the CE control performance is nearly as good as that of the optimal control.

This work can be extended to the Jump Quadratic Gaussian (JQG) control problem, adopting the formulations of Griffith and Loparo(1985). Therefore the algorithm proposed has a broad spectrum of applications, including those stochastic systems with abrupt changing structures. For the multiple input multiple output (MIMO), higher order systems, the dual control problem becomes mathematically more complicated. The concepts developed in this work extend naturally to this situation.

It is clear that the stochastic optimal dual control problem, in general, is not solvable analytically. The procedure of finding dual control laws in terms of future observations is a difficult problem. It is also a difficult task to do the error analysis once a suboptimal dual control law is found. It is hoped, however, that having the approach outlined here will provide a useful tool for theoretical analysis and a contribution in the search for reasonably performing yet practically implementable dual controls.

References

- Akella, R., Kumar, P.R., (1985) "Optimal control of production rate in a failure prone manufacturing systems", *IEEE Trans. Automatic Control*, Vol. AC-31, pp. 116.
- Alster, J., Belanger, P.R., (1974) "A Technique for Dual Adaptive Control", *Automatica*, Vol. 10, pp. 627-634.
- Aoki, M., (1967) *Optimization of Stochastic Systems, Topics in Discrete Time Systems*, Academic Press, New York, Vol. 32.
- Aster, R., et al, (1976) "Optimal open-loop feedback control for linear systems with unknown parameters", *Information Sciences*, Vol. 11, pp. 256-277.
- Åström, K., Wittenmark, B., (1971) "Problems of identification and control", *J. Math. Anal. Appl.*, Vol. 34, pp. 90.
- Athans, M., et al, (1977) "The uncertainty threshold principle: Some fundamental limitations on optimal decision making under dynamic uncertainty", *IEEE Trans. Automatic Control*, Vol. AC-22.
- Bar-Shalom, Y., (1969) "On the optimal control of discrete time linear systems with random parameters", *IEEE Trans. Automatic Control*, Vol. AC-14, pp. 3-8.
- Bar-Shalom, Y., Tse, E., (1974) "Dual Effect, Certainty Equivalence, and Separation In Stochastic Control", *IEEE Trans. Automatic Control*, Vol. AC-19, pp. 494-500.
- Bar-Shalom, Y., (1981) "Stochastic Dynamic Programming: Caution and Probing", *IEEE Trans. Automatic Control*, Vol. AC-26, pp. 1184-1194.
- Bertsekas, D.P., (1976) *Dynamic Programming and Stochastic Control*, Academic Press.
- Birdwell, J.D., Castanon, D.A. & Athans, M., (1986) "On Reliable control system designs", *IEEE Trans. Systems Man & Cybernetics*, Vol. SMC-16.
- Blair, W.P., Sworder, D.D., (1975) "Feedback Control of a Class of Linear discrete Systems with Jump Parameters and Quadratic Cost Criteria", *Int. J. Control*, Vol. 21, pp. 833-841.
- Caines, P.E., Chen, H.F., (1985) "Optimal Adaptive LQG Control for Systems with Finite State Process Parameters", *IEEE Trans. Automatic Control*, Vol. AC-30, pp. 185-189.

- Casiello, F. A., Loparo, K., (1985) "A Dual Controller for Linear Systems with Random Jump Parameters", *Proc. 24th IEEE CDC*, Fort Lauderdale, pp. 911-915.
- Casiello, F. A., Loparo, K., (1989) "Optimal Control of Unknown Parameter Systems", *IEEE Trans. Automatic Control*, Vol. AC-34, No. 10., Oct.
- Casiello, F. A., Loparo, K., (1989) "Optimal Policies for Passive Learning Controllers", *Automatica*, Vol.25, No. 5, Sept.
- Chan, S., Zarrop, M., (1985) "A suboptimal dual controller for stochastic systems with unknown parameters", *Int. J. Control*, Vol. 41, pp. 507-524.
- Chang, C., Athans, M., (1978) "State estimation for discrete systems with switching parameters", *IEEE Trans. Aerospace and Electronic Systems*, Vol. AES-14, pp. 418-424.
- Chizeck, H. J., (1986) "Discrete-time Markovian-jump Linear Quadratic Optimal Control", *Int. J. Control*, Vol. 43, pp. 213-231.
- Cramer, H., (1946) *Mathematical methods of statistics*.
- Curry, R.E., (1969) "A new algorithm for suboptimal stochastic control", *IEEE Trans. Automatic Control*, Vol. AC-14, pp. 533-536.
- Dersin, P., (1981) "Some Properties of the Dual Adaptive Stochastic Control Algorithm", *IEEE Trans. Automatic Control*, Vol. AC-26, pp. 1001-1008.
- Deshpande, J.G., Upadhyay, T.N. & Lainiotis, D.G., (1973) "Adaptive control of linear stochastic systems", *Automatica*, Vol. 9, pp. 107-115.
- Dreyfus, S., (1964) "Some types of optimal control of stochastic systems", *SIAM J. Control*, Vol. 2, pp. 120-134.
- Eckert, S. J., (1986) *Dual Control Aspects in Systems with Uncertain Structure*, Ph.D. Dissertation, Systems Engr, CWRU.
- Fel'dbaum, A., (1960) "Dual control theory, I-IV", *Automation and remote control*, Vol. 21, pp. 874-1033.
- Fel'dbaum, A. A., (1965) *Optimal Control Systems*, Academic Press, Vol. 22.
- Florentine, J.J., (1962) "Optimal probing adaptive control of a simple Bayesian system", *J. Electron. Control*, Vol. 11, pp. 165.

- Gorman, D., Zaborszky, J., (1968) "Stochastic optimal control of continuous time systems with unknown gain", *IEEE Trans. Automatic Control*, Vol. AC-13, pp. 630.
- Grammaticos, A.J., Horowitz, B.M., (1970) "The optimal adaptive control law for a linear plant with unknown input gains", *Int. J. control*, Vol. 12, pp. 337.
- Griffiths, B. E., Loparo, K., (1985) "Optimal Control of Jump-linear Gaussian Systems", *Int. J. Control*, Vol. 42, pp. 791-819.
- Gunckel, T.F., Franklin, G.F., (1963) "A General Solution for linear Sampled-data control systems", *Trans. ASME*, Vol. 85D, pp. 197.
- Hijab, O., (1983) "The adaptive LQG problem - part I", *IEEE Trans. Automatic Control*, Vol. AC-28, pp. 171-178.
- Hughs, D.J., Jacobs, O.L.R., (1974) "Turn-off, escape and probing in nonlinear stochastic control", Preprint *IFAC Symp. on stochastic control*, Budapest.
- Jacobs, O.L.R., (1964) *IEEE Trans. Automatic Control*, Vol. AC-9, pp. 574.
- Jacobs, O.L.R., Langdon, S.M., (1970) "An optimal extremum control system", *Automatica*, Vol. 6, pp. 297.
- Jacobs, O.L.R., Patchell, J.W., (1972) "Caution and Probing in Stochastic Control", *Int. J. Control*, Vol. 16, pp. 189-199.
- Joseph, P.D., Tou, J.T., (1961) "On Linear control Theory", *Trans. AIEE, Part III*, Vol. 80, pp. 193-196.
- Kuntsevich, V., (1980) "Optimal control of discrete dynamic systems with unknown nonstationary parameters", *Automation and remote control*, Vol. 41, pp. 200-207.
- Kushner, H., (1965) "On the stochastic maximum principle: fixed time of control", *J. Math. Anal. Appl.*, Vol. 11, pp. 78-92.
- Malhame, R., Chong, C.Y., (1985) "Electric load model synthesis by diffusion approximation in a high-order hybrid-state stochastic model", *IEEE Trans. Automatic Control*, Vol. AC-30, pp. 854.
- Mariton, M., Bertrand, P., (1985) "Output Feedback for a class of linear Systems with Stochastic Jump Parameters", *IEEE Trans. Automatic Control*, Vol. AC-30, pp. 898-900.

- Mariton, M., (1986) "Optimal Output Feedback for Jump Linear Systems with State- and Control-dependent Noises", *Control-Theory and Advanced Technology*, Vol. 2, pp. 633-639.
- Milito, R., Padilla, C. and Padilla, R., (1982) "An Innovations Approach to Dual control", *IEEE Trans. Automatic Control*, Vol. AC-27, pp. 132-137.
- Padilla, C.S., (1979) "Conceptual Framework of Safer Control", *Proc. 18th IEEE CDC*, Fort Lauderdale.
- Patchell, J. W., Jacobs, O.L.R., (1971) "Separability, Neutrality and Certainty Equivalence", *Int. J. Control*, Vol. 13, pp. 337-342.
- Peirce, B.D., Sworder, D.D., (1971) "Bayes and Minimax Controllers for a Linear Systems with Stochastic Jump Parameters", *IEEE Trans. Automatic Control*, Vol. AC-16, pp. 300-307.
- Rishel, R., (1975) "Control of Systems with Jump Markov Disturbances", *IEEE Trans. Automatic Control*, pp. 241-244.
- Rishel, R., (1981) "A Comment on a Dual Control Problem", *IEEE Trans. Automatic Control*, Vol. AC-26, pp. 606-609.
- Saridis, G., Dao, T.K., (1972) "A Learning Approach to the Parameter Adaptive Self-Organizing Control Problem". *Automatica*, Vol. 8, pp. 589-597.
- Schwartz, S.C., Steiglitz, K., (1971) "The identification and control of unknown linear discrete systems", *Int. J. Control*, Vol. 14, pp. 43.
- Siljak, D.D., (1980) "Reliable Control Using Multiple control Systems", *Int. J. Control*, Vol. 31, pp. 303-329.
- Spang, H.A., (1965) "Optimum control of an unknown linear plant using Bayesian estimation of error", *IEEE Trans. Automatic Control*, Vol. AC-10, pp. 80-83.
- Stratonovich, R.L., (1962) *Automation and remote control*, Vol. 23, pp. 847.
- Striebel, C., (1965) *J. Math. Anal. Appl.*, Vol. 12, pp. 576.
- Sworder, D.D., (1969) "Feedback Control of a Class of Linear Systems with Jump Parameters", *IEEE Trans. Automatic Control*, Vol. AC-14, pp. 9-14.
- Sworder, D.D., Robinson, V., (1973) "Feedback Regulators for Jump Parameter Systems with State and Control Dependent Transition Rates", *IEEE Trans. Automatic Control*, Vol. AC-18, pp. 355-360.

- Sworder, D.D., Choi, L.L., (1976) "Stationary cost densities for optimally controlled stochastic systems", *IEEE Trans. Automatic Control*, Vol. AC-21, pp. 492.
- Sworder, D.D., (1976) *Proc. Inst. Elect. Electron. Engrs*, Vol. 64, pp. 1214.
- Sworder, D.D., Roger, R.O., (1983) "An LQ-solution to a Control Problem Associated with a Solar Thermal Central Receiver", *IEEE Trans. Automatic Control*, Vol. AC-28, pp. 971-978.
- Sworder, D.D., Chou, D.S., (1985) "A Survey of some Design Methods for Random Parameter Systems", *Proc 24th IEEE Confr. Decision and Control*, Fort Lauderdale.
- Sworder, D.D., Chou, D.S., (1986) "Passive Adaptation in Control system Design", *Control and Dynamic Systems*, Academic Press, Leondes ed., pp. 315-356.
- Tse, E., Dressler, R. and Bar-Shalom, Y., (1972) "Application of adaptive tuning of filters to exoatmospheric target tracking", *Proc. 3rd Symp. Nonlinear Estimation Theory*, San Diego, CA.
- Tse, E., Bar-Shalom, Y. and Meier, L. (1973a) "Wide-Sense Adaptive Dual Control for Nonlinear Stochastic Systems", *IEEE Trans. Automatic Control*, Vol. AC-18, pp. 98-108.
- Tse, E., Bar-Shalom, Y., (1973b) "An Active Adaptive Control for Linear systems with Random Parameters via the Dual control Approach", *IEEE Trans. Automatic Control*, Vol. AC-18, pp. 109-117.
- Wenk, C., (1980) "A Multiple Model Adaptive Dual control Algorithm for Stochastic systems with Unknown Parameters", *IEEE Trans. Automatic Control*, Vol. AC-25, pp. 703-710.
- Wieslander, J., Wittenmark, B., (1971) "An approach to adaptive control using real time identification", *Automatica*, Vol. 7, pp. 211.
- Wilk, S.S., (1962) *Mathematical Statistics*.
- Willsky, A. S., (1976) "A Survey of Design Methods for Failure Detection in Dynamic Systems", *Automatica*, Vol. 12, pp. 601-611.
- Willsky, A. S., (1986) "Detection of Abrupt Changes in Dynamic Systems".
- Witsenhausen, H.S., (1971) "Separation of Estimation and Control for discrete-time Systems", *Proc. IEEE*, Vol. 59, pp. 1557-1566.
-

- Wittenmark, B., (1975) "An active suboptimal dual controller for systems with stochastic parameters", *Automatic Control Theory and Applications*, Canada.
- Wonham, W.M., (1968) "On the Separation theorem of Stochastic Control", *SIAM J. Control*, Vol. 6, pp. 312-326.
- Wonham, W.M., (1970) "Random Differential Equations in Control theory", Academic Press, Bharucha-Reid, A.T., *Probability Methods in Applied Mathematics*, Vol. 2, pp. 131-212.
-