INFORMATION TO USERS

This manuscript has been reproduced from the microfilm master. UMI films the text directly from the original or copy submitted. Thus, some thesis and dissertation copies are in typewriter face, while others may be from any type of computer printer.

The quality of this reproduction is dependent upon the quality of the copy submitted. Broken or indistinct print, colored or poor quality illustrations and photographs, print bleedthrough, substandard margins, and improper alignment can adversely affect reproduction.

In the unlikely event that the author did not send UMI a complete manuscript and there are missing pages, these will be noted. Also, if unauthorized copyright material had to be removed, a note will indicate the deletion.

Oversize materials (e.g., maps, drawings, charts) are reproduced by sectioning the original, beginning at the upper left-hand corner and continuing from left to right in equal sections with small overlaps. Each original is also photographed in one exposure and is included in reduced form at the back of the book.

Photographs included in the original manuscript have been reproduced xerographically in this copy. Higher quality 6" x 9" black and white photographic prints are available for any photographs or illustrations appearing in this copy for an additional charge. Contact UMI directly to order.

U·M·I

University Microfilms International
A Bell & Howell Information Company
300 North Zeeb Road, Ann Arbor, MI 48106-1346 USA
313.761-4700 800.521-0600

Order Number 9236364

**Optimal design of gradient waveforms for magnetic resonance
imaging**

Simonetti, Orlando Paul, Ph.D.

Case Western Reserve University, 1992

Copyright ©1993 by Simonetti, Orlando Paul. All rights reserved.

U·M·I

**300 N. Zeeb Rd.
Ann Arbor, MI 48106**

OPTIMAL DESIGN OF GRADIENT WAVEFORMS
FOR
MAGNETIC RESONANCE IMAGING

by
ORLANDO PAUL SIMONETTI

Submitted in partial fulfillment of the requirements
for the Degree of Doctor of Philosophy

Thesis Advisor: Jeffrey L. Duerk, Ph.D.

Department of Biomedical Engineering
CASE WESTERN RESERVE UNIVERSITY

May 1992

CASE WESTERN RESERVE UNIVERSITY

GRADUATE STUDIES

We hereby approve the thesis of

ORLANDO PAUL SIMONETTI

candidate for the Ph.D.

degree.*

Signed:

Jeffrey L. Quirk, Ph.D.
(Chairman)
Mark D. Pryor, Ph.D.
David L. Wilson
Gerald M. Sanders
Vina Cheng

Date Jan 27, 1992

*We also certify that written approval has
been obtained for any proprietary material
contained therein.

I grant to Case Western Reserve University the right to use this work, irrespective of any copyright, for the University's own purposes without cost to the University or to its students, agents and employees. I further agree that the University may reproduce and provide single copies of the work, in any format other than in or from microforms, to the public for the cost of reproduction.

Charles P. Smith

OPTIMAL DESIGN OF GRADIENT WAVEFORMS
FOR
MAGNETIC RESONANCE IMAGING

Abstract

by

ORLANDO PAUL SIMONETTI

Fourier transform magnetic resonance imaging utilizes temporally varying linear magnetic field gradients to encode spatial information. These gradient waveforms influence image properties such as resolution, signal-to-noise ratio, and sensitivity to motion. This thesis presents a general formalism for the design of gradient waveforms using non-linear constrained optimization. Methods of formulating and solving the optimal waveform design problem are described, and example waveforms and images are displayed for a variety of design objectives and constraint sets. Artificial constraints on waveform shape imposed by multi-lobe waveform designs are eliminated by defining the waveform as a set of discrete amplitudes. These amplitudes are determined subject to the constraints defined by imaging conditions and the specific gradient hardware system of interest. Most waveform design

objectives are expressed as linear or quadratic functions of the discrete parameter set, and most constraints as linear functions. Linear and quadratic programming techniques are thus utilized to solve the optimization problem and generate physically realizable waveforms which optimally achieve specific imaging and motion artifact reduction goals.

Another important aspect of gradient waveform design explored in this thesis is the relationship between gradient waveform time moments and motion sensitivity. Theoretical analysis, computer simulations, and experiments with a computer controlled linear motion phantom reveal several key points. In general, waveform time moments define sensitivity to the time derivatives of position of moving material only at a single point in time: the time about which the moments are computed. A Taylor's Series description of instantaneous position is expanded about this same point in time to compute the phase acquired due to specific derivatives of position. A moment is representative of the phase sensitivity to a particular derivative of position throughout the waveform only when sensitivity to all lower order derivatives is zero. The choice of the moment center or point of expansion adds a degree of freedom which may be used advantageously in the design of motion compensating and motion phase encoding

gradient waveforms. These concepts are demonstrated by human imaging examples, and may prove useful in MR angiography and echo planar imaging.

Dedication

To Lynn

Acknowledgements

First, I would like to thank my thesis advisor, Dr. Jeffrey Duerk. We began this project as great friends, and remained so throughout it all. I think our work over the past three years shows that we had a way of bringing out the best in each other. I will always be indebted to Jeff for opening the door to MRI research and being an outstanding teacher and advisor.

Next, I would like to acknowledge everyone at MetroHealth Medical Center who took part in this project. Special thanks goes to Dr. Errol Bellon for his generous financial support. To Dr. Gregory Hurst goes the "Sixth Man Award." While not officially on my five member research committee, Greg was always there to discuss problems, edit manuscripts, and boost my ego during the rough times. Thanks go to my friend Randall Holt, for sharing a tiny office and a lot of laughs while we both worked wildly to finish our theses. Thanks also to Dr. William Sattin, for his helpful insights in the practical aspects of imaging. I would also like to acknowledge Mike Pettit, Ed Kubiez, and all of the technologists at the MetroHealth MRI Facility for their assistance and friendship.

Special thanks go to Dr. Vira Chankong for letting me tap into his vast knowledge of optimization theory. Thanks

also to my other research committee members: Dr. Gerald Saidel, Dr. Mark Rzeszutarski, and Dr. David Wilson for their interest and assistance in this project. Dr. Richard E. Wendt III also deserves special acknowledgement for his contributions to Chapter 5, and for sharing his knowledge of motion effects in MRI. I also wish to thank Dr. Mohammed Modarreszadeh for his friendship and assistance, and Dr. Eugene Bruce, for teaching me the signal analysis skills that proved so useful in understanding MRI.

My love and deepest appreciation of all goes to my wife, Lynn. It doesn't seem fair to drag a spouse through the rigors of graduate school, but Lynn was always there for me. I am the one to receive the diploma, but Lynn has had to work just as hard, and sacrifice just as much, for me to reach this goal. I hope that somehow I can make up for all the time spent away from her and our daughter Hannah.

Finally, I want to thank all of my friends and family for their support, and for always believing that I would finish school one day.

Table of Contents

Abstract	ii
Dedication	v
Acknowledgements	vi
Table of Contents	viii
List of Figures	xii
List of Tables	xvii
List of Symbols	xix
1. Function and Design of Gradient Waveforms in Magnetic Resonance Imaging	1
1.1 Spatial Encoding with Magnetic Field Gradients	1
1.1.1 The Slice Select Gradient	5
1.1.2 The Frequency and Phase Encoding Gradients	8
1.1.3 Resolution and Bandwidth Relationships	14
1.1.4 Gradients and Signal Phase	16
1.2 Example Pulse Sequences	19
1.2.1 Gradient or Field Echo	19
1.2.2 Spin Echo	19
1.2.3 3D Gradient Echo	22
1.2.4 FLASH Imaging Sequence	24
1.3 Phase Sensitivity to Motion	26
1.4 Gradient Waveform Design	31
1.4.1 Standard Imaging Sequences	31
1.4.2 Practical Considerations	32
1.5 Gradient Waveforms with Controlled Motion Sensitivity	34
1.5.1 Introduction	34
1.5.2 Exploiting NMR Phase Sensitivity to Motion	36
1.5.3 Motion Compensated Gradient Waveform Design Techniques	39
1.6 Optimal Design Technique	45
1.6.1 Deficiencies of Standard Algebraic Design	45
1.6.2 Proposal of Optimal Waveform Design Technique	46

2. Gradient Waveform Optimization	48
2.1 Introduction	48
2.1.1 Background	48
2.1.2 Applications of Optimization Theory in MRI	49
2.1.3 Overview of the Proposed Design Technique	50
2.2 Theory	51
2.2.1 Waveform Parameterization	52
2.2.2 Objectives	55
2.2.2.1 Minimize RMS Current	55
2.2.2.2 Minimize Waveform Slewing	57
2.2.2.3 Minimize deviation from desired moment values	59
2.2.2.4 Maximize Resolution	61
2.2.2.5 Maximize or Minimize Diffusion Sensitivity	63
2.2.2.6 Echo Time Minimization	64
2.2.3 Constraints	65
2.2.3.1 Amplitude Limits	66
2.2.3.2 RMS Current or Duty Cycle Limits	67
2.2.3.3 Slew or Rise Time Limits	67
2.2.3.4 Fixed Moment Values	67
2.2.3.5 Fixed Resolution and Bandwidth	69
2.2.3.6 Diffusion Sensitivity	69
2.2.3.7 System Frequency Response	70
2.2.4 Methods of Solution	71
2.2.4.1 Linear and Quadratic Programming	71
2.2.4.2 Multi-Objective Functions	75
2.3 Discussion	78
3. Example Waveforms and Images	79
3.1 Waveform Generation	79
3.1.1 Introduction	79
3.1.2 Implementation	80
3.2 Example Waveforms	83
3.2.1 RMS Current Minimized Waveforms	92
3.2.2 Total Slew Minimized Waveforms	96
3.2.3 Minimum Motion Sensitivity Waveforms	101
3.2.4 Maximum Resolution Waveforms	104
3.2.6 Diffusion Sensitivity Maximized Waveforms	109
3.3 Waveform Comparisons	115
3.4 Imaging Examples	116
3.4.1 FE18 RMS Current Minimization	117

3.4.2	Optimal Moment Compensation	120
3.4.3	Echo Time Minimization	124
3.4.4	Minimum FOV Catheter Coil Images	129
3.5	Discussion	133
4.	Gradient System Simulations	135
4.1	Introduction	135
4.2	Waveform Generation with Improved Gradient System.	135
4.3	Unconstrained Waveform Generation	145
5.	The Theoretical Significance of the Point of Expansion in the Interpretation of Gradient Moments and Motion Sensitivity	154
5.1	Introduction	154
5.2	Theory	157
5.3	Computer Simulations	169
5.3.1	Phase Trajectories	169
5.3.2	Bloch Equation Solver	178
5.4	Discussion	187
6.	The Significance of the Expansion Point in Gradient Waveform Design	189
6.1	Introduction	189
6.2	Compensation of Misregistration Artifacts	189
6.2.1	Theory	192
6.2.2	Linear Motion Phantom Imaging Experiments	198
6.2.3	Human Imaging Experiments	209
6.2.3.1	Two Dimensional Spin Echo Imaging	209
6.2.3.2	Three-Dimensional Gradient Echo Imaging	211
6.2.4	Conclusions	218
6.3	Motion encoding	218
6.3.1	Theory	218
6.3.2	Phantom Experiments	220
6.4	Motion Compensation in Echo Planar Imaging	227
6.4.1	Introduction and Theory	227
6.4.2	EPI Simulations	232
6.5	Significance of the Expansion Point in Optimal Waveform Design	237
6.6	Conclusions	238
7.	Conclusions and Future Directions	239
7.1	Conclusions	239
7.1.1	Optimization of Gradient Waveforms	239
7.1.2	Significance of the Expansion Point in Waveform Design	241

7.2 Future directions	243
7.2.1 Optimization of Gradient Waveforms .	243
7.2.2 Significance of the Expansion Point .	245
Appendix A. Linear Motion Phantom	247
A.1 Introduction	247
A.2 Technical Specifications	248
A.3 Phantom Cine Imaging	255
A.4 Recommended Design Modifications	260
References	262

List of Figures

Figure 1.1	X and Y gradient fields.	3
Figure 1.2	Prototype gradient echo spin-warp imaging pulse sequence diagram. . . .	4
Figure 1.3	Basic principles of selective excitation.	7
Figure 1.4	Illustration of data sample point distribution in k-space.	13
Figure 1.5	Basic spin echo imaging sequence. . .	21
Figure 1.6	Three-Dimensional gradient echo imaging sequence.	23
Figure 1.7	FLASH imaging sequence.	25
Figure 1.8	Bipolar velocity encoding gradient waveform.	35
Figure 1.9	Velocity compensated slice select and frequency encoding waveforms.	42
Figure 2.1	Generic velocity compensated field echo waveforms.	54
Figure 3.1	Velocity compensated field echo sequence (18 millisecond echo time) optimized for minimum RMS current. . .	94
Figure 3.2	Spin echo sequence (20 millisecond echo time) optimized for minimum RMS current.	95
Figure 3.3	Velocity compensated field echo sequence (18 millisecond echo time) optimized for minimum sum of squared first-order differences (slew). . . .	98
Figure 3.4	Spin echo sequence (20 millisecond echo time) optimized for minimum sum of squared first order differences (slew).	99
Figure 3.5	Slew minimized spin echo sequence (80 millisecond echo time).	100
Figure 3.6	Velocity compensated field echo sequence (18 millisecond echo time) optimized for minimum sensitivity to acceleration.	102
Figure 3.7	Spin echo sequence (20 millisecond echo time) optimized for minimum sensitivity to motion.	103
Figure 3.8	Velocity compensated field echo sequence (18 millisecond echo time) optimized for minimum FOV and slice thickness (maximum resolution). . . .	105

Figure 3.9	Spin echo sequence (20 millisecond echo time) optimized for minimum FOV and slice thickness.	106
Figure 3.10	Velocity compensated field echo sequence (15.5 millisecond echo time) optimized from minimum total slew with simultaneous iterative minimization of echo time.	108
Figure 3.11	Diffusion sensitivity (b factor) maximized spin echo sequence (120 millisecond echo time).	111
Figure 3.12	Diffusion sensitivity (b factor) maximized, velocity compensated spin echo sequence (120 millisecond echo time).	112
Figure 3.13	Images of a resolution phantom for various objectives.	118
Figure 3.14	Axial images of the cervical spine at different levels of motion compensation.	122
Figure 3.15	Velocity sensitivity of minimum slew (uncompensated) and minimum first moment waveforms	127
Figure 3.16	Axial images of the cervical spine at different echo times.	128
Figure 3.17	TE60 sequence generated for high resolution imaging with intravascular catheter receiver coil.	131
Figure 3.18	Axial images of the femoral artery of a dog.	132
Figure 4.1	Acceleration compensated FE18 field echo sequence optimized for minimum total slew under 2 G/cm amplitude and 2 G/cm/msec slew constraints.	139
Figure 4.2	Velocity compensated FE18 field echo sequence optimized for maximum resolution under 2 G/cm amplitude and 2 G/cm/msec slew constraints.	141
Figure 4.3	Velocity compensated FE11.5 field echo sequence iteratively optimized for minimum echo time. Simultaneous minimization of RMS current under 2 G/cm amplitude and 2 G/cm/msec slew constraints.	143
Figure 4.4	FE 18 field echo sequence designed for 2 cm FOV without constraints on amplitude and slew. Slice select gradient velocity compensated.	148

Figure 4.5	Acceleration compensated field echo sequence designed for 10 cm FOV without constraints on amplitude and slew.	150
Figure 4.6	Velocity compensated field echo sequence designed for 5 msec echo time without constraints on amplitude and slew.	152
Figure 5.1	FEER gradient waveform used in simulations.	172
Figure 5.2	Time varying position of simulated isochromat.	173
Figure 5.3	Phase trajectories computed about start of waveform.	175
Figure 5.4	Phase trajectories computed about center of waveform.	176
Figure 5.5	Phase trajectories computed about echo time.	177
Figure 5.6	Pulse sequence used in Bloch Equation simulation.	181
Figure 5.7	Initial distribution of spin groups along the x-axis.	182
Figure 5.8	Real and imaginary parts of one-dimensional reconstruction of the simulated signal from moving spin groups.	185
Figure 5.9	Real and imaginary parts of one-dimensional reconstruction of the simulated signal from moving spin groups.	186
Figure 6.1	Diagram illustrating mechanism of oblique flow misregistration.	190
Figure 6.2	Summary of the theoretical concepts of misregistration compensation.	196
Figure 6.3	Parabolic laminar flow velocity profile.	197
Figure 6.4	The computer controlled linear motion phantom system.	199
Figure 6.5	Time varying position and velocity profiles of the linear motion phantom.	201
Figure 6.6	TE80 Misregistration compensated sequence.	202
Figure 6.7	Images of phantom moving along the PE axis with time-varying position indicated in Figure 6.5.	204

Figure 6.8	Images of the phantom moving at 45° oblique to read and phase axes with profile shown in Figure 6.5.	205
Figure 6.9	Human image examples of misregistration compensation: TE80/TR2000 Spin Echo.	212
Figure 6.10	Three-Dimensional gradient echo sequence with misregistration compensation on two axes.	214
Figure 6.11a	Axial, coronal, and sagittal views of the 3D data sets generated using the sequence shown in Figure 6.10a. . . .	215
Figure 6.11b	Axial, coronal, and sagittal views of the 3D data sets generated using the sequence shown in Figure 6.10b. . . .	216
Figure 6.12	Maximum Intensity Projection (MIP) axial views of the head generated with a 10.5 msec echo time, gradient echo sequences.	217
Figure 6.13	Phantom position, velocity, and acceleration profiles used in velocity quantification experiment.	221
Figure 6.14	Velocity encoding waveforms.	223
Figure 6.15	Velocity encoded phantom images. . . .	224
Figure 6.16	Computed (dots) and predicted (line) phantom velocity with constant acceleration.	225
Figure 6.17	RF refocussed, blipped phase encoding, echo planar sequence.	230
Figure 6.18	Gradient echo EPI sequence with velocity compensated, blipped phase encoding waveform.	233
Figure 6.19	Phase trajectories due to velocity through different EPI phase encoding waveforms.	234
Figure 6.20	Blurring due to velocity through different EPI phase encoding waveforms.	235
Figure A.1	The linear motion phantom	249
Figure A.2	An example motion control program. . .	250
Figure A.3	Sketch of a Delrin bearing mount used to support the phantom drive shaft. .	253
Figure A.4	Sketch of the motion phantom.	255
Figure A.5	The dovetail slide track.	256
Figure A.6	Programmed and measured time-varying phantom position profile.	257

List of Tables

Table 3.1	Imaging conditions fixed by pulse sequence designer prior to optimization.	84
Table 3.2	Imaging conditions fixed by the pulse sequence designer prior to waveform optimization.	85
Table 3.3	Figures of merit for comparison of slice select waveforms of the field echo sequences	86
Table 3.4	Figures of merit for comparison of frequency encoding waveforms of the field echo sequences	87
Table 3.5	Figures of merit for comparison of phase encoding waveforms of the field echo sequences	88
Table 3.6	Figures of merit for comparison of slice select waveforms of the spin echo sequences	89
Table 3.7	Figures of merit for comparison of frequency encoding waveforms of the spin echo sequences	90
Table 3.8	Figures of merit for comparison of phase encoding waveforms of the spin echo sequences	91
Table 3.9	Figures of merit for comparison of spin echo slice select waveforms . . .	113
Table 3.10	Figures of merit for comparison of spin echo frequency encoding waveforms	114
Table 3.11	Slice thickness and FOV obtained for identical RMS current levels using sequences designed with three different objectives.	119
Table 3.12	Summary of differences in signal intensity and artifact level in axial C-Spine images shown in Figure 3.14. .	123
Table 3.13	Summary of differences in signal intensity and artifact level in axial C-Spine images shown in Figure 3.16. .	128
Table 4.1	Figures of merit for gradient echo sequence shown in Figure 4.1.	140
Table 4.2	Figures of merit for gradient echo sequence shown in Figure 4.2.	142
Table 4.3	Figures of merit for gradient echo sequence shown in Figure 4.3.	144

Table 4.4	Figures of merit for gradient echo sequence shown in Figure 4.4.	149
Table 4.5	Figures of merit for gradient echo sequence shown in Figure 4.5.	151
Table 4.6	Figures of merit for gradient echo sequence shown in Figure 4.6.	153
Table 5.1	First four time moments of rectangular gradient waveform with amplitude G and duration t_d	162
Table 5.2	First four moments of a balanced bipolar gradient waveform with amplitude $\pm G$ and lobe duration t_d . .	163
Table 5.3	First four moments of a three lobe FEER gradient waveform with amplitude $\pm G$ and lobe duration t_d	164
Table 5.4	Coefficients of motion at different points in time throughout the sequence used in the phase trajectory simulation.	174
Table 5.5	Derivatives of position of simulated isochromatic spin groups evaluated at times t_0 and t_2 as defined in Figure 5.1.	183
Table 5.6	Derivatives of position of simulated isochromatic spin groups evaluated at times t_0 and t_2 defined in Figure 5.1.	184
Table 6.1	Summary of results for phantom motion along the phase encoded axis.	206
Table 6.2	Summary of results for phantom motion at 45° angle oblique to frequency and phase encoding axes.	208
Table 6.3	Acquisition parameters for 2D spin echo sequences demonstrating misregistration artifact.	210
Table 6.4	Expected and measured velocity profiles shown in Figure 6.16.	226
Table A.1	Acquisition parameters for CINE imaging of linear motion phantom. . .	260

List of Symbols

ω :	Precessional or resonant frequency
γ :	Gyromagnetic ratio
B :	Magnetic field strength
G :	Three-dimensional gradient field vector
G_z or G_{ss}	Slice select gradient
G_x or G_{fc}	Frequency encoding gradient
G_y or G_{pe}	Phase encoding gradient
r :	Three-dimensional spatial coordinate vector
rf:	Radio-frequency
Δf :	rf bandwidth
f_1 :	rf center frequency
d or ΔZ :	Slice thickness
FWHM:	Full width half maximum
ρ :	Spin density
$s(t)$:	NMR signal
P :	Spatial Fourier transform of ρ
k :	Spatial frequency or wavenumber
FOV:	Field of view
BW:	Bandwidth
ϕ :	Phase angle
TE:	Echo time
TR:	Repetition time
T1:	Spin-lattice relaxation constant

T_2 :	Spin-spin relaxation constant
S/N :	Signal-to-Noise ratio
α :	rf flip angle
x :	Position
$x^{(i)}$:	i th time derivative of x
v :	Velocity
a :	Acceleration
j :	Jerk
t' :	Moment center of expansion point
M_i :	i th time moment
t_d :	Gradient waveform lobe duration
g_i :	Discrete gradient amplitude at time t_i
Δt :	Time interval between discrete gradient amplitudes
I_{RMS} :	RMS current
Φ :	Objective function
$\min$:	Minimize
$\mathcal{R}$:	Set of all real numbers
H :	Hessian matrix of quadratic coefficients
T_k :	k th target moment
b :	Gradient diffusion sensitivity
DG :	Gradient slew limit
F :	Matrix of linear filter coefficients
A :	Matrix of linear constraint coefficients

1. Function and Design of Gradient Waveforms in Magnetic Resonance Imaging

1.1 Spatial Encoding with Magnetic Field Gradients

In 1972, Paul Lauterbur described a new imaging technique he referred to as NMR Zeugmatography (1). It was based on the application of linear magnetic field gradients to encode spatial position into the frequency of a nuclear magnetic resonance (NMR) signal. Lauterbur's idea became the basis for magnetic resonance imaging (MRI) as we know it today (2,3,4).

The mapping of position to frequency by a magnetic field gradient follows directly from the Larmor Equation

$$\omega = \gamma B \quad [1.1]$$

which relates the resonant frequency (ω) of a nuclear spin to magnetic field (B) by the gyromagnetic ratio (γ) (5,6). From [1.1] we see that spatial variation in field B will cause spins at different locations to precess at different frequencies (7). In MRI, the required variation in B is created by a computer-controlled system of amplifiers and coils which generate spatially and temporally varying linear gradient fields. The three dimensional gradient field vector $\vec{G}(t)$ consists of orthogonal components $G_x(t)$, $G_y(t)$, and $G_z(t)$, where

$$\begin{aligned}
G_x(t) &= \frac{\partial B_z(t)}{\partial x} \\
G_y(t) &= \frac{\partial B_z(t)}{\partial y} \\
G_z(t) &= \frac{\partial B_z(t)}{\partial z} .
\end{aligned}
\tag{1.2}$$

The x and y gradient fields are illustrated in Figure 1.1. The instantaneous amplitude of $\vec{G}(t)$ is the slope of the spatial variation in B_z . A gradient vector with any arbitrary direction can be established by the linear combination of the three independent orthogonal components in Eq.[1.2] (8). The precessional frequency at a point in space ($\vec{r} = [x, y, z]$) now becomes

$$\omega(\vec{r}) = \gamma(B_z + \vec{G} \cdot \vec{r}) , \tag{1.3}$$

a function of the applied gradient $\vec{G}$.

While a number of techniques (1,3,4,9,10,11,12) have been proposed for producing images by spatial encoding with linear magnetic field gradients, most commercial imaging systems employ adaptations of the spin-warp (4,11) variant of Fourier imaging (3). The basic structure of a gradient echo spin-warp imaging sequence is shown in Figure 1.2, but many variations of this scheme are used in MRI.

X Gradient

Y Gradient

Figure 1.1 Static field lies along Z-axis. X and Y gradient fields indicated by arrows parallel to Z-field. Field strength along gradient axis corresponds to length of arrows. Gradient amplitudes (G_x and G_y) correspond to slope of spatial variation in field strength. Z gradient field (not shown) functions in the same manner along the Z-axis.

Figure 1.2 Prototype gradient echo spin-warp imaging pulse sequence diagram. Selective excitation takes place during interval **A**. Rephasing in the slice-select direction, dephasing in the frequency encoded direction, and spatial phase encoding all occur during time interval **B**. Data sampling performed during interval **C**. Gradient echo forms at time TE.

This spin warp sequence will be used as an example to describe the basic functions of gradient waveforms. Each of the three orthogonal gradients functions in a different manner to spatially encode the spins along the corresponding axis. For the sake of discussion, the slice select gradient will be referred to as G_{ss} or G_z , the frequency encode gradient as G_{fe} or G_x , and the phase encode gradient as G_{pe} or G_y . The relationship between G_z and G_{ss} , G_x and G_{fe} , and G_y and G_{pe} is provided for a historical reference to earlier MRI literature. Functional notation (G_{ss} , G_{fe} , G_{pe}) is preferred over geometric (G_z , G_x , G_y), since the actual spatial orientation of these axes is arbitrary.

1.1.1 The Slice Select Gradient

The slice select gradient is usually held constant during radio frequency (rf) excitation to select the plane or slice of tissue to be imaged. The gradient determines the frequency of precession of spins along the slice select axis. A bandlimited rf pulse will affect only those spins precessing at frequencies within its bandwidth. This is illustrated in Figure 1.3 which shows how the steepness of the linear variation in B_z along the slice select axis (the amplitude of G_{ss}), together with the rf pulse bandwidth (Δf) and center frequency (f_1), determine slice location and

thickness. From the Larmor Equation [1.1], we derive

$$d = \frac{2\pi\Delta f}{\gamma G_{ss}} \quad [1.4]$$

which defines the relationship between slice thickness (d), rf bandwidth (Δf) (typically measured as the full width at half the maximum amplitude (FWHM) of the Fourier transform of the rf pulse), and gradient amplitude (G_{ss}) along the slice select axis during the rf pulse. The desired result of applying the selective pulse is excitation of spins in the selected plane of tissue. Selective excitation takes place during time interval A indicated in Figure 1.2. The excited spins produce the time-varying NMR signal.

Figure 1.3 Illustration of the basic principles of selective excitation. RF pulse bandwidth (Δf) is directly proportional to slice thickness (Δz). RF center frequency determines slice location. Gradient amplitude, which corresponds to the slope of the spatial variation in field strength, is inversely proportional to slice thickness.

1.1.2 The Frequency and Phase Encoding Gradients

The function of the other two spatially orthogonal gradients (frequency encoding gradient G_{fe} and phase encoding gradient G_{pe}) is to encode the position of spins within the selected plane. Defining r as the two dimensional spatial coordinate vector within the excited plane, $\rho(r)$ as the spatial distribution of spins, and ignoring relaxation effects, the received NMR signal, $s(t)$, after demodulation by the Larmor frequency imposed by the main field ($\omega_0 = \gamma B_0$), can be expressed as

$$s(t) = \int \rho(\vec{r}) e^{-j\gamma 2\pi \int_0^t \vec{G}(t') \cdot \vec{r} dt'} d\vec{r} \quad . \quad [1.5]$$

Equation [1.5] is easily understood by recognizing that the NMR signal is the sum of signals from all excited spins; the frequency of precession of a spin is determined by the field strength at that location, which is in turn determined by the gradient; and the phase is due to the time history of the precessional frequency.

The two-dimensional spatial Fourier transform of the spin density is defined as

$$\mathcal{F}[\rho(\vec{r})] = P(\vec{k}) = \int \rho(\vec{r}) e^{-j2\pi \vec{k} \cdot \vec{r}} d\vec{r} \quad , \quad [1.6]$$

where $\vec{k}$ is the spatial frequency or wavenumber vector; $\vec{r}$

and $\vec{k}$ are Fourier conjugate variables; $\vec{r}$ is expressed in cm and $\vec{k}$ in cycles/cm. Noting that spatial frequency is measured as phase per distance, and recognizing from Eq.[1.3] that a gradient imparts a phase linearly proportional to distance along the direction of the gradient vector, we see that

$$\vec{k}(t) = \gamma \int_0^t \vec{G}(t') dt' \quad [1.7]$$

indicating that

$$s(t) = \mathcal{F}[\hat{\rho}(\vec{r})] = P(\vec{k}) \quad [1.8]$$

That is, the MR signal can be interpreted as the spatial Fourier transform of the projection of the spin density along the direction defined by the gradient vector. Equation [1.7] indicates that the time integral of the gradient waveform determines the trajectory through the spatial frequency domain or "k-space" followed by the NMR signal (13,14). This concept forms the basis for the design of frequency ($G_x(t)$) and phase encoding ($G_{pe}(t)$) gradient waveforms for spin warp imaging.

Separating Eq.[1.5] into orthogonal x and y components, corresponding to frequency and phase encoding directions, leads to the two-dimensional imaging equation:

$$s(t) = \iint \hat{\rho}(x, y) e^{-j2\pi \gamma \left(\int_0^t G_x(t_x) x dt_x + \int_0^t G_y(t_y) y dt_y \right)} dx dy \quad [1.9]$$

or

$$s(t) = s(k_x, k_y) = \iint \hat{\rho}(x, y) e^{-j2\pi \gamma (k_x x + k_y y)} dx dy \quad [1.10]$$

which is the two-dimensional Fourier transform of the spin density, where k_x and k_y are the Fourier conjugate variables of the in-plane spatial variables x and y , respectively.

The spin density function $\hat{\rho}$ in Eqs.[1.9] and [1.10] is assumed to incorporate the T1 and T2 relaxation processes and their effects on the NMR signal. While gradient waveform timing parameters TE (echo time) and TR (repetition time) are chosen based on these relaxation effects and image contrast considerations, this thesis is mainly concerned with the effects of gradient waveforms which enter into the imaging equation (Eq.[1.9]) in the exponential term, that is, as phase effects. Therefore, relaxation terms will be grouped together with spin density as $\rho(x, y)$ and, for the most part, not enter into this discussion.

From Eqs.[1.9 & 1.10], the x and y components of spatial wavenumber vector $\vec{k}$ can be defined as

$$k_x(t) = \gamma \int_0^t G_x(t_x) dt_x \quad [1.11]$$

and

$$k_y(t) = \gamma \int_0^t G_y(t_y) dt_y \quad . \quad [1.12]$$

These equations indicate that the spatial frequency domain or k-space can be sampled by controlling $G_x(t)$ and $G_y(t)$ to increment $s(t)$ through discrete values of $P(k_x, k_y)$. The inverse Fourier transform of $s(t)$ converts the k-space data back to object space, reconstructing an image of $\rho(x, y)$. The resolution and signal-to-noise (S/N) in the image are determined, in part, by the area of k-space covered and the number of sample points acquired.

In spin-warp imaging, the phase-encoding gradient is repeatedly pulsed with a different amplitude before each data sampling period, as indicated in interval B of Figure 1.2. From Eqs.[1.9 & 1.12], we see that the area of this phase encoding pulse determines the particular value of k_y , or line of k-space, to be sampled as shown in Figure 1.4.

The frequency encoding gradient is constant during data acquisition (sampling) as seen in interval C of Figure 1.2. The NMR signal is sampled at discrete time points which (from Eq.[1.11]) correspond to discrete spatial

frequencies of the distribution $\rho(x,y)$ in the frequency encode direction, along the k_y line in k-space defined by the phase encoding gradient. Thus, each data sample corresponds to a different point in k-space, as indicated in Figure 1.4, defined by the frequency and phase encoding gradients.

Spatial Frequency Domain or "k-Space"

Figure 1.4 Illustration of data sample point distribution in the spatial frequency domain or "k-space." Basic principles of the 2D Fourier transform, together with resolution, S/N, FOV requirements, and gradient system limitations, determine placement of data points in k-space.

1.1.3 Resolution and Bandwidth Relationships

The properties of the Fourier transform (15) dictate the manner in which k-space is sampled to generate an image with the desired field-of-view (FOV) and resolution in each dimension. Higher values of k correspond to higher spatial frequencies and higher resolution; the separation of k-space samples (Δk) is inversely proportional to the FOV. From Eq.[1.12], we can define the relationships in the frequency encoded direction between number of sample points (n), resolution (Δx), field of view (FOV_x), data bandwidth (BW) and gradient amplitude (G_x) as

$$\Delta x = \frac{1}{\gamma G_x n \Delta t_x} = \frac{1}{n \Delta k_x} \quad [1.13]$$

$$FOV_x = \frac{1}{\gamma G_x \Delta t_x} = \frac{1}{\Delta k_x} \quad [1.14]$$

$$BW = \gamma G_x FOV_x \quad . \quad [1.15]$$

In Equations [1.13-1.15] it is assumed that n evenly spaced samples are acquired during a linear gradient of constant amplitude G_x .

Similar equations exist for the phase encoding gradient:

$$\Delta y = \frac{1}{\left[\gamma m \Delta \int_0^T G_y(t) dt \right]} = \frac{1}{m \Delta k_y} \quad [1.16]$$

$$FOV_y = \frac{1}{\gamma \Delta \int_0^T G_y dt} = \frac{1}{\Delta k_y} \quad [1.17]$$

where k_y is sampled by incrementing the area of the gradient waveform m times by equal area steps. This is accomplished by repeating the sequence, shown in Figure 1.2, m times with only the area of the phase encode waveform changed. Each repetition is referred to as a phase encoding view or step. The frequency content of the signal, determined by the frequency encoding gradient, remains the same with each repetition; phase varies with the area of the phase encode gradient. The relationships defined in Eqs.[1.13-1.17] follow directly from the properties of the discrete Fourier transform.

Thus, the gradient waveforms during rf excitation, data sampling, and phase encoding are designed using Eq.[1.4] and Eqs.[1.13-1.17] to meet the requirements of FOV, BW, and resolution for the specific imaging application.

1.1.4 Gradients and Signal Phase

In addition to the above relationships between gradient waveforms and image formation, some additional effects related to the phase of the NMR signal must be considered in gradient waveform design.

From Eq.[1.8], it can be shown that the phase at any time T ($\phi(T)$) of an isochromat (a group of spins with the same precessional frequency and phase) in the presence of a field gradient ($G(t)$) is given by

$$\phi(r, T) = \gamma \int_0^T \vec{G}(t) \cdot \vec{r} dt \quad [1.18]$$

where $\vec{r}$ describes the position of the isochromat along the direction of the gradient.

Extending the imaging equation (Eq.[1.10]) to three dimensions:

$$s(t) = \iiint \hat{\rho}(x, y, z) e^{-j2\pi \gamma \left(\int_0^t G_x(t_x) x dt_x + \int_0^t G_y(t_y) y dt_y + \int_0^t G_z(t_z) z dt_z \right)} dx dy dz \quad [1.19]$$

we see that all three orthogonal gradient components, including the slice select gradient ($G_z(t)$), contribute to the signal phase. At the end of a selective pulse, a phase distribution in the transverse magnetization exists from one side of the slice to the other due to dispersion of precessional frequencies established by the slice select

gradient (16). For most commonly used rf pulses, this phase distribution is approximately linear across the slice (17), as indicated by Eq.[1.18] over the interval from the center to the end of the rf pulse.

In Fourier Transform MRI, the signal from a voxel is the vector sum of signals from all spins within the voxel. Thus, any distribution of phase within a voxel will attenuate the MR signal. A reversed field gradient, as shown in interval B of Figure 1.2, with approximately one-half the area of the positive section of the slice select gradient can be applied after the rf pulse to rephase the transverse magnetization. Extending the interval of integration in Eq.[1.18] from the center of the rf pulse to the end of the slice select gradient waveform, we see that the phase at any position along the slice select axis is brought back to zero by the refocussing gradient. This rephasing is not perfect, since the rf pulse is not instantaneous. New, more elaborate, rf pulse shaping techniques have been described which attempt to eliminate the need for a refocussing gradient (18,17).

The formation of a gradient echo along the frequency encoded axis is another function which must be taken into account in the design of gradient waveforms. A gradient echo forms a peak in the magnitude signal $|s(t)|$ when the transverse magnetization along the frequency encoded axis

is rephased after some period of dephasing. From Eq.[1.18], it can be shown that the echo will be centered at the time that the integral of $G_x(t)$ is zero; Equation [1.11] indicates that this coincides with the time that the data passes through the origin of the k_x axis (dc spatial frequency). Similar to the rephasing of magnetization along the slice axis, the frequency encoding waveform is designed such that the magnetization is first *dephased* by a negative gradient, and then *rephased* to form an echo. This initial dephasing can also be viewed as an initialization of the k-space trajectory, such that during sampling, k-space is traversed from negative to positive values of k_x as shown in Figure 1.4. The dephasing is accomplished by the addition of a single negative gradient lobe to $G_x(t)$ before the data sampling period, as seen in interval B of Figure 1.2.

The objective of the phase encoding gradient is to impose a phase distribution linearly proportional to position along y at the echo, rather than zero phase. This linear phase distribution is the direct result of encoding a single spatial frequency by the phase encoding pulse (interval B of Figure 1.2). The area of the pulse determines the line of k-space to be sampled.

1.2 Example Pulse Sequences

The basic functions of gradients in controlling the spatial and temporal distribution of the frequency and phase of spins are used to form a variety of imaging sequences. Some of these are shown in Figure 1.2 and Figures 1.5 - 1.7. These will be discussed in terms of gradient waveform design considerations, in light of the theme of this thesis.

1.2.1 Gradient or Field Echo

The original spin-warp sequence depicted in Figure 1.2 is also commonly referred to as a gradient echo, field echo, or gradient field echo sequence. The details of this sequence have already been discussed.

1.2.2 Spin Echo

The sequence shown in Figure 1.5 is a spin-echo sequence (19,20). A 180° rf pulse is used after the 90° pulse to reverse the phase of the NMR signal and form a signal echo. The slice select waveform ($G_z(t)$) differs from that of the gradient echo sequence (Figure 1.2) in that there are now two selective rf pulses, and hence, two sections of the slice select waveform with constant amplitudes fixed by slice thickness and rf bandwidth as

defined in Eq.[1.2]. The negative lobe of G_z functions, as it did in the gradient echo sequence, to rephase the signal across the slice after dephasing by the gradient during the last half of the 90° pulse. No rephasing lobe is required after the 180° pulse since the 180° rf pulse itself reverses the signal phase. The frequency encoding waveform (G_x) in Figure 1.5 differs from that in Figure 1.2; the dephasing lobe is positive rather than negative. This is due to the phase reversal effect of the 180° pulse. The phase encoding waveform is identical to that of the gradient echo sequence. The location of the 180° pulse and sign of the phase encode waveform determine the direction that k-space is traversed in the phase encode direction.

Figure 1.5 Basic spin echo imaging sequence. 180° rf pulse utilized to form a spin echo.

1.2.3 3D Gradient Echo

Examining the 3D imaging equation (Eq.[1.19]) reveals that k-space can be traversed in all three spatial dimensions by appropriate gradient waveform design. This is typically accomplished by frequency encoding one axis and phase encoding two axes, although all three axes can be phase encoded. Figure 1.6 shows a three-dimensional (3D) gradient echo imaging sequence (11). The slice select gradient functions not only to select a slab of tissue, but to phase encode positional information along the slice select axis. The resulting NMR signal corresponds to the 3D Fourier transform of the selected slab. This permits imaging thinner slices than can be readily obtained using 2D imaging techniques with standard gradient and rf systems.

Figure 1.6 Three-Dimensional gradient echo imaging sequence. Phase encoding of position performed along two axes. Selective excitation is utilized to excite a thick slab of tissue, which is divided into thin slices by secondary phase encoding waveform. Frequency and primary phase encoding waveforms function identical to 2D sequence shown in Figure 1.2.

1.2.4 FLASH Imaging Sequence

Figure 1.7 is an example of a Fast Low Angle SHot (FLASH) imaging sequence (21). This sequence is similar to the gradient echo sequence of Figure 1.2, but utilizes a rf pulse which only partially tips the magnetization vector into the transverse plane. This lessens the effects of saturation and allows scan time to be decreased by reducing repetition time, at the expense of some S/N and contrast (22). The additional incremented gradient lobe on the slice select axis after data acquisition serves to "spoil" any coherence in the transverse magnetization between repetitions (23). Other methods exist to spoil transverse magnetization as well (24).

The concept of gradient spoiling is important, not only in FLASH and other fast imaging techniques, but in spin echo sequences as well. Imperfections in the slice profile selected by a 180° pulse result in excitation and partial tipping of magnetization outside the desired region. The resulting signal from out-of-slice tissue can contaminate the signal and produce artifacts (25). Spoiling can be incorporated into the gradient waveforms to ensure that undesired signals or echoes are suppressed.

Figure 1.7 FLASH imaging sequence. Variable gradient spoiling lobe at end of sequence "spoils" transverse magnetization between phase encoded acquisitions.

1.3 Phase Sensitivity to Motion

In Eq.[1.18], the phase of the magnetization at a specific point in space and time was defined in terms of the gradient waveform ($G(t)$), and the position (r) of the isochromat of interest. This equation is central to the design of most gradient waveforms, including those shown in Figure 1.2, and Figures 1.5-1.7. It is valid only under the assumption that the positions of spins remain unchanged during the interval of integration. However, most biomedical applications of MRI involve the imaging of living organisms; the assumption that spins remain stationary during imaging is often violated.

An isochromat moving parallel to the direction of a time-varying magnetic field gradient $G(r)$ will accumulate a phase shift described by the integral equation

$$\phi(t) = \int_{t_0}^t \gamma G(\tau) x(\tau) d\tau \quad [1.20]$$

where τ is the variable of integration and $x(\tau)$ is the time varying position of the moving isochromat in the direction defined by the gradient. Equation [1.20] indicates that the phase of spins moving in the presence of magnetic gradients is a function of the motion itself. At times, it may be desirable to quantify physiological motion, utilize motion as a contrast mechanism, or minimize its effects in

an image. Gradient waveforms can be designed which exploit the motion dependence of the phase of the NMR signal to achieve these goals.

Equation [1.20] is usually evaluated at the echo ($t = TE$) where the result indicates the phase shift of the dominant $k_x = 0$ or dc spatial frequency component of the image. Phase is measured relative to the linear phase trajectory expected for stationary isochromats in a constant field gradient. Isochromats moving along a constant linear field gradient will exhibit a nonlinearly varying phase as a function of time (26,27) due to their time varying frequency.

The canonical relationship between data space (k -space) and image space can be corrupted by this motion dependent phase, resulting in image artifacts by several mechanisms. Dispersion of phase by variations of the motion of spins within a voxel will cause a loss of signal intensity (28). If this phase dispersion changes with time, it may cause ghosting and blurring (29,30). If all of the spins within a voxel are moving in the same manner, they all acquire the same phase shift due to motion. This can result in a misregistration artifact if there is a motion component in the phase encode direction (31). This misregistration may also lead to ghosting and

blurring if it varies from view-to-view. A novel technique for eliminating the misregistration artifact (32,33) will be described in detail in Chapter 6. Another artifacting mechanism is a blurring due to the non-linear phase trajectory acquired by spins moving along the read gradient during data sampling (27,26). A new method of compensating for this blurring in Echo Planar Imaging (EPI) (34) will be presented in Chapter 6 as well.

To facilitate an understanding of the effects of motion on the MR signal phase, it is helpful to expand the instantaneous position in a Taylor series (26). Taylor's theorem states (35) that if a function $x(t)$ and its first n derivatives $x^{(k)}(t)$, $k = 1, 2, \dots, n$, are continuous on an interval containing the points t and t' , then $x(t)$ has the following expansion into a polynomial of order n and variable $(t - t')$:

$$x_n(t-t') = x(t') + \sum_{k=1}^n \frac{x^{(k)}(t')}{k!} (t - t')^k + R_n, \quad [1.21]$$

where the remainder after n terms is

$$R_n = \int_{t'}^t (t-\tau)^n x^{(n+1)}(\tau) / n! d\tau \quad . \quad [1.22]$$

In Eq.[1.21], $x^{(k)}(t')$ represents the k th time derivative of $x(t)$ evaluated at t' . The first three derivatives of

position are known commonly as velocity, acceleration, and jerk:

$$\begin{aligned}
 x^{(0)}(t') &= x(t') \text{ (position)} \\
 x^{(1)}(t') &= v(t') \text{ (velocity)} \\
 x^{(2)}(t') &= a(t') \text{ (acceleration)} \\
 x^{(3)}(t') &= j(t') \text{ (jerk)}
 \end{aligned}
 \tag{1.23}$$

Jerk has occasionally (and misleadingly) been called "pulsatility" in the MRI literature.

The remainder term (R_n) accounts for any higher order components of motion not included in the series expansion. Equation [1.22] shows this remainder to be a function of the integral of the next higher order derivative evaluated over the entire time interval, thus including all higher order terms. In practice, the order (n) and point of expansion (t') are chosen so that R_n can be neglected over the time interval of interest. For the short time intervals defined by the typical echo times used in MRI, most physiological motion may be represented by a finite Taylor series expansion with negligible remainder (36,37).

Substituting the Taylor series expansion of instantaneous position into the equation for the phase shift at time ($t - t'$) of a moving isochromat yields the equation

$$\begin{aligned}
\phi(t-t') &= \gamma \left[\sum_{k=0}^n \frac{x^{(k)}(t')}{k!} \int_{t_0-t'}^{t-t'} G(\tau) \tau^k d\tau \right] \\
&= \gamma \left[\sum_{k=0}^n \frac{x^{(k)}(t')}{k!} M_k(t') \right]
\end{aligned} \tag{1.24}$$

where M_k is the k -th time moment of the gradient waveform computed about time t' .

Equation [1.24] separates the phase due to motion into terms dependent on the instantaneous position and derivatives of position evaluated at time t' . From this equation, the k -th order time moment of the gradient waveform, scaled by $1/k!$ and computed about t' , can be interpreted as the phase sensitivity to the k -th derivative of position evaluated at t' . This separation of phase into terms due to specific derivatives of position is the basis of a family of techniques of suppressing motion induced artifacts, MR angiography, and MR motion quantification.

The explicit dependence of the phase on **instantaneous** derivatives of position evaluated at time t' is often overlooked in the design of motion compensation and quantification waveforms. The significance of the expansion point (t') is substantial, and is thoroughly investigated in Chapters 5 and 6 of this thesis.

1.4 Gradient Waveform Design

1.4.1 Standard Imaging Sequences

In the previous sections it was shown how the frequency and phase of the NMR signal are controlled by gradient waveforms to encode spatial information. The magnitude of the field gradient determines the spatial distribution of resonant frequencies (Eq.[1.3]), and an integral relationship is held between the gradients and the sampled spatial frequency content of the resulting image (Eqs.[1.5-1.12]). As a result, slice thickness, image resolution, FOV, bandwidth, and motion sensitivity are all dependent on the gradient behavior as a function of time. Gradient waveforms for imaging are designed based on these dependencies.

Waveform design for most imaging sequences typically proceeds in the following manner. First, sequence type (gradient echo, spin echo, inversion recovery, etc.) and timing parameters (TR, TE, TI, etc.) are determined based on desired image contrast. Then, the amplitudes and durations of those sections of the waveform during rf excitation, phase-encoding, and data sampling are specified by slice-thickness, resolution, FOV, and bandwidth considerations, as well as hardware limitations. Using any time available between rf excitations and data sampling, lobes or pulses are added to the waveforms to rephase

magnetization across the slice and to form an echo. The amplitudes of these additional gradient pulses are found by solving Eq.[1.18] for the amplitude which nulls the phase integral at the appropriate times.

1.4.2 Practical Considerations

The gradient waveforms shown in the example pulse sequences (Figure 1.2 and Figures 1.5-1.7) are delivered through a system of current amplifiers and coils. The physical limitations on gradient system performance must be taken into account in the design of gradient waveforms for specific imaging applications.

Equations [1.5-1.12] reveal the direct dependence of resolution, bandwidth, FOV, and S/N on gradient amplitude. Physical limitations on current amplitude in the gradient coils, and hence, gradient amplitude, often force compromises to be made in these image characteristics.

Likewise, hardware limitations on gradient switching times or slew rates also influence waveform design, restricting waveform shape and duration. Waveform switching time can be further degraded by eddy currents induced in conductive structures surrounding the gradient coils. These currents generate spatially and temporally varying fields which superimpose on the applied linear gradient fields, distorting their shape and destroying the

required canonical relationship between data space and image space (38,39). Compensation circuits (39) and gradient shielding (40) are used to reduce the distortion of gradient waveforms by eddy currents. Even with these compensation strategies, the gradient system can only generate waveforms of finite bandwidth.

Amplifier RMS current limits also influence gradient waveform design by restricting gradient activity over the entire image acquisition time. This can effectively limit minimum repetition time (TR), or alternately, limit gradient amplitudes.

These limitations of the gradient system can have a profound effect on the ability of an MRI system to achieve specific imaging goals (14) and provide the motivation for the development of a waveform design method which takes best advantage of the capabilities of the gradient subsystem.

To design standard imaging sequences like those shown in Figure 1.2 and Figures 1.5-1.7, trapezoidal or sinusoidal pulses are frequently utilized to stay within the slew rate limits of the gradient system and reduce eddy current distortion. The amplitudes of these pulses are computed using Eqs.[1.4, 1.13-1.18] to meet specific imaging requirements. The resulting solution may or may not be practically realizable due to the physical

limitations of the gradient system. Several iterations using tradeoffs between gradient amplitude, gradient duration, S/N, bandwidth, and resolution, may be required before a feasible solution is obtained.

1.5 Gradient Waveforms with Controlled Motion Sensitivity

1.5.1 Introduction

Equation [1.20] indicates that the phase of the magnetization of an isochromat moving in the presence of a magnetic field gradient is a function of the motion itself. Gradient waveforms have been designed to exploit this phase dependence to quantify motion (27,41,41,42,43,44), utilize motion as a contrast mechanism for angiography (45,46,47), or minimize the effects of motion on an image (27,30,48). These goals complicate the waveform design problem; in addition to waveform amplitudes and areas, motion sensitivity in the form of waveform moments must be controlled.

A number of techniques have been put forth for designing gradient waveforms with nulled moments or explicit sensitivity to specific derivatives of position. For the most part, these are algebraic methods which take advantage of the linear relationship between gradient waveform time moments and waveform lobe amplitudes to generate motion compensated or sensitized waveforms.

Figure 1.8 Bipolar velocity encoding gradient waveform proposed by Moran (28). This waveform has no phase sensitivity to position, and sensitivity to velocity of $\gamma G t_d^2$.

1.5.2 Exploiting NMR Phase Sensitivity to Motion

In 1960, before the use of gradients for spatial encoding in NMR had been proposed, E.L. Hahn (49) devised a method of using NMR to measure the velocity of a moving sample (sea-water) by observing the phase shift at the center of a spin echo. In a constant field gradient, this phase is proportional to the velocity of moving spins. This was the first example of utilizing a gradient waveform to encode velocity in the phase of the NMR signal.

P.R. Moran (41), in 1982, proposed the use of a pulsed, balanced-bipolar gradient waveform within an MRI pulse sequence to phase-encode velocity. This waveform, shown in Figure 1.8, has zero area (zero-th order moment) and therefore, no phase sensitivity to position. The phase sensitivity to velocity of this waveform can be shown to be $\gamma G \cdot t_d^2$ rads/cm/sec where $\pm G$ is the lobe amplitude and t_d is the lobe duration (50). This bipolar waveform is incorporated into an imaging pulse sequence to encode velocity along the direction of the gradient into the phase of the NMR signal. The application of this technique was demonstrated in 1984 by both van Dijk (43) and Bryant et al. (44) to measure velocity directly from the phase of a complex image voxel.

In 1984, Constantinesco et al. (42) recognized that

the phase of the NMR signal ($s(t)$) from constant velocity spins could be separated into terms due to position

$$\phi_{x_0} = \int \gamma G_x(t) x_0 dt \quad [1.25]$$

and velocity

$$\phi_{v_0} = \int \gamma G_x(t) v_0 t dt \quad [1.26]$$

This separation led to the design of waveforms which selectively encode spatial location or flow velocity independent of one another. Constantinesco realized that cancelling the phase contribution of velocity by designing a waveform which nulled Eq.[1.26] (the first moment of the waveform) could help alleviate the adverse effects of motion from conventional MR imaging. However, he did not propose a method for incorporating these concepts into imaging pulse sequences.

In 1985, Wendt et al. (26) expanded the phase integral to include terms due to higher derivatives of position (acceleration, jerk, etc.) by expressing the time varying position as a Taylor Series expansion. This expansion lead to methods of quantifying blood acceleration (28,51), and ultimately, to the design of waveforms insensitive to dephasing due to higher order derivatives of position.

It was recognized by Constantinesco and Moran that conventional imaging gradient waveforms possessed

unintentional phase sensitivity to motion which confused velocity quantification schemes. Moran (28) suggested that:

"..more elaborate data balancing and reconstruction will eliminate phase-error artifacts due to accidental modulation inherent in conventional NMR sequences."

In 1985, LeRoux and Floch (52) proposed a means of incorporating the moment-nulling concept of Constanesco into imaging pulse sequences to suppress phase modulations due to velocity. This was done to generate a background phase image for phase subtractive velocity quantification, not for motion artifact reduction. The same concept was employed in 1986 by Dumoulin and Hart (45) and Nishimura et al. (47) to generate angiographic images of blood vessels solely from the NMR phase sensitivity to motion. Complex subtraction of images generated by sequences with different phase sensitivity to velocity (first moment) left an image of only moving material. The motion of blood serves as a type of contrast agent in this technique, which has come to be known as phase contrast MR angiography.

In 1987, gradient moment nulling was recognized for its benefits in reducing motion induced artifacts in conventional gradient and spin echo imaging (27,30,48). The gradient waveform design problem, not only for motion quantification and angiography, but for many conventional

imaging sequences, took on an added level of complexity with the inclusion of gradient moment nulling. This spawned a variety of new gradient waveform design techniques.

1.5.3 Motion Compensated Gradient Waveform Design Techniques

In a recent article (53), R.E. Wendt states:

"The design of a magnetic resonance imaging pulse sequence that includes motion compensation involves a constrained nonlinear optimization in the general case."

The accuracy of this statement is the basis for the optimal gradient waveforms design technique presented as the major focus of this thesis. However, a number of non-optimal methods based on the algebraic relationship between gradient waveform lobe amplitudes and time moments have been proposed over the past several years. These will be briefly reviewed here to provide the motivation for the development of the optimization approach to gradient waveform design.

In Duerk's 1987 dissertation (27), a general solution for the design of gradient waveforms with any number of nulled moments was proposed. Pattany et al. (30) later published a description of this technique, patented (54) as: MAST (Motion Artifact Suppression Technique).

The MAST technique can be described as follows. A gradient waveform with $m+1$ lobes or pulses is used to null m moments, resulting in phase insensitivity through the $(m-1)$ st derivative of position. Linear algebra methods are used to determine gradient lobe amplitudes that meet imaging and refocussing conditions. The matrix equation used to determine the amplitudes of arbitrarily shaped lobes placed at predetermined points in time, may be defined as

$$\begin{pmatrix} \frac{1}{0!} \int_{A1}^{A2} G_A(t) t^0 dt & \frac{1}{0!} \int_{B1}^{B2} G_B(t) t^0 dt & \dots & \frac{1}{0!} \int_{n1}^{n2} G_n(t) t^0 dt \\ \frac{1}{1!} \int_{A1}^{A2} G_A(t) t^1 dt & \frac{1}{1!} \int_{B1}^{B2} G_B(t) t^1 dt & \dots & \frac{1}{1!} \int_{n1}^{n2} G_n(t) t^1 dt \\ \frac{1}{2!} \int_{A1}^{A2} G_A(t) t^2 dt & \frac{1}{2!} \int_{B1}^{B2} G_B(t) t^2 dt & \dots & \frac{1}{2!} \int_{n1}^{n2} G_n(t) t^2 dt \\ \dots & \dots & \dots & \dots \\ \frac{1}{n!} \int_{A1}^{A2} G_A(t) t^n dt & \frac{1}{n!} \int_{B1}^{B2} G_B(t) t^n dt & \dots & \frac{1}{n!} \int_{n1}^{n2} G_n(t) t^n dt \end{pmatrix} \begin{pmatrix} a \\ b \\ c \\ \cdot \\ n \end{pmatrix} = \begin{pmatrix} D_0 \\ D_1 \\ D_2 \\ \cdot \\ D_n \end{pmatrix} - \begin{pmatrix} S_0 \\ S_1 \\ S_2 \\ \cdot \\ S_n \end{pmatrix} \quad [1.27]$$

or equivalently as

$$[M] \vec{A} = \vec{D} - \vec{S} \quad [1.28]$$

where D is the vector of desired waveform moments and S is the vector of moments of those sections of the waveform which are fixed by imaging considerations. These include sections of the slice select gradient during rf excitation and the frequency encoding waveform during data sampling. A is the vector of lobe scale factors to be solved for, and

matrix element M_{ij} is the i -th moment of the j -th waveform lobe. Thus, Eq.[1.28] represents a system of n linear equations which can be solved for the n unknown gradient lobe amplitudes which satisfy the specified imaging and moment nulling requirements. The velocity compensated gradient echo sequence depicted in Figure 1.9 shows how lobe amplitudes and moments fit into Eqs.[1.27 & 1.28].

This formulation allows for any arbitrary lobe shape $G_j(t)$ (i.e. trapezoidal, triangular, sinusoidal, etc.). The only constraint is that the moment integrals (M_{ij}) are available by either analytic solution or discrete approximation, and the number of lobes equals the number of moments to be nulled. The same matrix equation can be used to solve for the moments of an existing waveform, and to design waveforms with non-zero valued moments for encoding specific derivatives of position.

Duerk's dissertation (27) also suggested a method of iterating through different gradient lobe placements durations, solving for amplitudes at each iteration by Eq.[1.28]. In this manner, a type of iterative optimization is performed to find waveforms which meet amplitude, slew, and timing constraints while either minimizing echo time, or maximizing S/N by providing the longest possible sampling window. Thus, the need for an

Figure 1.9 Velocity compensated slice select and frequency encoding gradient waveforms. Lobe intervals and amplitudes on frequency encoding waveform correspond to those used in the MAST matrix equation (Equation 1.27).

optimal design technique was recognized and a method proposed for iteratively optimizing waveform timing. Similar techniques of iterative optimization were described in 1987 by Groen (55) and in 1989 by Yamagata (56).

Xiang and Nalcioğlu (57) also presented a method to generate waveforms for phase encoding a specific derivative of position independent of others. The only difference between this method and MAST is in the choice of basis sets. MAST is formulated to solve for lobe amplitude scale factors; Xiang introduces a basis set of multi-lobe waveforms $P_i(t)$ which span the entire time interval available. The gradient waveform is defined a linear combination of these basis waveforms as

$$G(t) = \alpha_0 P_0(t) + \alpha_1 P_1(t) + \dots + \alpha_{n_{P_g}}(t) \quad [1.29]$$

The basis waveforms are defined recursively in a manner which guarantees that the resulting set of linear equations (identical to Eq.[1.28]) can be solved for the scale factors α_i . Xiang suggested that practical considerations like gradient amplitude and rise time limitations could be taken into account by choosing basis sets with low amplitudes and smooth transitions.

Choosing a basis set of waveforms which cover the entire time interval available, as proposed by Xiang, eliminates the requirement that the pulse sequence designer

choose gradient pulse locations before solving for their amplitudes. However, this method would be difficult to use to design spin-echo or multi-echo waveforms where two or more sections of each waveform are fixed by imaging requirements.

A similar design method was presented in 1987 which should be mentioned for completeness. Chang (58) related the design of moment nulled gradient waveforms to the theory of electrical multipoles and generated gradients as the summation of a basis set of waveforms.

In 1988, Keller and Wehrli (59) proposed a waveform design method using binomial expansion coefficients to define the amplitudes of equal duration, equally spaced waveform lobes. This method requires rectangular gradient lobes and will always suffer inaccuracy in moment values due to the finite rise times of actual gradient systems.

Also in 1988, Wendt (60) stated the need for a constrained optimization approach to waveform design. He presented an iterative technique utilizing a personal computer spreadsheet program in lieu of the availability of software to perform a true optimization. Wendt (61) also suggested the use of triangular gradient lobes to allow more degrees of freedom in waveform design, and to possibly reduce the total energy required for motion compensated sequences.

In 1991, Pipe and Chenevert (62) recognized the requirements in gradient waveform design of not only moment nulling, but meeting imposed imaging requirements (e.g. slice selection or frequency encoding), avoiding undesirable effects like spurious echoes (63), and staying within gradient system limitations. They present a graphical method of easily generating motion compensated waveforms, but admit that the technique is limited in the complexity of waveforms it can produce.

1.6 Optimal Design Technique

1.6.1 Deficiencies of Standard Algebraic Design

While the above mentioned techniques are often adequate, several potential deficiencies may limit their effectiveness in gradient waveform design. First, gradient waveforms are constrained by the physical limitations of the system of gradient amplifiers and coils. These constraints may prevent the attainment of specific imaging goals and are not explicitly included in algebraic design techniques; some computationally inefficient methods were proposed to iterate through algebraic solutions until a feasible one is found. This does not guarantee that a feasible solution will be found even if one exists. Second, the resulting waveform may not be optimal in any sense. Feasible waveforms with lower RMS current, less

motion sensitivity, etc., may exist which would not be found with these methods. Third, waveforms designed by algebraic techniques are constrained to equal numbers of unknowns and equations, restricting the number of parameters defining the waveform. This may artificially constrain the waveform shape and restrict the solution space, reducing the chances of finding a feasible solution.

1.6.2 Proposal of Optimal Waveform Design Technique

A more robust method of gradient waveform design would (1) incorporate as much *a priori* knowledge of the gradient system as possible; (2) generate waveforms which are optimal for any of a number of imaging goals; (3) generate waveforms with shapes which are constrained only by the limitations of the hardware system and (4) guarantee waveform feasibility. A design approach with these characteristics can be developed through the application of formal optimization techniques to ensure utilization of the gradient system to its maximum potential.

This thesis presents a general formalism for the design of gradient waveforms using constrained optimization. Methods of formulating and solving the optimal waveform design problem are described in Chapter 2, and example waveforms and images are presented for a variety of design objectives and constraints in Chapter 3.

In Chapter 4, the proposed optimal waveform design technique is used to simulate alternative gradient systems, and to determine the necessary gradient system parameters required to achieve specific imaging goals. Chapter 5 examines the significance of the moment center or Taylor series expansion point in the design of motion compensated gradient waveforms. Several applications of the theory put forth in Chapter 5 are demonstrated by simulation and imaging experiments in Chapter 6. Finally, conclusions and future directions for this research are addressed in Chapter 7.

2. Gradient Waveform Optimization

2.1 Introduction

2.1.1 Background

Pulsed magnetic field gradients are essential to Fourier transform magnetic resonance imaging. As such, the design of these gradient waveforms is an important part of effective imaging. Pulsed magnetic field gradients are used in MRI to spatially and temporally control the frequency and phase of nuclear magnetization. This control is essential for spatial encoding of the MR signal. The magnitudes of the gradients determine the spatial distribution of resonant frequencies, and a relationship is held between the time integral of the field gradients and the sampled spatial frequency content of the resulting image (3,14,64). As a result, slice thickness, image resolution, field-of-view (FOV), bandwidth (BW), and motion sensitivity are all dependent on the gradient behavior as a function of time.

Sections of the gradient waveforms between rf excitation and data sampling are typically designed to control the phase of the MR signal. For the simple cases of gradient echo formation and refocussing of static material, trapezoidal or sinusoidal pulses are often utilized to compensate for the phase acquired during slice selection and data acquisition. The only restrictions on

these pulses are that they do not exceed the limitations of the gradient hardware system, and they meet the timing requirements of the particular imaging sequence.

A number of gradient waveform design techniques have been put forth, in particular, to perform the task of designing nulled moment gradient waveforms for motion compensation (30,48,57,58,59,56,62,61,53), or equivalently, motion sensitized waveforms for flow encoding (41,42) or phase contrast MR angiography (47,45). As described in Chapter 1, these algebraic design techniques take advantage of the linear relationship between gradient waveform time moments and lobe amplitudes to generate motion compensated or sensitized waveforms. While these methods are often adequate, several potential deficiencies were pointed out in Chapter 1 which can limit their effectiveness. A more robust method of gradient waveform design utilizing formal optimization is presented in this chapter.

2.1.2 Applications of Optimization Theory in MRI

While the term "optimization" is often used incorrectly in the MRI literature, formal optimization has indeed been applied to several aspects of magnetic resonance imaging. RF pulse shapes have been optimized for slice profile (65,66,67), minimal phase twist across the slice (66,18,17), and minimum specific absorption rate

(SAR) (68). Pulse sequence timing has also been treated as an optimization problem (69,70) with the objective of maximizing some measure of image contrast.

It has been recognized that gradient waveform design can be generalized as a problem of non-linear constrained optimization (53), but no design formalism has been presented to date. Only for the specific case of optimization of slice profile or SAR by the use of time varying gradients during rf application (18,68) has the use of optimization in gradient waveform design been described.

2.1.3 Overview of the Proposed Design Technique

A method of using non-linear constrained optimization to design gradient waveforms for magnetic resonance imaging is presented in this chapter. The formulation and solution of the waveform optimization problem are described; example waveforms and images are presented in Chapter 3.

Among the many possible design objectives, those considered in this work are (1) minimize RMS current; (2) minimize waveform slewing; (3) minimize waveform moments to reduce motion induced dephasing; (4) minimize echo time (TE) for given imaging and motion refocussing conditions; (5) maximize the gradient amplitude during RF application and sampling, and the area of the phase encoding waveform, to maximize resolution; and (6) minimize or maximize the

gradient b factor or diffusion sensitivity. Artificial constraints on waveform shape imposed by multi-lobe designs are eliminated by defining the waveform as a set of discrete amplitudes. These amplitudes are the parameters determined in the optimization procedure, subject to the constraints defined by imaging conditions and the specific gradient hardware system of interest.

Most design objectives can be expressed as linear or quadratic functions of the discrete parameter set, and most constraint functions are linear. Thus, linear (LP) and quadratic programming (QP) techniques can be utilized in most cases to solve the optimization problem. Methods of handling objective and constraint functions which do not fit the LP or QP forms are discussed. Some techniques to handle multi-objective optimization are also proposed.

2.2 Theory

The goal in gradient waveform design is to best meet some specific imaging performance criteria without exceeding the constraints imposed by the hardware limitations of the gradient system. Thus, the waveform design problem may be viewed as one of constrained optimization. Formulation of any constrained optimization problem involves four basic steps (71):

1. Select a parameter set.
2. Define the objective.
3. Specify the constraints.
4. Determine a suitable means of solution.

The application of these four steps to the gradient waveform design problem permits its formulation and solution as a constrained nonlinear optimization.

2.2.1 Waveform Parameterization

The design objectives and constraints must be expressed in terms of a parameter set which fully describes the gradient waveform. The ability to achieve a feasible solution is highly dependent on the choice of parameter set.

Gradient waveforms are typically designed as a sequence of trapezoidal or sinusoidal lobes or pulses (30,57) to stay within the slew rate limitations of the gradient amplifier system. The parameter set describing this type of waveform consists of lobe amplitudes and durations. Triangular lobes (61), Fourier coefficients (72) or polynomial coefficients (73) can also be used as parameter sets to describe a gradient waveform.

Since gradient waveforms are computer generated discrete functions applied to the gradient amplifiers and

coils via digital-to-analog (D/A) converters, the most obvious and general parameter set is a discrete series of equally spaced point-by-point gradient amplitudes. This set may be expressed in vector form as

$$\vec{g} = [g_1, g_2, \dots, g_i, \dots, g_N] \quad [2.1]$$

where g_i indicates the amplitude of the waveform at time $t_i = i \cdot \Delta t$, and Δt is the sample interval. The N -points define the waveform for a single phase-encoded view from the end of the first rf pulse to the start of data sampling as shown in Figure 2.1. Sections of the waveforms before and after these points minimally affect the design objectives discussed here, and are generated separately to limit the size of the parameter set.

Expressing a gradient waveform as such a series of discrete points removes artificial constraints on shape, and expands the feasible solution space to the limits of the gradient hardware system.

Figure 2.1 Generic velocity compensated field echo waveforms showing discrete amplitude waveform parameterization. Endpoint g_1 on the slice select waveform defines the gradient amplitude during rf excitation. Endpoint g_N on the frequency encoding waveform defines the gradient amplitude during data acquisition.

2.2.2 Objectives

The objective function is an expression of the specific waveform design goal in terms of the chosen parameter set. Gradient waveform design is guided by many possible objectives, a limited number of which are described here. These are presented and implemented as single objective functions. Some methods of combining these into multi-objective functions are discussed in Section 2.2.4.

2.2.2.1 Minimize RMS Current

Gradient waveforms are produced by a system of amplifiers which drive current through gradient coils. The field gradient amplitude is, in general, directly proportional to the current amplitude. RMS current (I_{RMS}) or duty cycle limits are placed on this system to prevent excessive heating and energy dissipation in the coils or amplifiers. I_{RMS} limits in typical whole-body MRI systems may necessitate compromises in the number of slices, FOV, slice thickness (d), and repeat time (TR). Design of gradient waveforms with minimum I_{RMS} may reduce the severity of these compromises.

RMS current is related to the gradient waveform by:

$$I_{RMS} \propto \sqrt{\frac{1}{TR} \int_0^{TR} g^2(t) dt} \quad [2.2]$$

where $g(t)$ incorporates as many repetitions of the waveform per TR interval as required by the number of slices in a multislice 2DFT sequence.

Assuming that the waveform amplitudes during slice selection and data sampling are fixed by imaging considerations, the objective (Φ) becomes to minimize the RMS current of the remaining waveform portions while meeting imaging goals. This can be expressed as the integral

$$\min \Phi = \int g^2(t) dt \quad [2.3]$$

which can be approximated for the discrete waveform as

$$\min_{\vec{g} \in \Re} \Phi = \sum_{i=1}^{N-1} \Delta t (g^2_i + g^2_{i+1}) / 2 \quad [2.4]$$

using trapezoidal numerical integration. This can be written in matrix form as the quadratic function

$$\Phi = \frac{1}{2} \vec{g}^T \mathbf{H} \vec{g} \quad [2.5]$$

with no linear terms. The positive definite (pd) Hessian matrix ($\mathbf{H}$) of quadratic coefficients is defined as

$$H = 2 \cdot \begin{bmatrix} \frac{\Delta t}{2} & 0 & 0 & \dots & 0 & 0 \\ 0 & \Delta t & 0 & \dots & 0 & 0 \\ 0 & 0 & \Delta t & \dots & 0 & 0 \\ \cdot & \cdot & \cdot & \dots & \cdot & \cdot \\ \cdot & \cdot & \cdot & \dots & \cdot & \cdot \\ \cdot & \cdot & \cdot & \dots & \cdot & \cdot \\ 0 & 0 & 0 & \dots & \Delta t & 0 \\ 0 & 0 & 0 & \dots & 0 & \frac{\Delta t}{2} \end{bmatrix} \quad [2.6]$$

2.2.2.2 Minimize Waveform Slewing

Time varying fields may induce eddy currents in conductive structures within the magnet. These currents, which are dependent on dB/dt , can generate spatially and temporally varying fields which oppose the applied linear gradients. They can lead to transient field errors which degrade imaging performance by distorting the desired gradient profile (38). Pre-emphasis (39,74) and active shielding (40,75) are techniques used to reduce eddy current effects.

Additionally, or alternately, it may be possible to reduce eddy current generation via minimization of dB/dt . That is, by minimizing the total rate of change of the gradient waveform (slew rate), dB/dt is minimized over all space.

The first difference is often used as a mathematical approximation for the instantaneous derivative (or slew rate) of a function (76). Using this approximation, the objective of total minimum waveform slewing can be expressed as a least-squares objective function, minimizing the sum of squared first-order differences between sample points on the waveform. This technique has been used in optimal design of rf pulse envelopes for MRI with the goal of generating smooth, narrow bandwidth pulses (66). The resulting quadratic objective can be expressed for the discrete waveform as

$$\begin{aligned}
 \min_{\mathbf{g} \in \mathbb{R}} \Phi &= \sum_{i=1}^{N-1} \left(\frac{g_{i+1} - g_i}{\Delta t} \right)^2 \\
 &= \sum_{i=1}^{N-1} \left(\frac{g_{i+1}^2 - 2g_i g_{i+1} + g_i^2}{(\Delta t)^2} \right) \\
 &= \sum_{i=1}^{N-1} \left(\frac{1}{(\Delta t)^2} g_i^2 + \frac{1}{(\Delta t)^2} g_{i+1}^2 - \frac{2}{(\Delta t)^2} g_i g_{i+1} \right)
 \end{aligned} \tag{2.7}$$

where the positive semi-definite (psd) Hessian is

$$\mathbf{H} = 2 \cdot \begin{bmatrix} \frac{1}{(\Delta t)^2} & -\frac{1}{(\Delta t)^2} & 0 & 0 & 0 & 0 & \dots & 0 \\ -\frac{1}{(\Delta t)^2} & \frac{2}{(\Delta t)^2} & -\frac{1}{(\Delta t)^2} & 0 & 0 & 0 & \dots & 0 \\ 0 & -\frac{1}{(\Delta t)^2} & \frac{2}{(\Delta t)^2} & -\frac{1}{(\Delta t)^2} & 0 & 0 & \dots & 0 \\ \cdot & \cdot & \cdot & \cdot & \cdot & \cdot & \cdot & \cdot \\ 0 & \dots & 0 & -\frac{1}{(\Delta t)^2} & \frac{2}{(\Delta t)^2} & -\frac{1}{(\Delta t)^2} & \dots & 0 \\ \cdot & \cdot & \cdot & \cdot & \cdot & \cdot & \cdot & \cdot \\ 0 & \dots & 0 & 0 & 0 & -\frac{1}{(\Delta t)^2} & \frac{2}{(\Delta t)^2} & -\frac{1}{(\Delta t)^2} \\ 0 & \dots & 0 & 0 & 0 & 0 & -\frac{1}{(\Delta t)^2} & \frac{1}{(\Delta t)^2} \end{bmatrix} \tag{2.8}$$

2.2.2.3 Minimize deviation from desired moment values

One goal of gradient waveform design may be that the waveform possesses specific time moments. The moments may be treated as constraints when they must match specific values, or as objectives when it is sufficient to get as close as possible to the targeted values. This objective may be driven by goals of gradient moment minimization to reduce dephasing caused by the motion of spins (30,48,47), or by phase encoding of motion for phase contrast angiography (47,45) and flow quantification (41,43) applications. A least-squares function defines the objective in either case as minimization of the squared deviation of the waveform time moments from targeted values. The target moments are zero for motion compensation and non-zero for motion encoding.

The objective of optimizing the k -th moment value may be expressed as the least-squares objective

$$\begin{aligned} \min_{\vec{g} \in \mathfrak{R}} \Phi &= (T_k - M_k)^2 \\ &= (T_k^2 + M_k^2 - 2 T_k M_k) \end{aligned} \quad [2.9]$$

where T_k is the target moment and M_k is the actual moment. The constant term T_k^2 can be dropped from [2.9] without changing the location of the minima yielding

$$\min_{\vec{g} \in \mathfrak{R}} \Phi = M_k^2 - 2 T_k M_k \quad . \quad [2.10]$$

Since the waveform is defined as a vector of discrete amplitudes, the moment M_k can be approximated using trapezoidal numerical integration yielding

$$\min_{\vec{g} \in \mathfrak{R}} \Phi = \left[\sum_{i=1}^{n-1} \frac{\Delta t}{2} (g_i t_i^k + g_{i+1} t_{i+1}^k) \right]^2 - 2 T_k \sum_{i=1}^{n-1} \frac{\Delta t}{2} (g_i t_i^k + g_{i+1} t_{i+1}^k) \quad [2.11]$$

This can be expressed using matrix notation as

$$\min_{\vec{g} \in \mathfrak{R}} \Phi = \frac{1}{2} \vec{g}^T \mathbf{H} \vec{g} + \vec{c}^T \vec{g} \quad [2.12]$$

a quadratic function of $\vec{g}$, the discrete waveform parameter set. The psd Hessian matrix of quadratic coefficients is

$$\mathbf{H} = 2 \cdot \begin{bmatrix} (\frac{\Delta t}{2})^2 t_1^{2k} & \frac{(\Delta t)^2}{2} t_1^k t_2^k & \dots & \frac{(\Delta t)^2}{2} t_1^k t_{n-1}^k & (\frac{\Delta t}{2})^2 t_1^k t_n^k \\ \frac{(\Delta t)^2}{2} t_2^k t_1^k & (\Delta t)^2 t_2^{2k} & \dots & (\Delta t)^2 t_2^k t_{n-1}^k & \frac{(\Delta t)^2}{2} t_2^k t_n^k \\ . & . & \dots & . & . \\ . & . & \dots & . & . \\ . & . & \dots & . & . \\ \frac{(\Delta t)^2}{2} t_{n-1}^k t_1^k & (\Delta t)^2 t_{n-1}^k t_2^k & \dots & (\Delta t)^2 t_{n-1}^{2k} & \frac{(\Delta t)^2}{2} t_{n-1}^k t_n^k \\ (\frac{\Delta t}{2})^2 t_n^k t_1^k & \frac{(\Delta t)^2}{2} t_n^k t_2^k & \dots & \frac{(\Delta t)^2}{2} t_n^k t_{n-1}^k & (\frac{\Delta t}{2})^2 t_n^{2k} \end{bmatrix} \quad [2.13]$$

and the vector ($\vec{c}$) of linear coefficients is

$$\begin{aligned} \vec{c} &= \left[2T_k \left(\frac{\Delta t}{2} \right) t_1^k \quad 2T_k \left(\frac{\Delta t}{2} \right) 2t_2^k \quad \dots \quad 2T_k \left(\frac{\Delta t}{2} \right) 2t_{n-1}^k \quad 2T_k \left(\frac{\Delta t}{2} \right) t_n^k \right] \\ &= \left[T_k \Delta t t_1^k \quad 2T_k \Delta t t_2^k \quad \dots \quad 2T_k \Delta t t_{n-1}^k \quad T_k \Delta t t_n^k \right]. \end{aligned} \quad [2.14]$$

Note that the linear coefficient vector $\vec{c}$ is null when the target moments are zero.

2.2.2.4 Maximize Resolution

Slice thickness for a given rf pulse can be minimized by maximizing the gradient amplitude during slice selection. Field-of-view in the frequency encoded direction can be minimized for a given data sampling rate by maximizing the amplitude of the applied gradient during data acquisition. These objectives can be expressed as the linear objective function

$$\max_{\vec{g} \in \mathfrak{R}} \Phi = g_j \quad [2.15]$$

where parameter g_j is an endpoint of the discrete waveform section. As seen in Figure 2.1, the amplitudes of the constant sections of the waveform during rf excitation and sampling are determined by the corresponding endpoint of the discrete waveform section. Thus, this objective involves the maximization of a single parameter. Since this is a linear objective function, it can be solved with linear programming (LP) methods, provided any constraint

functions are linear as well.

Field-of-view in the phase-encoded direction can be minimized for a given number of phase-encoding steps by maximizing the zero-th moment or area of the waveform used for the maximum phase-encoding step. Again, using trapezoidal integration, this objective can be expressed in terms of the discrete waveform parameter set as

$$\begin{aligned} \max_{\vec{g} \in \mathfrak{R}} \Phi &= M_0 \\ &= \sum_{i=1}^{N-1} \frac{\Delta t}{2} (g_i + g_{i+1}) \end{aligned} \quad [2.16]$$

This is also a linear function of the discrete parameter set. Waveforms for all other phase-encoding steps are merely amplitude scaled versions of the resulting waveform.

2.2.2.5 Maximize or Minimize Diffusion Sensitivity

Diffusion or Intra Voxel Incoherent Motion (IVIM) imaging requires the addition of high amplitude "diffusion" gradient pulses to imaging gradient waveforms (77,78). The purpose of these additional pulses is to control the sensitivity of the MR signal to IVIM. This sensitivity can be specified by the gradient b factor (77) which is defined as

$$b(T) = \int_0^T k(t)^2 dt \quad [2.17]$$

where

$$k(t) = \gamma \int_0^t g(t') dt' \quad [2.18]$$

Using the discrete parameter set to define $g(t)$, k^2 can be approximated as

$$k_j^2 = \left(\frac{\gamma \Delta t}{2} \right)^2 \bar{g} \bar{a}_j^T \bar{a}_j \bar{g}^T \quad [2.19]$$

where the N-element vector a_j is defined as

$$\begin{aligned} \bar{a}_1 &= [1 \ 1 \ 0 \ 0 \ 0 \ \dots \ 0 \ 0] \\ \bar{a}_2 &= [1 \ 2 \ 1 \ 0 \ 0 \ \dots \ 0 \ 0] \\ \bar{a}_3 &= [1 \ 2 \ 2 \ 1 \ 0 \ \dots \ 0 \ 0] \\ &\vdots \\ \bar{a}_N &= [1 \ 2 \ 2 \ 2 \ 2 \ \dots \ 2 \ 1] \end{aligned} \quad [2.20]$$

Now, an approximation of the gradient diffusion sensitivity factor b can be written as a quadratic function of the discrete parameter set g as

$$\begin{aligned} b &= \left(\frac{\Delta t}{2} \right)^2 \sum_{j=1}^{N-2} k_j^2 + k_{j+1}^2 \\ &= \gamma^2 \left(\frac{\Delta t}{2} \right)^2 \sum_{j=1}^{N-2} \bar{g} \bar{a}_j^T \bar{a}_j \bar{g}^T + \bar{g} \bar{a}_{j+1}^T \bar{a}_{j+1} \bar{g}^T \end{aligned} \quad [2.21]$$

Optimization can be used to maximize or minimize the b factor while maintaining waveform feasibility and desired

level of coherent motion insensitivity. Maximizing b subject to linear constraints creates a concave programming problem; the solution may be unbounded in some instances.

2.2.2.6 Echo Time Minimization

Fast imaging techniques require very short echo times and short repeat times. Minimum echo time under specific imaging conditions is considered as a waveform design goal in time-of-flight angiography sequences to minimize dephasing of blood due to uncompensated orders of motion (79,80). One approach to solving this problem by optimization requires a modification of the discrete amplitude parameter set to include the waveform sampling interval. This new parameter set is defined as

$$\vec{x} = [g_1, g_2, \dots, g_N, \Delta t] \quad [2.22]$$

and the objective function as

$$\min_{\vec{x} \in \mathfrak{X}} \Phi = \Delta t \quad [2.23]$$

While this objective is linear in the parameters, the inclusion of sample interval in the parameter set results in quadratic constraint functions; this can complicate the optimization.

A simpler solution is to decrement the value of Δt or the number of sample points until a feasible waveform can

not be generated. Infeasibility is easily detected in LP and QP problems (85) making this type of iterative minimization fairly efficient, as demonstrated in (81). At each iteration, an additional objective is optimized at the corresponding echo time.

2.2.3 Constraints

The constraints of an optimization problem are the conditions which define the feasible set of solutions. Depending on the specific imaging application, it may be necessary to fix or limit any of the objectives defined above, in which case they become constraints in the optimization problem. In addition, other gradient system hardware limitations and waveform characteristics required to generate an image form a natural set of constraints for the design of gradient waveforms. Inclusion of these constraints, together with proper methods of solution, ensure that the resulting waveforms will be physically realizable and meet the required imaging goals. These constraints must be expressed as equalities or inequalities in terms of the waveform parameter set.

2.2.3.1 Amplitude Limits

Gradient amplifiers have peak current limits which restrict the maximum excursion of gradient waveform

amplitude. These limits can be expressed as inequality range constraints on each of the N points in the discrete waveform sequence as

$$G_{\min} \leq g_i \leq G_{\max} \quad \text{for all } i = 1, 2, \dots, N \quad [2.24]$$

where $G_{\min}$ and $G_{\max}$ are the minimum and maximum allowable gradient amplitudes.

2.2.3.2 RMS Current or Duty Cycle Limits

Using the definition of RMS current given in Eq [8], the inequality constraint can be expressed as

$$\frac{1}{TR} \int_0^{TR} g^2(t) dt \approx \sum_{i=1}^{N-1} \frac{\Delta t}{2 \cdot TR} (g_i^2 + g_{i+1}^2) \leq (I_{RMS_{MAX}})^2 \quad [2.25]$$

where I_{RMS} is expressed in gradient units rather than amps. This constraint is a quadratic function of the parameter set, thus LP or QP solution methods are not applicable. However, the solution space defined by this constraint is convex, and convex programming techniques (82) may be used.

2.2.3.3 Slew or Rise Time Limits

Gradient amplifiers also have limits on slew rate or rate of change of amplitude. This can be approximated as an inequality range constraint on the first-order

difference between adjacent discrete points as

$$DG_{\min} \leq \left(\frac{g_{i+1} - g_i}{\Delta t} \right) \leq DG_{\max} \quad \text{for all } i = 1, 2, \dots, N \quad [2.26]$$

where $DG_{\min}$ and $DG_{\max}$ are the minimum and maximum allowable slew limits.

2.2.3.4 Fixed Moment Values

The zero-th time moment or waveform area may be constrained to zero to rephase static material (slice select), to form an echo (frequency encoding), or incremented to step through k -space (phase encoding). Higher order moments may also be fixed to achieve a specific level of motion sensitivity or insensitivity.

It may also be necessary to constrain the area of specific sections of the waveform to spoil undesired transverse magnetization. For example, in spin echo sequences, inaccuracies in the slice profile selected by the 180° pulse may generate a free induction decay (FID) from material outside of the desired slice. Artifacts caused by this spurious signal can be reduced by designing the gradient waveforms to dephase it, and to ensure it does not form an echo within the data sampling interval. This is sometimes done by addition of symmetrical, equal area lobes to the phase encoding waveform, centered about the

180° pulse.

Any of these goals: echo formation, rephasing material across the slice, motion compensation, motion encoding, and gradient spoiling, can be achieved by fixing the appropriate moment or moments of specific sections of the waveform. Setting the k th moment (M_k) equal to some target value (T_k) results in the equality constraint

$$M_k = T_k \quad [2.27]$$

This equality may be expressed in terms of the parameter vector g over the entire waveform as the linear function

$$\sum_{i=1}^{N-1} \frac{\Delta t}{2} (g_i t_i^k + g_{i+1} t_{i+1}^k) = T_k \quad . \quad [2.28]$$

2.2.3.5 Fixed Resolution and Bandwidth

The amplitudes of the waveform during rf application and data sampling may be fixed by specific resolution and bandwidth requirements. This can be expressed as an equality constraint on the fixed waveform sample points as

$$g_j = G_j \quad [2.29]$$

where G_j is the required amplitude of the j th sample point. The amplitude of the entire waveform section during rf excitation or sampling is determined by this single point, G_j as indicated in Figure 2.1. Resolution in the phase

encode direction is fixed by constraining the area of the phase encode waveform, as described previously.

2.2.3.6 Diffusion Sensitivity

Gradient waveforms with different levels of diffusion sensitivity are required to estimate tissue diffusion coefficients (78). Thus, it may be desirable to constrain the b factor to a specific value when designing diffusion sensitized gradient waveforms. The b factor is a quadratic function of the discrete waveform parameter set; LP and QP optimization techniques cannot solve the b constrained problem. However, the convexity of the feasible space is preserved and convex programming methods (82) can be applied.

2.2.3.7 System Frequency Response

Every system of gradient amplifiers and coils has a characteristic frequency response due to amplifier and coil design, digital-to-analog converter (DAC) output filters, and eddy currents. These factors can combine to produce a low-pass filtering (LPF) effect on the gradient waveform (39). This filtering constrains the frequency content of the gradient waveforms, restricting it to stay within the system passband.

Filtering of the input waveform resulting from the

gradient subsystem can be modelled as a linear digital filter function to define a new parameter set

$$\begin{aligned}\vec{f} &= [f_1, f_2, \dots, f_N] \\ &= \mathbf{F}\vec{g}\end{aligned}\tag{2.30}$$

; a filtered version of the original set, where $\mathbf{F}$ is the convolution matrix of linear filter coefficients representing an FIR (finite impulse response) LPF, or approximate transfer function of the gradient system. This filter can be incorporated into the design procedure to generate a waveform, which when convolved with an estimate of the impulse response ($\mathbf{F}$) of the gradient subsystem, yields a time varying waveform with the desired characteristics. This input waveform is applied to the gradient system to generate the output waveform which is the actual time varying field gradient.

This process is roughly equivalent to digital pre-emphasis. However, by including the filter function within the waveform design process, constraints and objectives associated with input and output waveforms can be separated. For example, it may be desirable to constrain the amplitude of the input (unfiltered) waveform, while minimizing a time moment of the output (filtered) waveform.

This filtering technique is proposed, but not

implemented in this work. An accurate model of the gradient system transfer function is required for proper implementation. This is a system identification problem which is discussed further in the section of Chapter 7 dealing with future directions.

2.2.4 Methods of Solution

2.2.4.1 Linear and Quadratic Programming

With the exceptions of the RMS current and diffusion sensitivity constraints, all of the objective and constraint functions described fit the definitions of either linear (LP) or quadratic programming (QP) problems. These are special cases of linearly constrained optimization that occur when the objective function is linear or quadratic in the parameters (83,82). The general form of the these types of optimization problems can be expressed as:

$$\begin{aligned} \min_{\tilde{g} \in \mathbb{R}} \quad & \Phi = \frac{1}{2} \tilde{g}^T H \tilde{g} + \tilde{c}^T \tilde{g} \\ \text{s. t.} \quad & a_i^T \tilde{g} = b_i, \quad i \in E \\ & a_j^T \tilde{g} \geq b_j, \quad j \in I \end{aligned} \quad [2.31]$$

where g is the parameter vector, H is the Hessian matrix of quadratic coefficients, c is the vector of linear coefficients, a_i is a vector of linear constraint

coefficients, E is the set of equality constraint indices, and I is the set of inequality constraint indices. The linear filter function of [2.28], F , can be included in equation [2.29] as:

$$\begin{aligned} \min_{\vec{g} \in \mathcal{R}} \quad & \Phi = \frac{1}{2} \vec{g}^T \mathbf{F}^T \mathbf{H} \mathbf{F} \vec{g} + \vec{c}^T \mathbf{F} \vec{g} \\ \text{s.t.} \quad & a_i^T \mathbf{F} \vec{g} = b_i, \quad i \in E \\ & a_j^T \mathbf{F} \vec{g} = b_j, \quad j \in I \end{aligned} \quad [2.32]$$

as discussed in the previous section.

All of the QP objectives described (except maximization of b factor) possess either positive definite (pd) or positive semi-definite (psd) Hessian matrices. A quadratic function is convex and the QP solution is a global optimum when the Hessian is psd, and a quadratic is strictly convex and the QP solution global and unique when the Hessian is pd. Thus, solution of all objectives presented (except b maximization) will result in global optima. Diffusion sensitivity *maximization* subject to linear constraints creates a concave programming problem which can present some difficulties. Some specialized solution procedures exist for solving this type of problem (84).

An additional advantage of LP and QP problem formulation is that although the problem may be infeasible, or the solution unbounded, these situations are easily

detected in the solution algorithms (85). Also, the LP and QP problems can be solved in a finite number of steps, and all iterates are feasible. These characteristics of LP and QP optimization make them more tractable than general non-linear programming forms, which are notoriously difficult to solve. Robust, efficient algorithms for LP and QP problems are widely available which lead to quick and easy solution on a personal computer.

Optimization problems with linear inequality constraints are often solved by "active set" methods (83, 85). The active set strategy is implemented in the 386-MATLAB software package which was utilized to solve the waveform optimization problem. Detailed descriptions of the method are given in (83, 85); a brief synopsis of the algorithm is provided here.

The general class of problem considered is that of minimizing some objective $F(x)$, subject to a set of linear inequality constraints:

$$\begin{aligned} &\underset{x \in \mathbb{R}^n}{\text{minimize}} && F(x) \\ &\text{s.t.} && Ax \geq b \end{aligned} \quad [2.33]$$

Only the constraints which are *active* at the solution, that is, constraints which are exactly satisfied by equality, are significant in the optimality conditions. This is the basis for the active set solution strategy. If the active

set were known *a priori*, then the solution of [2.33] would also be a solution of the equality constrained problem:

$$\begin{aligned} & \underset{x \in \mathbb{R}^n}{\text{minimize}} && F(x) \\ & \text{s.t.} && \hat{A}x = \hat{b} \end{aligned} \quad [2.34]$$

subject only to the active constraints. Efficient techniques are available to solve the linear equality constrained problem; equality constraints effectively reduce the problem dimension. Thus, the basis of the active set solution strategy is to predict the set of constraints which are active at the solution, and solve the resulting linear equality constrained problem. Since the prediction may be wrong at any iteration, procedures are included for altering the working set of active constraints. At each iteration, the solution generated by this method is feasible.

Linear inequality constrained linear and quadratic programming problems form special subsets of the general linear constrained optimization problem of Eq.[2.33]. The well known simplex method (86) of solving LP problems is actually an active set strategy, although it was originally developed from a much different viewpoint. Almost all algorithms available for solving QP problems are based on active set methods. Characteristics of the LP and QP

problems can be exploited to reduce the computational requirements of these solution methods.

2.2.4.2 Multi-Objective Functions

As presented, this waveform design technique has been applied to the optimization of single objective functions. Only one of the objectives discussed in Section 2.2.2 is optimized in any particular gradient waveform. However, it may be desirable to design waveforms which are optimal with respect to more than one objective. This represents a multi-objective problem for which several solution strategies exist (87).

Since all objectives are convex (except b maximization), a simple strategy is to combine the objective functions into a single "weighted sum" objective. The weights not only represent the relative importance of individual objectives, but also reflect unit conversions among the different objectives. For a given set of weights, a solution will be "efficient" in the sense that no one objective can be improved without degrading at least one other. By systematically varying the weights, the process may converge to a gradient waveform with desired tradeoffs among the different goals. In practice, however, applying this weighting strategy to the gradient waveform design problem may be difficult. Because the objectives

have very diverse units and scales, the solution of the weighted objective problem is very sensitive to the weights chosen. This makes the task of choosing weights and making subsequent adjustments very difficult.

An alternative strategy is to select a primary objective to optimize, and set upper (or lower) limits on the remaining objectives of interest. The task then is to design a gradient waveform which is optimal with respect to the chosen primary objective while keeping the remaining objectives within set limits. A solution generated in this manner is also efficient in the sense defined above. By systematically varying the upper (lower) limits on the "secondary" objectives, an efficient waveform with the desired tradeoffs may be generated. Varying these limits is often easier than varying weights, since these limits can be varied independently of each other and since such limits usually have meaningful interpretation.

Noting that nearly all of the objectives defined in Section 2.2.2 are also defined as constraints in Section 2.2.3, a simplification of multi-objective optimization by defining secondary objectives is effectively implemented in the design technique described in this work. That is, any number of objectives may be constrained to specific values, or to lie within a specific range, while a single objective is optimized. However, no iterative variation in the

constraints is attempted.

The only difficulty with this type of approach to multi-objective optimization is that the resulting problem may no longer have only linear constraints. In fact, the modified problem will be a convex program with a linear or convex quadratic objective and linear or convex quadratic constraints. Several dual methods for solving convex programs such as this exist (82).

2.3 Discussion

A number of gradient waveform design techniques have been proposed in the literature. In this chapter, a goal-directed method of gradient waveform design using constrained optimization techniques is presented which has a number of advantages over other methods.

The discrete amplitude waveform parameterization ensures that no artificial constraints on shape are imposed by the design procedure, and facilitates the constrained optimization of most applicable design goals. These goals are treated as single objective functions, although most objectives can be constrained to a specific range or value while another objective is optimized. Any or all of the constraint functions presented can be included in the optimization of a particular waveform.

The parameter set, objectives, and constraint

functions have been set up to facilitate the use of linear or quadratic programming optimization techniques, in most cases. This eases the computational burden associated with general, nonlinear constrained optimization problems, and permits solution on a personal computer system.

3. Example Waveforms and Images

3.1 Waveform Generation

3.1.1 Introduction

In this chapter, the optimal gradient waveform design method proposed in Chapter 2 is used to generate some example waveforms and images. Before presenting these examples, it is best to reiterate exactly what optimization problem is being solved.

The discrete waveform amplitude parameters shown in Figure 2.1 define those sections of the waveform between rf pulses and data sampling intervals. These are the parameters to be optimized. In most cases, the timing, durations, and amplitudes of the other waveform sections (during rf and sampling) are predetermined by the sequence designer. That is, contrast, FOV, rf and sampling duration and bandwidth are fixed before the optimization of the remaining waveform sections. The exceptions to this are the objectives of FOV or slice thickness minimization, and echo time minimization. However, even in these cases, the rf and sampling durations and bandwidths are assumed to be fixed.

The objectives listed in Section 2.2.2 are treated as single objective functions in the implementation described here. However, in some cases, one or more of these objectives may be constrained to specific values while

another is optimized. For example, the first moment or velocity sensitivity may be fixed while RMS current is minimized. As discussed in Chapter 2, this may be considered as a simple type of multi-objective optimization.

Only those objectives and constraints which fit the linear or quadratic programming forms are solved by the optimization. Thus constraints on RMS current and gradient b factor are not implemented.

3.1.2 Implementation

The MATLAB (The MathWorks, Inc., Natick, MA) software package for 80386 based MS-DOS personal computers was used to solve the optimal waveform design problem. The MATLAB Optimization Toolbox includes an implementation of the active set-null space method described by Gill, Murray and Wright (83, 85) to solve QP problems, and a variation of the simplex method developed by Dantzig et al. (86) for linear programming. These MATLAB routines were incorporated into a program which takes input information about the objective, constraints, and waveform timing, constructs the vectors and matrices which define the LP or QP problem, and generates the optimal waveform. Computation time required for a single waveform averages about 30 seconds on a 33 MHz 80486 based personal computer

system. The resulting sets of point-by-point gradient amplitudes for a representative sample of objectives and constraints were ported via 9-track tape to a Picker Vista HPQ 1.5 Tesla imager for incorporation into new and existing pulse sequences. Some of these sequences together with example images are shown in this chapter.

The waveforms were generated with the gradient amplitude constraint set conservatively at 9.5 mT/m, and the slew constraint set at 6.67 mT/m/msec (1.5 msec "rise time"). Depending on the duration of the gradient waveform, the discrete waveform amplitudes were spaced at from 250 to 1000 microsecond intervals.

Several trade-offs were considered in determining the spacing of waveform sample points. Increasing the number of sample points (parameters) may increase waveform accuracy by reducing the discretization errors associated with the sample-and-hold operation of D/A converters. Unfortunately, a large number of parameters can render the optimization problem extremely difficult, or even impossible to solve due to computer memory limitations, and ill-conditioning of the problem. For this reason, sample spacing was selected to keep total number of parameters under 100; the MATLAB routines were found to handle this number of parameters in most cases.

Following optimization, the number of points in each

waveform was increased by linear interpolation to an effective sampling rate of 10 kHz. This was done to minimize discretization errors associated with sparse sample points. Linear interpolation preserves the accuracy of the trapezoidal integration estimates of waveform moment integrals, diffusion sensitivity, and RMS current estimates.

The interpolated waveform was passed through an eighth order Hamming window low-pass FIR filter with 3 dB cutoff set at half the original sampling rate. This was done to ensure that the bandwidth of the interpolated waveform remained consistent with the original Nyquist frequency. The amplitude values were scaled and rounded to 16-bit integer values for application to the gradient system via D/A converter.

The waveform area, from initial rf pulse to the echo, was constrained to zero for all slice-select and frequency-encoding waveforms to refocus static material and form an echo. Phase-encoding waveforms were designed for the maximum phase-encoding step and then scaled appropriately for all other views. When not maximized, the zero-th moments of the phase-encoding waveforms were constrained to values determined by FOV and resolution considerations. Higher moments of phase-encoding waveforms were computed using TE as the moment center as prescribed in (32,33).

3.2 Example Waveforms

Figures 3.1 - 3.12 show field echo and spin echo sequences with gradient waveforms designed to optimize various objectives. Tables 3.1 and 3.2 summarize the imaging conditions (rf pulse duration, sampling rate, etc.) which were held constant for all of the field echo and TE20 spin echo sequences shown. It is important to note that these conditions help to define the feasible solution space in the waveform optimization. These parameters are fixed by the pulse sequence designer prior to the waveform optimization. Changing any of these fixed parameters may affect the optimal solution. They are held constant throughout the following examples so that we may examine the affects of the optimization itself, with respect to different objective functions.

Tables 3.3 to 3.10 list some additional figures of merit for the waveforms shown. These tables are useful in evaluating the tradeoffs in waveform characteristics associated with each objective. Some example images formed using the optimized waveforms are shown in Section 3.4.

RF Pulse Duration	4 msec
RF Pulse Bandwidth	750 Hz
Sampling Duration	8.192 msec
Sampling Rate	125 KHz
FOV (if not minimized)	25 cm
Repetition Time	200 msec
Echo Time (if not minimized)	18 msec
Image Matrix Size	256x256

Table 3.1 Imaging conditions fixed by pulse sequence designer prior to optimization. These parameters are used in the field echo sequences shown throughout this chapter.

90° RF Pulse Duration	4 msec
180° RF Pulse Duration	4 msec
RF Pulse Bandwidth	563 Hz
Sampling Duration	12.288 msec
Sampling Rate	83.33 KHz
FOV (if not minimized)	20 cm
Repetition Time	200 msec
Echo Time	20 msec
Image Matrix Size	256x256

Table 3.2 Imaging conditions fixed by the pulse sequence designer prior to waveform optimization. These parameters are used in the TE20 spin echo sequences shown in this chapter

Figure Number	Sequence Type	Objective	ΔZ (mm)	Velocity Sens. (rad/cm/s)	Accel. Sens. (rad/cm/s ²)	Single Slice I _{rms} (mT/m)
3.1	FE 18	I _{RMS} Min	3.00	0.0	.1545x10 ⁻²	1.09 @ TR200
3.3	FE 18	Slew Min	3.00	0.0	.1599x10 ⁻²	1.15 @ TR200
3.6	FE 18	Acc Sens Min	3.00	0.0	.7784x10 ⁻³	1.69 @ TR200
3.8	FE 18	Resolution Max	1.53	0.0	.4214x10 ⁻²	2.21 @ TR200
3.10	FE 15.5	TE/Slew min	3.00	0.0	.5155x10 ⁻³	1.19 @ TR200

Table 3.3 Figures of merit for comparison of slice select waveforms of the field echo sequences shown in Figures 3.1, 3.3, 3.6, 3.8, and 3.10

Figure Number	Sequence Type	Objective	FOV (cm)	Velocity Sens. (rad/cm/s)	Accel. Sens. (rad/cm/s ²)	Single Slice I _{rms} (mT/m)
3.1	FE 18	I _{RMS} Min	25	0.0	.1149x10 ⁻²	1.11 @ TR200
3.3	FE 18	Slew Min	25	0.0	.1167x10 ⁻²	1.18 @ TR200
3.6	FE 18	Acc Sens Min	25	0.0	.7789x10 ⁻³	1.68 @ TR200
3.8	FE 18	Resolution Max	15	0.0	.2107x10 ⁻²	2.08 @ TR200
3.10	FE 15.5	TE/Slew Min	25	0.0	.8390x10 ⁻³	1.25 @ TR200

Table 3.4 Figures of merit for comparison of frequency encoding waveforms of the field echo sequences shown in Figures 3.1, 3.3, 3.6, 3.8, 3.10.

Figure Number	Sequence Type	Objective	FOV (cm)	Velocity Sens. (rad/cm/s)	Accel. Sens. (rad/cm/s ²)	Single Slice I _{rms} (mT/m)
3.1	FE 18	I _{RMS} Min	25	0.0	.2298x10 ⁻²	.91 @ TR200
3.3	FE 18	Slew Min	25	0.0	.2334x10 ⁻²	.99 @ TR200
3.6	FE 18	Acc Sens Min	25	0.0	.1558x10 ⁻²	1.54 @ TR200
3.8	FE 18	Resolution Max	15	0.0	.5300x10 ⁻²	1.75 @ TR200
3.10	FE 15.5	TE/Slew Min	25	0.0	.1215x10 ⁻²	1.18 @ TR200

88

Table 3.5 Figures of merit for comparison of phase encoding waveforms of the field echo sequences shown in Figures 3.1, 3.3, 3.6, 3.8, and 3.10. FOV specified for 256 steps. Motion sensitivity specified for maximum step.

Figure Number	Sequence Type	Objective	ΔZ (mm)	Velocity Sens. (rad/cm/s)	Accel. Sens. (rad/cm/s ²)	Single Slice I _{rms} (mT/m)
3.2	SE 20	I _{RMS} Min	5.00	.178	-	.6424 @ TR200
3.2	SE 20	I _{RMS} Min	5.00	0.0	.7459x10 ⁻³	.6852 @ TR200
3.4	SE 20	Slew Min	5.00	.226	-	.9764 @ TR200
3.4	SE 20	Slew Min	5.00	0.0	.7156x10 ⁻³	.7705 @ TR200
3.7	SE 20	Vel Sens Min	5.00	0.0	.3797x10 ⁻³	.7986 @ TR200
3.9	SE 20	Resolution Max	3.17	0.0	.1217x10 ⁻²	1.3282 @ TR200

Table 3.6 Figures of merit for comparison of slice select waveforms of the spin echo sequences shown in Figures 3.2, 3.4, 3.7, and 3.9.

Figure Number	Sequence Type	Objective	FOV (cm)	Velocity Sens. (rad/cm/s)	Single Slice I_{rms} (mT/m)
3.2	SE 20	I_{RMS} Min	20	.506	.9027 @ TR200
3.4	SE 20	Slew Min	20	.627	.0092 @ TR200
3.7	SE 20	Vel Sens Min	20	.496	1.3771 @ TR200
3.9	SE 20	Resolution Max	13	1.299	2.1969 @ TR200

Table 3.7 Figures of merit for comparison of frequency encoding waveforms of the spin echo sequences shown in Figures 3.2, 3.4, 3.7, and 3.9.

Figure Number	Sequence Type	Objective	FOV (cm)	Velocity Sens. (rad/cm/s)	Single Slice I _{rms} (mT/m)
3.2	SE 20	I _{RMS} Min	20	.603	.4582 @ TR200
3.4	SE 20	Slew Min	20	.603	.4901 @ TR200
3.7	SE 20	Vel Sens Min	20	.229	.9844 @ TR200
3.9	SE 20	Resolution Max	5	2.03	1.5674 @ TR200

Table 3.8 Figures of merit for comparison of phase encoding waveforms of the spin echo sequences shown in Figures 3.2, 3.4, 3.7, and 3.9. FOV specified for 256 steps. Motion sensitivity specified for maximum step.

3.2.1 RMS Current Minimized Waveforms

The FE18 field echo waveforms in Figures 3.1 and TE20 spin echo waveforms in Figure 3.2 were optimized with the objective of minimizing the RMS current in the waveform sections between rf pulses and data sampling. The imaging conditions described in Tables 3.1 and 3.2 were fixed for these sequences prior to optimization. Minimization of RMS current was done with the goal of reducing the severity of compromises, like number of slices per TR, in I_{RMS} limited sequences. RMS current values for these and all optimized waveforms shown in this chapter can be found in Tables 3.3 - 3.10. These current values were computed assuming single slice imaging and a 200 msec repetition time. RMS current is indicated in units of mT/m to avoid dependency on any specific gradient subsystem.

The FE18 velocity compensated, RMS current minimized waveforms in Figure 3.1 exhibit the triangular shape suggested by Wendt (61) to reduce energy dissipated in the gradient amplifier and coil system. In comparison to the acceleration sensitivity minimized waveforms shown in Figure 3.6, RMS current is reduced by 35%, 34%, and 41% for the slice select (SS), frequency encoding (FE), and phase encoding (PE) waveforms.

The SE20 spin echo sequence in Figure 3.2 shows two

different slice select waveforms: with and without velocity compensation. The uncompensated spin echo sequence demonstrates an even distribution of gradient amplitude over all available time to minimize RMS current. This is evidenced by the equal amplitude, positive and negative sections of the read and slice select waveforms in those portions of the waveforms not during data sampling and slice selection. In comparison to the velocity sensitivity minimized waveforms shown in Figure 3.7, RMS current is reduced by 20%, 34%, and 53% for the uncompensated slice select (SS), frequency encoding (FE), and phase encoding (PE) waveforms.

The frequency encoding waveform in Figure 3.2 may cause artifacts by forming a gradient echo from signal due to out of slice material. This effect can be controlled by constraining the area of the waveform after the 180° pulse to ensure any spurious echoes occur outside of the sampling window, or by a simple non-negativity constraint on waveform amplitude after the 180° pulse. This "spoiling" constraint is demonstrated in the TE80 sequence shown in the next section.

Figure 3.1 Velocity compensated field echo sequence (18 millisecond echo time) optimized for minimum RMS current. Triangular shaped lobes have been previously proposed to reduce total energy dissipation in the gradient system. Note that this and all motion compensated phase encoding waveforms shown are designed to eliminate misregistration artifacts by nulling moments about TE.

Figure 3.2 Spin echo sequence (20 millisecond echo time) optimized for minimum RMS current. Two slice select waveforms shown: with and without velocity compensation. Note the even distribution of gradient amplitude over time in the uncompensated waveforms.

3.2.2 Total Slew Minimized Waveforms

The minimum total slew optimization results in the FE18 waveforms shown in Figure 3.3 and the TE20 and TE80 waveforms in Figures 3.4 and 3.5. The imaging conditions of the FE18 and TE20 waveforms are again fixed at the values given in Table 3.1 and 3.2. Note the smooth variations in waveform amplitude. This smoothing effect can reduce the waveform bandwidth, and hence, reduce the frequency response characteristics of the gradient system required to meet specific imaging goals. While imaging performance improvements with slew minimization has not been demonstrated, the reduced bandwidth of these waveforms should result in more accurate waveform generation in a band-limited gradient system.

The TE80 spin echo sequence in Figure 3.5 is compensated through jerk (third moment) on the slice select axis, and through acceleration on the read and phase encode axes. The jerk-compensated TE80 slice-select waveform in Figure 3.5 demonstrates an additional advantage of the discrete amplitude parameter set. Conventional multi-lobe waveform design would require a six lobe waveform to achieve slice selection and third order motion (jerk) compensation.

Experience with this and other slew minimized sequences suggest that they may decrease audible gradient

noise. This can be an important factor in making MRI an acceptable procedure for some apprehensive patients.

The frequency encoding waveform in Figure 3.5 also demonstrates the gradient spoiling constraint. The area of the frequency encoding waveform between the 180° pulse and the echo is fixed to prevent any out-of-slice signal brought into the transverse plane by the 180° pulse from forming an echo within the sampling interval. This is done by constraining the area between the 180° pulse and the end of the sampling interval to be less than zero.

Figure 3.3 Velocity compensated field echo sequence (18 millisecond echo time) optimized for minimum sum of squared first-order differences (slew). This objective has been used as a penalty function in optimal rf pulse design to smooth the pulse shapes and narrow the bandwidth (66).

Figure 3.4 Spin echo sequence (20 millisecond echo time) optimized for minimum sum of squared first order differences (slew). Note the smooth, nearly sinusoidal shape of the waveforms.

Figure 3.5 Slew minimized spin echo sequence (80 millisecond echo time). Slice select gradient compensated through third order derivative of position (jerk); frequency and phase encoding waveforms compensated through acceleration. Area of the frequency encoding gradient after the 180° rf pulse is constrained to help spoil spurious echoes. It is worth noting that jerk compensation and slice selection are achieved with only four gradient lobes; an algebraic solution would require six lobes, possibly increasing audible gradient noise and susceptibility to eddy current distortion.

3.2.3 Minimum Motion Sensitivity Waveforms

The minimum second moment FE18 waveforms in Figure 3.6 demonstrate optimal compensation of acceleration. The TE20 spin echo waveforms in Figure 3.7 are velocity sensitivity minimized. Full compensation is not feasible under the specific imaging conditions (TE, BW, etc.) defined for these sequences in Tables 3.1 and 3.2. In comparison to the RMS current minimized sequences shown in Figures 3.1 and 3.2, sensitivity to acceleration was decreased by 50%, 32%, and 32% for the SS, FE, and PE waveforms of the field echo sequence. The velocity sensitivity of the FE and PE waveforms of the TE20 spin echo sequence decreased by 2% and 49%, respectively. Total velocity compensation was attained on the slice select axis; acceleration sensitivity was decreased by 49%.

Note the formation of an additional waveform lobe on each of the gradient axes. Optimization provides an advantage over algebraic design since the number, placement, and duration of waveform lobes need not be pre-determined. The optimization completely determines the feasible waveform shape required to attain maximum motion compensation. Note the unusual shape of the spin echo slice select, velocity sensitivity minimized waveform in Figure 3.7. This shape could not be determined by any of the conventional design techniques discussed in Chapter 1.

Figure 3.6 Velocity compensated field echo sequence (18 millisecond echo time) optimized for minimum sensitivity to acceleration. In this example, gradient system and time limitations preclude full compensation of the second order time moment. Optimization affords maximum motion compensation under fixed conditions of echo time, resolution, and bandwidth.

Figure 3.7 Spin echo sequence (20 millisecond echo time) optimized for minimum sensitivity to motion. In this example, gradient system and time limitations prevent full compensation of the first order time moment of the frequency and phase encoding waveforms, and of the second moment of the slice select waveform. Note the unusual shape of the slice select waveform, and the triangular lobes, ramping at maximum slew rate, of the frequency encoding waveform.

3.2.4 Maximum Resolution Waveforms

The sequences in Figures 3.8 and 3.9 exhibit maximum gradient amplitude during rf excitation and data acquisition, and maximum phase encode gradient area. The design objective is to maximize resolution under the fixed conditions of rf and sampling durations and bandwidths given in Tables 3.1 and 3.2, and under the constraints of the gradient system.

Under the specified conditions, minimum slice thickness of 1.53 mm and minimum FOV of 15 cm was obtained for the FE18 field echo sequence; minimum slice thickness of 3.17 mm and FOV of 5 cm in the PE direction and 13 cm in the FE direction were obtained for the TE20 spin echo sequence. Higher resolution would be possible by altering rf and sampling duration and bandwidth.

Figure 3.8 Velocity compensated field echo sequence (18 millisecond echo time) optimized for minimum FOV and slice thickness (maximum resolution). Note that the slice select rephasing and frequency encoding dephasing lobes are at the slew and amplitude limits of the gradient system.

Figure 3.9 Spin echo sequence (20 millisecond echo time) optimized for minimum FOV and slice thickness. Note the use of all available time to achieve maximum gradient amplitude during slice select and data sampling.

3.2.5 Echo Time Minimized Waveforms

Figure 3.10 shows a velocity compensated field echo sequence designed for minimum RMS current with TE iteratively reduced to the minimum feasible value of 15.5 msec. This echo time was achieved by decrementing TE from 18 msec in steps of .5 msec, while maintaining resolution and bandwidth, until a feasible solution could not be found.

No attempt was made to modify the rf pulse or sampling rate, duration, or symmetry to attain shorter echo times; these parameters were again held constant at the values listed in Table 3.1. The phase encode gradient limited the minimum echo time to 15.5 msec. A shorter echo time could be attained if velocity compensation was removed from the PE waveform, or if the rf pulse or data sampling durations were shortened.

Figure 3.10 Velocity compensated field echo sequence (15.5 millisecond echo time) optimized from minimum total slew with simultaneous iterative minimization of echo time. TE was decremented in .5 msec steps from 18 msec down to 15.5 msec. A phase encoding waveform with the desired characteristics could not be generated at shorter echo times due to system and imaging constraints (see Table 3.1).

3.2.6 Diffusion Sensitivity Maximized Waveforms

Diffusion imaging pulse sequences are intentionally made sensitive to microscopic, random motion, typically by the addition of high amplitude pulses to the gradient waveforms. Unfortunately, this sensitivity to microscopic motion also renders diffusion sequences sensitive to macroscopic "coherent" motion (flow, tissue pulsation, gross patient motion, etc.) as well (25). This sensitivity to coherent motion has hindered clinical application of diffusion imaging techniques (25).

First order moment compensation can be utilized in diffusion imaging sequences, but severely limits the attainable diffusion sensitivity (gradient b factor). Optimization provides a means of incorporating gradient moment nulling while maximizing diffusion sensitivity.

Figures 3.11 and 3.12 show spin-echo ($TE = 120$ msec) slice select and frequency encoding waveforms sensitized to diffusion by maximizing the gradient b factor both with (Figure 3.12), and without (Figure 3.11) velocity compensation to reduce sensitivity to coherent motion. The imaging conditions specified for these sequences are listed in Table 3.9.

The b values obtainable (see Tables 3.10 and 3.11) are closely tied to the gradient subsystem hardware limitations. Diffusion sensitivity scales as approximately

the square of the maximum gradient amplitude provided maximum slew is increased proportionately. The velocity compensated, diffusion sensitive waveforms in Figure 3.12 are similar to the bipolar gradients proposed in (88) to measure diffusion coefficients in the presence of bulk motion. Even with optimization, velocity compensation severely attenuates diffusion sensitivity, in this example by 79% in the SS waveform and 85% in the FE waveform.

Figure 3.11 Diffusion sensitivity (b factor) maximized spin echo sequence (120 millisecond echo time). Optimization provides maximum diffusion sensitivity possible under gradient system limits and echo time, resolution, and bandwidth considerations, as well as smooth transitions from "diffusion" lobes to slice selection and frequency encoding lobes.

Figure 3.12 Diffusion sensitivity (b factor) maximized, velocity compensated spin echo sequence (120 millisecond echo time). Velocity compensation reduces sensitivity to coherent motion, but severely restricts diffusion sensitivity obtainable.

Figure Number	Sequence Type	Objective	ΔZ (mm)	Velocity Sens. (rad/cm/s)	Accel. Sens. (rad/cm/s ²)	Single Slice I rms (mT/m)	<i>b</i> factor (sec/mm ²)
3.5	SE 80	Slew Min	3.00	0.0	0.0	.924 @ TR2000	-
3.11	SE 120	<i>b</i> Max	3.00	52.89	-	1.89 @ TR2000	362.77
3.12	SE 120	<i>b</i> Max	3.00	0.0	.7312	1.84 @ TR2000	74.55

Table 3.9 Figures of merit for comparison of spin echo slice select waveforms shown in Figures 3.5, 3.11, and 3.12.

Figure Number	Sequence Type	Objective	FOV (cm)	Velocity Sens. (r/cm/s)	Accel. Sens. (r/cm/s ²)	SSingle Slice Irms (mT/m)	b factor (sec/mm ²)
3.5	SE 80	Slew Min	25	0.0	0.0	.805 @ TR2000	-
3.11	SE 120	b Max	25	66.32	-	1.87 @ TR2000	539.98
3.12	SE 120	b Max	25	0.0	.7137	1.75 @ TR2000	77.13

Table 3.10 Figures of merit for comparison of spin echo frequency encoding waveforms shown in Figures 3.5, 3.11, and 3.12.

3.3 Waveform Comparisons

Tables 3.1 to 3.10 facilitate examination of the tradeoffs required to optimize each objective function. It is evident from these tables that optimization of any single objective usually results in less than optimal values for all other design objectives. Minimization of RMS current, FOV or slice thickness, and motion sensitivity are all competing objectives within the constrained parameter space.

Some examples of these tradeoffs are evident in Tables 3.3 - 3.8 describing the field echo and TE20 spin echo sequences shown in the previous section. Looking at RMS current (the last column of each table), we see that minimization of I_{RMS} always results in the lowest current for the specified imaging conditions. Minimization of slew, motion sensitivity, and voxel size are all done at the expense of higher than optimal RMS current. The same trend is evident in motion sensitivity (acceleration sensitivity in the field echo and velocity sensitivity in the spin echo sequences).

Two objectives which appear from Tables 3.3 to 3.5 to be complementary are echo time minimization and motion sensitivity minimization. The last row of each of these tables which lists the characteristics of the TE minimized

sequence shows that the 15.5 msec SS and PE waveforms have less phase sensitivity to acceleration than the second moment minimized FE18 sequence. A shortened echo time in itself helps to reduce motion sensitivity. However, complete moment compensation requires time, and hence competes with echo time minimization. A waveform with constrained motion sensitivity will, in general, require a longer minimum echo time than one with no fixed motion sensitivity. Also, altering TE to control motion sensitivity will change the contrast characteristics of the sequence.

Generally, optimization of any of the design goals discussed requires gradient amplitude and time. Since a finite amount of these quantities is available for any given waveform, the optimization essentially decides how to distribute them to optimize the stated objective.

3.4 Imaging Examples

Some of the sequences shown in the prior section, as well as other optimal waveforms, were used to generate the images presented in this section. Phantom and human images are shown to demonstrate some of the benefits of waveform optimization, and to examine some of the tradeoffs required to optimize each objective.

3.4.1 FE18 RMS Current Minimization

The FE18 sequences shown in Figures 3.1, 3.3, and 3.6, optimized for minimum I_{rms} , minimum total slew, and minimum acceleration sensitivity respectively, were used to image a composite phantom to examine some possible advantages of RMS current minimization.

The frequency encoding and slice select gradient waveforms were scaled to attain the same RMS current levels for each objective to determine the tradeoffs in FOV and slice thickness. The results are summarized in Table 3.11. The RMS current minimized sequence generated a FOV 14% smaller than the slew min sequence and 30% smaller than the acceleration sensitivity minimized sequence at the same RMS current level. Slice thickness was also decreased by 13% and 35%, respectively. Phantom images generated using the three sequences are shown in Figure 3.13. Note the increased signal intensity in the images with thicker slices due to increased voxel size.

Figure 3.13 Images of a resolution phantom generated using (A) Irms minimized, (B) total slew minimized, and (C) acceleration sensitivity minimized FE18 sequences depicted in Figures 3.1, 3.3, and 3.6. FOV and slice thickness adjusted for each sequence to run at the same RMS current. RMS current minimized sequence can attain thinner slices, and smaller FOV at the same current level as the other waveforms. Results are summarized in Table 3.9.

Corresponding Image	Objective	Slice Select Irms (amps)	Freq. Enc. Irms (amps)	ΔZ (mm)	FOV (cm)
Fig. 3.13a	Irms Min	42.0	40.5	4	30
Fig 3.13b	Slew Min	42.1	40.4	4.6	35
Fig 3.13c	Acc Min	42.0	40.3	6.1	43

Table 3.11 Slice thickness and FOV obtained for identical RMS current levels using sequences designed with three different objectives. Minimization of RMS current can also be used to run sequences at shorter repeat times or with more slices.

3.4.2 Optimal Moment Compensation

An example of minimizing motion sensitivity by optimal waveform design is shown in the sequence of images in Figure 3.14. In this case, the frequency encoding, slice select, and phase encoding waveforms of a TE14 gradient echo sequence were designed for minimum first moment. The velocity sensitivity plots in Figure 3.15 indicate that only partial velocity compensation is attainable at this echo time for the given gradient system and imaging conditions listed in Table 3.1. The optimal sequence was utilized to obtain axial images of the cervical spine of a volunteer to compare to TE14 sequences optimized for I_{RMS} , total slew, and resolution with no moment compensation.

The images in Figure 3.14a, 3.14b, and 3.14d generated with RMS current, slew, and voxel size minimized TE14 sequences respectively, show significant loss of signal in the vessels of the neck and splattering of this signal across the image in the phase encode direction (horizontally). The image in Figure 3.14c using the first moment minimized sequence, shows more signal in the vessels and less splatter and ghosting.

Signal to artifact noise was used to measure these apparent changes in sensitivity to motion. The mean pixel value within the left jugular was used as a measure of signal intensity; the standard deviation (std) of pixel

intensity in a region lying outside the neck, horizontally along the phase encoded axis in line with the left internal jugular was used as a measure of artifact noise std. Table 3.12 summarizes the resulting changes in signal intensity in the left internal jugular in Figures 3.14a-c.

The dominant component of motion within the jugular is probably along the slice select gradient axis in these images. Thus, the relative velocity sensitivities of the slice select waveforms should closely parallel the S/N ratios listed in Table 3.12. The resolution maximized image deviates slightly from this expected trend, probably since the regions used to measure signal and noise were of different size and location in these images, due to the change in FOV from 30 cm to 20 cm.

The point of this demonstration is not to prove that moment nulling works as a means of motion artifact reduction. That has been accepted for several years. The point is to show that the optimal design approach guarantees maximum compensation will be attained if that is the waveform design goal. It also provides the means of knowing exactly how much compensation can be attained under fixed conditions of echo time, resolution, and bandwidth.

Figure 3.14 Axial images of the cervical spine. Image (A) generated with RMS current minimized FE14 sequence, image (B) generated with slew minimized FE14 sequence, image (C) generated with first moment minimized FE14 sequence, image (D) generated with resolution maximized FE14 sequence.

Image	Objective	V. Sens. (SS) (r/cm/s)	V. Sens. (FE) (r/cm/s)	V. Sens. (PE) (r/cm/s)	Signal	Artifact	Sig/Art Ratio
3.14a	I _{RMS}	.1643	.2216	.1649	845.1	140.7	6.0
3.14b	Slew	.1930	.2421	.1649	857.3	165.0	5.2
3.14c	V Sens	.0248	.0667	.0717	2116.4	88.7	23.8
3.14d	FOV	.1782	.3113	.3267	538.5	70.4	7.6

Table 3.12

Summary of differences in signal intensity and artifact level in axial C-Spine images shown in Figure 3.14. Signal measured as average intensity within left internal jugular. Artifact measured as standard deviation within area of ghosting adjacent to neck. Minimization of velocity sensitivity objective increases signal intensity in jugular and decreases flow artifact.

3.4.3 Echo Time Minimization

Gradient moment nulling and echo time reduction are two techniques commonly used to reduce motion artifacts in MRI. Moment nulling is done to cancel specific gradient waveform time moments; shortening TE reduces motion sensitivity by an implicit reduction of all time moments with decreased waveform duration (79,80,81). TE reduction directly affects image contrast. Alternately, TE may be extended to incorporate moment nulling, in which case contrast is affected and sensitivity to uncompensated, higher orders of motion increases. A decision must often be made whether to reduce TE, or to attempt moment nulling to reduce motion sensitivity.

Minimization of the first waveform time moment results in optimal insensitivity to velocity at all feasible echo times. Field echo sequences were generated for three different echo times (10, 14, and 18 msec) to investigate the tradeoffs between echo time, velocity sensitivity, and flow artifacts. The same imaging conditions (FOV, BW, etc.) listed in Table 3.1 and used in the design of the field echo sequences in Section 3.2 were held constant for all three echo times. At TE 18, full velocity compensation is feasible, at TE 14, only partial compensation, and at TE 10, no compensation. Shorter echo times with less motion sensitivity would be attainable if the fixed imaging

conditions were modified. For example, using a shorter rf pulse, or a shorter sampling interval may allow shorter echo times, at the expense of slice profile and signal to noise.

Velocity sensitivity of the frequency encode and slice select waveforms as a function of echo time (under fixed conditions of resolution and rf and sampling bandwidth) are plotted in Figure 3.15. In each figure, the upper curve defines velocity sensitivity with no moment nulling, the lower curve with minimization of first moment. These graphs indicate that at any echo time above the minimum feasible for a given set of imaging and gradient system parameters, at least partial moment compensation is attainable. Optimization provides the means of obtaining the maximum compensation possible.

Axial images of the cervical spine at the three echo times are shown in Figure 3.16. The images show relative levels of artifact (ghosting), loss of signal intensity, and corresponding drop in signal to artifact noise ratio due to flow in the carotid arteries which qualitatively agree with the predicted velocity sensitivities of the waveforms. Flow artifact is more apparent in the TE 10 image with no compensation than in the TE 14 image with partial compensation, or the TE 18 image with full velocity compensation. The changes in signal intensity in the

internal jugular with echo time and level of motion compensation were quantified by the same measurement described in Section 3.4.2. These results are summarized in Table 3.13.

Optimization provides the ability to achieve maximum motion compensation at a given echo time under limited gradient amplitude and slew capabilities. These images indicate that even partial compensation can help reduce motion artifacts.

Image	3.16a	3.16b	3.16c
Echo Time	18	14.5	10
SS Vsens	0.	.0248	.0971
FE Vsens	0.	.0667	.1442
PE Vsens	0.	.0717	.1266
Signal	2404.1	2116.4	1170.0
Artifact	75.0	88.7	57.5
Sig/Art	32.1	23.8	20.3

Table 3.13 Summary of differences in signal intensity and artifact level in axial C-spine images shown in Figure 3.16. Signal measured as average intensity within left internal jugular. Artifact measured as average intensity within area of ghosting adjacent to neck.

Velocity Sensitivity Slice Select

Velocity Sensitivity Read

Figure 3.15 Velocity sensitivity of minimum slew (uncompensated) and minimum first moment slice select (a) and frequency encoding (b) waveforms are plotted vs. echo time. Velocity sensitivity monotonically decreases with decreasing TE for the uncompensated waveforms. Velocity sensitivity was lower with first moment minimization at all feasible echo times. The sensitivity curves for compensated and uncompensated waveforms meet at the minimum TE feasible for the given gradient system and resolution and bandwidth considerations.

Figure 3.16 Axial images of the cervical spine. Image (A) generated with FE10, uncompensated field echo sequence. Image (B) generated with velocity sensitivity minimized FE14 sequence. Image (C) generated with FE18 sequence with full velocity compensation on all axes.

3.4.4 Minimum FOV Catheter Coil Images

An intravascular catheter receiver coil is under development at the MetroHealth Medical Center Radiology Department (89). The goal of this project is to depict structures within the wall of human arteries. The intravascular probe is used in an effort to solve the problems of poor S/N and image aliasing associated with the small field of view (high resolution) required to image the structures of interest.

Gradient waveform design for this application poses some special problems. The main design goals are extremely small FOV (2 cm) and minimum motion sensitivity in a T2 weighted (long TE, long TR) spin-echo sequence. A 2 cm FOV requires a high amplitude gradient and long duration data acquisition. These factors can make moment compensation of the frequency encoding gradient a difficult matter.

The required imaging conditions outlined in Table 3.14 were defined prior to waveform optimization. Asymmetric sampling ($f = .5$) (90) was employed to obtain a 2 cm FOV with the specified gradient system constraints and full velocity compensation of the SS and FE axes at a 60 msec echo time. The level of asymmetry was chosen such that standard Fourier reconstruction could be used without significant loss of signal-to-noise (90). Only partial compensation of the phase encoding waveform was attainable

under these conditions.

The resulting sequence is shown in Figure 3.17. An axial view of the femoral artery of a live dog generated with this TE60 sequence is shown in Figure 3.18.

Figure 3.17 TE60 sequence generated for high resolution imaging with intravascular catheter receiver coil. 2 cm FOV with velocity compensation in slice select and frequency encoding directions and partial compensation in phase encoding direction attained by optimization. Asymmetric sampling used to provide additional time for compensation.

Figure 3.18 Axial image of the femoral artery of a dog generated using intravascular catheter receiver coil and sequence shown in Figure 3.17.

3.5 Discussion

The waveforms and images presented in this chapter exhibit just some of the possible uses of the optimal design technique. Waveforms for virtually any type of imaging pulse sequence should benefit from optimal design. Additional design objectives and constraints may prove useful in the future. The unusual shapes exhibited by some of the example waveforms suggest that, in many cases, conventional design approaches may be far from optimal for the specific objectives considered here.

In spite of the tradeoffs required in waveform characteristics to optimize specific objectives, the optimal design technique should help to make gradient waveform design less of an art and more of a science. Manual determination of the duration, placement, and amplitude of gradient lobes for spoiling or motion compensation is eliminated with results which are guaranteed to be optimal and feasible for the stated design goals and constraints.

Gradient hardware characteristics like peak gradient amplitude, maximum slew rate, maximum RMS current, and gradient system frequency response are constraints which are easily changed to use this technique on any MR imaging system. Additionally, these constraints can be increased to help predict future gradient system characteristics

required to meet specific imaging goals. This is explored in the next chapter.

4. Gradient System Simulations

4.1 Introduction

Gradient system performance is probably the single most important factor limiting MR imaging performance. Faster switching, and more powerful gradients can provide faster imaging times, more and thinner slices, greater levels of motion compensation at short echo times, and smaller fields of view. While optimization provides the maximum performance from a limited gradient system, the optimal design protocol also affords the opportunity to investigate potential imaging improvements attainable with refinements to gradient system hardware. Since the gradient hardware limitations are incorporated as constraints in the optimization, it is a simple matter to vary them to simulate any existing or theoretical gradient systems. This chapter will explore the use of the gradient waveform optimization technique developed in Chapter 2 in determining the imaging performance to be expected from alternative gradient systems. The constraints on amplitude and slew will also be removed and waveforms generated by optimization to determine the gradient capabilities required to meet specific imaging goals.

4.2 Waveform Generation with Improved Gradient System.

A gradient system was simulated with amplitude and

slew limits approximately double those of the system used to generate the waveforms in Chapter 3 to investigate potential improvements in imaging performance. The gradient amplitude limit was set at ± 2.0 G/cm and slew limits at ± 2.0 G/cm/msec. These limits are not unreasonable and will probably be attainable with the next generation of commercial gradient system hardware.

To compare with some of the field-echo sequences of the previous section (Figures 3.6, 3.8, 3.10), three sequences were generated with the new constraint set: (1) an 18 msec echo, 25 cm FOV, 3 mm slice thickness, acceleration compensated, slew minimized sequence; (2) an 18 msec echo time, 6 cm FOV, .7 mm slice thickness, velocity compensated read and slice, resolution maximized sequence; and (3) an 11.5 msec echo time, 25 cm FOV, 3 mm slice thickness, velocity compensated, echo time/ I_{RMS} minimized sequence. These sequences are shown in Figures 4.1 - 4.3, respectively. Tables 4.1 - 4.3 list some figures of merit for these waveforms.

The predetermined imaging conditions (FOV, RF duration and bandwidth, etc.) used in the field echo waveforms of Chapter 3 were again fixed at the values listed in Table 3.1. This was done to facilitate a comparison of the effects of the increased gradient system capability on the

optimized waveform sections.

The slew minimized sequence in Figure 4.1 can be compared with the acceleration sensitivity minimized sequence in Figure 3.6. Full compensation of acceleration is attainable with the improved gradient system constraints at the 18 msec echo time. Only partial compensation was possible under the original constraints of .95 G/cm and .667 G/cm/msec with identical resolution, sampling and rf bandwidth and duration.

The resolution maximized sequence in Figure 4.2 can be compared to the resolution maximized sequence in Figure 3.8. A FOV of 6 cm and slice thickness of .7 mm are attainable with the improved gradient system constraints. Minimum FOV under the original constraint set was 15 cm and minimum slice thickness of 1.5 mm under identical imaging conditions. These gains in resolution are based solely on the increase in gradient amplitude during rf excitation and data sampling. All other factors are the same between the two sequences.

The TE minimized sequence in Figure 4.3 can be compared to the TE minimized sequence in Figure 3.10. An echo time of 11.5 msec is attainable with the improved gradient system constraints. Minimum echo time under the original constraint set was 15.5 msec under identical conditions of resolution, bandwidth, and motion

compensation. Shorter echo times could be achieved by reducing the duration of the rf pulse and data sampling interval, asymmetric sampling of the signal echo, and/or reduction in motion compensation requirements.

This simulation points out some of the benefits to be expected from a theoretical next generation of gradient hardware. Significant decreases in echo time, FOV, slice thickness, and motion sensitivity can be attained with a factor of 2 gain in gradient amplitude, and a factor of 3 increase in slew rate. Tables 4.1 - 4.3 also indicate that an approximate doubling of RMS current capabilities (measured in mT/m) is required to generate these waveforms. Actual current requirements (amps) would depend on the amplifier system and coil efficiency.

Figure 4.1 Acceleration compensated FE18 field echo sequence optimized for minimum total slew under 2 G/cm amplitude and 2 G/cm/msec slew constraints. See Table 4.1 for sequence parameters.

GRAD AXIS	TE (msec)	OBJ	RFBW (hz)	ΔZ (mm)	Δt (μ sec)	FOV (cm)	MOTION COMP	I _{rms} (mT/m)	G _{max} (G/cm)	dG _{max} (G/cm/ms)
SLICE	18	SLEW	613	3	-	-	ACC	1.61	1.25	1.32
FREQ	18	SLEW	-	-	32	25	ACC	2.49	1.83	1.69
PHASE	18	I _{rms}	-	-	-	25	ACC	2.98	2.00	2.00

Table 4.1 Figures of merit for gradient echo sequence shown in Figure 4.1. Sequence designed for full acceleration compensation using 2 G/cm, 2 G/cm/msec constraints.

Figure 4.2 Velocity compensated FE18 field echo sequence optimized for maximum resolution under 2 G/cm amplitude and 2 G/cm/msec slew constraints. See Table 4.2 for sequence parameters.

GRAD AXIS	TE (msec)	OBJ	RFBW (hz)	ΔZ (mm)	Δt (μ sec)	FOV (cm)	MOTION COMP	I _{rms} (mT/m)	G _{max} (G/cm)	dG _{max} (G/cm/ms)
SLICE	18	ΔZ	613	.7	-	-	VEL	4.81	2.00	2.00
FREQ	18	FOV	-	-	32	6	VEL	4.90	2.00	2.00
PHASE	18	I _{rms}	-	-	-	6	-	1.09	.50	.47

Table 4.2 Figures of merit for gradient echo sequence shown in Figure 4.2. Sequence designed for minimum FOV using 2 G/cm, 2 G/cm/msec constraints.

Figure 4.3 Velocity compensated FE11.5 field echo sequence iteratively optimized for minimum echo time. Simultaneous minimization of RMS current under 2 G/cm amplitude and 2 G/cm/msec slew constraints. See Table 4.3 for sequence parameters.

GRAD AXIS	TE (msec)	OBJ	RFBW (hz)	ΔZ (mm)	Δt (μ sec)	FOV (cm)	MOTION COMP	Irms (mT/m)	Gmax (G/cm)	dGmax (G/cm/ms)
SLICE	11.5	Irms	613	3	-	-	VEL	1.36	1.54	2.00
FREQ	11.5	TE (Irms)	-	-	32	25	VEL	1.86	1.71	2.00
PHASE	11.5	TE (Irms)	-	-	-	25	VEL	2.24	2.0	2.0

Table 4.3 Figures of merit for gradient echo sequence shown in Figure 4.3. Sequence designed for minimum echo time using 2 G/cm, 2 G/cm/msec constraints. TE iteratively decremented in .5 msec steps while minimizing Irms at each step.

4.3 Unconstrained Waveform Generation

By completely removing the amplitude and slew constraints, the optimal design protocol can be utilized to investigate the gradient performance required to attain specific imaging goals. That is, the optimization can be run to find the amplitude, slew, and current requirements of waveforms which meet specific imaging requirements. Three sequences were generated without constraints on amplitude and slew: (1) an 18 msec echo time, 2 cm FOV, .8 mm slice thickness, uncompensated, slew minimized sequence, (2) an 18 msec echo time, 10 cm FOV, 1 mm slice thickness, acceleration compensated, slew minimized sequence; and (3) a 5 msec echo time, 25 cm FOV, 3 mm slice thickness, velocity compensated, I_{RMS} minimized sequence. These sequences are shown in Figures 4.4 - 4.6, respectively. Tables 4.4 - 4.6 list some figures of merit for these waveforms. The rf pulse and data sampling durations and bandwidths were again fixed at the values listed in Table 3.1.

The sequence in Figure 4.4 was generated to investigate the hardware specifications needed to produce the extremely high resolution sequences required for intra-vascular imaging by catheter receiver coil (89). The high amplitude of the frequency encoding gradient (3.67 G/cm)

could be alleviated some by decreasing the sampling rate, and using asymmetric sampling to avoid lengthening the echo time. This strategy was employed in the TE60 catheter coil sequence discussed in Chapter 3 to obtain a 2 cm FOV under conservative gradient system constraints.

The sequence in Figure 4.5 was designed to examine the hardware requirements for a fairly high resolution, acceleration compensated gradient echo sequence. This type of sequence may be used with surface coils for imaging of the joints and extremities. A high price is paid in gradient amplitude (6 G/cm) and slew (5 G/cm/msec) to achieve this level of motion compensation and resolution.

The short echo time, velocity compensated sequence in Figure 4.6 may be used in time-of-flight MR angiography. This type of sequence requires extremely fast gradient switching times as evidenced by the slew rates on the order of 16 G/cm/msec listed in Table 4.4 - 4.6. These rapid switching times would generate a field rate of change on the order of 20 T/sec at the edges of a 25 cm FOV. For sinusoidal gradient waveforms, rates of 60 T/sec have been shown to consistently cause sensations of electric shock(91). The threshold may be different for non-sinusoidal waveforms like those in Figure 4.6. Safety factors become even more important at high gradient amplitudes and slew rates and may be the ultimate limiting

factor as hardware improves.

Figure 4.4 FE 18 field echo sequence designed for 2 cm FOV without constraints on amplitude and slew. Slice select gradient velocity compensated. See Table 4.4 for sequence parameters.

GRAD AXIS	TE (msec)	OBJ	RFBW (hz)	ΔZ (mm)	Δt (μ sec)	FOV (cm)	MOTION COMP	Irms (mT/m)	Gmax (G/cm)	dGmax (G/cm/ms)
SLICE	18	SLEW	613	1	-	-	VEL	3.49	1.93	1.73
FREQ	18	SLEW	-	-	32	2	-	9.81	3.67	2.02
PHASE	18	SLEW	-	-	-	2	-	3.53	2.08	.64

Table 4.4 Figures of merit for gradient echo sequence shown in Figure 4.4. Sequence designed for 2 cm FOV without constraints on amplitude and slew. Velocity compensation included in slice select gradient.

Figure 4.5 Acceleration compensated field echo sequence designed for 10 cm FOV without constraints on amplitude and slew. See Table 4.5 for sequence parameters.

GRAD AXIS	TE (msec)	OBJ	RFBW (hz)	ΔZ (mm)	Δt (μ sec)	FOV (cm)	MOTION COMP	I _{rms} (mT/m)	G _{max} (G/cm)	dG _{max} (G/cm/ms)
SLICE	18	SLEW	613	1	-	-	ACC	5.30	3.74	3.95
FREQ	18	SLEW	-	-	32	10	ACC	6.40	4.57	4.23
PHASE	18	SLEW	-	-	-	10	ACC	8.80	5.98	4.99

Table 4.5 Figures of merit for gradient echo sequence shown in Figure 4.5. Sequence designed for 10 cm FOV with acceleration compensation on all axes without constraints on amplitude and slew.

Figure 4.6 Velocity compensated field echo sequence designed for 5 msec echo time without constraints on amplitude and slew. See Table 4.6 for sequence parameters.

GRAD AXIS	TE (msec)	OBJ	RFBW (hz)	ΔZ (mm)	Δt (μ sec)	FOV (cm)	MOTION COMP	I _{rms} (mT/m)	G _{max} (G/cm)	dG _{max} (G/cm/ms)
SLICE	5	I _{rms}	613	3	-	-	VEL	2.57	4.50	12.92
FREQ	5	I _{rms}	-	-	8	25	VEL	3.07	5.20	16.36
PHASE	5	I _{rms}	-	-	-	25	VEL	3.12	5.56	14.57

Table 4.6 Figures of merit for gradient echo sequence shown in Figure 4.6. Sequence designed for 5 msec echo time with velocity compensation on all axes without constraints on amplitude and slew. Note prohibitively high slew rate required to achieve this short echo time.

5. The Theoretical Significance of the Point of Expansion in the Interpretation of Gradient Moments and Motion Sensitivity

5.1 Introduction

Spin groups moving in the presence of a magnetic field gradient acquire a net phase shift relative to stationary spins. The Taylor Series expansion is often used to describe the motion of spins and to express motion sensitivity in terms of gradient waveform time moments. Gradient waveforms are commonly designed based on this expression of motion sensitivity with goals of reducing motion artifacts (30,48,42,57) or phase encoding specific derivatives of position (41,28,92,93) (position, velocity, acceleration, etc.).

The goal of gradient moment nulling (GMN) varies with gradient axis. In the read direction, the goal is to force the nonlinear phase trajectory of moving spins to cross zero at $k_x = 0$. In the slice direction, GMN brings the phase of moving spins back to zero after slice selection. In the PE direction, the goal of GMN is to make the phase linearly proportional to instantaneous position, independent of motion.

One of the objectives in optimal waveform design:

minimization of motion sensitivity, served as the original motivation for much of the work presented in this thesis. While investigating methods of minimizing dephasing due to multiple derivatives of position (velocity, acceleration, jerk, etc.), it became apparent that the choice of moment center, or expansion point of the Taylor series description of motion, takes on an importance in waveform design which has not been recognized.

Descriptions of moment nulling and motion phase-encoding techniques often refer to the gradient waveform time moments as the phase sensitivity to the corresponding derivatives of position (41,92,93); the first moment corresponding to sensitivity to velocity, the second moment to sensitivity to acceleration, and so on. Specific claims that the Field Even Echo Refocussing (FEER) gradient waveform is insensitive to all odd order derivatives of position (93,94,95,96) and the use of moment nulling in phase encoding waveforms (36,97,98), indicate that the relationship between gradient waveform time moments and motion sensitivity requires clarification. Furthermore, to use the optimal waveform design procedure, presented in Chapter 2, to design waveforms which minimize dephasing due to particular types of motion, a complete understanding of waveform moments and motion sensitivity is required.

In this chapter, the relationship between magnetic

field gradient waveform time moments, the moment center or expansion point, and the motion sensitivity of MRI is explored analytically, by computer simulation, and by phantom and human imaging experiments. This investigation reveals several key points. In general, waveform time moments define sensitivity to the time derivatives of position of moving material only at a single point in time: the time about which the moments are computed. A Taylor's Series description of instantaneous position is expanded about this same point in time to compute the phase acquired due to specific derivatives of position. A moment is proportional to phase sensitivity to a particular derivative of position throughout the waveform only when sensitivity to all lower order derivatives is zero. The choice of the moment center or point of expansion adds a degree of freedom which may be used advantageously in the design of motion compensating and motion encoding gradient waveforms.

These principles enable: (a) elimination of misregistration artifacts by design of phase-encoding waveforms which encode the position of spins at the echo time, independent of motion; (b) encoding of instantaneous derivatives of position independent of higher order derivatives; and (c) elimination of blurring due to motion in the phase encoded direction in Echo Planar Imaging

(EPI). These applications are demonstrated by simulation and/or phantom and human images.

5.2 Theory

The motivation for the design of motion compensating gradient waveforms (30,48,42,57) is the desire to make the phase shift of moving isochromats equal to that of stationary isochromats at the time of the echo (TE). Under this condition, the streaking artifacts in two and three dimensional Fourier transform images which arise from irregular motion can be reduced or eliminated.

An isochromat moving parallel to the direction of a time-varying magnetic field gradient $G(\tau)$ will accumulate a phase shift described by the integral equation

$$\phi(t) = \int_{t_0}^t \gamma G(\tau) x(\tau) d\tau \quad [5.1]$$

where $x(\tau)$ is the time varying position of the moving isochromat. Assuming that the phase coherence of the transverse magnetization is negligible just prior to the initiation of each acquisition cycle (TR interval), the phase and amplitude of the net magnetization vector begins with the initial rf excitation pulse of a given acquisition cycle. This will be defined as the time origin t_0 . It is assumed that no steady state component of transverse

magnetization is carried over from previous cycles, and thus the phase evolution for each TR cycle can be considered independent of all others.

Equation 5.1 is usually evaluated at the echo ($t = TE$) where the result indicates the phase shift of the dominant $k_x = 0$ or dc spatial frequency component of the image. Phase is measured relative to the linear phase trajectory expected for stationary isochromats in a constant field gradient. In general, isochromats moving along a constant linear field gradient will exhibit a nonlinearly varying phase as a function of time (41,28,27).

It is customary when considering continuously differentiable motion to expand the instantaneous position in a Taylor series. Taylor's theorem states (99) that if a function $x(t)$ and its first n derivatives $x^{(k)}(t)$, $k = 1, 2, \dots, n$, are continuous on an interval containing the points t and t' , then $x(t)$ has the following expansion into a polynomial of order n and variable $(t - t')$:

$$x_n(t-t') = x(t') + \sum_{k=1}^n \frac{x^{(k)}(t')}{k!} (t - t')^k + R_n, \quad [5.2]$$

where the remainder after n terms is

$$R_n = \int_{t'}^t (t-\tau)^n x^{(n+1)}(\tau) / n! d\tau \quad . \quad [5.3]$$

Here $x^{(k)}(t')$ represents the k th time derivative of $x(t)$ evaluated at t' . The first three derivatives of position are known commonly as velocity, acceleration, and jerk. Jerk has occasionally (and misleadingly) been called "pulsatility."

The remainder term accounts for any higher order components of motion not included in the series expansion. Equation 5.3 shows that this remainder is a function of the integral of the next higher order derivative evaluated over the entire time interval, thus including all higher order terms. In practice, the order (n) and point of expansion (t') are chosen so that R_n can be neglected over the time interval of interest. For the the short time intervals defined by the typical echo times used in MRI, most physiological motion can be represented by a finite Taylor series expansion with negligible remainder (36,37).

Substituting the Taylor series expansion of instantaneous position into the equation for the phase shift of a moving isochromat yields the equation

$$\phi(t-t') = \gamma \left[\sum_{k=0}^n \frac{x^{(k)}(t')}{k!} \int_{t_0-t'}^{t-t'} G(\tau) \tau^k d\tau + \int_{t_0-t'}^{t-t'} G(\tau) R_2 d\tau \right] . \quad [5.4]$$

Neglecting the remainder term, phase shift due to specific derivatives of position may be compensated by designing the gradient waveform $G(\tau)$ such that the integral

$$\int_{t_0-t'}^{t-t'} G(\tau) \tau^k d\tau \quad [5.5]$$

is zero at the center of the signal echo. This integral represents the k th time moment of the gradient waveform computed about time t' . Hence, this motion compensation technique is commonly referred to as "gradient moment nulling". Equation 5.4 is also used to design waveforms which impart a phase proportional to position, velocity, or other derivatives of position.

Expanding Equation 5.4 to show individual terms for phase due to position $x(t')$, velocity $v(t')$, and acceleration $a(t')$ at the point of expansion (t') yields

$$\begin{aligned} \phi(t-t') &= \frac{\gamma x(t')}{0!} \int_{t_0-t'}^{t-t'} G(\tau) \tau^0 d\tau + \frac{\gamma x^{(1)}(t')}{1!} \int_{t_0-t'}^{t-t'} G(\tau) \tau^1 d\tau + \frac{\gamma x^{(2)}(t')}{2!} \int_{t_0-t'}^{t-t'} G(\tau) \tau^2 d\tau + \dots \\ &= \frac{\gamma x(t')}{0!} M_0(t-t') + \frac{\gamma x^{(1)}(t')}{1!} M_1(t-t') + \frac{\gamma x^{(2)}(t')}{2!} M_2(t-t') + \dots \\ &= \frac{\gamma x(t')}{0!} M_0(t-t') + \frac{\gamma v(t')}{1!} M_1(t-t') + \frac{\gamma a(t')}{2!} M_2(t-t') + \dots \end{aligned} \quad [5.6]$$

where $M_k(t-t')$ is the k th time moment of the waveform

computed about time t' . Assuming that the remainder term (R_n) is zero implies that the first $n-1$ derivatives of position are time varying, the n th order derivative is time invariant, and all higher order derivatives are zero. This is a valid assumption if the number of terms in the expansion is sufficient to accurately represent the motion. Apart from the stipulation that $x(t)$ be continuously differentiable to the k th order on the interval (t', t) , the choice of t' is arbitrary. This introduces a degree of freedom in the determination of phase due to specific derivatives of position which is not usually considered in gradient waveform design or motion sensitivity analysis. Tables 5.1, 5.2, and 5.3 illustrate the effect of varying t' on the moments of rectangular, balanced-bipolar, and FEER type waveforms. The tables and Equation 5.6 suggest that moments represent the sensitivity of a waveform to the derivatives of position evaluated at a single instant of time, t' . Also, Tables 5.1 - 5.3 indicate that moment values are independent of t' only when all lower order moments are zero.

Gradient Waveform	Moment	$t' = t_1$	$t' = t_2$	$t' = t_3$
M_0	$G \cdot t_d$	$G \cdot t_d$	$G \cdot t_d$
	M_1	$G \cdot t_d^2/2$	0	$-G \cdot t_d^2/2$
	M_2	$G \cdot t_d^3/3$	$G \cdot t_d^3/12$	$G \cdot t_d^3/3$
	M_3	$G \cdot t_d^4/4$	0	$-G \cdot t_d^4/4$

Table 5.1 First four time moments of rectangular gradient waveform with amplitude G and duration t_d computed using three different choices of expansion point.

Gradient Waveform	Moment	$t' = t_1$	$t' = t_2$	$t' = t_3$
M_0	0	0	0
	M_1	$G \cdot t_d^2$	$G \cdot t_d^2$	$G \cdot t_d^2$
	M_2	$2G \cdot t_d^3$	0	$-2G \cdot t_d^3$
	M_3	$7G \cdot t_d^4/2$	$G \cdot t_d^4/2$	$7G \cdot t_d^4/2$

Table 5.2 First four moments of a balanced bipolar gradient waveform with amplitude $\pm G$ and lobe duration t_d computed using three different choices of expansion point.

Gradient Waveform	Moment	$t' = t_1$	$t' = t_2$	$t' = t_3$
<p>The diagram shows a three-lobe FEER gradient waveform. The vertical axis represents the gradient amplitude G and $-G$. The horizontal axis represents time. The waveform consists of three rectangular pulses: a positive pulse of height G from t_1 to $t_1 + t_d$, a negative pulse of height $-G$ from $t_1 + t_d$ to $t_1 + t_d + 2t_d$, and a positive pulse of height G from $t_1 + t_d + 2t_d$ to $t_1 + t_d + 2t_d + t_d$. The total duration is $4t_d$. The expansion points are marked as t_1, t_2 (at the center), and t_3. The pulse widths are labeled t_d and $2t_d$.</p>	M_0	0	0	0
	M_1	0	0	0
	M_2	$4G \cdot t_d^3$	$4G \cdot t_d^3$	$4G \cdot t_d^3$
	M_3	$24G \cdot t_d^4$	0	$-24G \cdot t_d^4$

Table 5.3 First four moments of a three lobe FEER gradient waveform with amplitude $\pm G$ and lobe duration t_d computed using three different choices of expansion point.

It can be shown algebraically that even though derivatives of position and waveform moments generally depend on the point of expansion chosen, computation of the total phase due to motion does not. Consider motion which can be completely characterized by a four term expansion. The Taylor Series can be used to describe the coefficients of motion at one time (t_2) in terms of those at another time (t_1) as

$$\begin{aligned}
 x_2 &= x_1 + v_1(t_2 - t_1) + \frac{a_1}{2!}(t_2 - t_1)^2 + \frac{j_1}{3!}(t_2 - t_1)^3 \\
 v_2 &= v_1 + a_1(t_2 - t_1) + \frac{j_1}{2!}(t_2 - t_1)^2 \\
 a_2 &= a_1 + j_1(t_2 - t_1) \\
 j_2 &= j_1
 \end{aligned} \tag{5.7}$$

higher terms = 0

This relationship can be expressed in matrix form as

$$\begin{bmatrix} x_2 \\ v_2 \\ \frac{a_2}{2!} \\ \frac{j_2}{3!} \end{bmatrix} = \begin{bmatrix} 1 & c & c^2 & c^3 \\ 0 & 1 & 2c & 3c^2 \\ 0 & 0 & 1 & 3c \\ 0 & 0 & 0 & 1 \end{bmatrix} \begin{bmatrix} x_1 \\ v_1 \\ \frac{a_1}{2!} \\ \frac{j_1}{3!} \end{bmatrix} \tag{5.8}$$

or equivalently as

$$\vec{X}' = [A] \vec{X} \tag{5.9}$$

where c is the time difference ($t_2 - t_1$). Noting that the i -th column of matrix A consists of the terms of the binomial expansion $(c+1)^i$, we see that Equation 5.8 may be

easily extended to the general case of n significant derivatives of position. Thus, the coefficients of motion at any point in time can be defined in terms of those at any other time. This implies that any choice of expansion point can be used to correctly describe the motion of an isochromat.

To determine phase due to specific derivatives of position, waveform moments are computed about the point of expansion of the Taylor series of the motion. Only the zero-th moment (M_0) is always independent of the point of expansion. Higher order moments will change with point of expansion unless all lower order moments are zero. This can be shown by noting that a forward shift of the point of expansion is equivalent to a backward time-shift of the gradient waveform and writing equations which describe the moments of a time-shifted waveform (37) as

$$\begin{aligned}
 M'_0 &= M_0 \\
 M'_1 &= M_1 - cM_0 \\
 M'_2 &= M_2 - 2cM_1 + c^2M_0 \\
 M'_3 &= M_3 - 3cM_2 + 3c^2M_1 - c^3M_0
 \end{aligned}
 \tag{5.10}$$

to express the moments computed about one time (t_2) in terms of the moments computed about another time (t_1). M'_i is the i -th time moment computed about time t_2 , M_i is the i -th

moment computed about time t_1 , and c is the time shift ($t_2 - t_1$). The same relationship can be expressed in matrix form as

$$\begin{bmatrix} M'_0 \\ M'_1 \\ M'_2 \\ M'_3 \end{bmatrix} = \begin{bmatrix} 1 & 0 & 0 & 0 \\ -c & 1 & 0 & 0 \\ c^2 & -2c & 1 & 0 \\ -c^3 & 3c^2 & -3c & 1 \end{bmatrix} \begin{bmatrix} M_0 \\ M_1 \\ M_2 \\ M_3 \end{bmatrix} \quad [5.11]$$

or equivalently as

$$\vec{M}' = [B] \vec{M} \quad [5.12]$$

These equations reveal that the i -th moment computed about one time (M'_i) is a function of all moments of equal and lower order (M_j for all $j \leq i$) computed about a different point in time. This indicates that moment values are independent of the expansion point only when all lower order moments are zero.

In Equation 5.6, the total phase shift due to motion was expressed as a scaled sum of the products of waveform moments and derivatives of position; both are quantities which have been shown in Equations 5.7 - 5.12 to vary with choice of expansion point. Using the matrix notation introduced in Equations 5.9 and 5.12, the total phase shift computed using arbitrary points of expansion $t' = t_1$ and $t' = t_2$ can be expressed as

$$\begin{aligned}\phi_{total}(\tau) \big|_{t'=t_1} &= \gamma \vec{M}^T \vec{X} \\ \phi_{total}(\tau) \big|_{t'=t_2} &= \gamma \vec{M}'^T \vec{X}'\end{aligned}\tag{5.13}$$

where $\tau = (t-t')$. Now using Equations 5.9 and 5.12 to express $\mathbf{M}'$ and $\mathbf{X}'$ in terms of $\mathbf{M}$ and $\mathbf{X}$ and rearranging terms yields

$$\gamma \vec{M}'^T \vec{X}' = \gamma \mathbf{M}^T \mathbf{B}^T \mathbf{A} \vec{X} \quad . \tag{5.14}$$

It can be shown (100) that

$$\mathbf{B}^T = \mathbf{A}^{-1} \tag{5.15}$$

which reveals that

$$\begin{aligned}\phi_{total}(\tau) \big|_{t'=t_2} &= \gamma \vec{M}^T \mathbf{A}^{-1} \mathbf{A} \vec{X} \\ &= \gamma \mathbf{M}^T \vec{X} \\ &= \phi_{total}(\tau) \big|_{t'=t_1} \quad .\end{aligned}\tag{5.16}$$

Thus total phase shift due to motion is a quantity which can be found provided the coefficients of motion and waveform moments about any point of expansion are known. But, care must be taken when attempting to attribute the phase to a specific derivative of position since the derivatives and waveform moments change with point of expansion.

This point is related to the previously shown (37) independence of moment values to the position of the waveform on the time axis when all lower moment values are

zero. We predict that nulling a specific moment will render a waveform insensitive to the corresponding derivative of position only when all lower order moments are nulled as well. Also, we expect that gradient waveforms designed to phase encode position, velocity, or other derivatives of position will actually encode the position or derivative at a single instant of time: t' .

5.3 Computer Simulations

Two sets of one-dimensional computer simulations were run to demonstrate the relationship between the point of expansion, waveform moments, and motion sensitivity, and to test our predictions based on that relationship. The idealized three-lobe FEER waveform with lobe amplitudes ± 2.35 mT/m and lobe duration $t_d = 1.28$ msec shown in Figure 5.1 was used throughout.

5.3.1 Phase Trajectories

For the first simulation, a four-term Taylor Series expansion was assumed to completely characterize the motion of a single isochromat for the duration of the gradient waveform. The unidirectional time varying position of the isochromat is plotted in Figure 5.2. The coefficients describing the simulated motion at the four points in time

indicated in Figures 5.1 and 5.2 are listed in Table 5.4. Since the remainder term in the expansion is assumed to be zero, this set is self-consistent in that the coefficients at one point in time can be defined in terms of the coefficients at any other time within the view.

Equation 5.6 was used to calculate the time varying phase due to motion using the three choices of expansion point (t_1 , t_2 , and t_3) indicated in Table 5.4. 386-MATLAB (The MathWorks, Inc., South Natick, Massachusetts) software was used to compute and plot the evolution of phase over the time course of the gradient waveform. The resulting phase trajectories (101,26) for each point of expansion and derivative of position are shown in Figures 5.2, 5.3, and 5.4. In each plot, the phase components ϕ_i are defined as

$$\begin{aligned}\phi_i(t-t') &= \frac{\gamma X^{(i)}(t')}{i!} \int_{t_0-t'}^{t-t'} G(\tau) \tau^i d\tau \\ &= \frac{\gamma X^{(i)}(t')}{i!} M_i(t-t')\end{aligned}\quad [5.17]$$

and the total phase ϕ_c is defined as in Equation 5.6. In the usual form of expansion used to determine phase due to each component of motion (47,102), ϕ_1 is assumed to correspond to the phase due to velocity, ϕ_2 is phase due to acceleration, and so on.

Figure 5.3 depicts the phase trajectories computed using the start of the gradient waveform as the point of expansion. Note the non-zero components of phase at TE due to acceleration (ϕ_2) and jerk (ϕ_3). In Figure 5.4, the point of expansion was chosen as the mid-point of the FEER waveform. Note the difference in the phase trajectories due to each order of motion from those in Figure 5.3. The phases due to position, velocity, and jerk are all zero at TE leaving only the phase component due to acceleration. Choosing TE as the expansion point results in the phase trajectories in Figure 5.5. Again, note the difference in the trajectories of phase due to each derivative of position while the total phase (ϕ_T) is the same in Figures 5.3, 5.4, and 5.5.

Figure 5.1 FEER gradient waveform used in simulations.

Figure 5.2 Time varying position of isochromat with motion described by coefficients in Table 5.4.

time (msec)	$t_0 = 0.0$	$t_1 = 0.5$	$t_2 = 3.06$	$t_3 = 5.62$
x (cm)	0	.06182	.43951	.93210
v (cm/sec)	120	127.328	168.858	217.099
a (cm/sec ²)	14400	14912	17533.4	20154.9
j (cm/sec ³)	1024000	1024000	1024000	1024000

Table 5.4 Coefficients of motion at different points in time throughout the sequence used in the phase trajectory simulation. Times correspond to those indicated in Figures 5.1 and 5.2a.

Figure 5.3 Trajectories of total phase (ϕ_z) and components due to position (ϕ_0), velocity (ϕ_1), acceleration (ϕ_2), and jerk (ϕ_3). Moments expanded about time t_1 indicated in Figures 5.1 and 5.2. Phases ϕ_0 and ϕ_1 are nulled at the echo independent of expansion point. Phases ϕ_2 and ϕ_3 at the echo vary with point of expansion, and are non-zero in this case. Total dephasing due to motion (ϕ_z) remains unchanged with choice of expansion point.

Figure 5.4 Trajectories of total phase (ϕ_z) and components due to position (ϕ_0), velocity (ϕ_1), acceleration (ϕ_2), and jerk (ϕ_3). Moments expanded about time t_2 indicated in Figures 5.1 and 5.2. Phases ϕ_0 and ϕ_1 are nulled at the echo independent of expansion point. Phases ϕ_2 and ϕ_3 at the echo vary with point of expansion. In this case, phase due to jerk (ϕ_3) is zero. Total dephasing due to motion (ϕ_z) remains unchanged with choice of expansion point.

Figure 5.5 Trajectories of total phase (ϕ_{Σ}) and components due to position (ϕ_0), velocity (ϕ_1), acceleration (ϕ_2), and jerk (ϕ_3). Moments expanded about time t_3 indicated in Figures 5.1 and 5.2. Phases ϕ_0 and ϕ_1 are null at the echo independent of expansion point. Phases ϕ_2 and ϕ_3 at the echo vary with point of expansion, and are non-zero in this case. Total dephasing due to motion (ϕ_{Σ}) remains unchanged with choice of expansion point.

5.3.2 Bloch Equation Solver

A second set of simulations were run using a program which solves the Bloch equations and includes rectilinear motion explicitly. It should be noted that this simulation software was developed and run by Dr. Richard E. Wendt III at Baylor University. It is included in this thesis because it was part of an article authored by myself, Dr. Wendt, and Dr. Jeffrey Duerk, and it is a useful demonstration of the theory put forth in this chapter.

The input to the simulation program consists of a pulse sequence describing the rf pulses and gradient waveforms and a file that describes each of the isochromatic spin groups to be simulated. For deterministic, rectilinear motion, the program updates the state of the magnetization vector of each isochromat according to the Bloch equations. This updating occurs every time there is a change in the external magnetic fields and also regularly at the sampling frequency of the output data, which are the three components of the net magnetization of the sample. The precession of 85 isochromatic spin groups was simulated for 6.9 msec. Relaxation parameters were chosen so that the simulated isochromats are realigned on the z or longitudinal axis just prior to the 90° RF pulse, and the dephasing caused by

T2 relaxation during sampling can be neglected. The isochromats are arrayed along the x-axis with different spatial distributions so that their projections onto the x-axis resemble the letters 'N', 'M', and 'R' with a dot to the left of the 'N' and another dot to the right of the 'R'. The isochromats are excited by an ideal instantaneous 90° pulse in the absence of any gradients. Each letter moves independently in the x-direction with motion defined by the coefficients listed in Tables 5.5 and 5.6. The two dots are stationary and separated by 55 cm. The coefficients in Table 5.5 were chosen such that at time t_0 , the spins in each letter have only one non-zero derivative of position. Those in Table 5.6 were chosen such that the letter 'M' isochromats have only position and jerk components of motion at time t_2 .

The same FEER waveform as in the phase trajectory simulation was used. The amplitude of the readout gradient pulse was 1000 Hz/cm (2.35 mT/m). The program also performed the one-dimensional Fourier Transform reconstruction on the simulated echo data.

Figure 5.6 shows the simulated pulse sequence used in the Bloch equation solver. The original position of the spin groups at time t_0 are shown in Figure 5.7. Real and imaginary parts of the Fourier transform reconstruction are

shown in Figures 5.8 and 5.9 for motion described in Tables 5.5 and 5.6 respectively. The motion of the letters along the x-axis was slight, but perceptible by superimposing Figures 5.7, 5.8, and 5.9. Any non-zero imaginary component in the transform indicates a phase shift due to motion. Note in Figure 5.8 that the 'N' moving with a constant velocity acquires no phase at the echo while the 'M' moving with constant acceleration and 'R' with constant jerk both exhibit motion induced dephasing. In Figure 5.9, the motion of the 'M' group of isochromats was defined such that only the position and jerk components are non-zero at time t_2 . The 'M' exhibits no motion induced dephasing in the reconstruction.

Figure 5.6 Pulse sequence used in Bloch solver. Gradient is applied to one axis only to simplify the analysis of results.

Figure 5.7 Initial distribution of spin groups along the x-axis. The projection of the spatial distribution of the spins along the x-axis resemble the letters 'N', 'M', and 'R'.

	N		M		R	
	t_0	t_2	t_0	t_2	t_0	t_2
x (cm)	0	.3672	0	.0674	0	4.89e-3
v (cm/sec)	120	120	0	44.06	0	4.7942
a (cm/sec ²)	0	0	14400	14400	0	3133.44
j (cm/sec ³)	0	0	0	0	1024000	1024000

Table 5.5 Derivatives of position of simulated isochromatic spin groups evaluated at times t_0 and t_2 as defined in Figure 5.1. Position (x) measured relative to starting position since the letters are distributed along the x-axis. Each spin group starts at time t_0 with only one non-zero derivative of position.

	N		M		R	
	t_0	t_2	t_0	t_2	t_0	t_2
x (cm)	0	0	0	4.89e-3	0	4.89e-3
v (cm/sec)	4.7942	-4.7942	4.7942	0	0	4.7942
a (cm/sec ²)	-3133.44	-3133.44	-3133.44	0	0	3133.44
j (cm/sec ³)	0	0	1024000	1024000	1024000	1024000

Table 5.6 Derivatives of position of simulated isochromatic spin groups evaluated at times t_0 and t_2 defined in Figure 5.1. The motion of isochromatic spin group 'M' results in zero valued velocity and acceleration components at time t_2 .

Figure 5.8 Real and imaginary parts of discrete Fourier transform (DFT) one-dimensional reconstruction of the simulated signal from spin groups moving as described in Table 5.5. The Fourier transform plots have a frequency width of 100 kHz. Presence of imaginary parts in the reconstructed 'M' and 'R' spin groups indicates motion induced dephasing occurred. The 'N' group moving with constant velocity was completely rephased at the echo.

Figure 5.9 Real and imaginary parts of discrete Fourier transform (DFT) one-dimensional reconstruction of the simulated signal from spin groups moving as described in Table 5.6. The Fourier transform plots have a frequency width of 100 kHz. The 'M' group which has only position and jerk components at time t_2 is completely rephased at the echo. This indicates that the waveform is insensitive to the instantaneous jerk component at time t_2 .

5.4 Discussion

The results of the theoretical analysis and computer simulations reveal some interesting details about the relationship between gradient waveform time moments and motion sensitivity. Recognizing the expansion point (t') as an additional degree of freedom refines the interpretation of phase due to motion, with implications in the design of motion compensating and motion encoding waveforms.

Tables 5.1 - 5.3 show that, in general, the value of a waveform moment depends on the point in time about which the moment is computed. By varying the choice of expansion point, virtually any gradient waveform will have one or more zero-valued moments. This is evident in Tables 5.1 - 5.3 where the choice of $t' = t_2$ results in nulled odd or even order moments for all three waveforms. This does not indicate insensitivity to dephasing by the corresponding derivatives of position as has been suggested for the FEER waveform (93,94,95,96). Instead, moment values should be interpreted as the sensitivity to a derivative of position evaluated at the point of expansion only. This is supported by Figure 5.8 which shows that simulated motion defined only by jerk (an odd order of motion) at time t_0 causes dephasing by a FEER waveform. Table 5.3 indicates

that the third moment of the FEER waveform computed about $t' = t_2$ is zero. The simulation results in Figure 5.9 show that motion consisting of only a jerk component at time t_2 in the FEER waveform causes no dephasing, again indicating that a moment is correctly interpreted as the sensitivity to a derivative of position evaluated at the point of expansion.

The phase trajectories in Figures 5.3-5.5 show that only nulled moments which are independent of expansion point are indicative of insensitivity to an order of motion throughout the waveform. It is demonstrated by the examples in Tables 5.1 - 5.3, that a moment value is independent of expansion point only when all lower order moments are zero. Thus, the proper way to use gradient moment nulling to render a waveform insensitive to a particular derivative of position is to first null all lower order moments. For example, compensation of acceleration can only be achieved together with velocity compensation.

6. The Significance of the Expansion Point in Gradient Waveform Design

6.1 Introduction

The theory and simulations presented in Sections 5.3 and 5.4 indicate that the choice of expansion point must be considered in the design of motion compensated and motion encoding gradient waveforms. Frequency encoding and slice select gradients have nulled zero-th order moments (waveform area); higher order moments are typically nulled starting with the first moment (velocity sensitivity) and working up. Since it was shown that moment values are independent of the moment center when all lower order moments are nulled, the applications presented in this section deal only with phase encoding waveforms. Recalling from Tables 5.1 - 5.3 that phase encoding of position requires a waveform with non-zero area, phase encoding of velocity requires non-zero first moment, etc., the choice of expansion point assumes a great importance in application of motion compensation techniques to phase encoding waveforms.

6.2 Compensation of Misregistration Artifacts

Spatial misregistration of flowing blood is a common artifact which has been well described in the literature (103,104,96,105). The source of the artifact is

Figure 6.1 Diagram illustrating mechanism of oblique flow misregistration. Basic spin echo sequence in **A** encodes position along frequency and phase axes at different time points. This results in spatial misregistration of material moving oblique to the imaging axes, as shown in **B**.

the time delay between the phase encoding of position and the echo time. It was shown in Table 5.1 that the unipolar single lobe waveform, commonly used for positional phase encoding, imparts a phase proportional to the position that constant velocity spins have at the center of the gradient lobe. A frequency encoding waveform encodes the dc spatial frequency corresponding to position at the echo time. This non-simultaneous encoding of coordinates results in a spatial misregistration of moving material as diagrammed in Figure 6.1.

Conventional gradient moment nulling (GMN) procedures (30,42) do not address these misregistration artifacts. Attempts to eliminate motion effects along the phase encode (PE) axis (36,97,98) have been impaired by neglect of the significance of the expansion point in GMN. As reported by Moran, standard GMN can exacerbate misregistration artifacts (106), as will be shown by phantom and human imaging experiments; however, moment nulling of the PE waveform can eliminate these artifacts with the proper choice of moment center or expansion point (32,33).

The theory developed in Sections 5.3 and 5.4 of the previous chapter can be applied to simply and directly explain and suppress the oblique flow misregistration artifact. A computer controlled linear motion phantom was

used to demonstrate the theory and prove the effectiveness of this technique. Human head images exhibiting misregistration artifacts and their elimination are also shown for 2D spin-echo and 3D gradient echo sequences.

6.2.1 Theory

Expressing the time varying position of moving spins in terms of the Taylor Series expansion about time t' results in an expression for phase evaluated at a time measured relative to t' . Consider the simple case of constant velocity motion:

$$x(t-t') = x(t') + v(t') (t-t')$$

$$\phi(t-t') = \gamma x(t') \int_{t_0-t'}^{t-t'} G(\tau) d\tau + \gamma v(t') \int_{t_0-t'}^{t-t'} G(\tau) \tau d\tau \quad [6.1]$$

$$\text{phase due to } x(t') \quad \text{phase due to } v(t')$$

As explained in Section 5.4, we are free to choose the expansion point t' and design a moment nulled positional phase encoding waveform which will generate a phase linearly proportional to the instantaneous position $x(t')$. This phase is independent of the instantaneous velocity $v(t')$ which is assumed to be constant on the time interval including t' and the gradient waveform. Although constant velocity motion is assumed in the remainder of this discussion, these principles are easily extended to higher

order derivatives of position.

As indicated in Table 5.1, the first moment of a standard single lobe PE waveform is zero when evaluated about the center of the waveform. Thus, single lobe PE waveforms encode the instantaneous position at this time. The frequency encoding waveform encodes position at the echo time, resulting in non-simultaneous encoding of the respective image coordinates. This can result in a misregistration of material moving oblique to the frequency and phase encoding axes, as shown in Figure 6.1. Blood flowing oblique to the imaging axes will appear in the image shifted orthogonal to the direction of flow by:

$$D = v(TE - TP) \sin\theta \cos\theta \quad [6.2]$$

where D is the shifted distance, v is the magnitude of the flow velocity, TE is the echo time, TP is the time of phase encoding, and θ is the angle between the direction of the flow and the frequency encoding axis. Equation 6.2 reveals that the amount of shift is proportional to the velocity and the time delay between frequency and phase encoding, and is a maximum for flow at a 45° angle oblique to the imaging axes.

Standard GMN waveforms are nulled about the start of the waveform, encoding the position at a time which is actually further removed from the echo time, resulting in

an increase of the interval (TE - TP) and exacerbation of misregistration artifacts. Designing a PE waveform with first moment nulled about $t' = TE$ results in encoding of position at the echo, simultaneous with the frequency encoding of position, thereby eliminating misregistration.

Moran (106) and Nishimura (105) have both reached effectively the same conclusion in a slightly different fashion. They recognize that standard GMN only makes misregistration artifacts worse. But, as mentioned above, standard GMN techniques null moments about the start of the gradient waveform. Nishimura (105) states "...moment compensation for displacement reduction corresponds to making the first moment large, not zero," and Moran (106) that "...gradient moment nulling compensations produced greater motion artifacts in experiments than did use of no waveform compensation at all." These statements are true, as long as it is understood that the beginning of the PE waveform is used as the moment center. Gradient moment nulling can be used to compensate misregistration artifact, as shown in this chapter, by nulling about the echo time.

It should be noted that moment nulling of the phase encoding waveform only serves to shift the point in time at which the position of moving spins is encoded. In the frequency encoding and slice select directions, a distribution of velocity within a voxel causes a

distribution of phase which results in signal attenuation due to destructive interference. A distribution of velocities in the phase encoded direction results in a distribution of encoded positions. It will be shown that this may attenuate, or enhance the signal in a given voxel. Regardless of the velocity, the position is encoded at the point in time which defines the moment center about which the first moment is zero. For unipolar waveforms, this is the center of the lobe; for MAST compensated waveforms, this is the beginning of the waveform; using the compensation scheme proposed here, this is the echo time. These concepts are summarized in Figure 6.2.

The effect of a spatial velocity distribution in the case of flow oblique to frequency and phase encoded axes is also important. As indicated by Equation 6.2, the distance that flowing material misregisters in an image is proportional to the velocity (and higher order derivatives if significant). Assuming laminar flow, a two-dimensional parabolic distribution of velocity will exist across the lumen of a vessel with peak velocity at the center as shown in Figure 6.3. From Equation 6.2, we deduce that the signals from the fastest moving spins in the center of the laminar flow profile will displace further than those at the edges of the vessel where velocity is lowest. This variation in misregistration can cause the signal from

- A** Standard single lobe PE gradient
 First moment nulled about TC
 Position of constant velocity spins encoded at time TC
 Misregistration of spins moving oblique to read and phase axes

- B** Standard GMN compensated PE gradient
 First moment nulled about T0
 Position of constant velocity spins encoded at time T0
 Exacerbates misregistration

- C** Misregistration compensated PE gradient
 First moment nulled about TE
 Position of constant velocity spins encoded at time TE
 Eliminates misregistration

Figure 6.2 Summary of the theoretical concepts of misregistration compensation. Standard single lobe PE waveform (A), standard gradient moment nulled PE waveform (B), and PE waveform with first moment nulled about TE (C), each encode position of constant velocity spins at a different time point.

Figure 6.3 Parabolic laminar flow velocity profile predicted by Poiseuille's equation for Newtonian fluid and a circular rigid tube shown as a mesh plot in A. Velocity dependent misregistration causes apparent location of moving material to shift, piling up signal from blood within the vessel as seen in B.

flowing blood at different positions across the lumen to be encoded to the same position, as shown in Figure 6.3. This superposition of signal may produce an increase in signal intensity in the image.

Compensation of the misregistration artifact may actually reduce the signal of some flowing blood by eliminating this paradoxical enhancement. An additional enhancement mechanism may be that misregistered blood overlays tissue adjacent to the vessel. The apparent signal from the blood is thus the sum of the blood and adjacent tissue signals. These signal enhancement mechanisms may be important in 2D and 3D time-of-flight and phase contrast angiography. Variations in signal intensity due to the velocity and direction of flow may be mistaken for changes in lumen diameter and vessel patency.

Evidence for these paradoxical signal enhancement effects and their elimination by moment nulling about the echo time are seen in the human images presented in this section.

6.2.2 Linear Motion Phantom Imaging Experiments

A linear motion phantom system was used to examine the effects of motion along the PE axis and evaluate compensation schemes. The phantom, depicted in Figure 6.4, consists of a computer controlled stepper motor, a ball-

Figure 6.4 The computer controlled linear motion phantom system used to generate bulk motion which is identical from view to view. The phantom motion is free of the spatial distribution of velocities present in flow phantoms, and provides precise control of position, velocity, and acceleration.

screw assembly which converts the rotary motion of the motor shaft to linear motion, a 16' long plastic drive shaft supported by plastic bearing blocks to carry the motion into the imager, and a gel-filled plastic phantom. This system provides accurate control of the position, velocity, and acceleration of the solid phantom. A detailed description of the construction and operation of this phantom can be found in Appendix A.

The bulk nature of the phantom motion, together with gating, eliminates view-to-view variations in position or dephasing. This phantom provides a means of examining the effectiveness of motion compensation schemes in eliminating misregistration artifacts.

The phantom moved with the time varying position plotted in Figure 6.5. Pulse sequences were applied during the constant velocity (40 cm/sec) portion of the motion profile from 200 to 285 msec after the gating trigger. The times indicated on the phantom position profile (Figure 6.5) correspond to the encoded positions in Figures 6.7 and 6.8.

The optimal waveform design procedure presented in Chapter 2 was used to generate the oblique flow compensation sequences to minimize slewing and maintain feasibility. An example waveform with acceleration compensation on read and slice axes and velocity

Figure 6.5 The time varying position and velocity profiles of the linear motion phantom. Letters A, B, C, and D indicate the predicted positions of the phantom in the images shown in the corresponding parts of Figures 6.7 and 6.8.

Figure 6.6 TE80 Misregistration compensated sequence. Optimal design protocol use to minimize slewing, constrain moments to desired values, and guarantee feasibility. Phase encoding waveform compensated through acceleration.

compensation on the PE axis is shown in Figure 6.6.

Three TE80 spin echo sequences with identical read and slice select but different PE waveforms were used to generate all images; one using a standard single lobe PE waveform, one using standard GMN velocity compensation, and one using moment nulling about TE. The resulting images of the phantom stationary, moving along the PE axis, and moving at a 45° angle to the read and PE axes are shown in Figures 6.7 and 6.8. The moving block of gelatin appears as a rectangular, light object in the images. Along either side of the phantom track are stationary vials of water to serve as reference markers. These appear as small light circles in the images.

Figure 6.7a is an image of the stationary phantom at its initial position in the motion profile. Figure 6.7b shows the phantom position imaged with a unipolar PE gradient, Figure 6.7c with the first moment of the PE waveform nulled about the beginning of the waveform, and Figure 6.7d with first moment nulled about TE.

Phantom position was measured directly from each image by averaging the positions of the leading and trailing edges to give an estimate of the position of the center of the phantom along the direction of motion. The expected position was determined from the programmed motion profile

Figure 6.7 Images of phantom moving along the PE axis with time-varying position indicated in Figure 6.5. Dots are stationary tubes of water. Image (A) shows the phantom stationary at its initial position. Image (B) was generated using an uncompensated PE waveform. Imaged position corresponds to that at the center of the waveform. Image (C) was generated using first moment nulling about the start of the waveform. Imaged position corresponds to that at the start of the waveform, only slightly displaced from that with no compensation. Image (D) was generated with first moment nulling about TE with the sequence shown in Figure 6.6. Imaged position corresponds to that at the echo.

Figure 6.8 Images of the phantom moving at 45° oblique to read and phase axes with profile shown in Figure 6.5. Dots are stationary tubes of water. Image (A) shows the phantom stationary at its initial position. Image (B) was generated using an uncompensated PE waveform. Note misregistration of phantom towards the lower row of dots to a position it never physically had. Image (C) was generated using first moment nulling about the start of the waveform. Note approximately the same misregistration as seen in B. Image (D) was generated with first moment nulling about TE. Imaged position corresponds to that at the echo with no misregistration evident.

Figure	6.7a	6.7b	6.7c	6.7d
PE Waveform	Single Lobe	Single Lobe	GMN(T0) M1 = 0	GMN(TE) M1 = 0
Encoded Time Rel to Trig (msec)	0	283	267	344
Encoded Time Rel to RF (msec)	19	19	3	80
Expected Position (mm)	0.	72.72	66.73	97.45
Measured Position (mm)	-39.85	32.80	26.35	58.00
Relative Measured Position (mm)	0.	72.65	66.20	97.85
% Error	-	.6	.8	.4

Table 6.1 Summary of results for phantom motion along the phase encoded axis. Stationary phantom position (Figure 6.7a) used as position origin. Measured positions correspond to average of leading and trailing edges edge of phantom. Expected positions correspond to predicted position of phantom at moment center about which first moment of PE waveform is nulled.

(seen in Figure 6.6), and the point in time about which the first moment of each waveform was nulled.

Table 6.1 provides a quantitative summary of the experimental results. Expected and encoded positions for each phase encoding waveform are given, as well as the percent error. All imaged positions fall within one pixel of those predicted from the phantom motion profile, verifying that the encoded position corresponds to the point in time at which sensitivity to velocity is zero. This holds true for this case in which the phantom is moving with constant velocity during gradient activity.

The phantom positions imaged in Figures 6.8a-d correspond to those in Figure 6.7a-d, but with the in-plane gradient axes rotated 45° . This simulates motion oblique to the frequency and phase encoding axes. Figure 6.8a shows the phantom at its initial stationary position. The image in Figure 6.8b was generated using the single lobe PE gradient. Note the misregistration of the phantom. It appears shifted up and to the right, towards the upper row of stationary water vials. In Figure 6.8c, with first moment nulling about the start of the waveform, the misregistration is slightly worse; the phantom is shifted slightly further out of its actual path, as expected. In Figure 6.8d, the imaged position corresponds to that at the echo, with little misregistration evident.

Figure	6.8a	6.8b	6.8c	6.8d
PE Waveform	Single Lobe	Single Lobe	GMN(T0) M1 = 0	GMN(TE) M1 = 0
Encoded Time Rel to Trig (msec)	0	283	267	344
Encoded Time Rel to RF (msec)	19	19	3	80
Expected Displacement (mm)	0.	12.20	15.40	0.
Measured Displacement (mm)	0.	15.26	18.43	2.75
Error	0.	3.06	3.03	2.75

Table 6.2 Summary of results for phantom motion at 45° angle oblique to frequency and phase encoding axes. Stationary phantom position (Figure 6.8a) used as position origin. Expected positions correspond to predicted position of phantom at moment center about which first moment of PE waveform is nulled. Nearly constant displacement offset in all images may be due to misalignment of the phantom motion from desired 45° path.

Table 6.2 provides a quantitative summary of the experimental results. Phantom displacement was measured as the average position of the leading and trailing edges in the direction of displacement. Equation 6.2 was used to compute the expected displacement for motion 45° to the imaging axes, and the time intervals defined by imaging sequences. A slight offset of about 3 mm (< 2 pixels) was observed in all three measurements of moving phantom position. This is probably due to a misalignment of the phantom track along the long axis of the magnet. A misalignment of less than 2° would result in a 3 mm displacement over the 10 cm covered by the phantom from initial position, to its position at the echo. This 2° error is less than the expected precision obtainable in setting up the motion phantom. Taking this constant offset into account, the imaged positions agree very well with those predicted by the theory presented in Chapter 5.

6.2.3 Human Imaging Experiments

6.2.3.1 Two Dimensional Spin Echo Imaging

Axial images of the head of a volunteer were generated using the same TE80 sequences as used with the phantom to demonstrate the compensation of misregistration due to blood flow. These T2 weighted images are shown in Figure 6.9. The acquisition parameters are listed in Table 6.3.

Slice Orientation	Axial
Phase Encoding Axis	Anterior/Posterior
Number of Slices	1
Repeat Time	150 msec
Field of View	35 cm
Phase Encoded Views	192
Number of Signals Averaged	1
Slice Thickness	10 mm
RF Flip Angle	90°
Scan Time	.48 minutes

Table 6.3 Acquisition parameters for 2D spin echo sequences demonstrating misregistration artifact. Sequence used in phantom and human imaging experiments.

The image in Figure 6.9a was generated with moment nulling about the start of the PE waveform. Note the characteristic bright/dark banding pattern in the vessels due to misregistration. The brightness of the misregistered blood may be due to the signal enhancement mechanisms suggested in the previous section. In Figure 6.9b, the PE waveform first moment is nulled about the echo; misregistration of blood is effectively suppressed. Note that the signal of the blood in the vessels in Figure 6.9b is not as intense as the misregistered blood seen in Figure 6.9a.

6.2.3.2 Three-Dimensional Gradient Echo Imaging

In three-dimensional spin warp imaging, two axes are phase-encoded rather than one. A thick slab of tissue is selectively excited and a phase encoding gradient used to divide this slab up into thinner slices. This secondary (2°) phase encode axis is susceptible to the same misregistration artifacts as the primary (1°) phase encode. Thus, in 3D imaging, 1° phase encoding, 2° phase encoding, and frequency encoding may all occur at different times, leading to misregistration in all directions. Misregistration due to 2° phase encoding can shift the blood signal to a different slice, or out of the imaged slab of tissue.

Figure 6.9 Human image examples: TE80/TR2000/SPIN ECHO. Image A generated using standard GMN on the PE axis. Note the misregistration of blood in cranial vessels which appears as adjacent bright and dark bands. Image B generated with first and second moment nulling about TE.

The three-dimensional gradient echo sequences depicted in Figure 6.10 were used to image the head of a volunteer. In the sequence in Figure 6.10a, the 1° PE waveform is uncompensated and the 2° PE waveform is nulled about the start of the waveform. Assuming constant velocity motion, the instantaneous position is encoded at a different time for each gradient axis. In the sequence of Figure 6.10b, both PE waveforms are first moment nulled about TE to eliminate misregistration artifacts.

Axial and coronal views of 3D data sets generated using these sequences are shown in Figure 6.11a and b. Misregistration is evident in both views of the uncompensated image, and effectively eliminated in the compensated image.

A short echo time (TE10.5) 3D sequence typically used for MR angiography was also examined for misregistration artifacts. The resulting data sets from misregistration compensated and uncompensated images are depicted as Maximum Intensity Projections (MIP) in Figure 6.12. Note the loss of signal from the smaller blood vessels with misregistration compensation. This suggests that misregistration may act as an important signal enhancement mechanism in time-of-flight (TOF) angiography. The superposition of blood on adjacent tissue and blood on blood due to misregistration may help raise the signal

Figure 6.10 Three-Dimensional gradient echo sequences. Sequence A has unipolar 1° PE waveform and 2° PE with first moment nulled about the start of the waveform. Positions of spins are encoded at different times for each of the three gradient axes as indicated. Sequence B has 1° and 2°

Figure 6.11a Axial, coronal, and sagittal views of the 3D data sets generated using the sequence shown in Figure 6.10a. Note the misregistration of flowing blood evident in all three planes.

Figure 6.11b Same axial, coronal, and sagittal views as in Figure 6.11a, now imaged using the misregistration compensated sequence shown in Figure 6.10b. Note the disappearance of the bright/dark banding patterns characteristic of misregistration.

Figure 6.12 Maximum Intensity Projection (MIP) axial views of the head generated with a 10.5 msec echo time, gradient echo sequence. Image (A), generated without misregistration compensation, shows more detail and finer vessels than image (B), with compensation. This difference in signal intensity may be due to enhancement by superposition of blood on blood, and blood on adjacent tissue.

intensity of blood above the background. This hypothesis has significant implications in MR angiography and requires further investigation.

6.2.4 Conclusions

An additional aspect of GMN on the PE axis which must be considered is the choice of the instant of time at which moving spins are encoded. Phase-encoding waveforms which null moments about a point of expansion other than TE will generate misregistration artifacts. Standard GMN sets this time as the beginning of the waveform, amplifying misregistration. Choosing TE as the moment center, PE waveforms are designed to encode the position of the spins at the echo, independent of motion. This eliminates oblique misregistration artifacts caused by non-simultaneous frequency and phase encoding, as demonstrated in the phantom and human images shown here.

6.3 Motion encoding

6.3.1 Theory

The theory presented in Chapter 5 is also important in the design of waveforms to phase encode velocity and higher derivatives of position for motion quantification. In Equation 5.6, we see that it is the derivatives of position evaluated at the point of expansion which are encoded in

the phase. Since the total phase ϕ_e is the only measureable quantity, the variation in contributions of ϕ_2 and ϕ_3 at the echo with point of expansion seen in Figures 5.2b-d indicates that more information is required to determine phase due to individual components of motion. Otherwise, Equation 5.6 represents an underdetermined case of one phase equation in a number of unknowns corresponding to the number of significant derivatives of position. The additional information needed to solve this equation may be in the form of assumptions about the motion which reduce the number of unknowns, or the use of multiple phase-encoding experiments to effectively increase the number of equations. For example, the balanced-bipolar waveform shown in Table 5.2 has been used for velocity encoding; this waveform has a velocity sensitivity which is independent of expansion point, and has no sensitivity to acceleration at time t_2 , the point of symmetry midway through the waveform.

Acceleration and higher derivatives of motion contribute to signal phase and can corrupt velocity quantification. If we assume a constant accelerative motion, i.e., jerk and higher derivatives are zero, then phase due to motion can be completely attributed to the velocity at time t_2 , i.e., $\phi_e = \phi_1$. The encoded

instantaneous velocity at time t_2 corresponds to the average velocity over the duration of the waveform for this case of constant acceleration. The same process can be used to describe phase encoding of average position with a rectangular gradient lobe in the presence of constant velocity motion, and the encoding of average acceleration by the FEER waveform.

Other waveforms used to encode velocity may null the second moment (M_2) at a point of expansion other than the middle of the waveform. In any case, if all phase is attributed to velocity, the instantaneous velocity at the point about which M_2 is zero will be encoded.

This can all be summed up as a single hypothesis: velocity encoding waveforms with the same calculated velocity sensitivity but different shapes produce different estimates of instantaneous velocity in the presence of acceleration.

6.3.2 Phantom Experiments

The linear motion phantom was used to test this hypothesis. The phantom was programmed to move with the triangular velocity profile shown in Figure 6.13. This type of motion results in intervals of constant acceleration and deceleration at ± 400 cm/sec. The phase

Figure 6.13 Phantom position, velocity, and acceleration profiles used in velocity quantification experiment. Image acquisition took place during intervals of constant acceleration and deceleration to examine effects of acceleration on velocity quantification.

encoding waveform of the TE80 sequence described in Section 5.5.1 was replaced with the five velocity encoding waveforms shown in Figure 6.14. Each of these waveforms is designed for no phase sensitivity to position, a sensitivity to velocity of 4.02 radians/(cm/sec), and sensitivity to acceleration nulled at a different point in time for each waveform, as indicated in Figure 6.14.

These five sequences were run to encode velocity at four different echo delays from the gating pulse at the start of the motion profile. Examples of the velocity encoded images are shown in Figure 6.15. In these images, the vertical axis corresponds to velocity, not position. The bottom of the image corresponds to a velocity of -100 cm/sec and the top to +100 cm/sec. Since the gel phantom moves as a unit with no spatial distribution of velocity, it appears as a line in the velocity encoded images. The stationary water viles located alongside the phantom appear as small lines on either side of the image at zero velocity. The predicted phantom velocities and those encoded with the five waveforms shown in Figure 6.14 are plotted in Figure 6.16. The experimental results shown in Figure 6.16 are summarized in Table 6.4.

According to the theory presented in Chapter 5, each different velocity encoding waveform encodes the instantaneous velocity at the moment center about which the

Figure 6.14 Velocity encoding waveforms. Each of the five waveforms encodes the instantaneous velocity (assuming constant acceleration) at a different point in time, indicated as the origin on each time axis. Each waveform is scaled and incremented through positive and negative values to encode velocity to one image axis.

Figure 6.15 Velocity encoded phantom image. Position along vertical axis is proportional to velocities ranging from -100 cm/sec to 100 cm/sec. Bulk motion of the phantom generates a single line at a position corresponding to the phantom velocity. Stationary water vials are projected onto $v = 0$ position.

Figure 6.16 Computed (dots) and predicted (line) phantom velocity with constant acceleration.

Wavefrm	Echo Time after Trigger (msec)	Encoded Time after Trigger (msec)	Expected Velocity (cm/sec)	Encoded Velocity (cm/sec)	Error (cm/sec)
6.14a	148	88	35.2	37.0	1.8
6.14b	148	98	39.2	41.4	2.2
6.14c	148	108	43.2	44.5	1.2
6.14d	148	118	47.2	47.7	0.5
6.14e	148	128	51.2	53.1	1.9
6.14a	308	248	27.6	26.5	-1.1
6.14b	308	258	23.6	24.2	0.6
6.14c	308	268	19.6	20.3	0.7
6.14d	308	278	15.6	17.2	1.6
6.14e	308	288	11.6	14.1	2.5
6.14a	458	398	-32.4	-33.6	-1.2
6.14b	458	408	-36.4	-38.3	-1.9
6.14c	458	418	-40.4	-40.6	-.2
6.14d	458	428	-44.4	-45.3	-1.9
6.14e	458	438	-48.4	-49.2	-0.8
6.14a	618	558	-30.4	-30.5	-0.1
6.14b	618	568	-26.4	-27.3	-0.9
6.14c	618	578	-22.4	-23.5	-1.1
6.14d	618	588	-18.4	-19.5	-1.1
6.14e	618	598	-14.4	-17.2	-2.8

Table 6.4 Expected and measured velocity profiles shown in Figure 6.16. Velocity phase encoded using waveforms shown in Figure 6.14 with acceleration sensitivity nulled at different expansion points.

second moment (M_2) is nulled. This is supported by the experimental data presented in Table 6.4. The average absolute error is the least (0.8 cm/sec) when velocity at the center of the waveform is encoded. It is apparent from the waveforms in Figure 6.14, that this (Figure 6.14c) is the simplest, and probably the least susceptible to eddy current distortions. The error in velocity are greater the more complicated the waveforms are.

This example points out that instantaneous velocity can be encoded, independent of acceleration, by simple bipolar phase encoding waveforms. Second moment nulling to reduce "errors" in velocity quantification (98) only shifts the point in time at which velocity is encoded.

6.4 Motion Compensation in Echo Planar Imaging

6.4.1 Introduction and Theory

Echo-planar imaging (EPI) and its derivatives, are methods of rapid magnetic field gradient waveform modulation and NMR data acquisition initially developed to decrease scan time in magnetic resonance imaging. EPI's sequence of gradient oscillations are approximately equal to the interval from excitation to acquisition for a single echo or view (20-150 msec) in more conventional 2DFT spin-echo imaging. An advantage of the fast acquisition time of

these techniques is that variations in the spin density distribution function associated with gross patient motion are reduced from one data sampling interval to the next (107,108,109,4,96).

While view-to-view variations in the spin density distribution may be reduced by the rapid acquisition procedure of echo-planar imaging, motion artifacts and signal loss can still occur. The unique characteristics of EPI sequences, such as sampling throughout the balanced bipolar oscillations of the read gradient and relying on accumulation of phase from "blipped" gradients for spatial encoding along the other axis, suggest potential sources of artifact. This added level of complexity is not present in the better understood motion effects seen in conventional MRI.

Motion compensation by gradient moment nulling in EPI in the slice select and frequency encoded directions is accomplished in the same manner as in standard 2D or 3D spin warp imaging. EPI motion desensitization techniques have been proposed which compensate the slice select waveform, and the frequency encoding waveform at specific (108) or alternate (109) rows in K-space. As in spin warp imaging, the choice of moment center is irrelevant in these cases and will not be discussed here.

Dephasing due to motion along the phase encoding axis

in EPI is much different than in standard imaging. The "blipped" echo planar (BEPI) sequence diagrammed in Figure 6.17, relies on the accumulation of phase over the duration of the acquisition to traverse k -space in the phase encoded direction. Phase due to motion also accumulates over the entire acquisition. Constant velocity motion along the PE axis leads to a phase trajectory which has linear and quadratic components. The linear component is the spatial encoding term, while the quadratic term due to velocity produces a complex blurring in the image and a phase offset at the ($k_y = 0$) center of k -space.

As in the spin warp case, the choice of expansion point is critical in the compensation of motion effects in the phase encode direction in EPI, but must be handled differently than the method presented in Section 6.2.1 of this chapter. The work in (108) and (109) have presented methods to achieve a nulled first moment at the central or any specific single phase encoded view. However, the quadratic phase evolution remains; these methods provide no relief for its blurring and signal loss in the final image.

The quadratic phase term results from the encoding of different positions for the moving spins at each row in K -space with the blipped, incremented, or constant waveform. This "chirp" signal is encountered in conventional

Figure 6.17 RF refocussed, blipped phase encoding, echo planar sequence. 180° rf pulses used to generate spin echoes. Blipped phase encoding relies on the accumulation of phase over the duration of the acquisition to phase encode position.

sequences with motion along the frequency encoding axis giving rise to spins with frequency which changes throughout the sampling time. However, while there are currently no practical techniques for dealing with the quadratic phase trajectory in conventional sequences, the short time involved in EPI and the discrete nature of k -space sampling along the phase encoding direction provides opportunity for compensation.

The elimination of the quadratic phase trajectory can be achieved by designing phase encoding waveforms that encode the spatial position of the spins at a single instant of time, independent of velocity. As described in Sections 5.3 and 5.4, this time can be chosen as any point in which the Taylor expansion holds. Depending on the motion, this point can be within, or conceivably outside of the acquisition window in the EPI sequence. The waveforms for the phase encoding steps are designed to have a non-zero zeroth moment for spatial position encoding and a first moment nulled about the instant in time chosen to define the imaged position of the spins. By nulling the first moment at each phase encoding step about a common time point, phase accumulates linearly with the desired imaged position of the spins, removing the offset at $k_y = 0$ and any quadratic component resulting from variable

position encoding with each view (due to motion). The dual lobe phase encoding waveforms shown in Figure 6.18 are designed in this manner to compensate for blurring and signal loss caused by constant velocity motion.

6.4.2 EPI Simulations

Four separate phase encoding waveforms were simulated to investigate the effect of motion along this axis in EPI. A blipped EPI phase encoding waveform (similar to that shown in Figure 6.17), the phase encoding waveform described by Weisskoff (109), a refocussed phase encoding waveform designed to encode the position of the spin at the center of the data acquisition and a sequence designed to encode the position of the spin at the start of the gradient oscillations. All waveforms were designed to have identical lobe durations, time of application, field of view, and resolution. Each lobe was 0.25 msec in duration, were applied every 1 msec in a 64 view sequence. A spin with an initial position of -5.16 cm and a constant velocity of 100 cm/sec along the phase encoding axis was simulated. The phase for this moving spin was sampled at each echo in the four sequences and is shown in Figure 6.19. These phase trajectories were Fourier transformed, and plotted in magnitude format in Figure 6.20 to examine blurring and shifting from use of these gradient waveforms.

Figure 6.18 Gradient echo EPI sequence with velocity compensated, blipped phase encoding waveform. Each bipolar PE waveform is first moment nulled about the center of the entire acquisition. Imaged position of constant velocity spins corresponds the instantaneous position at the moment center.

Figure 6.19 Phase trajectories of an uncompensated, blipped waveform, a waveform with first moment nulling to compensate phase offset only, and two new sequences which compensate for the quadratic phase trajectory due to velocity as described in the text. The difference in the slopes of the linear phase trajectories of the new sequences illustrates the encoding of the position of a moving spin at different points in time by nulling moments about different expansion points.

Figure 6.20 The quadratic term in the k_y phase evolution creates a complex convolution in the final image. The normal blipped waveform and earlier compensation methods both experience this modulation induced blurring and encode the average position of the spin throughout the sequence. The phase linearization eliminates the blurring, regardless of the velocity. The difference in encoded position by the two sequences is a result of the selection of different points of expansion.

Each individual phase encoding lobe is short in time, and gives rise to only an incremental change in motion dephasing. Because blipped EPI relies on the accumulation of phase due to position over the acquisition, two things occur: 1) the spins move to new locations throughout the scan and 2) velocity induced dephasing accumulates. This velocity induced dephasing has been estimated as approximately 30 times higher than along the read axis, by the $k_y = 0$ step, in some EPI systems currently available. This quadratic distortion and offset of the ideally linear phase trajectory is identical to the condition of phase offset at the echo and the quadratic phase evolution during sampling that existed prior to gradient moment nulling techniques. While GMN can only account for the phase offset at the echo, the quadratic distortion can be removed as shown here by designing gradient waveforms for each step through k-space with moments nulled about a single instant of time. This point in time can be selected to encode the instantaneous position of the spins, independent of velocity (32,50). Examination of Figure 6.20 shows that different spatial positions can be encoded by altering the point of expansion, and that the blurring can be eliminated. Note that in the sequence simulated, a constant velocity of 100 cm/sec can give rise to a complex

blur over approximately $1/5$ of the field of view. The broadening observed in the spatial localization of the moving spins in the linearized phase encoding methods is only due to the encoded position of the spins not falling at the center of a pixel. It is interesting to note that the quadratic phase evolution and subsequent image blurring was initially observed in conventional sequences from motion along the read axis. Now, the blurring appears on the PE axis since the EPI phase encoding axis relies on the accumulation of phase over the acquisition and its duration approaches that of conventional read waveforms.

6.5 Significance of the Expansion Point in Optimal Waveform Design

The theory presented in Sections 5.3 and 5.4 is also important in the use of formal optimization techniques in gradient waveform design. The theory indicates that to reduce motion sensitivity, it only makes sense to minimize a specific waveform moment if all lower order moments are zero. Thus, motion sensitivity of a gradient waveform can potentially be minimized by constraining the first n moments of a waveform to zero and minimizing the next higher moment.

6.6 Conclusions

In summary, moments describe motion sensitivity at an instant of time, and the interpretation of phase due to motion is dependent on the point of expansion chosen. Only when all lower order moments are zero are time moments indicative of sensitivity or insensitivity to a specific derivative of position throughout the waveform. These results are important in the design of both motion compensating and motion encoding gradient waveforms.

7. Conclusions and Future Directions

7.1 Conclusions

The overall theme of this thesis has been gradient waveform design for MRI, with some emphasis on motion compensation and encoding. In the first four chapters, a new gradient waveform design method based on formal optimization techniques was developed and demonstrated. In Chapters 5 and 6, the significance of the moment center or expansion point in gradient waveform design was developed and shown by computer simulation and phantom and human experiments. The advantages and limitations of these ideas and proposed techniques are briefly summarized in this section.

7.1.1 Optimization of Gradient Waveforms

The optimal gradient waveform design technique proved to possess a number of advantages over the conventional, algebraic methods discussed in Chapter 1.

Using the proposed design method, the resulting gradient waveforms are optimal with respect to any one of many possible design objectives. Also, the waveforms are guaranteed to be feasible with respect to the constraints which define the limits of the particular gradient system and pulse sequence. Optimality and feasibility are conditions which can not be met efficiently by standard

algebraic design.

The proposed discrete, point-by-point amplitude waveform parameter set also offers advantages. Artificial constraints on waveform shape imposed by multi-lobe design methods are eliminated, extending the feasible solution space to the hardware defined limits. Also, the tasks of determining waveform lobe placement and duration are eliminated. These advantages were demonstrated by the unusual shapes of some of the motion compensated waveforms.

The formulation of the waveform optimization problem as a linear or quadratic programming problem eliminates many of the difficulties associated with solving constrained optimization problems, and permits easy solution on a personal computer system. It was also demonstrated in Chapter 4, that by changing the hardware constraints, the performance of alternate gradient systems is easily investigated. Eliminating the hardware limits provides a means of evaluating the gradient performance characteristics required to achieve specific imaging goals.

To go with these advantages, there are some limitations which should also be pointed out. The linear or quadratic programming formulation excludes nonlinear constraints from the design. The most notable nonlinear constraints are RMS current limits and diffusion sensitivity. Alternative nonlinear programming techniques

are required to handle these and any other nonlinear constraints.

Another limitation of the problem formulation is that it is set up to handle only single objective functions. That is, only one measure of waveform quality is optimized in any design. Methods of including additional objectives as constraints, or as weighted terms in a multi-objective function were discussed.

While not a limitation, it should also be noted that optimization has its most profound impact when excess gradient amplitude, and/or time, are available in the sequence. At short echo times and when no motion compensation is desired, optimization may provide little or no difference in waveform design from multi-lobe algebraic techniques. It is the more complicated, motion compensated, spin or multi echo waveforms which stand to show most improvement from the optimal design techniques. In uncompensated, short echo time sequences, the best waveform design may be obvious. However, optimization will always ensure that maximum gradient performance is obtained.

7.1.2 Significance of the Expansion Point in Waveform Design

Theoretical analysis, computer simulations, phantom

and human imaging experiments were presented to define the relationship between the moment center or expansion point of the Taylor Series description of motion, and waveform motion sensitivity. Several important theoretical points and implications in waveform design arose from the analysis and experiments.

The theoretical significance of the expansion point can be summarized in two statements: (1) Gradient moment values depend on choice of moment center when lower order moments are not zero; and (2) moment values are, in general, related to the sensitivity of the waveform to the **instantaneous** derivative of position evaluated at the moment center.

Several applications of these points in gradient waveform design were demonstrated in Chapter 6. All of these pertain to the phase encode axis, for either motion compensation, or motion encoding. Elimination of misregistration artifacts due to blood flow oblique to imaging axes was demonstrated by phantom and human imaging experiments. Encoding of instantaneous derivatives of position independent of higher order derivatives was demonstrated by the linear motion phantom. Compensation of blurring and signal loss due to motion along the phase encoded axis in echo planar imaging was shown by computer simulation.

One limitation of motion compensation on the phase encoding axis is the additional gradient activity required, meaning either additional time or gradient power is needed. This is the usual tradeoff which must be considered in any motion compensation scheme.

7.2 Future directions

Much of the work presented in this thesis began with the future directions proposed in the Ph.D. thesis of Jeffrey Duerk (27). It is hoped that this legacy can continue with some of the suggestions made in the following sections.

7.2.1 Optimization of Gradient Waveforms

The goal in this thesis of formulating and solving the problem of gradient waveform design as one of constrained optimization has been successfully met. However, the proposed method is open to expansion and improvement in several directions. Most of the following suggested areas of future research address the limitations discussed in the previous section.

The optimization of some objectives has generated some simple waveform functions (linear ramps, triangular lobes, quadratics). It may be possible to use this information advantageously to reduce the parameter set and speed up

solution for real time waveform design. For example, if it is known *a priori* that triangular lobes form the minimum RMS current solution for a particular waveform, a very small parameter set could be used to define the waveform without reducing the feasible space. Difficulties may arise in expressing the objective and constraints as functions of the new parameter set.

Multi-objective optimization was discussed briefly in Chapter 2; there is still room for research in this area of waveform design. Techniques are available to combine design objectives to achieve compromises in waveform characteristics. In many cases, the best approach may be to constrain several objectives to acceptable values while optimizing another. This was the method used to some extent in this thesis. It could be extended to include additional, nonlinear constraints such as RMS current and diffusion sensitivity.

Generalizing the optimization to include non-quadratic objectives and nonlinear constraints, the waveform design problem could be extended to include additional pulse sequence parameters, giving rise to a number of possible design goals. The design technique, as presented here, solves only part of the sequence development problem. It is still up to the sequence designer to provide the appropriate sequence type, echo symmetry, bandwidth and

other parameters. By including these and other sequence parameters (TE, TR, TI, sampling duration, rf pulse duration, etc.) as variables, it may be possible to optimize objectives such as image contrast and S/N.

Gradient system response modelling is an area of research which, together with the optimization of discrete gradient waveforms, could improve the accuracy of the generated waveforms. As discussed in Chapter 2, a gradient system transfer function model is easily incorporated into optimal design protocol. This is yet another example of how a *priori* information about the gradient system can be included into the design protocol itself. It may even be possible to extend this concept to spatial modelling of gradient field distortion due to eddy currents and imperfect coil design. Higher order, nonlinear gradient fields could possibly be used to compensate for these spatial distortions.

7.2.2 Significance of the Expansion Point

The explanation of the role of the moment center or expansion point given in Chapter 5 opens up several areas of future research in motion compensation and encoding. Perhaps the most important of these will be an investigation of the effects of spatial misregistration of flowing blood in angiographic imaging. The combined

effects of misregistered blood overlaying adjacent tissue, and adjacent blood of different velocity, may contribute significantly to variations in vessel signal intensity. A thorough investigation utilizing a flow phantom with known motion characteristics is required to quantify this paradoxical enhancement. The human images shown in Chapter 6 suggest that misregistration may play a large role in the appearance of smaller vessels.

The simulation of motion compensation of the phase encoding waveform in echo planar imaging demonstrated in Chapter 6 suggests that, contrary to popular belief, motion may contribute significantly to signal loss and blurring in EPI. This hypothesis, and the impact of the motion compensation scheme proposed in Chapter 6, need to be investigated experimentally to examine practical limitations, and possible benefits.

The linear motion phantom, described in detail in Appendix A, also opens up some possibilities for future investigations. The phantom may prove useful in the investigation of respiratory and cardiac gating techniques, as well as velocity and acceleration encoding schemes.

Appendix A. Linear Motion Phantom

A.1 Introduction

A motion phantom system was required to experimentally verify the theory put forth in Chapter 5 concerning the significance of the expansion point in the design of motion compensating and encoding gradient waveforms. The important requirements of this phantom are as follows: (1) the velocity, acceleration, and possibly higher orders of phantom motion must be accurately controlled; (2) the phantom must move without any spatial variation in velocity, acceleration, etc.; and (3) the phantom must be able to reasonably reproduce the velocities and accelerations found in the human body.

Several types of motion phantoms for MRI have been presented in the literature, none meet all of these requirements. Most motion phantoms used in MRI have been designed with the goal of mimicking blood flow. Some examples are simple laminar flow phantoms (110) using gravity fed tubes, pulsatile flow phantoms (111) using special pumps, a "leaky valve" phantom (112,113) using a controlled pressure gradient across an orifice, and a computer controlled flow phantom (114) which uses a stepper motor to push and pull fluid through a tube. None of these phantoms can accurately control both the velocity

and the acceleration of the moving fluid, and all produce a spatial distribution of velocities which complicates an evaluation of the effects of motion on MRI. A rotating solid disk phantom (115) has also been developed which avoids some of the problems associated with moving liquids, but still does not afford direct control of linear acceleration, and generates a spatially varying velocity.

A.2 Technical Specifications

With the desired characteristics in mind, the linear motion phantom system depicted in the sketch in Figure A.1 was designed and constructed. A brief description of the technical specifications of this phantom, as well as some motion profile accuracy test results, and recommendations for design improvements, are provided in the following sections of this appendix.

The linear motion phantom is driven by a computer controlled stepper motor (Model M093-FF-402, Superior Electric, Bristol, CT). This motor is controlled by an 80386 based personal computer equipped with a PC34 Intelligent Motor Controller (Oregon Micro Systems, Inc. Beaverton, OR). The PC34 generates step and direction pulses for control of the stepper motor.

A library of simple ASCII commands is provided with

Figure A.1 Diagram of the linear motion phantom system. Personal computer system controls motor velocity profile. Ballscrew assembly is used to convert rotary motion of the motor shaft into linear phantom motion.

```

*Veltrig
*Linear Motion Phantom Test Program
*Trapezoidal velocity profile
*for imaging constant velocity motion
*Load init first to establish origin

*X-axis only
ax

*convert units to cm.
uu787.40157

*Constant acceleration = 200cm/sec/sec
ac400

*Constant deceleration = 200cm/sec/sec
dc400

*Peak (constant) velocity = 40cm/sec
vl40

*Loop moving back and forth 16cm
*Results in a trapezoidal velocity profile
*Set bit 0 at the start of each cycle to trigger imager
*Reset bit zero at end of each cycle
*Motion cycle takes 1200 msec
*Loop counter set at 10000 reps

bl0
ls10000
  bh0
  ma10 gu
  ma0 gu
  bl0
le

```

Figure A.2 An example motion control program. A library of ASCII command codes is provided with the PC34 motor controller. Some of these commands are used in this simple example to execute the trapezoidal velocity profile shown in Figure 6.5.

the PC34 to facilitate high level language programming. An example program is listed in Figure A.2. This sequence of commands generates the motion profile plotted in Figure 6.5. Linear, parabolic, and sinusoidal velocity profiles can be implemented with the PC34 controller. Only linear velocity ramps (constant acceleration) were utilized in the experiments discussed in Chapter 6, but others may prove useful in future experiments, and in simulation of physiological motion.

The PC34 provides control signals to a Model 3180-PT10 (Superior Electric, Bristol CT) packaged translator stepper motor drive. This unit converts the input pulses from the PC34 controller into the properly sequenced drive signals and current levels needed to operate the stepper motor.

The 3180-PT10 provides microstepping control; each step is equivalent to $.18^\circ$ of shaft revolution. A standard step is considered to be 1.8° . Microstepping provides finer position resolution, and smoother operation at low velocities. For the 1" lead ball-screw utilized (Comptrol, Inc., Cleveland, OH), each microstep translates into $.0005"$ of linear motion. The actual positioning accuracy of the stepper motor, even with microstepping, is ± 1 full step, or $\pm .005"$. The lead deviation tolerance of the ball screw ($\pm .003"$) further degrades this accuracy.

The stepper motor was chosen based on the torque-

velocity characteristics required to move the phantom over a reasonable range of simulated physiological motion. CAMAS Torque-finder software (Superior Electric, Bristol, CT) was used to determine the motor and drive combination required to generate the desired velocities and accelerations. The M093 motor/3180 PT10 drive combination is capable of accelerating the phantom at approximately 400 cm/sec/sec, with a peak velocity of about 65 cm/sec.

A ballscrew assembly (Comptrol, Inc., Cleveland, OH) converts the rotary motion of the motor shaft into the linear phantom motion. The motor shaft is coupled to the ball screw with an aluminum flexible shaft coupler (Helical Products Company, Inc., Santa Maria, CA). A ball-bearing type screw was chosen over a simple ACME screw due to its high efficiency (90%), minimal starting friction, minimal backlash (.01" max.), and accuracy (.003"/foot screw length).

The ballscrew assembly is connected via a 16' Delrin drive shaft (WENTEC, Inc., Cleveland, OH) to a gel-filled Delrin dovetail slider located within the bore of the imaging magnet. Plastic bearing mounts are mounted to plywood which rests on the imager patient couch to support the drive shaft over the 16' length from the ball screw to the phantom itself. These bearing mounts, sketched in Figure A.3, utilize Acetron oil-impregnated, self-

Figure A.3 Sketch of a Delrin bearing mount used to support the phantom drive shaft. All dimensions in inches. The inner surface of the bearing mount is lined with Acetron, an oil impregnated self-lubricating plastic, to minimize friction. In addition, the shaft is coated with mineral oil to further reduce vibration.

lubricating plastic to minimize friction.

The required shaft length was determined by operating the motor in the magnet room while scanning a uniform phantom. No degradation in signal-to-noise was observed with the motor placed 16' or more from magnet isocenter. At this shaft length, the desired phantom velocities and accelerations could be attained. As seen in Figure A.1, the motor shaft is aligned with the static field of the imaging magnet. For safety reasons, no attempt was made to bring the motor any closer to the magnet.

The phantom itself is a Delrin dovetail slider with a section approximately 10 cm by 12 cm by 2 cm deep bored out to hold gelatin. A rough sketch is provided in Figure A.4. The slide track, shown in Figure A.5, is mounted to wood which sits in the headholder of the patient couch. Mineral oil is used on the drive shaft and phantom slide to minimize friction.

A mixture of animal hide gelatin, water, and formaldehyde was used as phantom material (116). The object in mixing the phantom material was not to replicate the relaxation characteristics of human tissue, but to produce a substance stiff enough to minimize vibrations, while still providing an adequate NMR signal to measure phantom position.

Figure A.4 Sketch of the motion phantom. All dimensions in inches. The phantom consists of a gel filled trough in a dovetail type slider. A stiff mixture of animal hide gelatin is used to fill the phantom.

DELFIN Dovetail Slide Track

Figure A.5 The dovetail slide track. All dimensions in inches. The Delrin track is coated with mineral oil to reduce friction.

Figure A.6 Programmed and measured time-varying phantom position profile. Each circle (with error bars) represents the phantom position measured by CINE MR imaging. All measured positions fall within the error bars of ± 1 pixel measurement error.

A.3 Phantom Cine Imaging

The field of the imaging magnet made an independent measure of phantom position difficult. Therefore, CINE MR studies were utilized to evaluate phantom positioning accuracy. CINE imaging generates a sequence of images, each acquired at a different delay after a triggering pulse. The PC34 controller provided a gating pulse at the initiation of each phantom motion cycle. The results of an example CINE study are presented in this section.

Table A.1 lists the acquisition parameters used in a CINE study of an example trapezoidal velocity motion profile. Sixty-four "frames" of data were collected at 22.344 msec intervals. This covered phantom position over slightly more than one full motion cycle of 1200 msec duration. Phantom motion was along the phase-encoded direction. In each of the resulting 64 images, the positions of the leading and trailing edges of the phantom were measured directly off of the viewing screen, and averaged to obtain an estimate of the position of the phantom center.

Repeat Time	2400 msec
Echo Time	12 msec
RF Flip Angle	10°
Motion Cycle Duration	1200 msec
Number of Frames	64
Time Between Frames	22.344 msec

Table A.1 Acquisition parameters for CINE imaging of linear motion phantom.

The 64 measured positions are indicated in Figure A.6, superimposed on the programmed time varying position profile. The maximum deviation found between any measured and expected value was less than one pixel, verifying the positioning accuracy of the phantom. Similar results were found for other motion profiles.

A.4 Recommended Design Modifications

The design and construction of the linear motion phantom was a learning experience and revealed some important considerations in motion phantom design. The phantom was successfully used to demonstrate the theoretical concepts presented in Chapter 6. It provided

experimental verification that instantaneous position and velocity are encoded at the predicted time point for constant velocity and constant acceleration motion. This could not have been accomplished with a fluid flow phantom. However, the phantom could not be utilized to evaluate the effectiveness of gradient moment compensation due to excessive vibration in the phantom system. Vibration results in a random view-to-view motion which causes ghosting regardless of the level of motion compensation. Two likely sources of vibration exist in the phantom system.

First, even with microstepping, the stepper motor moves in discrete intervals, not in a completely smooth, continuous fashion. Thus, there will be vibration inherent to the system unless some damping is provided between the motor and drive shaft. Rubber coupling devices exist for this purpose.

A second possible source of vibration in the phantom system lies in the drive shaft supports. The use of multiple supports, spaced approximately 12" apart, is very unforgiving of deviations in shaft diameter and straightness. Alignment of the shaft supports was extremely difficult and time consuming. Even with careful alignment, several of the supports displayed severe vibration, indicating excessive friction and loading on the motor as well. Perhaps a more successful design would be

some type of piston device, in which the drive shaft slides within a continuous tube. Alternate drive shaft materials should also be investigated to produce a straighter, rounder shaft.

References

1. Lauterbur, P.C., "Image Formation by Induced Local Interactions: Examples Employing Nuclear Magnetic Resonance," *Nature*, vol. 242, pp. 190-191 (1973)
2. Mansfield, P. and Morris, P.G., *NMR in Biomedicine*, Academic Press, New York, p 32 (1982)
3. Kumar, A., Welte, D., and Ernst, R.R., "NMR Fourier Zeugmatography," *J. Magn. Reson.*, vol. 18, pp. 69-83 (1975)
4. Edelstein, W.A., Hutchinson, J.M.S., Johnson, G., and Redpath, T.W., "Spin warp NMR imaging and Applications to Whole-Body Imaging," *Physics Med. Biol.*, vol. 25, pp. 751-756 (1980)
5. Slichter, C.P., *Principles of Magnetic Resonance*, (M. Cardona, P. Fulde, and H.J. Quessier, eds.), vol. 1 in Springer Series in Solid State Sciences, Springer-Verlag, Berlin and New York, (1978)
6. Abragam, A., *Principles of Nuclear Magnetism*, Oxford University Press, New York, New York, (1961)
7. Hinshaw, W.S. and Lent, A.H., "An Introduction to NMR Imaging: From the Bloch Equation to the Imaging Equation," *Proceedings of the IEEE*, vol. 71, no. 3, pp. 338-350 (1983)
8. Thomas, S.R., Busse, L.J., and Schenck, J.F., "Gradient Coil Technology," in *NMR in Medicine: The Instrumentation and Clinical Applications* (ed. S.R. Thomas and R.L. Dixon), American Institute of Physics, Inc., (1986)
9. Hinshaw, W.S., "Image Formation by Nuclear Magnetic Resonance: The Sensitive Point Method," *J. Appli. Phys.* vol. 47, 3709-3721 (1976)
10. Hinshaw, W.S., Bottomley P.A., and Holland, G.N., "Radiographic Thin-Section Imaging of the Human Wrist by Nuclear Magnetic Resonance," *Nature* vol. 270, pp. 722-723 (1977)
11. Johnson, G., Hutchinson, J.M.S., Redpath, T.W., and Eastwood, L.M., "Improvements in performance time for simultaneous three-dimensional NMR imaging,"

J. Magn. Reson., vol. 54, pp. 374-384 (1983)

12. Mansfield, P. and Maudsley, A.A., "Planar Spin Imaging by NMR," *J. Phys. Chem.: Solid St. Phys.*, vol. 9, pp. 409-411 (1976)
13. Ljunggren, S., "A Simple Graphical Representation of Fourier-Based Imaging Methods," *J. Magn. Reson.*, vol. 54, pp.338-343 (1983)
14. Twieg, D.B., "The k-Trajectory Formulation of the NMR Imaging Process with Applications in Analysis and Synthesis of Imaging Methods," *Med. Phys.*, vol. 10(5), pp. 610-621 (1983)
15. Bracewell, R., *The Fourier Transform and Its Applications*, McGraw-Hill Book Company, New York, NY (1965)
16. Hoult, D.I., *J. Magn. Reson.*, **26**, 165 (1977).
17. Emsley, L. and Bodenhausen, G., "Self-Refocussing 270° Gaussian Pulses for Slice Selection without Gradient Reversal in Magnetic Resonance Imaging," *Magn. Reson. Med.*, vol. 10, pp. 273-281 (1989)
18. Hardy, C.J., and Bottomley, P.A., "Slice Selection without Gradient Refocussing? A Simulated Annealing Approach," in *Book of Abstracts, Society of Magnetic Resonance in Medicine, Seventh Annual Meeting*, p 657 (1988)
19. Bailes D.R., Young, I.R., Thomas, D.J., Straughan, K., Bydder, G.M., Steiner, R.E., "NMR Imaging of the Brain Using Spin-Echo Sequences," *Clinical Radiology*, vol. 33, pp. 395-414, (1982)
20. Young, I.R., Bailes, D.R., Burl, M., et al., "Initial Clinical Evaluation of a Whole Body Nuclear Magnetic Resonance (NMR) Tomograph," *J. Comput. Assist. Tomogr.*, vol. 6, pp. 1-18, (1982)
21. Haase, A., Frahm, J., Matthaei, D., Hanicke, W., and Merboldt, K.D., "FLASH Imaging: Rapid NMR Imaging Using Low Flip-Angle Pulses," *J. Magn. Reson.*, vol. 67, pp. 258-266 (1986)

22. Wehrli, F.W., *Fast-Scan Magnetic Resonance Principles and Applications*, Raven Press, Ltd., New York, pp. 10-15 (1991)
23. Tkach, J.A., "Signal- and Contrast-to-Noise in Fast Magnetic Resonance Imaging: Expectation and Reality," Thesis, Case Western Reserve University, Cleveland, OH (1988)
24. Graumann, R., Oppelt, A., and Stetter, E., "Multiple-Spin-Echo Imaging with a 2D Fourier Method," *Magn. Reson. Med.*, vol. 3, pp. 707-721 (1986)
25. Zur, Y., Zou, X., and Neuringer, L.J., "Multiecho, Spin-Echo Sequence to Eliminate Unwanted Echoes," *Magn. Reson. Med.*, vol. 19, pp. 464-469 (1991)
26. Wendt, R.E., Murphy, P.H., Ford, J.J., Bryan, R.N., and Burdine, J.A., "Phase Alterations of Spin Echoes by Motion Along Magnetic Field Gradients," *Magn. Reson. Med.*, vol. 2, pp. 527-533 (1987)
27. Duerk, J.L., "A Magnetic Resonance Imaging Gradient Modulation Technique for Motion Artifact Reduction and Flow Quantification," Thesis, Case Western Reserve University, Cleveland, OH (1986)
28. Moran, P.R., and Moran, R.A., "Imaging True Motion Velocity and Higher Order Motion Quantities by Phase Gradient Modulation Techniques in NMR Scanners," in *Technology of Nuclear Magnetic Resonance*, Esser and Johnston, Eds., Soc. Nuc. Med. Inc., New York, (1985)
29. Wood, M.L., and Henkelman, R.M., "MR Image Artifacts from Periodic Motion," *Medical Physics*, vol. 12(2), pp. 143-151 (1985)
30. Pattany, P.M., Phillips, J.J., Chiu, L.C., et al., "Motion Artifact Suppression Technique (MAST) for MR Imaging," *J.Comput. Assist. Tomogr.*, vol. 11, no. 3, pp. 369-377 (1987)
31. Larson, T.C., Kelly, W.M., Ehman, R.L., Wehrli, F.W., "Spatial Misregistration of Vascular Flow during MR Imaging of the CNS: Cause and Clinical Significance," *AJR*, vol. 155, pp. 1117-1124 (1990)

32. Simonetti, O.P., Duerk, J.L., "Compensation of Oblique Flow Misregistration Artifacts," Book of Abstracts, Society of Magnetic Resonance in Medicine, Tenth Annual Meeting, p 1165 (1991)
33. Frank, L.B., Crawley, A.P., Buxton, R.B., and Musicus, B.R., "Elimination of Oblique Flow Artifacts," in Book of Abstracts, Society of Magnetic Resonance in Medicine, Tenth Annual Meeting, p 832 (1991)
34. Duerk, J.L., and Simonetti, O.P., "Theoretical Aspects of Motion Sensitivity and Compensation in Echo Planar Imaging," *JMRI*, vol. 1, no. 6, pp. 643-650 (1991)
35. Thompson, W.J., *Computing in Applied Science*, pp. 27-33, Wiley & Sons, New York, NY (1984)
36. Duerk, J.L., and Pattany, P.M., "Analysis of Imaging Axes of Significance in Motion Artifact Suppression Technique (MAST): MRI of Turbulent Flow and Motion," *Magn. Reson. Imaging*, vol. 7, pp. 251-263 (1989)
37. Duerk, J.L., Simonetti, O.P., Hurst, G.C., and Motta, A.O., "MEMMORE: Multi-Echo, Multi-Moment Refocussing of Motion in MRI," *Magn. Reson. Imaging*, vol. 8, pp. 535-541 (1990)
38. Ahn, C.B., and Cho, Z.H., "Analysis of Eddy Currents in Nuclear Magnetic Resonance Imaging," *Magn. Reson. Med.*, vol. 17, pp. 149-163 (1991)
39. Morich, M.A., Lampman, D.A., Dannels, W.R., and Goldie, F.T., "Exact Temporal Eddy Current Compensation in Magnetic Resonance Imaging Systems," *IEEE Trans. Med. Imaging*, vol. 7, no. 3, pp. 247-254 (1988)
40. Mansfield P, Chapman, B., *Active Magnetic Screening of Gradient Coils in NMR Imaging*, *J. Magn. Res.*, vol. 66, pp. 573-576 (1986)
41. Moran, P.R., "A Flow Velocity Zeugmatographic Interlace for NMR Imaging in Humans," *Magn. Reson. Imaging*, vol.1, pp. 197-203 (1982)

42. Constantinesco, A., Mallet, J.J., Bonmartin, A., Lallot, C., and Briguet, A., "Spatial or Flow Velocity Phase Encoding Gradients in NMR Imaging," *Magn. Reson. Imaging*, vol. 2, pp. 335-340 (1984)
43. van Dijk, P., "Direct Cardiac NMR Imaging of Heart Wall and Blood Flow Velocity," *J. Comp. Assist. Tomogr.*, vol. 8, pp.429-436 (1984)
44. Bryant, D.J., Payne J.A., Firmin, D.N., and Longmore, D.B., "Measurement of Flow with NMR Imaging using a Gradient Pulse and Phase Difference Technique," *J. Comput. Assist. Tomogr.*, vol. 8, pp. 588-593 (1984)
45. Dumoulin, C.L., and Hart, H.R., "Magnetic Resonance Angiography," *Radiology* vol.161, pp. 717-720 (1986)
46. Nishimura, D.G., Macovski, A., and Pauly, J.M., "Magnetic Resonance Angiography," *IEEE Trans. Med. Imaging*, vol. 5, no. 3, pp. 140-151 (1986)
47. Laub, G.A., and Kaiser, W.A., "MR Angiography with Gradient Motion Refocussing," *J. Comput. Assist. Tomogr.*, vol. 12, pp. 377-382 (1988)
48. Haacke, E.M., and Lenz, G.W., "Improving MR Image Quality in the Presence of Motion by Using Rephasing Gradients," *AJR*, vol. 148, pp. 1251-1258 (1987)
49. Hahn, E.L., "Detection of Sea-Water Motion by Nuclear Precession," *J. Geophys. Res.*, vol. 65, no.2, pp. 776-777 (1960)
50. Simonetti, O.P., Wendt, R.E., and Duerk, J.L., "Significance of the Point of Expansion in Interpretation of Gradient Moments and Motion Sensitivity," *JMRI*, vol. 1, pp. 569-577 (1991)
51. Norris, D.G., "Acceleration Imaging by NMR," *Proc. Sci. Program of the Fourth Meet. of the Society of Magn. Reson. Med.*, London, England, pp. 593-594 (1985)

52. LeRoux, P., and Floch, J., "Cancellation of the Shear Rate Influence on Flow Velocity Imaging," in Book of Abstracts, Society of Magnetic Resonance in Medicine, Fourth Annual Meeting, pp.585-586 (1985)
53. Wendt, R.E., "Interactive Design of Motion Compensated Gradient Waveforms with a Personal Computer Spreadsheet Program," *JMRI*, vol. 1, pp. 87-92 (1991)
54. Pattany, P.M., and McNally, J.E., "Motion Artifact Suppression Technique of Magnetic Resonance Imaging," U.S. Patent 4,728,890, (1988)
55. Groen, J.P., van Dijk, P., and In den Kleef, J.J.E., "Design of flow Adjustable Gradient Waveforms," in Book of Abstracts, Society of Magnetic Resonance in Medicine, Sixth Annual Meeting," p 868 (1987)
56. Yamagata, H., Buonocore, M.H., Telford, B., and Sanders, J., "Optimized Gradient Pulses for MR Quantitative Flow Imaging and Angiography," *Radiology*, vol. 173(P), p 162 (1989)
57. Xiang, Q.S., and Nalcioglu, O., "A Formalism for Generating Multiparametric Encoding Gradients in NMR Tomography," *IEEE Trans. Med. Imaging*, vol. 6, no. 1, pp. 14-20, (1987)
58. Chang, R., "Electrical Multipoles: An Aid to Analysis and Design of Complex Gradient Sequences in Magnetic Resonance Imaging," in Book of Abstracts, Society of Magnetic Resonance in Medicine, Sixth Annual Meeting, p 873 (1987)
59. Keller, P.J. and Wehrli, F.W., "Gradient Moment Nulling through the Nth Moment. Application of Binomial Expansion Coefficients to Gradient Amplitudes," *J. Magn. Reson.*, vol. 78, pp. 145-149 (1988)
60. Wendt, R.E., and Murphy, P.H., "Interactive Design of Motion-Compensating Gradients using a Personal Computer Spreadsheet Program," in Book of Abstracts, Society of Magnetic Resonance in Medicine, Seventh Annual Meeting , p 124 (1988)

61. Wendt, R.E., Nitz, W., and Murphy, P.H., "Triangular Gradient Pulses for Motion Compensation and Encoding in NMR Imaging," in Book of Abstracts, Society of Magnetic Resonance in Medicine, Seventh Annual Meeting, p 124 (1988)
62. Pipe, J.G., and Chenevert, T.L., "A Prograssive Gradient Moment Nulling Design Technique," *Magn. Reson. Med.*, vol. 19, pp. 175-179 (1991)
63. Chenevert, T.L., Fechner, K.P., and Gelblum, D.Y., "Utility of Motion Corrective Gradients for MR Angiography and Motion Artifact Suppression," in Book of Abstracts, Society of Magnetic Resonance in Medicine, Sixth Annual Meeting, p 867 (1987)
64. King, K.F., and Moran, P.R. "A Unified Description of NMR Imaging, Data-collection Strategies, and Reconstruction," *Med. Phys.*, 11(1), pp. 1-14 (1984)
65. Conolly, S., Nishimura, D., and Macovski, A., "Optimal Control Solutions to the Magnetic Resonance Selective Excitation Problem," *IEEE Trans. Med. Imaging*, 5(2), pp. 106-115 (1986)
66. Murdoch, J.B., Lent, A.H., and Kritzer, M.R., "Computer-Optimized Narrowband Pulses for Multislice Imaging," *J. Magn. Reson.*, 74, pp. 226-263 (1987)
67. Mao, J., Virapongse, C., and Fitzsimmons, J.R., "A Study of Optimization of the Complex Hyperbolic Secant Inversion Pulses," *Magn. Reson. Med.*, 13, pp. 293-298 (1990)
68. Conolly, S., Nishimura, D., Macovski, A., and Glover, G., "Variable-Rate Selective Excitation," *J. Magn. Reson.*, 78, pp. 440-458 (1988)
69. Dreher W., and Börnert, P. "Pulse Sequence and Parameter Choice in NMR Imaging as a Problem of Constrained Multidimensional Nonlinear Optimization," *Magn. Reson. Med.*, 8, pp. 16-24 (1988)
70. Epstein, F.H., and Mugler, J.P., "Application of the Simulated Annealing Algorithm to Pulse Sequence Parameter Optimization," in "Proceedings, 10th

Annual Meeting of the Society of Magnetic Resonance in Medicine," p 1180 (1991)

71. Reklaitis, Ravindran, and Ragsdell, in "Engineering Optimization Methods and Applications," Wiley, (1983)
72. Pykett, I.L., Rzedzian, R.R., "Instant Imaging of the Body by Magnetic Resonance," *Magn. Reson. Med.*, vol. 5, pp. 563-571, (1987)
73. Simonetti, O.P., Duerk, J.L. and Hurst, G.C., "Optimal Gradient Waveforms for Motion Artifact Suppression," *Magn. Reson. Imaging*, 8(S1), p 26 (1990)
74. Jensen, D.J., Brey, W.W., Delayre, J.L., and Narayana, P.A., *Med. Phys.*, 14, 859 (1987)
75. Turner, R., and Bowley, R.M., "Passive Screening of Switched Magnetic Field Gradients," *J. Phys. E*, 19, 876 (1986)
76. Gerald, C.F., "Applied Numerical Analysis," Addison-Wesley, Reading, MA, (1980)
77. LeBihan, D., Breton, E., Lallemand, D., Grenier, P., Cabanis, E., Laval-Jeantet, M., "MR Imaging of Intravoxel Incoherent Motions: Application to Diffusion and Perfusion in Neurologic Disorders," *Radiology* 161, pp. 401-407, (1986)
78. LeBihan, D., Breton, E., Lallemand, D., Aubin, M., Vignaud, J., Laval-Jeantet, M., "Separation of Diffusion and Perfusion in Intravoxel Incoherent Motion MR Imaging," *Radiology* 168, 497-505 (1988)
79. Nishimura, D., Macovski, A., Jackson, J., et al., "Magnetic Resonance Angiography by Selective Inversion Recovery using a Compact Gradient Echo Sequence," *Magn. Reson. Med.*, 8, pp. 96-103 (1988)
80. Haacke, E.M., Masaryk, T.J., Wielpolski, P.A., Zypman, F.R., Tkach, J.A., Amatur, S., Mitchell, J., Clampitt, M., and Paschal, C., "Optimizing Blood Vessel Contrast in Fast Three-Dimensional MRI," *Magn. Reson. Med.*, vol. 14, pp. 202-221 (1990)

81. Simonetti, O.P., Duerk, J.L., and Hurst, G.C., "Optimal Gradient Moment Compensation at Reduced Echo Times," in Book of Abstracts, Society of Magnetic Resonance in Medicine, Ninth Annual Meeting, p 465 (1990)
82. Luenberger, D.G., "Introduction to Linear and Nonlinear Programming," Addison-Wesley, Menlo Park, CA, (1973)
83. Gill, P.E., Murray, W., and Wright, M.H., "Practical Optimization", Academic Press, New York, (1981).
84. Falk, J.E., and Hoffman, K.L., "Concave Minimization via Collapsing Polytopes," *Operations Research*, 34(6), pp.919-929 (1986).
85. Fletcher, R. "Practical Methods of Optimization, Volume 2, Constrained Optimization," John Wiley and Sons, New York, (1981)
86. Dantzig, G.B., Orden, A., and Wolfe, P., *Pacific J. Math.* 5, p 183 (1955).
87. Chankong, V., and Haimes, Y.Y., "Multiobjective Decision Making: Theory and Methodology," Elsevier, North-Holland, New York (1983)
88. Prasad, P.V., and Nalcioğlu, O., "A Modified Pulse Sequence for in Vivo Diffusion Imaging with reduced Motion Artifacts," *Magn. Reson. Med.*, 18, 116 (1991)
89. Hurst, G.C., Hua, J., Duerk, J.L., and Cohen A.M., "Intravascular (Catheter) NMR Receiver Probe: Preliminary Design Analysis and Application to Canine Iliofemoral Imaging," *Magn. Reson. Med.*, in press, (1992)
90. Hurst, G.C., Hua, J., Simonetti, O.P., and Duerk, J.L., "Signal-to-Noise, Resolution, and Bias Function Analyses of Asymmetric Sampling with Direct Magnitude FT Reconstruction," *Magn. Reson. Med.*, in press, (1992)
91. Budinger, T.F., Fischer, H., et al., "Neural Stimulation dB/dt Thresholds for frequency and number of oscillations using Sinusoidal Magnetic Gradient Fields," in "Book of Abstracts, Society

of Magnetic Resonance in Medicine, Ninth Annual Meeting," p.276 (1990)

92. Duerk, J.L., and Pattany, P.M., "In-plane flow velocity quantification along the phase encoding axis in MRI," *Magn. Reson. Imaging*, vol. 6, pp. 321-333 (1988)
93. Naylor, G.L., Firmin, D.N., and Longmore, D.B., "Blood Flow Imaging by Cine Magnetic Resonance," *J. Comput. Assist. Tomogr.*, vol. 10, pp. 715-722 (1986)
94. Firmin, D.N., Kilner, P.J., Pennell, D.J., et al., "Short Echo Time (3.5 to 6 msec) Field Even Echo Rephasing Sequences for Improved Accuracy and Reliability of Blood Flow Velocity and Acceleration Measurements," in *Book of Abstracts, Society of Magnetic Resonance in Medicine*, p 888 (1989)
95. Katz, J., Peshock, R.M., Malloy, C.R., Schaeffer, S., and Parkey, R.W., "Even-echo Rephasing in Constant Velocity Flow," *Magn. Reson. Med.*, vol. 4, pp. 422-430 (1987)
96. Firmin, D.N., Naylor, G.L., Kilner, P.J., and Longmore, D.B., "The Application of Phase Shifts in NMR for Flow Measurement," *Magn. Reson. Med.*, vol. 4, pp.230-241 (1990)
97. Liu, K., Maier, S.E., Meier, D., et al., "The Influence of Flow Compensation in the Phase Encoding Direction in MR Angiography," in *Book of Abstracts, Society of Magnetic Resonance in Medicine, Tenth Annual Meeting*, p 826 (1991)
98. NessAvier, M., "Acceleration Measurements Obtained with High Temporal Resolution Velocity Measurements," *Journal of Magn. Reson. Imaging*, vol. 1(2), p 215 (1991)
99. Thompson, W.J., *Computing in Applied Science*, Wiley Press, New York, pp. 27-33 (1984)
100. Beyer, W.H., ed., *CRC Standard Math Tables, 26th Edition*, CRC Press, Boca Raton, Florida, p 35 (1981)

101. Singer, J.R., "NMR Diffusion and Flow Measurements and an Introduction to Spin Phase Graphing," *J. Phys. E.*, vol. 11, pp. 281-291 (1978)
102. Colletti, P.M., Raval, J.K., et al, "Motion Artifact Suppression Technique (MAST) in Magnetic Resonance Imaging: Clinical Results," *Magn. Reson. Imaging*, vol.6, pp. 293-299 (1988)
103. Larson, T.C., Kelley, W.M., Ehman, R.L., and Wehrli, F.W., "Spatial Misregistration of Vascular Flow During MR Imaging of the CNS: Cause and Clinical Significance," *AJNR*, vol. 11, pp. 1041-1048 (1990)
104. Moran, P.R., Nalcioğlu, O., and Juh, S.C., "Oblique Vascular Displacement Flow Artifacts in Conventional MRI Sequences," *Magn. Reson. Imaging*, vol. 5(suppl 1), pp. 34-35 (1987)
105. Nishimura, D.G., Jackson, J.I., and Pauly, J.M., "On the Nature and Reduction of the Displacement Artifact in Flow Images," *Magn. Reson. Med.*, vol. 22, pp. 481-492 (1991)
106. Moran, P.R., "Experiments for Two MR Imaging Theories of Motion Phase Sensitivity," *Radiology*, vol. 180, pp. 115-119 (1991)
107. Hennel, F., Jasinski, A., and Tomanek, B. "Double EPI Sequence with 180-degree RF Pulses," *Magn. Reson. Med.*, vol. 16, pp. 161-165 (1990)
108. Firmin, D.N., Klipstein, R.H., et al., "Echo-Planar High-Resolution Flow Velocity Mapping," *Magn. Reson. Med.*, vol. 12, pp. 316-327 (1989)
109. Weisskoff, R.M., Crawley, A.P., Wedeen, V., "Flow Sensitivity and Flow Compensation in Instant Imaging," in Book of Abstracts, Society of Magnetic Resonance in Medicine, Ninth Annual Meeting, p 398 (1990)
110. Stahlberg, F., Nordell, B., et al., "Quantitative Study of Flow Dependence in NMR Images at Low Flow Velocities," *J. Comput. Assis. Tomogr.*, vol. 8, pp. 429-436 (1984)

111. Evans, A.J., Hedlund, L.W., Herfkens, R.J., "A Cardiac Phantom and Pulsatile Flow Pump for Magnetic Resonance Imaging Studies," *Invest. Radiology*, vol. 23(8), pp. 579-583 (1988)
112. Duerk J.L., and Teague, S.M., "Computer-controlled Regurgitant Flow Phantom with Measurable Pressures and Compliances," *JMRI*, vol. 1(2), p 215 (1991)
113. Duerk, J.L., Teague, S.M., Lawler, B., "A Physiologic Regurgitant Cardiac Valve Phantom for Magnetic Resonance Imaging or Color Doppler Ultrasound Study," submitted for publication in *IEEE Trans. Med. Imaging* (1992)
114. Frayne, R., Gowman, L., et al., "A Novel Flow Simulator for MR Flow Experiments," Book of Abstracts, Society of Magnetic Resonance in Medicine, Ninth Annual Meeting, p 474 (1990)
115. Nordell, B., Stahlberg, F., Ericsson, A., and Ranta, C., "A Rotating Phantom for the Study of Flow Effects in MR Imaging," *Magn. Reson. Imaging*, vol. 6, pp. 695-705 (1988)
116. Madsen, E.L., Blechinger, J.C., Frank, G.R., "Low-contrast Focal Lesion Detectability Phantom for ¹H MR Imaging," *Med. Phys.*, vol. 18(3), pp. 549-554 (1991)