INFORMATION TO USERS

This manuscript has been reproduced from the microfilm master. UMI films the text directly from the original or copy submitted. Thus, some thesis and dissertation copies are in typewriter face, while others may be from any type of computer printer.

The quality of this reproduction is dependent upon the quality of the copy submitted. Broken or indistinct print, colored or poor quality illustrations and photographs, print bleedthrough, substandard margins, and improper alignment can adversely affect reproduction.

In the unlikely event that the author did not send UMI a complete manuscript and there are missing pages, these will be noted. Also, if unauthorized copyright material had to be removed, a note will indicate the deletion.

Oversize materials (e.g., maps, drawings, charts) are reproduced by sectioning the original, beginning at the upper left-hand corner and continuing from left to right in equal sections with small overlaps. Each original is also photographed in one exposure and is included in reduced form at the back of the book.

Photographs included in the original manuscript have been reproduced xerographically in this copy. Higher quality 6" x 9" black and white photographic prints are available for any photographs or illustrations appearing in this copy for an additional charge. Contact UMI directly to order.

UMI

A Bell & Howell Information Company
300 North Zeeb Road, Ann Arbor MI 48106-1346 USA
313/761-4700 800/521-0600

MULTIRESOLUTIONAL CONTROLLER DESIGN

DISSERTATION

Presented in Partial Fulfillment of the Requirements for
the Degree Doctor of Philosophy in the
Graduate School of The Ohio State University

By

Daniel J. Clancy, B.S.E.E., M.S.

* * * * *

The Ohio State University

1997

Dissertation Committee:

Professor Ümit Özgüner, Adviser

Professor Hitay Özbay

Professor Lee Potter

Approved by

Adviser

Department of Electrical
Engineering

UMI Number: 9801669

UMI Microform 9801669
Copyright 1997, by UMI Company. All rights reserved.

**This microform edition is protected against unauthorized
copying under Title 17, United States Code.**

UMI
300 North Zeeb Road
Ann Arbor, MI 48103

ABSTRACT

A multiresolutional signal decomposition allows a signal to have equivalent representations at different scales or levels of detail. This idea can be extended to a control system by having a multiresolutional representation of the plant and of the controller. One important purpose for developing a multiresolutional control system is to have the capability of controlling a plant with a high resolution representation using a low resolution controller. A multiresolutional controller could also be used to control only a particular aspect of a plant.

The framework necessary for achieving a multiresolutional control system was developed by this research. This research was focused on modeling the plant using a best orthonormal wavelet packet basis and then determining the optimal controller using the same orthonormal wavelet packet basis or another related orthonormal wavelet packet basis. A theorem for designing a wavelet packet controller which minimizes the 2-norm sensitivity function for a single-input single-output (SISO) system is presented. A theorem for designing a wavelet packet controller which minimizes the 2-norm mixed sensitivity function for a SISO system is also presented. New theoretical results on orthonormal wavelet packets and on what the author calls B-spline packets are presented. The new theoretical results provide the practical computational tools required to solve the posed control optimization problems. Lastly, multiresolutional controller design examples are presented and compared with discrete H^2 controllers. The control design examples demonstrate that the finite impulse response (FIR) for the free controller parameter found using the multiresolutional control design methodology discussed herein approximates the equivalent transfer function for the free

controller parameter found using discrete H^2 control based on the linear fractional transformation (LFT) framework. However, the multiresolutional controllers have the added advantage of requiring only impulse response data, along with being able to optimize the free controller parameter for any desired FIR of length N .

Dedicated to Pamela and our Families

ACKNOWLEDGMENTS

I would like to acknowledge my advisor, Professor Ümit Özgüner, for the assistance and support he has given me throughout this research. His words of encouragement at desperate times are greatly appreciated. I would also like to thank Professor Hitay Özbay and Professor Lee Potter for serving on my doctoral committee and providing comments that improved the quality of my research. In addition, I would like to acknowledge The Ohio State University for the financial support that enabled this research to be conducted.

I would like to thank the graduate students, both past and present, who have made my time at The Ohio State University memorable. Their friendship and support is greatly appreciated. They will certainly not be forgotten.

Finally, I would like to thank my family for their endless support and understanding. I would also like to thank my extended family for their patience and words of wisdom. And most importantly, I would like to thank my wife, Pamela, who has stood by me, helping and guiding me along the way. Together, their belief in me and continuous words of encouragement have been vital to my success.

VITA

June 10, 1966 Born - Garden City Michigan

June, 1988 B.S. Electrical Engineering
Michigan Technological University
Houghton, MI

June, 1988 - September, 1992 Systems Engineer
Raytheon Company
Tewksbury, MA

January, 1991 M.S. Electrical Engineering
Boston University
Boston, MA

September, 1992 - September, 1995 Graduate Research Associate
The Ohio State University
Columbus, OH

September, 1995 - Present Graduate Teaching Associate
The Ohio State University
Columbus, OH

PUBLICATIONS

Research Publications

1. D. Clancy and Ü. Özgüner, "Multiresolutional Controller Design: Sensitivity Minimization," *Proceedings of the 35th IEEE Conference on Decision and Control*, Kobe, Japan, December 1996.

2. A. Annaswamy and D. Clancy, "Adaptive Control Strategies For Vibration Suppression in Flexible Space Structures," *IEEE Transactions on Aerospace and Electronic Systems*, July 1996.
3. D. Clancy and Ü. Özgüner, "A Multiresolutional Controller for Sensitivity Minimization," *Proceedings of the 13th World Congress of IFAC*, San Francisco, CA, July 1996.
4. D. Clancy and Ü. Özgüner, "A Multiresolutional Controller Design Approach Using Wavelets," *Proceedings of the IEEE International Symposium on Intelligent Control*, Monterey, CA, August 1995.
5. D. Clancy and Ü. Özgüner, "Wavelet Neural Networks: A Design Perspective," *Proceedings of the IEEE International Symposium on Intelligent Control*, Columbus, OH, August 1994.
6. D. Clancy, Ü. Özgüner, and R. Graham, "Determination of the Optimal Beta Gimbal Angles for the Solar Arrays of the Space Station Using a Neural Network," *Proceedings of the 26th IEEE Southeastern Symposium on System Theory*, Athens, OH, March 1994.
7. D. Clancy, Ü. Özgüner, and R. Graham, "Optimal Space Station Solar Array Gimbal Angle Determination Via Radial Basis Function Neural Networks," *NASA Lewis Research Center Technical Report*, NASA-TM-106482, March 1994.
8. A. Annaswamy and D. Clancy, "Adaptive Control Strategies For Vibration Suppression in Flexible Structures," *AIAA Guidance, Navigation, and Control Conference*, August 1991.

FIELDS OF STUDY

Major Field: Electrical Engineering

Studies in:

Control Systems

Signal Processing

Mathematics

TABLE OF CONTENTS

	Page
Abstract	ii
Dedication	iv
Acknowledgments	v
Vita	vi
List of Tables	x
List of Figures	xi
Chapters:	
1. Introduction	1
2. Literature survey on the application of orthogonal functions to control theory	4
3. Wavelets and multiresolution analysis	11
4. Wavelets and filter banks	18
5. Wavelet packets	25
6. Wavelet modeling of systems	36

7.	Orthonormal wavelet packets	42
7.1	Representation of orthonormal wavelet packets	42
7.2	Orthonormal wavelet packet inner products	46
7.3	Continuous Haar wavelet packets	49
7.4	Multiplication of Haar wavelet packets	52
7.5	Discrete Haar wavelet packets	54
8.	B-spline packets	60
8.1	B-splines	60
8.2	Generalized B-spline packets	66
8.3	Generalized B-spline packet inner products	76
8.4	Discrete B-spline packets	86
9.	Multiresolutional controller design	91
9.1	Mathematical preliminaries	91
9.2	Multiresolutional sensitivity minimization	96
9.3	Multiresolutional mixed sensitivity minimization	105
9.4	Discrete H^2 control	112
10.	Discrete Multiresolutional controller design examples	117
10.1	Discrete multiresolutional minimum sensitivity controller design example	117
10.2	Discrete multiresolutional minimum mixed sensitivity controller design example	118
10.3	Comparison between discrete multiresolutional controllers and discrete H^2 controllers	120
11.	Conclusions	123
Appendices:		
A.	Proofs of multiresolutional controller design lemmas	125
Bibliography		132

LIST OF TABLES

Table	Page
10.1 Comparison of Discrete Multiresolutional Controller Designs for Sensitivity Minimization as a function of N	119
10.2 Comparison of Multiresolutional Controller Designs for Mixed Sensitivity Minimization as a function of N	120

LIST OF FIGURES

Figure	Page
4.1 Perfect Reconstruction Filter Bank	19
4.2 Wavelet Analysis Filter Bank	22
4.3 Wavelet Synthesis Filter Bank	22
4.4 Noble Identities for Multirate Filter Banks. (a) Interchange property between down-sampling and filtering operations. (b) Interchange property between upsampling and filtering operations.	23
5.1 Wavelet Packet Analysis Filter Bank	27
5.2 Some possible orthogonal bases for a signal, $x(t)$ at the scale $s = 3$, analyzed using wavelet packets: (i) the wavelet basis, (ii) a level basis, (iii) an arbitrary basis. . . .	35
6.1 Impulse and frequency response for a flexible structure with two modes	38
6.2 Wavelet packet decomposition for a flexible structure with two modes	39
6.3 Best basis, best level basis, and wavelet basis selection for a flexible structure with two modes	40
6.4 Reconstruction of the impulse response for a flexible structure with two modes . . .	41
7.1 The natural ordered wavelet packet basis functions for several subspaces, W_f^s , based on applying the Haar quadrature filter operators, F_0 and F_1	50
7.2 The sequency ordered wavelet packet basis functions for several subspaces, $\widetilde{W}_f^s$, based on applying the Haar quadrature filter operators, F_0 and F_1	51

8.1	(a) Plot of $\mathcal{W}_{0,0}(t)$, (b) Plot of $\mathcal{W}_{0,1}(t)$	73
8.2	(a) Plot of $\mathcal{W}_{1,0}(t)$, (b) Plot of $\mathcal{W}_{1,3}(t)$, (c) Plot of $\mathcal{W}_{1,1}(t)$	74
8.3	(a) Plot of $\mathcal{W}_{2,0}(t)$, (b) Plot of $\mathcal{W}_{2,7}(t)$, (c) Plot of $\mathcal{W}_{2,1}(t)$, (d) Plot of $\mathcal{W}_{2,3}(t)$	75
9.1	(a) Lower LFT $F_l(P, K_l)$, (b) Upper LFT $F_u(P, K_u)$	95
9.2	Redheffer Star Product	96
9.3	Feedback Control System For Sensitivity Minimization	97
9.4	Multiresolutional Controller C_K Signal Block Diagram	104
9.5	Feedback Control System For Mixed Sensitivity Minimization	105
9.6	Equivalent Feedback Control System For Mixed Sensitivity Minimization	105
9.7	Youla Parameterization for stable plants using LFTs	112

CHAPTER 1

INTRODUCTION

The control of large systems presents many unique and challenging problems. Many of the controller architectures proposed for large, complex systems have a hierarchical framework. A hierarchical control system consists of having different controllers for different tasks. For example, the low level controllers perform very specific tasks and provide a fine level of control, whereas the high level controllers perform supervisory tasks and provide a coarse level of control. The hierarchy within the controller architecture inherently has a multiresolutional aspect. Multiresolution encompasses the idea of scale and the process of moving from one scale to another, e.g., moving from a coarse scale to a finer scale or vice versa. The concept of a multiresolutional representation refers to a hierarchical architecture for interpreting information. The most intuitive environment for such a multiresolutional representation is in the field of image processing [1]. The different resolutions of an image tend to characterize the various physical structures present within the image. A coarse resolution would provide general trends, or larger scale structures present within the image. A fine resolution would accentuate the details, or small scale structures present within the image.

The primary goal of this research was to apply the ideas of multiresolution to a control system. The ultimate objective would be to be able to use images in a control system. In other words, given an image as a sensor output, the controller would enable a system to perform a certain function, e.g., move the robot through a door and pick up an object, etc. However, the framework still needs to be established before such a goal can be reached. This work takes a step back from images, and is concerned with signals of systems as a starting point for the development of a multiresolutional control system.

The theory of multiresolution analysis was pioneered by Stephane Mallat [2] and Yves Meyer [3] and was the impetus for the fast growing field of wavelets. A multiresolutional signal decomposition allows a signal to be represented equivalently at different scales or levels of detail. The theory of multiresolution analysis is one of the primary ways of deriving wavelets and wavelet packets. Wavelet packets provide a rich theory with a library of functions and algorithms available for modeling signals.

Wavelet packets also have the ability to attain a best basis for a signal or class of signals. Wavelet packet coefficients tend to decay quickly and usually require substantially fewer basis functions compared with a Fourier basis. Wavelet packet basis functions can be easily modified to account for uncertainties, failures, and changes in the operating environment of a system.

This research involved developing a multiresolutional control system. First of all, it was necessary to obtain a multiresolutional representation of the plant to be controlled. Then, a controller for the system was developed which also had a multiresolutional representation. One important purpose for developing a multiresolutional control system was to have the capability of controlling a plant with a high resolution using a low resolution controller. Another purpose for developing a multiresolutional control system was to be able to control a group or class of plants with the same controller. The controller can have multiple resolutions or only one resolution. In addition, a multiresolutional controller could be used to control only a particular aspect of a plant.

The framework necessary for achieving a multiresolutional control system was developed by this research. The first step towards achieving a multiresolutional control system was to use wavelet packet theory in order to model the plant to be controlled. The main idea was to model the plant using a “best” orthonormal wavelet packet basis. The word best is in quotes since the best wavelet packet basis may be very dependent on the control objectives, plant characteristics, etc., and therefore could vary greatly from one control system to another. This framework is very general and allows the control designer to ascertain what is the “best” basis for their individual control system. The optimal controller was then determined using either the same orthonormal wavelet packet basis or another related orthonormal wavelet packet basis. A related orthonormal wavelet packet basis is a different basis derived from the same mother wavelet. If the controller has the same wavelet packet basis as the plant, then it may be possible to easily modify the controller in order to account for uncertainties, changes in operating environment, etc., thus making for a robust and adaptable controller. This research presents a theorem for designing a wavelet packet controller which minimizes the sensitivity function for a single-input single-output (SISO) system. A theorem for designing a wavelet packet controller which minimizes the mixed sensitivity function for a SISO system is also presented. New theoretical results on orthonormal wavelet packets and on what the author calls B-spline packets are presented. The new theoretical results provide the practical computational tools required to solve the posed control optimization problems. Lastly, multiresolutional controller design examples are presented and compared with discrete H^2 controllers. The control design examples demonstrate that the finite impulse response (FIR) for the free controller parameter found using the multiresolutional control design methodology discussed herein approximates the equivalent transfer function for the free controller parameter found using discrete H^2 control based on the linear fractional transformation (LFT) framework. However, the multiresolutional controllers have

the added advantage of requiring only impulse response data, along with being able to optimize the free controller parameter for any desired FIR of length N .

The next chapter, chapter 2, presents an abridged literature survey on the use of orthogonal functions in control theory. Orthogonal functions have been used extensively in estimation theory as well, but since the focus of this thesis is on the control problem, estimation theory results will not be discussed. Chapter 3 briefly introduces wavelet theory and the theory of multiresolution analysis. The following chapter, chapter 4, reviews wavelet theory from a filter bank theoretic viewpoint. Chapter 5 presents wavelet packet theory, which is a generalization of the wavelet theory presented in chapters 3 and 4. The next chapter, chapter 6, discusses using wavelet packet theory to model systems from experimental data. In this case, orthonormal wavelet packets are employed to model the impulse response data of the system to be controlled. The next two chapters, chapter 7 and 8, and the corresponding discrete-time sections within those chapters, sections 7.5 and 8.4, present new mathematical results necessary for solving the sensitivity and mixed sensitivity control problems presented in chapter 9. Chapter 7 presents new mathematical results pertaining to orthonormal wavelet packets, and section 7.5 presents new mathematical results for discrete-time Haar wavelet packets. Chapter 8 presents new mathematical results on what the author's call B-spline packets and section 8.4 presents the corresponding theoretical results for discrete-time B-spline packets. Chapter 9 formulates and solves the sensitivity and mixed sensitivity control problems based on modeling the control system components using Haar wavelet packets. This chapter also briefly presents the discrete H^2 control problem based on the LFT framework in section 9.4. The LFT based discrete H^2 controllers are developed solely for the purpose of controller comparison with the multiresolutional controllers. In other words, plant and disturbance models are assumed in order to develop LFT based discrete H^2 controllers. The corresponding impulse response data for the plant and disturbance models is used to develop the multiresolutional controllers. Multiresolutional controller design examples for the sensitivity and mixed sensitivity control problems are presented in sections 10.1 and 10.2. The discrete H^2 LFT based controllers and the multiresolutional controllers are then directly compared in section 10.3. The control design examples demonstrate that the FIR for the free controller parameter found using the multiresolutional control design methodology discussed herein approximates the equivalent transfer function for the free controller parameter found using discrete H^2 control based on the LFT framework. However, the multiresolutional controllers have the added advantage of requiring only impulse response data, along with being able to optimize the free controller parameter for any desired FIR of length N .

CHAPTER 2

LITERATURE SURVEY ON THE APPLICATION OF ORTHOGONAL FUNCTIONS TO CONTROL THEORY

Orthogonal functions have been applied to systems and control theory in numerous ways. The massive amount of literature available on this topic makes it impossible to give adequate treatment to this entire research area in a single chapter. Therefore, this chapter will concentrate only on those types of orthogonal functions most closely related to the wavelet theory discussed in the sequel. The type of orthogonal functions that will be considered is those classified as piecewise constant. In other words, this chapter will discuss exclusively piecewise constant orthogonal basis functions (PCBFs) [4]. The four most widely used types of PCBFs for the normal interval $[0, 1)$, will now be presented in a manner similar to that found in [4] where $m = 2^d$ for some $d \in \mathbb{Z}^+$.

Definition 2.1 (Block-Pulse Functions (BPFs) [5])

A set of m BPFs, $\{\eta_k(t)\}$, is defined for each integer k , $k = 0, 1, \dots, m-1$:

$$\eta_k(t) = \begin{cases} \sqrt{m} & t \in [\frac{k}{m}, \frac{k+1}{m}) \\ 0 & \text{otherwise} \end{cases} \quad (2.1)$$

The system of m BPFs is orthonormal and complete.

Definition 2.2 (Rademacher Functions (RFs) [6])

A set of m RFs, $\{\rho_k(t)\}$, is defined for $t \in [0, 1)$ and for each integer k , $k = 0, 1, \dots, m-1$:

$$\begin{aligned} \rho_0(t) &= \begin{cases} 1 & t \in [0, 1) \\ 0 & \text{otherwise} \end{cases} \\ \rho_1(t) &= \begin{cases} 1 & t \in [0, \frac{1}{2}) \\ -1 & t \in [\frac{1}{2}, 1) \end{cases} \\ \rho_{k+n}(t) &= \rho_k(2^n t) \end{aligned} \quad (2.2)$$

The number of cycles of the function $\rho_k(t)$ in the interval $0 \leq t \leq 1$ is 2^{k-1} for $k \geq 1$. The system of m RFs is orthonormal, but is not complete.

Definition 2.3 (Walsh Functions (WFs) [6])

A set of m WFs, $\{\psi_k(t)\}$, is defined for $t \in [0, 1)$ and for each integer k , $k = 0, 1, \dots, m-1$:

$$\psi_k(t) = \begin{cases} \rho_0(t) & k = 0 \\ \prod_{n=0}^{[\log_2(k+1)]-1} \rho_{n+1}^{k_n} & k \geq 1 \end{cases} \quad (2.3)$$

where $[\bullet]$ is the greatest integer function and k_n are binary coefficients for $k \in \mathbb{Z}$. The system of m WFs is orthonormal and complete.

Definition 2.4 (Haar Functions (HFs) [7])

A set of m HFs, $\{\phi_k(t)\}$, is defined for each integer k , $k = 0, 1, \dots, m-1$:

$$\begin{aligned} \phi_0(t) &= \begin{cases} 1 & t \in [0, 1) \\ 0 & \text{otherwise} \end{cases} \\ \phi_k(t) &= \begin{cases} 2^{n/2} & t \in [\frac{2m}{2^{n+1}}, \frac{2m+1}{2^{n+1}}) \\ -2^{n/2} & t \in [\frac{2m+1}{2^{n+1}}, \frac{2m+2}{2^{n+1}}) \\ 0 & \text{otherwise} \end{cases} \end{aligned} \quad (2.4)$$

where $k = 2^n + m$, $n \geq 0$, and $0 \leq m \leq 2^n - 1$. The system of m HFs is orthonormal and complete.

The Walsh and Haar functions just presented can be expressed as linear combinations of BPFs [4]. In other words, there exists linear, constant coefficient, invertible transformation matrices which convert the basis matrices for Walsh or Haar functions into a BPF basis matrix.

Walsh functions were utilized to solve differential equations in state space form through the development of an operational matrix [6], [8], [9]. Let $\Psi_{(m)}(t) = [\psi_0(t) \ \psi_1(t) \ \dots \ \psi_{m-1}(t)]^T$. The operational matrix allows integration to be performed by multiplying by a constant matrix as follows:

$$\int_0^t \Psi_{(m)}(\sigma) d\sigma \approx P_{(m \times m)} \Psi_{(m)}(t) \quad (2.5)$$

where $P_{(m \times m)}$ is an $(m \times m)$ matrix of Walsh coefficients corresponding to a m term Walsh series approximation for the integrals of the m Walsh functions. The standard state-space equation:

$$\dot{x}(t) = Ax(t) + Bu(t), \quad x(0) = x_0 \quad (2.6)$$

with the rate vector, $\dot{x} \in \mathbb{R}^n$, represented by a Walsh series expansion, $\dot{x} = E\Psi_{(m)}(t)$ with E a $(n \times m)$ Walsh coefficient matrix, the state variable x represented by $x(t) = E \int_0^t \Psi_{(m)}(\sigma) d\sigma + x_0 = EP_{(m \times m)}\Psi_{(m)}(t) + x_0$, and the input vector $u \in \mathbb{R}^p$, represented by a Walsh series expansion, $u(t) = F\Psi_{(m)}(t)$. Now equation 2.6 can be represented as follows:

$$\begin{aligned} E\Psi_{(m)}(t) &= A(EP_{(m \times m)}\Psi_{(m)}(t) + x_0) + BF\Psi_{(m)}(t) \\ E\Psi_{(m)}(t) &= AEP_{(m \times m)}\Psi_{(m)}(t) + G\Psi_{(m)}(t) + BF\Psi_{(m)}(t) \\ E &= AEP_{(m \times m)} + G + BF = AEP_{(m \times m)} + K \end{aligned} \quad (2.7)$$

where $Ax_0 = Ax_0\psi_0(t) = [Ax_0 \overbrace{00\cdots 0}^{m-1}] := G\Psi_{(m)}(t)$. One approach for solving equation 2.7 for the $(n \times m)$ matrix E is to rearrange E and K into $(n \times m \times 1)$ vectors e and k according to

$$\begin{aligned} e &= [A \otimes P_{(m \times m)}]e + k \\ e &= [I - A \otimes P_{(m \times m)}^T]^{-1}k \end{aligned} \quad (2.8)$$

where $\otimes :=$ Kronecker product and I is an identity matrix. This exact same representation will also result for block-pulse functions when Ψ is replaced by η and the P matrix contains the corresponding block-pulse coefficients [5] and [10].

One practical consideration of utilizing PCBFs for the solution of differential equations or for solving control theory problems is how to perform the PCBF computations over intervals larger than the normal interval $[0, 1]$. The first approach is to normalize the entire time period of interest to the normal interval $[0, 1]$ and then use the PCBFs directly. This approach necessitates an increase in the number of PCBFs, m , to be utilized in the computations as the length of the original time interval increases. Another approach is to perform the computations over subintervals of the entire original time interval. This approach requires appropriate connection of the subintervals at their endpoints. One such approach is the single term Walsh series (STWS) approach [11] which requires no Kronecker product or inversion of large matrices, no operational matrices for integration, and no Walsh basis matrices or Walsh coefficient matrices. The approach is based on the trapezoidal rule of integration, and essentially reduces to an integration method for differential equations.

The applications of PCBFs to control theory have been primarily limited to solving the quadratic optimal control problem with fixed final time, which will now be presented for completeness. Given the state space equation 2.6, define the quadratic performance index:

$$J = \frac{1}{2} \int_0^{t_f} \left(x^T(t)Qx(t) + u^T(t)Ru(t) \right) dt \quad (2.9)$$

where $Q \geq 0$ the state weighting matrix, $R > 0$ the control weighting matrix and t_f is the fixed final time. The well-known optimal control solution to this problem is given by the following:

$$u^*(t) = R^{-1}B^T\lambda(t) \quad (2.10)$$

where $\lambda(t)$ satisfies the following Hamiltonian system of equations:

$$\begin{bmatrix} \dot{x}(t) \\ \dot{\lambda}(t) \end{bmatrix} = \begin{bmatrix} A & BR^{-1}B^T \\ Q & -A^T \end{bmatrix} \begin{bmatrix} x(t) \\ \lambda(t) \end{bmatrix} := H \begin{bmatrix} x(t) \\ \lambda(t) \end{bmatrix} \quad (2.11)$$

and the boundary conditions are specified as:

$$x(0) = x_0 \quad (2.12)$$

$$\lambda(t_f) = 0 \quad (2.13)$$

where equation 2.13 is known as the transversality condition. Performing the change of variable $\tau = t_f - t$, equation 2.11 becomes:

$$\begin{bmatrix} \dot{x}(\tau) \\ \dot{\lambda}(\tau) \end{bmatrix} = \begin{bmatrix} -A & -BR^{-1}B^T \\ -Q & A^T \end{bmatrix} \begin{bmatrix} x(\tau) \\ \lambda(\tau) \end{bmatrix} = -H \begin{bmatrix} x(\tau) \\ \lambda(\tau) \end{bmatrix} \quad (2.14)$$

The solution of equation 2.14 is given by:

$$\begin{bmatrix} x(\tau) \\ \lambda(\tau) \end{bmatrix} = e^{-H\tau} \begin{bmatrix} x(\tau = 0) \\ \lambda(\tau = 0) \end{bmatrix} \quad (2.15)$$

where $e^{-H\tau}$, the transition matrix of equation 2.14, is given as follows:

$$e^{-H\tau} = \begin{bmatrix} q_{11}(\tau) & q_{12}(\tau) \\ q_{21}(\tau) & q_{22}(\tau) \end{bmatrix} \quad (2.16)$$

The boundary conditions which result from the change of variable, $\tau = t_f - t$, are $x(\tau = t_f) = x_0$ and $\lambda(\tau = 0) = 0$. Putting the second boundary condition into equation 2.15 yields the following:

$$x(\tau) = q_{11}(\tau)x(\tau = 0) \quad (2.17)$$

$$\lambda(\tau) = q_{21}(\tau)x(\tau = 0) \quad (2.18)$$

Substituting equation 2.17 into equation 2.18 results in:

$$\lambda(\tau) = q_{21}(\tau)q_{11}^{-1}(\tau)x(\tau) \quad (2.19)$$

and the optimal control, equation 2.10, becomes:

$$u^*(t) = R^{-1}B^T q_{21}(t_f - t)q_{11}^{-1}(t_f - t)x(t_f - t) := -K(t_f - t)x(t_f - t) \quad (2.20)$$

The solution to this linear, continuous time, time-invariant optimal control problem with fixed final time will now be presented using Walsh functions [9], [12]. The Walsh series solution begins with normalizing the problem to the interval $[0, 1)$ by using the change of variable $\sigma = \tau/t_f$ in equation 2.14 as follows:

$$\begin{bmatrix} \dot{x}(\sigma) \\ \dot{\lambda}(\sigma) \end{bmatrix} = -t_f H \begin{bmatrix} x(\sigma) \\ \lambda(\sigma) \end{bmatrix} \quad (2.21)$$

and then $\dot{x}(\sigma)$ and $\dot{\lambda}(\sigma)$ are expanded into a Walsh series. The solution proceeds identically to that presented in equations 2.7 and 2.8. The solution to this linear, continuous time, time-invariant optimal control problem with fixed final time using block-pulse functions has also been determined [13].

For linear, continuous time, time-varying optimal control problems with fixed final time, the state equation 2.6, the cost function 2.9, the optimal control 2.10, the Hamiltonian system 2.11 and

the corresponding boundary conditions 2.12 and 2.13 are identical except that A , B , Q , R , and H are functions of time $A(t)$, $B(t)$, $Q(t)$, $R(t)$, and $H(t)$. The time varying equivalent of equation 2.11, which is given by:

$$\begin{bmatrix} \dot{x}(t) \\ \dot{\lambda}(t) \end{bmatrix} = \begin{bmatrix} A(t) & B(t)R^{-1}(t)B^T(t) \\ Q(t) & -A^T(t) \end{bmatrix} \begin{bmatrix} x(t) \\ \lambda(t) \end{bmatrix} := H(t) \begin{bmatrix} x(t) \\ \lambda(t) \end{bmatrix} \quad (2.22)$$

Let the state transition matrix of equation 2.22, $q(t_f, t)$, be given as follows:

$$q(t_f, t) = \begin{bmatrix} q_{11}(t_f, t) & q_{12}(t_f, t) \\ q_{21}(t_f, t) & q_{22}(t_f, t) \end{bmatrix} \quad (2.23)$$

The state equation for the state transition matrix is given by:

$$\dot{q}(t_f, t) = -H(t)q(t_f, t) \quad (2.24)$$

with $q(t_f, t_f) = I$. The solution to equation 2.22 is given by:

$$\begin{bmatrix} x(t_f) \\ \lambda(t_f) \end{bmatrix} = q(t_f, t) \begin{bmatrix} x(t) \\ \lambda(t) \end{bmatrix} \quad (2.25)$$

Putting the second boundary condition into equation 2.25 yields the following:

$$\lambda(t) = -q_{22}^{-1}(t_f, t)q_{21}(t_f, t)x(t) \quad (2.26)$$

and the optimal control, equation 2.10, becomes:

$$u^*(t) = R^{-1}B^T q_{22}^{-1}(t_f, t)q_{21}(t_f, t)x(t) := -K(t)x(t) \quad (2.27)$$

The solution to this linear, continuous time, time-varying optimal control problem with fixed final time has been carried out using Walsh functions [14], [15]. The solution in [14] used a Walsh series approximation of both the state transition matrix, $\lambda(t_f, t)$ and $H(t)$ to solve equation 2.24 by integrating backward in time from t_f to t and then obtaining the time varying feedback control using equation 2.27. The backward integration of the Walsh functions was represented as $\int_1^t \Psi_{(m)}(\sigma) d\sigma \approx Q_{(m \times m)} \Psi_{(m)}(t)$, where $Q_{(m \times m)}$ is an $(m \times m)$ matrix of Walsh coefficients corresponding to a m term Walsh series approximation for the backward integration of the m Walsh functions. An interesting property of Walsh product matrices presented in [14] is the following:

$$\Psi_{(m \times m)}(t)\gamma_{(m)} = \Gamma_{(m \times m)}\Psi_{(m)}(t) \quad (2.28)$$

where $\Psi_{(m \times m)}(t) := \Psi_{(m)}(t)\Psi_{(m)}^T(t)$ is the Walsh product matrix, $\gamma_{(m)}$ is a $(m \times 1)$ vector of Walsh coefficients, and $\Gamma_{(m \times m)} := \gamma_{(m)}\gamma_{(m)}^T$.

The linear, continuous time, time-invariant optimal control problem with fixed final time for systems with state delay and with state and control delays was solved using PCBFs in [4]. PCPFs were utilized to solve delay differential equations in state space form through the development of PCBF shift matrices, i.e., delay and advance matrices, [16], [17] and [18]. The idea behind delay and advance matrices is to relate the delayed or advanced matrix of PCBFs to the standard PCBF matrix as follows [17] and [18]:

$$\Psi(t - \tau_d) = T_d \Psi(t) \quad (2.29)$$

$$\Psi(t + \tau_d) = T_a \Psi(t) \quad (2.30)$$

where $\tau_d > 0$. For Walsh basis matrices, $T_a = T_d^T$.

The corresponding linear, discrete time, time-invariant and time-varying optimal control problems with both fixed final time and fixed final states were solved using Walsh functions in [19] and [20]. In a discrete time system, the state equation, 2.6, is a difference equation as opposed to a differential equation, represented as follows for $k = 0, 1, \dots, N-1$:

$$x(k+1) = Ax(k) + Bu(k), \quad x(0) = x_0 \quad (2.31)$$

For the time varying case, A and B become $A(k)$ and $B(k)$. Given the state space equation 2.31, define the discrete quadratic performance index with a fixed final time, N , and a fixed final state, $x(N) = X_N$, as follows:

$$J = \frac{1}{2} \sum_{k=0}^{N-1} \left(x^T(k) Q x(k) + u^T(k) R u(k) \right) + \alpha (x(N) - X_N)^T (x(N) - X_N) \quad (2.32)$$

where $Q \geq 0$ the state weighting matrix and $R > 0$ the control weighting matrix. In the time-varying optimal control case, Q and R become functions of time $Q(k)$ and $R(k)$. In order to solve difference equations using Walsh functions, the idea of a summation matrix was introduced as follows [19]:

$$\sum_{j=0}^k \Psi_{(m)}(j) = S \Psi_{(m)}(k) \quad (2.33)$$

where S is the $(m \times m)$ discrete Walsh summation matrix. The idea behind a summation matrix is to relate the sum of the individual components of a Walsh basis matrix at any time k to the standard Walsh basis matrix. Using the advance matrix transform equation, 2.30, and the summation matrix transform equation, 2.33, the solution to difference equations can be obtained. The time-invariant difference equation is solved by representing both $x(k)$ and $u(k)$ using a discrete Walsh series, $x(k) = E \Psi_{(m)}(k)$ and $u(k) = F \Psi_{(m)}(k)$, and then putting the Walsh series representations for $x(k)$ and $u(k)$ into the difference equation, thereby converting the state equation into an algebraic equation. Through this algebraic equation, the Walsh coefficients for $x(k)$, E , are directly related

to the Walsh coefficients for $u(k)$, F . In the time-varying case, the $A(k)$ and $B(k)$ matrices are also represented using a discrete Walsh series and then also put back into the difference equation to yield an algebraic equation which can be used to relate E to F . The time-invariant optimal control problem is solved by using the Walsh representation for $x(k)$ and $u(k)$ in the cost function, equation 2.32, using the solved difference equation relationship between the Walsh coefficients for $x(k)$, E , and the Walsh coefficients for $u(k)$, F , and then optimizing with respect to either E or F using the necessary condition for optimization $\frac{\partial J}{\partial E} = 0$ or $\frac{\partial J}{\partial F} = 0$. The time-varying optimal control problem is solved the exact same way except that $Q(k)$ and $R(k)$ are also represented by a discrete Walsh series.

CHAPTER 3

WAVELETS AND MULTIREOLUTION ANALYSIS

The theory of multiresolution analysis (MRA), or multiresolution signal decomposition, pioneered by Meyer [3] and Mallat [2], provides a natural framework for formulating and understanding wavelet theory. A recapitulation of these concepts as given in [2], [21], and [22] will now be presented.

Definition 3.1 (Translation Operator)

1. The translation operator is represented by:

$$T_k x(t) := x(t - k), \quad k \in \mathbb{Z} \quad (3.1)$$

In shorthand notation, $x_k(t) := T_k x(t)$.

2. The adjoint of the translation operator is represented by:

$$T_k^* x(t) := x(t + k) \quad (3.2)$$

In shorthand notation, $x_{k*}(t) := T_k^* x(t)$.

Definition 3.2 (Dilation Operator)

1. The dilation operator is represented by:

$$D_m x(t) := 2^{m/2} x(2^m t), \quad m \in \mathbb{Z} \quad (3.3)$$

In shorthand notation, $x^m(t) := D_m x(t)$.

2. The adjoint of the dilation operator is represented by:

$$D_m^* x(t) := 2^{-m/2} x(2^{-m} t) \quad (3.4)$$

In shorthand notation, $x^{m*}(t) := D_m^* x(t)$.

Definition 3.3 (Combined Operations)

1. The dilation operator followed by the translation operation is represented by:

$$T_k D_m x(t) := 2^{m/2} x(2^m t - k) \quad (3.5)$$

In shorthand notation, $x_k^m(t) := T_k D_m x(t)$.

2. The translation operator followed by the dilation operation is represented by:

$$D_m T_k x(t) := 2^{m/2} x(2^m(t - k)) \quad (3.6)$$

In shorthand notation, $\tilde{x}_k^m(t) := D_m T_k x(t)$.

3. The adjoint of the dilation operator followed by the translation operator is represented by:

$$(T_k D_m)^* x(t) := D_m^* T_k^* x(t) = 2^{-m/2} x(2^{-m}(t + k)) \quad (3.7)$$

In shorthand notation, $x_{k*}^{m*}(t) := D_m^* T_k^* x(t)$.

4. The adjoint of the translation operator followed by the dilation operator is represented by

$$(D_m T_k)^* x(t) := T_k^* D_m^* x(t) = 2^{-m/2} x(2^{-m}t + k) \quad (3.8)$$

In shorthand notation, $\tilde{x}_{k*}^{m*}(t) := T_k^* D_m^* x(t)$.

Definition 3.4 (Riesz Basis)

In a Hilbert space $\mathcal{H}$, an unconditional basis, i.e., linearly independent and the order of the basis vectors is irrelevant, is known as a Riesz basis. An equivalent condition is that given a collection of functions, $\{\phi_n : n \in \mathbb{Z}\}$, if there exists two constants A and B , with $0 < A \leq B < \infty$ such that for all $x \in \mathcal{H}$:

$$A\|x\|^2 \leq \sum_{k \in \mathbb{Z}} |\langle x, \phi_n \rangle|^2 \leq B\|x\|^2 \quad (3.9)$$

and the collection $\{\phi_n : n \in \mathbb{Z}\}$ is linearly independent, then it is a Riesz basis. Any Riesz basis can be made into an orthonormal basis using Gram-Schmidt orthogonalization. For an orthonormal basis, $A = B = 1$. Note that $\langle \bullet, \bullet \rangle$ represents an inner product.

A multiresolution signal analysis in Hilbert space $\mathcal{H}$ entails a sequence of successive closed approximation subspaces, V_m with $m \in \mathbb{Z}$, satisfying the following properties:

Nesting Property

$$\cdots \subset V_{-2} \subset V_{-1} \subset V_0 \subset V_1 \subset V_2 \subset \cdots \quad (3.10)$$

Union Property

$$\overline{\bigcup_{m \in \mathbb{Z}} V_m} = \mathcal{H} \quad (3.11)$$

Intersection Property

$$\bigcap_{m \in \mathbb{Z}} V_m = \{0\} \quad (3.12)$$

Dilation Property

$$x(t) \in V_m \iff x^1(t) \in V_{m+1} \quad (3.13)$$

Translation Property

$$x(t) \in V_0 \implies x_k(t) \in V_0 \quad \forall k \in \mathbb{Z} \quad (3.14)$$

Basis Property $\exists$ a scaling function $\phi \in V_0$ such that

$$\{\phi_k^0(t) = \phi(t - k) : k \in \mathbb{Z}\} \text{ is a Riesz basis for } V_0 \quad (3.15)$$

$$\text{with } \phi_k^m(t) = 2^{m/2} \phi(2^m t - k) \quad \forall k, m \in \mathbb{Z}$$

Equations 3.13 and 3.15 imply that $\{\phi_k^m(t) : k \in \mathbb{Z}\}$ is a Riesz basis for V_m , $\forall m \in \mathbb{Z}$. The multiresolution aspect of the approximation subspace V_m comes from the dilation, translation, and basis properties, equations 3.13, 3.14, and 3.15. The basic tenet of multiresolution analysis is that given a collection of closed subspaces satisfying properties 3.10 - 3.15, there exists a Riesz wavelet basis $\{\psi_k^m(t) : m, k \in \mathbb{Z}\}$ for $\mathcal{H}$. The explicit construction of the wavelet $\psi(t)$ will now be presented.

For every $m \in \mathbb{Z}$, define the complementary subspace of V_m in V_{m+1} as W_m . At every scale, $s \in \mathbb{Z}$,

$$V_{m+1} = V_m + W_m \quad (3.16)$$

$$W_m \subset V_{m'} \quad \text{if } m < m' \quad (3.17)$$

Then, for $m \geq M$,

$$V_{m+1} = V_M + \sum_{i=M}^m W_i \quad (3.18)$$

From equations 3.11 and 3.12, it follows that $\mathcal{H}$ can be decomposed into complementary subspaces according to

$$\sum_{m \in \mathbb{Z}} W_m = \mathcal{H} \quad (3.19)$$

The W_m subspaces acquire the dilation property of equation 3.13:

$$x(t) \in W_m \iff x^1(t) \in W_{m+1} \quad (3.20)$$

and the translation property of equation 3.14:

$$x(t) \in W_0 \implies x_k(t) \in W_0 \quad \forall k \in \mathbb{Z} \quad (3.21)$$

It follows that there exists a wavelet function $\psi \in W_0$ such that

$$\{\psi_k^0(t) = \psi(t - k) : k \in \mathbb{Z}\} \text{ is a Riesz basis for } W_0 \quad (3.22)$$

In light of the above properties for W_m , equations 3.20 and 3.22 guarantee that $\{\psi_k^m(t) : k \in \mathbb{Z}\}$ is a Riesz basis for W_m , $\forall m \in \mathbb{Z}$.

When the MRA is orthogonal, the Riesz basis is an orthonormal basis. Let the Fourier Transform of a signal $x(t)$, $\mathcal{F}\{x(t)\}$, be represented by $X(\omega)$. An interesting remark in this case is that since the family of functions, $\{\phi(t-k) : k \in \mathbb{Z}\}$, are orthonormal, $\langle \phi(t), \phi(t-k) \rangle = \delta(k)$, the orthonormality of this family of functions can be equivalently represented in the Fourier domain as:

$$\mathcal{F}\{\langle \phi(t), \phi(t-k) \rangle\} = \sum_{n \in \mathbb{Z}} |\Phi(\omega + 2\pi n)|^2 = 1 \text{ a.e.} \quad (3.23)$$

For an orthogonal MRA, define P_m to be the orthogonal projection operator onto V_m . By 3.11, $\lim_{m \rightarrow \infty} P_m x = x \quad \forall x \in \mathcal{H}$. The crux of an orthogonal MRA is that if a set of closed subspaces satisfies 3.10 - 3.15, then there exists an orthonormal wavelet basis of $\mathcal{H}$ given by:

$$\begin{aligned} &\{\psi_k^m(t) : m, k \in \mathbb{Z}\} \\ \psi_k^m(t) &= 2^{m/2} \psi(2^m t - k) \end{aligned} \quad (3.24)$$

which for all $x \in \mathcal{H}$ satisfies the relation

$$P_{m+1} x = P_m x + \sum_{k \in \mathbb{Z}} \langle x, \psi_k^m(t) \rangle \psi_k^m(t) \quad (3.25)$$

Now, for every $m \in \mathbb{Z}$, define the orthogonal complement of V_m in V_{m+1} as W_m . At every scale

$$V_{m+1} = V_m \oplus W_m \quad (3.26)$$

$$W_m \perp W_{m'} \quad \text{if } m \neq m' \quad (3.27)$$

$$W_m \subset V_{m'} \quad \text{if } m < m' \quad (3.28)$$

where $V_m \oplus W_m$ signifies the direct sum of the spaces V_m and W_m to form a new space V_{m+1} . The underlying set of V_{m+1} is the Cartesian product $V_m \times W_m$. Then, for $m \geq M$,

$$V_{m+1} = V_M \oplus \bigoplus_{i=M}^m W_i \quad (3.29)$$

Note that $\bigoplus$ signifies the direct sum of a group of spaces. From equations 3.11 and 3.12, it follows that $\mathcal{H}$ can be decomposed into mutually orthogonal subspaces according to

$$\bigoplus_{m \in \mathbb{Z}} W_m = \mathcal{H} \quad (3.30)$$

With the orthogonal property for W_m , equation 3.27, equation 3.25 equivalently states that $\{\psi_k^m(t) : k \in \mathbb{Z}\}$ is an orthonormal basis for W_m , $\forall m \in \mathbb{Z}$. Similar to equation 3.23, since the family of

functions, $\{\psi(t-k); k \in \mathbb{Z}\}$, are orthonormal, $\langle \psi(t), \psi(t-k) \rangle = \delta(k)$, the orthonormality of this family of functions can be equivalently represented in the Fourier domain as:

$$\mathcal{F}\{\langle \psi(t), \psi(t-k) \rangle\} = \sum_{n \in \mathbb{Z}} |\Psi(\omega + 2\pi n)|^2 = 1 \text{ a.e.} \quad (3.31)$$

Using the orthogonal complement property, equation 3.26, the relationship $\langle \psi(t-l), \phi(t-k) \rangle = 0$ between the corresponding families of functions can be represented in the Fourier domain as:

$$\mathcal{F}\{\langle \psi(t-l), \phi(t-k) \rangle\} = \sum_{n \in \mathbb{Z}} \Psi(\omega + 2\pi n) \overline{\Phi(\omega + 2\pi n)} = 0 \text{ a.e.} \quad (3.32)$$

It has been shown in [3] that functions, $\phi(t)$ and $\psi(t)$, satisfying all of the above properties, necessarily satisfy the following:

$$\int \psi(t) dt = 0 \quad (3.33)$$

$$\int \phi(t) dt \neq 0 \quad (3.34)$$

The nesting, dilation, and basis properties, equations 3.10, 3.13, and 3.15, imply that a normalized scaling function, defined as $\int \phi(t) dt = 1$ with $\phi \in V_0 \subset \mathcal{L}^2(\mathbb{R})$, satisfies the following two-scale dilation equation:

$$\phi(t) = \sqrt{2} \sum_{k \in \mathbb{Z}} h(k) \phi(2t-k) := F_0 \phi(t) \quad (3.35)$$

where $\{h(k)\}$ is a square-summable sequence of coefficients which defines an operator F_0 . Examining the scaling function dilation equation 3.35 for an orthogonal MRA demonstrates that the scaling function dilation coefficients, $h(k)$, satisfy the following relationships:

$$h(k) = \langle \phi(t), \sqrt{2} \phi(2t-k) \rangle \quad (3.36)$$

$$\langle \phi(t), \phi(t) \rangle = \sum_{k \in \mathbb{Z}} \sum_{n \in \mathbb{Z}} h(k) \overline{h(n)} \langle \sqrt{2} \phi(2t-k), \sqrt{2} \phi(2t-n) \rangle \quad (3.37)$$

$$= \sum_{k \in \mathbb{Z}} |h(k)|^2 = 1 \quad (3.38)$$

where $\bar{x}$ indicates the complex conjugate of x . Similarly, a normalized wavelet function, defined as $\int \psi(t) dt = 0$ with $\psi \in W_0 \subset \mathcal{L}^2(\mathbb{R})$, satisfies the following two-scale wavelet equation:

$$\psi(t) = \sqrt{2} \sum_{k \in \mathbb{Z}} g(k) \phi(2t-k) := F_1 \phi(t) \quad (3.39)$$

where $\{g(k)\}$ is a square-summable sequence of coefficients which defines an operator F_1 . Examining the wavelet function dilation equation 3.39 for an orthogonal MRA demonstrates that the wavelet function dilation coefficients, $g(k)$, satisfy the following relationships:

$$g(k) = \langle \psi(t), \sqrt{2} \phi(2t-k) \rangle \quad (3.40)$$

$$\langle \psi(t), \psi(t) \rangle = \sum_{k \in \mathbb{Z}} \sum_{n \in \mathbb{Z}} g(k) \overline{g(n)} \langle \sqrt{2}\phi(2t - k), \sqrt{2}\phi(2t - n) \rangle \quad (3.41)$$

$$= \sum_{k \in \mathbb{Z}} |g(k)|^2 = 1 \quad (3.42)$$

Now using equations 3.37 and 3.41, it follows that:

$$\langle \psi(t), \phi(t) \rangle = \sum_{k \in \mathbb{Z}} \sum_{n \in \mathbb{Z}} g(k) \overline{h(n)} \langle \sqrt{2}\phi(2t - k), \sqrt{2}\phi(2t - n) \rangle = \sum_{k \in \mathbb{Z}} g(k) \overline{h(k)} = 0 \quad (3.43)$$

$$\langle \phi(t), \psi(t) \rangle = \sum_{k \in \mathbb{Z}} \sum_{n \in \mathbb{Z}} h(k) \overline{g(n)} \langle \sqrt{2}\phi(2t - k), \sqrt{2}\phi(2t - n) \rangle = \sum_{k \in \mathbb{Z}} h(k) \overline{g(k)} = 0 \quad (3.44)$$

Taking the Fourier transform of equations 3.35 and 3.39 allows for an equivalent representation of the two-scale equations as follows:

$$\Phi(\omega) = \frac{1}{\sqrt{2}} \sum_{k \in \mathbb{Z}} h(k) e^{-jk\omega/2} \Phi(\omega/2) = \Theta_0(\omega/2) \Phi(\omega/2) \text{ a.e.} \quad (3.45)$$

$$\Psi(\omega) = \frac{1}{\sqrt{2}} \sum_{k \in \mathbb{Z}} g(k) e^{-jk\omega/2} \Phi(\omega/2) = \Theta_1(\omega/2) \Phi(\omega/2) \text{ a.e.} \quad (3.46)$$

where $\Theta_0(\omega) = \frac{1}{\sqrt{2}} \sum_{k \in \mathbb{Z}} h(k) e^{-jk\omega}$ and $\Theta_1(\omega) = \frac{1}{\sqrt{2}} \sum_{k \in \mathbb{Z}} g(k) e^{-jk\omega}$ are 2π -periodic functions in $\mathcal{L}^2([0, 2\pi])$. Substituting equation 3.45 into equation 3.23 and 3.46 into equation 3.31 yields:

$$\mathcal{F}\{\langle \phi(t), \phi(t - k) \rangle\} = \sum_{n \in \mathbb{Z}} |\Theta_0(\omega/2 + \pi n)|^2 |\Phi(\omega/2 + \pi n)|^2 = 1 \text{ a.e.} \quad (3.47)$$

$$\mathcal{F}\{\langle \psi(t), \psi(t - k) \rangle\} = \sum_{n \in \mathbb{Z}} |\Theta_1(\omega/2 + \pi n)|^2 |\Phi(\omega/2 + \pi n)|^2 = 1 \text{ a.e.} \quad (3.48)$$

Now splitting the above sum into a sum for n even and into a sum for n odd, using the periodicity of Θ_0 and Θ_1 , and utilizing equation 3.23 gives:

$$\mathcal{F}\{\langle \phi(t), \phi(t - k) \rangle\} = |\Theta_0(\omega/2)|^2 + |\Theta_0(\omega/2 + \pi)|^2 = 1 \text{ a.e.} \quad (3.49)$$

$$\mathcal{F}\{\langle \psi(t), \psi(t - k) \rangle\} = |\Theta_1(\omega/2)|^2 + |\Theta_1(\omega/2 + \pi)|^2 = 1 \text{ a.e.} \quad (3.50)$$

In addition, substituting equations 3.45 and 3.46 into equation 3.32 yields:

$$\mathcal{F}\{\langle \psi(t - n), \phi(t - k) \rangle\} = \sum_{n \in \mathbb{Z}} \Theta_1(\omega/2 + \pi n) \overline{\Theta_0(\omega/2 + \pi n)} |\Phi(\omega/2 + \pi n)|^2 = 0 \text{ a.e.} \quad (3.51)$$

Splitting this sum into a sum for n even and into a sum for n odd, using the periodicity of Θ_0 and Θ_1 , and utilizing equation 3.23 gives:

$$\mathcal{F}\{\langle \psi(t - n), \phi(t - k) \rangle\} = \Theta_1(\omega/2) \overline{\Theta_0(\omega/2)} + \Theta_1(\omega/2 + \pi) \overline{\Theta_0(\omega/2 + \pi)} = 0 \text{ a.e.} \quad (3.52)$$

According to equation 3.49, $\overline{\Theta_0(\omega/2)}$ and $\overline{\Theta_0(\omega/2 + \pi)}$ cannot both vanish on a set of nonzero measure, which implies the existence of a 2π -periodic function, $\beta(\omega/2)$, such that

$$\Theta_1(\omega/2) = \beta(\omega/2) \overline{\Theta_0(\omega/2 + \pi)} \quad (3.53)$$

where $\beta(\omega/2) + \beta(\omega/2 + \pi) = 0$ a.e. or equivalently, $\beta(\omega/2) = e^{j\omega/2}\alpha(\omega)$ with $\alpha(\omega)$ 2π -periodic. Choosing $\alpha(\omega) = \alpha_0 e^{jk\omega}$ with $k \in \mathbb{Z}$, and $|\alpha_0| = 1$, equation 3.53 becomes:

$$\Theta_1(\omega/2) = e^{j\omega/2}\alpha(\omega)\overline{\Theta_0(\omega/2 + \pi)} \quad (3.54)$$

Now the wavelet dilation equation coefficients, $g(k)$, can be related to the scaling function dilation equation coefficients, $h(k)$, in a number of ways. The two most commonly used relationships are as follows:

$$g(k) = (-1)^k \overline{h(1-k)} \quad (3.55)$$

$$g(k) = (-1)^k \overline{h(N-k)} \quad (3.56)$$

with $N = L - 1$, where L is the length of the impulse response for the filter $h(k)$ which is even. Note that equation 3.56 results in a causal filter $g(k)$.

If $\phi \in \mathcal{L}^1(\mathbb{R})$, then equations 3.45 and 3.46 can be iterated on the right hand side to yield:

$$\Phi(\omega) = \Theta_0(\omega/2) \prod_{k=1}^{\infty} \Theta_0(2^{-(k+1)}\omega) \Phi(0) \quad (3.57)$$

$$\Psi(\omega) = \Theta_1(\omega/2) \prod_{k=1}^{\infty} \Theta_0(2^{-(k+1)}\omega) \Phi(0) \quad (3.58)$$

Since the scaling function is assumed to be normalized such that $\int \phi(t)dt = 1 = \Phi(0)$, the above equations become:

$$\Phi(\omega) = \Theta_0(\omega/2) \prod_{k=1}^{\infty} \Theta_0(2^{-(k+1)}\omega) \quad (3.59)$$

$$\Psi(\omega) = \Theta_1(\omega/2) \prod_{k=1}^{\infty} \Theta_0(2^{-(k+1)}\omega) \quad (3.60)$$

The minimum requirement for any infinite product to converge is that $\Theta_0(2^{-k}\omega) \rightarrow 1$ as $k \rightarrow \infty$. Therefore, $\Theta_0(0) = 1$ provides another condition, besides conditions 3.36 and 3.37, which the scaling function dilation equation coefficients, $h(k)$, must satisfy, (see equation 3.35):

$$\sum_{k \in \mathbb{Z}} h(k) = \sqrt{2} \quad (3.61)$$

Also observe that since $\Psi(0) = 0$, see equation 3.33, and $\Theta_0(0) = 1$, it follows that $\Theta_1(0) = 0$. Now, $\Theta_1(0) = 0$ provides a another condition, besides conditions 3.40 or 3.41, which the wavelet function dilation equation coefficients, $g(k)$, must satisfy, (see equation 3.39):

$$\sum_{k \in \mathbb{Z}} g(k) = 0 \quad (3.62)$$

It should be noted that if $\phi(t) \in \mathcal{L}^2(\mathbb{R})$ and $\phi(t)$ has compact support, then $\phi(t) \in \mathcal{L}^1(\mathbb{R})$. Therefore, $\phi(t) \in \mathcal{L}^2(\mathbb{R}) \cap \mathcal{L}^1(\mathbb{R})$.

CHAPTER 4

WAVELETS AND FILTER BANKS

A quadrature filter denotes an operator which performs convolution and then decimation. The operators defined previously in chapter 3, 3.35 and 3.39, namely, F_0 and F_1 , are quadrature filters. Typically, F_0 consists of a low pass filter (LPF), H , followed by a decimator, $\downarrow 2$, whereas F_1 consists of a high pass filter (HPF), G , followed by a decimator. Note that $\downarrow 2$ indicates downsampling by 2. A complementary quadrature filter denotes an operator which performs interpolation and then convolution. The complementary quadrature operators are denoted by $\tilde{F}_0$ and $\tilde{F}_1$. Typically, $\tilde{F}_0$ consists of an interpolator, $\uparrow 2$, followed by a low pass filter (LPF), $\tilde{H}$, whereas $\tilde{F}_1$ consists of an interpolator, $\uparrow 2$, followed by a high pass filter (HPF), $\tilde{G}$. Note that $\uparrow 2$ indicates upsampling by 2. In general, a quadrature filter is not invertible, i.e., there does not exist a complementary quadrature filter which would guarantee perfect reconstruction of the input signal after the quadrature filter's decimation process. A two channel, perfect reconstruction (PR) filter bank, also called a subband decomposition, is shown in figure 4.1 and guarantees that the output signal of the filter bank, $\hat{x}(t)$, is a perfect replica of the input signal, $x(t)$. The output signal from a PR filter bank is usually a delayed version of the input signal. The analysis filter bank, see figure 4.1, consists of a pair of quadrature filters, F_0 and F_1 , and the synthesis bank contains a pair of complementary quadrature filters, $\tilde{F}_0$ and $\tilde{F}_1$. The first type of two channel PR filter bank used quadrature mirror filters (QMFs) [23], with low and high pass filters are related by $G(z) = H(-z)$. The Fourier Transforms for QMFs have mirror symmetry about the frequency $\frac{\pi}{2}$. However, it is impossible to construct orthogonal, finite impulse response (FIR) QMFs with perfect reconstruction since the QMF filters are nonideal. The next development in two channel PR filter banks used quadrature filters in which the low and high pass filters are related according to [24], [25] and [26]:

$$G(z) = -z^{-N} \overline{H(-z)} \quad (4.1)$$

where the length, L , of the impulse response of the filter $H(z)$ is even with $N = L - 1$ and $\bar{x}$ symbolizes complex conjugate of x . Note that for filters $H(z)$ with real coefficients, equation 4.1

becomes $G(z) = -z^{-N}H(-z^{-1})$. The inverse z -transform of equation 4.1 yields the relationship between the coefficients $g(k)$ and $h(k)$ given by equation 3.56 in chapter 3. Equation 4.1 allows for orthogonal, FIR, PR filter banks. Some of the numerous additional extensions of the above results include M -channel PR filter banks [27], [28] and biorthogonal PR filter banks [29].

Figure 4.1: Perfect Reconstruction Filter Bank

Definition 4.1 (Biorthogonal Quadrature Filter Operators [30])

The quadrature filters, F_0 and F_1 , and complementary quadrature filters, $\tilde{F}_0$ and $\tilde{F}_1$, in a two-channel, PR, biorthogonal filter bank satisfy the following conditions:

$$\begin{aligned} \text{Duality: } F_0 \tilde{F}_0 &= F_1 \tilde{F}_1 = \tilde{F}_0^* F_0^* = \tilde{F}_1^* F_1^* = I, \\ \sum_{k \in \mathbb{Z}} h(k) \tilde{h}(k+2n) &= \sum_{k \in \mathbb{Z}} g(k) \tilde{g}(k+2n) = \delta(n); \end{aligned}$$

$$\begin{aligned} \text{Independence: } F_1 \tilde{F}_0 &= F_0 \tilde{F}_1 = \tilde{F}_1^* F_0^* = \tilde{F}_0^* F_1^* = 0, \\ \sum_{k \in \mathbb{Z}} g(k) \tilde{h}(k+2n) &= \sum_{k \in \mathbb{Z}} h(k) \tilde{g}(k+2n) = 0; \end{aligned}$$

$$\text{Perfect Reconstruction: } \tilde{F}_0 F_0 + \tilde{F}_1 F_1 = \tilde{F}_0^* F_0^* + \tilde{F}_1^* F_1^* = I;$$

$$\begin{aligned} \text{Normalization: (i) } F_0 \mathbf{1} &= \sqrt{2} \mathbf{1} = \sqrt{2} \begin{bmatrix} \dots & 1 & 1 & \dots \end{bmatrix}^T, \\ \sum_{k \in \mathbb{Z}} h(k) &= \sqrt{2}; \\ \text{(ii) } F_1 \mathbf{1} &= \tilde{F}_1 \mathbf{1} = \mathbf{0} = \begin{bmatrix} \dots & 0 & 0 & \dots \end{bmatrix}^T, \\ \sum_{k \in \mathbb{Z}} g(k) &= \sum_{k \in \mathbb{Z}} \tilde{g}(k) = 0; \\ \text{(iii) } \tilde{F}_0 \mathbf{1} &= \frac{1}{\sqrt{2}} \mathbf{1}, \\ \sum_{k \in \mathbb{Z}} \tilde{h}(2k) &= \sum_{k \in \mathbb{Z}} \tilde{h}(2k+1) = \frac{1}{\sqrt{2}}. \end{aligned}$$

Definition 4.2 (Orthogonal Quadrature Filter Operators [30])

In a two-channel, PR, orthogonal filter bank, the complementary quadrature filters are the corresponding adjoints of the quadrature filters, $\tilde{F}_0 = F_0^*$ and $\tilde{F}_1 = F_1^*$, satisfying the following conditions:

$$\begin{aligned} \text{Self-Duality: } F_0 F_0^* &= F_1 F_1^* = I, \\ \sum_{k \in \mathbb{Z}} h(k) \tilde{h}(k+2n) &= \sum_{k \in \mathbb{Z}} g(k) \tilde{g}(k+2n) = \delta(n); \end{aligned}$$

$$\begin{aligned} \text{Independence: } F_1 F_0^* &= F_0 F_1^* = 0, \\ \sum_{k \in \mathbb{Z}} g(k) \tilde{h}(k+2n) &= \sum_{k \in \mathbb{Z}} h(k) \tilde{g}(k+2n) = 0; \end{aligned}$$

$$\text{Perfect Reconstruction: } F_0^* F_0 + F_1^* F_1 = I;$$

$$\begin{aligned} \text{Normalization: (i) } F_0 \mathbf{1} &= \sqrt{2} \mathbf{1}, \\ \sum_{k \in \mathbb{Z}} h(k) &= \sqrt{2}; \\ \text{(ii) } F_1 \mathbf{1} &= \mathbf{0}, \\ \sum_{k \in \mathbb{Z}} g(k) &= 0; \\ \text{(iii) } F_0^* \mathbf{1} &= \frac{1}{\sqrt{2}} \mathbf{1}, \\ \sum_{k \in \mathbb{Z}} h(2k) &= \sum_{k \in \mathbb{Z}} h(2k+1) = \frac{1}{\sqrt{2}}. \end{aligned}$$

The quadrature filter operators can be represented in the following matrix form:

$$F_0 = \begin{bmatrix} \ddots & & \ddots & & \ddots \\ \cdots & h(3) & h(2) & h(1) & h(0) & \cdots \\ \cdots & h(5) & h(4) & h(3) & h(2) & \cdots \\ \ddots & & \ddots & & \ddots \end{bmatrix} \quad (4.2)$$

$$F_1 = \begin{bmatrix} \ddots & & \ddots & & \ddots \\ \cdots & g(3) & g(2) & g(1) & g(0) & \cdots \\ \cdots & g(5) & g(4) & g(3) & g(2) & \cdots \\ \ddots & & \ddots & & \ddots \end{bmatrix} \quad (4.3)$$

The actions of the quadrature filter operators on a function of a single variable, $x(t)$, are represented as follows:

$$F_0 x(t) = \sqrt{2} \sum_{k \in \mathbb{Z}} h(k) x(2t - k) \quad (4.4)$$

$$F_1 x(t) = \sqrt{2} \sum_{k \in \mathbb{Z}} g(k) x(2t - k) \quad (4.5)$$

The complementary quadrature filter operators can be represented in the following matrix form:

$$\bar{F}_0 = \begin{bmatrix} \ddots & \vdots & \vdots & \ddots \\ & \bar{h}(3) & \bar{h}(5) & \\ \vdots & \bar{h}(2) & \bar{h}(4) & \vdots \\ \vdots & \bar{h}(1) & \bar{h}(3) & \vdots \\ & \bar{h}(0) & \bar{h}(2) & \\ \ddots & \vdots & \vdots & \ddots \end{bmatrix} \quad (4.6)$$

$$\bar{F}_1 = \begin{bmatrix} \ddots & \vdots & \vdots & \ddots \\ & \bar{g}(3) & \bar{g}(5) & \\ \vdots & \bar{g}(2) & \bar{g}(4) & \vdots \\ \vdots & \bar{g}(1) & \bar{g}(3) & \vdots \\ & \bar{g}(0) & \bar{g}(2) & \\ \ddots & \vdots & \vdots & \ddots \end{bmatrix} \quad (4.7)$$

The actions of the complementary quadrature filter operators on a function of a single variable, $x(t)$, are represented as follows:

$$\bar{F}_0 x(t) = \frac{1}{\sqrt{2}} \sum_{k \in \mathbb{Z}} \bar{h}(k) x\left(\frac{t+k}{2}\right) = \frac{1}{\sqrt{2}} \sum_{k \in \mathbb{Z}} \bar{h}(2k) x\left(\frac{t}{2} + k\right) \quad (4.8)$$

$$\bar{F}_1 x(t) = \frac{1}{\sqrt{2}} \sum_{k \in \mathbb{Z}} \bar{g}(k) x\left(\frac{t+k}{2}\right) = \frac{1}{\sqrt{2}} \sum_{k \in \mathbb{Z}} \bar{g}(2k) x\left(\frac{t}{2} + k\right) \quad (4.9)$$

The connection between orthogonal wavelets and orthogonal, PR filters banks of finite length was first established in [31]. A similar connection can be made between biorthogonal wavelets and biorthogonal, PR filter banks of finite length as was demonstrated in [32], [33]. The scaling function, $\phi(t)$, and wavelet function, $\psi(t)$, which were derived based on a multiresolution analysis in chapter 3, can also be derived by performing an infinite, lowpass iteration on particular perfect reconstruction filter banks as shown in figures 4.2 and 4.3. Figure 4.2 displays an infinite iteration on the wavelet analysis filter bank and figure 4.3 displays an infinite iteration on the wavelet synthesis filter bank.

The scaling function, $\phi(t)$, and wavelet function, $\psi(t)$, for the wavelet analysis bank of figure 4.2 will now be derived. The scaling function, $\tilde{\phi}(t)$, and wavelet function, $\tilde{\psi}(t)$, for the wavelet synthesis bank, figure 4.3, can be derived in a similar way and will not be presented here. The Noble identities [34], see figure 4.4, are essential to the derivation of the scaling function and wavelet function for each of the corresponding filter banks. For the wavelet analysis bank, figure 4.2, assume that the low and high pass filters are FIR filters. The derivation of the scaling function, $\phi(t)$, will now be performed. Using the first Noble identity, figure 4.4(a), in an iterative manner on the low pass filters

Figure 4.2: Wavelet Analysis Filter Bank

Figure 4.3: Wavelet Synthesis Filter Bank

in figure 4.2, $\mathbf{H}$, leads to the following relationship:

$$H^{(m)}(z) = \prod_{k=0}^m H(z^{2^k}), \quad m = 0, 1, \dots \quad (4.10)$$

followed by downsampling by 2^{m+1} . The length of the impulse response of the filter, $H^{(m)}(z)$, at each iteration m is $L^{(m)} = (2^{m+1} - 1)(L - 1) + 1$. Define a piecewise constant function at each iteration m as follows:

$$\phi^{(m)}(t) = 2^{\frac{m+1}{2}} h^{(m)}(n), \quad \frac{n}{2^{m+1}} \leq t < \frac{n+1}{2^{m+1}} \quad (4.11)$$

The normalization factor, $2^{\frac{m+1}{2}}$, is to ensure that $\int (\phi^{(m)}(t))^2 dt = 1$ when $\sum (h^{(m)}(n))^2 = 1$. Similarly, $\|h^{(m)}\|_2 = 1$ when $\|h^{(m-1)}\|_2 = 1$. Equation 4.10 can be written as a function of the

$$\begin{array}{c} \text{---} \overline{\mathbf{F}(\mathbf{z}^{\mathbf{M}})} \text{---} \overline{\mathbf{M}} \text{---} \equiv \text{---} \overline{\mathbf{M}} \text{---} \overline{\mathbf{F}(\mathbf{z})} \text{---} \\ \text{(a)} \end{array}$$

$$\begin{array}{c} \text{---} \overline{\mathbf{M}} \text{---} \overline{\mathbf{F}(\mathbf{z}^{\mathbf{M}})} \text{---} \equiv \text{---} \overline{\mathbf{F}(\mathbf{z})} \text{---} \overline{\mathbf{M}} \text{---} \\ \text{(b)} \end{array}$$

Figure 4.4: Noble Identities for Multirate Filter Banks. (a) Interchange property between downsampling and filtering operations. (b) Interchange property between upsampling and filtering operations.

previous iteration as follows:

$$H^{(m)}(z) = H(z^{2^m})H^{(m-1)}(z), \quad m = 0, 1, \dots \quad (4.12)$$

Recall the following z-transform relation:

$$\mathcal{Z}^{-1}\{H(z^M)\} = \begin{cases} h\left(\frac{n}{M}\right), & n = kM, k \in \mathbb{Z} \\ 0 & \text{otherwise} \end{cases} \quad (4.13)$$

with $\mathcal{Z}$ signifying the z-transform. Taking the inverse z-transform of equation 4.12 yields:

$$h^{(m)}(n) = \sum_{k \in \mathbb{Z}} h\left(\frac{k}{2^m}\right) h^{(m-1)}(n - k) = \sum_{k \in \mathbb{Z}} h(k) h^{(m-1)}(n - 2^m k) \quad (4.14)$$

Using equation 4.14 in equation 4.11 gives:

$$\phi^{(m)}(t) = 2^{\frac{m+1}{2}} \sum_{k \in \mathbb{Z}} h(k) h^{(m-1)}(n - 2^m k), \quad \frac{n}{2^{m+1}} \leq t < \frac{n+1}{2^{m+1}} \quad (4.15)$$

It is necessary to express $h^{(m-1)}(n - 2^m k)$ in terms of $\phi^{(m-1)}$ for the interval $\frac{n}{2^{m+1}} \leq t < \frac{n+1}{2^{m+1}}$.

This is accomplished by the following relation:

$$h^{(m-1)}(n - 2^m k) = 2^{\frac{m}{2}} \phi^{(m-1)}(2t - k), \quad \frac{n}{2^{m+1}} \leq t < \frac{n+1}{2^{m+1}} \quad (4.16)$$

Using equation 4.16 in equation 4.15 leads to the result:

$$\phi^{(m)}(t) = 2^{\frac{1}{2}} \sum_{k \in \mathbb{Z}} h(k) \phi^{(m-1)}(2t - k), \quad \frac{n}{2^{m+1}} \leq t < \frac{n+1}{2^{m+1}} \quad (4.17)$$

Define the limit function for equation 4.17 to be the scaling function $\phi(t)$. Assuming pointwise convergence *a.e.* of $\phi^{(m)}(t) \rightarrow \phi(t)$ as $m \rightarrow \infty$, it follows that by taking the limit in equation 4.17 yields:

$$\phi(t) = \sqrt{2} \sum_{k \in \mathbb{Z}} h(k) \phi(2t - k) \quad (4.18)$$

Observe that equation 4.18 is a two-scale dilation equation identical to equation 3.35, given in chapter 3, which is the desired result.

The derivation of the wavelet function, $\psi(t)$, for the wavelet analysis bank of figure 4.2 is very similar to the previous derivation for the scaling function, $\phi(t)$, but will be presented for completeness. Using the first Noble identity, figure 4.4(a), in an iterative manner on the low pass filters in figure 4.2, **H**, with the last filter being a high pass filter, **G**, leads to the following relationship:

$$G^{(m)}(z) = G(z^{2^m}) \prod_{k=0}^{m-1} H(z^{2^k}) = G(z^{2^m}) H^{(m-1)}(z), \quad m = 1, 2, \dots \quad (4.19)$$

followed by downsampling by 2^{m+1} . Define $G^{(0)}(z) = 1$. Once again, define a piecewise constant function at each iteration m as follows:

$$\psi^{(m)}(t) = 2^{\frac{m+1}{2}} g^{(m)}(n), \quad \frac{n}{2^{m+1}} \leq t < \frac{n+1}{2^{m+1}} \quad (4.20)$$

Taking the inverse z-transform of equation 4.19 gives:

$$g^{(m)}(n) = \sum_{k \in \mathbb{Z}} g\left(\frac{k}{2^m}\right) h^{(m-1)}(n - k) = \sum_{k \in \mathbb{Z}} g(k) h^{(m-1)}(n - 2^m k) \quad (4.21)$$

Using equation 4.21 in equation 4.20 gives:

$$\psi^{(m)}(t) = 2^{\frac{m+1}{2}} \sum_{k \in \mathbb{Z}} g(k) h^{(m-1)}(n - 2^m k), \quad \frac{n}{2^{m+1}} \leq t < \frac{n+1}{2^{m+1}} \quad (4.22)$$

Using equation 4.16 in equation 4.22 leads to the result:

$$\psi^{(m)}(t) = 2^{\frac{1}{2}} \sum_{k \in \mathbb{Z}} g(k) \phi^{(m-1)}(2t - k), \quad \frac{n}{2^{m+1}} \leq t < \frac{n+1}{2^{m+1}} \quad (4.23)$$

Define the limit function for equation 4.23 to be the wavelet function $\psi(t)$. Assuming pointwise convergence *a.e.* of $\psi^{(m)}(t) \rightarrow \psi(t)$ and $\phi^{(m)}(t) \rightarrow \phi(t)$ as $m \rightarrow \infty$, it follows that by taking the limit in equation 4.23 yields:

$$\psi(t) = \sqrt{2} \sum_{k \in \mathbb{Z}} g(k) \phi(2t - k) \quad (4.24)$$

Observe that equation 4.24 is a two-scale dilation equation identical to equation 3.39, given in chapter 3, which is the desired result.

CHAPTER 5

WAVELET PACKETS

The theory of wavelet packets is a generalization of wavelet theory and multiresolution analysis introduced by Coifman and Meyer [35], and Wickerhauser [36], [37], [38], and [30]. This chapter will present a recapitulation of the main concepts of wavelet packet theory utilized in the sequel, along with some minor theoretical extensions which do not appear in the literature.

Definition 5.1 (Combined Operations for Wavelet Packets)

1. The dilation operator followed by the translation operation for a wavelet packet function $\psi_f(t)$ is represented by:

$$T_p D_s \psi_f(t) := 2^{s/2} \psi_f(2^s t - p) \quad (5.1)$$

In shorthand notation, $\psi_{f,p}^s(t) := T_p D_s \psi_f(t)$.

2. The translation operator followed by the dilation operation for a wavelet packet function $\psi_f(t)$ is represented by:

$$D_s T_p \psi_f(t) := 2^{s/2} \psi_f(2^s(t - p)) \quad (5.2)$$

In shorthand notation, $\tilde{\psi}_{f,p}^s(t) := D_s T_p \psi_f(t)$.

3. The adjoint of the dilation operator followed by the translation operator for a wavelet packet function $\psi_f(t)$ is represented by:

$$(T_p D_s)^* \psi_f(t) := D_s^* T_p^* \psi_f(t) = 2^{-s/2} \psi_f(2^{-s}(t + p)) \quad (5.3)$$

In shorthand notation, $\psi_{f,k_*}^{s*}(t) := D_s^* T_p^* \psi_f(t)$.

4. The adjoint of the translation operator followed by the dilation operator for a wavelet packet function $\psi_f(t)$ is represented by:

$$(D_s T_p)^* \psi_f(t) := T_p^* D_s^* \psi_f(t) = 2^{-s/2} \psi_f(2^{-s}t + p) \quad (5.4)$$

In shorthand notation, $\tilde{\psi}_{f,k_*}^{m*}(t) := T_p^* D_s^* \psi_f(t)$.

Definition 5.2 (Binary Representation)

For any $f \in \mathbb{Z}^+$, where $\mathbb{Z}^+$ is the positive integers, the infinite binary expansion of f is given by:

$$f = \sum_{k=0}^{\infty} f_k 2^k, \quad f_k \in \{0, 1\} \quad (5.5)$$

In shorthand notation, $\{f_k : k \in \mathbb{Z}^+\} := \sum_{k=0}^{\infty} f_k 2^k$.

Definition 5.3 (Wavelet Packet Frequency Filter Sequence)

Let the wavelet packet frequency, $f \in \mathbb{Z}^+$, $0 \leq f \leq 2^N - 1$, be represented by an infinite binary expansion, $\{f_k : k \in \mathbb{Z}^+\}$. Define the wavelet packet frequency filter sequence (WPFFS) in the frequency domain, $Q_{N-1}Q_{N-2} \cdots Q_0$ with length N , according to:

$$Q_k = \begin{cases} H, & \text{if } f_k = 0 \\ G, & \text{if } f_k = 1 \end{cases} \quad (5.6)$$

The corresponding time domain representation, q_k , for an element of the WPFFS, Q_k , is as follows:

$$q_k = \begin{cases} h, & \text{if } f_k = 0 \\ g, & \text{if } f_k = 1 \end{cases} \quad (5.7)$$

Define the wavelet packet frequency operator sequence (WPFOS), $\eta_{N-1}\eta_{N-2} \cdots \eta_0$, according to:

$$\eta_k = \begin{cases} F_0, & \text{if } f_k = 0 \\ F_1, & \text{if } f_k = 1 \end{cases} \quad (5.8)$$

Recall that F_0 and F_1 are quadrature filter operators as shown in figure 4.1.

Chapter 3 described a MRA with a scaling basis function, $D_m\phi(t) \in V_m$, whose translations k , $\{T_k D_m\phi(t) : k \in \mathbb{Z}\}$, comprised a Riesz basis for V_m . Similarly, chapter 3 presented a wavelet basis function, $D_m\psi(t) \in W_m$, whose translations k , $\{T_k D_m\psi(t) : k \in \mathbb{Z}\}$, comprised a Riesz basis for W_m . According to equations 3.15, 3.18 and 3.22, any signal, $x \in V_m$, can be decomposed into a series of scaling basis functions and wavelet basis functions. The previous chapter, chapter 4, demonstrated how an iterated, perfect reconstruction filter bank can be viewed as generating a MRA, and generated the scaling and wavelet basis functions in the context of such filter banks. This chapter generalizes the concepts presented in chapters 3 and 4.

Wavelet packets can be viewed as a generalization of a MRA. Simply put, wavelet packets are particular linear combinations of wavelets whose translations also comprise a Riesz basis for $V_m \subset \mathcal{H}$, $\forall m \in \mathbb{Z}$. The two-scale dilation and wavelet equations, 3.35 and 3.39, can be generalized to form the unit scale wavelet packet equations as follows:

$$\psi_{2f}(t) = \sqrt{2} \sum_{k \in \mathbb{Z}} h(k) \psi_f(2t - k) := F_0 \psi_f(t) \in W_{2f} \quad (5.9)$$

$$\psi_{2f+1}(t) = \sqrt{2} \sum_{k \in \mathbb{Z}} g(k) \psi_f(2t - k) := F_1 \psi_f(t) \in W_{2f+1} \quad (5.10)$$

Note that $\phi(t)$ of equation 3.35 is given by $\phi(t) = \psi_0(t)$ and $\psi(t)$ of equation 3.39 is given by $\psi(t) = \psi_1(t)$. Examining the wavelet packet dilation equations 5.9 and 5.10 for an orthogonal MRA demonstrates that the wavelet packet function dilation coefficients, $h(k)$ and $g(k)$, satisfy the following relationships:

$$h(k) = \langle \psi_{2f}(t), \sqrt{2}\psi_f(2t - k) \rangle \quad (5.11)$$

$$g(k) = \langle \psi_{2f+1}(t), \sqrt{2}\psi_f(2t - k) \rangle \quad (5.12)$$

Equations 5.9 and 5.10 can be combined as follows:

$$\psi_f(t) = \begin{cases} F_0 \psi_{\frac{f}{2}}(t), & \text{if } f \text{ is even} \\ F_1 \psi_{\frac{f-1}{2}}(t), & \text{if } f \text{ is odd} \end{cases} \quad (5.13)$$

Wavelet packets can be viewed as a generalization of an iterated, perfect reconstruction filter bank, see figures 4.2 and 4.3. Figure 5.1 displays an infinite iteration on the generalized wavelet packet analysis filter bank. Recalling Definition 5.1, a unit scale, scale $s = 0$, wavelet packet is

Figure 5.1: Wavelet Packet Analysis Filter Bank

defined by:

$$\psi_{f,p}(t) := \psi_f(t - p) \quad (5.14)$$

where $f \in \mathbb{Z}^+$ is the frequency, and $p \in \mathbb{Z}$ is the position of the wavelet packet. Now the unit scale wavelet packet at a fixed position $p = 0$, $\psi_f(t) := \psi_{f,0}(t)$, with $0 \leq f \leq 2^N - 1$ will be derived

by performing an infinite iteration on the generalized wavelet packet analysis filter bank in figure 5.1. The derivation of the wavelet packet functions, $\psi_f(t)$, is very similar to the derivation for the wavelet function, $\psi(t)$, presented in chapter 4, which started with equation 4.23. The procedure for obtaining wavelet packets is identical, except that equation 4.19 is generalized for $m = N, N+1, \dots$, as follows:

$$Q^{(m)}(z) = \prod_{k=m-N+1}^m Q_{m-k}(z^{2^k}) \prod_{l=0}^{m-N} H(z^{2^l}) = \prod_{k=m-N+1}^m Q_{m-k}(z^{2^k}) H^{(m-N)}(z) \quad (5.15)$$

followed by downsampling by 2^{m+1} , where Q_k is the WPFFS described in Definition 5.3. Once again, define a piecewise constant function at each iteration m as follows:

$$\psi_f^{(m)}(t) = 2^{\frac{m+1}{2}} q^{(m)}(n), \quad \frac{n}{2^{m+1}} \leq t < \frac{n+1}{2^{m+1}} \quad (5.16)$$

Taking the inverse z-transform of equation 5.15 gives:

$$q^{(m)}(n) = \sum_{i \in \mathbb{Z}} q_0\left(\frac{i}{2^m}\right) \cdots \sum_{j \in \mathbb{Z}} q_{N-2}\left(\frac{j}{2^{m-N+2}}\right) \sum_{k \in \mathbb{Z}} q_{N-1}\left(\frac{k}{2^{m-N+1}}\right) h^{(m-N)}(n-i-\dots-j-k) \quad (5.17)$$

$$q^{(m)}(n) = \sum_{i \in \mathbb{Z}} q_0(i) \cdots \sum_{j \in \mathbb{Z}} q_{N-2}(j) \sum_{k \in \mathbb{Z}} q_{N-1}(k) h^{(m-N)}(n-2^m i - \dots - 2^{m-N+2} j - 2^{m-N+1} k) \quad (5.18)$$

Using equation 5.18 in equation 5.16 for the interval $\frac{n}{2^{m+1}} \leq t < \frac{n+1}{2^{m+1}}$ gives:

$$\psi_f^{(m)}(t) = 2^{\frac{m+1}{2}} \sum_{i \in \mathbb{Z}} q_0(i) \cdots \sum_{j \in \mathbb{Z}} q_{N-2}(j) \sum_{k \in \mathbb{Z}} q_{N-1}(k) h^{(m-N)}(n-2^m i - \dots - 2^{m-N+2} j - 2^{m-N+1} k) \quad (5.19)$$

Expressing $h^{(m-N)}(\bullet)$ of equation 5.19 in terms of $\phi^{(m-N)}$, see equation 4.11, for the interval $\frac{n}{2^{m+1}} \leq t < \frac{n+1}{2^{m+1}}$ gives:

$$h^{(m-N)}(n-2^m i - \dots - 2^{m-N+2} j - 2^{m-N+1} k) = 2^{\frac{-(m-N+1)}{2}} \phi^{(m-N)}(2^N t - 2^{N-1} i - \dots - 2j - k) \quad (5.20)$$

Using equation 5.20 in equation 5.19 for the interval $\frac{n}{2^{m+1}} \leq t < \frac{n+1}{2^{m+1}}$ leads to the result:

$$\psi_f^{(m)}(t) = 2^{\frac{N}{2}} \sum_{i \in \mathbb{Z}} q_0(i) \cdots \sum_{j \in \mathbb{Z}} q_{N-2}(j) \sum_{k \in \mathbb{Z}} q_{N-1}(k) \phi^{(m-N)}(2^N t - 2^{N-1} i - \dots - 2j - k) \quad (5.21)$$

Define the limit function for equation 5.21 to be the wavelet function $\psi_f(t)$. Assuming pointwise convergence a.e. of $\psi_f^{(m)}(t) \rightarrow \psi_f(t)$ and $\phi^{(m-N)}(t) \rightarrow \phi(t)$ as $m \rightarrow \infty$, it follows that by taking the limit in equation 5.21 yields:

$$\psi_f(t) = 2^{\frac{N}{2}} \sum_{i \in \mathbb{Z}} q_0(i) \cdots \sum_{j \in \mathbb{Z}} q_{N-2}(j) \sum_{k \in \mathbb{Z}} q_{N-1}(k) \phi(2^N t - 2^{N-1} i - \dots - 2j - k) \quad (5.22)$$

Recalling that $\psi_0(t) := \phi(t)$, equation 5.22 can be rewritten as:

$$\psi_f(t) = 2^{\frac{N}{2}} \sum_{i \in \mathbb{Z}} q_0(i) \cdots \sum_{j \in \mathbb{Z}} q_{N-2}(j) \sum_{k \in \mathbb{Z}} q_{N-1}(k) \psi_0(2^N t - 2^{N-1}i - \cdots - 2j - k) \quad (5.23)$$

Another equivalent representation of equation 5.23 will now be derived. First include another summation term for $q_{N-3}(m)$, then let $l = 2^{N-1}i + \cdots + 2j + k$ in equation 5.23 and finally let $k = l$ yielding:

$$\begin{aligned} \psi_f(t) &= 2^{\frac{N}{2}} \sum_{i \in \mathbb{Z}} q_0(i) \cdots \sum_{m \in \mathbb{Z}} q_{N-3}(m) \sum_{j \in \mathbb{Z}} q_{N-2}(j) \sum_{k \in \mathbb{Z}} \\ &\quad q_{N-1}(k - 2^{N-1}i - \cdots - 4m - 2j) \psi_0(2^N t - k) \end{aligned} \quad (5.24)$$

Now let $2k = k$ in equation 5.24, rearrange the order of the summations, and consolidate the convolution term, $*$:= convolution, as follows:

$$\begin{aligned} \psi_f(t) &= 2^{\frac{N}{2}} \sum_{i \in \mathbb{Z}} q_0(i) \cdots \sum_{m \in \mathbb{Z}} q_{N-3}(m) \sum_{k \in \mathbb{Z}} \sum_{j \in \mathbb{Z}} q_{N-2}(j) \\ &\quad q_{N-1}(2k - 2^{N-1}i - \cdots - 4m - 2j) \psi_0(2^N t - 2k) \\ &= 2^{\frac{N}{2}} \sum_{i \in \mathbb{Z}} q_0(i) \cdots \sum_{m \in \mathbb{Z}} q_{N-3}(m) \sum_{k \in \mathbb{Z}} q_{N-2}(k) * \\ &\quad q_{N-1}(2k - 2^{N-1}i - \cdots - 4m) \psi_0(2^N t - 2k) \end{aligned} \quad (5.25)$$

Now let $2k = k$ in equation 5.24, rearrange the order of the summations, and consolidate the convolution term as follows:

$$\begin{aligned} \psi_f(t) &= 2^{\frac{N}{2}} \sum_{i \in \mathbb{Z}} q_0(i) \cdots \sum_{k \in \mathbb{Z}} q_{N-2}(2k) * \\ &\quad \left(\sum_{m \in \mathbb{Z}} q_{N-3}(m) q_{N-1}(4k - 2^{N-1}i - \cdots - 4m) \right) \psi_0(2^N t - 4k) \\ &= 2^{\frac{N}{2}} \sum_{i \in \mathbb{Z}} q_0(i) \cdots \sum_{k \in \mathbb{Z}} q_{N-2}(2k) * q_{N-3}(k) * \\ &\quad q_{N-1}(4k - 2^{N-1}i - \cdots) \psi_0(2^N t - 4k) \end{aligned} \quad (5.26)$$

Repeating the above procedure another 2^{N-3} times, and then letting $k = 2^{N-1}k$ yields:

$$\begin{aligned} \psi_f(t) &= 2^{\frac{N}{2}} \sum_{k \in \mathbb{Z}} q_0(k) * \cdots * q_{N-3}(2^{N-3}k) * q_{N-2}(2^{N-2}k) * q_{N-1}(2^{N-1}k) \psi_0(2^N t - 2^{N-1}k) \\ &= 2^{\frac{N}{2}} \sum_{k \in \mathbb{Z}} q_0\left(\frac{k}{2^{N-1}}\right) * \cdots * q_{N-3}\left(\frac{k}{4}\right) * q_{N-2}\left(\frac{k}{2}\right) * q_{N-1}(k) \psi_0(2^N t - k) \\ &= 2^{\frac{N}{2}} \sum_{k \in \mathbb{Z}} \rho_N(k) \psi_0(2^N t - k) \end{aligned} \quad (5.27)$$

where

$$\rho_N(k) := q_0\left(\frac{k}{2^{N-1}}\right) * \cdots * q_{N-3}\left(\frac{k}{4}\right) * q_{N-2}\left(\frac{k}{2}\right) * q_{N-1}(k) \quad (5.28)$$

Recall the following z-transform relation:

$$\mathcal{Z}^{-1}\{Q_k(z^M)\} = \begin{cases} q_k\left(\frac{n}{M}\right), & n = lM, l \in \mathbb{Z} \\ 0 & \text{otherwise} \end{cases} \quad (5.29)$$

with $\mathcal{Z}$ signifying the z-transform. An equivalent representation of equation 5.28 is given by:

$$\rho_N(k) := q_0\left(\frac{k}{2^{N-1}}\right) * \cdots * q_{N-2}\left(\frac{k}{2}\right) * q_{N-1}(k) = \mathcal{Z}^{-1}\left\{\prod_{n=0}^{N-1} Q_{N-1-n}(z^{2^n})\right\} \quad (5.30)$$

Equation 5.27 can be equivalently represented by:

$$\psi_f(t) = \eta_{N-1}\eta_{N-2} \cdots \eta_0 \psi_0(t) \quad (5.31)$$

with η_k described in Definition 5.3. Notice that equations 5.9 and 5.10 can be equivalently represented by equation 5.27. Also observe that performing a recursion on equation 5.13 gives equation 5.31.

Taking the Fourier transform of equations 5.9 and 5.10 allows for an equivalent representation of the wavelet packet equations as follows:

$$\Psi_{2f}(\omega) = \frac{1}{\sqrt{2}} \sum_{k \in \mathbb{Z}} h(k) e^{-jk\omega/2} \Psi_f(\omega/2) = \Theta_0(\omega/2) \Psi_f(\omega/2) \quad (5.32)$$

$$\Psi_{2f+1}(\omega) = \frac{1}{\sqrt{2}} \sum_{k \in \mathbb{Z}} g(k) e^{-jk\omega/2} \Psi_f(\omega/2) = \Theta_1(\omega/2) \Psi_f(\omega/2) \quad (5.33)$$

where $\Theta_0(\omega) = \frac{1}{\sqrt{2}} \sum_{k \in \mathbb{Z}} h(k) e^{-jk\omega}$ and $\Theta_1(\omega) = \frac{1}{\sqrt{2}} \sum_{k \in \mathbb{Z}} g(k) e^{-jk\omega}$. Iterating on the right hand side of equations 5.32 and 5.33 yields:

$$\Psi_{2f}(\omega) = \Theta_0(\omega/2) \prod_{k=0}^{\infty} \Theta_{f_k}(2^{-(k+2)}\omega) \quad (5.34)$$

$$\Psi_{2f+1}(\omega) = \Theta_1(\omega/2) \prod_{k=0}^{\infty} \Theta_{f_k}(2^{-(k+2)}\omega) \quad (5.35)$$

where $f = \{f_0, f_1, \dots, f_k, \dots : k \in \mathbb{Z}^+\}$ is the binary representation of the positive integer f and $\Psi_0(0) = 1$. Taking the Fourier transform of equation 5.23 leads to the representation:

$$\Psi_f(\omega) = \Theta_{f_0}\left(\frac{\omega}{2}\right) \cdots \Theta_{f_{N-2}}\left(\frac{\omega}{2^{N-1}}\right) \Theta_{f_{N-1}}\left(\frac{\omega}{2^N}\right) \Psi_0\left(\frac{\omega}{2^N}\right) \quad (5.36)$$

Taking the limit as $N \rightarrow \infty$ with $\Psi_0(0) = 1$ yields [37]:

$$\Psi_f(\omega) = \prod_{k=0}^{\infty} \Theta_{f_k}(2^{-(k+1)}\omega) \quad (5.37)$$

It should be noted that equation 5.37 was arrived at differently in [37], and was not derived from equation 5.23 as was done herein. The natural basis for these spaces is given by the following theorem:

Theorem 5.1 ([37])

For each f , $f \in \mathbb{Z}^+$, the collection $\{\psi_{f,p} : p \in \mathbb{Z}\}$ is a Riesz basis for W_f .

Theorem 5.2 ([37])

The collection $\{\psi_{f,p} : p \in \mathbb{Z}, f \in \mathbb{Z}^+\}$ is a Riesz basis for $\mathcal{H}$.

Recalling Definition 5.1, a wavelet packet basis function, at the scale $s \in \mathbb{Z}$, is defined by:

$$\psi_{f,p}^s(t) := 2^{s/2} \psi_f(2^s t - p) \quad (5.38)$$

The unit scale wavelet packet equations, 5.9, 5.10, 5.13, 5.31, and 5.27 can be generalized for the scale $s \in \mathbb{Z}$ as follows:

$$\psi_{2f,p}^s(t) = 2^{\frac{s+1}{2}} \sum_{k \in \mathbb{Z}} h(k) \psi_f(2^{s+1} t - 2p - k) := F_0 \psi_{f,p}^s(t) \in W_{2f}^s \quad (5.39)$$

$$\psi_{2f+1,p}^s(t) = 2^{\frac{s+1}{2}} \sum_{k \in \mathbb{Z}} g(k) \psi_f(2^{s+1} t - 2p - k) := F_1 \psi_{f,p}^s(t) \in W_{2f+1}^s \quad (5.40)$$

$$\psi_{f,p}^s(t) = \begin{cases} F_0 \psi_{\frac{f}{2},p}^s(t), & \text{if } f \text{ is even} \\ F_1 \psi_{\frac{f-1}{2},p}^s(t), & \text{if } f \text{ is odd} \end{cases} \quad (5.41)$$

$$\psi_{f,p}^s(t) = 2^{\frac{s+N}{2}} \sum_{k \in \mathbb{Z}} \rho_N(k) \psi_0(2^{s+N} t - 2^N p - k) \quad (5.42)$$

$$\psi_{f,p}^s(t) = \eta_{N-1} \eta_{N-2} \cdots \eta_0 \psi_{0,p}^s(t) \quad (5.43)$$

with $q_m(n)$, η_k , and N described in Definition 5.3 and $\rho_N(k)$ defined in equation 5.30.

Now, a general relationship between the wavelet packet subspaces, $W_{f,p}^s$, for an orthogonal MRA will be derived as was done in [35]. Starting with equations 5.39 and 5.40, apply the corresponding adjoint quadrature filter operators to both sides and sum yielding:

$$F_0^* \psi_{2f,p}^s(t) + F_1^* \psi_{2f+1,p}^s(t) = F_0^* F_0 \psi_{f,p}^s(t) + F_1^* F_1 \psi_{f,p}^s(t) \quad (5.44)$$

Recalling the self-duality property for orthogonal quadrature operators given in Definition 4.2, equation 5.44 becomes:

$$\psi_{f,p}^s(t) = F_0^* \psi_{2f,p}^s(t) + F_1^* \psi_{2f+1,p}^s(t) \quad (5.45)$$

Using equations 5.38, 4.8, and 4.9 in equation 5.45 and reducing gives:

$$\begin{aligned} \psi_f(2^s t - p) &= \frac{1}{\sqrt{2}} \sum_{k \in \mathbb{Z}} \bar{h}(k) \psi_{2f}(2^{s-1} t - p/2 + k/2) + \\ &\quad \frac{1}{\sqrt{2}} \sum_{k \in \mathbb{Z}} \bar{g}(k) \psi_{2f+1}(2^{s-1} t - p/2 + k/2) \end{aligned} \quad (5.46)$$

Letting $t = 2^{s-1} t$ and $2k = k - p$ in equation 5.46 yields:

$$\psi_f(2t - p) = \frac{1}{\sqrt{2}} \sum_{k \in \mathbb{Z}} \bar{h}(2k + p) \psi_{2f}(t + k) +$$

$$\frac{1}{\sqrt{2}} \sum_{k \in \mathbb{Z}} \bar{g}(2k+p) \psi_{2f+1}(t+k) \quad (5.47)$$

Examination of equation 5.47 in light of Theorem 5.1 leads to the following conclusions for any p :

$$\psi_f(2t-p) \in W_f^1 \quad (5.48)$$

$$\sum_{k \in \mathbb{Z}} \bar{h}(2k+p) \psi_{2f,-k}(t) \in W_{2f} \quad (5.49)$$

$$\sum_{k \in \mathbb{Z}} \bar{g}(2k+p) \psi_{2f+1,-k}(t) \in W_{2f+1} \quad (5.50)$$

Therefore, from equations 5.47, 5.48, 5.49, and 5.50, a relationship between the wavelet packet subspaces, W_f^s , for an orthogonal MRA, is given by:

$$W_f^1 = W_{2f}^0 \oplus W_{2f+1}^0 \quad (5.51)$$

where $\oplus$ denotes the direct sum of the inner product spaces X and Y . Equation 5.51 can be generalized as follows:

$$W_f^s = W_{2f}^{s-1} \oplus W_{2f+1}^{s-1} \quad (5.52)$$

Recursively using equation 5.52 leads to the following relations:

$$\begin{aligned} W_0^1 \ominus W_0^0 &= W_1^0 \\ W_0^2 \ominus W_0^1 &= W_1^1 = W_2^0 \oplus W_3^0 \\ W_0^3 \ominus W_0^2 &= W_1^2 = W_4^0 \oplus W_5^0 \oplus W_6^0 \oplus W_7^0 \\ W_0^4 \ominus W_0^3 &= W_1^3 = W_8^0 \oplus W_9^0 \oplus W_{10}^0 \oplus W_{11}^0 \oplus W_{12}^0 \oplus W_{13}^0 \oplus W_{14}^0 \oplus W_{15}^0 \\ &\vdots \\ W_0^s \ominus W_0^{s-1} &= W_1^{s-1} = W_{2^{s-1}}^0 \oplus W_{2^{s-1}+1}^0 \oplus \cdots \oplus W_{2^s-1}^0 \end{aligned} \quad (5.53)$$

where $X \ominus Y$ denotes the direct subtraction of the inner product spaces X and Y . Adding W_0^{s-1} to the righthand side of the last equation in 5.53, leads to the following generalization:

$$W_0^s = W_0^0 \oplus W_1^0 \oplus \cdots \oplus W_{2^{s-1}}^0 \oplus \cdots \oplus W_{2^s-1}^0 \quad (5.54)$$

Equation 5.54 can be generalized as follows:

$$W_f^s = W_{2^s f}^0 \oplus W_{2^s f+1}^0 \oplus \cdots \oplus W_{2^s(f+1)-1}^0 \quad (5.55)$$

It should be noted that the scaling function spaces, V_m , and the wavelet function spaces, W_m , discussed in chapter 3, are represented using the wavelet packet notation of this chapter as follows:

$$W_0^m := V_m \quad (5.56)$$

$$W_1^m := W_m \quad (5.57)$$

Figure 5.2 provides an example of the relationships between the wavelet packet subspaces given by equations 5.52 and 5.55, along with demonstrating the wavelet basis, which contains the scaling function and wavelet function spaces as defined by equations 5.56 and 5.57. Figure 5.2 also provides an example of possible orthogonal bases for an orthonormal wavelet packet representation of a particular signal, along with giving three orthogonal bases: (i) the wavelet basis, (ii) a level basis, and (iii) an arbitrary orthogonal basis, for a given signal, $x(t)$ at the scale, $s = 3$.

The next theorem generalizes Theorem 5.2 and demonstrates that wavelet packets at multiple scales form a complete basis for $\mathcal{L}^2(\mathbb{R})$.

Theorem 5.3 ([37])

If, except for a denumerable set, $\mathcal{I}$ is a disjoint dyadic cover of $\mathbb{R}^+$ made up of the intervals $I_f^s := [2^s f, 2^s(f+1))$, then the corresponding wavelet packets $\{\psi_{f,p}^s : I_f^s \in \mathcal{I}, p \in \mathbb{Z}\}$ form a basis for $\mathcal{L}^2(\mathbb{R})$.

Notice that there is a direct correspondence between the dyadic subintervals, I_f^s , and the wavelet packet subspaces, W_f^s .

The last part of this chapter will involve deriving the relationships necessary for numerically calculating the wavelet packet coefficients. Let $\{w_f^s(p) : p \in \mathbb{Z}\}$ represent the sequence of inner products of a function $x(t) \in \mathcal{L}^2(\mathbb{R})$ with the reflected wavelet packet functions, $\check{\psi}_{f,p}^s = 2^{s/2}\psi_f(p - 2^s t) \in W_f^s$:

$$w_f^s(p) := \langle x(t), \check{\psi}_{f,p}^s(t) \rangle = \int_{\mathbb{R}} \bar{x}(t) 2^{s/2} \psi_f(p - 2^s t) dt \quad (5.58)$$

The following lemma defines the recursive relations for the packet coefficients:

Lemma 5.1 ([30])

The wavelet packet coefficient sequences $\{w_f^s(p)\}$ satisfy the following recursion relations:

$$w_{2f}^{s-1}(p) = F_0 w_f^s(p) \quad (5.59)$$

$$w_{2f+1}^{s-1}(p) = F_1 w_f^s(p) \quad (5.60)$$

Proof:

$$w_{2f}^{s-1}(p) = \int_{\mathbb{R}} \bar{x}(t) 2^{s-1/2} \check{\psi}_{2f}^{s-1}(p - 2^{s-1} t) dt \quad (5.61)$$

Using equation 5.9 in equation 5.61 gives:

$$w_{2f}^{s-1}(p) = \int_{\mathbb{R}} \bar{x}(t) 2^{\frac{s-1}{2}} [\sqrt{2} \sum_{k \in \mathbb{Z}} h(k) \psi_f(2p - k - 2^s t)] dt \quad (5.62)$$

Switching the order of integration and summation and using equation 5.58 yields:

$$\begin{aligned} w_{2f}^{s-1}(p) &= \sum_{k \in \mathbb{Z}} h(k) \int_{\mathbb{R}} \bar{x}(t) 2^{s/2} \psi_f(2p - k - 2^s t) dt \\ &= \sum_{k \in \mathbb{Z}} h(k) w_f^s(2p - k) := F_0 w_f^s(p) \end{aligned}$$

Equation 5.60 follows similarly. ■

Remark 5.1 The most important realization to be made from lemma 5.1 is that the wavelet packet coefficient sequences can be generated using the same quadrature filter operators used for determining the wavelet packet basis functions.

Remark 5.2 Equations 5.59 and 5.60 define the relationship for the wavelet packet analysis bank coefficients, for an orthogonal MRA. The relationship for the wavelet packet synthesis bank coefficients for an orthogonal MRA can be found by applying the corresponding adjoint quadrature filter operators to both sides of equations 5.59 and 5.60 and summing to give:

$$w_f^s(p) = F_0^* w_{2f}^{s-1}(p) + F_1^* w_{2f+1}^{s-1}(p) \quad (5.63)$$

Figure 5.2: Some possible orthogonal bases for a signal, $x(t)$ at the scale $s = 3$, analyzed using wavelet packets: (i) the wavelet basis, (ii) a level basis, (iii) an arbitrary basis.

CHAPTER 6

WAVELET MODELING OF SYSTEMS

This chapter discusses the modeling of single-input single-output (SISO) plants using compactly supported, orthonormal wavelet packets at multiple scales and introduces the notion of a “best” basis for a given signal, $x \in \mathcal{H}$. Modeling of systems from experimental data is the primary advantage of employing orthonormal wavelet packets to model impulse response data of the system to be controlled.

Modeling of a system using orthonormal wavelet packets will be achieved by modeling the impulse response data of the system as follows:

$$p(t) = \sum_{k=0}^{\infty} \beta_k \psi_{f_k, p_k}^{s_k}(t) \quad (6.1)$$

where $\psi_{f_k, p_k}^{s_k}(t) \in L^2(0, \infty) \cap L^1(0, \infty)$ is an orthonormal set of wavelet packet basis functions. Selecting a wavelet packet basis to give an “optimal” representation for the impulse response data is very system specific as well as being dependent on the control objectives. The control designer would like to be able to obtain a best basis for a given system, or possibly a best basis for a class of systems and their subsystems.

The first step is to select a particular basis to be used, e.g., the wavelet basis, or to select an information cost function to measure the decorrelation between packets and then utilize a basis selection algorithm. Example information cost functions commonly used in measuring the decorrelation between wavelet packets are given by the following:

1. Entropy cost function: $\sum_{k=1}^{\infty} p(k) \log \frac{1}{p(k)}$
2. l^2 cost function: $(\sum_{k=1}^{\infty} p^2(k))^{1/2}$

Example basis selection algorithms commonly employed are the following:

1. Best basis selection algorithm [36]
2. Best level basis selection algorithm [36].

It should be noted that the wavelet basis is directly determined based on the maximum desired scale level. The entropy cost function and the l^2 cost function are only two methods, out of many possible methods, used to measure the decorrelation. The primary objective of the best basis selection algorithm is to produce a signal representation which has the most decorrelation. There are also a number of adaptive techniques which can be utilized in the selection of the best basis for a given signal.

For the controller designs presented in the sequel, the basis elements selected to represent the given system components must be derived from the same mother wavelet. In other words, the different system components can be composed of different wavelet packet basis elements, but the wavelet packet basis elements must all have been derived from the same mother wavelet. Thus, the basis selection procedures employed herein select the “best” orthonormal wavelet packet basis out of all of the possible wavelet packet subspaces generated from a particular orthonormal mother wavelet. The “best” basis may be a best level basis determined by considering the bases for each scale level of a given system.

The following example serves the purpose of illustrating a wavelet representation for a system, but is by no means all inclusive of the type of plants that can be represented using wavelet packets. The example system to be represented using orthonormal wavelet packets is that of a SISO flexible structure. It should be noted that orthonormal wavelet packets can be used to represent both linear and nonlinear plants. A general SISO flexible structure plant can be represented as:

$$P(s) = \sum_{k=0}^{\infty} \frac{g_k}{s^2 + 2\zeta_k \omega_k s + \omega_k^2} \quad (6.2)$$

where g_k is a gain term. Assume that any rigid body modes have been stabilized by an inner loop. Then $P(s) \in H^2$. Due to the linearity of the Fourier Transform, and the fact that the Fourier Transform is an isomorphism between $L^2[0, \infty)$ and H^2 , the time domain representation of a flexible structure can be modeled by using an orthonormal wavelet packet representation given by equation 6.1.

Figures 6.1 - 6.4 present an example of a wavelet packet analysis and synthesis on the SISO flexible structure discussed above containing two modes at $\omega_1 = 2\pi$ and $\omega_2 = 6\pi$ with the identical damping factor of $\zeta = 0.01$. Figure 6.1 provides the impulse response of the structure and the corresponding fast Fourier transform (FFT) frequency domain magnitude response. Figure 6.2 expresses a decomposition of the impulse response of the system into wavelet packets using Haar wavelet packets. Figure 6.3 provides an example of three possible orthogonal bases: (i) an arbitrary basis, (ii) a level basis, and (iii) the wavelet basis. The arbitrary basis in figure 6.3 is labelled the best basis since it minimizes a particular information cost function, which for this case was the entropy cost function, relative to all of the possible wavelet packet bases. Similarly, the level basis

in figure 6.3 is labelled the best level basis since it minimizes the same selected information cost function relative to all the possible level wavelet packet bases. The wavelet basis is only a function of depth, or equivalently scale, and, for a given depth, is always the same. It should be noted that the wavelet basis is not determined by minimizing a particular information cost function. Figure 6.4 gives the wavelet packet synthesis result, which is the reconstruction of the impulse response for the flexible structure containing two modes, based on the wavelet packet best basis given in figure 6.3. Similar synthesis results were achieved for the best level basis and the wavelet basis shown in figure 6.3 and therefore are not included. The synthesis results were identical since no compression was performed on the selected wavelet packet coefficients.

Figure 6.1: Impulse and frequency response for a flexible structure with two modes

Figure 6.2: Wavelet packet decomposition for a flexible structure with two modes

Figure 6.3: Best basis, best level basis, and wavelet basis selection for a flexible structure with two modes

Figure 6.4: Reconstruction of the impulse response for a flexible structure with two modes

CHAPTER 7

ORTHONORMAL WAVELET PACKETS

This chapter develops some of the necessary mathematical tools in order to utilize wavelet packet theory in control theory. New theoretical results for compactly supported, orthonormal wavelet packets at the scale s with dilation factor 2 are presented. An orthonormal wavelet packet refers to a wavelet packet whose basis functions are normalized and whose dilation equation coefficients are orthogonal. It is to be assumed throughout this chapter, and the remaining chapters, that the equation, $\psi_{f,p}^s(\bullet)$, refers to a compactly supported, orthonormal wavelet packet basis function at the scale s with dilation factor 2 which is either continuous or discrete. A wavelet packet inner product theorem is presented for continuous-time orthonormal wavelet packets. Haar wavelet packets are shown analytically to be closed under multiplication. In addition, new results for discrete Haar wavelet packets are presented. First, a representation theorem for orthonormal wavelet packets is developed. Then a formula for the inner product between any two orthonormal wavelet packet basis functions is presented. Continuous-time Haar wavelet packets are presented, along with product theorem between two Haar wavelet packets. Lastly, the results of this chapter are extended to discrete-time Haar wavelet packets. These results include demonstrating that the continuous-time inner product and the discrete-time inner product for Haar wavelet packets are identical.

7.1 Representation Of Orthonormal Wavelet Packets

This section develops an explicit relationship between compactly supported, orthonormal wavelet packets with dilation factor 2 at different scales and different frequencies. In other words, any compactly supported, orthonormal wavelet packet basis function, $\psi_{f,p}^s(t)$, at the scale s , can be represented by a summation of wavelet packet basis functions at a finer scale, $s + \alpha$, $\alpha \in \mathbb{Z}^+$. The next theorem presents this explicit relationship for orthonormal wavelet packets. This theorem is exploited in the proofs of several key theorems to be presented in this chapter and the following chapter, chapter 8.

Theorem 7.1 (Orthonormal Wavelet Packet Representation Theorem)

Let $\psi_{f,p}^s(t)$ be a compactly supported, orthonormal wavelet packet basis function with dilation factor 2, whose dilation equation coefficients, h and g , correspond to causal, orthogonal, FIR filters of length Γ . Represent the frequency of the wavelet packet basis function, $f \in \mathbb{Z}^+$, by the infinite binary expansion, $\{f_n : n \in \mathbb{Z}^+\}$. Then, for any $\alpha \in \mathbb{Z}^+$, the wavelet packet basis function, $\psi_{f,p}^s(t)$, can be represented by the following relationship:

$$\psi_{f,p}^s(t) = 2^{\frac{s+\alpha}{2}} \sum_{k=0}^{(2^\alpha-1)(\Gamma-1)} \tilde{m}_\alpha(k) \psi_{\tilde{f}_\alpha}(2^{s+\alpha}t - 2^\alpha p - k) \quad (7.1)$$

where: $\tilde{f}_\alpha = \begin{cases} \frac{\tilde{f}_{\alpha-1}}{2}, & \text{if } f_{\alpha-1} = 0 \\ \frac{\tilde{f}_{\alpha-1}-1}{2}, & \text{if } f_{\alpha-1} = 1 \end{cases}$ with $\tilde{f}_0 = f$;

$$\tilde{m}_\alpha(k) := \begin{cases} q_0(\frac{k}{2^{\alpha-1}}) * \dots * q_{\alpha-1}(k) & \text{if } \alpha > 0 \\ \delta_{k,0} & \text{if } \alpha = 0 \end{cases}$$

$$:= \mathcal{Z}^{-1}\{\tilde{Q}_\alpha(z)\} \text{ for } k = 0, \dots, (2^\alpha - 1)(\Gamma - 1);$$

$$q_n(k) = \begin{cases} h(k), & \text{if } f_n = 0 \\ g(k), & \text{if } f_n = 1 \end{cases};$$

$$\tilde{Q}_\alpha(z) = \begin{cases} \prod_{n=0}^{\alpha-1} Q_{\alpha-1-n}(z^{2^n}), & \text{if } \alpha > 0 \\ 1, & \text{if } \alpha = 0 \end{cases} = \sum_{k=0}^{(2^\alpha-1)(\Gamma-1)} \tilde{m}_\alpha(k) z^{-k};$$

$$Q_n = \begin{cases} H, & \text{if } f_n = 0 \\ G, & \text{if } f_n = 1 \end{cases};$$

$\mathcal{Z}^{-1}$ represents the inverse z -transform.

Proof: Define two cases. For Case 1, let $\alpha = 0$. Equation 7.1 reduces simply to equation 5.1 of Definition 5.1. For Case 2, let $\alpha > 0$. Now perform induction on α , for any given f, p, s , and Γ .

For $\alpha = 1$,

$$\psi_{f,p}^s(t) = 2^{\frac{s+1}{2}} \sum_{k=0}^{\Gamma-1} \tilde{m}_1(k) \psi_{\tilde{f}_1}(2^{s+1}t - 2p - k) \quad (7.2)$$

with

$$\tilde{f}_1 = \begin{cases} \frac{\tilde{f}_0}{2} = \frac{f}{2}, & \text{if } f_0 = 0 \\ \frac{\tilde{f}_0-1}{2} = \frac{f-1}{2}, & \text{if } f_0 = 1 \end{cases} \quad (7.3)$$

and

$$\begin{aligned} \{\tilde{m}_1(k) : k = 0, \dots, \Gamma - 1\} &= q_0(k) = \mathcal{Z}^{-1}\{\tilde{Q}_1(z)\} \\ &= \mathcal{Z}^{-1}\left\{ \begin{matrix} H, & \text{if } f_0 = 0 \\ G, & \text{if } f_0 = 1 \end{matrix} \right\} = \begin{cases} h(k), & \text{if } f_0 = 0 \\ g(k), & \text{if } f_0 = 1 \end{cases} \end{aligned} \quad (7.4)$$

$$\begin{aligned}
\psi_{f,p}^s(t) &= \begin{cases} 2^{\frac{s+1}{2}} \sum_{k=0}^{\Gamma-1} h(k) \psi_{\frac{t}{2}}(2^{s+1}t - 2p - k), & \text{if } f_0 = 0 \\ 2^{\frac{s+1}{2}} \sum_{k=0}^{\Gamma-1} g(k) \psi_{\frac{t-1}{2}}(2^{s+1}t - 2p - k), & \text{if } f_0 = 1 \end{cases} \\
&= \begin{cases} F_0 \psi_{\frac{t}{2},p}^s(t), & \text{if } f \text{ is even} \\ F_1 \psi_{\frac{t-1}{2},p}^s(t), & \text{if } f \text{ is odd} \end{cases}
\end{aligned} \tag{7.5}$$

Assume equation 7.1 holds for $\alpha = N$, which implies that the following relation holds:

$$\psi_{f,p}^s(t) = 2^{\frac{s+N}{2}} \sum_{k=0}^{(2^N-1)(\Gamma-1)} \tilde{m}_N(k) \psi_{\bar{f}_N}(2^{s+N}t - 2^N p - k) \tag{7.6}$$

with

$$\bar{f}_N = \begin{cases} \frac{\bar{f}_{N-1}}{2}, & \text{if } f_{N-1} = 0 \\ \frac{\bar{f}_{N-1}-1}{2}, & \text{if } f_{N-1} = 1 \end{cases} \text{ with } \bar{f}_0 = f \tag{7.7}$$

and

$$\begin{aligned}
\{\tilde{m}_N(k) : k = 0, \dots, (2^N-1)(\Gamma-1)\} &= q_0\left(\frac{k}{2^{N-1}}\right) * \dots * q_{N-2}\left(\frac{k}{2}\right) * q_{N-1}(k) \\
&= \mathcal{Z}^{-1} \left\{ \tilde{Q}_N(z) \right\} = \mathcal{Z}^{-1} \left\{ Q_{N-1}(z) Q_{N-2}(z^2) \dots Q_0(z^{2^{N-1}}) \right\}
\end{aligned} \tag{7.8}$$

Represent $\psi_{\bar{f}_N}(2^{s+N}t - 2^N p - k)$ of equation 7.6, using the wavelet packet dilation equation 5.41, as follows:

$$\begin{aligned}
\psi_{\bar{f}_N}(2^{s+N}t - 2^N p - k) &= \begin{cases} \sqrt{2} \sum_{l=0}^{\Gamma-1} h(l) \psi_{\frac{\bar{f}_N}{2}}(2^{s+N+1}t - 2^{N+1}p - 2k - l), & \text{if } \bar{f}_N \text{ is even} \\ \sqrt{2} \sum_{l=0}^{\Gamma-1} g(l) \psi_{\frac{\bar{f}_N-1}{2}}(2^{s+N+1}t - 2^{N+1}p - 2k - l), & \text{if } \bar{f}_N \text{ is odd} \end{cases} \\
&= \sqrt{2} \sum_{l=0}^{\Gamma-1} q_N(l) \psi_{\bar{f}_{N+1}}(2^{s+N+1}t - 2^{N+1}p - 2k - l)
\end{aligned} \tag{7.9}$$

with

$$\bar{f}_{N+1} = \begin{cases} \frac{\bar{f}_N}{2}, & \text{if } \bar{f}_N \text{ is even} \\ \frac{\bar{f}_N-1}{2}, & \text{if } \bar{f}_N \text{ is odd} \end{cases} \text{ with } \bar{f}_0 = f \tag{7.10}$$

and

$$q_N(k) = \begin{cases} h(k), & \text{if } \bar{f}_N \text{ is even} \\ g(k), & \text{if } \bar{f}_N \text{ is odd} \end{cases} \tag{7.11}$$

Then, equation 7.6 becomes:

$$\psi_{f,p}^s(t) = 2^{\frac{s+N+1}{2}} \sum_{k=0}^{(2^N-1)(\Gamma-1)} \tilde{m}_N(k) \sum_{l=0}^{\Gamma-1} q_N(l) \psi_{\bar{f}_{N+1}}(2^{s+N+1}t - 2^{N+1}p - 2k - l) \tag{7.12}$$

Letting $l = l + 2k$ in the second sum on the right hand side of equation 7.12 and rearranging yields:

$$\begin{aligned}
\psi_{f,p}^s(t) &= 2^{\frac{s+N+1}{2}} \sum_{l=0}^{(2^{N+1}-1)(\Gamma-1)} \left[\sum_{k=0}^{(2^N-1)(\Gamma-1)} \tilde{m}_N(k) q_N(l - 2k) \right] \\
&\quad \psi_{\bar{f}_{N+1}}(2^{s+N+1}t - 2^{N+1}p - l)
\end{aligned} \tag{7.13}$$

Now let $2l = l$ in equation 7.13, consolidate the convolution term, and then let $l = 2l$ as follows:

$$\begin{aligned}
\psi_{f,p}^s(t) &= 2^{\frac{s+N+1}{2}} \sum_{l \in \mathbb{Z}} \left[\sum_{k=0}^{(2^N-1)(\Gamma-1)} \check{m}_N(k) q_N(2l-2k) \right] \psi_{\tilde{f}_{N+1}}(2^{s+N+1}t - 2^{N+1}p - 2l) \\
&= 2^{\frac{s+N+1}{2}} \sum_{l \in \mathbb{Z}} \check{m}_N(l) * q_N(2l) \psi_{\tilde{f}_{N+1}}(2^{s+N+1}t - 2^{N+1}p - 2l) \\
&= 2^{\frac{s+N+1}{2}} \sum_{l \in \mathbb{Z}} \check{m}_N\left(\frac{l}{2}\right) * q_N(l) \psi_{\tilde{f}_{N+1}}(2^{s+N+1}t - 2^{N+1}p - l) \\
&= 2^{\frac{s+N+1}{2}} \sum_{l=0}^{(2^{N+1}-1)(\Gamma-1)} \check{m}_{N+1}(l) \psi_{\tilde{f}_{N+1}}(2^{s+N+1}t - 2^{N+1}p - l)
\end{aligned} \tag{7.14}$$

with

$$\{\check{m}_{N+1}(l) : l = 0, \dots, (2^{N+1}-1)(\Gamma-1)\} = q_0\left(\frac{l}{2^N}\right) * \dots * q_{N-1}\left(\frac{l}{2}\right) * q_N(l) \tag{7.15}$$

An alternative derivation of equation 7.14 starts by observing the following:

$$\begin{aligned}
\tilde{Q}_\alpha(z) &= \prod_{n=0}^{\alpha-1} Q_{\alpha-1-n}(z^{2^n}) = \tilde{Q}_{\alpha-1}(z^2) Q_{\alpha-1}(z) \\
&= \sum_{k=0}^{(2^{\alpha-1}-1)(\Gamma-1)} \check{m}_{\alpha-1}(k) \sum_{l=0}^{\Gamma-1} q_{\alpha-1}(l) z^{-l-2k}
\end{aligned} \tag{7.16}$$

with

$$q_j(k) = \begin{cases} h(k), & \text{if } f_{j-1} = 0 \\ g(k), & \text{if } f_{j-1} = 1 \end{cases} \tag{7.17}$$

Letting $l = l + 2k$ in the last right hand expression of equation 7.16 and rearranging gives:

$$\begin{aligned}
\tilde{Q}_\alpha(z) &= \sum_{l=0}^{(2^\alpha-1)(\Gamma-1)} \left[\sum_{k=0}^{(2^{\alpha-1}-1)(\Gamma-1)} \check{m}_{\alpha-1}(k) q_{\alpha-1}(l-2k) \right] z^{-l} \\
&= \sum_{l=0}^{(2^\alpha-1)(\Gamma-1)} \check{m}_\alpha(l) z^{-l}
\end{aligned} \tag{7.18}$$

Therefore,

$$\check{m}_\alpha(l) = \sum_{k=0}^{(2^{\alpha-1}-1)(\Gamma-1)} m_{\alpha-1}(k) q_{\alpha-1}(l-2k) \tag{7.19}$$

Using equation 7.19 in equation 7.13 results in equation 7.14 and equation 7.15 is equivalently represented as follows:

$$\begin{aligned}
\{\check{m}_{N+1}(l) : l = 0, \dots, (2^{N+1}-1)(\Gamma-1)\} &= q_0\left(\frac{l}{2^N}\right) * \dots * q_{N-1}\left(\frac{l}{2}\right) * q_N(l) \\
&= \mathcal{Z}^{-1} \left\{ \tilde{Q}_{N+1}(z) \right\} = \mathcal{Z}^{-1} \left\{ \prod_{n=0}^N Q_{N-n}(z^{2^n}) \right\}
\end{aligned} \tag{7.20}$$

Equations 7.14, 7.10, and 7.20 define the relations for $\alpha = N + 1$. ■

Remark 7.1 An equivalent form of Theorem 7.1 can be determined by defining $\bar{\alpha} := s + \alpha$ and letting $s\Delta = \alpha$ resulting in:

$$\psi_{f,p}^s(t) = 2^{\frac{\bar{\alpha}}{2}} \sum_{k=0}^{(2^{s\Delta}-1)(\Gamma-1)} \tilde{m}_{s\Delta}(k) \psi_{\bar{f},\Delta}(2^{\bar{\alpha}}t - 2^{s\Delta}p - k) \quad (7.21)$$

Remark 7.2 The equivalent form of Theorem 7.1, equation 7.21, demonstrates that every compactly supported, orthonormal wavelet packet with dilation factor 2 at any scale s , frequency f , or position p , $\psi_{f,p}^s(t)$, can be represented as a sum of the original, possibly dilated, scaling function, $\psi_{\bar{f},\Delta}(t) = \psi_0(2^{\bar{\alpha}}t) = \phi(2^{\bar{\alpha}}t)$ with $\bar{\alpha}$ determined as follows:

$$\bar{\alpha} \geq s + [\log_2(f + 1)] \quad (7.22)$$

where $[x] = n$ with n denoting the greatest integer satisfying the relationship $(n - 1) < x \leq n$.

Now it will be important to define explicitly the support interval for a compactly supported, orthonormal wavelet packet basis function generated using causal, orthogonal, FIR filter sequences of even length $\Gamma \geq 2$. The support of $\psi_{f,p}^s(t)$ is given by:

$$Supp\{\psi_{f,p}^s(t)\} = [2^{-s}p, 2^{-s}(p + \Gamma - 1)] \quad (7.23)$$

7.2 Orthonormal Wavelet Packet Inner Products

This section develops an explicit formula for the calculation of the inner products between two orthonormal wavelet packets. It should be emphasized that orthonormal wavelet packet basis functions at different scales are not necessarily orthogonal! The following lemma states the orthonormality condition for two unit scale, $s = 0$, normalized, wavelet packet basis functions.

Lemma 7.1 ([30])

Given two orthonormal wavelet packet basis functions $\psi_{f1,p1}(t)$ and $\psi_{f2,p2}(t)$, their inner product is given by the following:

$$\langle \psi_{f1}(t - p1), \psi_{f2}(t - p2) \rangle = \delta_{f1,f2} \delta_{p1,p2} \quad (7.24)$$

where $\delta_{x1,x2} = \begin{cases} 1, & \text{if } x1 = x2 \\ 0, & \text{otherwise} \end{cases}$, which is the Dirac delta function.

The next theorem presents an explicit formula for the inner product of any two compactly supported, orthonormal wavelet packet basis functions at possibly different scales with dilation factor 2.

Theorem 7.2 (Wavelet Packet Inner Product Theorem)

Let $\psi_{f_1, p_1}^{s_1}(t)$ and $\psi_{f_2, p_2}^{s_2}(t)$ be two orthonormal wavelet packet basis functions at the scales s_1 and s_2 respectively. The inner product of these two orthonormal wavelet packet basis functions is given explicitly by the following:

$$\langle \psi_{f_1, p_1}^{s_1}(t), \psi_{f_2, p_2}^{s_2}(t) \rangle = \sum_{k \in \mathbb{Z}} \check{m}_{s\Delta_1}(k - 2^{s\Delta_1}p_1) \check{m}_{s\Delta_2}(k - 2^{s\Delta_2}p_2) \quad (7.25)$$

$$\text{where: } \check{m}_{s\Delta_i}(k) := \begin{cases} q_0(\frac{k}{2^{s\Delta_i-1}}) * \dots * q_{s\Delta_i-1}(k) & \text{if } s\Delta_i > 0 \\ \delta_{k,0} & \text{if } s\Delta_i = 0 \end{cases}, \text{ as given in Theorem 7.1;}$$

$$s\Delta_i := \bar{\alpha} - s_i, \forall i = 1, 2;$$

$$\bar{\alpha} := \max(s_i + \lceil \log_2(f_i + 1) \rceil, \forall i = 1, 2);$$

$$q_n(k) = \begin{cases} h(k), & \text{if } f_{i_n} = 0 \\ g(k), & \text{if } f_{i_n} = 1 \end{cases};$$

$\{f_{i_n} : n \in \mathbb{Z}^+\}$ is the infinite binary expansion of the frequency, f_i , for $\psi_{f_i, p_i}^{s_i}(t)$.

Proof: The first step is to expand each orthonormal wavelet packet basis function, using the equivalent form of the orthonormal wavelet packet representation theorem, equation 7.21, presented in remark 7.1, as follows:

$$\psi_{f_i, p_i}^{s_i}(t) := 2^{\frac{\bar{\alpha}}{2}} \sum_{k=0}^{(2^{s\Delta_i}-1)} \check{m}_{s\Delta_i}(k) \psi_0(2^{\bar{\alpha}}t - 2^{s\Delta_i}p_i - k) \quad (7.26)$$

Recall remark 7.2, which states that every compactly supported, orthonormal wavelet packet basis function with dilation factor 2 at any scale s , frequency f , or position p , can be represented as a sum of the original scaling function, $\psi_{\bar{f}_a}(t) = \psi_0(2^{\bar{\alpha}}t)$ with $\bar{\alpha}$ determined by using equation 7.22. In light of equation 7.22, define $\bar{\alpha} := \max(s_i + \lceil \log_2(f_i + 1) \rceil, \forall i = 1, 2)$. Observe that it is necessary to define $\bar{\alpha}$ in this manner in order to ensure that all resultant original scaling functions, $\psi_0(2^{\bar{\alpha}}t)$, will be at the same scale. Also, define $s\Delta_i := \bar{\alpha} - s_i, \forall i = 1, 2$. After using equation 7.26 to expand each orthonormal wavelet packet basis function, $\psi_{f_1, p_1}^{s_1}(t)$ and $\psi_{f_2, p_2}^{s_2}(t)$, let $j = j + 2^{s\Delta_1}p_1$ and $k = k + 2^{s\Delta_2}p_2$, and then apply the Riesz basis property for the original scaling function, equation 3.15, to yield:

$$\begin{aligned} \langle \psi_{f_1, p_1}^{s_1}(t), \psi_{f_2, p_2}^{s_2}(t) \rangle &= 2^{\bar{\alpha}} \sum_{j \in \mathbb{Z}} \sum_{k \in \mathbb{Z}} \check{m}_{s\Delta_1}(j) \check{m}_{s\Delta_2}(k) \langle \psi_0(2^{\bar{\alpha}}t - 2^{s\Delta_1}p_1 - j), \psi_0(2^{\bar{\alpha}}t - 2^{s\Delta_2}p_2 - k) \rangle \\ &= \sum_{j \in \mathbb{Z}} \sum_{k \in \mathbb{Z}} \check{m}_{s\Delta_1}(j - 2^{s\Delta_1}p_1) \check{m}_{s\Delta_2}(k - 2^{s\Delta_2}p_2) \langle \psi_0(t - j), \psi_0(t - k) \rangle \\ &= \sum_{k \in \mathbb{Z}} \check{m}_{s\Delta_1}(k - 2^{s\Delta_1}p_1) \check{m}_{s\Delta_2}(k - 2^{s\Delta_2}p_2) \quad \blacksquare \end{aligned}$$

Remark 7.3 If $s_1 + \lceil \log_2(f_1 + 1) \rceil \neq s_2 + \lceil \log_2(f_2 + 1) \rceil$ then $\langle \psi_{f_1, p_1}^{s_1}(t), \psi_{f_2, p_2}^{s_2}(t) \rangle = 0$. Observation of figures 7.1 and 7.2 presented in section 7.3 illustrate this point.

The following wavelet packet inner product theorem is an alternative to theorem 7.2.

Theorem 7.3 (Alternate Wavelet Packet Inner Product Theorem)

Given two orthonormal wavelet packet basis functions $\psi_{f_1, p_1}^{s_1}(t)$ and $\psi_{f_2, p_2}^{s_2}(t)$ at the scales s_1 and s_2 respectively, assume, without loss of generality, that $s_1 \geq s_2$. Represent the frequency of the second wavelet packet basis function, $f_2 \in \mathbb{Z}^+$, by the infinite binary expansion, $\{f_{2_n} : n \in \mathbb{Z}^+\}$. Define the scale difference between the two orthonormal wavelet packet basis functions as $s\Delta := s_1 - s_2$. Define the position difference as $k\Delta := p_1 - 2^{s\Delta}p_2$. Define the position set $\mathcal{K} := \{0, \dots, (2^{s\Delta} - 1)(\Gamma - 1)\}$. The inner product of these two orthonormal wavelet packet basis functions is given explicitly by the following:

$$\langle \psi_{f_1, p_1}^{s_1}(t), \psi_{f_2, p_2}^{s_2}(t) \rangle = \begin{cases} \delta_{f_1, f_2} \delta_{p_1, p_2}, & \text{if } s\Delta = 0 \\ \delta_{f_1, \tilde{f}_{2, \Delta}} \max(\tilde{m}_{s\Delta}(k\Delta) \delta_{k\Delta, k} \forall k \in \mathcal{K}), & \text{if } s\Delta > 0 \end{cases} \quad (7.27)$$

$$\text{where: } \tilde{f}_{2, \Delta} = \begin{cases} \frac{\tilde{f}_{2, \Delta-1}}{2}, & \text{if } f_{2, \Delta-1} = 0 \\ \frac{\tilde{f}_{2, \Delta-1}-1}{2}, & \text{if } f_{2, \Delta-1} = 1 \end{cases} \text{ with } \tilde{f}_{2, 0} = f_2;$$

$$\tilde{m}_{s\Delta}(k) := \begin{cases} q_0(\frac{k}{2^{s\Delta}-1}) * \dots * q_{s\Delta-1}(k) & \text{if } s\Delta > 0 \\ \delta_{k, 0} & \text{if } s\Delta = 0 \end{cases}, \text{ as given in Theorem 7.1.}$$

Proof: Define two cases. For Case 1, let $s\Delta = 0$, i.e., $s_1 = s_2$.

$$\begin{aligned} \langle \psi_{f_1, p_1}^{s_1}(t), \psi_{f_2, p_2}^{s_1}(t) \rangle &= 2^{s_1} \int_{\mathbb{R}} \psi_{f_1}(2^{s_1}t - p_1) \psi_{f_2}(2^{s_1}t - p_2) dt \\ &= \int_{\mathbb{R}} \psi_{f_1}(t - p_1) \psi_{f_2}(t - p_2) dt \end{aligned} \quad (7.28)$$

which by Lemma 7.1 yields:

$$\langle \psi_{f_1, p_1}^{s_1}(t), \psi_{f_2, p_2}^{s_1}(t) \rangle = \delta_{f_1, f_2} \delta_{p_1, p_2}, \quad \text{if } s\Delta = 0 \quad (7.29)$$

For Case 2, let $s\Delta > 0$, i.e., $s_1 > s_2$. Use theorem 7.1 to represent the second wavelet packet in the inner product as follows:

$$\begin{aligned} \langle \psi_{f_1, p_1}^{s_1}(t), \psi_{f_2, p_2}^{s_2}(t) \rangle &= 2^{\frac{s_1+s_2+s\Delta}{2}} \int_{\mathbb{R}} \psi_{f_1}(2^{s_1}t - p_1) \sum_{k=0}^{(2^{s\Delta}-1)(\Gamma-1)} \tilde{m}_{s\Delta}(k) \\ &\quad \psi_{\tilde{f}_{2, \Delta}}(2^{s_2+s\Delta}t - 2^{s\Delta}p_2 - k) dt \\ &= \sum_{k=0}^{(2^{s\Delta}-1)(\Gamma-1)} \tilde{m}_{s\Delta}(k) \\ &\quad \int_{\mathbb{R}} \psi_{f_1}(t - p_1) \psi_{\tilde{f}_{2, \Delta}}(t - 2^{s\Delta}p_2 - k) dt \end{aligned} \quad (7.30)$$

which by Lemma 7.1 yields the following for $s\Delta > 0$ with $k = 0, \dots, (2^{s\Delta} - 1)(\Gamma - 1)$:

$$\langle \psi_{f1,p1}^{s1}(t), \psi_{f2,p2}^{s2}(t) \rangle = \delta_{f1,\bar{f}2,\Delta} \max(\tilde{m}_{s\Delta}(k) \delta_{k\Delta,k}) \quad (7.31)$$

where $\tilde{m}_{s\Delta}(k) := \begin{cases} q_0(\frac{k}{2^{s\Delta-1}}) * \dots * q_{s\Delta-1}(k) & \text{if } s\Delta > 0 \\ \delta_{k,0} & \text{if } s\Delta = 0 \end{cases}$, as given in Theorem 7.1.

Equations 7.29 and 7.31 give the desired result. ■

7.3 Continuous Haar Wavelet Packets

This section explicitly defines continuous-time Haar wavelet packets and demonstrates that the Walsh functions are one of the bases contained within the Haar wavelet packets subspaces. In addition, natural and sequency ordered wavelet packet subspaces are presented along with a transformation between these two ordering schemes.

Definition 7.1 (Haar Wavelet Packets [30])

The Haar wavelet packets are defined by the impulse response coefficients for the quadrature filter F_0 , $h(k)$, and by the impulse response coefficients for the quadrature filter F_1 , $g(k)$, as follows:

$$\begin{aligned} h(k) &= \frac{1}{\sqrt{2}}, \quad \text{for } k = 0, 1 \\ g(k) &= \frac{(-1)^k}{\sqrt{2}}, \quad \text{for } k = 0, 1 \end{aligned} \quad (7.32)$$

Figure 7.1 illustrates the wavelet packet basis functions on a compact interval, $I = [a, b]$, for several wavelet packet subspaces, W_f^s , based on applying the Haar quadrature filter operators, F_0 and F_1 , defined by the coefficients given in equation 7.32. When moving from left to right in figure 7.1, note that the support of the basis functions doubles. This support property holds for the general interval, $I = (-\infty, \infty)$, as well. For a compact interval, the number of basis functions, p , in each subspace, W_f^s , is halved when moving from left to right in figure 7.1. Lastly, the wavelet packet subspaces, $W_0^0 - W_7^0$, shown in figure 7.1, each have one of the first eight Paley or natural ordered Walsh functions as their corresponding basis function. Figure 7.2 provides an alternative representation of the wavelet packet basis functions based on applying the Haar quadrature filter operators, F_0 and F_1 . The wavelet packet subspaces, $\widetilde{W}_0^0 - \widetilde{W}_7^0$, shown in figure 7.2, each have one of the first eight Walsh or sequency ordered Walsh functions as their corresponding basis function.

Both of these wavelet packet ordering conventions are commonly used and will be used herein for different mathematical developments. The relationship between the wavelet packet subspaces for the two different ordering conventions is given by the following definition.

Figure 7.1: The natural ordered wavelet packet basis functions for several subspaces, W_f^s , based on applying the Haar quadrature filter operators, F_0 and F_1 .

Definition 7.2 (Sequency to natural ordered wavelet packet transformation)

Represent the frequency of the sequency ordered wavelet packet basis function, $\tilde{f} \in \mathbb{Z}^+$, by the infinite binary expansion, $\{\tilde{f}_n : n \in \mathbb{Z}^+\}$. The corresponding frequency of the natural ordered wavelet packet basis function, $f \in \mathbb{Z}^+$, is given by the infinite binary expansion, $\{f_n : n \in \mathbb{Z}^+\}$ with $f_n = \tilde{f}_n \oplus \tilde{f}_{n+1}$ where $\tilde{f}_n \oplus \tilde{f}_{n+1} := |\tilde{f}_n - \tilde{f}_{n+1}|$. The corresponding frequency of the natural ordered wavelet packet basis function is $f = \sum_{n=0}^{\infty} |\tilde{f}_n - \tilde{f}_{n+1}| 2^n$. The transformation between the sequency ordered wavelet packet subspaces, $\widetilde{W}_f$, and natural ordered wavelet packet subspaces, W_f , using the above representations, is denoted by $\chi : \widetilde{W}_f \mapsto W_f$ or equivalently, $f := \chi(\tilde{f})$.

Remark 7.4 Definition 7.2 relating Walsh and Paley ordered wavelet packet functions can be found in [39] with reference to Walsh functions.

Figure 7.2: The sequence ordered wavelet packet basis functions for several subspaces, $\tilde{W}_f^s$, based on applying the Haar quadrature filter operators, F_0 and F_1 .

Remark 7.5 When the Haar wavelet packet subspaces are sequence ordered, $\tilde{W}_{\tilde{f}}^s$, refer to figure 7.2, the parity of the Haar wavelet packet basis function(s) within a particular wavelet packet subspace is identical to the parity of the corresponding Haar wavelet packet subspace's frequency, $\tilde{f}$, i.e., if the Haar wavelet packet subspace's frequency is even (odd), the corresponding Haar wavelet packet basis function(s) are even (odd) functions.

Remark 7.6 Each subspace, W_f^0 or $\tilde{W}_f^0$, has the f th Walsh function, natural or sequence ordered, as its corresponding basis function. It follows that the unit scale Haar wavelet packets are the Walsh functions, Paley or Walsh ordered, supported on the interval $[0, 1)$.

7.4 Multiplication Of Haar Wavelet Packets

This section demonstrates that Haar wavelet packets are closed under multiplication. A multiplication theorem for Haar wavelet packets is presented which enables the explicit calculation of the product between two Haar wavelet packet basis functions. The following theorem is essential to proving that the Haar wavelet packets are closed under multiplication.

Theorem 7.4 ([7])

Let $\psi_{f_1}(t)$ and $\psi_{f_2}(t)$ be two Walsh functions whose corresponding frequencies, $f_1 \in \mathbb{Z}^+$ and $f_2 \in \mathbb{Z}^+$, are represented by their infinite binary expansions, $\{f_{1k} : k \in \mathbb{Z}^+\}$ and $\{f_{2k} : k \in \mathbb{Z}^+\}$. The Walsh functions are closed under multiplication with their product given by:

$$\psi_{f_1}(t)\psi_{f_2}(t) = \psi_{f_1 \oplus f_2}(t) \quad (7.33)$$

where $f_1 \oplus f_2 := \sum_{k=0}^{\infty} |f_{1k} - f_{2k}| 2^k \in \mathbb{Z}^+$.

This next theorem extends the multiplication property of Walsh functions to include Haar wavelet packet basis functions on the interval $[0, 1)$, and gives explicitly the resultant product.

Theorem 7.5 (Haar Wavelet Packet Multiplication Theorem)

Let $\psi_{f,p}^s(t)$ be a Haar wavelet packet basis function whose dilation equation coefficients, h and g , are given in Definition 7.1. Given two Haar wavelet packet basis functions, $\psi_{f_1,p_1}^{s_1}(t)$ and $\psi_{f_2,p_2}^{s_2}(t)$, at the scales s_1 and s_2 respectively, assume, without loss of generality, that $s_1 \geq s_2$. Represent the frequency of the second Haar wavelet packet basis function, $f_2 \in \mathbb{Z}^+$, by the infinite binary expansion, $\{f_{2n} : n \in \mathbb{Z}^+\}$. For $\mathcal{L}^2[0, 1)$, the scale of the Haar wavelet packet basis functions must be such that $s \geq 0$ and the position of the Haar wavelet packet basis function is given by $0 \leq p \leq 2^s - 1$. Define the scale difference between the two orthonormal wavelet packet basis functions as $s\Delta := s_1 - s_2$. Define the position difference as $k\Delta := p_1 - 2^{s\Delta}p_2$. Define the position set $\mathcal{K} := \{0, \dots, 2^{s\Delta} - 1\}$. The Haar wavelet packet basis functions on $\mathcal{L}^2[0, 1)$ are closed under multiplication, with their product given as follows:

$$\psi_{f_1,p_1}^{s_1}(t)\psi_{f_2,p_2}^{s_2}(t) = \begin{cases} 2^{s_1}\psi_{f_1 \oplus f_2}(2^{s_1}t - p_1) \delta_{k\Delta,0}, & \text{if } s\Delta = 0 \\ 2^{s_1} \max(\tilde{m}_{s\Delta}(k\Delta) \delta_{k\Delta,k} \forall k \in \mathcal{K}) \psi_{f_1 \oplus \tilde{f}_{2,s\Delta}}(2^{s_1}t - p_1), & \text{if } s\Delta > 0 \end{cases} \quad (7.34)$$

$$\begin{aligned} \text{where: } \tilde{f}_{2,s\Delta} &= \begin{cases} \frac{\tilde{f}_{2,s\Delta-1}}{2}, & \text{if } f_{2,s\Delta-1} = 0 \\ \frac{\tilde{f}_{2,s\Delta-1}-1}{2}, & \text{if } f_{2,s\Delta-1} = 1 \end{cases} \text{ with } \tilde{f}_{2,0} = f_2; \\ \tilde{m}_{s\Delta}(k) &:= \begin{cases} q_0(\frac{k}{2^{s\Delta-1}}) * \dots * q_{s\Delta-1}(k) & \text{if } s\Delta > 0 \\ \delta_{k,0} & \text{if } s\Delta = 0 \end{cases}, \text{ as given in Theorem 7.1;} \\ f_1 \oplus f_2 &:= \sum_{n=0}^{\infty} |f_{1n} - f_{2n}| 2^n \in \mathbb{Z}^+. \end{aligned}$$

Proof: Define two cases. For Case 1, let $s\Delta = 0$, i.e., $s_1 = s_2$. Recall the position difference defined previously, $k\Delta := p_1 - 2^{s\Delta}p_2$. The result for case 1 is determined from theorem 7.4 and the support interval condition, $\left[\frac{p_1}{2^{s_1}}, \frac{p_1+1}{2^{s_1}}\right) \cap \left[\frac{p_2}{2^{s_2}}, \frac{p_2+1}{2^{s_2}}\right) \neq \emptyset$, which must be satisfied in order for $\psi_{f_1,p_1}^{s_1}(t)\psi_{f_2,p_2}^{s_2}(t) \neq 0$, and is given as follows for $s\Delta = 0$:

$$\psi_{f_1,p_1}^{s_1}(t)\psi_{f_2,p_2}^{s_2}(t) = 2^{s_1}\psi_{f_1 \oplus f_2}(2^{s_1}t - p_1) \delta_{k\Delta,0} \quad (7.35)$$

For Case 2, let $s\Delta > 0$, i.e., $s_1 > s_2$. Use theorem 7.1 to represent the second Haar wavelet packet in the product as follows:

$$\begin{aligned} \psi_{f_1,p_1}^{s_1}(t)\psi_{f_2,p_2}^{s_2}(t) &= 2^{\frac{s_1+s_2+s\Delta}{2}}\psi_{f_1}(2^{s_1}t - p_1) \sum_{k=0}^{(2^{s\Delta}-1)} \tilde{m}_{s\Delta}(k)\psi_{\tilde{f}_{2,s\Delta}}(2^{s_2+s\Delta}t - 2^{s\Delta}p_2 - k) \\ &= 2^{s_1}\psi_{f_1}(2^{s_1}t - p_1) \sum_{k=0}^{(2^{s\Delta}-1)} \tilde{m}_{s\Delta}(k)\psi_{\tilde{f}_{2,s\Delta}}(2^{s_1}t - 2^{s\Delta}p_2 - k) \end{aligned} \quad (7.36)$$

The interval $[0, 1)$ is divided into 2^s subintervals, for each scale s . When the wavelet subspaces are restricted to a finite interval, the possible positions for the wavelet packet basis functions are restricted as well to $0 \leq p \leq 2^s - 1$. Theorem 7.1 represents a single wavelet packet basis function contained in a lower scale wavelet subspace as a sum of wavelet packet basis functions contained in a higher scale wavelet subspace, which leads to the following interval relationship:

$$\left[\frac{p_2}{2^{s_2}}, \frac{p_2+1}{2^{s_2}}\right) = \left[\frac{2^{s\Delta}p_2 + k}{2^{s_1}}, \frac{2^{s\Delta}p_2 + 1 + k}{2^{s_1}}\right) \quad (7.37)$$

with $k \in \{0, \dots, 2^{s\Delta} - 1\}$. In light of the position difference defined previously as $k\Delta := p_1 - 2^{s\Delta}p_2$, the following equivalences can be made:

$$\left\{\left[\frac{p_1}{2^{s_1}}, \frac{p_1+1}{2^{s_1}}\right) \cap \left[\frac{p_2}{2^{s_2}}, \frac{p_2+1}{2^{s_2}}\right) \neq \emptyset\right\} \equiv \{k\Delta \in \{0, \dots, 2^{s\Delta} - 1\}\} \quad (7.38)$$

$$\left\{\left[\frac{p_1}{2^{s_1}}, \frac{p_1+1}{2^{s_1}}\right) \cap \left[\frac{p_2}{2^{s_2}}, \frac{p_2+1}{2^{s_2}}\right) = \emptyset\right\} \equiv \{k\Delta \notin \{0, \dots, 2^{s\Delta} - 1\}\} \quad (7.39)$$

Therefore, if $\left[\frac{p_1}{2^{s_1}}, \frac{p_1+1}{2^{s_1}}\right) \cap \left[\frac{p_2}{2^{s_2}}, \frac{p_2+1}{2^{s_2}}\right) \neq \emptyset$ and $s\Delta > 0$, then it follows that:

$$\psi_{f_1,p_1}^{s_1}(t)\psi_{f_2,p_2}^{s_2}(t) = 2^{s_1}\tilde{m}_{s\Delta}(k\Delta) \psi_{f_1 \oplus \tilde{f}_{2,s\Delta}}(2^{s_1}t - p_1) \quad (7.40)$$

Otherwise, if $\left[\frac{p_1}{2^{s_1}}, \frac{p_1+1}{2^{s_1}}\right) \cap \left[\frac{p_2}{2^{s_2}}, \frac{p_2+1}{2^{s_2}}\right) = \emptyset$ and $s\Delta > 0$, then it follows that:

$$\psi_{f_1,p_1}^{s_1}(t)\psi_{f_2,p_2}^{s_2}(t) = 0 \quad (7.41)$$

Equations 7.40 and 7.41 can be equivalently stated as follows:

$$\psi_{f_1,p_1}^{s_1}(t)\psi_{f_2,p_2}^{s_2}(t) = 2^{s_1} \max(\tilde{m}_{s\Delta}(k\Delta) \delta_{k\Delta,k} \forall k \in \mathcal{K}) \psi_{f_1 \oplus \tilde{f}_{2,s\Delta}}(2^{s_1}t - p_1) \quad (7.42)$$

Equations 7.35 and 7.42 combine to give the desired result. ■

Remark 7.7 Note that Theorem 7.5 can be trivially extended to Haar wavelet packet basis functions defined on $\mathcal{L}^2[0, \infty)$ by letting $p \in \mathbb{Z}^+$ and extended to Haar wavelet packet basis functions defined on $\mathcal{L}^2(\mathbb{R})$ by letting $p \in \mathbb{Z}$.

Remark 7.8 Also note that $\psi_{f1,p1}^{s1}(t)\psi_{f2,p2}^{s2}(t) = 0$ if $s\Delta \geq 0$ and $k\Delta \notin \mathcal{K}$, which is equivalent to $[\frac{p1}{2^{s1}}, \frac{p1+1}{2^{s1}}) \cap [\frac{p2}{2^{s2}}, \frac{p2+1}{2^{s2}}) = \emptyset$.

7.5 Discrete Haar Wavelet Packets

Continuous-time Haar wavelet packet basis functions are represented using theorem 7.1. A sampling theorem for Walsh functions was previously determined based on the sequency bandwidth of the corresponding Walsh function [40]. The sequency bandwidth is simply the number of zero crossings per unit time, in this case per second.

Theorem 7.6 ([40])

A signal limited in sequency bandwidth to S zero crossings per second can be reconstructed completely when the sampling frequency, F_s , is defined as follows:

$$\begin{aligned} F_s &= 2^{\bar{\nu}} \\ \bar{\nu} &\geq \lceil \log_2(S) \rceil \end{aligned} \quad (7.43)$$

with $\bar{\nu} \in \mathbb{Z}^+$ and $\lceil x \rceil = n$ with n denoting the greatest integer satisfying the relationship $(n - 1) < x \leq n$.

Remark 7.9 When the Walsh functions are sequency ordered, $\widetilde{W}_{\tilde{f}}^0$, an equivalent relation in terms of the frequency of the Walsh functions, see figure 7.2, is given by:

$$\bar{\nu} \geq \lceil \log_2(\tilde{f} + 1) \rceil \quad (7.44)$$

Remark 7.10 Theorem 7.6 applies directly to sequency ordered Haar wavelet packet subspaces, $\widetilde{W}_{\tilde{f}}^{\tilde{s}}$, with the caveat that the sequency bandwidth for a particular Haar wavelet packet subspace must be determined by summing up the zero crossings per second for each Haar wavelet packet basis function contained within that subspace, or equivalently:

$$\bar{\nu} \geq \tilde{s} + \lceil \log_2(\tilde{f} + 1) \rceil \quad (7.45)$$

A sampled time domain version of any sequency ordered Haar wavelet packet basis function, $\tilde{\psi}_{\tilde{f},\tilde{p}}^{\tilde{s}}(t) \in \tilde{W}_{\tilde{f}}^{\tilde{s}}$, will now be determined based on the sampling rate, F_s , defined in theorem 7.6 and remark 7.10.

Lemma 7.2 (Discrete Time Haar Wavelet Packet Basis Functions)

Let $\tilde{\psi}_{\tilde{f},\tilde{p}}^{\tilde{s}}(t) \in \tilde{W}_{\tilde{f}}^{\tilde{s}}$ be any continuous-time, sequency ordered Haar wavelet packet basis function. Let the corresponding sampling frequency be $F_s = 2^{\tilde{\nu}}$ with $\tilde{\nu} \geq \tilde{s} + \lceil \log_2(\tilde{f} + 1) \rceil$. The corresponding discrete-time Haar wavelet packet basis function is given by the following:

$$\tilde{\psi}_{\tilde{f},\tilde{p}}^{\tilde{s}}(k) = 2^{\frac{\tilde{s}}{2}} \tilde{m}_{\tilde{s}\Delta}(k - 2^{\tilde{s}\Delta}\tilde{p}) \quad (7.46)$$

$$\text{where: } \tilde{m}_{\tilde{s}\Delta}(k - 2^{\tilde{s}\Delta}\tilde{p}) := \begin{cases} q_0(\frac{k}{2^{\tilde{s}\Delta-1}}) * q_1(\frac{k}{2^{\tilde{s}\Delta-2}}) * \cdots * q_{\tilde{s}\Delta-1}(k - 2^{\tilde{s}\Delta}\tilde{p}) & \text{if } \tilde{s}\Delta > 0 \\ \delta_{k,0} & \text{if } \tilde{s}\Delta = 0 \end{cases};$$

$$\tilde{s}\Delta := \tilde{\nu} - \tilde{s};$$

$$\tilde{f} := \chi(\tilde{f}) \text{ as given in definition 7.2;}$$

$$\{f_n : n \in \mathbb{Z}^+\} \text{ is the infinite binary expansion of } \tilde{f} \in \mathbb{Z}^+;$$

$$q_n(k) = \begin{cases} h(k), & \text{if } f_n = 0 \\ g(k), & \text{if } f_n = 1 \end{cases}.$$

Proof: Represent the continuous-time Haar wavelet packet basis function using the equivalent form of theorem 7.1, equation 7.21 with $\tilde{s}\Delta = \tilde{\nu} - \tilde{s}$, after applying the sequency to natural ordered wavelet packet mapping, definition 7.2, $\chi : \tilde{W}_{\tilde{f}} \mapsto W_{\tilde{f}}$, or equivalently, $\tilde{f} := \chi(\tilde{f})$, as follows:

$$\tilde{\psi}_{\tilde{f},\tilde{p}}^{\tilde{s}}(t) = 2^{\frac{\tilde{s}}{2}} \sum_{k=0}^{(2^{\tilde{s}\Delta}-1)} \tilde{m}_{\tilde{s}\Delta}(k) \psi_{\tilde{f}\tilde{s}\Delta}(2^{\tilde{\nu}}t - 2^{\tilde{s}\Delta}\tilde{p} - k) \quad (7.47)$$

Now use remark 7.10, which demonstrates that the theorem 7.6 is directly applicable to Haar wavelet packet basis functions with the sampling rate, $F_s = 2^{\tilde{\nu}}$, and $\tilde{\nu}$ defined as: $\tilde{\nu} \geq \tilde{s} + \lceil \log_2(\tilde{f} + 1) \rceil$. Recall remark 7.2 which demonstrates that $\psi_{\tilde{f}\tilde{s}\Delta}(t) = \psi_0(2^{\tilde{\nu}}t)$. Equation 7.47 becomes:

$$\begin{aligned} \tilde{\psi}_{\tilde{f},\tilde{p}}^{\tilde{s}}(t) &= 2^{\frac{\tilde{s}}{2}} \sum_{k=0}^{(2^{\tilde{s}\Delta}-1)} \tilde{m}_{\tilde{s}\Delta}(k) \psi_0(2^{\tilde{\nu}}t - 2^{\tilde{s}\Delta}\tilde{p} - k) \\ &= 2^{\frac{\tilde{s}}{2}} \sum_{k=0}^{(2^{\tilde{s}\Delta}-1)} \tilde{m}_{\tilde{s}\Delta}(k - 2^{\tilde{s}\Delta}\tilde{p}) \psi_0(2^{\tilde{\nu}}t - k) \end{aligned} \quad (7.48)$$

The time domain interpolation function for a Walsh function is a pulse [40], or equivalently, a Haar scaling function. The Haar scaling function is also the time domain interpolation function for any Haar wavelet packet basis function. Since $\psi_0(2^{\tilde{\nu}}t - k)$ is simply a Haar scaling function, and the sampling period is given by $\tau_s := 2^{-\tilde{\nu}}$ with $\tilde{\nu} \geq \tilde{s} + \lceil \log_2(\tilde{f} + 1) \rceil$, the desired result follows

immediately:

$$\begin{aligned}\tilde{\psi}_{f,\tilde{p}}^{\tilde{s}}(n) &= \tilde{\psi}_{f,\tilde{p}}^{\tilde{s}}(k\tau_s) = 2^{\frac{\tilde{s}}{2}} \sum_{k=0}^{(2^{\tilde{s}\Delta}-1)} \tilde{m}_{s\Delta}(k - 2^{\tilde{s}\Delta}\tilde{p})\psi_0(n-k) \\ &= 2^{\frac{\tilde{s}}{2}}\tilde{m}_{s\Delta}(n - 2^{\tilde{s}\Delta}\tilde{p}) \quad \blacksquare\end{aligned}\tag{7.49}$$

Remark 7.11 Notice that the length, N , of the discrete-time representation for $\tilde{\psi}_{f,\tilde{p}}^{\tilde{s}}(t)$ is $N = 2^{\tilde{\nu}}$.

Remark 7.12 Observe that $\tilde{s}\Delta = 0$ only when the wavelet packet subspace contains scaling functions and the minimum sampling rate is used, i.e., $\tilde{s}\Delta = 0$ for all wavelet packet subspaces of the form $\tilde{W}_0^{\tilde{s}}$ when $\tilde{\nu} = \tilde{s}$.

The following example will illustrate the use of equation 7.46.

Example 7.1 The sampled time domain representations for the Haar wavelet basis functions contained in the wavelet packet subspaces, $\tilde{W}_0^0$, $\tilde{W}_1^0$, $\tilde{W}_1^1$, and $\tilde{W}_1^2$ as shown in Figure 7.2, based on using the minimum sampling rate necessary to adequately represent all of these Haar wavelet functions, $\tilde{\nu} = 3$, can be expressed by the following Haar Wavelet Packet Basis (HWPB) matrix:

$$\Lambda_1 = \begin{bmatrix} \tilde{\psi}_{0,0}^0(k) \\ \tilde{\psi}_{1,0}^0(k) \\ \tilde{\psi}_{1,0}^1(k) \\ \tilde{\psi}_{1,1}^1(k) \\ \tilde{\psi}_{1,0}^2(k) \\ \tilde{\psi}_{1,1}^2(k) \\ \tilde{\psi}_{1,2}^2(k) \\ \tilde{\psi}_{1,3}^2(k) \end{bmatrix} = \begin{bmatrix} 1 & 1 & 1 & 1 & 1 & 1 & 1 & 1 \\ 1 & 1 & 1 & 1 & -1 & -1 & -1 & -1 \\ \sqrt{2} & \sqrt{2} & -\sqrt{2} & -\sqrt{2} & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & \sqrt{2} & \sqrt{2} & -\sqrt{2} & -\sqrt{2} \\ 2 & -2 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & 2 & -2 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & 2 & -2 & 0 & 0 \\ 0 & 0 & 0 & 0 & 0 & 0 & 2 & -2 \end{bmatrix}\tag{7.50}$$

Example 7.2 The sampled time domain representations for the Walsh functions contained in the Haar wavelet packet subspaces, $\tilde{W}_0^0 - \tilde{W}_7^0$, based on the minimum sampling rate, $\tilde{\nu} = 3$, has the

following HWPB matrix representation, which is a Hadamard matrix [7]:

$$\Lambda_2 = \begin{bmatrix} \tilde{\psi}_0^0(k) \\ \tilde{\psi}_1^0(k) \\ \tilde{\psi}_2^0(k) \\ \tilde{\psi}_3^0(k) \\ \tilde{\psi}_4^0(k) \\ \tilde{\psi}_5^0(k) \\ \tilde{\psi}_6^0(k) \\ \tilde{\psi}_7^0(k) \end{bmatrix} = \begin{bmatrix} 1 & 1 & 1 & 1 & 1 & 1 & 1 & 1 \\ 1 & 1 & 1 & 1 & -1 & -1 & -1 & -1 \\ 1 & 1 & -1 & -1 & -1 & -1 & 1 & 1 \\ 1 & 1 & -1 & -1 & 1 & 1 & -1 & -1 \\ 1 & -1 & -1 & 1 & 1 & -1 & -1 & 1 \\ 1 & -1 & -1 & 1 & -1 & 1 & 1 & -1 \\ 1 & -1 & 1 & -1 & -1 & 1 & -1 & 1 \\ 1 & -1 & 1 & -1 & 1 & -1 & 1 & -1 \end{bmatrix} \quad (7.51)$$

Continuous-time inner products between orthonormal wavelet packet basis functions can be determined explicitly using theorem 7.2. Theorem 7.2 emphasizes the most powerful property of wavelet packets, which is that all properties possessed by the continuous-time wavelet packet basis functions are also possessed by the corresponding wavelet packet coefficients. Further examination of theorem 7.2 demonstrates that the inner product between continuous-time orthonormal wavelet packet basis functions can be directly determined from the corresponding wavelet packet coefficients only. It follows that the inner product between two continuous-time Haar wavelet packet basis functions can be determined directly from the corresponding discrete-time Haar wavelet packet basis functions, as given by the following corollary to theorem 7.2.

Corollary 7.1 (Haar Wavelet Packet Inner Product Formula)

Let $\tilde{\psi}_{\tilde{f}_1, \tilde{p}_1}^{\tilde{s}_1}(t) \in \widetilde{W}_{\tilde{f}_1}^{\tilde{s}_1}$ and $\tilde{\psi}_{\tilde{f}_2, \tilde{p}_2}^{\tilde{s}_2}(t) \in \widetilde{W}_{\tilde{f}_2}^{\tilde{s}_2}$ be any two continuous-time, sequency ordered Haar wavelet packet basis functions. Let the sampling frequency for the corresponding discrete time Haar wavelet packet basis functions be $F_s = 2^{\tilde{\nu}}$ with $\tilde{\nu} \geq \max(\tilde{s}_i + \lceil \log_2(f_i + 1) \rceil, \forall i = 1, 2)$. The continuous-time Haar wavelet packet inner product can then be calculated using the corresponding discrete-time Haar wavelet packet basis functions as follows:

$$\langle \psi_{\tilde{f}_1, \tilde{p}_1}^{\tilde{s}_1}(t), \psi_{\tilde{f}_2, \tilde{p}_2}^{\tilde{s}_2}(t) \rangle = 2^{-\tilde{\nu}} \sum_{k \in \mathbb{Z}} \psi_{\tilde{f}_1, \tilde{p}_1}^{\tilde{s}_1}(k) \psi_{\tilde{f}_2, \tilde{p}_2}^{\tilde{s}_2}(k) \quad (7.52)$$

where $\psi_{\tilde{f}_i, \tilde{p}_i}^{\tilde{s}_i}(k)$ is determined using lemma 7.2.

Proof: Start with the wavelet packet inner product theorem, theorem 7.2, as follows:

$$\langle \psi_{\tilde{f}_1, \tilde{p}_1}^{\tilde{s}_1}(t), \psi_{\tilde{f}_2, \tilde{p}_2}^{\tilde{s}_2}(t) \rangle = \sum_{k \in \mathbb{Z}} \tilde{m}_{\tilde{s}_1 \Delta_1}(k - 2^{\tilde{s}_1 \Delta_1} \tilde{p}_1) \tilde{m}_{\tilde{s}_2 \Delta_2}(k - 2^{\tilde{s}_2 \Delta_2} \tilde{p}_2) \quad (7.53)$$

where: $\tilde{m}_{\tilde{s}_i \Delta_i}(k) := \begin{cases} q_0(\frac{k}{2^{\tilde{s}_i \Delta_i - 1}}) * \dots * q_{\tilde{s}_i \Delta_i - 1}(k) & \text{if } \tilde{s}_i \Delta_i > 0 \\ \delta_{k,0} & \text{if } \tilde{s}_i \Delta_i = 0 \end{cases}$, as given in Theorem 7.1;

$$\bar{s}\Delta_i := \bar{\nu} - s_i, \forall i = 1, 2;$$

$$f_i := \chi(\bar{f}_i) \text{ as given in definition 7.2;}$$

$$\{f_{i_n} : n \in \mathbb{Z}^+\} \text{ is the infinite binary expansion of the frequency, } f_i;$$

$$q_n(k) = \begin{cases} h(k), & \text{if } f_{i_n} = 0 \\ g(k), & \text{if } f_{i_n} = 1 \end{cases}.$$

Use the discrete-time representation for a Haar wavelet packet basis function, lemma 7.2, to yield the desired result:

$$\begin{aligned} \langle \psi_{\bar{f}_1, \bar{p}_1}^{\bar{s}_1}(t), \psi_{\bar{f}_2, \bar{p}_2}^{\bar{s}_2}(t) \rangle &= \sum_{k \in \mathbb{Z}} \tilde{m}_{\bar{s}\Delta_1}(k - 2^{\bar{s}\Delta_1}\bar{p}_1) \tilde{m}_{\bar{s}\Delta_2}(k - 2^{\bar{s}\Delta_2}\bar{p}_2) \\ &= 2^{-\bar{\nu}} \sum_{k \in \mathbb{Z}} \tilde{\psi}_{\bar{f}_1, \bar{p}_1}^{\bar{s}_1}(k) \tilde{\psi}_{\bar{f}_2, \bar{p}_2}^{\bar{s}_2}(k) \quad \blacksquare \end{aligned}$$

Definition 7.3

It is desirable to make the discrete-time Haar wavelet packet inner products identical to the corresponding continuous-time Haar wavelet packet inner products. This allows the orthonormality property to be identical for both continuous-time and discrete-time inner products. Using the result of corollary 7.1, the discrete-time Haar wavelet packet inner products will be defined as follows:

$$\langle \tilde{\psi}_{\bar{f}_1, \bar{p}_1}^{\bar{s}_1}(k), \tilde{\psi}_{\bar{f}_2, \bar{p}_2}^{\bar{s}_2}(k) \rangle := \langle \psi_{\bar{f}_1, \bar{p}_1}^{\bar{s}_1}(t), \psi_{\bar{f}_2, \bar{p}_2}^{\bar{s}_2}(t) \rangle = 2^{-\bar{\nu}} \sum_{k \in \mathbb{Z}} \tilde{\psi}_{\bar{f}_1, \bar{p}_1}^{\bar{s}_1}(k) \tilde{\psi}_{\bar{f}_2, \bar{p}_2}^{\bar{s}_2}(k) \quad (7.54)$$

Continuous-time inner products between bases of sampled Haar wavelet packet basis functions can be determined directly by using the corresponding HWPB matrices.

Example 7.3 Using the same HWPB matrices already developed in examples 7.1 and 7.2, the continuous-time inner products between the bases of Haar wavelet packet basis functions contained in matrices Λ_1 and Λ_2 with $N = 2^{\bar{\nu}} = 8$ are given by:

$$\begin{aligned} \begin{bmatrix} \langle \tilde{\psi}_0^0(t), \tilde{\psi}_0^0(t) \rangle & \cdots & \langle \tilde{\psi}_0^0(t), \tilde{\psi}_7^0(t) \rangle \\ \vdots & \ddots & \vdots \\ \langle \tilde{\psi}_{1,3}^2(t), \tilde{\psi}_0^0(t) \rangle & \cdots & \langle \tilde{\psi}_{1,3}^2(t), \tilde{\psi}_7^0(t) \rangle \end{bmatrix} &= \frac{1}{N} \Lambda_1 \Lambda_2^T \\ &= \begin{bmatrix} 1 & 0 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 & 0 & 0 & 0 & 0 \\ 0 & 0 & \frac{1}{\sqrt{2}} & \frac{1}{\sqrt{2}} & 0 & 0 & 0 & 0 \\ 0 & 0 & -\frac{1}{\sqrt{2}} & \frac{1}{\sqrt{2}} & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & 0 & \frac{1}{2} & \frac{1}{2} & \frac{1}{2} & \frac{1}{2} \\ 0 & 0 & 0 & 0 & -\frac{1}{2} & -\frac{1}{2} & \frac{1}{2} & \frac{1}{2} \\ 0 & 0 & 0 & 0 & \frac{1}{2} & -\frac{1}{2} & -\frac{1}{2} & \frac{1}{2} \\ 0 & 0 & 0 & 0 & -\frac{1}{2} & \frac{1}{2} & -\frac{1}{2} & \frac{1}{2} \end{bmatrix} \end{aligned} \quad (7.55)$$

Remark 7.13 Example 7.3 demonstrates that the use of HWPB matrices greatly simplifies the calculation of the corresponding continuous-time inner products presented in Theorem 7.2. In other words, the discrete representation of the Haar wavelet packet basis functions, using HWPB matrices, allows continuous-time inner products to be calculated using simple matrix multiplication.

The calculation of Haar wavelet packet products, given by theorem 7.5, for discrete-time Haar wavelet packet basis functions is also greatly simplified by using HWPB matrices. Discrete-time Haar wavelet packet products between bases of sampled Haar wavelet packet basis functions can be determined directly by using the corresponding HWPB matrices.

Example 7.4 Using the same HWPB matrices already developed in examples 7.1 and 7.2, the discrete Haar wavelet packet products between the bases of Haar wavelet packet basis functions contained in matrices Λ_1 and Λ_2 with $N = 8$ are given by:

$$\begin{bmatrix} \tilde{\psi}_0^0(k)\tilde{\psi}_0^0(k) \\ \vdots \\ \tilde{\psi}_{1,3}^2(k)\tilde{\psi}_{0,0}^0(k) \\ \vdots \\ \tilde{\psi}_0^0(k)\tilde{\psi}_7^0(k) \\ \vdots \\ \tilde{\psi}_{1,3}^2(k)\tilde{\psi}_7^0(k) \end{bmatrix} = (\mathbf{1}_N \otimes \Lambda_1) \circ (\Lambda_2 \otimes \mathbf{1}_N) = \begin{bmatrix} \tilde{\psi}_0^0(k) \\ \vdots \\ \tilde{\psi}_{1,3}^2(k) \\ \vdots \\ \tilde{\psi}_7^0(k) \\ \vdots \\ \tilde{\psi}_{0,3}^2(k) \end{bmatrix} \quad (7.56)$$

where $\circ$ represents the Hadamard product [41], and $\mathbf{1}_N$ is a $N \times 1$ vector of ones. The matrix given by equation 7.56 is of dimension $N^2 \times N$ and is composed of matrix blocks of dimension $N \times N$, where each block represents the Haar wavelet packet products of the matrix Λ_1 with one of the basis functions contained in matrix Λ_2 .

Remark 7.14 In order to perform the reverse transformation between natural and sequency ordered wavelet packet subspaces, a simple table look-up scheme can be constructed from the resultant sequency to natural ordered transformation presented in definition 7.2, $\chi : \widetilde{W}_{\tilde{f}} \mapsto W_f$ or equivalently $f := \chi(\tilde{f})$. Due to these transformations between sequency and natural ordered wavelet packet subspaces and vice versa, no further mention will be made in the sequel of the ordering for the wavelet packet subspaces.

CHAPTER 8

B-SPLINE PACKETS

This chapter presents new theoretical results for B-splines, defines the notion of a B-spline packet, and presents new theoretical results for B-spline packets. The focus of this chapter will be limited to B-splines [42], and B-spline packets with compact support.

8.1 B-splines

This section defines B-splines and develops the corresponding two-scale dilation equation satisfied by B-splines. Several important lemmas which are utilized in the sequel are also presented.

Definition 8.1 (B-splines)

The N th order B-spline, $B_N(t)$, with knots contained in the set $\mathbb{Z}^+$ can be defined as follows:

$$\begin{aligned} B_0(t) &= \chi_{[0,1)}(t) \\ B_N(t) &= B_{N-1}(t) * B_0(t) = \int_0^1 B_{N-1}(t-x)dx = \int_{t-1}^t B_{N-1}(x)dx \end{aligned} \quad (8.1)$$

where $\chi_A :=$ the characteristic function of the set A .

The support of $B_N(t)$ is given by:

$$Supp\{B_N(t)\} = [0, N+1] \quad (8.2)$$

Remark 8.1 Note that $B_0(t)$ is simply the Haar scaling function.

Remark 8.2 Definition 8.1 demonstrates that the N th order B-spline, $B_N(t)$, is created by convolving $N+1$ Haar scaling functions.

It has been observed by [43], [44], and [34] that almost every formula for wavelets can be applied directly to splines. The B-splines satisfy the following two-scale dilation equation [43], [44], and [34]:

$$\mathcal{B}_N(t) = 2^{-N} \sum_{k=0}^{N+1} \binom{N+1}{k} \mathcal{B}_N(2t - k) = 2 \sum_{k=0}^{N+1} \tilde{h}_N(k) \mathcal{B}_N(2t - k) \quad (8.3)$$

where: $\tilde{h}_N(k) := \underbrace{\tilde{h}_0(k) * \tilde{h}_0(k) * \cdots * \tilde{h}_0(k)}_{N+1}$, which is a vector of length $N + 2$;

$$\tilde{h}_0(k) := \begin{cases} \frac{1}{2}, & k = 0, 1 \\ 0, & \text{otherwise} \end{cases}.$$

Several new equivalent forms of equation 8.3 will now be developed. The first step will be to develop and prove some lemmas necessary for accomplishing this task.

Lemma 8.1

$$\begin{aligned} \mathcal{B}_{N-1}(2^\alpha t - i) * \mathcal{B}_0(2^\alpha t - j) &= \mathcal{B}_{N-1}(2^\alpha t) * \mathcal{B}_0(2^\alpha t - (i + j)) \\ &= \frac{1}{2^\alpha} \mathcal{B}_N(2^\alpha t - (i + j)) \end{aligned} \quad (8.4)$$

Proof:

$$\begin{aligned} \mathcal{B}_{N-1}(2^\alpha t - i) * \mathcal{B}_0(2^\alpha t - j) &= \int_{-\infty}^{\infty} \mathcal{B}_{N-1}(2^\alpha \tau - i) \mathcal{B}_0(2^\alpha t - j - 2^\alpha \tau) d\tau \\ &= \frac{1}{2^\alpha} \int_{-\infty}^{\infty} \mathcal{B}_{N-1}(\tau) \mathcal{B}_0(2^\alpha t - (i + j) - \tau) d\tau \\ &= \frac{1}{2^\alpha} \mathcal{B}_N(2^\alpha t - (i + j)) \\ &= \int_{-\infty}^{\infty} \mathcal{B}_{N-1}(2^\alpha \tau) \mathcal{B}_0(2^\alpha t - (i + j) - 2^\alpha \tau) d\tau \\ &= \mathcal{B}_{N-1}(2^\alpha t) * \mathcal{B}_0(2^\alpha t - (i + j)) \quad \blacksquare \end{aligned}$$

The right hand side of Lemma 8.1 is further generalized by the following lemma.

Lemma 8.2

$$\begin{aligned} \frac{1}{2^{\alpha N}} \mathcal{B}_N(2^\alpha t - (i + \cdots + j + k + l)) &= \underbrace{\mathcal{B}_0(2^\alpha t - i) * \cdots * \mathcal{B}_0(2^\alpha t - k) * \mathcal{B}_0(2^\alpha t - l)}_{N+1} \\ &= \underbrace{\mathcal{B}_0(2^\alpha t) * \cdots * \mathcal{B}_0(2^\alpha t)}_N * \\ &\quad \mathcal{B}_0(2^\alpha t - (i + \cdots + j + k + l)) \\ &= \frac{1}{2^{\alpha(N-1)}} \mathcal{B}_{N-1}(2^\alpha t) * \\ &\quad \mathcal{B}_0(2^\alpha t - (i + \cdots + j + k + l)) \end{aligned} \quad (8.5)$$

Proof: Applying Lemma 8.1 to the following equation yields:

$$\frac{1}{2^{\alpha N}} \mathcal{B}_N(2^\alpha t - (i + \dots + j + k + l)) = \left(\frac{1}{2^{\alpha(N-1)}} \mathcal{B}_{N-1}(2^\alpha t - (i + \dots + j + k)) \right) * \mathcal{B}_0(2^\alpha t - l) \quad (8.6)$$

Recursively applying lemma 8.1 N more times, as was just preformed on equation 8.6, to the first term on the RHS of equation 8.6 gives the first result. Now, applying lemma 8.1 to the following equation and rearranging yields:

$$\underbrace{\mathcal{B}_0(2^\alpha t - i) * \dots * \mathcal{B}_0(2^\alpha t - k) * \mathcal{B}_0(2^\alpha t - l)}_{N+1} = \mathcal{B}_0(2^\alpha t) * \left(\underbrace{\mathcal{B}_0(2^\alpha t - i) * \dots * \mathcal{B}_0(2^\alpha t - j) * \mathcal{B}_0(2^\alpha t - (k + l))}_{N-1} \right) \quad (8.7)$$

Recursively performing this same procedure $N - 1$ more times on the second term on the RHS of equation 8.7 gives the second result. The third result follows directly from recursive use of definition 8.1. ■

Lemma 8.1 is generalized by the following lemma.

Lemma 8.3

$$\mathcal{B}_N(2^\alpha t - i) * \mathcal{B}_M(2^\alpha t - j) = \frac{1}{2^\alpha} \mathcal{B}_{N+M+1}(2^\alpha t - (i + j)) \quad (8.8)$$

Proof: Start by using Lemma 8.2 to expand the term $\mathcal{B}_M(2^\alpha t - j)$, then apply lemma 8.1 recursively on the RHS to yield the desired result:

$$\begin{aligned} \mathcal{B}_N(2^\alpha t - i) * \mathcal{B}_M(2^\alpha t - j) &= \mathcal{B}_N(2^\alpha t - i) * \underbrace{2^{\alpha M} \mathcal{B}_0(2^\alpha t - j) * \dots * \mathcal{B}_0(2^\alpha t)}_{M+1} \\ &= 2^{\alpha(M-1)} \mathcal{B}_{N+1}(2^\alpha t - i - j) * \underbrace{\mathcal{B}_0(2^\alpha t) * \dots * \mathcal{B}_0(2^\alpha t)}_M \\ &= \frac{1}{2^\alpha} \mathcal{B}_{N+M+1}(2^\alpha t - (i + j)) \quad \blacksquare \end{aligned}$$

Lemma 8.4

$$\sum_{k \in \mathbb{Z}} h_N \mathcal{B}_N(2t - k) = 2 \sum_{k \in \mathbb{Z}} \sum_{j \in \mathbb{Z}} h_{N-1}(j) h_0(k) \mathcal{B}_{N-1}(2t - j) * \mathcal{B}_0(2t - k) \quad (8.9)$$

Proof:

$$\begin{aligned}
\sum_{k \in \mathbb{Z}} h_N \mathcal{B}_N(2t - k) &= \sum_{k \in \mathbb{Z}} (h_{N-1} * h_0)(k) \mathcal{B}_N(2t - k) \\
&= \sum_{k \in \mathbb{Z}} \sum_{j \in \mathbb{Z}} h_{N-1}(j) h_0(k - j) \mathcal{B}_N(2t - k) \\
&= \sum_{k \in \mathbb{Z}} \sum_{j \in \mathbb{Z}} h_{N-1}(j) h_0(k) \mathcal{B}_N(2t - (j + k)) \\
&= 2 \sum_{k \in \mathbb{Z}} \sum_{j \in \mathbb{Z}} h_{N-1}(j) h_0(k) \mathcal{B}_{N-1}(2t - j) * \mathcal{B}_0(2t - k) \quad \blacksquare
\end{aligned}$$

Lemma 8.4 is generalized by the following lemma.

Lemma 8.5

$$\begin{aligned}
2^{-\frac{N-1}{2}} \sum_{k \in \mathbb{Z}} h_N(k) \mathcal{B}_N(2t - k) &= \\
2^{\frac{N+1}{2}} \underbrace{\sum_{j \in \mathbb{Z}} \dots \sum_{k \in \mathbb{Z}}}_{N+1} \underbrace{(h_0(j) \dots h_0(k))}_{N+1} \underbrace{[\mathcal{B}_0(2t - j) * \dots * \mathcal{B}_0(2t - k)]}_{N+1} & \quad (8.10)
\end{aligned}$$

Proof:

$$\begin{aligned}
2^{-\frac{N-1}{2}} \sum_{k \in \mathbb{Z}} h_N(k) \mathcal{B}_N(2t - k) &= 2^{-\frac{N-3}{2}} \sum_{k \in \mathbb{Z}} \sum_{j \in \mathbb{Z}} h_{N-1}(j) h_0(k) \mathcal{B}_{N-1}(2t - j) * \mathcal{B}_0(2t - k) \\
&= \left(2^{-\frac{N-3}{2}} \sum_{j \in \mathbb{Z}} h_{N-1}(j) \mathcal{B}_{N-1}(2t - j) \right) * \left(\sum_{k \in \mathbb{Z}} h_0(k) \mathcal{B}_0(2t - k) \right) \quad (8.11)
\end{aligned}$$

Applying lemma 8.4 recursively to the first term on the RHS of equation 8.11 and rearranging each time yields the desired result. $\blacksquare$

The corresponding lemma to lemma 8.5 for the RHS of the original B-spline dilation equation, 8.3, is given by the following lemma.

Lemma 8.6

$$2 \sum_{k \in \mathbb{Z}} \tilde{h}_N(k) \mathcal{B}_N(2t - k) = 2^{N+1} \underbrace{\sum_{j \in \mathbb{Z}} \dots \sum_{k \in \mathbb{Z}}}_{N+1} \underbrace{(\tilde{h}_0(j) \dots \tilde{h}_0(k))}_{N+1} \underbrace{[\mathcal{B}_0(2t - j) * \dots * \mathcal{B}_0(2t - k)]}_{N+1} \quad (8.12)$$

Proof: Basically identical to the proof of lemma 8.5 and is therefore omitted. $\blacksquare$

Using Lemmas 8.1 - 8.6, the B-spline dilation equation 8.3 is shown to have several equivalent representations by the following definition.

Lemma 8.7 (B-spline Dilation Equation)

The B-splines satisfy the following two-scale dilation equation:

$$\mathcal{B}_N(t) = 2^{-\frac{N-1}{2}} \sum_{k \in \mathbb{Z}} h_N(k) \mathcal{B}_N(2t - k) \quad (8.13)$$

$$\mathcal{B}_N(t) = \underbrace{\left(\sqrt{2} \sum_{j \in \mathbb{Z}} h_0(j) \mathcal{B}_0(2t - j) \right) * \cdots * \left(\sqrt{2} \sum_{k \in \mathbb{Z}} h_0(k) \mathcal{B}_0(2t - k) \right)}_{N+1} \quad (8.14)$$

$$\mathcal{B}_N(t) = 2^{\frac{N+1}{2}} \underbrace{\sum_{j \in \mathbb{Z}} \cdots \sum_{k \in \mathbb{Z}}}_{N+1} \underbrace{(h_0(j) \cdots h_0(k))}_{N+1} \underbrace{[\mathcal{B}_0(2t - j) * \cdots * \mathcal{B}_0(2t - k)]}_{N+1} \quad (8.15)$$

where: $h_0(k) :=$ the Haar scaling function coefficients, $h(k)$, presented in definition 7.1;

$h_N(k) := \underbrace{h_0(k) * h_0(k) * \cdots * h_0(k)}_{N+1}$, which is a vector of length $N + 2$.

Proof: Observe that the first part is identical to proving that lemma 8.5 is equivalent to lemma 8.6.

Start with lemma 8.5, and yield lemma 8.6 as follows:

$$\begin{aligned} 2^{-\frac{N-1}{2}} \sum_{k \in \mathbb{Z}} h_N(k) \mathcal{B}_N(2t - k) &= 2^{-\frac{N-1}{2}} \underbrace{\sum_{j \in \mathbb{Z}} \cdots \sum_{k \in \mathbb{Z}}}_{N+1} \underbrace{(h_0(j) \cdots h_0(k))}_{N+1} \mathcal{B}_N(2t - k) \\ &= 2^{-\frac{N-1}{2}} \frac{2^{-\frac{N+1}{2}}}{2^{-\frac{N+1}{2}}} \underbrace{\sum_{j \in \mathbb{Z}} \cdots \sum_{k \in \mathbb{Z}}}_{N+1} \underbrace{(h_0(j) \cdots h_0(k))}_{N+1} \mathcal{B}_N(2t - k) \\ &= 2 \underbrace{\sum_{j \in \mathbb{Z}} \cdots \sum_{k \in \mathbb{Z}}}_{N+1} \underbrace{(\tilde{h}_0(j) \cdots \tilde{h}_0(k))}_{N+1} \mathcal{B}_N(2t - k) \\ &= 2 \sum_{k \in \mathbb{Z}} \tilde{h}_N(k) \mathcal{B}_N(2t - k) \end{aligned}$$

The second part follows trivially from a rearrangement of lemma 8.5 and the third part is lemma 8.5. ■

Theorem 8.1 (B-Spline Representation Theorem)

Define $\mathcal{B}_{N,p}^s(t) := 2^{\frac{s}{2}} \mathcal{B}_N(2^s t - p)$ to be a dilated and translated B-Spline at the scale $s \in \mathbb{Z}$ and at the position $p \in \mathbb{Z}$. For any $\alpha \in \mathbb{Z}^+$, the B-spline, $\mathcal{B}_{N,p}^s(t)$, can be represented as follows:

$$\mathcal{B}_{N,p}^s(t) = 2^{\frac{s-\alpha(N-1)}{2}} \sum_{k \in \mathbb{Z}} \check{h}_{N+\alpha}(k) \mathcal{B}_N(2^{s+\alpha} t - 2^\alpha p - k) \quad (8.16)$$

$$\text{where: } \check{h}_{N+\alpha}(k) := \begin{cases} h_N(\frac{k}{2^{\alpha-1}}) * \cdots * h_N(\frac{k}{2}) * h_N(k), & \text{if } \alpha > 0 \\ \delta_{k,0}, & \text{if } \alpha = 0 \end{cases};$$

$h_N(k) := \underbrace{h_0(k) * h_0(k) * \dots * h_0(k)}_{N+1}$, which is a vector of length $N + 2$.

Proof: Define two cases. For Case 1, let $\alpha = 0$. Equation 8.16 reduces simply to the definition $B_{N,p}^s(t) := 2^{\frac{s}{2}} B_N(2^s t - p)$. For Case 2, let $\alpha > 0$. Now use the B-spline dilation equation 8.13 on the B-spline, $B_{N,p}^s(t)$, and repeat this process on each successive, equivalent B-spline term a total of α times, and use lemma 8.3 to yield:

$$\begin{aligned} B_{N,p}^s(t) &= 2^{\frac{s-(N-1)}{2}} \sum_{k \in \mathbb{Z}} h_N(k) B_N(2^{s+1}t - 2p - k) \\ &= 2^{\frac{s-\alpha(N-1)}{2}} \underbrace{\sum_{i \in \mathbb{Z}} h_N(i) \dots \sum_{j \in \mathbb{Z}} h_N(j) \sum_{k \in \mathbb{Z}} h_N(k)}_{\alpha} \\ &\quad B_N(2^{s+\alpha}t - 2^\alpha p - 2^{\alpha-1}i - \dots - 2j - k) \end{aligned} \quad (8.17)$$

Now let $k = 2^{\alpha-1}i + \dots + 2j + k$ in equation 8.17, then let $2k = k$, rearrange the order of the summations, and consolidate the convolution term yielding:

$$\begin{aligned} &2^{\frac{s-\alpha(N-1)}{2}} \underbrace{\sum_{i \in \mathbb{Z}} h_N(i) \dots \sum_{j \in \mathbb{Z}} h_N(j) \sum_{k \in \mathbb{Z}} h_N(k)}_{\alpha} \\ &\quad B_N(2^{s+\alpha}t - 2^\alpha p - 2^{\alpha-1}i - \dots - 2j - k) \\ &= 2^{\frac{s-\alpha(N-1)}{2}} \underbrace{\sum_{i \in \mathbb{Z}} h_N(i) \dots \sum_{j \in \mathbb{Z}} h_N(j) \sum_{k \in \mathbb{Z}} h_N(k - 2^{\alpha-1}i - \dots - 2j)}_{\alpha} \\ &\quad B_N(2^{s+\alpha}t - 2^\alpha p - k) \\ &= 2^{\frac{s-\alpha(N-1)}{2}} \underbrace{\sum_{i \in \mathbb{Z}} h_N(i) \dots \sum_{k \in \mathbb{Z}} \sum_{j \in \mathbb{Z}} h_N(j) h_N(2k - 2^{\alpha-1}i - \dots - 2j)}_{\alpha} \\ &\quad B_N(2^{s+\alpha}t - 2^\alpha p - 2k) \\ &= 2^{\frac{s-\alpha(N-1)}{2}} \underbrace{\sum_{i \in \mathbb{Z}} h_N(i) \dots \sum_{k \in \mathbb{Z}} h_N(k) * h_N(2k - 2^{\alpha-1}i - \dots - 2j)}_{\alpha-1} \\ &\quad B_N(2^{s+\alpha}t - 2^\alpha p - 2k) \end{aligned} \quad (8.18)$$

Repeating the above procedure on equation 8.18 another $\alpha - 2$ times, and then letting $k = 2^{\alpha-1}k$ yields the desired result:

$$\begin{aligned} &2^{\frac{s-\alpha(N-1)}{2}} \underbrace{\sum_{i \in \mathbb{Z}} h_N(i) \dots \sum_{k \in \mathbb{Z}} h_N(k) * h_N(2k - 2^{\alpha-1}i - \dots - 2j)}_{\alpha-1} \\ &\quad B_N(2^{s+\alpha}t - 2^\alpha p - 2k) \end{aligned}$$

$$\begin{aligned}
&= 2^{\frac{s-\alpha(N-1)}{2}} \sum_{k \in \mathbb{Z}} \underbrace{h_N(k) * \dots * h_N(2^{\alpha-2}k) * h_N(2^{\alpha-1}k)}_{\alpha} \\
&\quad \mathcal{B}_N(2^{s+\alpha}t - 2^\alpha p - 2^{\alpha-1}k) \\
&= 2^{\frac{s-\alpha(N-1)}{2}} \sum_{k \in \mathbb{Z}} \underbrace{h_N(\frac{k}{2^{\alpha-1}}) * \dots * h_N(\frac{k}{2}) * h_N(k)}_{\alpha} \\
&\quad \mathcal{B}_N(2^{s+\alpha}t - 2^\alpha p - k) \\
&= 2^{\frac{s-\alpha(N-1)}{2}} \sum_{k \in \mathbb{Z}} \check{h}_{N+\alpha}(k) \mathcal{B}_N(2^{s+\alpha}t - 2^\alpha p - k)
\end{aligned}$$

where

$$\check{h}_{N+\alpha}(k) := \begin{cases} h_N(\frac{k}{2^{\alpha-1}}) * \dots * h_N(\frac{k}{2}) * h_N(k), & \text{if } \alpha > 0 \\ \delta_{k,0}, & \text{if } \alpha = 0 \end{cases} \quad \blacksquare$$

Lemma 8.8

Given two B-Splines, $\mathcal{B}_N(2^{s_1}t - p_1)$ and $\mathcal{B}_M(2^{s_2}t - p_2)$, at the scales s_1 and s_2 respectively, assume, without loss of generality, that $s_1 \geq s_2$. The convolution of these two B-splines is given as follows:

$$\begin{aligned}
&\mathcal{B}_N(2^{s_1}t - p_1) * \mathcal{B}_M(2^{s_2}t - p_2) = \\
&\quad 2^{-\frac{(s_1-s_2)M+s_1+s_2}{2}} \sum_{k \in \mathbb{Z}} \check{h}_{M+s_1-s_2}(k) \mathcal{B}_{N+M+1}(2^{s_1}t - 2^{s_1-s_2}p_2 - p_1 - k) \quad (8.19)
\end{aligned}$$

$$\text{where } \check{h}_{M+s_1-s_2}(k) := \begin{cases} h_M(\frac{k}{2^{s_1-s_2-1}}) * \dots * h_M(\frac{k}{2}) * h_M(k), & \text{if } s_1 > s_2 \\ \delta_{k,0}, & \text{if } s_1 = s_2 \end{cases}.$$

Proof: Define two cases. For Case 1, let $s_1 = s_2$. This result is simply lemma 8.3. For Case 2, let $s_1 > s_2$. Start by using the B-spline representation theorem, theorem 8.1, on the second B-spline, $\mathcal{B}_M(2^{s_2}t - p_2)$, with $\alpha = s_1 - s_2$, and use lemma 8.3 to yield:

$$\begin{aligned}
&\mathcal{B}_N(2^{s_1}t - p_1) * \mathcal{B}_M(2^{s_2}t - p_2) = \mathcal{B}_N(2^{s_1}t - p_1) * \\
&\quad 2^{-\frac{(s_1-s_2)(M-1)}{2}} \sum_{k \in \mathbb{Z}} \check{h}_{M+s_1-s_2}(k) \mathcal{B}_M(2^{s_1}t - 2^{s_1-s_2}p_2 - k) \\
&= 2^{-\frac{(s_1-s_2)M+(s_1+s_2)}{2}} \sum_{k \in \mathbb{Z}} \check{h}_{M+s_1-s_2}(k) \mathcal{B}_{N+M+1}(2^{s_1}t - p_1 - 2^{s_1-s_2}p_2 - k) \quad \blacksquare
\end{aligned}$$

8.2 Generalized B-spline Packets

This section develops the theory leading to generalized B-spline packets. First, complementary B-splines are defined and a convolution lemma with B-splines is presented. Then generalized B-splines are defined, along with Haar wavelet packet splines and B-spline packets. Lastly, generalized B-spline packets are defined and a representation theorem is developed.

Definition 8.2 (Complementary B-splines)

The N th order complementary B-spline, $C_N(t)$, with knots contained in the set $\mathbb{Z}^+$ can be defined as follows:

$$\begin{aligned} C_0(t) &= (-1)^k \chi_{[0+\frac{1}{2}^*, 1/2+\frac{1}{2}^*)}(t), \quad \text{for } k = 0, 1 \\ C_N(t) &= C_{N-1}(t) * C_0(t) = \int_0^{1/2} C_{N-1}(t-x)dx - \int_{1/2}^1 C_{N-1}(t-x)dx \\ &= \int_{t-\frac{1}{2}}^t C_{N-1}(x)dx - \int_{t-1}^{t-\frac{1}{2}} C_{N-1}(x)dx \end{aligned} \quad (8.20)$$

It can be proven, using the same procedure detailed above to derive the B-spline dilation equation, that the complementary B-splines satisfy the following equation:

$$C_N(t) = 2^{-\frac{N-1}{2}} \sum_{k \in \mathbb{Z}} g_N(k) B_N(2t - k) \quad (8.21)$$

where: $g_0(k) :=$ the Haar wavelet function coefficients, $g(k)$, presented in equation 7.1;

$$g_N(k) := \underbrace{g_0(k) * g_0(k) * \dots * g_0(k)}_{N+1}, \text{ which is a vector of length } N+2.$$

Remark 8.3 Note that $C_0(t)$ is simply the Haar wavelet function.

Remark 8.4 Definition 8.2 demonstrates that the N th order complementary B-spline, $C_N(t)$, is created by convolving $N+1$ Haar wavelet functions.

Remark 8.5 Equation 8.21 of Definition 8.2 demonstrates that the complementary B-splines satisfy a two-scale equation which is identical in form to the two-scale wavelet equation, equation 3.39.

Lemma 8.9

Given a complementary B-spline, $C_N(t)$, and a B-spline, $B_M(t)$, their convolution is given as follows:

$$C_N(t) * B_M(t) = 2^{-\frac{N+M}{2}} \sum_{k \in \mathbb{Z}} m_{N+M+1}(k) B_{N+M+1}(2t - k) \quad (8.22)$$

where $m_{N+M+1}(k) := h_M(k) * g_N(k)$.

Proof: Using equation 8.21 for $C_N(t)$ and equation 8.13 for $B_M(t)$, expanding, and applying lemma 8.4 gives the desired result as follows:

$$\begin{aligned} C_N(t) * B_M(t) &= \left(2^{-\frac{N-1}{2}} \sum_{k \in \mathbb{Z}} g_N(k) B_N(2t - k) \right) * \left(2^{-\frac{M-1}{2}} \sum_{l \in \mathbb{Z}} h_M(l) B_M(2t - l) \right) \\ &= 2^{-\frac{N+M-2}{2}} \sum_{k \in \mathbb{Z}} \sum_{l \in \mathbb{Z}} g_N(k) h_M(l) B_N(2t - k) * B_M(2t - l) \\ &= 2^{-\frac{N+M}{2}} \sum_{k \in \mathbb{Z}} m_{N+M+1}(k) B_{N+M+1}(2t - k) \end{aligned}$$

where $m_{N+M+1}(k) := h_M(k) * g_N(k)$. ■

Lemma 8.9 allows the following definition to be made.

Definition 8.3 (Generalized B-splines)

Let a generalized B-spline be represented symbolically by $\mathcal{W}_{N,\kappa_N}(t)$. For $N = 0$, make the following definitions:

$$\mathcal{W}_{0,0}(t) := 2^{\frac{1}{2}} \sum_{k \in \mathbb{Z}} h_0(k) \mathcal{B}_0(2t - k) = \mathcal{B}_0(t) \quad (8.23)$$

$$\mathcal{W}_{0,1}(t) := 2^{\frac{1}{2}} \sum_{k \in \mathbb{Z}} g_0(k) \mathcal{B}_0(2t - k) = \mathcal{C}_0(t) \quad (8.24)$$

Recalling definition 5.2, define the convolution sequence number, $\kappa_N \in \mathbb{Z}^+$ with $0 \leq \kappa_N \leq 2^{N+1} - 1$ and $\kappa_{N,k} \in \{0, 1\}$, for the N th order, generalized B-spline as follows:

$$\kappa_N := \sum_{k=0}^N \kappa_{N,k} 2^k = \{\kappa_{N,0} \cdots \kappa_{N,N}\} = \{\kappa_{N,k} : k \in \mathbb{Z}^+\} \quad (8.25)$$

Now the N th order, generalized B-spline, $\mathcal{W}_{N,\kappa_N}(t)$, for $N > 0$ with knots contained in the set $\mathbb{Z}^+$, can be defined as follows:

$$\mathcal{W}_{N,\kappa_N}(t) = \mathcal{W}_{N-1,\kappa_{N-1}}(t) * \mathcal{W}_{0,\kappa_0}(t) = 2^{-\frac{N-1}{2}} \sum_{k \in \mathbb{Z}} m_N(k) \mathcal{B}_N(2t - k) \quad (8.26)$$

$$\text{where: } \kappa_N := \begin{cases} \{ \{ \kappa_{N-1,0} \cdots \kappa_{N-1,N-1} \} 0 \}, & \text{if } \kappa_0 = 0 \\ \{ 1 \{ \kappa_{N-1,0} \cdots \kappa_{N-1,N-1} \} \}, & \text{if } \kappa_0 = 1 \end{cases};$$

$$m_N(k) := \begin{cases} m_{N-1}(k) * h_0(k), & \text{if } \kappa_0 = 0 \\ m_{N-1}(k) * g_0(k), & \text{if } \kappa_0 = 1 \end{cases}.$$

Remark 8.6 Note that $\mathcal{B}_N(t)$ of equation 8.13 is given by $\mathcal{B}_N(t) = \mathcal{W}_{N,0}(t)$ and $\mathcal{C}_N(t)$ of equation 8.2 is given by $\mathcal{C}_N(t) = \mathcal{W}_{N,2^{N+1}-1}(t)$.

Remark 8.7 Due to the commutative property of the convolution operator, the convolution sequence number, κ_N , is not unique and can be arbitrarily defined. In order to avoid this ambiguity, the structure presented in definition 8.3 will be imposed. This structure for determining the convolution sequence number, κ_N , results in the smallest value being chosen out of all of its potential values. For example, let $\mathcal{W}_{N-1,\kappa_{N-1}}(t) = \mathcal{C}_{0,1}(t)$ and let $\kappa_0 = 0$, which yields the function $\mathcal{W}_{1,\kappa_1}(t) = \mathcal{C}_0(t) * \mathcal{B}_0(t) = \mathcal{B}_0(t) * \mathcal{C}_0(t)$. However, notice that the value for κ_1 is ambiguous, $\kappa_1 = 1$ or $\kappa_1 = 2$ are both valid. In order to avoid this ambiguity, the scheme in definition 8.3 is used, yielding $\kappa_1 = 1$.

Definition 8.4 (Haar Wavelet Packet Splines)

The N th order Haar wavelet packet spline, $\mathcal{W}_{N,f}(t)$, with knots contained in the set $\mathbb{Z}^+$ can be defined as follows:

$$\begin{aligned}\mathcal{W}_{0,f}(t) &= \psi_f(t) \\ \mathcal{W}_{N,f}(t) &= \mathcal{W}_{N-1,f}(t) * \mathcal{W}_{0,f}(t)\end{aligned}\tag{8.27}$$

where ψ_f is the Haar wavelet packet at the frequency f . The support of $\mathcal{W}_{N,f}(t)$ is given by:

$$\text{Supp}\{\mathcal{W}_{N,f}(t)\} = [0, N + 1]\tag{8.28}$$

Remark 8.8 Note that $\mathcal{B}_N(t)$ of equation 8.13 is given by $\mathcal{B}_N(t) = \mathcal{W}_{N,0}(t)$ and $\mathcal{C}_N(t)$ of equation 8.2 is given by $\mathcal{C}_N(t) = \mathcal{W}_{N,1}(t)$.

The two-scale, generalized B-spline equation, equation 8.3, can be further generalized to form the unit scale, B-spline packet equations as given by the following definition.

Definition 8.5 (Unit Scale B-spline Packets)

Let a B-spline packet be represented symbolically by $\mathcal{W}_{N,\kappa_N,f}(t)$. Define $\psi_f(t)$ to be a unit scale Haar wavelet packet. For $N = 0$, make the following definitions:

$$\mathcal{W}_{0,0,2f}(t) = 2^{\frac{1}{2}} \sum_{k \in \mathbb{Z}} h_0(k) \psi_f(2t - k)\tag{8.29}$$

$$\mathcal{W}_{0,1,2f+1}(t) = 2^{\frac{1}{2}} \sum_{k \in \mathbb{Z}} g_0(k) \psi_f(2t - k)\tag{8.30}$$

Define the convolution sequence number, $\kappa_N \in \mathbb{Z}^+$, in the same manner as was done previously in definition 8.3. The N th order, B-spline packet, $\mathcal{W}_{N,\kappa_N,f}(t)$, for $N > 0$ with knots contained in the set $\mathbb{Z}^+$, can be defined as follows:

$$\mathcal{W}_{N,\kappa_N,f_N}(t) = \mathcal{W}_{N-1,\kappa_{N-1},f_{N-1}}(t) * \mathcal{W}_{0,\kappa_0,f}(t) = 2^{-\frac{N-1}{2}} \sum_{k \in \mathbb{Z}} m_N(k) \mathcal{W}_{N,f}(2t - k)\tag{8.31}$$

$$\text{where: } \kappa_N := \begin{cases} \{ \{ \kappa_{N-1,0} \cdots \kappa_{N-1,N-1} \} 0 \}, & \text{if } \kappa_0 = 0 \\ \{ 1 \{ \kappa_{N-1,0} \cdots \kappa_{N-1,N-1} \} \}, & \text{if } \kappa_0 = 1 \end{cases};$$

$$f_N := \begin{cases} 2f, & \text{if } \kappa_0 = 0 \\ 2f + 1, & \text{if } \kappa_0 = 1 \end{cases};$$

$$m_N(k) := \begin{cases} m_{N-1}(k) * h_0(k), & \text{if } \kappa_0 = 0 \\ m_{N-1}(k) * g_0(k), & \text{if } \kappa_0 = 1 \end{cases};$$

$\mathcal{W}_{N,f}(t)$ is given by definition 8.4.

Remark 8.9 Note that $\mathcal{B}_N(t)$ of equation 8.13 is given by $\mathcal{B}_N(t) = \mathcal{W}_{N,0,0}(t)$ and $\mathcal{C}_N(t)$ of equation 8.2 is given by $\mathcal{C}_N(t) = \mathcal{W}_{N,2^{N+1}-1,1}(t)$.

Remark 8.10 Also observe that the generalized B-splines, $\mathcal{W}_{N,\kappa_N}(t)$, of definition 8.3 are given by either $\mathcal{W}_{N,\kappa_N}(t) = \mathcal{W}_{N,\kappa_N,0}(t)$ or $\mathcal{W}_{N,\kappa_N}(t) = \mathcal{W}_{N,\kappa_N,1}(t)$, depending on the value of $\kappa_0 \in \{0, 1\}$.

The unit scale B-spline packet equation 8.31 can be generalized for the scale $s \in \mathbb{Z}$ and for the position $p \in \mathbb{Z}$ with the following Corollary to Theorem 8.1.

Corollary 8.1 (Representation of B-Spline Packets)

Define $\mathcal{W}_{N,\kappa_N,f_N,p}^s(t) := 2^{\frac{s}{2}} \mathcal{W}_{N,\kappa_N,f_N}(2^s t - p)$ to be a dilated and translated B-spline packet at the scale $s \in \mathbb{Z}$ and at the position $p \in \mathbb{Z}$. For any $\alpha \in \mathbb{Z}^+$, the B-spline packet, $\mathcal{W}_{N,\kappa_N,f_N,p}^s(t)$, can be represented as follows:

$$\mathcal{W}_{N,\kappa_N,f_N,p}^s(t) = 2^{\frac{s-\alpha(N-1)}{2}} \sum_{k \in \mathbb{Z}} \check{m}_{N+\alpha}(k) \mathcal{W}_{N,f}(2^{s+\alpha} t - 2^\alpha p - k) \quad (8.32)$$

$$\text{where } \check{m}_{N+\alpha}(k) := \begin{cases} m_N(\frac{k}{2^{\alpha-1}}) * \dots * m_N(\frac{k}{2}) * m_N(k), & \text{if } \alpha > 0 \\ \delta_{k,0}, & \text{if } \alpha = 0 \end{cases},$$

κ_N and f_N are presented in Definition 8.5, and $\mathcal{W}_{N,f}$ is given in Definition 8.4.

Proof: Omitted since the proof is identical to that for Theorem 8.1 with $\mathcal{B}_{N,p}^s(t)$ and its corresponding elements replaced by $\mathcal{W}_{N,\kappa_N,f_N,p}^s(t)$ and its corresponding elements. ■

Remark 8.11 The support of $\mathcal{W}_{N,\kappa_N,f_N,p}^s(t)$ is given by:

$$\text{Supp}\{\mathcal{W}_{N,\kappa_N,f_N,p}^s(t)\} = [2^{-s}p, 2^{-s}(p + N + 1)] \quad (8.33)$$

Remark 8.12 Note that $\mathcal{W}_{N,\kappa_N,p}^s(t) := 2^{\frac{s}{2}} \mathcal{W}_{N,\kappa_N}(2^s t - p)$ is a dilated and translated generalized B-spline at the scale $s \in \mathbb{Z}$ and at the position $p \in \mathbb{Z}$.

Remark 8.13 Note that Corollary 8.1 can be simplified for generalized b-splines, $\mathcal{W}_{N,\kappa_N,p}^s(t)$, by replacing $\mathcal{W}_{N,f}(2^{s+\alpha} t - 2^\alpha p - k)$ with $\mathcal{B}_N(2^{s+\alpha} t - 2^\alpha p - k)$.

The next theorem presents a representation theorem for generalized B-spline packet basis functions.

Theorem 8.2 (Generalized B-Spline Packet Representation Theorem)

Define $\mathcal{W}_{N,\kappa_N}(t) := \psi_{f_0,p_0}^{s_0}(t) * \dots * \psi_{f_N,p_N}^{s_N}(t)$ to be a generalized B-spline packet basis function of order N , i.e., the convolution of $N + 1$ Haar wavelet packet basis functions, $\psi_{f_k,p_k}^{s_k}(t)$. Represent the

frequencies of the individual Haar wavelet packet basis functions, $f_0 \in \mathbb{Z}^+, \dots, f_N \in \mathbb{Z}^+$, by their infinite binary expansions, $\{f_{0,n} : n \in \mathbb{Z}^+\}, \dots, \{f_{N,n} : n \in \mathbb{Z}^+\}$. Define

$$\Psi_N(t) := \{\psi_{f_0,p_0}^{s_0}(t), \dots, \psi_{f_N,p_N}^{s_N}(t)\} := \{\Psi_{N,0}(t), \dots, \Psi_{N,N}(t)\}$$

to be the entire, possibly redundant, ordered set of Haar wavelet packet basis functions contained in the generalized B-spline packet. Define

$$F_N := \{f_0, \dots, f_N\} := \{F_{N,0}, \dots, F_{N,N}\}$$

to be the entire, possibly redundant, ordered set of frequencies contained in the generalized B-spline packet. Similarly, define

$$S_N := \{s_0, \dots, s_N\} := \{S_{N,0}, \dots, S_{N,N}\}$$

to be the entire, possibly redundant, ordered set of scales contained in the generalized B-spline packet. Lastly, define

$$P_N := \{p_0, \dots, p_N\} := \{P_{N,0}, \dots, P_{N,N}\}$$

to be the entire, possibly redundant, ordered set of positions contained in the generalized B-spline packet. For any $\tilde{\alpha} \in \mathbb{Z}^+$, the generalized B-spline packet basis function, $\mathcal{W}_{N,\kappa_N}^s(t)$, can be represented as follows:

$$\begin{aligned} \mathcal{W}_{N,\kappa_N}(t) &= 2^{-\frac{\tilde{\alpha}(N-1)}{2}} \sum_{k \in \mathbb{Z}} m_N(k - \sum_{i=0}^N 2^{s\Delta_i} P_{N,i}) \mathcal{B}_N(2^{\tilde{\alpha}} t - k) \\ &= 2^{-\frac{\tilde{\alpha}(N-1)}{2}} \sum_{k \in \mathbb{Z}} m_N(k) \mathcal{B}_N(2^{\tilde{\alpha}} t - k - \sum_{i=0}^N 2^{s\Delta_i} P_{N,i}) \end{aligned} \quad (8.34)$$

where: $\tilde{\alpha} := \max(S_{N,k} + \lceil \log_2(F_{N,k} + 1) \rceil, \forall k = 0, \dots, N)$;

$$s\Delta_i := \tilde{\alpha} - S_{N,i}, \forall i = 0, \dots, N;$$

$$m_N(k) := \underbrace{\tilde{m}_{s\Delta_0}(k) * \dots * \tilde{m}_{s\Delta_N}(k)}_{N+1}, \text{ which is a vector of length } \sum_{i=0}^N 2^{s\Delta_i} - N;$$

$$\tilde{m}_{s\Delta_i}(k) := \begin{cases} q_0(\frac{k}{2^{s\Delta_i-1}}) * \dots * q_{s\Delta_i-2}(\frac{k}{2}) * q_{s\Delta_i-1}(k), & \text{if } s\Delta_i > 0 \\ \delta_{k,0}, & \text{if } s\Delta_i = 0 \end{cases};$$

$$q_n(k) = \begin{cases} h(k), & \text{if } f_{i_n} = 0 \\ g(k), & \text{if } f_{i_n} = 1 \end{cases};$$

$\{f_{i_n} : n \in \mathbb{Z}^+\}$ is the infinite binary expansion of the frequency, f_i , for $\psi_{f_i,p_i}^{s_i}(t)$.

Proof: The first step is to expand every Haar wavelet packet basis function composing $\mathcal{W}_{N,\kappa_N}(t)$ using the equivalent form of the orthonormal wavelet packet representation theorem, equation 7.21,

presented in remark 7.1, as follows:

$$\begin{aligned}
\Psi_{N,i}(t) &:= 2^{\frac{\tilde{\alpha}}{2}} \sum_{k=0}^{(2^{s\Delta_i}-1)} \tilde{m}_{s\Delta_i}(k) \mathcal{B}_0(2^{\tilde{\alpha}}t - 2^{s\Delta_i}P_{N,i} - k) \\
&:= 2^{\frac{\tilde{\alpha}}{2}} \sum_{k=0}^{(2^{s\Delta_i}-1)} \tilde{m}_{s\Delta_i}(k - 2^{s\Delta_i}p_i) \mathcal{B}_0(2^{\tilde{\alpha}}t - k)
\end{aligned} \tag{8.35}$$

Recall remark 7.2, which states that every compactly supported, Haar wavelet packet basis function with dilation factor 2 at any scale s , frequency f , or position p , $\psi_{f,p}^s(t)$, can be represented as a sum of zeroth order, dilated B-splines, $\psi_{\tilde{f}_\alpha}(t) = \mathcal{B}_0(2^{\tilde{\alpha}}t)$ with $\tilde{\alpha}$ determined as follows:

$$\tilde{\alpha} \geq s + [\log_2(f + 1)] \tag{8.36}$$

where $[x] = n$ with n denoting the greatest integer satisfying the relationship $(n - 1) < x \leq n$. In light of equation 8.36, define

$$\tilde{\alpha} := \max(S_{N,k} + [\log_2(F_{N,k} + 1)], \forall k = 0, \dots, N) \tag{8.37}$$

Observe that it is necessary to define $\tilde{\alpha}$ in this manner in order to ensure that all resultant B-splines, $\mathcal{B}_0(2^{\tilde{\alpha}}t)$, will be at the same scale. Also, define $s\Delta_i := \tilde{\alpha} - S_{N,i}$, $\forall i = 0, \dots, N$. After using equation 8.35 to expand each Haar wavelet packet basis function contained in $\mathcal{W}_{N,\kappa_N}(t)$, apply lemmas 8.2 and 8.7 to give the desired result:

$$\begin{aligned}
\mathcal{W}_{N,\kappa_N}(t) &= \psi_{f_0,p_0}^{s_0}(t) * \dots * \psi_{f_N,p_N}^{s_N}(t) \\
&= 2^{\frac{\tilde{\alpha}(N+1)}{2}} \underbrace{\sum_{i \in \mathbb{Z}} \dots \sum_{j \in \mathbb{Z}}}_{N+1} \underbrace{(\tilde{m}_{s\Delta_0}(i - 2^{s\Delta_0}p_0) \dots \tilde{m}_{s\Delta_N}(j - 2^{s\Delta_N}p_N))}_{N+1} \\
&\quad \underbrace{[\mathcal{B}_0(2^{\tilde{\alpha}}t - i) * \dots * \mathcal{B}_0(2^{\tilde{\alpha}}t - j)]}_{N+1} \\
&= 2^{-\frac{\tilde{\alpha}(N-1)}{2}} \sum_{k \in \mathbb{Z}} m_N(k - \sum_{i=0}^N 2^{s\Delta_i}P_{N,i}) \mathcal{B}_N(2^{\tilde{\alpha}}t - k) \\
&= 2^{-\frac{\tilde{\alpha}(N-1)}{2}} \sum_{k \in \mathbb{Z}} m_N(k) \mathcal{B}_N(2^{\tilde{\alpha}}t - k - \sum_{i=0}^N 2^{s\Delta_i}P_{N,i}) \quad \blacksquare
\end{aligned}$$

Remark 8.14 It should be noted that the only case in which $s\Delta_i = 0$ is when $\psi_{f_k,p_k}^{s_k}(t)$ is a B-spline and $\tilde{\alpha} = s_k$.

Several examples of generalized B-spline packet basis functions will now be presented. Figure 8.1 shows the generalized B-spline packet basis functions for $N = 0$. In figure 8.1, (a) is the Haar scaling function, $\mathcal{W}_{0,0}(t)$, and (b) is the Haar wavelet function, $\mathcal{W}_{0,1}(t)$. Figure 8.2 presents the generalized B-spline packet basis functions for $N = 1$. For figure 8.2, (a) is the convolution of two Haar scaling

functions, $\mathcal{W}_{1,0}(t)$, (b) is the convolution of two Haar wavelet functions, $\mathcal{W}_{1,3}(t)$, and (c) is the convolution of a Haar scaling function and a Haar wavelet function, $\mathcal{W}_{1,1}(t)$. Figure 8.3 presents the generalized B-spline packet basis functions for $N = 2$. In figure 8.3, (a) is the convolution of three Haar scaling functions, $\mathcal{W}_{2,0}(t)$, (b) is the convolution of three Haar wavelet functions, $\mathcal{W}_{2,7}(t)$, and (c) is the convolution of a two Haar scaling functions and a Haar wavelet function, $\mathcal{W}_{2,1}(t)$, and (d) is the convolution of two Haar wavelet functions and a Haar scaling function, $\mathcal{W}_{2,3}(t)$.

Figure 8.1: (a) Plot of $\mathcal{W}_{0,0}(t)$, (b) Plot of $\mathcal{W}_{0,1}(t)$

(a)

(b)

(c)

Figure 8.2: (a) Plot of $w_{1,0}(t)$, (b) Plot of $w_{1,3}(t)$, (c) Plot of $w_{1,1}(t)$

Figure 8.3: (a) Plot of $W_{2,0}(t)$, (b) Plot of $W_{2,7}(t)$, (c) Plot of $W_{2,1}(t)$, (d) Plot of $W_{2,3}(t)$

8.3 Generalized B-spline Packet Inner Products

This section develops some of the necessary computation tools in order to utilize wavelet packet theory in control theory. This section presents several inner product theorems. First, an inner product theorem between two B-splines is developed. Then an inner product theorem between a complementary B-spline and a B-spline is demonstrated. A dilated B-spline inner product theorem is given. Next, a generalized B-spline inner product theorem is provided. Lastly, the inner product between two generalized B-spline packet basis functions is evaluated.

The following theorem gives a closed form solution for the inner product between two B-splines of arbitrary order. The inner product between two N th order B-splines was stated previously in [42], [45], and [34].

Theorem 8.3 (B-Spline Inner Product Formula)

The inner product between two B-splines of arbitrary orders, $B_N(t - i)$ and $B_M(t - j)$, is given by the following formula:

$$\langle B_N(t - i), B_M(t - j) \rangle = B_{N+M+1}(N + 1 + i - j) = B_{N+M+1}(M + 1 + j - i) \quad (8.38)$$

Proof:

$$\begin{aligned} \langle B_N(\tau - i), B_M(\tau - j) \rangle &= \int_{-\infty}^{\infty} B_N(\tau - i) \overline{B_M(\tau - j)} d\tau \\ &= \int_{-\infty}^{\infty} B_N(\tau - i + j) B_M(\tau) d\tau \\ &= \int_{-\infty}^{\infty} B_N(\tau) B_M(\tau - j + i) d\tau \end{aligned} \quad (8.39)$$

Using the following relationship, which is due to the even symmetry and finite support of B-splines,

$$B_K(\tau - n) = B_K(K + 1 + n - \tau) \quad (8.40)$$

on equation 8.39 and letting $l = i - j$ gives:

$$\int_{-\infty}^{\infty} B_N(\tau - l) B_M(\tau) d\tau = \int_{-\infty}^{\infty} B_N(N + 1 + l - \tau) B_M(\tau) d\tau \quad (8.41)$$

$$\int_{-\infty}^{\infty} B_N(\tau) B_M(\tau + l) d\tau = \int_{-\infty}^{\infty} B_N(\tau) B_M(M + 1 - l - \tau) d\tau \quad (8.42)$$

Applying lemma 8.3 to equations 8.41 - 8.42 to yield the desired result:

$$\begin{aligned} \int_{-\infty}^{\infty} B_N(\tau - l) B_M(\tau) d\tau &= B_{N+M+1}(N + 1 + i - j) \\ \int_{-\infty}^{\infty} B_N(\tau) B_M(\tau + l) d\tau &= B_{N+M+1}(M + 1 + j - i) \quad \blacksquare \end{aligned}$$

Remark 8.15 For $N = M$, theorem 8.3 emphasizes the even symmetry of the B-spline, $B_{2N+1}(\bullet)$, about its midpoint $N + 1$.

Remark 8.16 The evaluation of the k th order B-spline, $B_k(x)$ with $k \in \mathbb{N}$ and $x \in \mathbb{R}$, can be easily computed through the use of the following recurrence relation for B-splines [46]:

$$B_k(x) = \frac{x}{k} B_{k-1}(x) + \frac{k+1-x}{k} B_{k-1}(x-1) \quad (8.43)$$

The next lemma gives a simple, closed form solution for the inner product between a B-spline and a complementary B-spline of arbitrary orders.

Lemma 8.10 (B-Spline / Complementary B-Spline Inner Product Formula)

Given a complementary B-spline, $C_N(t-i)$, and a B-spline, $B_M(t-j)$, their inner product is given as follows:

$$\begin{aligned} \langle C_N(t-i), B_M(t-j) \rangle &= 2^{-\frac{N+M}{2}} \sum_{k \in \mathbb{Z}} c_{N+M+1}(k) B_{N+M+1}(N+1+2(i-j)+k) \\ &= 2^{-\frac{N+M}{2}} \sum_{k \in \mathbb{Z}} \tilde{c}_{N+M+1}(k) B_{N+M+1}(M+1+2(j-i)+k) \end{aligned} \quad (8.44)$$

where $\left\{ \begin{array}{l} c_{N+M+1}(k) := g_N(k) * h_M(-k) \\ \tilde{c}_{N+M+1}(k) := h_M(k) * g_N(-k) \end{array} \right\}$, are vectors of length $N+M-1$.

Proof: Start by representing the B-spline, $B_M(\tau-j)$, using the dilation equation, equation 8.13, and representing the complementary B-spline, $C_N(\tau-i)$, using equation 8.21, switch the order of summation and integration, and apply lemma 8.1 giving:

$$\begin{aligned} \langle C_N(\tau-i), B_M(\tau-j) \rangle &= \int_{-\infty}^{\infty} C_N(\tau-i) \overline{B_M(\tau-j)} d\tau \\ &= \int_{-\infty}^{\infty} C_N(\tau-i+j) B_M(\tau) d\tau \\ &= \int_{-\infty}^{\infty} C_N(\tau) B_M(\tau-j+i) d\tau \\ &= \int_{-\infty}^{\infty} \left(2^{-\frac{N-1}{2}} \sum_{k \in \mathbb{Z}} g_N(k) B_N(2\tau-2i-k) \right) \\ &\quad \left(2^{-\frac{M-1}{2}} \sum_{l \in \mathbb{Z}} h_M(l) B_M(2\tau-2j-l) \right) d\tau \\ &= 2^{-\frac{N+M}{2}} \sum_{k \in \mathbb{Z}} \sum_{l \in \mathbb{Z}} g_N(k) h_M(l) \\ &\quad \int_{-\infty}^{\infty} B_N(\tau-2i+2j-k+l) B_M(\tau) d\tau \end{aligned} \quad (8.45)$$

$$\begin{aligned}
&= 2^{-\frac{N+M}{2}} \sum_{k \in \mathbb{Z}} \sum_{l \in \mathbb{Z}} g_N(k) h_M(l) \\
&\quad \int_{-\infty}^{\infty} B_N(\tau) B_M(\tau - 2j + 2i - l + k) d\tau
\end{aligned} \tag{8.46}$$

Use the B-spline relationship, equation 8.40, on the $B_N(\tau - 2(i - j) - k + l)$ term in equation 8.45, apply lemma 8.3, and let $k = k - l$, yielding the first result:

$$\begin{aligned}
&2^{-\frac{N+M}{2}} \sum_{k \in \mathbb{Z}} \sum_{l \in \mathbb{Z}} g_N(k) h_M(l) \int_{-\infty}^{\infty} B_N(\tau - 2i + 2j - k + l) B_M(\tau) d\tau \\
&= 2^{-\frac{N+M}{2}} \sum_{k \in \mathbb{Z}} \sum_{l \in \mathbb{Z}} g_N(k) h_M(l) \int_{-\infty}^{\infty} B_N(N + 1 + 2(i - j) + k - l - \tau) B_M(\tau) d\tau \\
&= 2^{-\frac{N+M}{2}} \sum_{k \in \mathbb{Z}} \sum_{l \in \mathbb{Z}} g_N(k) h_M(l) B_{N+M+1}(N + 1 + 2(i - j) + k - l) \\
&= 2^{-\frac{N+M}{2}} \sum_{k \in \mathbb{Z}} \sum_{l \in \mathbb{Z}} g_N(k + l) h_M(l) B_{N+M+1}(N + 1 + 2(i - j) + k) \\
&= 2^{-\frac{N+M}{2}} \sum_{k \in \mathbb{Z}} c_{N+M+1}(k) B_{N+M+1}(N + 1 + 2(i - j) + k)
\end{aligned}$$

where $c_{N+M+1}(k) := \sum_{l \in \mathbb{Z}} g_N(k + l) h_M(l) = g_N(k) * h_M(-k)$. The second result follows from using the B-spline relationship, equation 8.40, on the $B_M(\tau - 2(j - i) - l + k)$ term in equation 8.46, applying lemma 8.3, and letting $l = l - k$:

$$\begin{aligned}
&2^{-\frac{N+M}{2}} \sum_{k \in \mathbb{Z}} \sum_{l \in \mathbb{Z}} g_N(k) h_M(l) \int_{-\infty}^{\infty} B_N(\tau) B_M(\tau - 2(j - i) - l + k) d\tau \\
&= 2^{-\frac{N+M}{2}} \sum_{k \in \mathbb{Z}} \sum_{l \in \mathbb{Z}} g_N(k) h_M(l) \int_{-\infty}^{\infty} B_N(\tau) B_M(M + 1 + 2(j - i) + l - k - \tau) d\tau \\
&= 2^{-\frac{N+M}{2}} \sum_{k \in \mathbb{Z}} \sum_{l \in \mathbb{Z}} g_N(k) h_M(l) B_{N+M+1}(M + 1 + 2(j - i) + l - k) \\
&= 2^{-\frac{N+M}{2}} \sum_{l \in \mathbb{Z}} \sum_{k \in \mathbb{Z}} g_N(k) h_M(l + k) B_{N+M+1}(N + 1 + 2(j - i) + l) \\
&= 2^{-\frac{N+M}{2}} \sum_{l \in \mathbb{Z}} \tilde{c}_{N+M+1}(l) B_{N+M+1}(N + 1 + 2(j - i) + l)
\end{aligned}$$

where $\tilde{c}_{N+M+1}(k) := \sum_{l \in \mathbb{Z}} g_N(l) h_M(k + l) = h_M(k) * g_N(-k)$. ■

Remark 8.17 Note that replacing the complementary B-spline, $C_N(t - i)$, in lemma 8.10 by a regular B-spline, $B_N(t - i)$, results in the following equivalent representation for the inner product between two B-splines given by Theorem 8.3:

$$\begin{aligned}
\langle B_N(t - i), B_M(t - j) \rangle &= 2^{-\frac{N+M}{2}} \sum_{k \in \mathbb{Z}} c_{N+M+1}(k) B_{N+M+1}(N + 1 + 2(i - j) + k) \\
&= 2^{-\frac{N+M}{2}} \sum_{k \in \mathbb{Z}} \tilde{c}_{N+M+1}(k) B_{N+M+1}(M + 1 + 2(j - i) + k) \\
&= B_{N+M+1}(N + 1 + i - j) = B_{N+M+1}(M + 1 + j - i)
\end{aligned} \tag{8.47}$$

where $\left\{ \begin{array}{l} c_{N+M+1}(k) := h_N(k) * h_M(-k) \\ \tilde{c}_{N+M+1}(k) := h_M(k) * h_N(-k) \end{array} \right\}$, which are vectors of length $N+M-1$.

The next theorem presents an explicit formula for the inner product of any two compactly supported, B-splines at different scales with dilation factor 2.

Theorem 8.4 (Dilated B-Spline Inner Product Formula)

The inner product between two B-splines of arbitrary orders and of arbitrary scales with dilation factor 2, $B_{N,p1}^{s1}(t)$ and $B_{M,p2}^{s2}(t)$, assuming without loss of generality that $s1 \geq s2$, is given by the following formula:

$$\begin{aligned} & \langle B_{N,p1}^{s1}(t), B_{M,p2}^{s2}(t) \rangle \\ &= 2^{-\frac{(s1-s2)M}{2}} \sum_{k \in \mathbb{Z}} \check{h}_{M+s1-s2}(k) B_{N+M+1}(N+1+p1-2^{s1-s2}p2-k) \end{aligned} \quad (8.48)$$

$$= 2^{-\frac{(s1-s2)M}{2}} \sum_{k \in \mathbb{Z}} \check{h}_{M+s1-s2}(k) B_{N+M+1}(M+1+2^{s1-s2}p2+k-p1) \quad (8.49)$$

$$\text{where } \check{h}_{M+s1-s2}(k) := \begin{cases} h_M(\frac{k}{2^{s1-s2}}) * \dots * h_M(\frac{k}{2}) * h_M(k), & \text{if } s1 > s2 \\ \delta_{k,0}, & \text{if } s1 = s2 \end{cases}.$$

Proof: Define two cases. For Case 1, let $s1 = s2$. This result is simply theorem 8.3. For Case 2, let $s1 > s2$. Start by using the B-spline representation theorem, theorem 8.1, on the second B-spline, $B_{M,p2}^{s2}(\tau)$, with $\alpha = s1 - s2$ to yield:

$$\begin{aligned} \langle B_{N,p1}^{s1}(t), B_{M,p2}^{s2}(t) \rangle &= \int_{-\infty}^{\infty} B_N(2^{s1}\tau - p1) \\ &\quad \left(2^{\frac{s1+s2-(s1-s2)(M-1)}{2}} \sum_{k \in \mathbb{Z}} \check{h}_{M+s1-s2}(k) B_M(2^{s1}\tau - 2^{s1-s2}p2 - k) \right) d\tau \\ &= 2^{\frac{s1+s2-(s1-s2)(M-1)}{2}} \sum_{k \in \mathbb{Z}} \check{h}_{M+s1-s2}(k) \int_{-\infty}^{\infty} B_N(2^{s1}\tau - p1) B_M(2^{s1}\tau - 2^{s1-s2}p2 - k) d\tau \\ &= 2^{-\frac{(s1-s2)M}{2}} \sum_{k \in \mathbb{Z}} \check{h}_{M+s1-s2}(k) \int_{-\infty}^{\infty} B_N(\tau - p1) B_M(\tau - 2^{s1-s2}p2 - k) d\tau \\ &= 2^{-\frac{(s1-s2)M}{2}} \sum_{k \in \mathbb{Z}} \check{h}_{M+s1-s2}(k) \int_{-\infty}^{\infty} B_N(\tau - p1 + 2^{s1-s2}p2 + k) B_M(\tau) d\tau \end{aligned} \quad (8.50)$$

$$= 2^{-\frac{(s1-s2)M}{2}} \sum_{k \in \mathbb{Z}} \check{h}_{M+s1-s2}(k) \int_{-\infty}^{\infty} B_N(\tau) B_M(\tau - 2^{s1-s2}p2 - k + p1) d\tau \quad (8.51)$$

Use the following relationship, which is due to the even symmetry and finite support of B-splines,

$$B_K(2^\alpha \tau - n) = B_K(K+1+n-2^\alpha \tau) \quad (8.52)$$

on equations 8.50-8.51, let $n = p1 - 2^{s1-s2}p2 - k$, and apply lemma 8.3 to yield the desired results:

$$2^{-\frac{(s1-s2)M}{2}} \sum_{n \in \mathbb{Z}} \check{h}_{M+s1-s2}(n) \int_{-\infty}^{\infty} B_N(\tau - n) B_M(\tau) d\tau$$

$$\begin{aligned}
&= 2^{-\frac{(s_1-s_2)M}{2}} \sum_{n \in \mathbb{Z}} \check{h}_{M+s_1-s_2}(n) \int_{-\infty}^{\infty} B_N(N+1+n-\tau) B_M(\tau) d\tau \\
&= 2^{-\frac{(s_1-s_2)M}{2}} \sum_{k \in \mathbb{Z}} \check{h}_{M+s_1-s_2}(k) B_{N+M+1}(N+1+p_1-2^{s_1-s_2}p_2-k) \quad (8.53) \\
&2^{-\frac{(s_1-s_2)M}{2}} \sum_{n \in \mathbb{Z}} \check{h}_{M+s_1-s_2}(n) \int_{-\infty}^{\infty} B_N(\tau) B_M(\tau-n) d\tau \\
&= 2^{-\frac{(s_1-s_2)M}{2}} \sum_{n \in \mathbb{Z}} \check{h}_{M+s_1-s_2}(n) \int_{-\infty}^{\infty} B_N(\tau) B_M(M+1-n-\tau) d\tau \\
&= 2^{-\frac{(s_1-s_2)M}{2}} \sum_{k \in \mathbb{Z}} \check{h}_{M+s_1-s_2}(k) B_{N+M+1}(M+1+2^{s_1-s_2}p_2+k-p_1) \quad \blacksquare
\end{aligned}$$

The next theorem presents an explicit formula for the inner product of any two compactly supported, generalized B-splines at different scales with dilation factor 2.

Theorem 8.5 (Generalized B-Spline Inner Product Formula)

The inner product between two generalized B-splines of arbitrary orders and of arbitrary scales with dilation factor 2, $\mathcal{W}_{N,\kappa_N,p_1}^{s_1}(t)$ and $\mathcal{W}_{M,\kappa_M,p_2}^{s_2}(t)$, assuming without loss of generality that $s_1 \geq s_2$, is given by the following formula:

$$\langle \mathcal{W}_{N,\kappa_N,p_1}^{s_1}(t), \mathcal{W}_{M,\kappa_M,p_2}^{s_2}(t) \rangle \quad (8.54)$$

$$= 2^{-\frac{(s_1-s_2)M+N+M}{2}} \sum_{k \in \mathbb{Z}} c_{N+M+1}(k) B_{N+M+1}(N+1+p_1-2^{s_1-s_2}p_2-k) \quad (8.55)$$

$$= 2^{-\frac{(s_1-s_2)M+N+M}{2}} \sum_{k \in \mathbb{Z}} \tilde{c}_{N+M+1}(k) B_{N+M+1}(M+1+2^{s_1-s_2}p_2+k-p_1) \quad (8.56)$$

$$\begin{aligned}
\text{where: } c_{N+M+1}(k) &:= \begin{cases} \check{m}_{N+1}(k) * \check{m}_{M+s_1-s_2}(-k), & \text{if } s_1 > s_2 \\ m_N(k) * m_M(-k), & \text{if } s_1 = s_2 \end{cases}; \\
\tilde{c}_{N+M+1}(k) &:= \begin{cases} \check{m}_{M+s_1-s_2}(k) * \check{m}_{N+1}(-k), & \text{if } s_1 > s_2 \\ m_M(k) * m_N(-k), & \text{if } s_1 = s_2 \end{cases}; \\
\check{m}_{K+\alpha}(k) &:= m_K(\frac{k}{2^{\alpha-1}}) * \dots * m_K(\frac{k}{2}) * m_K(k) \text{ if } \alpha > 0; \\
m_K(k) &:= \begin{cases} m_{K-1}(k) * h_0(k), & \text{if } \kappa_{K,K} = 0 \\ m_{K-1}(k) * g_0(k), & \text{if } \kappa_{K,K} = \kappa_{K-1,K-1} \end{cases}.
\end{aligned}$$

Proof: Define two cases. For Case 1, let $s_1 = s_2$. This result is simply lemma 8.10 with $g_N(k)$ replaced by $m_N(k)$ and $h_M(k)$ replaced by $m_M(k)$. For Case 2, let $s_1 > s_2$. Start by using the representation of B-spline packets, Corollary 8.1, on both B-spline packets with $\alpha = 1$ for the first B-spline packet and $\alpha = s_1 - s_2 + 1$ for the second B-spline packet to yield:

$$\begin{aligned}
\langle \mathcal{W}_{N,\kappa_N,p_1}^{s_1}(t), \mathcal{W}_{M,\kappa_M,p_2}^{s_2}(t) \rangle &= \int_{-\infty}^{\infty} \left(2^{\frac{s_1-(N-1)}{2}} \sum_{k \in \mathbb{Z}} \check{m}_{N+1}(k) B_N(2^{s_1+1}\tau - 2p_1 - k) \right) \\
&\quad \left(2^{\frac{s_2-(s_1-s_2+1)(M-1)}{2}} \sum_{l \in \mathbb{Z}} \check{m}_{M+s_1-s_2}(l) B_M(2^{s_1+1}\tau - 2^{s_1-s_2+1}p_2 - l) \right) d\tau
\end{aligned}$$

$$\begin{aligned}
&= 2^{\frac{s_1+s_2-(N-1)-(s_1-s_2+1)(M-1)}{2}} \sum_{k \in \mathbb{Z}} \sum_{l \in \mathbb{Z}} \check{m}_{N+1}(k) \check{m}_{M+s_1-s_2}(l) \\
&\quad \int_{-\infty}^{\infty} B_N(2^{s_1+1}\tau - 2p_1 - k) B_M(2^{s_1+1}\tau - 2^{s_1-s_2+1}p_2 - l) d\tau \\
&= 2^{-\frac{(s_1-s_2)M+N+M}{2}} \sum_{k \in \mathbb{Z}} \sum_{l \in \mathbb{Z}} \check{m}_{N+1}(k) \check{m}_{M+s_1-s_2}(l) \\
&\quad \int_{-\infty}^{\infty} B_N(\tau - 2p_1 - k) B_M(\tau - 2^{s_1-s_2+1}p_2 - l) d\tau \\
&= 2^{-\frac{(s_1-s_2)M+N+M}{2}} \sum_{k \in \mathbb{Z}} \sum_{l \in \mathbb{Z}} \check{m}_{N+1}(k) \check{m}_{M+s_1-s_2}(l) \\
&\quad \int_{-\infty}^{\infty} B_N(\tau - 2p_1 + 2^{s_1-s_2+1}p_2 - k + l) B_M(\tau) d\tau \tag{8.57} \\
&= 2^{-\frac{(s_1-s_2)M+N+M}{2}} \sum_{k \in \mathbb{Z}} \sum_{l \in \mathbb{Z}} \check{m}_{N+1}(k) \check{m}_{M+s_1-s_2}(l) \\
&\quad \int_{-\infty}^{\infty} B_N(\tau) B_M(\tau - 2^{s_1-s_2+1}p_2 + 2p_1 - l + k) d\tau \tag{8.58}
\end{aligned}$$

Use the B-spline relationship, equation 8.52, on equation 8.57, apply lemma 8.3, and let $k = k - l$ to yield the first result:

$$\begin{aligned}
&2^{-\frac{(s_1-s_2)M+N+M}{2}} \sum_{k \in \mathbb{Z}} \sum_{l \in \mathbb{Z}} \check{m}_{N+1}(k) \check{m}_{M+s_1-s_2}(l) \\
&\quad \int_{-\infty}^{\infty} B_N(\tau - 2p_1 + 2^{s_1-s_2+1}p_2 - k + l) B_M(\tau) d\tau \\
&= 2^{-\frac{(s_1-s_2)M+N+M}{2}} \sum_{k \in \mathbb{Z}} \sum_{l \in \mathbb{Z}} \check{m}_{N+1}(k) \check{m}_{M+s_1-s_2}(l) \\
&\quad \int_{-\infty}^{\infty} B_N(N+1+2p_1-2^{s_1-s_2+1}p_2+k-l-\tau) B_M(\tau) d\tau \\
&= 2^{-\frac{(s_1-s_2)M+N+M}{2}} \sum_{k \in \mathbb{Z}} \sum_{l \in \mathbb{Z}} \check{m}_{N+1}(k) \check{m}_{M+s_1-s_2}(l) B_{N+M+1}(N+1+2p_1-2^{s_1-s_2+1}p_2+k-l) \\
&= 2^{-\frac{(s_1-s_2)M+N+M}{2}} \sum_{k \in \mathbb{Z}} \sum_{l \in \mathbb{Z}} \check{m}_{N+1}(k+l) \check{m}_{M+s_1-s_2}(l) B_{N+M+1}(N+1+2p_1-2^{s_1-s_2+1}p_2+k) \\
&= 2^{-\frac{(s_1-s_2)M+N+M}{2}} \sum_{k \in \mathbb{Z}} c_{N+M+1}(k) B_{N+M+1}(N+1+2p_1-2^{s_1-s_2+1}p_2+k)
\end{aligned}$$

where $c_{N+M+1}(k) := \sum_{l \in \mathbb{Z}} \check{m}_{N+1}(k+l) \check{m}_{M+s_1-s_2}(l) = \check{m}_{N+1}(k) * \check{m}_{M+s_1-s_2}(-k)$. The second result follows from using the B-spline relationship, equation 8.52, on equation 8.58, applying lemma 8.3, and letting $l = l - k$:

$$\begin{aligned}
&2^{-\frac{(s_1-s_2)M+N+M}{2}} \sum_{k \in \mathbb{Z}} \sum_{l \in \mathbb{Z}} \check{m}_{N+1}(k) \check{m}_{M+s_1-s_2}(l) \\
&\quad \int_{-\infty}^{\infty} B_N(\tau) B_M(\tau - 2^{s_1-s_2+1}p_2 + 2p_1 - l + k) d\tau \\
&= 2^{-\frac{(s_1-s_2)M+N+M}{2}} \sum_{k \in \mathbb{Z}} \sum_{l \in \mathbb{Z}} \check{m}_{N+1}(k) \check{m}_{M+s_1-s_2}(l)
\end{aligned}$$

$$\begin{aligned}
& \int_{-\infty}^{\infty} B_N(\tau) B_M(M+1+2^{s_1-s_2+1}p_2-2p_1+l-k-\tau) d\tau \\
&= 2^{-\frac{(s_1-s_2)M+N+M}{2}} \sum_{k \in \mathbb{Z}} \sum_{l \in \mathbb{Z}} \tilde{m}_{N+1}(k) \tilde{m}_{M+s_1-s_2}(l) B_{N+M+1}(M+1+2^{s_1-s_2+1}p_2-2p_1+l-k) \\
&= 2^{-\frac{(s_1-s_2)M+N+M}{2}} \sum_{l \in \mathbb{Z}} \sum_{k \in \mathbb{Z}} \tilde{m}_{N+1}(k) \tilde{m}_{M+s_1-s_2}(l+k) B_{N+M+1}(M+1+2^{s_1-s_2+1}p_2-2p_1+l) \\
&= 2^{-\frac{(s_1-s_2)M+N+M}{2}} \sum_{l \in \mathbb{Z}} \tilde{c}_{N+M+1}(l) B_{N+M+1}(M+1+2^{s_1-s_2+1}p_2-2p_1+l)
\end{aligned}$$

where $\tilde{c}_{N+M+1}(k) := \sum_{l \in \mathbb{Z}} \tilde{m}_{N+1}(l) \tilde{m}_{M+s_1-s_2}(k+l) = \tilde{m}_{M+s_1-s_2}(k) * \tilde{m}_{N+1}(-k)$. ■

Remark 8.18 The generalized B-splines $\mathcal{W}_{N,\kappa_N,p_1}^{s_1}(t)$ and $\mathcal{W}_{M,\kappa_M,p_2}^{s_2}(t)$ can be represented as the convolution of $N+1$ and $M+1$ Haar wavelet basis functions respectively at arbitrary scales and positions. In other words, Theorem 8.5 provides an explicit formula for the inner product between two arbitrarily convolved Haar wavelet basis functions.

The next theorem presents an explicit formula for the inner product of any two compactly supported, B-spline packet basis functions at different scales with dilation factor 2.

Theorem 8.6 (Generalized B-Spline Packet Inner Product Formula)

Define $\mathcal{W}_{N,\kappa_N}(t) := \psi_{f_0,p_0}^{s_0}(t) * \dots * \psi_{f_N,p_N}^{s_N}(t)$ to be a generalized B-spline packet basis function of order N , i.e., the convolution of $N+1$ Haar wavelet packet basis functions, $\psi_{f_k,p_k}^{s_k}(t)$. Define $\mathcal{W}_{M,\kappa_M}(t) := \psi_{f_{N+1},p_{N+1}}^{s_{N+1}}(t) * \dots * \psi_{f_{N+M+1},p_{N+M+1}}^{s_{N+M+1}}(t)$ to be another generalized B-spline packet basis function of order M . Define

$$\begin{aligned}
\Psi_{N+M+1}(t) &:= \{\psi_{f_0,p_0}^{s_0}(t), \dots, \psi_{f_N,p_N}^{s_N}(t), \psi_{f_{N+1},p_{N+1}}^{s_{N+1}}(t), \dots, \psi_{f_{N+M+1},p_{N+M+1}}^{s_{N+M+1}}(t)\} \\
&:= \{\Psi_{N+M+1,0}(t), \dots, \Psi_{N+M+1,N}(t), \Psi_{N+M+1,N+1}(t), \dots, \Psi_{N+M+1,N+M+1}(t)\}
\end{aligned}$$

to be the entire, possibly redundant, ordered set of Haar wavelet packet basis functions contained in both generalized B-spline packets. Define

$$\begin{aligned}
\mathbf{F}_{N+M+1} &:= \{f_0, \dots, f_N, f_{N+1}, \dots, f_{N+M+1}\} \\
&:= \{\mathbf{F}_{N+M+1,0}, \dots, \mathbf{F}_{N+M+1,N}, \mathbf{F}_{N+M+1,N+1}, \dots, \mathbf{F}_{N+M+1,N+M+1}\}
\end{aligned}$$

to be the entire, possibly redundant, ordered set of frequencies contained in both generalized B-spline packets. Similarly, define

$$\begin{aligned}
\mathbf{S}_{N+M+1} &:= \{s_0, \dots, s_N, s_{N+1}, \dots, s_{N+M+1}\} \\
&:= \{\mathbf{S}_{N+M+1,0}, \dots, \mathbf{S}_{N+M+1,N}, \mathbf{S}_{N+M+1,N+1}, \dots, \mathbf{S}_{N+M+1,N+M+1}\}
\end{aligned}$$

to be the entire, possibly redundant, ordered set of scales contained in both generalized B-spline packets. Lastly, define

$$\begin{aligned} \mathbf{P}_{N+M+1} &:= \{p_0, \dots, p_N, p_{N+1}, \dots, p_{N+M+1}\} \\ &:= \{\mathbf{P}_{N+M+1,0}, \dots, \mathbf{P}_{N+M+1,N}, \mathbf{P}_{N+M+1,N+1}, \dots, \mathbf{P}_{N+M+1,N+M+1}\} \end{aligned}$$

to be the entire, possibly redundant, ordered set of positions contained in both generalized B-spline packets. The inner product of these two generalized B-spline packet basis functions is given explicitly by the following:

$$\begin{aligned} &\langle \mathcal{W}_{N,\kappa_N}(t), \mathcal{W}_{M,\kappa_M}(t) \rangle \\ &= 2^{-\frac{\bar{\alpha}(N+M)}{2}} \sum_{j \in \mathbb{Z}} c_{N+M+1}(j) \mathcal{B}_{N+M+1}(N+1+j+ \\ &\quad \sum_{i=0}^N 2^{s\Delta_i} \mathbf{P}_{N+M+1,i} - \sum_{l=0}^M 2^{s\Delta_{N+1+l}} \mathbf{P}_{N+M+1,N+1+l}) \\ &= 2^{-\frac{\bar{\alpha}(N+M)}{2}} \sum_{k \in \mathbb{Z}} \tilde{c}_{N+M+1}(k) \mathcal{B}_{N+M+1}(M+1+k+ \\ &\quad \sum_{l=0}^M 2^{s\Delta_{N+1+l}} \mathbf{P}_{N+M+1,N+1+l} - \sum_{i=0}^N 2^{s\Delta_i} \mathbf{P}_{N+M+1,i}) \end{aligned} \quad (8.59)$$

where: $\bar{\alpha} := \max(\mathbf{S}_{N+M+1,k} + \lceil \log_2(\mathbf{F}_{N+M+1,k} + 1) \rceil, \forall k = 0, \dots, N+M+1)$;

$$s\Delta_i := \bar{\alpha} - \mathbf{S}_{N+M+1,i}, \forall i = 0, \dots, N+M+1;$$

$$c_{N+M+1}(k) := m_N(k) * \tilde{m}_M(-k);$$

$$\tilde{c}_{N+M+1}(k) := \tilde{m}_M(k) * m_N(-k);$$

$$m_N(j) := \underbrace{\tilde{m}_{s\Delta_0}(j) * \dots * \tilde{m}_{s\Delta_N}(j)}_{N+1};$$

$$\tilde{m}_M(k) := \underbrace{\tilde{m}_{s\Delta_{N+1}}(k) * \dots * \tilde{m}_{s\Delta_{N+M+1}}(k)}_{M+1};$$

$$\tilde{m}_{s\Delta_i}(k) := \begin{cases} q_0(\frac{k}{2^{s\Delta_i-1}}) * \dots * q_{s\Delta_i-2}(\frac{k}{2}) * q_{s\Delta_i-1}(k), & \text{if } s\Delta_i > 0 \\ \delta_{k,0}, & \text{if } s\Delta_i = 0 \end{cases};$$

$$q_n(k) = \begin{cases} h(k), & \text{if } f_{i_n} = 0 \\ g(k), & \text{if } f_{i_n} = 1 \end{cases};$$

$\{f_{i_n} : n \in \mathbb{Z}^+\}$ is the infinite binary expansion of the frequency, f_i , for $\psi_{f_i, p_i}^{s_i}(t)$;

Proof: The first step is to represent each generalized B-spline packet basis function, $\mathcal{W}_{N,\kappa_N}(t)$ and $\mathcal{W}_{M,\kappa_M}(t)$, using the generalized B-spline packet basis function representation theorem, theorem 8.2,

as follows:

$$\mathcal{W}_{N,\kappa_N}(t) = 2^{-\frac{\bar{\alpha}(N-1)}{2}} \sum_{k \in \mathbb{Z}} m_N(k - \sum_{i=0}^N 2^{s\Delta_i} P_{N+M+1,i}) \mathcal{B}_N(2^{\bar{\alpha}}t - k) \quad (8.60)$$

$$\mathcal{W}_{M,\kappa_M}(t) = 2^{-\frac{\bar{\alpha}(M-1)}{2}} \sum_{k \in \mathbb{Z}} \tilde{m}_M(k - \sum_{l=0}^M 2^{s\Delta_l} P_{N+M+1,N+1+l}) \mathcal{B}_M(2^{\bar{\alpha}}t - k) \quad (8.61)$$

where: $m_N(k - \sum_{i=0}^N 2^{s\Delta_i} P_{N+M+1,i}) := \underbrace{\tilde{m}_{s\Delta_0}(k - 2^{s\Delta_0}p_0) * \dots * \tilde{m}_{s\Delta_N}(k - 2^{s\Delta_N}p_N)}_{N+1}$;

$$\begin{aligned} \tilde{m}_M(k - \sum_{l=0}^M 2^{s\Delta_l} P_{N+M+1,N+1+l}) &:= \\ &\underbrace{\tilde{m}_{s\Delta_{N+1}}(k - 2^{s\Delta_{N+1}}p_{N+1}) * \dots * \tilde{m}_{s\Delta_{N+M+1}}(k - 2^{s\Delta_{N+M+1}}p_{N+M+1})}_{M+1}; \\ \tilde{m}_{s\Delta_i}(k - 2^{s\Delta_i}p_i) &:= \begin{cases} q_0(\frac{k}{2^{s\Delta_i-1}}) * \dots * q_{s\Delta_i-2}(\frac{k}{2}) * q_{s\Delta_i-1}(k - 2^{s\Delta_i}p_i), & \text{if } s\Delta_i > 0 \\ \delta_{k,0}, & \text{if } s\Delta_i = 0 \end{cases}; \end{aligned}$$

$$q_n(k) = \begin{cases} h(k), & \text{if } f_{i_n} = 0 \\ g(k), & \text{if } f_{i_n} = 1 \end{cases};$$

$\{f_{i_n} : n \in \mathbb{Z}^+\}$ is the infinite binary expansion of the frequency, f_i , for $\psi_{f_i, p_i}^{s_i}(t)$.

Observe that it is necessary to define $\bar{\alpha} := \max(S_{N+M+1,k} + \lceil \log_2(F_{N+M+1,k} + 1) \rceil, \forall k = 0, \dots, N + M + 1)$, in order to ensure that all resultant B-splines, $\mathcal{B}_0(2^{\bar{\alpha}}t)$, will be at the same scale. Also, define $s\Delta_i := \bar{\alpha} - S_{N+M+1,i}$, $\forall i = 0, \dots, N + M + 1$. After using theorem 8.2 to represent each generalized B-spline packet basis function, equations 8.60 and 8.61, apply theorem 8.3 to yield:

$$\begin{aligned} &\langle \mathcal{W}_{N,\kappa_N}(t), \mathcal{W}_{M,\kappa_M}(t) \rangle \\ &= \langle \psi_{f_0, p_0}^{s_0}(t) * \dots * \psi_{f_N, p_N}^{s_N}(t), \psi_{f_{N+1}, p_{N+1}}^{s_{N+1}}(t) * \dots * \psi_{f_{N+M+1}, p_{N+M+1}}^{s_{N+M+1}}(t) \rangle \\ &= \langle 2^{-\frac{\bar{\alpha}(N-1)}{2}} \sum_{j \in \mathbb{Z}} m_N(j - \sum_{i=0}^N 2^{s\Delta_i} P_{N+M+1,i}) \mathcal{B}_N(2^{\bar{\alpha}}t - j), \\ &\quad 2^{-\frac{\bar{\alpha}(M-1)}{2}} \sum_{k \in \mathbb{Z}} \tilde{m}_M(k - \sum_{l=0}^M 2^{s\Delta_{N+1+l}} P_{N+M+1,N+1+l}) \mathcal{B}_M(2^{\bar{\alpha}}t - k) \rangle \\ &= 2^{-\frac{\bar{\alpha}(N+M)}{2}} \sum_{j \in \mathbb{Z}} \sum_{k \in \mathbb{Z}} m_N(j - \sum_{i=0}^N 2^{s\Delta_i} P_{N+M+1,i}) \tilde{m}_M(k - \sum_{l=0}^M 2^{s\Delta_{N+1+l}} P_{N+M+1,N+1+l}) \\ &\quad \langle \mathcal{B}_N(t - j), \mathcal{B}_M(t - k) \rangle \\ &= 2^{-\frac{\bar{\alpha}(N+M)}{2}} \sum_{j \in \mathbb{Z}} \sum_{k \in \mathbb{Z}} m_N(j - \sum_{i=0}^N 2^{s\Delta_i} P_{N+M+1,i}) \tilde{m}_M(k - \sum_{l=0}^M 2^{s\Delta_{N+1+l}} P_{N+M+1,N+1+l}) \\ &\quad \mathcal{B}_{N+M+1}(N + 1 + j - k) \end{aligned} \quad (8.62)$$

$$\begin{aligned} &= 2^{-\frac{\bar{\alpha}(N+M)}{2}} \sum_{j \in \mathbb{Z}} \sum_{k \in \mathbb{Z}} m_N(j - \sum_{i=0}^N 2^{s\Delta_i} P_{N+M+1,i}) \tilde{m}_M(k - \sum_{l=0}^M 2^{s\Delta_{N+1+l}} P_{N+M+1,N+1+l}) \\ &\quad \mathcal{B}_{N+M+1}(M + 1 + k - j) \end{aligned} \quad (8.63)$$

Now let $j = j - k$ in equation 8.62 and let $k = k - j$ in equation 8.63 to yield the final results:

$$\begin{aligned}
& 2^{-\frac{\tilde{s}(N+M)}{2}} \sum_{j \in \mathbb{Z}} \sum_{k \in \mathbb{Z}} m_N(j - \sum_{i=0}^N 2^{s\Delta_i} P_{N+M+1,i}) \tilde{m}_M(k - \sum_{l=0}^M 2^{s\Delta_{N+1+l}} P_{N+M+1,N+1+l}) \\
& \quad \mathcal{B}_{N+M+1}(N+1+j-k) \\
&= 2^{-\frac{\tilde{s}(N+M)}{2}} \sum_{j \in \mathbb{Z}} \sum_{k \in \mathbb{Z}} m_N(j+k - \sum_{i=0}^N 2^{s\Delta_i} P_{N+M+1,i}) \tilde{m}_M(k - \sum_{l=0}^M 2^{s\Delta_{N+1+l}} P_{N+M+1,N+1+l}) \\
& \quad \mathcal{B}_{N+M+1}(N+1+j) \\
&= 2^{-\frac{\tilde{s}(N+M)}{2}} \sum_{j \in \mathbb{Z}} c_{N+M+1}(j - \sum_{i=0}^N 2^{s\Delta_i} P_{N+M+1,i} + \sum_{l=0}^M 2^{s\Delta_{N+1+l}} P_{N+M+1,N+1+l}) \\
& \quad \mathcal{B}_{N+M+1}(N+1+j) \\
&= 2^{-\frac{\tilde{s}(N+M)}{2}} \sum_{j \in \mathbb{Z}} c_{N+M+1}(j) \\
& \quad \mathcal{B}_{N+M+1}(N+1+j + \sum_{i=0}^N 2^{s\Delta_i} P_{N+M+1,i} - \sum_{l=0}^M 2^{s\Delta_{N+1+l}} P_{N+M+1,N+1+l}) \\
& 2^{-\frac{\tilde{s}(N+M)}{2}} \sum_{j \in \mathbb{Z}} \sum_{k \in \mathbb{Z}} m_N(j - \sum_{i=0}^N 2^{s\Delta_i} P_{N+M+1,i}) \tilde{m}_M(k - \sum_{l=0}^M 2^{s\Delta_{N+1+l}} P_{N+M+1,N+1+l}) \\
& \quad \mathcal{B}_{N+M+1}(M+1+k-j) \\
&= 2^{-\frac{\tilde{s}(N+M)}{2}} \sum_{k \in \mathbb{Z}} \sum_{j \in \mathbb{Z}} m_N(j - \sum_{i=0}^N 2^{s\Delta_i} P_{N+M+1,i}) \tilde{m}_M(k+j - \sum_{l=0}^M 2^{s\Delta_{N+1+l}} P_{N+M+1,N+1+l}) \\
& \quad \mathcal{B}_{N+M+1}(M+1+k) \\
&= 2^{-\frac{\tilde{s}(N+M)}{2}} \sum_{k \in \mathbb{Z}} \tilde{c}_{N+M+1}(k - \sum_{l=0}^M 2^{s\Delta_{N+1+l}} P_{N+M+1,N+1+l} + \sum_{i=0}^N 2^{s\Delta_i} P_{N+M+1,i}) \\
& \quad \mathcal{B}_{N+M+1}(M+1+k) \\
&= 2^{-\frac{\tilde{s}(N+M)}{2}} \sum_{k \in \mathbb{Z}} \tilde{c}_{N+M+1}(k) \\
& \quad \mathcal{B}_{N+M+1}(M+1+k + \sum_{l=0}^M 2^{s\Delta_{N+1+l}} P_{N+M+1,N+1+l} - \sum_{i=0}^N 2^{s\Delta_i} P_{N+M+1,i})
\end{aligned}$$

where $c_{N+M+1}(k) := m_N(k) * \tilde{m}_M(-k)$ and $\tilde{c}_{N+M+1}(k) := \tilde{m}_M(k) * m_N(-k)$. ■

Remark 8.19 If the generalized B-spline packet basis functions are composed only of B-splines at identical scales, then it follows that $s\Delta_i = 0 \forall i$. In this case, an equivalent result to Theorem 8.6 can be obtained by a simple generalization of Theorem 8.4 with $p1$ and $p2$ of Theorem 8.4 replaced by $p1 = \sum_{i=0}^N P_{N+M+1,i}$ and $p2 = \sum_{l=0}^M P_{N+M+1,N+1+l}$ as follows:

$$\begin{aligned}
\langle \mathcal{W}_{N,\kappa_N}(t), \mathcal{W}_{M,\kappa_M}(t) \rangle &= \mathcal{B}_{N+M+1}(N+1 + \sum_{i=0}^N P_{N+M+1,i} - \sum_{l=0}^M P_{N+M+1,N+1+l}) \\
&= \mathcal{B}_{N+M+1}(M+1 + \sum_{l=0}^M P_{N+M+1,N+1+l} - P_{N+M+1,i}) \quad (8.64)
\end{aligned}$$

Remark 8.20 Lemma 5.1 defined the recursive relations utilized in the numerical calculation of the wavelet packet coefficients, which are based on the reflected wavelet packet functions, $\check{\psi}_{f,p}^s = 2^{s/2}\psi_f(p - 2^s t) \in W_f^s$. Remark 7.5 demonstrated that the parity of the frequency $\tilde{f}$ for a sequency ordered Haar wavelet packet subspace determined the function parity of the corresponding Haar wavelet packet basis function(s). Define $\overline{\mathcal{W}}_{N,\kappa_N}(t) := \check{\psi}_{f_0,p_0}^{s_0}(t) * \cdots * \check{\psi}_{f_N,p_N}^{s_N}(t)$ to be a reverse generalized B-spline packet basis function of order N . Define $\overline{\mathcal{W}}_{M,\kappa_M}(t) := \check{\psi}_{f_{N+1},p_{N+1}}^{s_{N+1}}(t) * \cdots * \check{\psi}_{f_{N+M+1},p_{N+M+1}}^{s_{N+M+1}}(t)$ to be another reverse generalized B-spline packet basis function of order M . The ordered set of frequencies contained in both reverse generalized B-spline packet basis functions is given by F_{N+M+1} . Define $\overline{F}_{N+M+1}$ to be the corresponding set of sequency ordered frequencies for the reverse generalized B-spline packet basis functions determined by using definition 7.2. The resultant inner product of these two reverse generalized B-spline packet basis functions can now be determined explicitly in terms of the resultant inner product given by theorem 8.6 for the corresponding normal generalized B-spline packet basis functions as follows:

$$\begin{aligned} & \langle \overline{\mathcal{W}}_{N,\kappa_N}(t), \overline{\mathcal{W}}_{M,\kappa_M}(t) \rangle \\ &= (-1)^{\sum_{k=0}^{N+M+1} \overline{F}_{N+M+1,k}} \langle \mathcal{W}_{N,\kappa_N}(t), \mathcal{W}_{M,\kappa_M}(t) \rangle \end{aligned} \quad (8.65)$$

The main observation leading to this result is the fact that

$$\langle \overline{\mathcal{W}}_{N,\kappa_N}(t), \overline{\mathcal{W}}_{M,\kappa_M}(t) \rangle = \langle \mathcal{W}_{N,\kappa_N}(t), \mathcal{W}_{M,\kappa_M}(t) \rangle$$

when both basis functions are even or odd. A sign change occurs when one basis function is even and the other is odd. Since the sum rules between even and odd numbers can be directly equated to the relationship just discussed between the inner products and since the parity of the frequency $\tilde{f}$ for a sequency ordered Haar wavelet packet subspace determines the function parity of the corresponding Haar wavelet packet basis function(s), it follows that equation 8.65 gives the desired result.

8.4 Discrete B-spline Packets

Continuous-time, generalized B-spline packet basis functions were represented using theorem 8.2. As was demonstrated in section 7.5, discrete-time Haar wavelet packet basis functions can be determined using definition 7.2. Also recall that a Haar Wavelet Packet Basis (HWPB) matrix is an equivalent representation for a sampled set of Haar wavelet packet basis functions. Similarly, the convolution of $L + 1$ sampled Haar wavelet packet basis functions corresponds to a discrete-time, generalized B-spline packet basis function of order L as shown by the next lemma.

Lemma 8.11 (Discrete Generalized B-spline Packet Representation Lemma)

Define $\mathcal{W}_{L,\kappa_L}(k) := \psi_{f_0,p_0}^{s_0}(k), \dots, \psi_{f_L,p_L}^{s_L}(k)$ to be a discrete-time generalized B-spline packet basis function of order L , i.e., the convolution of $L + 1$ discrete-time Haar wavelet packet basis functions, $\psi_{f_j,p_j}^{s_j}(k)$. Represent the frequencies of the individual Haar wavelet packet basis functions, $f_0 \in \mathbb{Z}^+, \dots, f_L \in \mathbb{Z}^+$, by their infinite binary expansions, $\{f_{0,n} : n \in \mathbb{Z}^+\}, \dots, \{f_{L,n} : n \in \mathbb{Z}^+\}$. Define

$$\Psi_L(k) := \{\psi_{f_0,p_0}^{s_0}(k), \dots, \psi_{f_L,p_L}^{s_L}(k)\} := \{\Psi_{L,0}(k), \dots, \Psi_{L,L}(k)\}$$

to be the entire, possibly redundant, ordered set of Haar wavelet packet basis functions contained in the generalized B-spline packet. Define

$$F_L := \{f_0, \dots, f_L\} := \{F_{L,0}, \dots, F_{L,L}\}$$

to be the entire, possibly redundant, ordered set of frequencies contained in the generalized B-spline packet. Similarly, define

$$S_L := \{s_0, \dots, s_L\} := \{S_{L,0}, \dots, S_{L,L}\}$$

to be the entire, possibly redundant, ordered set of scales contained in the generalized B-spline packet. Lastly, define

$$P_L := \{p_0, \dots, p_L\} := \{P_{L,0}, \dots, P_{L,L}\}$$

to be the entire, possibly redundant, ordered set of positions contained in the generalized B-spline packet. A discrete-time, generalized B-spline packet basis function of order L , can be represented by the following:

$$\mathcal{W}_{L,\kappa_L}(k) = 2^{-\frac{\tilde{\nu}(L-1)}{2}} m_L(k - \sum_{i=0}^L 2^{s\Delta_i} P_{L,i}) \quad (8.66)$$

where: $2^{\tilde{\nu}}$ is the length of the discrete-time representation for each of the

$$\begin{aligned} & \text{Haar wavelet packet basis functions, } \psi_{f_0,p_0}^{s_0}(k), \dots, \psi_{f_L,p_L}^{s_L}(k); \\ & m_L(k - \sum_{j=0}^L 2^{s\Delta_j} P_{L,j}) := \underbrace{\tilde{m}_{s\Delta_0}(k - 2^{s\Delta_0} p_0) * \dots * \tilde{m}_{s\Delta_L}(k - 2^{s\Delta_L} p_L)}_{L+1}; \\ & \tilde{m}_{s\Delta_i}(k - 2^{s\Delta_i} p_i) := \begin{cases} q_0(\frac{k}{2^{s\Delta_i-1}}) * \dots * q_{s\Delta_i-2}(\frac{k}{2}) * q_{s\Delta_i-1}(k - 2^{s\Delta_i} p_i), & \text{if } s\Delta_i > 0 \\ \delta_{k,0}, & \text{if } s\Delta_i = 0 \end{cases}; \\ & q_n(k) = \begin{cases} h(k), & \text{if } f_{i,n} = 0 \\ g(k), & \text{if } f_{i,n} = 1 \end{cases}; \\ & \{f_{i,n} : n \in \mathbb{Z}^+\} \text{ is the infinite binary expansion of the frequency, } f_i, \text{ for } \psi_{f_i,p_i}^{s_i}(t). \end{aligned}$$

From the sampling theorem applied to discrete-time Haar wavelet packet basis functions, see lemma 7.2, it follows that $\mathcal{W}_{L,\kappa_L}(k) = \mathcal{W}_{L,\kappa_L}(k\tau_s) \rightarrow \mathcal{W}_{L,\kappa_L}(t)$ as $F_s = 2^{\tilde{\nu}} \rightarrow \infty$.

Proof: First, represent each discrete-time, Haar wavelet packet basis function using its corresponding sampled, continuous-time, Haar wavelet packet basis function given by equation 7.47 of lemma 7.2 as follows:

$$\Psi_{L,i}(n) = \Psi_{L,i}(t) |_{t=n\tau_s} = 2^{\frac{\tilde{\nu}}{2}} \sum_{l=0}^{(2^{s\Delta_i}-1)} \check{m}_{s\Delta_i}(l - 2^{s\Delta_i} P_{L,i}) \psi_0(2^{\tilde{\nu}} t - l) |_{t=n\tau_s}, \quad (8.67)$$

Based on the sampling theorem condition of lemma 7.2, $\tilde{\nu} \geq S_{L,i} + [\log_2(F_{L,i} + 1)]$, it follows that the appropriate sampling frequency, $F_s = 2^{\tilde{\nu}}$, must be determined based on all of the Haar wavelet packet basis functions according to the following:

$$\tilde{\nu} := \max(S_{L,i} + [\log_2(F_{L,i} + 1)], \forall i = 0, \dots, L) \quad (8.68)$$

Then use the continuous-time, generalized B-spline packet representation theorem, theorem 8.2, on the sampled version of each Haar wavelet packet basis function represented by equation 8.67, let $\tau_s = 2^{-\tilde{\nu}}$, apply the corresponding discrete-time version of lemma 8.2, and employ equation 7.49 to yield the desired result:

$$\begin{aligned} \mathcal{W}_{L,\kappa_L}(n) &= \mathcal{W}_{L,\kappa_L}(t) |_{t=n\tau_s} = 2^{-\frac{\tilde{\nu}(L-1)}{2}} \sum_{k \in \mathbb{Z}} m_L(k - \sum_{i=0}^L 2^{s\Delta_i} P_{L,i}) \mathcal{B}_L(2^{\tilde{\nu}} t - k) |_{t=n\tau_s} \\ &= 2^{-\frac{\tilde{\nu}(L-1)}{2}} m_L(k - \sum_{i=0}^L 2^{s\Delta_i} P_{L,i}) * \underbrace{\mathcal{B}_0(2^{\tilde{\nu}} t) * \dots * \mathcal{B}_0(2^{\tilde{\nu}} t)}_{L+1} |_{t=n\tau_s} \\ &= 2^{-\frac{\tilde{\nu}(L-1)}{2}} \left[\sum_{k \in \mathbb{Z}} m_L(k - \sum_{i=0}^L 2^{s\Delta_i} P_{L,i}) \mathcal{B}_0(n - k) \right] * \underbrace{\mathcal{B}_0(n) * \dots * \mathcal{B}_0(n)}_L \\ &= 2^{-\frac{\tilde{\nu}(L-1)}{2}} m_L(k - \sum_{i=0}^L 2^{s\Delta_i} P_{L,i}) * \underbrace{\mathcal{B}_0(n) * \dots * \mathcal{B}_0(n)}_L \\ &\vdots \\ &= 2^{-\frac{\tilde{\nu}(L-1)}{2}} \sum_{k \in \mathbb{Z}} m_L(k - \sum_{i=0}^L 2^{s\Delta_i} P_{L,i}) \mathcal{B}_0(n - k) \\ &= 2^{-\frac{\tilde{\nu}(L-1)}{2}} m_L(k - \sum_{i=0}^L 2^{s\Delta_i} P_{L,i}) \quad \blacksquare \end{aligned}$$

A closed form solution for continuous-time, generalized B-spline packet inner products was presented in theorem 8.6. Lemma 8.11 demonstrated that discrete-time, generalized B-spline packet basis functions resulted from the convolution of discrete-time Haar wavelet packet basis functions. Recall definition 7.54, which made the orthonormality property identical for both continuous-time and discrete-time Haar wavelet packet inner products. Similarly, it is desirable to make the discrete-time generalized B-spline packet inner products approximately equal to the continuous-time generalized B-spline packet inner products with the degree of approximation satisfying the following

convergence property:

$$\lim_{F_s=2^{\bar{\nu}} \rightarrow \infty} \langle \widetilde{\mathcal{W}}_{L,\kappa_L}(k\tau_s), \widetilde{\mathcal{W}}_{M,\kappa_M}(k\tau_s) \rangle \longrightarrow \langle \widetilde{\mathcal{W}}_{L,\kappa_L}(t), \widetilde{\mathcal{W}}_{M,\kappa_M}(t) \rangle \quad (8.69)$$

The resultant inner product between two discrete-time generalized B-spline packet basis functions is given by following lemma.

Lemma 8.12 (Discrete Generalized B-spline Packet Inner Products)

Let $\mathcal{W}_{L,\kappa_L}(k) = 2^{-\bar{\nu}L} \psi_{f_0,p_0}^{s_0}(k), \dots, \psi_{f_L,p_L}^{s_L}(k)$ be a discrete-time generalized B-spline packet basis function and let $\mathcal{W}_{M,\kappa_M}(k) = 2^{-\bar{\nu}M} \psi_{f_{L+1},p_{L+1}}^{s_{L+1}}(k), \dots, \psi_{f_{L+M+1},p_{L+M+1}}^{s_{L+M+1}}(k)$ be another discrete-time generalized B-spline packet basis function. Define

$$\begin{aligned} \Psi_{L+M+1}(k) &:= \{ \psi_{f_0,p_0}^{s_0}(k), \dots, \psi_{f_L,p_L}^{s_L}(k), \psi_{f_{L+1},p_{L+1}}^{s_{L+1}}(k), \dots, \psi_{f_{L+M+1},p_{L+M+1}}^{s_{L+M+1}}(k) \} \\ &:= \{ \Psi_{L+M+1,0}(k), \dots, \Psi_{L+M+1,N}(k), \Psi_{L+M+1,L+1}(k), \dots, \Psi_{L+M+1,L+M+1}(k) \} \end{aligned}$$

to be the entire, possibly redundant, ordered set of Haar wavelet packet basis functions contained in both generalized B-spline packets. Define

$$\begin{aligned} \mathbf{F}_{L+M+1} &:= \{ f_0, \dots, f_L, f_{L+1}, \dots, f_{L+M+1} \} \\ &:= \{ \mathbf{F}_{L+M+1,0}, \dots, \mathbf{F}_{L+M+1,L}, \mathbf{F}_{L+M+1,L+1}, \dots, \mathbf{F}_{L+M+1,L+M+1} \} \end{aligned}$$

to be the entire, possibly redundant, ordered set of frequencies contained in both generalized B-spline packets. Similarly, define

$$\begin{aligned} \mathbf{S}_{L+M+1} &:= \{ s_0, \dots, s_L, s_{L+1}, \dots, s_{L+M+1} \} \\ &:= \{ \mathbf{S}_{L+M+1,0}, \dots, \mathbf{S}_{L+M+1,L}, \mathbf{S}_{L+M+1,L+1}, \dots, \mathbf{S}_{L+M+1,L+M+1} \} \end{aligned}$$

to be the entire, possibly redundant, ordered set of scales contained in both generalized B-spline packets. Lastly, define

$$\begin{aligned} \mathbf{P}_{L+M+1} &:= \{ p_0, \dots, p_L, p_{L+1}, \dots, p_{L+M+1} \} \\ &:= \{ \mathbf{P}_{L+M+1,0}, \dots, \mathbf{P}_{L+M+1,L}, \mathbf{P}_{L+M+1,L+1}, \dots, \mathbf{P}_{L+M+1,L+M+1} \} \end{aligned}$$

to be the entire, possibly redundant, ordered set of positions contained in both generalized B-spline packets. The inner product of these two discrete-time generalized B-spline packet basis functions is given explicitly by the following:

$$\begin{aligned} \langle \mathcal{W}_{L,\kappa_L}(k), \mathcal{W}_{M,\kappa_M}(k) \rangle &= 2^{-\frac{\bar{\nu}(L+M)}{2}} \sum_{k \in \mathbb{Z}} m_L(k - \sum_{i=0}^L 2^{s_{\Delta_i}} \mathbf{P}_{L+M+1,i}) \tilde{m}_M(k - \sum_{j=0}^M 2^{s_{\Delta_j}} \mathbf{P}_{L+M+1,L+1+j}) \\ &= \frac{1}{2^{\bar{\nu}(L+M+1)}} \langle \psi_{f_0,p_0}^{s_0}(k) * \dots * \psi_{f_L,p_L}^{s_L}(k), \psi_{f_{L+1},p_{L+1}}^{s_{L+1}}(k) * \dots * \psi_{f_{L+M+1},p_{L+M+1}}^{s_{L+M+1}}(k) \rangle \quad (8.70) \end{aligned}$$

where: $2^{\bar{\nu}}$ is the length of the discrete-time representation for each element in the entire

$$\begin{aligned}
& \text{ordered set of Haar wavelet packet basis functions, } \tilde{\Psi}_{L+M+1}(k); \\
& m_L(k - \sum_{i=0}^L 2^{s\Delta_i} P_{L+M+1,i}) := \underbrace{\tilde{m}_{s\Delta_0}(k - 2^{s\Delta_0} p_0) * \cdots * \tilde{m}_{s\Delta_L}(k - 2^{s\Delta_L} p_L)}_{L+1}; \\
& \tilde{m}_M(k - \sum_{j=0}^M 2^{s\Delta_j} P_{L+M+1,L+1+j}) := \\
& \quad \underbrace{\tilde{m}_{s\Delta_{L+1}}(k - 2^{s\Delta_{L+1}} p_{L+1}) * \cdots * \tilde{m}_{s\Delta_{L+M+1}}(k - 2^{s\Delta_{L+M+1}} p_{L+M+1})}_{M+1}; \\
& \tilde{m}_{s\Delta_i}(k - 2^{s\Delta_i} p_i) := \begin{cases} q_0(\frac{k}{2^{s\Delta_i-1}}) * \cdots * q_{s\Delta_i-2}(\frac{k}{2}) * q_{s\Delta_i-1}(k - 2^{s\Delta_i} p_i), & \text{if } s\Delta_i > 0 \\ \delta_{k,0}, & \text{if } s\Delta_i = 0 \end{cases}; \\
& q_n(k) = \begin{cases} h(k), & \text{if } f_{i_n} = 0 \\ g(k), & \text{if } f_{i_n} = 1 \end{cases}; \\
& \{f_{i_n} : n \in \mathbb{Z}^+\} \text{ is the infinite binary expansion of the frequency, } f_i, \text{ for } \psi_{f_i, p_i}^{s_i}(t).
\end{aligned}$$

Proof: Represent each discrete-time, generalized B-spline packet basis function, $\mathcal{W}_{L, \kappa_L}(k)$ and $\mathcal{W}_{M, \kappa_M}(k)$, using its corresponding sampled, continuous-time, generalized B-spline packet basis function representation of lemma 8.11 as follows:

$$\mathcal{W}_{L, \kappa_L}(n) = 2^{-\frac{\bar{\nu}(L-1)}{2}} \sum_{k \in \mathbb{Z}} m_L(k - \sum_{i=0}^L 2^{s\Delta_i} P_{L+M+1,i}) \mathcal{B}_0(2^{\bar{\nu}} t - k) |_{t=n\tau_s} \quad (8.71)$$

$$\mathcal{W}_{M, \kappa_M}(n) = 2^{-\frac{\bar{\nu}(M-1)}{2}} \sum_{l \in \mathbb{Z}} \tilde{m}_M(l - \sum_{j=0}^M 2^{s\Delta_j} P_{L+M+1,L+1+j}) \mathcal{B}_0(2^{\bar{\nu}} t - l) |_{t=n\tau_s} \quad (8.72)$$

Form the inner product using equations 8.71 and 8.72, use definition 7.54 for the discrete-time Haar wavelet packet inner product, then apply the Riesz basis property for the original scaling function, equation 3.15, and lastly use lemma 8.11 to yield the desired result:

$$\begin{aligned}
\langle \mathcal{W}_{L, \kappa_L}(k), \mathcal{W}_{M, \kappa_M}(k) \rangle &= \langle 2^{-\frac{\bar{\nu}(L-1)}{2}} \sum_{k \in \mathbb{Z}} m_L(k - \sum_{i=0}^L 2^{s\Delta_i} P_{L+M+1,i}) \mathcal{B}_0(2^{\bar{\nu}} t - k), \\
& 2^{-\frac{\bar{\nu}(M-1)}{2}} \sum_{l \in \mathbb{Z}} \tilde{m}_M(l - \sum_{j=0}^M 2^{s\Delta_j} P_{L+M+1,L+1+j}) \mathcal{B}_0(2^{\bar{\nu}} t - l) \rangle |_{t=n\tau_s} \\
&= 2^{-\frac{\bar{\nu}(L+M)}{2}} \sum_{k \in \mathbb{Z}} \sum_{l \in \mathbb{Z}} m_L(k - \sum_{i=0}^L 2^{s\Delta_i} P_{L+M+1,i}) \tilde{m}_M(l - \sum_{j=0}^M 2^{s\Delta_j} P_{L+M+1,L+1+j}) \\
& \quad \langle \mathcal{B}_0(t - k), \mathcal{B}_0(t - l) \rangle \\
&= 2^{-\frac{\bar{\nu}(L+M)}{2}} \sum_{k \in \mathbb{Z}} m_L(k - \sum_{i=0}^L 2^{s\Delta_i} P_{L+M+1,i}) \tilde{m}_M(k - \sum_{j=0}^M 2^{s\Delta_j} P_{L+M+1,L+1+j}) \\
&= \frac{1}{2^{\bar{\nu}}} \langle 2^{-\frac{\bar{\nu}(L-1)}{2}} m_L(k - \sum_{i=0}^L 2^{s\Delta_i} P_{L+M+1,i}), 2^{-\frac{\bar{\nu}(M-1)}{2}} \tilde{m}_M(k - \sum_{j=0}^M 2^{s\Delta_j} P_{L+M+1,L+1+j}) \rangle \\
&= \frac{1}{2^{\bar{\nu}(L+M+1)}} \langle \psi_{f_0, p_0}^{s_0}(k) * \cdots * \psi_{f_L, p_L}^{s_L}(k), \psi_{f_{L+1}, p_{L+1}}^{s_{L+1}}(k) * \cdots * \psi_{f_{L+M+1}, p_{L+M+1}}^{s_{L+M+1}}(k) \rangle \quad \blacksquare
\end{aligned}$$

CHAPTER 9

MULTIRESOLUTIONAL CONTROLLER DESIGN

This chapter presents a sensitivity controller and a mixed sensitivity controller based on compactly supported, orthonormal wavelet packets at multiple scales with dilation factor 2. Throughout this chapter, any mention of wavelet packets will refer to Haar wavelet packets. Haar wavelet packets were chosen for simplicity, along with being an orthonormal basis over a compact interval. It has been shown by several researchers [47] that other orthonormal wavelet packets can be constructed to be orthogonal over a compact interval. However, these constructions involve considerably more computations than the Haar wavelet packet and therefore will not be considered herein. In addition, design examples will be presented for the sensitivity and mixed sensitivity multiresolutional controllers. For comparison purposes, the discrete H^2 controllers based on the linear fractional transformation (LFT) framework will also be determined. The mathematical background for this chapter can be found in [48], [49], [50], [51], [52], [53], [54], [55], [56], and [57]. The necessary mathematical and computational tools utilized in the solution of the multiresolutional controllers developed in this chapter were presented in chapters 7 and 8.

9.1 Mathematical Preliminaries

This section will focus on some of the necessary mathematical machinery that will be used in the sequel.

Definition 9.1 (Kronecker Product)

Let $A \in \mathbb{C}^{p \times q}$ and $B \in \mathbb{C}^{m \times n}$, then the Kronecker Product of A and B , $A \otimes B \in \mathbb{C}^{pm \times qn}$, is defined as follows:

$$A \otimes B := \begin{bmatrix} a_{11}B & \cdots & a_{1q}B \\ \vdots & \vdots & \vdots \\ a_{p1}B & \cdots & a_{pq}B \end{bmatrix} \quad (9.1)$$

Definition 9.2 (Kronecker Sum)

Let $A \in \mathbb{C}^{p \times p}$ and $B \in \mathbb{C}^{m \times m}$, then the Kronecker Sum of A and B , $A \oplus B \in \mathbb{C}^{pm \times pm}$, is defined as follows:

$$A \oplus B := (A \otimes I_m) + (I_p \otimes B) = \begin{bmatrix} a_{11}I_m & a_{12}I_m & \cdots & a_{1p}I_m \\ a_{21}I_m & a_{22}I_m & \cdots & a_{2p}I_m \\ \vdots & \vdots & \ddots & \vdots \\ a_{p1}I_m & a_{p2}I_m & \cdots & a_{pp}I_m \end{bmatrix} + \begin{bmatrix} B & 0_m & \cdots & 0_m \\ 0_m & B & \cdots & 0_m \\ \vdots & \vdots & \ddots & \vdots \\ 0_m & 0_m & \cdots & B \end{bmatrix} \quad (9.2)$$

where $I_m := m \times m$ identity matrix and $0_m := m \times m$ zero matrix.

Definition 9.3 (Kronecker Convolution)

Let

$$V \in \mathbb{C}^{p \times q} := \begin{bmatrix} V_1 \\ \vdots \\ V_p \end{bmatrix} = \begin{bmatrix} v_{1,1} & \cdots & v_{1,q} \\ \vdots & \vdots & \vdots \\ v_{p,1} & \cdots & v_{p,q} \end{bmatrix}$$

and

$$W \in \mathbb{C}^{m \times n} := \begin{bmatrix} W_1 \\ \vdots \\ W_m \end{bmatrix} = \begin{bmatrix} w_{1,1} & \cdots & w_{1,n} \\ \vdots & \vdots & \vdots \\ w_{m,1} & \cdots & w_{m,n} \end{bmatrix},$$

then the Kronecker Convolution of V and W , $V \circledast W \in \mathbb{C}^{pm \times (q+n-1)}$, is defined as follows:

$$V \circledast W := \begin{bmatrix} V_1 * W_1 \\ \vdots \\ V_1 * W_m \\ \vdots \\ V_p * W_1 \\ \vdots \\ V_p * W_m \end{bmatrix} \quad (9.3)$$

Definition 9.4 (Kronecker Inner Product)

Let

$$X \in \mathbb{C}^{p \times q} := \begin{bmatrix} X_1 \\ \vdots \\ X_p \end{bmatrix} = \begin{bmatrix} x_{1,1} & \cdots & x_{1,q} \\ \vdots & \vdots & \vdots \\ x_{p,1} & \cdots & x_{p,q} \end{bmatrix}$$

and

$$Y \in \mathbb{C}^{m \times q} := \begin{bmatrix} Y_1 \\ \vdots \\ Y_m \end{bmatrix} = \begin{bmatrix} y_{1,1} & \cdots & y_{1,q} \\ \vdots & \vdots & \vdots \\ y_{m,1} & \cdots & y_{m,q} \end{bmatrix},$$

then the Kronecker Inner Product of X and Y , $\mathcal{K}(\langle X, Y \rangle) \in \mathbb{C}^{pm \times 1}$, is defined as follows:

$$\mathcal{K}(\langle X, Y \rangle) := \begin{bmatrix} \langle X_1, Y_1 \rangle \\ \vdots \\ \langle X_1, Y_m \rangle \\ \vdots \\ \langle X_p, Y_1 \rangle \\ \vdots \\ \langle X_p, Y_m \rangle \end{bmatrix} \quad (9.4)$$

Definition 9.5 (Vector Operator)

Let

$$A \in \mathbb{C}^{p \times qL} := \begin{bmatrix} A_{11} & \cdots & A_{1q} \\ \vdots & \vdots & \vdots \\ A_{p1} & \cdots & A_{pq} \end{bmatrix},$$

then the Vector Operator acting on the matrix A , $\mathcal{V}_L(A) \in \mathbb{C}^{pq \times L}$, is defined as follows:

$$\mathcal{V}_L(A) := \begin{bmatrix} A_{11} \\ \vdots \\ A_{p1} \\ \vdots \\ A_{1q} \\ \vdots \\ A_{pq} \end{bmatrix} \quad (9.5)$$

Definition 9.6 (Matrix Operator)

Let

$$\tilde{A} \in \mathbb{C}^{pq \times L} := \begin{bmatrix} A_{11} \\ \vdots \\ A_{p1} \\ \vdots \\ A_{1q} \\ \vdots \\ A_{pq} \end{bmatrix},$$

then the Matrix Operator acting on the matrix $\tilde{A}$, $\mathcal{M}_{p \times qL}(\tilde{A}) \in \mathbb{C}^{p \times qL}$, is defined as follows:

$$\mathcal{M}_{p \times qL}(\tilde{A}) := \begin{bmatrix} A_{11} & \cdots & A_{1q} \\ \vdots & \vdots & \vdots \\ A_{p1} & \cdots & A_{pq} \end{bmatrix} \quad (9.6)$$

Remark 9.1 The Matrix Operator, $\mathcal{M}_{i \times LJ}(U)$, and the the Vector Operator, $\mathcal{V}_K(U)$, are inverse operations of each other only when $J = K$ and $U \in \mathbb{C}^{i \times LJ}$. Using the definitions of A and $\tilde{A}$ given above, note the following relationships:

$$\begin{aligned} A &= \mathcal{M}_{p \times qL}(\mathcal{V}_L(A)) \\ \tilde{A} &= \mathcal{V}_L(\mathcal{M}_{p \times qL}(\tilde{A})) \\ A &\neq \mathcal{M}_{q \times pL}(\mathcal{V}_L(A)) \\ \tilde{A} &\neq \mathcal{V}_L(\mathcal{M}_{q \times pL}(\tilde{A})) \end{aligned}$$

Remark 9.2 Let $A \in \mathbb{C}^{p \times q}$ and using the notation and definitions herein, observe that the standard vector operator found in the literature, $\text{vec}(A) = \mathcal{V}_1(A)$.

Remark 9.3 Throughout this chapter, let the matrix operator, $\mathcal{M}_{p \times qN}(\bullet)$ of definition 9.6, signify an operator on either continuous-time functions or discrete-time functions. For the case of continuous-time functions, N equals 1 and for the case of discrete-time functions, N equals the length of the corresponding discrete-time representation.

The remainder of this section will present the mathematical machinery necessary for solving the discrete H^2 control problem based on the LFT framework.

Figure 9.1: (a) Lower LFT $F_l(P, K_l)$, (b) Upper LFT $F_u(P, K_u)$

The discrete H^2 control design technique employed for comparison purposes herein is based on the matrix linear fractional transformation (LFT) framework and entails the solution of discrete algebraic Riccati equations. First, a very cursory review of the mathematics behind LFTs will be provided. Figure 9.1 provides a graphical representation of a lower LFT with respect to K_l and an upper LFT with respect to K_u . The formal definitions for lower and upper LFTs are presented in definition 9.7.

Definition 9.7 (Linear Fractional Transformations (LFTs))

Let $P \in \mathbb{C}^{(n_1+n_2) \times (m_1+m_2)}$ be a complex matrix partitioned according to:

$$P = \begin{bmatrix} P_{11} & P_{12} \\ P_{21} & P_{22} \end{bmatrix} \quad (9.7)$$

and let $K_l \in \mathbb{C}^{m_2 \times n_2}$ and $K_u \in \mathbb{C}^{m_1 \times n_1}$. A linear fractional transformation (LFT) is a complex mapping defined with respect to either K_l or K_u as follows:

Lower LFT: $\mathcal{F}_l(P, K_l) : \mathbb{C}^{m_2 \times n_2} \mapsto \mathbb{C}^{n_1 \times m_1}$

$$\mathcal{F}_l(P, K_l) := P_{11} + P_{12}K_l(I - P_{22}K_l)^{-1}P_{21} \quad (9.8)$$

provided that $(I - P_{22}K_l)^{-1}$ exists.

Upper LFT: $\mathcal{F}_u(P, K_u) : \mathbb{C}^{m_1 \times n_1} \mapsto \mathbb{C}^{n_2 \times m_2}$

$$\mathcal{F}_u(P, K_u) := P_{22} + P_{21}K_u(I - P_{11}K_u)^{-1}P_{12} \quad (9.9)$$

provided that $(I - P_{11}K_u)^{-1}$ exists.

In a control theory context, P is a proper transfer matrix representing the controlled plant, K is the controller or model uncertainty, and the LFTs $\mathcal{F}_l(P, K_l)$ and $\mathcal{F}_u(P, K_u)$ define the following closed-loop transfer matrices:

$$T_{zw} = \mathcal{F}_l(P, K_l), \quad T_{qv} = \mathcal{F}_u(P, K_u) \quad (9.10)$$

The main property of LFTs exploited by control theory is that any interconnection of LFTs is once again a LFT. The mathematical construct behind this property is the Redheffer star product shown in Figure 9.2 and defined formally as follows:

Definition 9.8 (Redheffer star product)

Let $P, K \in \mathcal{C}^{(n_1+n_2) \times (m_1+m_2)}$ be complex matrices partitioned according to:

$$P = \begin{bmatrix} P_{11} & P_{12} \\ P_{21} & P_{22} \end{bmatrix}, \quad K = \begin{bmatrix} K_{11} & K_{12} \\ K_{21} & K_{22} \end{bmatrix} \quad (9.11)$$

The Redheffer star product of P and K , with respect to the above partitionings, is defined as follows:

$$S(P, K) := \begin{bmatrix} \mathcal{F}_l(P, K_{11}) & P_{12}(I - K_{11}P_{22})^{-1}K_{12} \\ K_{21}(I - P_{22}K_{11})^{-1}P_{21} & \mathcal{F}_u(K, P_{22}) \end{bmatrix} \quad (9.12)$$

Figure 9.2: Redheffer Star Product

9.2 Multiresolutional Sensitivity Minimization

The feedback control system for this section is shown in Figure 9.3, where P is the plant to be controlled and W is the weight modeling the disturbances. The Wiener-Hopf approach to the

Figure 9.3: Feedback Control System For Sensitivity Minimization

sensitivity minimization problem involves finding an internally stabilizing controller, C , such that the following performance is achieved:

$$\mu := \min \|T_{zw}\|_2 = \inf_{C \text{ stabilizing } P} \|WS\|_2 \quad (9.13)$$

The sensitivity function for the feedback control system is given by:

$$S := (1 + PC)^{-1} \quad (9.14)$$

The sensitivity minimization problem has been studied by numerous researchers in terms of minimizing the H^2 norm and the H^∞ norm, see [58], [59], and [60] and the references contained therein.

Assumptions

1. $W \in RH^2$
2. $P \in H^2$

The first step in our multiresolutional controller development is to perform a Youla parameterization [61] for the controller C according to:

$$C = Q(1 - PQ)^{-1}, \quad Q \in H^\infty, \quad (1 - PQ) \neq 0 \quad (9.15)$$

The performance measure, equation 9.13, becomes

$$\mu = \inf_{Q \in H^\infty} \|W(1 - PQ)\|_2 \quad (9.16)$$

It can be assumed, without loss of generality, that W is outer function. This assumption is possible since any W can be decomposed using an inner-outer factorization into an inner function part, W_i ,

and an outer function part, W_o , according to $W = W_i W_o$. For any inner function, $\|W_i Q\| = \|Q\|$. With the assumption that W is an outer function, the following relationship holds:

$$\overline{\{ WQ : Q \in H^\infty \}} = H^2 \quad (9.17)$$

Applying equation 9.17 to equation 9.16 yields:

$$\mu = \inf_{\dot{Q} \in H^2} \|W - P\dot{Q}\|_2 \quad (9.18)$$

where $\dot{Q} = WQ$.

Our goal in developing a multiresolutional controller is to represent the plant, P , using its “best” orthonormal, Haar wavelet packet basis as follows:

$$p(\bullet) = \sum_{k=0}^{\infty} \beta_k \psi_{f_k, p_k}^{s_k}(\bullet) \quad (9.19)$$

$$(9.20)$$

Remark 9.4 For notational convenience, let $\psi_{f_k, p_k}^{s_k}(\bullet)$ signify either continuous-time basis functions, $\psi_{f_k, p_k}^{s_k}(t)$, or discrete-time basis functions $\psi_{f_k, p_k}^{s_k}(n)$, with $\bullet = t$ or $\bullet = n$ depending on whether the functions involved are continuous or discrete.

In addition, the disturbance weight W , and the controller parameter $\dot{Q}$ can be represented using their “best” orthonormal, Haar wavelet packet bases, which can be either the same orthonormal, Haar wavelet packet basis as the plant, $\psi_{f_k, p_k}^{s_k}(\bullet)$, or two completely different orthonormal, Haar wavelet packet bases. In the general case, the disturbance weight W , and the controller parameter $\dot{Q}$ will be represented by two different “best” orthonormal, Haar wavelet packet bases as follows:

$$w(\bullet) = \sum_{k=0}^{\infty} \alpha_k \tilde{\psi}_{f_k, p_k}^{s_k}(\bullet) \quad (9.21)$$

$$\dot{q}(\bullet) = \sum_{k=0}^{\infty} \gamma_k \dot{\psi}_{f_k, p_k}^{s_k}(\bullet) \quad (9.22)$$

The next theorem presents a practical, in general, suboptimal solution to the minimum sensitivity optimization problem, equation 9.18, using Haar wavelet packet representations for the signals W , P , and $\dot{Q}$.

Theorem 9.1 (Multiresolutional Sensitivity Minimization)

Let $W \in \mathcal{RH}^2$ be the weight modeling the disturbances and $P \in H^2$ be the plant to be controlled. Then the performance measure for the sensitivity minimization problem is given by:

$$\mu = \inf_{\dot{Q} \in H^2} \|W - P\dot{Q}\|_2 \quad (9.23)$$

Represent each of the quantities in 9.23 using a unique orthonormal, Haar wavelet packet basis composed of $L, M, K \in \mathbb{Z}^+$ elements respectively as follows:

$$\hat{w}(\bullet) = \sum_{k=0}^{L-1} \alpha_k \tilde{\psi}_{f_k, p_k}^{s_k}(\bullet) \approx w(\bullet) \quad (9.24)$$

$$\hat{p}(\bullet) = \sum_{k=0}^{M-1} \beta_k \dot{\psi}_{f_k, p_k}^{s_k}(\bullet) \approx p(\bullet) \quad (9.25)$$

$$\hat{q}_K(\bullet) = \sum_{k=0}^{K-1} \gamma_k \dot{\psi}_{f_k, p_k}^{s_k}(\bullet) \approx \dot{q}(\bullet) \quad (9.26)$$

The approximation to the performance measure of equation 9.23 is given by:

$$\hat{\mu} = \inf_{\hat{Q} \in H^2} \|\hat{W} - \hat{P}\hat{Q}\|_2 \approx \mu \quad (9.27)$$

The performance measure given by equation 9.27 is optimized by the gains

$$\gamma = \begin{bmatrix} \gamma_0 & \gamma_1 & \cdots & \gamma_{K-1} \end{bmatrix}^T$$

which are given by:

$$\gamma = A^{-1}b \quad (9.28)$$

where: $\begin{bmatrix} d_1 & \cdots & d_{K^2} \end{bmatrix} := (\beta \otimes \beta)^T \mathcal{K}(\langle \mathcal{M}_M \otimes \mathcal{K}_N(\dot{\psi} \otimes \dot{\psi}), \mathcal{M}_M \otimes \mathcal{K}_N(\dot{\psi} \otimes \dot{\psi}) \rangle);$
 $A = \{a_{i,j}\} = \{d_{K(i-1)+j} + d_{K(j-1)+i}\};$
 $b = 2 \left[(\alpha \otimes \beta)^T \mathcal{K}(\langle \dot{\psi}, \mathcal{M}_M \otimes \mathcal{K}_N(\dot{\psi} \otimes \dot{\psi}) \rangle) \right]^T.$

Proof: For notational convience, let $\psi_{f_k, p_k}^{s_k} := \psi_{f_k, p_k}^{s_k}(\bullet)$. Recall Plancherel's theorem, and represent the performance measure, equation 9.27, as an inner product:

$$J_K(\gamma) = \inf_{\hat{Q} \in H^2} \|\hat{W} - \hat{P}\hat{Q}\|_2^2 = \langle \hat{W} - \hat{P}\hat{Q}, \hat{W} - \hat{P}\hat{Q} \rangle = \langle \hat{w}, \hat{w} \rangle - 2\Re\{\langle \hat{w}, \hat{p} * \hat{q} \rangle\} + \langle \hat{p} * \hat{q}, \hat{p} * \hat{q} \rangle \quad (9.29)$$

The performance measure in equation 9.29 is to be examined on a term by term basis after appropriate substitution of the time domain representations of the signals $\hat{w}$, $\hat{p}$, and $\hat{q}$, see equations 9.25, 9.24 and 9.26:

$$\begin{aligned} \langle \hat{w}, \hat{w} \rangle &= \left\langle \sum_{i=0}^{L-1} \alpha_i \tilde{\psi}_{f_i, p_i}^{s_i}, \sum_{j=0}^{L-1} \alpha_j \tilde{\psi}_{f_j, p_j}^{s_j} \right\rangle \\ &= \sum_{i=0}^{L-1} \sum_{j=0}^{L-1} \alpha_i \alpha_j \langle \tilde{\psi}_{f_i, p_i}^{s_i}, \tilde{\psi}_{f_j, p_j}^{s_j} \rangle = \sum_{i=0}^{L-1} \alpha_i^2 \\ \langle \hat{w}, \hat{p} * \hat{q} \rangle &= \left\langle \sum_{i=0}^{L-1} \alpha_i \tilde{\psi}_{f_i, p_i}^{s_i}, \left(\sum_{j=0}^{M-1} \beta_j \dot{\psi}_{f_j, p_j}^{s_j} \right) * \left(\sum_{k=0}^{K-1} \gamma_k \dot{\psi}_{f_k, p_k}^{s_k} \right) \right\rangle \end{aligned} \quad (9.30)$$

$$= \left\langle \sum_{i=0}^{L-1} \alpha_i \tilde{\psi}_{f_i, p_i}^{s_i}, \sum_{j=0}^{M-1} \sum_{k=0}^{K-1} \beta_j \gamma_k \dot{\psi}_{f_j, p_j}^{s_j} * \dot{\psi}_{f_k, p_k}^{s_k} \right\rangle \quad (9.31)$$

$$\begin{aligned} \langle \hat{p} * \hat{q}, \hat{p} * \hat{q} \rangle &= \left\langle \left(\sum_{i=0}^{M-1} \beta_i \dot{\psi}_{f_i, p_i}^{s_i} \right) * \left(\sum_{j=0}^{K-1} \gamma_j \dot{\psi}_{f_j, p_j}^{s_j} \right), \right. \\ &\quad \left. \left(\sum_{k=0}^{M-1} \beta_k \dot{\psi}_{f_k, p_k}^{s_k} \right) * \left(\sum_{l=0}^{K-1} \gamma_l \dot{\psi}_{f_l, p_l}^{s_l} \right) \right\rangle \\ &= \left\langle \sum_{i=0}^{M-1} \sum_{j=0}^{K-1} \beta_i \gamma_j \dot{\psi}_{f_i, p_i}^{s_i} * \dot{\psi}_{f_j, p_j}^{s_j}, \sum_{k=0}^{M-1} \sum_{l=0}^{K-1} \beta_k \gamma_l \dot{\psi}_{f_k, p_k}^{s_k} * \dot{\psi}_{f_l, p_l}^{s_l} \right\rangle \end{aligned} \quad (9.32)$$

$$\mathcal{M}_{M \times KN}(\dot{\psi} \oplus \dot{\psi}) = \begin{bmatrix} \dot{\psi}_0 * \dot{\psi}_0 & \cdots & \dot{\psi}_0 * \dot{\psi}_{K-1} \\ \vdots & \ddots & \vdots \\ \dot{\psi}_{M-1} * \dot{\psi}_0 & \cdots & \dot{\psi}_{M-1} * \dot{\psi}_{K-1} \end{bmatrix} \quad (9.33)$$

$$\mathcal{K}(\langle \dot{\psi}, \mathcal{M}_{M \times KN}(\dot{\psi} \oplus \dot{\psi}) \rangle) := \begin{bmatrix} \langle \dot{\psi}_0, \dot{\psi}_0 * \dot{\psi}_0 \rangle & \cdots & \langle \dot{\psi}_0, \dot{\psi}_0 * \dot{\psi}_{K-1} \rangle \\ \vdots & \ddots & \vdots \\ \langle \dot{\psi}_0, \dot{\psi}_{M-1} * \dot{\psi}_0 \rangle & \cdots & \langle \dot{\psi}_0, \dot{\psi}_{M-1} * \dot{\psi}_{K-1} \rangle \\ \vdots & & \vdots \\ \langle \dot{\psi}_{L-1}, \dot{\psi}_0 * \dot{\psi}_0 \rangle & \cdots & \langle \dot{\psi}_{L-1}, \dot{\psi}_0 * \dot{\psi}_{K-1} \rangle \\ \vdots & \ddots & \vdots \\ \langle \dot{\psi}_{L-1}, \dot{\psi}_{M-1} * \dot{\psi}_0 \rangle & \cdots & \langle \dot{\psi}_{L-1}, \dot{\psi}_{M-1} * \dot{\psi}_{K-1} \rangle \end{bmatrix} \quad (9.34)$$

$$\begin{aligned} &\mathcal{K}(\langle \mathcal{M}_{M \times KN}(\dot{\psi} \oplus \dot{\psi}), \mathcal{M}_{M \times KN}(\dot{\psi} \oplus \dot{\psi}) \rangle) := \\ &\begin{bmatrix} \langle \dot{\psi}_0 * \dot{\psi}_0, \dot{\psi}_0 * \dot{\psi}_0 \rangle & \cdots & \langle \dot{\psi}_0 * \dot{\psi}_0, \dot{\psi}_0 * \dot{\psi}_{K-1} \rangle \\ \vdots & \ddots & \vdots & \cdots \\ \langle \dot{\psi}_0 * \dot{\psi}_0, \dot{\psi}_{M-1} * \dot{\psi}_0 \rangle & \cdots & \langle \dot{\psi}_0 * \dot{\psi}_0, \dot{\psi}_{M-1} * \dot{\psi}_{K-1} \rangle \\ \vdots & & \vdots & \cdots \\ \langle \dot{\psi}_{M-1} * \dot{\psi}_0, \dot{\psi}_0 * \dot{\psi}_0 \rangle & \cdots & \langle \dot{\psi}_{M-1} * \dot{\psi}_0, \dot{\psi}_0 * \dot{\psi}_{K-1} \rangle \\ \vdots & \ddots & \vdots & \cdots \\ \langle \dot{\psi}_{M-1} * \dot{\psi}_0, \dot{\psi}_{M-1} * \dot{\psi}_0 \rangle & \cdots & \langle \dot{\psi}_{M-1} * \dot{\psi}_0, \dot{\psi}_{M-1} * \dot{\psi}_{K-1} \rangle \end{bmatrix} \end{aligned}$$

$$\begin{bmatrix}
\langle \dot{\psi}_0 * \dot{\psi}_{K-1}, \dot{\psi}_0 * \dot{\psi}_0 \rangle & \cdots & \langle \dot{\psi}_0 * \dot{\psi}_{K-1}, \dot{\psi}_0 * \dot{\psi}_{K-1} \rangle \\
\vdots & \ddots & \vdots \\
\langle \dot{\psi}_0 * \dot{\psi}_{K-1}, \dot{\psi}_{M-1} * \dot{\psi}_0 \rangle & \cdots & \langle \dot{\psi}_0 * \dot{\psi}_{K-1}, \dot{\psi}_{M-1} * \dot{\psi}_{K-1} \rangle \\
\vdots & \ddots & \vdots \\
\langle \dot{\psi}_{M-1} * \dot{\psi}_{K-1}, \dot{\psi}_0 * \dot{\psi}_0 \rangle & \cdots & \langle \dot{\psi}_{M-1} * \dot{\psi}_{K-1}, \dot{\psi}_0 * \dot{\psi}_{K-1} \rangle \\
\vdots & \ddots & \vdots \\
\langle \dot{\psi}_{M-1} * \dot{\psi}_{K-1}, \dot{\psi}_{M-1} * \dot{\psi}_0 \rangle & \cdots & \langle \dot{\psi}_{M-1} * \dot{\psi}_{K-1}, \dot{\psi}_{M-1} * \dot{\psi}_{K-1} \rangle
\end{bmatrix} \quad (9.35)$$

Using definitions A.1, A.2, A.4, A.5, A.6, A.8, and A.9 given in appendix A, the Kronecker relationships presented in section 9.1, and equations 9.34 and 9.35, equations 9.30, 9.31 and 9.32 can be equivalently represented by the following lemmas, whose proofs are presented in appendix A:

Lemma 9.1

$$\langle \hat{w}, \hat{w} \rangle = \langle \alpha^T \tilde{\psi}, \alpha^T \tilde{\psi} \rangle = (\alpha \otimes \alpha)^T \mathcal{K}(\langle \tilde{\psi}, \tilde{\psi} \rangle) \quad (9.36)$$

Lemma 9.2

$$\langle \hat{w}, \hat{p} * \hat{q} \rangle = \langle \alpha^T \tilde{\psi}, (\beta^T \dot{\psi}) * (\gamma^T \dot{\psi}) \rangle = (\alpha \otimes \beta)^T \mathcal{K}(\langle \tilde{\psi}, \mathcal{M}_{M \times KN}(\dot{\psi} \oplus \dot{\psi}) \rangle) \gamma \quad (9.37)$$

Lemma 9.3

$$\begin{aligned}
\langle \hat{p} * \hat{q}, \hat{p} * \hat{q} \rangle &= \langle (\beta^T \dot{\psi}) * (\gamma^T \dot{\psi}), (\beta^T \dot{\psi}) * (\gamma^T \dot{\psi}) \rangle = \\
&(\beta \otimes \beta)^T \mathcal{K}(\langle \mathcal{M}_{M \times KN}(\dot{\psi} \oplus \dot{\psi}), \mathcal{M}_{M \times KN}(\dot{\psi} \oplus \dot{\psi}) \rangle) (\gamma \otimes \gamma)
\end{aligned} \quad (9.38)$$

The performance measure is to be minimized by choosing the optimal gains, γ , for the controller function $\hat{Q}$. The performance is optimized by the following necessary condition:

$$\nabla J_K(\gamma) := \left[\frac{\partial J_K}{\partial \gamma_0} \frac{\partial J_K}{\partial \gamma_1} \cdots \frac{\partial J_K}{\partial \gamma_{K-1}} \right] = 0 \quad (9.39)$$

Using lemmas 9.2 and 9.3 in the performance criterion 9.39 gives:

$$\begin{aligned}
\nabla J_K(\gamma) &= -2\Re \left\{ (\alpha \otimes \beta)^T \mathcal{K}(\langle \tilde{\psi}, \mathcal{M}_{M \times KN}(\dot{\psi} \oplus \dot{\psi}) \rangle) \frac{\partial \gamma}{\partial \gamma} \right\} + \\
&(\beta \otimes \beta)^T \mathcal{K}(\langle \mathcal{M}_{M \times KN}(\dot{\psi} \oplus \dot{\psi}), \mathcal{M}_{M \times KN}(\dot{\psi} \oplus \dot{\psi}) \rangle) \frac{\partial (\gamma \otimes \gamma)}{\partial \gamma}
\end{aligned}$$

$$\begin{aligned}
&= -2\Re \left\{ (\alpha \otimes \beta)^T \mathcal{K} \left(\langle \tilde{\psi}, \mathcal{M}_{M \times KN}(\dot{\psi} \oplus \dot{\psi}) \rangle \right) I_K \right\} + \\
&\quad (\beta \otimes \beta)^T \mathcal{K} \left(\langle \mathcal{M}_{M \times KN}(\dot{\psi} \oplus \dot{\psi}), \mathcal{M}_{M \times KN}(\dot{\psi} \oplus \dot{\psi}) \rangle \right) (\gamma \oplus \gamma) \\
&= 0
\end{aligned} \tag{9.40}$$

where $I_K := K \times K$ identity matrix and $\oplus$ is the Kronecker sum presented in definition 9.2. Equation 9.40 represents a system of K equations with K unknowns. It is desirable to be able to rearrange equation 9.40 so that the optimal γ 's can be solved for directly as follows:

$$A\gamma - b = 0 \tag{9.41}$$

where

$$A := \begin{bmatrix} A_0 & \cdots & A_{K-1} \end{bmatrix} = \begin{bmatrix} a_{0,0} & \cdots & a_{0,K-1} \\ \vdots & \vdots & \vdots \\ a_{K-1,0} & \cdots & a_{K-1,K-1} \end{bmatrix} \tag{9.42}$$

$$b := \begin{bmatrix} b_0 \\ \vdots \\ b_{K-1} \end{bmatrix} \tag{9.43}$$

Recalling the Kronecker sum definition 9.2, it follows that $\gamma \oplus \gamma = I_K \otimes \gamma + \gamma \otimes I_K$, which leads directly to the desired transformation matrices, T_i for each γ_i as follows:

$$T_i = I_K \otimes \begin{bmatrix} 0 \\ \vdots \\ 0 \\ i \\ 0 \\ \vdots \\ 0 \end{bmatrix} + \begin{bmatrix} 0 \\ \vdots \\ 0 \\ i \\ 0 \\ \vdots \\ 0 \end{bmatrix} \otimes I_K \tag{9.44}$$

$$A_i^T = (\beta \otimes \beta)^T \mathcal{K}(\langle \mathcal{M}_{M \times KN}(\dot{\psi} \oplus \dot{\psi}), \mathcal{M}_{M \times KN}(\dot{\psi} \oplus \dot{\psi}) \rangle) T_i \tag{9.45}$$

$$b_i = 2(\alpha \otimes \beta)^T \mathcal{K}(\langle \tilde{\psi}, \mathcal{M}_{M \times KN}(\dot{\psi} \oplus \dot{\psi}) \rangle) \begin{bmatrix} 0 \\ \vdots \\ 0 \\ i \\ 0 \\ \vdots \\ 0 \end{bmatrix} \tag{9.46}$$

Thus, equation 9.40 can be transformed as follows:

$$\nabla J_K(\gamma)^T = A\gamma - b = 0 \quad (9.47)$$

Define

$$\begin{bmatrix} d_1 & \cdots & d_{K^2} \end{bmatrix} := (\beta \otimes \beta)^T \mathcal{K}((\mathcal{M}_{M \times KN}(\dot{\psi} \oplus \dot{\psi}), \mathcal{M}_{M \times KN}(\dot{\psi} \oplus \dot{\psi}))) \quad (9.48)$$

Evaluating equations 9.45 and 9.46 $\forall i = 0, \dots, K-1$, results in the following equivalent representations for A and b :

$$A = \{a_{i,j}\} = \{d_{K(i-1)+j} + d_{K(j-1)+i}\} \quad (9.49)$$

$$b = 2 \left[(\alpha \otimes \beta)^T \mathcal{K}((\dot{\psi}, \mathcal{M}_{M \times KN}(\dot{\psi} \oplus \dot{\psi}))) \right]^T \quad (9.50)$$

Equation 9.47 can then be solved for the gains, γ , as follows:

$$\gamma = A^{-1}b \quad \blacksquare$$

Recall the following lemma, [62], [63], which gives the necessary and sufficient condition satisfied by the global minimum γ^* of the convex cost function, $J(\gamma)$ of equation 9.29.

Lemma 9.4 ([62],[63])

If $J(\gamma) : \mathbb{R}^K \mapsto \mathbb{R}$ is continuously differentiable, i.e, the partial derivatives $\frac{\partial J}{\partial \gamma_0}, \dots, \frac{\partial J}{\partial \gamma_{K-1}}$ exist for every $\gamma \in \mathbb{R}^K$ and the partial derivatives are continuous functions of γ , and is convex over $\mathbb{R}^K$, then γ^* is a global minimum for 9.40 $\iff$

$$\nabla J(\gamma^*) = 0$$

Remark 9.5 The existence of the solution for the free controller parameter gains, $\gamma \in \mathbb{R}^K$, given by equation 9.28, ensures that $J_K(\gamma)$ is a global minimum for the optimization problem posed by theorem 9.1, equation 9.27, as a function of K . Denote the optimal gamma for a given K by γ_K^* . However, the optimization problem given by equation 9.27, is also dependent on the approximation of the system quantities given by equations 9.24 and 9.25. However, $\exists \mathcal{L}$ and $\exists \mathcal{M}$, such that for each $L \geq \mathcal{L}$ and $M \geq \mathcal{M}$, the following are true:

$$\begin{aligned} \|w - \hat{w}\|_2 &= \langle w - \hat{w}, w - \hat{w} \rangle \\ &= \langle w, w \rangle - 2\Re\{\langle w, \hat{w} \rangle\} + \langle \hat{w}, \hat{w} \rangle \\ &= \sum_{i=0}^{\infty} \alpha_i^2 - 2 \sum_{j=0}^{L-1} \alpha_j^2 + \sum_{k=0}^{L-1} \alpha_k^2 \end{aligned}$$

$$= \sum_{i=L}^{\infty} \alpha_i^2 \leq \epsilon^2 \quad (9.51)$$

$$\begin{aligned} \|\hat{p} - p\|_2 &= \langle p - \hat{p}, p - \hat{p} \rangle \\ &= \sum_{j=M}^{\infty} \beta_j^2 \leq \epsilon^2 \end{aligned} \quad (9.52)$$

It can be shown that $\exists \epsilon_K$ such that for every $\delta_K > 0$ and $|\gamma^* - \gamma_K| < \delta_K$ that $|J^* - J_K| < \epsilon_K$.

Remark 9.6 Theorem 9.1 is applicable to signals whose finite wavelet representations are all of different lengths. The resultant sensitivity gains, γ , presented in Theorem 9.1, are, in general, suboptimal due to L , M , and K being finite. The calculation of the multiresolutional, minimum sensitivity gains presented in theorem 9.1 is very straightforward. If a unique, arbitrary Haar wavelet packet basis is used to represent each of the quantities in theorem 9.1, then the corresponding continuous inner products are determined explicitly by using theorem 8.6. The corresponding discrete inner products are calculated by using the discrete equivalent of theorem 8.6, lemma 8.12.

Remark 9.7 The (sub)optimal controller, C_K , as a function of the free controller parameter $\hat{Q}$, is presented in figure 9.4, which equals the following:

Figure 9.4: Multiresolutional Controller C_K Signal Block Diagram

$$C_K = \hat{W}^{-1} \hat{Q} (1 - \hat{P} \hat{W}^{-1} \hat{Q})^{-1}, \quad \hat{W}^{-1} \hat{Q} \in H^\infty, \quad (1 - \hat{P} \hat{W}^{-1} \hat{Q}) \neq 0 \quad (9.53)$$

9.3 Multiresolutional Mixed Sensitivity Minimization

The feedback control system for this section is shown in Figures 9.5 and 9.6, where P is the plant to be controlled, W_1 is the weight modeling the disturbances, and W_2 is the weight modeling the performance objectives. The Wiener-Hopf approach to the mixed sensitivity minimization

Figure 9.5: Feedback Control System For Mixed Sensitivity Minimization

Figure 9.6: Equivalent Feedback Control System For Mixed Sensitivity Minimization

problem involves finding an internally stabilizing controller, C , such that the following performance

is achieved:

$$\mu_2 := \min \|T_{zw}\|_2 = \inf_{C \text{ stabilizing } P} \left\| \begin{bmatrix} W_1 S & W_2 T \end{bmatrix} \right\|_2 = \inf_{C \text{ stabilizing } P} \left\| \begin{bmatrix} W_1 S \\ W_2 T \end{bmatrix} \right\|_2 \quad (9.54)$$

The sensitivity function for the feedback control system, S , was given previously by equation 9.14.

The complementary sensitivity function for the feedback control system, T , is given by:

$$T := PC(1 + PC)^{-1} \quad (9.55)$$

The mixed sensitivity minimization problem has been studied by researchers in terms of minimizing the H^2 norm and the H^∞ norm, see [59], [57], and the references contained therein.

Assumptions

1. $W_1 \in RH^2$.
2. $W_2 P \in RH^2$.
3. $P \in RH^2$.

Again, the first step in the multiresolutional controller development is to perform a Youla parameterization [61] for the controller C according to equation 9.15. The performance measure, equation 9.54, becomes

$$\mu_2 = \inf_{Q \in H^\infty} \left\| \begin{bmatrix} W_1(1 - PQ) & W_2 PQ \end{bmatrix} \right\|_2 \quad (9.56)$$

$$(9.57)$$

The plant, P , can be represented using any orthonormal, Haar wavelet packet basis as given by equation 9.19. The disturbance weight W_1 , the performance weight W_2 , and the controller function Q can similarly be represented using any orthonormal, Haar wavelet packet bases, which can be either the same orthonormal, Haar wavelet packet basis as the plant, $\hat{\psi}_{f_k, p_k}^{s_k}(\bullet)$, or three completely different orthonormal, Haar wavelet packet bases. In the general case, the disturbance weight W_1 , the performance weight W_2 , and the controller function Q will be represented by three different “best” orthonormal, Haar wavelet packet bases as follows:

$$w_1(\bullet) = \sum_{k=0}^{\infty} \alpha_k \hat{\psi}_{f_k, p_k}^{s_k}(\bullet) \quad (9.58)$$

$$w_2(\bullet)p(\bullet) = \sum_{k=0}^{\infty} \nu_k \hat{\psi}_{f_k, p_k}^{s_k}(\bullet) \quad (9.59)$$

$$q(\bullet) = \sum_{k=0}^{\infty} \gamma_k \hat{\psi}_{f_k, p_k}^{s_k}(\bullet) \quad (9.60)$$

The next theorem presents a practical, in general, suboptimal solution to the mixed sensitivity optimization problem, equation 9.57, using Haar wavelet packet representations for the signals W_1 , W_2 , P , and Q .

Theorem 9.2 (Multiresolutional Mixed Sensitivity Minimization)

Let $W_1 \in \mathcal{RH}^2$ be the weight modeling the disturbances, $W_2 \in \mathcal{RH}^2$ be the weight modeling the desired performance and $P \in \mathcal{RH}^2$ be the plant to be controlled. Then the performance measure for the sensitivity minimization problem is given by:

$$\mu_2 = \inf_{Q \in \mathcal{RH}^2} \left\| \begin{bmatrix} W_1(1 - PQ) & W_2PQ \end{bmatrix} \right\|_2 \quad (9.61)$$

Represent each of the quantities in 9.61 using a unique orthonormal, Haar wavelet packet basis composed of $L, M, K \in \mathbb{Z}^+$ elements respectively as follows:

$$\hat{w}_1(\bullet) = \sum_{k=0}^{L-1} \alpha_k \tilde{\psi}_{f_k, p_k}^{s_k}(\bullet) \approx w_1(\bullet) \quad (9.62)$$

$$\hat{w}_2(\bullet) = \sum_{k=0}^{J-1} \nu_k \tilde{\psi}_{f_k, p_k}^{s_k}(\bullet) \approx w_2(\bullet)p(\bullet) \quad (9.63)$$

$$\hat{p}(\bullet) = \sum_{k=0}^{M-1} \beta_k \dot{\psi}_{f_k, p_k}^{s_k}(\bullet) \approx p(\bullet) \quad (9.64)$$

$$\hat{q}_K(\bullet) = \sum_{k=0}^{K-1} \gamma_k \dot{\psi}_{f_k, p_k}^{s_k}(\bullet) \approx q(\bullet) \quad (9.65)$$

The approximation to the performance measure of equation 9.61 is given by:

$$\hat{\mu}_2 = \inf_{\hat{Q} \in \mathcal{RH}^2} \left\| \begin{bmatrix} \hat{W}_1(1 - \hat{P}\hat{Q}) & \hat{W}_2\hat{Q} \end{bmatrix} \right\|_2 \quad (9.66)$$

The performance measure given by equation 9.66 is optimized by the gains

$$\gamma = \begin{bmatrix} \gamma_0 & \gamma_1 & \cdots & \gamma_{K-1} \end{bmatrix}^T$$

which are given by:

$$\gamma = A^{-1}b \quad (9.67)$$

where: $\begin{bmatrix} d_1 & \cdots & d_{K^2} \end{bmatrix} := \left((\alpha \otimes \beta \otimes \alpha \otimes \beta)^T \mathcal{K}(\langle \tilde{\psi} \otimes \mathcal{M}_{M \times KN}(\dot{\psi} \otimes \dot{\psi}), \tilde{\psi} \otimes \mathcal{M}_{M \times KN}(\dot{\psi} \otimes \dot{\psi}) \rangle) \right. \\ \left. + (\nu \otimes \nu)^T \mathcal{K}(\langle \mathcal{M}_{M \times KN}(\dot{\psi} \otimes \tilde{\psi}), \mathcal{M}_{M \times KN}(\dot{\psi} \otimes \tilde{\psi}) \rangle) \right);$

$$A = \{a_{ij}\} = \{d_{K(i-1)+j} + d_{K(j-1)+i}\};$$

$$b = 2 \left[(\alpha \otimes \alpha \otimes \beta)^T \mathcal{K}(\langle \tilde{\psi}, \tilde{\psi} \otimes \mathcal{M}_{M \times KN}(\dot{\psi} \otimes \dot{\psi}) \rangle) \right]^T.$$

Proof: Recall Plancherel's theorem and represent the performance measure, equation 9.66, as an inner product:

$$J_K = \inf_{Q \in \mathcal{RH}^2} \left\| \begin{bmatrix} \hat{W}_1(1 - \hat{P}\hat{Q}) & \hat{W}_2\hat{Q} \end{bmatrix} \right\|_2^2 = \left\| \hat{W}_1(1 - \hat{P}\hat{Q}) \right\|_2^2 + \left\| \hat{W}_2\hat{Q} \right\|_2^2 \quad (9.68)$$

$$= \langle \hat{W}_1(1 - \hat{P}\hat{Q}), \hat{W}_1(1 - \hat{P}\hat{Q}) \rangle + \langle \hat{W}_2\hat{Q}, \hat{W}_2\hat{Q} \rangle \quad (9.69)$$

$$= \langle \hat{w}_1, \hat{w}_1 \rangle - 2\Re\{\langle \hat{w}_1, \hat{w}_1 * \hat{p} * \hat{q} \rangle\} + \langle \hat{w}_1 * \hat{p} * \hat{q}, \hat{w}_1 * \hat{p} * \hat{q} \rangle + \langle \hat{w}_2 * \hat{q}, \hat{w}_2 * \hat{q} \rangle \quad (9.70)$$

The performance measure of equation 9.70 is examined on a term by term basis after appropriate substitution of the time domain representations of the signals $\hat{w}_1$, $\hat{w}_2$, $\hat{p}$, and $\hat{q}$, see equations 9.62, 9.63, 9.64, and 9.65 and recall equation 9.30 with $\hat{w} = \hat{w}_1$:

$$\begin{aligned} \langle \hat{w}_1, \hat{w}_1 * \hat{p} * \hat{q} \rangle &= \left\langle \sum_{i=0}^{L-1} \alpha_i \tilde{\psi}_{f_i, p_i}^{s_i}, \left(\sum_{j=0}^{L-1} \alpha_j \tilde{\psi}_{f_j, p_j}^{s_j} \right) * \left(\sum_{k=0}^{M-1} \beta_k \dot{\psi}_{f_k, p_k}^{s_k} \right) * \left(\sum_{l=0}^{K-1} \gamma_l \dot{\psi}_{f_l, p_l}^{s_l} \right) \right\rangle \\ &= \left\langle \sum_{i=0}^{L-1} \alpha_i \tilde{\psi}_{f_i, p_i}^{s_i}, \sum_{j=0}^{L-1} \sum_{k=0}^{M-1} \sum_{l=0}^{K-1} \alpha_j \beta_k \gamma_l \tilde{\psi}_{f_j, p_j}^{s_j} * \dot{\psi}_{f_k, p_k}^{s_k} * \dot{\psi}_{f_l, p_l}^{s_l} \right\rangle \end{aligned} \quad (9.71)$$

$$\begin{aligned} \langle \hat{w}_1 * \hat{p} * \hat{q}, \hat{w}_1 * \hat{p} * \hat{q} \rangle &= \left\langle \left(\sum_{i=0}^{L-1} \alpha_i \tilde{\psi}_{f_i, p_i}^{s_i} \right) * \left(\sum_{j=0}^{M-1} \beta_j \dot{\psi}_{f_j, p_j}^{s_j} \right) * \left(\sum_{k=0}^{K-1} \gamma_k \dot{\psi}_{f_k, p_k}^{s_k} \right), \right. \\ &\quad \left. \left(\sum_{l=0}^{L-1} \alpha_l \tilde{\psi}_{f_l, p_l}^{s_l} \right) * \left(\sum_{m=0}^{M-1} \beta_m \dot{\psi}_{f_m, p_m}^{s_m} \right) * \left(\sum_{n=0}^{K-1} \gamma_n \dot{\psi}_{f_n, p_n}^{s_n} \right) \right\rangle \\ &= \left\langle \sum_{i=0}^{L-1} \sum_{j=0}^{M-1} \sum_{k=0}^{K-1} \alpha_i \beta_j \gamma_k \tilde{\psi}_{f_i, p_i}^{s_i} * \dot{\psi}_{f_j, p_j}^{s_j} * \dot{\psi}_{f_k, p_k}^{s_k}, \right. \\ &\quad \left. \sum_{l=0}^{L-1} \sum_{m=0}^{M-1} \sum_{n=0}^{K-1} \alpha_l \beta_m \gamma_n \tilde{\psi}_{f_l, p_l}^{s_l} * \dot{\psi}_{f_m, p_m}^{s_m} * \dot{\psi}_{f_n, p_n}^{s_n} \right\rangle \end{aligned} \quad (9.72)$$

$$\begin{aligned} \langle \hat{w}_2 * \hat{q}, \hat{w}_2 * \hat{q} \rangle &= \left\langle \left(\sum_{i=0}^{J-1} \nu_i \tilde{\psi}_{f_i, p_i}^{s_i} \right) * \left(\sum_{k=0}^{K-1} \gamma_k \dot{\psi}_{f_k, p_k}^{s_k} \right), \right. \\ &\quad \left. \left(\sum_{l=0}^{J-1} \nu_l \tilde{\psi}_{f_l, p_l}^{s_l} \right) * \left(\sum_{n=0}^{K-1} \gamma_n \dot{\psi}_{f_n, p_n}^{s_n} \right) \right\rangle \\ &= \left\langle \sum_{i=0}^{J-1} \sum_{k=0}^{K-1} \nu_i \gamma_k \tilde{\psi}_{f_i, p_i}^{s_i} * \dot{\psi}_{f_k, p_k}^{s_k}, \right. \\ &\quad \left. \sum_{l=0}^{J-1} \sum_{n=0}^{K-1} \nu_l \gamma_n \tilde{\psi}_{f_l, p_l}^{s_l} * \dot{\psi}_{f_n, p_n}^{s_n} \right\rangle \end{aligned} \quad (9.73)$$

$$\mathcal{K}(\langle \tilde{\psi}, \tilde{\psi} \otimes \mathcal{M}_{M \times KN}(\dot{\psi} \otimes \dot{\psi}) \rangle) :=$$

$$\begin{bmatrix}
\langle \tilde{\psi}_0, \tilde{\psi}_0 * \dot{\psi}_0 * \dot{\psi}_0 \rangle & \cdots & \langle \tilde{\psi}_0, \tilde{\psi}_0 * \dot{\psi}_0 * \dot{\psi}_{K-1} \rangle \\
\vdots & \ddots & \vdots \\
\langle \tilde{\psi}_0, \tilde{\psi}_{L-1} * \dot{\psi}_{M-1} * \dot{\psi}_0 \rangle & \cdots & \langle \tilde{\psi}_0, \tilde{\psi}_{L-1} * \dot{\psi}_{M-1} * \dot{\psi}_{K-1} \rangle \\
\vdots & & \vdots \\
\langle \tilde{\psi}_{L-1}, \tilde{\psi}_0 * \dot{\psi}_0 * \dot{\psi}_0 \rangle & \cdots & \langle \tilde{\psi}_{L-1}, \tilde{\psi}_0 * \dot{\psi}_0 * \dot{\psi}_{K-1} \rangle \\
\vdots & \ddots & \vdots \\
\langle \tilde{\psi}_{L-1}, \tilde{\psi}_{L-1} * \dot{\psi}_{M-1} * \dot{\psi}_0 \rangle & \cdots & \langle \tilde{\psi}_{L-1}, \tilde{\psi}_{L-1} * \dot{\psi}_{M-1} * \dot{\psi}_{K-1} \rangle
\end{bmatrix} \quad (9.74)$$

$$\mathcal{K}((\tilde{\psi} \otimes \mathcal{M}_{M \times KN}(\dot{\psi} \otimes \dot{\psi}), \tilde{\psi} \otimes \mathcal{M}_{M \times KN}(\dot{\psi} \otimes \dot{\psi}))) := \quad (9.75)$$

$$\begin{bmatrix}
\langle \tilde{\psi}_0 * \dot{\psi}_0 * \dot{\psi}_0, \tilde{\psi}_0 * \dot{\psi}_0 * \dot{\psi}_0 \rangle & \cdots & \langle \tilde{\psi}_0 * \dot{\psi}_0 * \dot{\psi}_0, \tilde{\psi}_0 * \dot{\psi}_0 * \dot{\psi}_{K-1} \rangle \\
\vdots & \ddots & \vdots & \cdots \\
\langle \tilde{\psi}_0 * \dot{\psi}_0 * \dot{\psi}_0, \tilde{\psi}_0 * \dot{\psi}_{M-1} * \dot{\psi}_0 \rangle & \cdots & \langle \tilde{\psi}_0 * \dot{\psi}_0 * \dot{\psi}_0, \tilde{\psi}_0 * \dot{\psi}_{M-1} * \dot{\psi}_{K-1} \rangle \\
\vdots & & \vdots & \cdots \\
\langle \tilde{\psi}_{L-1} * \dot{\psi}_0 * \dot{\psi}_0, \tilde{\psi}_0 * \dot{\psi}_0 * \dot{\psi}_0 \rangle & \cdots & \langle \tilde{\psi}_{L-1} * \dot{\psi}_0 * \dot{\psi}_0, \tilde{\psi}_0 * \dot{\psi}_0 * \dot{\psi}_{K-1} \rangle \\
\vdots & \ddots & \vdots & \cdots \\
\langle \tilde{\psi}_{L-1} * \dot{\psi}_0 * \dot{\psi}_0, \tilde{\psi}_0 * \dot{\psi}_{M-1} * \dot{\psi}_0 \rangle & \cdots & \langle \tilde{\psi}_{L-1} * \dot{\psi}_0 * \dot{\psi}_0, \tilde{\psi}_0 * \dot{\psi}_{M-1} * \dot{\psi}_{K-1} \rangle \\
\langle \tilde{\psi}_0 * \dot{\psi}_{M-1} * \dot{\psi}_{K-1}, \tilde{\psi}_{L-1} * \dot{\psi}_0 * \dot{\psi}_0 \rangle & \cdots & \langle \tilde{\psi}_0 * \dot{\psi}_{M-1} * \dot{\psi}_{K-1}, \tilde{\psi}_{L-1} * \dot{\psi}_0 * \dot{\psi}_{K-1} \rangle \\
\vdots & \ddots & \vdots & \cdots \\
\langle \tilde{\psi}_0 * \dot{\psi}_{M-1} * \dot{\psi}_{K-1}, \tilde{\psi}_{L-1} * \dot{\psi}_{M-1} * \dot{\psi}_0 \rangle & \cdots & \langle \tilde{\psi}_0 * \dot{\psi}_{M-1} * \dot{\psi}_{K-1}, \tilde{\psi}_{L-1} * \dot{\psi}_{M-1} * \dot{\psi}_{K-1} \rangle \\
\vdots & & \vdots & \cdots \\
\langle \tilde{\psi}_{L-1} * \dot{\psi}_{M-1} * \dot{\psi}_{K-1}, \tilde{\psi}_{L-1} * \dot{\psi}_0 * \dot{\psi}_0 \rangle & \cdots & \langle \tilde{\psi}_{L-1} * \dot{\psi}_{M-1} * \dot{\psi}_{K-1}, \tilde{\psi}_{L-1} * \dot{\psi}_0 * \dot{\psi}_{K-1} \rangle \\
\vdots & \ddots & \vdots & \cdots \\
\langle \tilde{\psi}_{L-1} * \dot{\psi}_{M-1} * \dot{\psi}_{K-1}, \tilde{\psi}_{L-1} * \dot{\psi}_{M-1} * \dot{\psi}_0 \rangle & \cdots & \langle \tilde{\psi}_{L-1} * \dot{\psi}_{M-1} * \dot{\psi}_{K-1}, \tilde{\psi}_{L-1} * \dot{\psi}_{M-1} * \dot{\psi}_{K-1} \rangle
\end{bmatrix}$$

Using definitions A.1, A.2, A.4, A.5, A.3, A.6, A.7, A.8, and A.9 presented in appendix A, the Kronecker relationships given in section 9.1, and equations 9.74, 9.75 and 9.35 with $\hat{w}_2$ replacing $\hat{p}$, equations 9.71, 9.72 and 9.73 can be equivalently represented by the following lemmas, which are proven in appendix A:

Lemma 9.5

$$\begin{aligned}
\langle w_1, w_1 * p * q \rangle &= \langle \alpha^T \tilde{\psi}, (\alpha^T \tilde{\psi}) * (\beta^T \dot{\psi}) * (\gamma^T \dot{\psi}) \rangle \\
&= (\alpha \otimes \alpha \otimes \beta)^T \mathcal{K}((\tilde{\psi}, \tilde{\psi} \otimes \mathcal{M}_{M \times KN}(\dot{\psi} \otimes \dot{\psi}))) \gamma
\end{aligned} \quad (9.76)$$

Lemma 9.6

$$\begin{aligned} \langle w_1 * p * q, w_1 * p * q \rangle &= \langle (\alpha^T \tilde{\psi}) * (\beta^T \dot{\psi}) * (\gamma^T \dot{\psi}), (\alpha^T \tilde{\psi}) * (\beta^T \dot{\psi}) * (\gamma^T \dot{\psi}) \rangle \\ &= (\alpha \otimes \beta \otimes \alpha \otimes \beta)^T \mathcal{K}(\langle \tilde{\psi} \otimes \mathcal{M}_{M \times KN}(\dot{\psi} \otimes \dot{\psi}), \tilde{\psi} \otimes \mathcal{M}_{M \times KN}(\dot{\psi} \otimes \dot{\psi}) \rangle) (\gamma \otimes \gamma) \end{aligned} \quad (9.77)$$

Lemma 9.7

$$\begin{aligned} \langle w_2 * q, w_2 * q \rangle &= \langle (\nu^T \tilde{\psi}) * (\gamma^T \dot{\psi}), (\nu^T \tilde{\psi}) * (\gamma^T \dot{\psi}) \rangle \\ &= (\nu \otimes \nu)^T \mathcal{K}(\langle \mathcal{M}_{M \times KN}(\dot{\psi} \otimes \tilde{\psi}), \mathcal{M}_{M \times KN}(\dot{\psi} \otimes \tilde{\psi}) \rangle) (\gamma \otimes \gamma) \end{aligned} \quad (9.78)$$

The performance measure is minimized by choosing the optimal gains, γ , for the controller function Q . The performance is optimized by the following necessary condition:

$$\nabla J_K(\gamma) = \left[\frac{\partial J_K}{\partial \gamma_0} \frac{\partial J_K}{\partial \gamma_1} \dots \frac{\partial J_K}{\partial \gamma_{K-1}} \right] = 0 \quad (9.79)$$

Using lemmas 9.5, 9.6 and 9.7 in the performance criterion 9.79 :

$$\begin{aligned} \nabla J_K(\gamma) &= -2\Re \left\{ (\alpha \otimes \alpha \otimes \beta)^T \mathcal{K}(\langle \tilde{\psi}, \tilde{\psi} \otimes \mathcal{M}_{M \times KN}(\dot{\psi} \otimes \dot{\psi}) \rangle) \frac{\partial \gamma}{\partial \gamma} \right\} + \\ &\quad \left((\alpha \otimes \beta \otimes \alpha \otimes \beta)^T \mathcal{K}(\langle \tilde{\psi} \otimes \mathcal{M}_{M \times KN}(\dot{\psi} \otimes \dot{\psi}), \tilde{\psi} \otimes \mathcal{M}_{M \times KN}(\dot{\psi} \otimes \dot{\psi}) \rangle) + \right. \\ &\quad \left. (\nu \otimes \nu)^T \mathcal{K}(\langle \mathcal{M}_{M \times KN}(\dot{\psi} \otimes \tilde{\psi}), \mathcal{M}_{M \times KN}(\dot{\psi} \otimes \tilde{\psi}) \rangle) \right) \frac{(\gamma \otimes \gamma)}{\partial \gamma} \\ &= -2\Re \left\{ (\alpha \otimes \alpha \otimes \beta)^T \mathcal{K}(\langle \tilde{\psi}, \tilde{\psi} \otimes \mathcal{M}_{M \times KN}(\dot{\psi} \otimes \dot{\psi}) \rangle) I_K \right\} + \\ &\quad \left((\alpha \otimes \beta \otimes \alpha \otimes \beta)^T \mathcal{K}(\langle \tilde{\psi} \otimes \mathcal{M}_{M \times KN}(\dot{\psi} \otimes \dot{\psi}), \tilde{\psi} \otimes \mathcal{M}_{M \times KN}(\dot{\psi} \otimes \dot{\psi}) \rangle) + \right. \\ &\quad \left. (\nu \otimes \nu)^T \mathcal{K}(\langle \mathcal{M}_{M \times KN}(\dot{\psi} \otimes \tilde{\psi}), \mathcal{M}_{M \times KN}(\dot{\psi} \otimes \tilde{\psi}) \rangle) \right) (\gamma \oplus \gamma) \\ &= 0 \end{aligned} \quad (9.80)$$

where $I_K := K \times K$ identity matrix and $\oplus$ is the Kronecker sum presented in definition 9.2. Equation 9.80 represents a system of K equations with K unknowns, very similar to equation 9.40. Equation 9.40 was transformed into equation 9.47 and similarly, equation 9.80 can be rearranged as follows:

$$\nabla J_K(\gamma)^T = A\gamma - b = 0 \quad (9.81)$$

Using the corresponding form of equations 9.45 and 9.46 presented in the proof of theorem 9.1, the desired A and b in this case are equivalent to the following:

$$A = \{a_{ij}\} = \{d_{K(i-1)+j} + d_{K(j-1)+i}\} \quad (9.82)$$

$$b = 2 \left[(\alpha \otimes \alpha \otimes \beta)^T \mathcal{K}(\langle \tilde{\psi}, \tilde{\psi} \otimes \mathcal{M}_{M \times KN}(\dot{\psi} \otimes \dot{\psi}) \rangle) \right]^T \quad (9.83)$$

with

$$\begin{bmatrix} d_1 & \cdots & d_{K^2} \end{bmatrix} := \left((\alpha \otimes \beta \otimes \alpha \otimes \beta)^T \mathcal{K}(\langle \tilde{\psi} \oplus \mathcal{M}_{M \times KN}(\tilde{\psi} \oplus \tilde{\psi}), \tilde{\psi} \oplus \mathcal{M}_{M \times KN}(\tilde{\psi} \oplus \tilde{\psi}) \rangle) + (\nu \otimes \nu)^T \mathcal{K}(\langle \mathcal{M}_{M \times KN}(\tilde{\psi} \oplus \tilde{\psi}), \mathcal{M}_{M \times KN}(\tilde{\psi} \oplus \tilde{\psi}) \rangle) \right) \quad (9.84)$$

Equation 9.81 can be solved for the gains, γ , as follows:

$$\gamma = A^{-1}b \quad \blacksquare$$

Remark 9.8 The resultant mixed sensitivity gains, γ , presented in theorem 9.2, are, in general, suboptimal. The calculation of the multiresolutional, minimum mixed sensitivity gains presented in theorem 9.2 is very practical. If a unique, arbitrary wavelet packet basis is used to represent each of the quantities in theorem 9.2, then the corresponding continuous inner products are determined explicitly by using theorem 8.6 and the corresponding discrete inner products are calculated by using lemma 8.12.

Remark 9.9 Observe that if the stronger assumption $W_2 \in RH^2$ holds, then theorem 9.2 is also directly applicable with very minor but obvious modifications.

Remark 9.10 The (sub)optimal controller, C_K , as a function of the free controller parameter $\hat{Q}$, is most easily implemented using a feedback configuration as was presented in figure 9.4 with $\hat{Q}$ replacing $\hat{W}^1 \hat{Q}$ and is given in equation form as follows:

$$C_K = \hat{Q}(1 - \hat{P}\hat{Q})^{-1}, \quad \hat{Q} \in RH^2, \quad (1 - \hat{P}\hat{Q}) \neq 0 \quad (9.85)$$

Remark 9.11 Remark 9.5 holds in this case as well.

Remark 9.12 Recall theorem 7.1, which demonstrates that Haar wavelet packets can be generated from a sum of Haar scaling functions. Section 7.5 demonstrated that equivalent sampled versions of the selected orthonormal Haar wavelet packet basis functions can be determined using theorem 7.1, equation 7.46. The convolution of $N + 1$ Haar scaling functions yields a compactly supported B-spline of degree N , $\mathcal{B}_N(t)$, see lemma 8.7. Also recall that the convolution of $N + 1$ sampled Haar wavelet packet basis functions corresponds to a sampled, generalized B-spline packet basis function of order N as was shown by lemma 8.11. The convolution of Haar wavelet packet basis functions carried out in the solution of the controller gains, γ , results in basis functions which are a generalization of the first degree B-splines, see theorem 9.1, and of the second degree B-splines, see theorem 9.2.

Remark 9.13 Computation of the multiresolutional controller gains, γ , presented in theorems 9.1 and 9.2 is very straightforward. The continuous inner products are determined explicitly using theorem 8.6. The discrete inner products are determined by the discrete equivalent of theorem 8.6, lemma 8.12. Therefore, the computation and implementation of these multiresolutional controllers is very practical.

9.4 Discrete H^2 Control

In this section, the design of discrete H^2 controllers based on the LFT framework for the control systems given in Figures 9.3 and 9.5, or equivalently 9.6, will be outlined. This presentation will be a brief recapitulation of the discrete H^2 controller development described in [57] to be used in chapter 10 for comparison purposes with the multiresolutional controllers presented in sections 9.2 and 9.3. Let the original system matrix, $G(z)$, be parameterized as follows:

$$G(z) = \left[\begin{array}{c|cc} A & B_1 & B_2 \\ \hline C_1 & D_{11} & D_{12} \\ C_2 & D_{21} & D_{22} \end{array} \right] = \begin{bmatrix} G_{11} & G_{12} \\ G_{21} & G_{22} \end{bmatrix} \quad (9.86)$$

Figure 9.7: Youla Parameterization for stable plants using LFTs

A Youla parameterization for a stable plant, $P = G_{22}$ in the LFT framework, is given by:

$$C = Q(I + G_{22}Q)^{-1} = \mathcal{F}_l \left(\begin{bmatrix} 0 & I \\ I & -G_{22} \end{bmatrix}, Q \right) = \mathcal{F}_l (\tilde{C}, Q) \quad (9.87)$$

Lemma 9.8 (Youla Parameterization For Stable Plants Using LFTs)

The equivalent LFT representation for the closed loop transfer function, T_{zw} , which enables the direct calculation of the free controller parameter in a Youla parameterization, Q , is given by:

$$T_{zw} = \mathcal{F}_l(G, \mathcal{F}_l(\tilde{C}, Q)) = \mathcal{F}_l(S(G, \tilde{C}), Q) = \mathcal{F}_l(\tilde{G}, Q) \quad (9.88)$$

where $\tilde{G} = S(G, \tilde{C})$, $S(\bullet, \bullet)$ is the Redheffer star product given by definition 9.8 and

$$\tilde{C} = \begin{bmatrix} 0 & I \\ I & -G_{22} \end{bmatrix}$$

Proof: Given equation 9.87, it follows that:

$$\begin{aligned} T_{zw} &= \mathcal{F}_l(G, \mathcal{F}_l(\tilde{C}, Q)) = \mathcal{F}_l(G, Q(I + G_{22}Q)^{-1}) \\ &= G_{11} + G_{12}Q(I + G_{22}Q)^{-1}(I - G_{22}Q(I + G_{22}Q)^{-1})^{-1}G_{21} \\ &= G_{11} + G_{12}QG_{21} = \mathcal{F}_l\left(\begin{bmatrix} G_{11} & G_{12} \\ G_{21} & 0 \end{bmatrix}, Q\right) \\ &= \mathcal{F}_l(S(G, \tilde{C}), Q) = \mathcal{F}_l(\tilde{G}, Q) \quad \blacksquare \end{aligned}$$

Remark 9.14 It should be noted that the system matrix $\tilde{G}$ is parameterized in terms of the original system matrix, G presented in equation 9.86, as follows:

$$\tilde{G}(z) = \left[\begin{array}{cc|cc} A & 0 & B_1 & B_2 \\ 0 & A & 0 & -B_2 \\ \hline C_1 & 0 & D_{11} & D_{12} \\ C_2 & C_2 & D_{21} & 0 \end{array} \right] = \left[\begin{array}{c|cc} \tilde{A} & \tilde{B}_1 & \tilde{B}_2 \\ \hline \tilde{C}_1 & \tilde{D}_{11} & \tilde{D}_{12} \\ \tilde{C}_2 & \tilde{D}_{21} & \tilde{D}_{22} \end{array} \right] = \begin{bmatrix} G_{11} & G_{12} \\ G_{21} & 0 \end{bmatrix} \quad (9.89)$$

Remark 9.15 The state space form for $\tilde{C}$ is given as follows:

$$\tilde{C} = \left[\begin{array}{c|cc} A & 0 & -B_2 \\ \hline 0 & 0 & I \\ C_2 & I & -D_{22} \end{array} \right] \quad (9.90)$$

Remark 9.16 Figure 9.7 demonstrates pictorially the LFT transformation given by lemma 9.8, which enables the free controller parameter Q to be determined directly. The LFT transformation given in Figure 9.7 allows for a direct comparison between the discrete H^2 transfer function representation of Q and the corresponding multiresolutional FIR representation of Q .

Remark 9.17 The free controller parameter Q can also be determined after the controller, C , has been derived by manipulating equation 9.87 to yield:

$$Q = C(I - G_{22}C)^{-1} = \mathcal{F}_l \left(\begin{bmatrix} 0 & I \\ I & G_{22} \end{bmatrix}, C \right) \quad (9.91)$$

Assumptions

1. (A, B_2) is stabilizable and (C_2, A) is detectable;
2. D_{12} is full column rank with $\begin{bmatrix} D_{12} & D_{12}^\perp \end{bmatrix}$ unitary and D_{21} is full row rank with $\begin{bmatrix} D_{21} \\ D_{21}^\perp \end{bmatrix}$ unitary;
3. $\begin{bmatrix} A - e^{j\theta}I & B_2 \\ C_1 & D_{12} \end{bmatrix}$ has full column rank $\forall \theta \in [0, 2\pi]$;
4. $\begin{bmatrix} A - e^{j\theta}I & B_1 \\ C_2 & D_{21} \end{bmatrix}$ has full row rank $\forall \theta \in [0, 2\pi]$;

Remark 9.18 Note that assumption 2 requires that $R = D_{12}^* D_{12} = I$. If $R \neq I$ then it becomes necessary to scale the control input, u , as follows:

$$\hat{u} \mapsto R^{\frac{1}{2}} u \quad (9.92)$$

Remark 9.19 Similarly, assumption 2 also requires that $Q = D_{21} D_{21}^* = I$. If $Q \neq I$ then it becomes necessary to scale the system input, w , as follows:

$$\hat{w} \mapsto Q^{\frac{1}{2}} w \quad (9.93)$$

Remark 9.20 Lastly, the LFT framework sets the D_{22} term in G to zero. This can be done without loss of generality as will be demonstrated below. When the controller parameter Q is determined directly, the $\tilde{D}_{22}$ term in $\tilde{G}$ is always zero.

Remark 9.21 Let $\hat{G}$ be the resultant system matrix after setting $D_{22} = 0$ and after applying equations 9.92 and 9.93 to yield:

$$\hat{G} = \left[\begin{array}{c|cc} A & B_1 Q^{-\frac{1}{2}} & B_2 R^{-\frac{1}{2}} \\ \hline C_1 & D_{11} Q^{-\frac{1}{2}} & D_{12} R^{-\frac{1}{2}} \\ C_2 & D_{21} Q^{-\frac{1}{2}} & 0 \end{array} \right] = \left[\begin{array}{c|cc} A & \hat{B}_1 & \hat{B}_2 \\ \hline C_1 & \hat{D}_{11} & \hat{D}_{12} \\ C_2 & \hat{D}_{21} & 0 \end{array} \right] \quad (9.94)$$

With the system matrix to be controlled given by $\hat{G}$, let the resultant controller be represented as $\hat{C}$. Now the resultant control input equation becomes $\hat{u} = \hat{C}\hat{e}$. The equivalent controller, C , for the original system matrix, G , can be recovered from $\hat{C}$ through the use of the following lemma.

Lemma 9.9 (LFT for Determining The Original System Controller C from $\hat{C}$)

$$C = \mathcal{F}_l \left(\begin{bmatrix} 0 & R^{-\frac{1}{2}} \\ I & -D_{22}R^{-\frac{1}{2}} \end{bmatrix}, \hat{C} \right) = R^{-\frac{1}{2}} \hat{C} (I + D_{22}R^{-\frac{1}{2}} \hat{C})^{-1} \quad (9.95)$$

Proof:

Recalling the state space equations for e and $\hat{e}$, write e in terms of $\hat{e}$ as follows:

$$\hat{e} = C_2 x + \hat{D}_{21} \hat{w} = e - D_{22} R^{-\frac{1}{2}} \hat{u} \quad (9.96)$$

Now express the control input equation for $\hat{u}$ in terms of e and u using equations 9.96 and 9.92 as follows:

$$\begin{aligned} \hat{u} &= \hat{C}\hat{e} = \hat{C} (e - D_{22} R^{-\frac{1}{2}} \hat{u}) \\ &= \hat{C} (I + D_{22} R^{-\frac{1}{2}} \hat{C})^{-1} e \\ u &= R^{-\frac{1}{2}} \hat{C} (I + D_{22} R^{-\frac{1}{2}} \hat{C})^{-1} e = Ce \end{aligned} \quad (9.97)$$

where $C = R^{-\frac{1}{2}} \hat{C} (I + D_{22} R^{-\frac{1}{2}} \hat{C})^{-1} = \mathcal{F}_l \left(\begin{bmatrix} 0 & R^{-\frac{1}{2}} \\ I & -D_{22} R^{-\frac{1}{2}} \end{bmatrix}, \hat{C} \right)$. ■

The next theorem finds the unique, discrete optimal controller which minimizes the two norm of the closed loop transfer function $\|T_{zw}\|_2$.

Theorem 9.3 ([57])

The unique optimal controller for the discrete H^2 control problem is given by the following:

$$C_{opt}(z) := \left[\begin{array}{c|c} \frac{A + B_2 F_2 + L_2 C_2 - B_2 L_0 C_2}{F_2 - L_0 C_2} & \frac{-L_2 + B_2 L_0}{L_0} \end{array} \right] \quad (9.98)$$

with $\min \|T_{zw}\|_2^2 = \|G_c\|_2^2 + \|G_f\|_2^2$.

$$\begin{aligned} \text{where: } G_c(z) &:= \left[\begin{array}{c|c} \frac{A + B_2 F_2}{C_1 + D_{12} F_2} & \frac{B_1 + B_2 F_0}{D_{11} + D_{12} F_0} \end{array} \right] \\ G_f(z) &:= \left[\begin{array}{c|c} \frac{A + L_2 C_2}{M^{\frac{1}{2}}(L_0 C_2 - F_2)} & \frac{B_1 + L_2 D_{21}}{M^{\frac{1}{2}}(L_0 D_{21} - F_0)} \end{array} \right] \end{aligned}$$

$$M := I + B_2^* X B_2;$$

$$F_2 := -M^{-1}(B_2^* X A + D_{12}^* C_1);$$

$$F_0 := -M^{-1}(B_2^* X B_1 + D_{12}^* D_{11});$$

$$L_2 := -(A Y C_2^* + B_1 D_{21}^*)(I + C_2 Y C_2^*)^{-1};$$

$$L_0 := (F_2 Y C_2^* + F_0 D_{21}^*)(I + C_2 Y C_2^*)^{-1};$$

$X \geq 0$ is the stabilizing solution to the following discrete Riccati equation

$$A_1^*(I + X B_2 B_2^*)^{-1} X A_1 - X + C_1^* D_{12}^\perp D_{12}^{\perp*} C_1 = 0;$$

$Y \geq 0$ is the stabilizing solution to the following discrete Riccati equation

$$A_2(I + Y C_2^* C_2)^{-1} Y A_2^* - Y + B_1 D_{21}^{\perp*} D_{21}^\perp B_1^* = 0;$$

$$A_1 := A - B_2 D_{12}^* C_1;$$

$$A_2 := A - B_1 D_{21}^* C_2.$$

CHAPTER 10

DISCRETE MULTIREOLUTIONAL CONTROLLER DESIGN EXAMPLES

This chapter presents discrete multiresolutional controller design examples which utilize theorems 9.1 and 9.2 and compares these multiresolutional controllers with discrete H^2 controllers, based on the LFT framework, developed using theorem 9.3.

10.1 Discrete Multiresolutional Minimum Sensitivity Controller Design Example

This section demonstrates the use of the discrete multiresolutional sensitivity minimization theorem (DMSMT), theorem 9.1 to design a controller $C_N = \dot{Q}(W - P\dot{Q})^{-1}$. The resultant controller was simply a function of the given plant P , the given disturbance weight W , and the free controller parameter $\dot{Q}$. The desired length of the FIR representation for the free controller parameter $\dot{Q}$ is denoted by N , with $N = 2^{\bar{\nu}}$ and $\bar{\nu} \in \mathbb{Z}^+$, satisfying lemma 7.2. Therefore, the free controller parameter is denoted by $\dot{Q}_N$. Although theorem 9.1 is valid for any N , L , M and K , in this example, $N = L = M = K_0$ was chosen to hold initially. In other words, no compression was performed on the corresponding system signal gains, α , β , and γ .

First, the DMSMT was used to find controllers for the following set of points

$$\mathcal{N} := \{N, N/2, N/4, \dots, 2\} = \{n_0, n_1, n_2, \dots, n_{\bar{\nu}-1}\}$$

with $K_i = n_i \in \mathcal{N}$ and $L = M$ remaining unchanged. Observe that $K_i \leq n_i \in \mathcal{N}$ is the general case. Next, a wavelet decomposition was performed on the initial free controller parameter, $\dot{Q}_N$, which was determined using the DMSMT with the initial number of even points N . Notice that when using the wavelet decomposition, the free parameter $\dot{Q}$ satisfies the following nesting property:

$$\dot{Q}_2 \subset \dot{Q}_4 \cdots \subset \dot{Q}_{N/2} \subset \dot{Q}_N$$

Lastly, for all points in $\mathcal{N}$, the resultant cost functions of the controllers designed using the DMSMT were compared with that of the controllers found using the wavelet decomposition on the initial free parameter $\dot{Q}_N$.

Definition 10.1

Define the following cost functions:

1. $J_{opt} :=$ the (sub)optimal cost minimized at each $n_i \in \mathcal{N}$ using the DMSMT
2. $J_{wpd} :=$ the cost at each $n_i \in \mathcal{N}$ as a result of performing a wavelet packet decomposition on the initial, minimized free parameter $\dot{Q}_N$ found using the DMSMT.

Given the control system shown in figure 9.3 with the following plant, $P(z)$, and the disturbance weight, $W(z)$:

$$P(z) = \frac{1 - 3z^{-1}}{2(1 - \frac{9}{8}z^{-1} + \frac{3}{8}z^{-2})} \quad (10.1)$$

$$W(z) = \frac{1}{1 - \frac{2}{3}z^{-1}} \quad (10.2)$$

The minimum sensitivity performance to be achieved is given by:

$$\min \|T_{zw}\|_2 = \inf_{\dot{Q} \in H^2} \|W - P\dot{Q}\|_2 = 1.2122 \quad (10.3)$$

where $\dot{Q} = WQ$. Observe that for $\dot{Q} = 0$, $\|T_{zw}\|_2 = \|W\|_2 = 1.3416$. Therefore, $\|W\|_2$ serves as an upper bound on the optimal performance cost $\|T_{zw}^{opt}\|_2 < 1.3416$.

Choose the initial number of points to be $N = 32$, and use the approach just discussed to determine the two multiresolutional sensitivity minimization controllers defined by the cost functions given in definition 10.1. Table 10.1 demonstrates that, for this example, the controller costs were identical for $N/2$ and $N/4$ points. The second scheme experienced a slight degradation for $N/8$ and $N/16$. Table 10.1 demonstrates that the system cost, J_{wpd} , due to wavelet packet decomposition on the initial free parameter $\dot{Q}_N$ provided an upper bound on the (sub)optimal cost, J_{opt} , found by using the DMSMT on each $n_i \in \mathcal{N}$.

10.2 Discrete Multiresolutional Minimum Mixed Sensitivity Controller Design Example

This section demonstrates the use of the discrete multiresolutional mixed sensitivity minimization theorem (DMMSMT), theorem 9.2 to design a controller $C_N = Q(1 - PQ)^{-1}$. The resultant controller is simply a function of the given plant P , the given disturbance weight W_1 , the performance weight W_2 , and the free controller parameter Q . The desired length of the FIR representation

Cost Function	N	$N/2$	$N/4$	$N/8$	$N/16$
J_{opt}	1.2122	1.2122	1.2122	1.2124	1.2148
J_{wpd}	1.2122	1.2122	1.2122	1.2126	1.2191

Table 10.1: Comparison of Discrete Multiresolutional Controller Designs for Sensitivity Minimization as a function of N

for the free controller parameter Q is denoted by N , with $N = 2^{\bar{\nu}}$ and $\bar{\nu} \in \mathbb{Z}^+$, satisfying lemma 7.2. Therefore, the free controller parameter is denoted by Q_N . Although theorem 9.2 is valid for any N , L , J , M and K , for the sake of simplicity, as was done in section 10.1, $N = L = J = M = K_0$ was chosen to hold initially. No compression was performed on the corresponding system signal gains, α , ν , β , and γ .

As was performed in section 10.1, first the DMMSMT was used to find controllers for the following set of points

$$\mathcal{N} := \{N, N/2, N/4, \dots, 2\} = \{n_0, n_1, n_2, \dots, n_{\bar{\nu}-1}\}$$

with $K_i = n_i \in \mathcal{N}$ and $L = J = M$ remaining unchanged. Next, a wavelet decomposition was performed on the initial free parameter Q_N , which was determined using the DMMSMT with the initial number of even points N . The resultant cost between the controllers designed using the DMMSMT and the controllers found using the wavelet decomposition on the initial free parameter Q_N were compared for all points in $\mathcal{N}$.

Definition 10.2

Define the following cost functions:

1. $J_{opt} :=$ the (sub)optimal cost minimized at each $n_i \in \mathcal{N}$ using the DMMSMT
2. $J_{wpd} :=$ the cost at each $n_i \in \mathcal{N}$ as a result of performing a wavelet packet decomposition on the initial, minimized free parameter Q_N found using the DMMSMT.

Given the control system shown in figure 9.5 with the same plant, $P(z)$, and disturbance weight, $W_1(z)$, as in section 10.1, now consider the additional performance weight, $W_2(z)$:

$$P(z) = \frac{1 - 3z^{-1}}{2(1 - \frac{9}{8}z^{-1} + \frac{3}{8}z^{-2})} \quad (10.4)$$

$$W_1(z) = \frac{1}{1 - \frac{2}{3}z^{-1}} \quad (10.5)$$

$$W_2(z) = \frac{z^{-1}}{1 + \frac{2}{3}z^{-1}} \quad (10.6)$$

The mixed sensitivity performance to be achieved is given by:

$$\min \|T_{zw}\|_2 = \inf_{Q \in RH^2} \left\| \begin{bmatrix} W_1(1 - PQ) & W_2PQ \end{bmatrix} \right\|_2 = 1.2495 \quad (10.7)$$

Observe that for $Q = 0$ or $Q = P^{-1}$, $\|T_{zw}\|_2 = \|W_1\|_2 = \|W_2\|_2 = 1.3416$. Therefore, $\|W_1\|_2$ or $\|W_2\|_2$ serves as an upper bound on the optimal performance cost $\|T_{zw}^{opt}\|_2 < 1.3416$.

Choose the initial number of points to be $N = 32$, and use the approach just discussed to determine two multiresolutional mixed sensitivity minimization controllers defined by the cost functions given in definition 10.2. Observation of table 10.2 demonstrates that, for this example, the controller designs were identical for $N/2$ and $N/4$ points. The second scheme experienced a slight degradation for $N/8$ and $N/16$. Table 10.2 demonstrates once again that the system cost, J_{wpd} , due to wavelet packet decomposition on the initial free parameter Q_N provided an upper bound on the (sub)optimal cost, J_{opt} , found by using the DMMSMT on each $n_i \in \mathcal{N}$.

Cost Function	N	$N/2$	$N/4$	$N/8$	$N/16$
J_{opt}	1.2495	1.2495	1.2495	1.2496	1.2623
J_{wpd}	1.2495	1.2495	1.2495	1.2499	1.3300

Table 10.2: Comparison of Multiresolutional Controller Designs for Mixed Sensitivity Minimization as a function of N

10.3 Comparison Between Discrete Multiresolutional Controllers And Discrete H^2 Controllers

This section presents the corresponding LFT based discrete H^2 controllers to the multiresolutional controllers designed in sections 10.1 and 10.2 for the systems shown in figures 9.3 and 9.5. The development of LFT based discrete H^2 controllers is solely for the purpose of controller comparison with the multiresolutional controllers. In other words, plant, disturbance weight, and performance weight models are assumed in order to develop the LFT based discrete H^2 controllers. The corresponding impulse response data for the plant, disturbance weight, and performance weight models was already used to develop multiresolutional controllers. For the LFT based discrete H^2 controllers presented herein, the optimal free controller parameter transfer function, $Q_{opt}(z)$, for a Youla parameterization will be determined directly using the LFT transformation given by lemma 9.8, which is shown pictorially in figure 9.7. The LFT transformation given in Figure 9.7 allows

for a direct comparison between the discrete H^2 transfer function of $Q_{opt}(z)$ and the corresponding multiresolutional FIR of $Q_{fir}(z)$.

For the system shown in figure 9.3 with the system transfer functions presented in equation 10.2, the optimal free controller parameter, $Q_{s,opt}(z)$, which minimizes the sensitivity performance criteria presented in equation 10.3, was determined to be:

$$Q_{s,opt}(z) = \frac{-0.2857 + 0.9048z^{-1} - 1.137z^{-2} + 0.7083z^{-3} - 0.2188z^{-4} + 0.0268z^{-5}}{1.0 - 2.25z^{-1} + 1.847z^{-2} - 0.6528z^{-3} + 0.8333z^{-4}} \quad (10.8)$$

The optimal performance cost $\min \|T_{zw}^{opt}\|_2 = 1.2122$, which is identical to the minimum cost found for the controller design presented in section 10.1, which utilized the discrete multiresolutional sensitivity minimization theorem (DMSMT). The FIR for the free controller parameter, $\dot{Q}_{s,fir}(z) = Q_{s,opt}(z)W(z)$ was found using the DMSMT is given by the following:

$$\begin{aligned} \dot{Q}_{s,fir}(z) = & -0.2857 + 0.0714z^{-1} + 0.0278z^{-2} + 0.0119z^{-3} + 0.0057z^{-4} \\ & + 0.0031z^{-5} + 0.0018z^{-6} + 0.0011z^{-7} + 0.0007z^{-8} + 0.0005z^{-9} \\ & + 0.0003z^{-10} + 0.0002z^{-11} + 0.0001z^{-13} + 0.0001z^{-14} + \dots \end{aligned} \quad (10.9)$$

Since $\dot{Q} \neq Q$, it is not surprising that equation 10.8 is not equivalent to equation 10.9. However, the DMMST can be used to solve the multiresolutional sensitivity minimization problem by setting $W_2 = 0$. The FIR for the free controller parameter, $Q_{s,fir}(z)$, found using the DMMST with $W_2 = 0$ is given by the following:

$$\begin{aligned} Q_{s,fir}(z) = & -0.2857 + 0.2619z^{-1} - 0.0198z^{-2} - 0.0066z^{-3} + 0.0022z^{-4} \\ & - 0.0007z^{-5} - 0.0002z^{-6} - 0.0001z^{-7} + \epsilon_{s,fir}z^{-8} + \dots \end{aligned} \quad (10.10)$$

where $\epsilon_{s,fir} < 4 \cdot 10^{-5}$. Observe that the transfer function presented in equation 10.8 has the FIR of equation 10.10.

For the system shown in figure 9.5 with the system transfer functions presented in equation 10.6, the optimal free controller parameter, $Q_{ms,opt}(z)$, which minimizes the mixed sensitivity performance criteria presented in equation 10.7, was determined to be:

$$\begin{aligned} Q_{ms,opt}(z) = & (-0.1429 + 0.2169z^{-1} - 0.0288z^{-2} - 0.2027z^{-3} + 0.1102z^{-4} + 0.0250z^{-5} \\ & - 0.0308z^{-6} + 0.0060z^{-7}) / (1.0 - 1.583z^{-1} + 0.3472z^{-2} + 0.5787z^{-3} \\ & - 0.3519z^{-4} + 0.0556z^{-5}) \end{aligned} \quad (10.11)$$

The optimal performance cost $\min \|T_{zw}^{opt}\|_2 = 1.2495$, which is identical to the minimum cost found for the controller design presented in section 10.2, which utilized the discrete multiresolutional mixed sensitivity minimization theorem (DMMSMT). The FIR for the free controller parameter, $Q_{ms,fir}(z)$

was found using the DMSMT is given by the following:

$$\begin{aligned} Q_{ms,fir}(z) = & -0.1429 + 0.0357z^{-1} + 0.07748z^{-2} - 0.0099z^{-3} + 0.0033z^{-4} \\ & + 0.0011z^{-5} + 0.0004z^{-6} + 0.0001z^{-7} + \epsilon_{ms,fir}z^{-8} + \dots \end{aligned} \quad (10.12)$$

where $\epsilon_{ms,fir} < 5 \cdot 10^{-5}$. Observe that the transfer function presented in equation 10.11 has the FIR of equation 10.12.

These control design examples demonstrate that the FIR for the free controller parameter Q found using the multiresolutional control design methodology discussed herein approximates the equivalent the transfer function for the free controller parameter found using discrete H^2 control based on the LFT framework. However, the multiresolutional controllers have the added advantage of requiring only impulse response data, along with being able to optimize Q for a desired FIR of length N .

CHAPTER 11

CONCLUSIONS

Multiresolution encompasses the ideas of scale and the process of moving from one scale to another, e.g., moving from a coarse scale to a finer scale or vice versa. The concept of a multiresolutional representation refers to a simple hierarchical architecture for interpreting information. The primary goal of this research was to apply the ideas of multiresolution to a control system. The framework necessary for achieving a multiresolutional control system was developed by this research. One important purpose for developing a multiresolutional control system was to have the capability of controlling a plant with a high resolution using a low resolution controller. Another purpose for developing a multiresolutional control system was to be able to control a group or class of plants with the same controller. The controller can have multiple resolutions or only one resolution. In addition, a multiresolutional controller could be used to control only a particular aspect of a plant.

A multiresolutional control system models the plant using a “best”, orthonormal wavelet packet basis and then determines an optimal controller using some performance criteria. The word best is in quotes since the best wavelet packet basis may be very dependent on the control objectives, plant characteristics, etc., and therefore could vary greatly from one control system to another. This framework is very general and allows the control designer to ascertain what is the “best” basis for their individual control system. The optimal controller was then determined using either the same orthonormal wavelet packet basis or another related orthonormal wavelet packet basis. A related orthonormal wavelet packet basis is a different basis derived from the same mother wavelet.

This research presented a theorem for designing a wavelet packet controller which minimizes the sensitivity function for a SISO system. A theorem for designing a wavelet packet controller which minimized the mixed sensitivity function for a SISO system was also presented. New theoretical results on orthonormal wavelet packets and on what the author’s call B-spline packets were presented. The new theoretical developments were required in order to make the implementation of the multiresolutional controllers very practical. The new theoretical results provided the computational tools necessary for solving the posed control optimization problems. Lastly, multiresolutional

controller design examples were presented and compared with discrete H^2 controllers. The control design examples demonstrated that the FIR for the free controller parameter found using the multiresolutional control design methodology discussed herein approximates the equivalent transfer function for the free controller parameter found using discrete H^2 control based on the LFT framework. However, the multiresolutional controllers have the added advantage of requiring only impulse response data, along with being able to optimize the free controller parameter for any desired FIR of length N .

The opportunity for future work in this area is immense. Multiresolutional controllers for unstable systems can be directly determined using the developments herein once the unstable system has been represented using a coprime factorization. This framework could also be utilized for representing uncertainty, in particular additive uncertainty, which has direct application to robust control. The multiresolutional framework and computational tools developed herein are readily applicable to adaptive control using a gradient tuning methodology. In addition, due to the capability of wavelet packets to model nonlinear systems, extensions of this work to nonlinear control are also possible.

APPENDIX A

PROOFS OF MULTIREOLUTIONAL CONTROLLER DESIGN LEMMAS

This appendix contains the proofs of the main lemmas employed in the development of the multiresolutional sensitivity minimization controller and in the development of the multiresolutional mixed sensitivity minimization controller presented in theorems 9.1 and 9.2. For notational convenience, let $\psi_k := \psi_{f_k, p_k}^{\sigma_k}(\bullet)$, where $\bullet = t$ or $\bullet = n$ depending on whether the basis functions are continuous or discrete. Define the following quantities which will be used throughout this appendix:

$$\psi := [\psi_0 \quad \psi_1 \quad \cdots \quad \psi_{N-1}]^T \quad (\text{A.1})$$

$$\alpha := [\alpha_0 \quad \alpha_1 \quad \cdots \quad \alpha_{L-1}]^T \quad (\text{A.2})$$

$$\nu := [\nu_0 \quad \nu_1 \quad \cdots \quad \nu_{J-1}]^T \quad (\text{A.3})$$

$$\beta := [\beta_0 \quad \beta_1 \quad \cdots \quad \beta_{M-1}]^T \quad (\text{A.4})$$

$$\gamma := [\gamma_0 \quad \gamma_1 \quad \cdots \quad \gamma_{K-1}]^T \quad (\text{A.5})$$

$$\hat{w} = \hat{w}_1 = \sum_{k=0}^{L-1} \alpha_k \tilde{\psi}_k = \alpha^T \tilde{\psi} \quad (\text{A.6})$$

$$\hat{w}_2 = \sum_{k=0}^{J-1} \nu_k \tilde{\psi}_k = \nu^T \tilde{\psi} \quad (\text{A.7})$$

$$\hat{p} = \sum_{k=0}^{M-1} \beta_k \hat{\psi}_k = \beta^T \hat{\psi} \quad (\text{A.8})$$

$$\hat{q} = \hat{\dot{q}} = \sum_{k=0}^{K-1} \gamma_k \dot{\psi}_k = \gamma^T \dot{\psi} \quad (\text{A.9})$$

Throughout this appendix, let the matrix operator, $\mathcal{M}_{p \times qN}(\bullet)$ of definition 9.6, signify an operation on continuous-time functions or on discrete-time functions. For the case of continuous-time functions, N equals 1 and for the case of discrete-time functions, N equals the length of the corresponding discrete-time representation.

Lemma A.1

Let $x \in \mathcal{C}^{p \times 1}$ and $y \in \mathcal{C}^{m \times 1}$, then the Kronecker product of x^T and y , $x^T \otimes y \in \mathcal{C}^{m \times p}$, is equivalent to the following:

$$x^T \otimes y = yx^T = y \otimes x^T \quad (\text{A.10})$$

Proof: Expand $x^T \otimes y$ and use the property $(x^T \otimes y)^T = x \otimes y^T$ given in [64], to yield the desired results:

$$\begin{aligned} x^T \otimes y &= \begin{bmatrix} x_0 y_0 & \cdots & x_{p-1} y_0 \\ \vdots & \vdots & \vdots \\ x_0 y_{m-1} & \cdots & x_{p-1} y_{m-1} \end{bmatrix} \\ &= yx^T = \left((yx^T)^T \right)^T = (xy^T)^T \\ &= (y^T \otimes x)^T = y \otimes x^T \quad \blacksquare \end{aligned}$$

Lemma A.2

Let $x \in \mathcal{C}^{p \times 1}$ and $y \in \mathcal{C}^{m \times 1}$, then the Kronecker product of x and y , $x \otimes y \in \mathcal{C}^{pm \times 1}$, is equivalent to the following:

$$x \otimes y = \mathcal{V}_1(yx^T) \quad (\text{A.11})$$

Proof: Expand $\mathcal{V}_1(yx^T)$ and use the definition of the vector operator, definition 9.5, to yield the desired result:

$$\begin{aligned} \mathcal{V}_1(yx^T) &= \mathcal{V}_1 \left(\begin{bmatrix} x_0 y_0 & \cdots & x_{p-1} y_0 \\ \vdots & \vdots & \vdots \\ x_0 y_{m-1} & \cdots & x_{p-1} y_{m-1} \end{bmatrix} \right) \\ &= \left[x_0 y_0 \quad \cdots \quad x_0 y_{m-1} \quad \cdots \quad x_{p-1} y_0 \quad \cdots \quad x_{p-1} y_{m-1} \right]^T \\ &= x \otimes y \quad \blacksquare \end{aligned}$$

Lemma A.3

$$\langle \hat{w}, \hat{w} \rangle = \langle \alpha^T \tilde{\psi}, \alpha^T \tilde{\psi} \rangle = (\alpha \otimes \alpha)^T \mathcal{K}(\langle \tilde{\psi}, \tilde{\psi} \rangle) \quad (\text{A.12})$$

Proof: Use equation A.6 to expand the left hand side of lemma A.3 as follows:

$$\begin{aligned} \langle \hat{w}, \hat{w} \rangle &= \left\langle \sum_{k=0}^{L-1} \alpha_k \tilde{\psi}_k, \sum_{l=0}^{L-1} \alpha_l \tilde{\psi}_l \right\rangle \\ &= \sum_{k=0}^{L-1} \alpha_k (\alpha_0 \langle \tilde{\psi}_k, \tilde{\psi}_0 \rangle + \cdots + \alpha_{L-1} \langle \tilde{\psi}_k, \tilde{\psi}_{L-1} \rangle) \end{aligned} \quad (\text{A.13})$$

Examination of the right hand side of equation A.13 in light of the Kronecker product definition 9.1 and the Kronecker inner product definition 9.4 demonstrates that:

$$\alpha_k (\alpha_0 \langle \tilde{\psi}_k, \tilde{\psi}_0 \rangle + \cdots + \alpha_{L-1} \langle \tilde{\psi}_k, \tilde{\psi}_{L-1} \rangle) = (\alpha_k \otimes \alpha)^T \mathcal{K}(\langle \tilde{\psi}_k, \tilde{\psi} \rangle) \quad (\text{A.14})$$

which is generalized $\forall k$ in equation A.13 as follows:

$$\begin{aligned} \langle \hat{w}, \hat{w} \rangle &= \sum_{k=0}^{L-1} \alpha_k \otimes (\alpha_0 \langle \tilde{\psi}_k, \tilde{\psi}_0 \rangle + \cdots + \alpha_{L-1} \langle \tilde{\psi}_k, \tilde{\psi}_{L-1} \rangle) \\ &= \sum_{k=0}^{L-1} (\alpha_k \otimes \alpha)^T \mathcal{K}(\langle \tilde{\psi}_k, \tilde{\psi} \rangle) \\ &= (\alpha \otimes \alpha)^T \mathcal{K}(\langle \tilde{\psi}, \tilde{\psi} \rangle) \quad \blacksquare \end{aligned}$$

Lemma A.4

$$\hat{p} * \hat{q} = (\beta^T \dot{\psi}) * (\gamma^T \dot{\psi}) = \beta^T \mathcal{M}_{M \times KN}(\dot{\psi} \circledast \dot{\psi}) \gamma \quad (\text{A.15})$$

Proof: Use equations A.8 and A.9 to expand the left hand side of lemma A.4, apply the Kronecker convolution definition 9.3 and lastly use the matrix operator definition 9.6 to yield the desired result as follows:

$$\begin{aligned} \hat{p} * \hat{q} &= (\beta^T \dot{\psi}) * (\gamma^T \dot{\psi}) = \left(\sum_{k=0}^{M-1} \beta_k \dot{\psi}_k \right) * \left(\sum_{l=0}^{K-1} \gamma_l \dot{\psi}_l \right) \\ &= \sum_{l=0}^{K-1} \left(\beta_0 (\dot{\psi}_0 * \dot{\psi}_l) + \cdots + \beta_{M-1} (\dot{\psi}_{M-1} * \dot{\psi}_l) \right) \gamma_l \\ &= \sum_{l=0}^{K-1} \beta^T (\dot{\psi} \circledast \dot{\psi}_l) \gamma_l = \sum_{l=0}^{K-1} \beta^T (\dot{\psi}_l \circledast \dot{\psi}) \gamma_l \\ &= \beta^T \mathcal{M}_{M \times KN}(\dot{\psi} \circledast \dot{\psi}) \gamma \quad \blacksquare \end{aligned}$$

Lemma A.5

$$\langle \hat{w}, \hat{p} * \hat{q} \rangle = \langle \alpha^T \tilde{\psi}, (\beta^T \dot{\psi}) * (\gamma^T \dot{\psi}) \rangle = (\alpha \otimes \beta)^T \mathcal{K}(\langle \tilde{\psi}, \mathcal{M}_{M \times K}(\dot{\psi} \oplus \dot{\psi}) \rangle) \gamma \quad (\text{A.16})$$

Proof: Use equations A.6, A.8, and A.9 to expand the left hand side of lemma A.5, apply the Kronecker product definition 9.1 and the Kronecker convolution definition 9.3, then apply the Kronecker inner product definition 9.4, and lastly employ lemma A.4 to yield the desired result as follows:

$$\begin{aligned} \langle \hat{w}, \hat{p} * \hat{q} \rangle &= \langle \alpha^T \tilde{\psi}, (\beta^T \dot{\psi}) * (\gamma^T \dot{\psi}) \rangle \\ &= \langle \sum_{i=0}^{L-1} \alpha_i \tilde{\psi}_i, (\sum_{j=0}^{M-1} \beta_j \dot{\psi}_j) * (\sum_{k=0}^{K-1} \gamma_k \dot{\psi}_k) \rangle \\ &= \sum_{i=0}^{L-1} \sum_{k=0}^{K-1} \alpha_i \otimes (\beta_0 \langle \tilde{\psi}_i, \dot{\psi}_0 * \dot{\psi}_k \rangle + \dots + \beta_{M-1} \langle \tilde{\psi}_i, \dot{\psi}_{M-1} * \dot{\psi}_k \rangle) \gamma_k \\ &= \sum_{i=0}^{L-1} \sum_{k=0}^{K-1} (\alpha_i \otimes \beta)^T \mathcal{K}(\langle \tilde{\psi}_i, \dot{\psi} \oplus \dot{\psi}_k \rangle) \gamma_k = \sum_{i=0}^{L-1} \sum_{k=0}^{K-1} (\alpha_i \otimes \beta)^T \mathcal{K}(\langle \tilde{\psi}_i, \dot{\psi}_k \oplus \dot{\psi} \rangle) \gamma_k \\ &= \sum_{i=0}^{L-1} (\alpha_i \otimes \beta)^T \mathcal{K}(\langle \tilde{\psi}_i, \mathcal{M}_{M \times K}(\dot{\psi} \oplus \dot{\psi}) \rangle) \gamma \\ &= (\alpha \otimes \beta)^T \mathcal{K}(\langle \tilde{\psi}, \mathcal{M}_{M \times K}(\dot{\psi} \oplus \dot{\psi}) \rangle) \gamma \quad \blacksquare \end{aligned}$$

Lemma A.6

$$\begin{aligned} \langle \hat{p} * \hat{q}, \hat{p} * \hat{q} \rangle &= \langle (\beta^T \dot{\psi}) * (\gamma^T \dot{\psi}), (\beta^T \dot{\psi}) * (\gamma^T \dot{\psi}) \rangle \\ &= (\beta \otimes \beta)^T \mathcal{K}(\langle \mathcal{M}_{M \times K}(\dot{\psi} \oplus \dot{\psi}), \mathcal{M}_{M \times K}(\dot{\psi} \oplus \dot{\psi}) \rangle) (\gamma \otimes \gamma) \end{aligned} \quad (\text{A.17})$$

Proof: Use equations A.8, and A.9 to expand the left hand side of lemma A.6, apply the Kronecker product definition 9.1 and the Kronecker inner product definition 9.4, then apply the Kronecker convolution definition 9.3, and lastly employ lemma A.4 to yield the desired result as follows:

$$\begin{aligned} \langle \hat{p} * \hat{q}, \hat{p} * \hat{q} \rangle &= \langle (\beta^T \dot{\psi}) * (\gamma^T \dot{\psi}), (\beta^T \dot{\psi}) * (\gamma^T \dot{\psi}) \rangle \\ &= \langle (\sum_{i=0}^{M-1} \beta_i \dot{\psi}_i) * (\sum_{j=0}^{K-1} \gamma_j \dot{\psi}_j), (\sum_{k=0}^{M-1} \beta_k \dot{\psi}_k) * (\sum_{l=0}^{K-1} \gamma_l \dot{\psi}_l) \rangle \\ &= \sum_{i=0}^{M-1} \sum_{j=0}^{K-1} \sum_{l=0}^{K-1} \beta_i \otimes (\beta_0 \langle \dot{\psi}_i * \dot{\psi}_j, \dot{\psi}_0 * \dot{\psi}_l \rangle + \dots \\ &\quad + \beta_{M-1} \langle \dot{\psi}_i * \dot{\psi}_j, \dot{\psi}_{M-1} * \dot{\psi}_l \rangle) (\gamma_j \otimes \gamma_l) \end{aligned}$$

$$\begin{aligned}
&= \sum_{i=0}^{M-1} \sum_{j=0}^{K-1} \sum_{l=0}^{K-1} (\beta_i \otimes \beta)^T \mathcal{K}(\langle \dot{\psi}_i * \dot{\psi}_j, \dot{\psi} * \dot{\psi}_l \rangle) (\gamma_j \otimes \gamma_l) \\
&= \sum_{i=0}^{M-1} \sum_{j=0}^{K-1} \sum_{l=0}^{K-1} (\beta_i \otimes \beta)^T \mathcal{K}(\langle \dot{\psi}_i * \dot{\psi}_j, \dot{\psi}_l * \dot{\psi} \rangle) (\gamma_j \otimes \gamma_l) \\
&= \sum_{j=0}^{K-1} \sum_{i=0}^{M-1} (\beta_i \otimes \beta)^T \mathcal{K}(\langle \dot{\psi}_i * \dot{\psi}_j, \mathcal{M}_{M \times KN}(\dot{\psi} \oplus \dot{\psi}) \rangle) (\gamma_j \otimes \gamma) \\
&= \sum_{j=0}^{K-1} (\beta \otimes \beta)^T \mathcal{K}(\langle \dot{\psi} * \dot{\psi}_j, \mathcal{M}_{M \times K}(\dot{\psi} \oplus \dot{\psi}) \rangle) (\gamma_j \otimes \gamma) \\
&= \sum_{j=0}^{K-1} (\beta \otimes \beta)^T \mathcal{K}(\langle \dot{\psi}_j * \dot{\psi}, \mathcal{M}_{M \times K}(\dot{\psi} \oplus \dot{\psi}) \rangle) (\gamma_j \otimes \gamma) \\
&= (\beta \otimes \beta)^T \mathcal{K}(\langle \mathcal{M}_{M \times K}(\dot{\psi} \oplus \dot{\psi}), \mathcal{M}_{M \times K}(\dot{\psi} \oplus \dot{\psi}) \rangle) (\gamma \otimes \gamma) \quad \blacksquare
\end{aligned}$$

Lemma A.7

$$\begin{aligned}
\langle \hat{w}_1, \hat{w}_1 * \hat{p} * \hat{q} \rangle &= \langle \alpha^T \tilde{\psi}, (\alpha^T \tilde{\psi}) * (\beta^T \dot{\psi}) * (\gamma^T \dot{\psi}) \rangle \\
&= (\alpha \otimes \alpha \otimes \beta)^T \mathcal{K}(\langle \tilde{\psi}, \tilde{\psi} \oplus \mathcal{M}_{M \times KN}(\dot{\psi} \oplus \dot{\psi}) \rangle) \gamma
\end{aligned} \tag{A.18}$$

Proof: Use equations A.6, A.8, and A.9 to expand the left hand side of lemma A.7, then apply the Kronecker product definition 9.1, the Kronecker convolution definition 9.3, the Kronecker inner product definition 9.4, and lemma A.4 as necessary to yield the desired result:

$$\begin{aligned}
\langle \hat{w}_1, \hat{w}_1 * \hat{p} * \hat{q} \rangle &= \langle \alpha^T \tilde{\psi}, (\alpha^T \tilde{\psi}) * (\beta^T \dot{\psi}) * (\gamma^T \dot{\psi}) \rangle \\
&= \langle \sum_{i=0}^{L-1} \alpha_i \tilde{\psi}_i, (\sum_{j=0}^{L-1} \alpha_j \dot{\psi}_j) * (\sum_{k=0}^{M-1} \beta_k \dot{\psi}_k) * (\sum_{l=0}^{K-1} \gamma_l \dot{\psi}_l) \rangle \\
&= \sum_{i=0}^{L-1} \sum_{j=0}^{L-1} \sum_{l=0}^{K-1} \alpha_i \otimes \alpha_j \otimes \left(\beta_0 \langle \tilde{\psi}_i, \tilde{\psi}_j * \dot{\psi}_0 * \dot{\psi}_l \rangle + \dots \right. \\
&\quad \left. + \beta_{M-1} \langle \tilde{\psi}_i, \tilde{\psi}_j * \dot{\psi}_{M-1} * \dot{\psi}_l \rangle \right) \gamma_l \\
&= \sum_{i=0}^{L-1} \sum_{j=0}^{L-1} \sum_{l=0}^{K-1} (\alpha_i \otimes \alpha_j \otimes \beta)^T \mathcal{K}(\langle \tilde{\psi}_i, \tilde{\psi}_j * \dot{\psi} * \dot{\psi}_l \rangle) \gamma_l \\
&= \sum_{i=0}^{L-1} \sum_{j=0}^{L-1} \sum_{l=0}^{K-1} (\alpha_i \otimes \alpha_j \otimes \beta)^T \mathcal{K}(\langle \tilde{\psi}_i, \tilde{\psi}_j * \dot{\psi}_l * \dot{\psi} \rangle) \gamma_l \\
&= \sum_{i=0}^{L-1} \sum_{j=0}^{L-1} (\alpha_i \otimes \alpha_j \otimes \beta)^T \mathcal{K}(\langle \tilde{\psi}_i, \tilde{\psi}_j * \mathcal{M}_{M \times KN}(\dot{\psi} \oplus \dot{\psi}) \rangle) \gamma \\
&= \sum_{i=0}^{L-1} (\alpha_i \otimes \alpha \otimes \beta)^T \mathcal{K}(\langle \tilde{\psi}_i, \tilde{\psi}_j * \mathcal{M}_{M \times KN}(\dot{\psi} \oplus \dot{\psi}) \rangle) \gamma
\end{aligned}$$

$$= (\alpha \otimes \alpha \otimes \beta)^T \mathcal{K}(\langle \tilde{\psi}, \tilde{\psi} \oplus \mathcal{M}_{M \times KN}(\tilde{\psi} \oplus \dot{\psi}) \rangle) \gamma \quad \blacksquare$$

Lemma A.8

$$\begin{aligned} \langle \hat{w}_1 * \hat{p} * \hat{q}, \hat{w}_1 * \hat{p} * \hat{q} \rangle &= \langle (\alpha^T \tilde{\psi}) * (\beta^T \dot{\psi}) * (\gamma^T \dot{\psi}), (\alpha^T \tilde{\psi}) * (\beta^T \dot{\psi}) * (\gamma^T \dot{\psi}) \rangle \\ &= (\alpha \otimes \beta \otimes \alpha \otimes \beta)^T \mathcal{K}(\langle \tilde{\psi} \oplus \mathcal{M}_{M \times K}(\tilde{\psi} \oplus \dot{\psi}), \tilde{\psi} \oplus \mathcal{M}_{M \times KN}(\tilde{\psi} \oplus \dot{\psi}) \rangle) (\gamma \otimes \gamma) \quad (\text{A.19}) \end{aligned}$$

Proof: Use equations A.6, A.8, and A.9 to expand the left hand side of lemma A.8, apply the Kronecker product definition 9.1, the Kronecker inner product definition 9.4, the Kronecker convolution definition 9.3, and lemma A.4 as necessary to yield the desired result:

$$\begin{aligned} \langle \hat{w}_1 * \hat{p} * \hat{q}, \hat{w}_1 * \hat{p} * \hat{q} \rangle &= \langle (\alpha^T \tilde{\psi}) * (\beta^T \dot{\psi}) * (\gamma^T \dot{\psi}), (\alpha^T \tilde{\psi}) * (\beta^T \dot{\psi}) * (\gamma^T \dot{\psi}) \rangle \\ &= \left\langle \sum_{i=0}^{L-1} \alpha_i \tilde{\psi}_i * \left(\sum_{j=0}^{M-1} \beta_j \dot{\psi}_j \right) * \left(\sum_{k=0}^{K-1} \gamma_k \dot{\psi}_k \right), \sum_{l=0}^{L-1} \alpha_l \tilde{\psi}_l * \left(\sum_{m=0}^{M-1} \beta_m \dot{\psi}_m \right) * \left(\sum_{n=0}^{K-1} \gamma_n \dot{\psi}_n \right) \right\rangle \\ &= \sum_{i=0}^{L-1} \sum_{j=0}^{M-1} \sum_{k=0}^{K-1} \sum_{l=0}^{L-1} \sum_{n=0}^{K-1} \alpha_i \otimes \beta_j \otimes \alpha_l \otimes \\ &\quad \left(\beta_0 \langle \tilde{\psi}_i * \dot{\psi}_j * \dot{\psi}_k, \tilde{\psi}_l * \dot{\psi}_0 * \dot{\psi}_n \rangle + \cdots + \beta_{M-1} \langle \tilde{\psi}_i * \dot{\psi}_j * \dot{\psi}_k, \tilde{\psi}_l * \dot{\psi}_{M-1} * \dot{\psi}_n \rangle \right) (\gamma_k \otimes \gamma_n) \\ &= \sum_{i=0}^{L-1} \sum_{j=0}^{M-1} \sum_{k=0}^{K-1} \sum_{l=0}^{L-1} \sum_{n=0}^{K-1} (\alpha_i \otimes \beta_j \otimes \alpha_l \otimes \beta)^T \mathcal{K} \left(\langle \tilde{\psi}_i * \dot{\psi}_j * \dot{\psi}_k, \tilde{\psi}_l * \dot{\psi}_n * \dot{\psi} \rangle \right) (\gamma_k \otimes \gamma_n) \\ &= \sum_{i=0}^{L-1} \sum_{j=0}^{M-1} \sum_{k=0}^{K-1} \sum_{l=0}^{L-1} (\alpha_i \otimes \beta_j \otimes \alpha_l \otimes \beta)^T \mathcal{K} \left(\langle \tilde{\psi}_i * \dot{\psi}_j * \dot{\psi}_k, \tilde{\psi}_l * \mathcal{M}_{M \times KN}(\tilde{\psi} \oplus \dot{\psi}) \rangle \right) (\gamma_k \otimes \gamma) \\ &= \sum_{i=0}^{L-1} \sum_{k=0}^{K-1} \sum_{j=0}^{M-1} (\alpha_i \otimes \beta_j \otimes \alpha \otimes \beta)^T \mathcal{K} \left(\langle \tilde{\psi}_i * \dot{\psi}_j * \dot{\psi}_k, \tilde{\psi} \oplus \mathcal{M}_{M \times KN}(\tilde{\psi} \oplus \dot{\psi}) \rangle \right) (\gamma_k \otimes \gamma) \\ &= \sum_{i=0}^{L-1} \sum_{k=0}^{K-1} (\alpha_i \otimes \beta \otimes \alpha \otimes \beta)^T \mathcal{K} \left(\langle \tilde{\psi}_i * \dot{\psi}_k * \dot{\psi}, \tilde{\psi} \oplus \mathcal{M}_{M \times KN}(\tilde{\psi} \oplus \dot{\psi}) \rangle \right) (\gamma_k \otimes \gamma) \\ &= \sum_{i=0}^{L-1} (\alpha_i \otimes \beta \otimes \alpha \otimes \beta)^T \mathcal{K} \left(\langle \tilde{\psi}_i * \mathcal{M}_{M \times KN}(\tilde{\psi} \oplus \dot{\psi}), \tilde{\psi} \oplus \mathcal{M}_{M \times KN}(\tilde{\psi} \oplus \dot{\psi}) \rangle \right) (\gamma \otimes \gamma) \\ &= (\alpha \otimes \beta \otimes \alpha \otimes \beta)^T \mathcal{K}(\langle \tilde{\psi} \oplus \mathcal{M}_{M \times K}(\tilde{\psi} \oplus \dot{\psi}), \tilde{\psi} \oplus \mathcal{M}_{M \times KN}(\tilde{\psi} \oplus \dot{\psi}) \rangle) (\gamma \otimes \gamma) \quad \blacksquare \end{aligned}$$

Lemma A.9

$$\begin{aligned}
\langle \hat{w}_2 * \hat{q}, \hat{w}_2 * \hat{q} \rangle &= \langle (\nu^T \bar{\psi}) * (\gamma^T \bar{\psi}), (\nu^T \bar{\psi}) * (\gamma^T \bar{\psi}) \rangle \\
&= (\nu \otimes \nu)^T \mathcal{K}((\mathcal{M}_{M \times KN}(\bar{\psi} \oplus \bar{\psi}), \mathcal{M}_{M \times KN}(\bar{\psi} \oplus \bar{\psi}))) (\gamma \otimes \gamma)
\end{aligned} \tag{A.20}$$

Proof: Identical to the proof of lemma A.6 with $\hat{w}_2$, equation A.7, replacing $\hat{p}$, equation A.8. ■

BIBLIOGRAPHY

- [1] J. Koenderink, "The structure of images," in *Biological Cybernetics*, New York: Springer Verlag, 1984.
- [2] S. G. Mallat, "A theory for multiresolution signal decomposition: The wavelet representation," *IEEE Transactions on Pattern Analysis and Machine Intelligence*, vol. 11, pp. 674–693, July 1989.
- [3] Y. Meyer, "Ondelettes et fonctions splines," in *Seminaire EDP*, Ecole Polytechnique, Paris, France, December 1986.
- [4] G. P. Rao, *Piecewise Constant Orthogonal Functions and Their Application to Systems and Control*. New York, NY: Springer-Verlag, 1993.
- [5] P. Sannuti, "Analysis and synthesis of dynamic systems via block-pulse functions," *Proceedings of the IEE*, vol. 124, pp. 569–571, June 1977.
- [6] M. S. Corrington, "Solution of differential and integral equations with walsh functions," *IEEE Transactions on Circuit Theory*, vol. 20, pp. 470–476, September 1973.
- [7] B. Golubov, A. Efimov, and V. Skvortsov, *Walsh Series and Transforms. Theory and Applications*. Boston, MA: Kluwer Academic, 1991.
- [8] C. F. Chen and C. H. Hsiao, "Time-domain synthesis via walsh functions," *Proceedings of the IEE*, vol. 122, pp. 565–570, May 1975.
- [9] C. F. Chen and C. H. Hsiao, "A state-space approach to walsh series solution of linear systems," *International Journal of Systems Science*, vol. 6, pp. 833–858, September 1975.
- [10] G. P. Rao, K. R. Palanisamy, and T. Srinivasan, "Remarks on 'authors reply' to 'comments on 'design of piecewise constant gains for optimal control via walsh functions''," *IEEE Transactions on Automatic Control*, vol. 23, pp. 762–763, August 1978.
- [11] G. P. Rao, K. R. Palanisamy, and T. Srinivasan, "Extension of computation beyond the limit of initial normal interval in walsh series analysis of dynamical systems," *IEEE Transactions on Automatic Control*, vol. 25, pp. 317–321, April 1980.
- [12] C. F. Chen and C. H. Hsiao, "Design of piecewise constant gains for optimal control via walsh functions," *IEEE Transactions on Automatic Control*, vol. 20, pp. 596–602, October 1975.

- [13] V. P. Rao and K. R. Rao, "Optimal feedback control via block-pulse functions," *IEEE Transactions on Automatic Control*, vol. 24, pp. 372–374, April 1979.
- [14] W.-L. Chen and Y.-P. Shih, "Analysis and optimal control of time-varying linear systems via walsh functions," *International Journal of Control*, vol. 27, pp. 917–932, June 1978.
- [15] K. R. Palanisamy, "Analysis and optimal control of linear systems via single term walsh series approach," *International Journal of Systems Science*, vol. 12, pp. 443–454, April 1981.
- [16] G. P. Rao and T. Srinivasan, "Analysis and synthesis of dynamic systems containing time delays via block-pulse functions," *Proceedings of the IEE*, vol. 125, pp. 1064–1068, October 1978.
- [17] W.-L. Chen and Y.-P. Shih, "Shift walsh matrix and delay-differential equations," *IEEE Transactions on Automatic Control*, vol. 23, pp. 1023–1028, December 1978.
- [18] G. P. Rao and K. R. Palanisamy, "Walsh stretch matrices and functional differential equations," *IEEE Transactions on Automatic Control*, vol. 27, pp. 272–276, February 1982.
- [19] I.-R. Horng and S.-J. Ho, "Discrete walsh operational matrices for analysis and optimal control of linear digital systems," *International Journal of Control*, vol. 42, pp. 1443–1455, June 1985.
- [20] I.-R. Horng and S.-J. Ho, "Discrete walsh polynomials in the optimal control of linear digital time-varying systems," *International Journal of Control*, vol. 43, pp. 615–627, February 1986.
- [21] I. Daubechies, "The wavelet transform, time-frequency localization and signal analysis," *IEEE Transactions on Information Theory*, vol. 36, pp. 961–1005, September 1990.
- [22] I. Daubechies, *Ten Lectures on Wavelets*. Philadelphia, PA: Society for Industrial and Applied Mathematics, 1992.
- [23] A. Croisier, D. Esteban, and C. Galand, "Perfect channel splitting by use of interpolation/decimation/tree decomposition techniques," in *International Conference on Information Sciences and Systems*, pp. 443–446, Patras, Greece, August 1976.
- [24] M. Smith and T. Barnwell III, "A procedure for designing exact reconstruction filter banks for tree structured sub-band coders," in *International Conference on Acoustics, Speech, and Signal Processing*, (San Diego, CA), pp. 27.1.1–27.1.4, IEEE, March 1984.
- [25] M. Smith and T. Barnwell III, "Exact reconstruction for tree-structured subband coders," *IEEE Transactions on Acoustics, Speech, and Signal Processing*, vol. 34, pp. 314–327, June 1986.
- [26] F. Mintzer, "Filters for distortion-free two-band multirate filter banks," *IEEE Transactions on Acoustics, Speech, and Signal Processing*, vol. 33, pp. 626–630, June 1985.
- [27] P. Vaidyanathan, "Quadrature mirror filter banks, m-band extensions and perfect reconstruction techniques," *IEEE ASSP Magazine*, vol. 4, pp. 4–20, July 1987.
- [28] P. Vaidyanathan, "Theory and design of m-channel maximally decimated quadrature mirror filters with arbitrary m, having the perfect reconstruction property," *IEEE Transactions on Acoustics, Speech, and Signal Processing*, vol. 35, pp. 476–492, April 1987.

- [29] M. Vetterli, "Filter banks allowing perfect reconstruction," *Signal Processing*, vol. 10, pp. 219–244, April 1986.
- [30] M. Wickerhauser, *Adapted Wavelet Analysis From Theory to Software*. Wellesley, MA: A. K. Peters, Ltd, 1994.
- [31] I. Daubechies, "Orthonormal bases of compactly supported wavelets," *Communications on Pure and Applied Mathematics*, vol. 41, pp. 909–996, September 1988.
- [32] A. Cohen, I. Daubechies, and J. Feauveau, "Biorthogonal bases of compactly supported wavelets," *Communications on Pure and Applied Mathematics*, vol. 45, pp. 485–500, June 1992.
- [33] M. Vetterli and C. Herley, "Wavelets and Filter Banks: Theory and Design," *IEEE Transactions on Signal Processing*, vol. 40, pp. 2207–2232, 1992.
- [34] G. Strang and T. Nguyen, *Wavelets and Filter Banks*. Wellesley, MA: Wellesley-Cambridge Press, 1996.
- [35] R. Coifman and Y. Meyer, "Orthonormal Wave Packet Bases." preprint, 1990.
- [36] R. R. Coifman and M. V. Wickerhauser, "Entropy Based Algorithms for Best Basis Selection," *IEEE Transactions on Information Theory*, vol. 38, no. 2, pp. 713–718, 1992.
- [37] R. R. Coifman, Y. Meyer, and M. V. Wickerhauser, "Size Properties of Wavelet Packets," in *Wavelets and Their Applications* (M. B. Ruskai and et al, eds.), pp. 453–470, Boston, MA: Jones and Bartlett, 1992.
- [38] R. R. Coifman, Y. Meyer, and M. V. Wickerhauser, "Wavelet Analysis and Signal Processing," in *Wavelets and Their Applications* (M. B. e. a. Ruskai, ed.), pp. 153–178, Boston, MA: Jones and Bartlett, 1992.
- [39] K. Beauchamp, *Walsh Functions and Their Applications*. New York, NY: Academic Press, 1975.
- [40] S. C. Kak, "Sampling Theorem In Walsh-Fourier Analysis," *Electronics Letters*, vol. 6, pp. 447–448, July 1970.
- [41] R. Horn and C. Johnson, *Topics in Matrix Analysis*. New York, NY: Cambridge University Press, 1991.
- [42] I. J. Schoenberg, *Cardinal Spline Interpolation*, vol. 12 of *CBMS-NSF Series in Applied Math*. Philadelphia, PA: Society for Industrial and Applied Mathematics, 1973.
- [43] C. K. Chui and J. Z. Wang, "A cardinal spline approach to wavelets," *Proceedings of the AMS*, vol. 113, pp. 785–793, November 1991.
- [44] C. K. Chui and J. Z. Wang, "On compactly supported spline wavelets and a duality principle," *Transactions of the AMS*, vol. 330, pp. 903–915, April 1992.

- [45] C. K. Chui, "Wavelets - With Emphasis on Spline-Wavelets and Applications to Signal Analysis," in *Approximation Theory, Spline Functions, and Applications* (S. P. Singh, ed.), pp. 19–39, Norwell, MA: Kluwer Academic Publishers, 1992.
- [46] C. de Boor, *A Practical Guide to Splines*, vol. 27 of *Applied Mathematical Sciences*. New York, NY: Springer-Verlag, 1978.
- [47] A. Cohen, I. Daubechies, and V. P., "Wavelets on the Interval and Fast Wavelet Transforms." *Applied and Computational Harmonic Analysis*, vol. 1, pp. 54–81, December 1993.
- [48] K. Hoffman, *Banach Spaces of Analytic Functions*. Englewood Cliffs, NJ: Prentice-Hall, Inc., 1962.
- [49] P. L. Duren. *Theory of H^p Spaces*. New York, NY: Academic Press, 1970.
- [50] C. A. Desoer and M. Vidyasagar, *Feedback Systems: Input-Output Properties*. New York, NY: Academic Press, 1975.
- [51] J. Brewer, "Kronecker Products and Matrix Calculus in System Theory," *IEEE Transactions on Circuits and Systems*, vol. 25, pp. 772–781, September 1978.
- [52] C. A. Desoer, R. W. Liu, J. Murray, and R. Saeks, "Feedback System Design: The Fractional Representation Approach to Analysis and Synthesis," *IEEE Transactions on Automatic Control*, vol. AC25, pp. 399–412, June 1980.
- [53] M. Vidyasagar, *Control System Synthesis: A Factorization Approach*. Cambridge, MA: The MIT Press. 1985.
- [54] B. A. Francis, *A Course in H^∞ Control Theory*. New York, NY: Springer-Verlag, 1987.
- [55] J. C. Doyle, B. A. Francis, and A. Tannenbaum, *Feedback Control Theory*. New York, NY: Macmillan Publishing Company, 1992.
- [56] V. Kucera, "The Algebraic Approach to Control System Design," in *Polynomial Methods in Optimal Control and Filtering* (K. J. Hunt, ed.), pp. 1–28, London, U.K.: Peter Peregrinus Ltd., 1993.
- [57] K. Zhou, J. C. Doyle, and K. Glover, *Robust and Optimal Control*. Upper Saddle River, NJ: Prentice Hall, 1996.
- [58] B. Francis, "On the Wiener-Hopf Approach to Optimal Feedback Design," *Systems and Control Letters*, vol. 2, pp. 197–201, December 1982.
- [59] J. C. Doyle, K. Glover, P. P. Khargonekar, and B. A. Francis, "State-Space Solutions to Standard H^2 and H^∞ Control Problems," *IEEE Transactions on Automatic Control*, vol. AC34, pp. 831–847, August 1989.
- [60] H. Özbay and A. Tannenbaum, "On the Structure of Suboptimal H^∞ Controllers in the Sensitivity Minimization Problem for Distributed Stable Plants," *Automatica*, vol. 27, no. 2, pp. 293–305, 1991.

- [61] D. C. Youla, J. J. Bongiorno, Jr., and H. A. Jabr, "Wiener-Hopf Design of Optimal Controllers - Part I: The Single-Input-Output Case," *IEEE Transactions Automatic Control*, vol. 21, pp. 3-13, 1976.
- [62] D. G. Luenberger, *Optimization by Vector Space Methods*. New York, NY: John Wiley and Sons, 1969.
- [63] S. S. Rao, *Optimization: Theory and Application*. New York, NY: John Wiley and Sons, 1984.
- [64] R. Bellman, *Introduction to Matrix Analysis*. New York, NY: McGraw-Hill, 2nd ed., 1970.