©2013

AARON JOSEPH STENTA

ALL RIGHTS RESERVED

ONE DIMENSIONAL APPROACH TO MODELING DAMAGE EVOLUTION IN
GALVANIC CORROSION

A Thesis

Presented to

The Graduate Faculty of The University of Akron

In Partial Fulfillment

of the Requirements for the Degree

Master of Science

Aaron Joseph Stenta

May, 2013

ONE DIMENSIONAL APPROACH TO MODELING DAMAGE EVOLUTION IN
GALVANIC CORROSION

Aaron Joseph Stenta

Thesis

Approved:

Accepted:

Advisor
Dr. Gerald Young

Dean of the College
Dr. Chand Midha

Faculty Reader
Dr. Curtis Clemons

Dean of the Graduate School
Dr. George R. Newkome

Faculty Reader
Dr. Kevin Kreider

Date

Department Chair
Dr. Timothy Norfolk

ABSTRACT

A one-dimensional mathematical model is developed to describe damage evolution in galvanic corrosion for a variety of geometries. An asymptotic procedure taking advantage of disparity in length scales is used to derive the model. The focus of this thesis is to detail the formulation and solution of the 1D model for basic cartesian and cylindrical configurations. The cartesian model defines a rectangular domain, while the cylindrical model defines a system of concentric disks. For each model a thin film approximation for the thickness of the electrolyte and a well-mixed assumption describing uniform concentration of species in the electrolyte is used. Further, the Wagner relationship restricts the size of the electrolyte thickness as compared to the solution conductivity and polarization slope. Numerical solutions, using Matlab, are obtained for the potential, current density, and corrosion damage through time. The initial time solutions are compared to solutions obtained through the software package, GalvanicMaster, and excellent agreement is found. The damage evolution results are verified using experimental data and corrosion simulations that are cited in the literature. A comparative analysis is performed considering the effect of changing area ratio, electrolyte thickness, IR drop, and Wagner relationship for each system. Fully derived 1D governing equations for additional geometries are also proposed.

ACKNOWLEDGEMENTS

I want to thank Dr. Young, Dr. Clemons, and Dr. Kreider for their extensive assistance throughout this entire process. I want to thank the remaining members of the corrosion squad (Math and Engineering Faculty) for their research assistance, instruction, and cooperation. Additionally, I want to thank my closest family and friends for their complete support. Their encouragement drove me to complete this research and further my education at The University of Akron.

TABLE OF CONTENTS

	Page
LIST OF TABLES	vii
LIST OF FIGURES	viii
CHAPTER	
I. INTRODUCTION	1
1.1 Understanding Galvanic Corrosion	1
1.2 Description of the Model	7
1.3 Literature Review	8
1.4 Main Results	11
II. MODEL FORMULATION	14
2.1 Governing Equation	14
2.2 Cartesian Model	17
2.3 Cylindrical Model	26
III. NUMERICAL FORMULATION	32
3.1 Numerical Domain	32
3.2 Discretization of the Damage Equation	35
3.3 Cartesian Potential Equation	35

3.4 Cylindrical Potential Equation	38
3.5 Numerical Model Parameters	39
3.6 GalvanicMaster Details	41
IV. RESULTS	43
4.1 Galvanic Couples with Polarization Data	43
4.2 Deshpande Verification	47
4.3 Capturing Physical Phenomena	54
4.4 Results in a Radial Geometry	66
4.5 Simulation Limitations	68
V. REVIEW AND FUTURE WORK	73
5.1 Conclusion	73
5.2 Future Work	77
BIBLIOGRAPHY	80
APPENDICES	82
APPENDIX A. ONE-DIMENSIONAL NUMERICAL CODE	83
APPENDIX B. OTHER CONFIGURATIONS AND EQUATIONS	90

LIST OF TABLES

Table	Page
2.1 Parameters and Units	30
2.2 Parameters and Units cont.	31
2.3 Relationships and Equations	31
3.1 Cartesian Analytic vs. Numeric BC's	37
3.2 Cylindrical Analytic vs. Numeric BC's	39
3.3 Material Parameters	40

LIST OF FIGURES

Figure	Page
1.1 Galvanic corrosion cell.	2
1.2 Galvanic series chart.	5
1.3 (a) Polarization data for an individual metal; (b) Polarization data for two dissimilar metals.	6
1.4 (a) Cartesian rectangular geometry; (b) Cylindrical plug configuration.	7
2.1 (a) Cartesian rectangular system; (b) Cartesian electrolyte domain as shown in (a).	17
2.2 Cross-sectional view of the electrolyte solution.	25
2.3 (a) Cylindrical concentric system; (b) Cylindrical electrolyte domain as shown in (a).	26
3.1 Discretization molecule - 1D space and time.	33
4.1 Magnesium vs. mild steel actual and smoothed polarization curves. . .	44
4.2 (a) Experimental aerated aluminum vs. copper polarization curve.(b) Artificial de-aerated aluminum vs. copper polarization curve.	45
4.3 Deshpande 2D initial potential distribution [1]. The cathode zone is from $-0.01 \leq x \leq 0$ m and the anode zone is from $0 \leq x \leq 0.01$ m. .	48

4.4	(a) GalvanicMaster vs. 1D initial potential results for smoothed Mg/MS polarization curve; (b) GalvanicMaster vs. 1D initial potential results for actual Mg/MS polarization curve. The anode zone is from $0 \leq x \leq 1 \text{ cm}$ and the cathode zone is from $1 \leq x \leq 2 \text{ cm}$	49
4.5	Deshpande 2D numerical vs. experimental (SVET) initial current density results [1]. The anode zone is from $0 \leq x \leq 10 \text{ mm}$ and the cathode zone is from $10 \leq x \leq 20 \text{ mm}$	50
4.6	(a) GalvanicMaster vs. 1D initial current density results for smoothed Mg/MS polarization curve; (b) GalvanicMaster vs. 1D initial current density results for actual Mg/MS polarization curve. The anode zone is from $0 \leq x \leq 1 \text{ cm}$ and the cathode zone is from $1 \leq x \leq 2 \text{ cm}$	50
4.7	Deshpande 2D numerical vs. immersion experimental damage results through 3 days [1]. The anode zone is from $0 \leq x \leq 10 \text{ mm}$ and the cathode zone is from $10 \leq x \leq 20 \text{ mm}$	52
4.8	(a) GalvanicMaster vs. 1D damage results through 3 days for smoothed Mg/MS polarization curve; (b) GalvanicMaster vs. 1D damage results through 3 days for actual Mg/MS polarization curve. The anode zone is from $0 \leq x \leq 1 \text{ cm}$ and the cathode zone is from $1 \leq x \leq 2 \text{ cm}$	52
4.9	(a) 1D damage evolution for smooth vs. actual polarization data through 8 hours in $w = .1 \text{ cm}$ electrolyte.; (b) 1D damage evolution for smooth vs. actual polarization data through 8 hours in $w = .05 \text{ cm}$ electrolyte. The anode zone is from $0 \leq x \leq 1 \text{ cm}$ and the cathode zone is from $1 \leq x \leq 2 \text{ cm}$	54
4.10	Mg/MS evolution of potential in $w = 0.1 \text{ cm}$ electrolyte. The anode zone is from $0 \leq x \leq 1 \text{ cm}$ and the cathode zone is from $1 \leq x \leq 2 \text{ cm}$	55
4.11	Mg/MS evolution of current density in $w = 0.1 \text{ cm}$ electrolyte. The anode zone is from $0 \leq x \leq 1 \text{ cm}$ and the cathode zone is from $1 \leq x \leq 2 \text{ cm}$	56
4.12	Potential resistance effects for Al/Cu in various electrolyte thickness. The anode zone is from $0 \leq x \leq 2 \text{ cm}$ and the cathode zone is from $2 \leq x \leq 4 \text{ cm}$	57
4.13	Current density resistance effects for Al/Cu in various electrolyte thickness. The anode zone is from $0 \leq x \leq 2 \text{ cm}$ and the cathode zone is from $2 \leq x \leq 4 \text{ cm}$	58

4.14	Potential resistance effects for Mg/MS in various electrolyte thickness. The anode zone is from $0 \leq x \leq 1$ cm and the cathode zone is from $1 \leq x \leq 2$ cm.	59
4.15	Current density resistance effects for Mg/MS in various electrolyte thickness. The anode zone is from $0 \leq x \leq 1$ cm and the cathode zone is from $1 \leq x \leq 2$ cm.	60
4.16	Al/Cu potential effects for various area ratios in $w = 0.1$ cm electrolyte.	61
4.17	Al/Cu current density for various area ratios in $w = 0.1$ cm electrolyte.	61
4.18	Mg/MS potential effects for various area ratios in $w = 0.01$ cm electrolyte.	63
4.19	Mg/MS current density for various area ratios in $w = 0.01$ cm electrolyte.	63
4.20	Critical cathode length for Al/Cu in $w = 0.01$ cm electrolyte. The anode zone is from $0 \leq x \leq 1$ cm and the cathode zone is from $1 \leq x \leq 45$ cm.	65
4.21	Critical cathode length for Mg/MS in $w = 0.01$ cm electrolyte. The anode zone is from $0 \leq x \leq 1$ cm and the cathode zone is from $1 \leq x \leq 11$ cm.	65
4.22	Potential results for a 2 cm Mg vs. 1 cm MS cylindrical plug in 0.1 cm electrolyte through 7 days.	66
4.23	Current density results for a 2 cm Mg vs. 1 cm MS cylindrical plug in 0.1 cm electrolyte through 7 days.	67
4.24	Damage results for a 2 cm Mg vs. 1 cm MS cylindrical plug in 0.1 cm electrolyte through 7 days.	67
4.25	(a) Steep anodic curve to demonstrate minimally restrictive Wagner representation; (b) Shallow anodic curve to demonstrate highly restrictive Wagner representation.	70
5.1	(a) Counter-sinked bolt-head; (b) Standard bolt-head configuration. . .	78
B.1	Exterior pipe configuration.	90
B.2	Interior pipe configuration.	91
B.3	Interior pipe configuration.	92

CHAPTER I

INTRODUCTION

The focus of this thesis is to establish an asymptotic approach to one-dimensional (1D) modeling of the damage evolution during galvanic corrosion for various geometric and electrochemical configurations. First, a base model in a cartesian coordinate system with a rectangular geometry is considered. Once the base model is analyzed, the same asymptotic approach is used to derive 1D governing system of equations for a cylindrical base fastener plug assembly. The model is developed for thin film electrolyte environments that are well-mixed. It is shown, however, that in some instances the thin film limit can be relaxed to properly simulate bulk electrolyte. The model is validated via comparison with experimental and numerical results available in the literature, as well as results from an additional software package. Further development will focus on extending the model into higher dimensions and incorporating ionic species in the electrolyte.

1.1 Understanding Galvanic Corrosion

Corrosion, in general, is defined as the degradation of a material by a chemical reaction with its environment. One of the main mechanisms of corrosion degradation is electrochemical corrosion. Electrochemical corrosion requires an oxidation reaction

and reduction reaction to occur simultaneously in a simple chemical process through which a metal returns to its lowest energy oxidation state [2].

Thermodynamics, the study of changes in energy that accompany chemical and physical changes, requires that an unstable system eventually return to its steady stable state. Some metals, such as gold, are already in steady state. These metals do not corrode because they are naturally stable. Unexposed, unprotected, and unstable metals, however, reach their stable state through electrochemical corrosion. For electrochemical corrosion to occur, four elements must be present as shown in Figure 1.1. These are an anode, a cathode, an electrolyte solution, and an electric, typically metallic, pathway connecting the anode and the cathode.

Figure 1.1: Galvanic corrosion cell.

An electrochemical reaction takes place between the anode and the cathode. The anode is the negatively charged electrode and the cathode is the positively

charged electrode. In a galvanic cell electric current flows from a positive to a negative charge, or into the anode. The direction of electron flow is opposite to that of the electric current. Therefore, in the electric pathway, electrons flow from the anode to the cathode. The cathodic consumption of electrons controls the corrosion rate of the anodic metal. Oxygen, or some other electron acceptor, is necessary for this reaction to take place. If an electron acceptor is not present then corrosion of the anode will slow down and eventually stop. After consuming the electrons from the anode, hydrogen ions are released at the cathode. The electron acceptor reacts with these hydrogen ions to maintain a balanced system. Without an electron acceptor, hydrogen ions build up on the cathode and block the absorption of electrons from the anode, thus slowing down the corrosion.

The electrolyte is the solution that surrounds the metal(s) and allows for the transport of ions. The electrical conductivity of the electrolyte (κ) plays an important role in determining the corrosive behavior of the anode. The electrolyte conductivity measures how easy it is for ions to flow between the electrodes. A minimally conductive electrolyte reduces corrosion, and a highly conductive electrolyte solution increases corrosion. Additionally, the metallic pathway closes the corrosion cell circuit and accounts for the physical connection between the anode and the cathode.

As compared to the standard electrochemical corrosion of a single metal, the corrosion behavior of multiple metals, galvanically coupled in an electrolyte, is more aggressive. Galvanic corrosion is the process of degradation due to any number of dissimilar metals that are in electrical contact. When placed in an identical electrolyte

various metals electrochemically operate at different resting potentials. These stable potentials define the open-circuit potentials for each metal. In a galvanic system the metal operating at the lowest open-circuit potential corrodes at a rate corresponding to the electron acceptance capacity of the cathodic metal(s), operating at a higher open-circuit potential.

A typical galvanic series chart, Figure 1.2, demonstrates the severity of this corrosive behavior. The more noble, corrosion resistant metals are in the lower right corner of Figure 1.2, while the more active, corrosion prone metals are in the upper left corner. When placed in the same electrolyte solution, a more noble metal operates at a higher open-circuit potential than a more active metal. The more noble metal is referred to as more cathodic, and the more active metal is referred to as more anodic. A larger distance between an anodic and a cathodic metal, on the chart, implies a greater acceptance of electrons by the cathodic metal. This increase in electron and current flow through the galvanic system leads to an increased corrosion rate for the anodic metal. For example, for the galvanic series in Figure 1.2, stainless steel (316) would corrode iron when in electrical contact, because it is more cathodic than iron and operates at a higher open-circuit potential.

The behavior of a galvanic system can be understood by examining the polarization diagram that depicts the system's potential vs. current relationship. It is typical that the polarization data for each metal is regularly plotted on a single curve. This allows one to easily recognize the severity of the corrosion rate as well as the extremity of the difference in potentials. A sample polarization curve for a single

Figure 1.2: Galvanic series chart.

metal is shown in Figure 1.3a. The upper curve is the anodic branch of the given metal and the lower curve is its cathodic branch. The open circuit potential of the metal occurs at the intersection of its cathodic and anodic curves. At that potential, the net current density in the system is zero.

In comparison, a sample polarization curve for two metals is shown in Figure 1.3b. In this plot, the metal with the higher open-circuit potential is more noble, and the metal with the lower open-circuit potential is more active. The intersection between the cathodic curve for the more noble metal and the anodic curve for the more active metal is known as the galvanic corrosion couple. This is the operating potential and current density for the given galvanic system. The corresponding potential and

Figure 1.3: (a) Polarization data for an individual metal; (b) Polarization data for two dissimilar metals.

current density describe the rate at which the anode will corrode. At this point, the larger the current density the greater the maximum anodic corrosion rate.

Many industries are interested in using combinations of metals to reduce weight, cost, etc. The immediate drawback of multi-metallic systems is the risk of galvanic corrosion. A model that can quickly describe the damage evolution during galvanic corrosion is of great interest in industry. The model developed in this thesis can assist in this major area of concern. After fully analyzing the damage evolution, one can make decisions to either initially protect the system, alter the designs of the system, replace the system after failure, or ignore the situation due to minimal severity of corrosion.

1.2 Description of the Model

The method used in this thesis is first developed for a rectangular galvanic configuration in a cartesian coordinate system, as shown in Figure 1.4a. After considering this initial model, systems with rotational symmetry are introduced using a cylindrical coordinate system. The cylindrical system derived in this paper describes a fastener plug, as shown in Figure 1.4b. The plug assembly is a system of concentric disks with a plug head attached on the top surface of the interior cylinder. The solution procedure is similar for all geometries under consideration. The final development of the base fastener, as shown in Figure 1.4b, allows for additional features to be accounted for as well as for more complex geometries to be solved.

Figure 1.4: (a) Cartesian rectangular geometry; (b) Cylindrical plug configuration.

For all galvanic corrosion damage models in electrochemical literature, the equations being solved are posed in the electrolyte only. Likewise, the boundary conditions describe the boundary surfaces of the electrolyte only. For all models in

this thesis, both in cartesian and cylindrical coordinates, a well-mixed assumption is used. That is, uniform concentration of species in the electrolyte is imposed. Under this assumption, the governing equations to be solved in the electrolyte reduce to the standard Laplace equation for the potential.

Other assumptions arising during the solution procedure include the thin film approximation for the electrolyte and the Wagner relationship. Introducing a small aspect ratio parameter for the electrolyte thickness versus its lateral extent allows for a reduction of dimensionality. The Wagner number relating the electrolyte thickness to the polarization slope and electrolyte conductivity, is required to be small in the solution procedure of this thesis.

An additional equation is needed to describe the damage evolution through time. The equation for the rate of the damage is derived from Faraday's law. This law states that the mass of material lost due to an electrochemical reaction is proportional to the current. Together with the derived potential equation, an iterative approach is taken to numerically simulate the damage evolution in galvanic corrosion.

1.3 Literature Review

Models of galvanic corrosion assuming a well-mixed electrolyte have been proposed by Jia [3]-[5], Deshpande [1, 6], Song [7]-[9], Hebert [10], Blanc [11], and many others. In all cases, the governing equation in the electrolyte is the Laplace equation for the potential under a well-mixed assumption. Other key aspects described in literature are the proper boundary conditions for the electrolyte, most importantly

at the metal/electrolyte interface. These conditions describe the surface behavior on the boundaries between the electrolyte and the anode and the electrolyte and the cathode, respectively. While the majority of literature poses only the governing equation and conditions for the potential in the electrolyte, Deshpande [1] proposes a method for modeling the damage evolution. Initial time calculations prescribe the corresponding polarization potentials and current densities across the solution domain, whereas, time-dependent solutions update the potentials and current densities for the evolving corroded shape of the anode.

Deshpande's mathematical work [1, 6] couples an Arbitrary Lagrangian Eulerian (ALE) method, capable of tracking moving boundaries, with a software package, COMSOL MultiPhysics [12], accounting for the potential profiles through time. This two-dimensional method, was used to obtain results for various magnesium micro-galvanic structures [6], as well as simple cartesian structures [1]. In all cases the full Laplace equation is solved for the potential in the electrolyte, coupled with the damage equation. The process in [1] is similar to that proposed here, except that the model in this thesis is one-dimensional. This reduction of dimensionality saves computational time, and is practical for many simple configurations.

Jorcin [13] and Hebert [10] analyze a cylindrical system of concentric aluminum and copper disks using a Finite Element Method (FEM) to solve the Laplace equation at the initial time. Then, using experimental results and computer simulations, a damage evolution prediction model is developed. These results would be worth comparing further provided that all proper input details were given. The re-

sults show an important local behavior of the degradation near the aluminum/copper interface for a bulk electrolyte environment.

Many methods have been proposed that solve for the initial potentials and current densities in a galvanic system. These results are then used to approximate the damage evolution corrosion rates. Jia [3] uses Boundary Element Method (BEM) numerical simulations coupled with experimental data to solve the Laplace equation for a well-mixed electrolyte. This numerical simulation outputs the corrosion rate at the surfaces of various galvanic systems. Additional attempts using BEM techniques were made by Jia [4, 5] and Aoki [14]. These works cover many scenarios and important factors that influence distributions of the time, $t = 0$. Also, Okado [15] presents a well-structured complete initiation model, including species. This paper could be useful in extending the current model to one that incorporates spatially varying chemical species profiles.

A completely analytic technique is proposed by Song [7] that develops initial potential and current expressions. Song’s model uses a thin film assumption for various simplified galvanic geometries. Some applications that can be represented by the simplified 1D model are also discussed. Song derives analytic expressions to imitate typical experimentally calculated potential and current expressions, and then derives a method for initiation of galvanic corrosion. In the end, a well-structured banded model is proposed. This banded model is a continuous series of alternating rectangular anodes and cathodes. Additional theoretical modeling approaches are reviewed in [16].

Wagner [17] introduced a fundamental concept that is used in many models. An assumption on linear polarization data is made to account for a small parameter. This small parameter defines the specific magnitude of a non-dimensional group of parameters in the model. Wagner’s assumption allows the governing equation for the potential to be reduced to one-dimension. Along with the thin film assumption, the metals chosen must also satisfy Wagner’s relationship. The metals must have a steep polarization slope, so that the polarization slope multiplied by the solution conductivity is much larger than the electrolyte thickness, $w \ll \frac{\Delta E}{\Delta i} \kappa$. Additional descriptions of the electrochemical process appear in [2, 18, 19].

1.4 Main Results

Results, by Deshpande [1, 6, 20], defining a magnesium/mild steel galvanic couple in 1.6% NaCl are used to benchmark the cartesian model for the damage evolution of the magnesium. This data provides the first verification for the one-dimensional method used in this thesis. Corrosion engineers at the University of Akron [21] provided polarization data for 99.9% copper and 99.999% aluminum in 0.1 molar NaCl. This additional galvanic couple is used to benchmark the cartesian and cylindrical models through analyzing known physical phenomena and comparing results with a software package. The software package is used to verify initial time, ($t = 0$), results for each proposed model. The program, GalvanicMaster [22], performs a finite grid surface mesh and solves the Laplace equation in the electrolyte with a thin film assumption using a boundary element method. The advantage of this software is that it can

easily handle complex geometries and it incorporates a user-friendly interface. The disadvantage is that it does not compute damage evolution. It computes the initial current, current density, potential, and corrosion rate.

After verifying the 1D model, a complete constraint analysis is performed. This analysis focuses on the limitations of the thin film assumption and the Ohm's law IR drop resistance effect in the system. Ohm's law states that the electric current in a conductive circuit is directly proportional to the voltage across it. By comparing cases with various electrolyte widths and lengths, this analysis can classify constraints that arise for each case. The resistance drop analysis helps to explain the cathode-to-anode area ratio effect in galvanic corrosion. It shows that systems with a large resistance in the electrolyte have a large voltage drop and therefore have minimal area ratio effect. On the other hand systems with a small resistance have a small voltage (IR) drop and have a strong area ratio effect. This effect relates to shifting the cathodic polarization curve to a higher or lower current density reflecting the change in cathode to anode areas. Additionally, specific cases are analyzed looking at the limitations of the Wagner relationship on the electrolyte thickness.

The results developed here are unique in that they provide damage evolution insight into various galvanic systems. These results will be used to examine future complex damage evolution galvanic models. The next step is to introduce species concentration into the system. This will remove the well-mixed electrolyte assumption and will account for the transport of species in the electrolyte throughout the damage process. All base models will then be more fully developed, and more accurately

imitate their real life applications. The final step is to construct a higher dimensional model accounting for the damage evolution, so that the modeling of complex fasteners can be developed. Our current model only accounts for those applications that imitate uni-directional corrosion damage.

Chapter 2 describes the formulation of the cartesian and cylindrical models. Chapter 3 describes the complete numerical solution procedure with the code presented in Appendix A, and the results presented in Chapter 4. Various simulations are conducted that are consistent with experimental efforts for validation purposes. GalvanicMaster is used for each validation of initial time results. Chapter 5 presents a detailed description of the upcoming model features that are addressed along with additional systems under future consideration. Finally, further base configurations and their potential and damage evolution equations are discussed in Appendix B.

CHAPTER II

MODEL FORMULATION

2.1 Governing Equation

The conservation of flux of the ionic species in a fluid medium is represented by the Nernst-Planck Equation. In its simplest form, this general species transport equation is written as

$$\frac{\partial C_i}{\partial t} = -\nabla \cdot \bar{J}, \quad (2.1)$$

where C_i is the concentration of the i -th species and $\bar{J}$ is the flux of the species. The flux is written as

$$\bar{J} = \left[-D_i \nabla C_i - Z_i \frac{D_i F_a}{RT} C_i \nabla E + \bar{u} C_i \right], \quad (2.2)$$

where D_i is the mass diffusion coefficient of the i -th species, Z_i is the valence number of the i -th species, F_a is Faraday's constant, R is the universal gas constant, $\bar{u}$ is the velocity of the fluid vector, T is the temperature, and E is the potential in the electrolyte. The valence number contains the number and sign of the gained/lost electrons for the species. For the transport of ionic species there are three main transport mechanisms: diffusion, migration, and convection. The first term on the right hand side of the flux equation (2.2) represents the diffusion in the system, the second term represents the migration, and the final term represents the convection.

Under the well-mixed assumption the concentrations of species are constants implying that their gradients are zero;

$$\nabla C_i = 0. \quad (2.3)$$

Combined with the assumption that the fluid flow is incompressible, which implies that the divergence of the fluid velocity is zero,

$$\nabla \bar{u} = 0, \quad (2.4)$$

the Nernst-Planck equation reduces to

$$\frac{\partial C_i}{\partial t} = -\nabla \cdot \left[-Z_i \frac{D_i F_a}{RT} C_i \nabla E \right]. \quad (2.5)$$

The governing equation must satisfy the electro-neutrality condition for the concentration of species. This condition implies that the cations in the system balance the anions, and that the sum of the charges is equal to zero, $\sum_i Z_i C_i = 0$. Combining the electro-neutrality condition with the transport equations for the species, the resulting equation is found to be

$$\sum_i Z_i \frac{\partial C_i}{\partial t} = \nabla \sum_i \left[Z_i^2 \frac{D_i F_a}{RT} C_i \nabla E \right] = 0. \quad (2.6)$$

Considering the parameters in (2.6) as known constant values and satisfying the electro-neutrality condition, the governing equation reduces to the Laplace equation,

$$\nabla^2 E = 0, \quad (2.7)$$

for the potential in the system.

Each galvanic system has a consistent set of boundary conditions on the bounding surfaces of the electrolyte. For a rectangular electrolyte configuration the top, left, and right boundary conditions are of a no flux type. Mathematically this condition is expressed as

$$\bar{J} \cdot \hat{n} = 0, \quad (2.8)$$

where $\hat{n}$ is the outward normal derivative to the boundary of the domain. Using the expression for the flux $\bar{J}$ from (2.2), the equation (2.8) is reduced to

$$\nabla E \cdot \hat{n} = 0. \quad (2.9)$$

This condition implies that there is no change in potential through the top, left, and right surface boundaries. The boundary condition on the electrolyte/metal interface is Ohm's Law and is written as

$$\bar{J} \cdot \hat{n} = \frac{i(E)}{F_a}, \quad (2.10)$$

where $i(E)$ is the current density as a function of the potential. The current density across the electrolyte/metal interface is the difference between the cathodic and anodic current densities, so

$$i(E) = i_a(E) - i_c(E). \quad (2.11)$$

The cathodic current density is negligible across the anode, and the anodic current density is negligible across the cathode. Under the well-mixed assumption, setting

$\kappa = F_a^2 \sum_i \left[Z_i^2 \frac{D_i}{RT} C_i \right]$, the equation (2.10) is rewritten as

$$-\kappa \nabla E \cdot \hat{n} = i(E). \quad (2.12)$$

2.2 Cartesian Model

The cartesian rectangular configuration and the corresponding electrolyte solution domain are represented in Figure 2.1.

Figure 2.1: (a) Cartesian rectangular system; (b) Cartesian electrolyte domain as shown in (a).

The Cartesian governing equation and boundary conditions are

$$E_{xx} + E_{yy} = 0, \quad (2.13)$$

$$E_x = 0 \text{ at } x = 0, \quad (2.14)$$

$$E_x = 0 \text{ at } x = L, \quad (2.15)$$

$$E_y = 0 \text{ at } y = w, \text{ and} \quad (2.16)$$

$$-\kappa \nabla E \cdot \hat{n} = i(E) \text{ at } y = -H(x). \quad (2.17)$$

The parameter w is the electrolyte thickness, κ is the electrical conductivity of the solution, $H(x)$ is the magnitude of the corrosion damage in the y direction defined only on the anode, $i(E)$ is the current density as a function of the potential E , the

value $x = 0$ corresponds to the left boundary of the anode, $x = L$ corresponds to the right boundary of the cathode, $x = F$ corresponds to the anode/cathode interface that can vary to model different area ratios, $y = w$ corresponds to the top surface of the electrolyte, and $y = -H(x)$ corresponds to the metal/electrolyte interface where $H = 0$ across the cathode. Using the component vector $\langle E_x, E_y \rangle$ for ∇E the normal vector, $\hat{n} = \frac{\langle H_x, 1 \rangle}{\sqrt{H_x^2 + 1}}$, describes the boundary along the electrolyte/metal interface allowing (2.17) to take the form

$$\kappa \frac{(E_x H_x + E_y)}{\sqrt{1 + H_x^2}} = i(E). \quad (2.18)$$

The negative sign from (2.17) coupled with the negative sign from the downward pointing directional normal explain the positive left hand side of (2.18).

Now that the governing equation for the potential is established together with boundary conditions, the asymptotic procedure is as follows. The first step is to identify a small parameter ϵ . In this case $w \ll L$ will be used to define the small parameter where $\epsilon = \frac{w}{L} \ll 1$. To non-dimensionalize the governing system the potential E is scaled with a reference value E^* , $i(E)$ with a reference value I^* , x with L , y with w , and $H(x)$ with w . Then the dimensionless equation and conditions are written as

$$\epsilon^2 \tilde{E}_{\tilde{x}\tilde{x}} + \tilde{E}_{\tilde{y}\tilde{y}} = 0, \quad (2.19)$$

$$\tilde{E}_{\tilde{x}} = 0 \text{ at } \tilde{x} = 0, \quad (2.20)$$

$$\tilde{E}_{\tilde{x}} = 0 \text{ at } \tilde{x} = 1, \quad (2.21)$$

$$\tilde{E}_{\tilde{y}} = 0 \text{ at } \tilde{y} = 1, \text{ and} \quad (2.22)$$

$$\kappa \frac{(\epsilon^2 \tilde{E}_{\tilde{x}} \tilde{H}_{\tilde{x}} + \tilde{E}_{\tilde{y}})}{\sqrt{1 + \epsilon^2 \tilde{H}_{\tilde{x}}^2}} = \tilde{i}(\tilde{E}) \text{ at } \tilde{y} = -\tilde{H}(\tilde{x}). \quad (2.23)$$

Performing a binomial expansion on $\frac{1}{\sqrt{1 + \epsilon^2 \tilde{H}_{\tilde{x}}^2}}$ in the last boundary condition, the equation (2.23) is rewritten as

$$\left(1 - \epsilon^2 \frac{\tilde{H}_{\tilde{x}}^2}{2} + \epsilon^4 \frac{3\tilde{H}_{\tilde{x}}^4}{8} - \dots\right) (\epsilon^2 \tilde{E}_{\tilde{x}} \tilde{H}_{\tilde{x}} + \tilde{E}_{\tilde{y}}) = \frac{I^* w}{\kappa E^*} \tilde{i}(\tilde{E}). \quad (2.24)$$

Here the binomial expansion is a valid approach because the second term of the expression is small as compared to the first.

The magnitude of the non-dimensional group, $W = \frac{I^* w}{\kappa E^*}$, on the right hand side of (2.24) must be determined. Using approximated values for each parameter, the group is defined as $\widehat{ND}\epsilon^2$, where $\widehat{ND}$ is a constant. The size $\mathcal{O}(\epsilon^2)$ guarantees that the current density term does not appear in the $\mathcal{O}(1)$ -problem for the potential but does appear in the $\mathcal{O}(\epsilon^2)$ -problem. It is now shown that the system can be reduced to a single dimension. Assuming the asymptotic expansion $1, \epsilon^2, \epsilon^4, \dots$, and dropping the tilde's for the dimensionless quantities the $\mathcal{O}(1)$ -problem is

$$E_{0yy} = 0 \text{ s.t. } E_{0y} = 0 \text{ at } y = 0, 1. \quad (2.25)$$

Integrating once with respect to y gives

$$E_{0y} = A(x), \quad (2.26)$$

where $A(x)$ is a function of the independent variable x . Applying the boundary condition $E_{0y} = 0$ implies that $A(x)$ must equal zero. Integrating the resulting first order equation, $E_{0y} = 0$, yields the $\mathcal{O}(1)$ potential equation,

$$E_0 = B(x), \quad (2.27)$$

where $B(x)$ is the $\mathcal{O}(1)$ potential that depends only on the spatial variable x .

The next term in the asymptotic sequence is of magnitude $\mathcal{O}(\epsilon^2)$ and is a small perturbation to the leading order solution. Together, the two define the shape of the potential in the electrolyte across the anode and cathode in the x direction. The $\mathcal{O}(\epsilon^2)$ equation and corresponding boundary conditions are

$$E_{1yy} = -E_{0xx}, \quad (2.28)$$

$$E_{1y} = 0 \text{ at } y = 1, \text{ and} \quad (2.29)$$

$$E_{1y} + E_{0x}H_x = \widehat{NDi}(E_0) \text{ at } y = -H. \quad (2.30)$$

Using (2.27) and (2.29) determines that

$$E_{1y} = -B_{xx}y + B_{xx}. \quad (2.31)$$

Applying (2.30), equation (2.31) reduces to

$$[(1 + H)B_x]_x = \widehat{NDi}(B). \quad (2.32)$$

After re-dimensionalizing the system, the final one-dimensional equation for the potential is written as

$$[(w + H)E_x]_x = \frac{i(E)}{\kappa}. \quad (2.33)$$

It is important to note that the damage H and the potential E are both spatially only a function of x . The advantage of this asymptotic approach is that the equation to be solved is reduced from two dimensions to a single dimension. The only limitations on the system are that ϵ must remain small and that the non-dimensional

Wagner group W must be $\mathcal{O}(\epsilon^2)$. The complete potential equation to be solved in the electrolyte is

$$\begin{aligned} \text{Anode : } [(w + H)E_x]_x &= \frac{i_a(E)}{\kappa} \\ \text{Cathode : } [wE_x]_x &= -\frac{i_c(E)}{\kappa}. \end{aligned} \tag{2.34}$$

The corresponding analytic boundary conditions for the 1D potential equations are

$$\text{No flux at } x = 0 : E_x = 0 \tag{2.35}$$

$$\text{No flux at } x = L : E_x = 0.$$

In (2.34) the damage H is zero across the cathode, the current density across the anode is $i_a(E)$, and the current density across the cathode is $i_c(E)$. The positive right hand side of the equation across the anode implies that the potential across the anode will be concave upward. The negative right hand side of the equation across the cathode implies that the potential across the cathode will be concave downward. The change in the direction of the current density thus accounts for the change in the concavity of the potential at the anode/cathode interface. In (2.35) $x = 0$ corresponds to the left anode boundary and $x = L$ corresponds to the right cathode boundary.

Integrating the potential equation (2.34) across the domain results in

$$\kappa[(w + H(F^-))E_x(F^-)] = \int_0^{F^-} i_a(E)dx \tag{2.36}$$

across the anode, and

$$\kappa[wE_x(F^+)] = \int_{F^+}^L -i_c(E)dx \tag{2.37}$$

across the cathode. The Divergence theorem (2.38) for the full potential is applied to the 2D electrolyte domain. Mathematically, the Divergence theorem applied to the electrolyte domain states that

$$\iint_R \nabla^2 E dA = \int_C \frac{\partial E}{\partial n} ds = 0, \quad (2.38)$$

where the double integral is defined on the closed bounded 2D electrolyte domain R and the line integral is defined along the piecewise smooth boundaries of the electrolyte domain C . The total line integral on the right hand side can be rewritten as the net sum of line integrals around the domain.

It is clear from the no flux boundary conditions across the top, left, and right electrolyte boundaries that the sum of the line integrals is equal to the contribution from the metal/electrolyte interface only. Here there are three segments; the damaged section along the anode, the newly exposed vertical segment at the interface of the cathode and anode, and the non-damaged horizontal segment along the cathode. Each part contributes to the integral based upon the corresponding Ohm's law boundary condition, $-\kappa \nabla E \cdot n = i(E)$, where $i(E) = i_a(E) - i_c(E)$. The line integral in (2.38) is then written as

$$\int_0^{F^-} (\nabla E \cdot n) \sqrt{1 + (H_x)^2} dx + \int_0^H -\frac{\partial E}{\partial x} dy + \int_{F^+}^L -\frac{\partial E}{\partial y} dx = 0. \quad (2.39)$$

Non-dimensionalizing the system with the same parameters used in equation (2.19) eliminates $\sqrt{1 + (H_x)^2}$ because $(H_x)^2$ becomes $\mathcal{O}(\epsilon^2)$. From the Ohm's law boundary condition $\nabla E \cdot n$ across the anode becomes $-\frac{i_a(E)}{\kappa}$ and $\frac{\partial E}{\partial y}$ across the

cathode becomes $\frac{i_c(E)}{\kappa}$. Assuming a constant potential field along the vertical segment, the integration of the second term becomes $-HE_x(F^+)$. The net sum in (2.39) becomes

$$\int_0^{F^-} \frac{i_a(E)}{\kappa} dx - HE_x(F^+) - \int_{F^+}^L \frac{i_c(E)}{\kappa} dx = 0. \quad (2.40)$$

Substituting the expressions from (2.36) and (2.37) into (2.40) results in

$$w(E_x(F^-) - E_x(F^+)) + H(E_x(F^-) - E_x(F^+)) = 0. \quad (2.41)$$

Since $w > 0$ and $H > 0$ for all systems, (2.41) demands that $(E_x(F^-) - E_x(F^+)) = 0$ to satisfy the right hand side of the equation. The Divergence theorem result thus requires the derivative of the potential across the anode/cathode interface to balance. Looking again at (2.36) and (2.37) it is clear that the expressions for the total net current across the anode and cathode do not balance. This implies that the analytic procedure is not directly accounting for the newly exposed vertical cathode segment. The additional term $H(F^-)E_x(F^-)\kappa$ is required to be added to the integral across the cathodic current density so that the net currents in the system will balance.

A second equation, coupled to (2.34), is required to model the damage evolution through time. This equation is derived directly from Faraday's law,

$$v \cdot \hat{n} = \frac{i_a(E)M_w}{ZF_a\rho}, \quad (2.42)$$

where $v \cdot \hat{n}$ is the normal velocity of the metal/electrolyte interface, $i_a(E)$ is the anodic current density, M_w is the molecular weight of the anodic metal that is corroding, ρ is the density of the anodic metal, F_a is Faraday's constant, and Z is the valence

number charge of an electron of the anodic metal. Using the properties of the normal derivative, the rate of corrosion dissolution becomes

$$\frac{H_t}{\sqrt{1 + H_x^2}} = \frac{i_a(E)M_w}{ZF_a\rho}. \quad (2.43)$$

After non-dimensionalizing the system the H_x^2 term in the denominator is of order $\mathcal{O}(\epsilon^2)$. Under this thin film approximation the leading order damage equation is

$$H_t = \frac{i_a(E)M_w}{ZF_a\rho}. \quad (2.44)$$

The corresponding initial condition for the damage is

$$H(x, 0) = 0. \quad (2.45)$$

The condition (2.45) implies that, prior to corrosion initiation, the damage across the anode is equal to zero.

Ohm's law states that the electric voltage in a system is equal to the product of current I and resistance R :

$$V = IR. \quad (2.46)$$

Analyzing the potential equation in cartesian coordinates with zero damage,

$$\kappa [wE_x]_x = i_a, \quad (2.47)$$

where E represents the potential and i_a represents the anodic current density, can help to describe the IR drop through the electrolyte. Replacing the partial derivatives with the length scale, L , (2.47) can be written as

$$\triangle E = i_a \frac{L^2}{\kappa w}. \quad (2.48)$$

Multiplying the right hand side of (2.48) by $\frac{D}{D}$, the voltage change is defined as ΔE , the current is $i_a LD$, and the resistance is $\frac{L}{\kappa w D}$. Combining these terms, (2.48) is described as the voltage = IR drop across the anode, as shown in Figure 2.2.

Figure 2.2: Cross-sectional view of the electrolyte solution.

Analyzing the Ohm's Law equation, written as

$$\Delta E = [i_a LD] \left[\frac{L}{\kappa w D} \right], \quad (2.49)$$

gives insight into potential distribution in the electrolyte solution. A large IR drop is equivalent to a large voltage drop, and is the result of a large current and/or a large resistance. A system with a large IR drop allows for a large change in potential across the anode/cathode domain. A small IR drop in the electrolyte restricts the potential drop through the domain. This resistance effect is a key piece of analysis when determining the corrosive behavior. Aggressive systems, with large domains in thin film environments, define the upper, maximum bound for IR drop. Vice versa, small domains in bulk electrolytes, with small galvanic current densities, describe the lower, minimum bound for IR drop. The one-dimensional potential equation,

coupled with the rate of corrosion damage equation, can now be solved using an iterative scheme. Before solving the governing equations in rectangular coordinates numerically, the 1D approach is extended to cylindrical coordinates.

2.3 Cylindrical Model

The cylindrical system and the corresponding electrolyte solution domain are represented in Figure 2.3.

Figure 2.3: (a) Cylindrical concentric system; (b) Cylindrical electrolyte domain as shown in (a).

The system is radially symmetric about the r axis at the reference point $r = 0$. The function $f(r)$ defines the shape of the inner cylinder's plug head. This base model does not model a fastener with a larger bolt head, as the damage cannot undercut the bolt head due to the one-dimensional damage equation. Like the cartesian setup, the cylindrical equations can be solved only for the damage in the positive y -direction. This restricts the 1D model to geometries that corrosively drill in a single direction.

The solution procedure for cylindrical configurations follows the same process as shown for the cartesian model. The governing equation and boundary conditions for the potential in the electrolyte for the base fastener system are

$$E_{rr} + \frac{1}{r}E_r + E_{zz} = 0, \quad (2.50)$$

$$E_r = 0 \text{ at } r = 0, \quad (2.51)$$

$$E_r = 0 \text{ at } r = L, \quad (2.52)$$

$$\nabla E \cdot \hat{n} = 0 \text{ at } z = w + f, \text{ and} \quad (2.53)$$

$$-\kappa \nabla E \cdot \hat{n} = i(E) \text{ at } z = S(r). \quad (2.54)$$

The function defining the shape of the bottom boundary is defined as $S(r) = f(r) - H(r)$, where $f(r) = 0$ from $F < r < L$ and $H(r) = 0$ from $0 < r < F$. Note that, when $f(r) = 0$ from $0 < r < F$, the system is simply two concentric disks. The point $r = 0$ corresponds to the center line of the cathode, and $r = L$ corresponds to the right boundary of the anode. After non-dimensionalizing r with L , z with w , f with w , and the other values with the same values as in the cartesian setup, the non-dimensional equation and boundary conditions are

$$\epsilon^2 \tilde{E}_{\tilde{r}\tilde{r}} + \frac{\epsilon^2}{\tilde{r}} \tilde{E}_{\tilde{r}} + \tilde{E}_{\tilde{z}\tilde{z}} = 0, \quad (2.55)$$

$$\tilde{E}_{\tilde{r}} = 0 \text{ at } \tilde{r} = 0, \quad (2.56)$$

$$\tilde{E}_{\tilde{r}} = 0 \text{ at } \tilde{r} = 1, \quad (2.57)$$

$$\nabla \tilde{E} \cdot \hat{n} = 0 \text{ at } \tilde{z} = 1 + \tilde{f}, \text{ and} \quad (2.58)$$

$$\left(1 - \epsilon^2 \frac{\tilde{S}_{\tilde{r}}^2}{2} + \epsilon^4 \frac{3\tilde{S}_{\tilde{r}}^4}{8} - \dots\right) (\epsilon^2 \tilde{E}_{\tilde{r}}(-\tilde{S}_{\tilde{r}}) + \tilde{E}_{\tilde{z}}) = \frac{I^* w \tilde{i}(\tilde{E})}{\kappa E^*} \text{ at } \tilde{z} = \tilde{S}. \quad (2.59)$$

After solving the $\mathcal{O}(1)$ problem it is found that $E_0 = B(r)$. After solving the $\mathcal{O}(\epsilon^2)$ problem, applying the boundary condition at $\tilde{z} = \tilde{S}$, and re-dimensionalizing the system, the one-dimensional equation for the potential becomes

$$\frac{1}{r} [r E_r]_r (w + f - S) - E_r S_r = \frac{i(E)}{\kappa}. \quad (2.60)$$

Together with the damage equation derived from Faraday's Law,

$$H_t = \frac{i_a(E) M_w}{Z F_a \rho} \text{ subject to } H(r, 0) = 0, \quad (2.61)$$

the damage evolution for the cylindrical model can be simulated using an iterative numerical approach. The completed potential equation to be solved is written as

$$\begin{aligned} \text{Anode : } & \frac{1}{r} [r E_r]_r (w + H) + E_r H_r = \frac{i_a(E)}{\kappa} \\ \text{Cathode : } & \frac{1}{r} [r E_r]_r (w) - E_r f_r = -\frac{i_c(E)}{\kappa}. \end{aligned} \quad (2.62)$$

The corresponding boundary conditions for (2.62) are

$$\text{No flux at } r = 0 : E_r = 0 \quad (2.63)$$

$$\text{No flux at } r = L : E_r = 0.$$

In (2.62) the shape of the bolt head f is zero across the anode, the damage H is zero across the cathode, the current density is $i_a(E)$ across the anode, and the current density is $i_c(E)$ across the cathode. In (2.63) $r = 0$ corresponds to the line of symmetry of the system and $r = L$ corresponds to the outside boundary location of the anodic disk.

The main purpose of proposing an additional one-dimensional model for the radial geometry is to show the versatility of this asymptotic approach. The same asymptotic procedure is followed for each system resulting in a uni-directional corrosive damage. Additional cylindrical geometries and their models are presented in Appendix B. Parameters and expressions used for the mathematical derivation procedure are defined in Tables 2.1, 2.2, and 2.3.

Table 2.1: Parameters and Units

Name	Variable	Units
Concentration of the i -th species	C_i	$\frac{\text{mole}}{\text{cm}^3}$
Flux of the species	J	$\frac{\text{mole}}{\text{cm}^2 \text{ s}}$
Mass diffusion coefficient of the i -th species	D_i	$\frac{\text{cm}^2}{\text{s}}$
Valence number of the i -th species	Z_i	$+/- \# \text{ of electrons}$
Faraday's constant	F_a	$\frac{\text{Coulomb}}{\text{mole}}$
Universal gas constant	R	$\frac{\text{Joule}}{\text{mole}^\circ K}$
Temperature	T	$^\circ K$
Velocity vector component	$\bar{u} = \langle u, v \rangle$	$\frac{\text{cm}}{\text{s}}$
Length of domain	L	cm
Distance from origin to anode/cathode interface	F	cm
Electrolyte thickness	w	cm
Conductivity of the electrolyte	κ	$\frac{\text{Siemens}}{\text{cm}}$
Damage shape function (cartesian)	$H(x)$	cm
Damage shape function (cylindrical)	$H(r)$	cm
Plug-head shape function	$f(r)$	cm
Potential	E	Volt
Current density	$i(E)$	$\frac{\text{Ampere}}{\text{cm}^2}$
Anodic current density	$i_a(E)$	$\frac{\text{Ampere}}{\text{cm}^2}$

Table 2.2: Parameters and Units cont.

Name	Variable	Units
Cathodic current density	$i_c(E)$	$\frac{\text{Ampere}}{\text{cm}^2}$
Molecular weight	M_W	$\frac{\text{gram}}{\text{mole}}$
Material density	ρ	$\frac{\text{gram}}{\text{cm}^3}$

Table 2.3: Relationships and Equations

Title	Description
Nernst-Plank equation	$\frac{\partial C_i}{\partial t} = -\nabla \cdot \bar{J}$
Electro-neutrality condition	$\sum_i Z_i C_i = 0$
Laplace equation	$\nabla^2 E = 0$
Aspect ratio	$\frac{w}{L} = \mathcal{O}(\epsilon)$
Wagner non-dimensional group	$\frac{I^* w}{\kappa E^*} = \widehat{ND} \epsilon^2$
Total current density	$i(E) = i_a(E) - i_c(E)$
Conductivity	$\kappa = F_a^2 \sum_i [Z_i^2 \frac{D_i}{RT} C_i]$
Directional normal vector (cartesian)	$\hat{n} = \frac{\langle H_x, 1 \rangle}{\sqrt{H_x^2 + 1}}$
Directional normal vector (cylindrical)	$\hat{n} = \frac{\langle H_r - f_r, 1 \rangle}{\sqrt{(H_r - f_r)^2 + 1}}$
Assumed asymptotic sequence	$1, \epsilon^2, \epsilon^4, \dots$
Ohm's law	$V = IR$

CHAPTER III

NUMERICAL FORMULATION

The equations (2.34) and (2.62) are second order boundary value problems (BVPs) with piece-wise defined sources. Matlab's [23] `bvp4c` solver can solve these problems effectively. The anodic and cathodic regions divide the entire domain into two sub-domains. The continuity of the potential and its derivative at the interface are automatically handled by the routine. At each time step, the potential is computed and the corresponding damage profile is updated.

3.1 Numerical Domain

A finite difference method (FDM) is a scheme in which each derivative is replaced with an approximation. The resulting 'discrete equation' is solved on the discretized grid, in this case (x_j, t_n) . Discretization in time is represented by the variable n , where n represents the current time step, $n - 1$ represents the previous time step, and $n + 1$ represents the next time step. Time steps n and $n - 1$ represent known terms in time and $n + 1$ represents unknown terms. Discretization in space is represented by the variable j representing the current grid point; $j - 1$ represents the grid point to the left, and $j + 1$ represents the grid point to the right of j , respectively. Discretization

in space only requires a single spatial grid, because the potential in the electrolyte is one-dimensional in space.

Figure 3.1: Discretization molecule - 1D space and time.

A discretization computational molecule, as shown in Figure 3.1, contains the entire set of points that are used in a FDM and can help to understand the numerical time and space grid. The solution to the damage equation is first calculated across the spatial grid for the initial time step, using a forward difference approximation at the left BC, a backward difference at the right BC, and central differences at the interior points. The various FDM schemes are chosen so that the solution at known grid points can be properly used to predict the solution at unknown grid points. The known spatial solution at t_n is then used to update the solution at the next time step via a forward difference approximation in time. This process is followed until

the solution is known at each spatial grid location and time step through the entire numerical computational molecule.

Numerical inputs include specifying the grid size for both time and space, the total time for the code to run, and the tolerance for the BVP solver. The integer $nmax$ represents the total length of the time grid, and dt represents the time increment. The integer $imax$ defines the length of the spatial grid, and dx represents the spatial increment. Both spatial and time grids are uniform. The specified uniform spatial grid is only used to solve the damage equation. A tolerance input, that is required by the `bvp4c` script, uses an adaptive grid technique to define the relative error permitted for the solution to the potential differential equation. The adaptive grid adapts with the solution. A minimal tolerance input creates a very fine grid across the potential solution domain. Additional grid points are placed at locations with sharp corners and less are used in more flat areas. In this numerical simulation the `bvp4c` scheme is only required for the potential equation. Therefore the input tolerance only effects the potential domain, while the specified dx and $imax$ specify the discretized damage spacing. The grid size and tolerance are chosen so that the code is efficient in calculation speed while still obtaining a minimal error to the solution and numerical convergence through time.

3.2 Discretization of the Damage Equation

The equation for corrosion damage, (2.44), is discretized using the common forward difference method, Euler's Method, and is written as

$$H_j^{N+1} = H_j^N + dt \frac{i_a(E_j(i))M_W}{2F_a\rho}. \quad (3.1)$$

Equation 3.1 is solved over an equally spaced anode grid. Here the forward difference method is used to approximate the time derivative H_t . The derivative H_x is required for the BVP solution procedure for the anodic potential equation. It is approximated by second order finite difference methods, and written as

$$\begin{aligned} (H_x)_j^{N+1} &= \frac{1}{2dx}(-3H_j^N + 4H_{j+1}^N - H_{j+2}^N) \quad \text{for } j = 1, \\ (H_x)_j^{N+1} &= \frac{1}{2dx}(H_{j+1}^N - H_{j-1}^N) \quad \text{for } j = 2, \dots, N-1, \text{ and} \\ (H_x)_j^{N+1} &= \frac{1}{2dx}(3H_j^N - 4H_{j-1}^N + H_{j-2}^N) \quad \text{for } j = N. \end{aligned} \quad (3.2)$$

Since the damage equation has no spatial components, the discretization for H and H' are the same for all 1D models in all coordinate systems.

3.3 Cartesian Potential Equation

$$[(w + H)E_x]_x = \frac{i(E)}{\kappa}. \quad (3.3)$$

The numerical setup for the potential equation is first described for the rectangular cartesian system. The second order cartesian potential equation (3.3) is cast as a system of first order equations for use in bvp4c. The standard definitions,

$$z_1 = E, \text{ and} \quad (3.4)$$

$$z_2 = E_x \quad (3.5)$$

where z_1 is defined as the potential E , and z_2 is the derivative of the potential E_x lead to the system

$$z_1' = z_2 \quad (3.6)$$

$$z_2' = \frac{i(z_1) - H'\kappa z_2}{(w + H)\kappa}. \quad (3.7)$$

In the anodic region $i(z_1) = i_a(E)$ allows equation (3.7) to be written as

$$E_{xx} = \frac{i_a(E) - H'\kappa E_x}{(w + H)\kappa}, \quad (3.8)$$

and in the cathodic region $i(z_1) = -i_c(E)$, $H = 0$, and $H' = 0$ because there is assumed to be no corrosion of the cathode, so equation (3.7) is written as

$$E_{xx} = \frac{-i_c(E)}{w\kappa}. \quad (3.9)$$

In mathematical terms, the second order ODE for the potential requires two boundary conditions in space. Numerically, `bvp4c` requires an additional boundary condition at the interface of the cathode/anode. Insulated boundary conditions are used for the two separate boundaries of the anode and cathode. These imply that no change in potential occurs in the far-field, away from the anode/cathode interface. The additional interface condition requires that the total net current across the anode and the cathode is balanced. This condition requires a continuous potential across the anode/cathode interface. Continuity is obtained via implementing matching potentials and change in potentials at the interface. Table 3.1 shows the variations between the cartesian analytical and `bvp4c` numerical boundary conditions.

Table 3.1: Cartesian Analytic vs. Numeric BC's

Location and Description	Math	Code
No flux at $x = 0$	$E_x = 0$ at $x = 0$	$El(2, 1) - 0$
No flux at $x = L$	$E_x = 0$ at $x = L$	$Er(2, end) - 0$
Matching potentials at interface	$E(x^+) = E(x^-)$ at $x = F$	$Er(1, 1) - El(1, 2)$
Matching flux at interface	$E_x(x^+) = E_x(x^-)$ at $x = F$	$Er(2, 1) - El(2, 2)$

Initial conditions are also required by the BVP solver `bvp4c`. An initial guess for the horizontal grid must be defined with equally spaced data points and a repeated interface location data point. This repeated point allows the BVP solver to identify where the system switches regions. An initial guess for the vertical component must also be defined. This component requires an initial condition for the potential and the current. The initial potential can be chosen as the initial operating galvanic couple potential, and the required balancing of currents implies an initially defined current of zero. These numerical initial conditions guarantee that `bvp4c` finds the appropriate solution to the potential equation.

3.4 Cylindrical Potential Equation

To numerically set up the fastener plug cylindrical model, the discretized system of equations for the potential need to be established from (3.10)

$$\frac{1}{r}[rE_r]_r(w + f - S) - E_r S_r = \frac{i(E)}{\kappa}. \quad (3.10)$$

The first order system of equations for the cylindrical model potential are

$$z'_1 = z_2, \text{ and} \quad (3.11)$$

$$z'_2 = \frac{\frac{i(z_1)}{\kappa} - \frac{1}{r+1e^{-6}}z_2(w + f - S) + z_2 S_r}{(w + f - S)}. \quad (3.12)$$

In the anodic region (3.12) is written as

$$E_{rr} = \frac{\frac{i_a(E)}{\kappa} - \frac{1}{r+1e^{-6}}E_r(w + H) - E_r H_r}{(w + H)}, \quad (3.13)$$

and in the cathodic region (3.12) is written as

$$E_{rr} = \frac{-\frac{i_c(E)}{\kappa} - \frac{1}{r+1e^{-6}}E_r(w + f) + E_r f_r}{(w)}. \quad (3.14)$$

Recall that in the anodic region $f = 0$ and in the cathodic region $H = 0$. A small correction term $1e^{-6}$ is added to the denominator of the $\frac{1}{r}$ term to prevent the possibility of division by zero. The numerical BC's for the cylindrical system, as compared to the corresponding analytical BC's, are shown in Table 3.2.

Notice that the boundary conditions are identical for both models. However the interpretation of the conditions differ. The location $r = L$ corresponds to the far field boundary of the anode, since the anode represents the outside disk of the

Table 3.2: Cylindrical Analytic vs. Numeric BC's

Location and Description	Math	Code
No flux at $r = 0$	$E_r = 0$ at $r = 0$	$El(2, 1) - 0$
No flux at $r = L$	$E_r = 0$ at $r = L$	$Er(2, end) - 0$
Matching potentials at interface	$E(r^+) = E(r^-)$ at $r = F$	$Er(1, 1) - El(1, 2)$
Matching flux at interface	$E_r(r^+) = E_r(r^-)$ at $r = F$	$Er(2, 1) - El(2, 2)$

system. Also, $r = 0$ corresponds to the axi-symmetric center location of the internal plug shaped disk. The matching potential and flux at the origin define that the peak potential across the internal cathode occurs at this location. The concavity of the potential must change at this location. After the equations are discretized and the model is fully defined, the global and case-specific parameters of the code are ready to be implemented.

3.5 Numerical Model Parameters

The system parameters are shown in Table 3.3. The molecular weight, M_w , and the density, ρ , of the anodic metal must both be specified. Additionally, the conductivity of the electrolyte solution, κ , the thickness of the electrolyte, w , the length from the origin to the cathode/anode interface, F , and the length of the entire system, L , must be specified. Faraday's constant is defined as a global parameter, and the corroding anode's valence number are required for the damage equation. A uniform electrolyte

Table 3.3: Material Parameters

Variable	Value
Conductivity of 1.6% NaCl (κ_m)	.0271 $\frac{\text{Siemens}}{\text{cm}}$
Conductivity of .1M NaCl (κ_a)	.0105 $\frac{\text{Siemens}}{\text{cm}}$
Aluminum molecular weight (M_w)	26.98 $\frac{\text{g}}{\text{mole}}$
Magnesium molecular weight (M_w)	26.82 $\frac{\text{g}}{\text{mole}}$
Aluminum density (ρ_a)	2.80 $\frac{\text{g}}{\text{cm}^3}$
Magnesium density (ρ_m)	1.820 $\frac{\text{g}}{\text{cm}^3}$
Faraday's constant (F_a)	96485.3365 $\frac{\text{Coulombs}}{\text{mole}}$
Aluminum valence number (Z_a)	3
Magnesium valence number (Z_m)	2

thickness is built into the model guaranteeing that there is a uniform thin film across the anode and defined cathode shape, as shown in Figure 2.3a. For the cylindrical, plug setup, the functional shape of the plug head must also be defined. The function describing the parabolic shape of the plug-head is

$$f(r) = p\sqrt{1 - \frac{(r - L)^2}{(L - F)^2}}, \quad (3.15)$$

where p is the height of the plug-head.

The final input required to run the numerical simulation for a given galvanic system is the galvanic polarization curve for the metals in consideration. This curve is typically plotted as the potential versus the logarithmic current density for each

metal on a single graph. This input is crucial as it is used to define the entire galvanic system and the severity of corrosion on the anode. The larger the current density of the galvanic couple, the greater the maximum corrosion rate of the anode. Relating to the domain, the corrosion is highest at those locations where the potential leads to the highest current density. The shape of the anodic and cathodic curves are then used to determine the rate of the corrosion across the rest of the anode. A steep polarization curve for the anode implies that a large change in potential results in a small change in current density. A shallow polarization curve implies that a small change in potential results in a large change in the current density.

3.6 GalvanicMaster Details

GalvanicMaster [22] is a user-friendly software package capable of predicting initial corrosive behavior for simple and complex galvanic assemblies. This tool is used to verify initial data for all simulations modeled in this thesis. These comparisons validate the setup of the model by comparing the current density, potential, and corrosion rate across the metal surface of the galvanic couple. An analysis is conducted in Chapter 4 comparing the initial time corrosion rate predictions of GalvanicMaster to the dynamic corrosion rate predictions of this thesis. It is shown that for some non-aggressive scenarios, the corrosion rate remains essentially unchanged for a long time. However, for most moderate to severely corrosive scenarios, the corrosion rate continuously increases through time, and the initial corrosion rate serves as a poor prediction of long term damage.

GalvanicMaster solves the Laplace equation (2.13) for the potential in the electrolyte. For all geometries a specified uniform thin film of electrolyte is present around the entire assembly. The electrolyte is assumed to be well mixed, with no change in conductivity or transport of ionic species. The benefit of this software is that it can simulate the galvanic effects of extremely complex systems with various metals in contact. The geometry is specified in a .stl file that is generated and meshed from a CAD file in Elsyca's meshing package, Cad2Mesh. Once the geometry and correct units are specified for the galvanic assembly, the metals are specified in GalvanicMaster. A text file defining the monotonic polarization data for each metal along with a text file specifying each metal's material properties must be provided. A scaling factor is required to verify that GalvanicMaster is using appropriate units for the surface area of the assembly.

GalvanicMaster automatically re-meshes the Cad2Mesh .stl input files. With a finely meshed surface, the electrolyte parameters are ready to be input and the boundary conditions are ready to be defined. GalvanicMaster requires the user to define the electrolyte thickness, the electrolyte conductivity, the material properties, and the electrical connections between the metals. The solution procedure for this software is fast in computing the potential, current density, and corrosion rate across the surfaces. The solution procedure is output in a log file, while the data is output in a graphical format that can be analyzed through an included visualization package, Xplorer. Xplorer allows the user to output all corrosion characteristics along any specified surface line to an output .txt file.

CHAPTER IV

RESULTS

4.1 Galvanic Couples with Polarization Data

Although the proposed solution procedure is capable of modeling many systems, there are two specific galvanic systems used here for validation. The first system is as specified in Deshpande [1], where magnesium (Mg) is coupled with mild steel (MS) in 1.6% sodium chloride (NaCl) electrolyte. Analyzing the basic galvanic series chart for this NaCl solution shows that the large difference in open-circuit potential will lead to the rapid corrosion of magnesium. The actual Mg vs. MS curve and a simplified smoothed version that is used for numerical simplicity and capability analysis, are shown in Figure 4.1.

Analyzing Figure 4.1 it is obvious that the slight variations in the two curves will impact the behavior of the corrosion degradation. The impacts are more sensitive for bulk environments when the change in potential through the electrolyte is two-dimensional. For thin film environments the systems are nearly identical, because the potential only changes in the horizontal direction. The couple potential is at a slightly higher current density for the actual system and the actual magnesium curve has a steeper slope near the couple. The oscillating-like shape of mild steel minimally

Figure 4.1: Magnesium vs. mild steel actual and smoothed polarization curves.

affects the shape of the cathodic current density and the balancing total current.

The second system that was considered in this thesis is 99.999% aluminum (Al) vs. 99.9% copper (Cu) in 0.1 molar (M) NaCl solution. Copper acting as the cathode will cause the more anodic aluminum to corrode when they are in a galvanic couple. The polarization data for aerated Al vs. Cu in 0.1 M NaCl is shown in Figure 4.2a and is calculated via a cyclic potentiodynamic polarization test method [21]. For this procedure the open-circuit potential is first calculated individually for each metal. Then negative and positive potentials are applied separately to the system to analyze the corresponding current. Note that each metal's polarization data is calculated separately and then plotted on the same set of axes to obtain the galvanic polarization curve. The cathodic portion of copper is defined by a reduction reaction, and the

anodic portion of aluminum is defined by an oxidation reaction. These two processes fully define the oxidation and reduction processes required by galvanic corrosion. Figure 4.2b is an artificial de-aerated Al vs. Cu system in .1 M NaCl that is used for numerical evaluation purposes only. The numerical solution procedure is capable of handling severely non-linear, non-smooth curves, however it performs orders of magnitude faster with smooth fit data. Without Al/Cu experimental damage results to compare, it is only necessary to evaluate the artificial de-aerated system to further show the 1D model's capabilities.

Figure 4.2: (a) Experimental aerated aluminum vs. copper polarization curve. (b) Artificial de-aerated aluminum vs. copper polarization curve.

Aerated aluminum systems alter only the open-circuit potential of aluminum. The effect of air exposure imposes an additional large potential drop at low current density near the open-circuit potential of aluminum. De-aerated systems do not notice this additional change in potential and maintain open-circuit potential at a point prior to this effect. The variation will only impact thin film domains where the voltage

drop is large enough to capture the additional potential. The smoothed de-aerated curve is used to verify that the model can capture known physical phenomena for an additional galvanic couple. For future experimental verification the experimental aerated curve will be used.

The current density across aluminum is much smaller than that across magnesium. The galvanic couple potential for the Mg/MS system is at a current density of approximately $10^{-2} \frac{A}{cm^2}$, and the couple potential for the Al/Cu system is at approximately $10^{-5} \frac{A}{cm^2}$. The greater current density in the Mg/MS system implies that the maximum corrosion rate of the magnesium anode is much larger than that of the aluminum anode. For similar input parameters, the Ohm's law relationship (2.49) shows that the Al/Cu system will have a much smaller change in potential than the Mg/MS system, because the current density is much smaller. For constant electrolyte thickness a larger domain length, L , is required to obtain a large change in potential across the Al/Cu domain.

The small aluminum current density and resulting small change in potential will force uniform corrosion damage for most Al/Cu configurations. A system allowing a large change in potential is required to see significant corrosion of aluminum at the anode/cathode interface. Magnesium coupled with mild steel will corrode much faster and more severely than aluminum coupled with copper. Mg/MS has a much larger current density near the galvanic corrosion potential, thus a much larger change in potential. This naturally large change in potential results in severe localized corrosion at the anode/cathode interface for most Mg/MS configurations. A small domain

length with a small change in potential is required to notice more uniform corrosion of magnesium. Understanding the impact of these curves is important to understanding the behavior of corrosion degradation in each galvanic system.

The standard galvanic polarization curve is for two metals in a single electrolyte with equal area ratios. Increasing and decreasing cathode to anode area ratios leads to shifting the cathode potential to higher or lower corresponding current density. The new galvanic corrosion point is then the intersection of the shifted cathodic curve and the original anodic curve. The same procedure describing the damage is followed. Both curves are followed back from the galvanic couple potential to their corresponding open-circuit potential. For a perfect system, with a minimal voltage drop, the cathodic curve shift is 100% proportional to its area ratio. For a restrictive system, with a large IR drop, the large resistance does not allow the cathodic curve to shift the entire proportion of its area ratio. Under a thin film assumption with a large galvanic current density, the change in cathodic area ratio impacts the damage of the anode minimally.

4.2 Deshpande Verification

A verification with the Deshpande data [1] for Mg/MS is shown first. The geometry for this case is a cartesian system with a magnesium anode length of 1 *cm* and a mild steel cathode length of 1 *cm*. The total domain length of the system is 2 *cm*. An electrolyte thickness of 1 *cm* is used to imitate the immersed system proposed by the experiment. This $\frac{w}{L}$ ratio of $\frac{1}{2}$ defines the 1D upper limit for the thin film assumption

that $w \ll L$. Simulating the damage evolution for $t = 3$ days using the 1D code and GalvanicMaster for the actual polarization data, the calculated potential, current density, and damage is shown along with Deshpande's results in Figures 4.3 -4.8. The results for the smoothed polarization data are also compared to the Deshpande results to demonstrate the polarization curve's sensitivity in bulk electrolyte.

Figure 4.3: Deshpande 2D initial potential distribution [1]. The cathode zone is from $-0.01 \leq x \leq 0$ m and the anode zone is from $0 \leq x \leq 0.01$ m.

As shown in Figure 4.4, the 1D model and GalvanicMaster show good agreement for the initial change in potential across the Mg/MS system for both the actual and smoothed polarization curves. At the cathode/anode interface the potentials properly match the corresponding couple potentials from the curves. The 2D potential field, shown in Figure 4.3, demonstrates that the change in potential through the electrolyte is two-dimensional. For the 2D numerical simulation the current density

Figure 4.4: (a) GalvanicMaster vs. 1D initial potential results for smoothed Mg/MS polarization curve; (b) GalvanicMaster vs. 1D initial potential results for actual Mg/MS polarization curve. The anode zone is from $0 \leq x \leq 1 \text{ cm}$ and the cathode zone is from $1 \leq x \leq 2 \text{ cm}$.

is calculated using the actual voltage drop across the metal/electrolyte interface. The 1D numerical approach averages through the vertical direction and uses this average potential drop to calculate the corresponding current density. Figures 4.3 and 4.4b show that the couple potential of -1.34 V is properly predicted at the cathode/anode interface for both methods. This is true because there is no vertical change in potential at the cathode/anode interface. However, it is clear that the 2D metal/electrolyte change in potential of 0.245 V is larger than the 1D vertical average change in potential of 0.1775 V . The 2D simulation will absorb more of the magnesium curve away from the couple potential resulting in lower current density predictions away from the cathode/anode interface. Additionally, the shape of the magnesium curve near the couple potential defines various potential drops for the smooth and actual polarization systems.

Figure 4.5: Deshpande 2D numerical vs. experimental (SVET) initial current density results [1]. The anode zone is from $0 \leq x \leq 10 \text{ mm}$ and the cathode zone is from $10 \leq x \leq 20 \text{ mm}$.

(a)

(b)

Figure 4.6: (a) GalvanicMaster vs. 1D initial current density results for smoothed Mg/MS polarization curve; (b) GalvanicMaster vs. 1D initial current density results for actual Mg/MS polarization curve. The anode zone is from $0 \leq x \leq 1 \text{ cm}$ and the cathode zone is from $1 \leq x \leq 2 \text{ cm}$.

Figure 4.6a shows that the initial current density calculated by GalvanicMaster and the 1D approach predicts an interface corrosion rate of $217.9 \frac{mm}{yr}$ for the smoothed data and $228 \frac{mm}{yr}$ for the actual data. Both techniques predict an initial corrosion rate of $80.3 \frac{mm}{yr}$ for the smoothed data and $105.7 \frac{mm}{yr}$ for the actual data in the far-field, away from the interface. As shown in Figure 4.5, the Deshpande 2D initial current density predicts an interface corrosion rate of $210 \frac{mm}{yr}$, while the Deshpande SVET Experiment predicts an interface corrosion rate of $197 \frac{mm}{yr}$.

As predicted, the 1D initial total net current across the anode balances the initial total net current across the cathode. Integrating magnesium's initial current density in the x -direction for a 1 cm wide system implies that the area under the curve, the total net current, is 0.0049 A for the smoothed data. Similarly, the area under the mild steel initial current density curve for smoothed data is 0.0049 A . It is evident that the initial net currents match. This is true because the damage of $H = 0$ is allowing the surface currents to properly balance. The 1D smooth current density increases across the entire domain through 3 days, while the 1D actual current density increases only at points away from the anode/cathode interface. Increasing anode/cathode area ratio through time does not impact the actual data interface corrosion potential, because the mild steel curve is nearly flat near the couple potential.

Figure 4.8 displays the damage evolution predicted by GalvanicMaster and the 1D model. They both predict an equivalent interface corrosion damage of 1.88 mm in agreement with their initial corrosion rate calculation of $228 \frac{mm}{yr}$. GalvanicMaster's far-field prediction slightly under predicts the 1D model as the 1D current density

Figure 4.7: Deshpande 2D numerical vs. immersion experimental damage results through 3 days [1]. The anode zone is from $0 \leq x \leq 10$ mm and the cathode zone is from $10 \leq x \leq 20$ mm.

(a)

(b)

Figure 4.8: (a) GalvanicMaster vs. 1D damage results through 3 days for smoothed Mg/MS polarization curve; (b) GalvanicMaster vs. 1D damage results through 3 days for actual Mg/MS polarization curve. The anode zone is from $0 \leq x \leq 1$ cm and the cathode zone is from $1 \leq x \leq 2$ cm.

continually increases. The Finite Element Method used by Comsol and Deshpande, as shown in Figure 4.7, has difficulty gridding sharp corners. Therefore, the 2D model under-predicts the interface damage and the location of this interface damage. The 1D model shows good agreement with the SVET experiment for the maximum corrosion damage at the interface, but over predicts the degradation in the far-field due to the vertical averaging of the potential in the electrolyte. However, by understanding the bulk environments where the potential changes vertically through the electrolyte and the impact that this change has on the degradation, the 1D model can properly predict the damage evolution in bulk electrolytes.

The results presented for the Deshpande verification clearly demonstrate that the polarization curve is highly sensitive for the 1D model in bulk electrolytes. For thin film electrolytes, as shown in Figure 4.9, the variation in polarization data has less of an impact on the damage evolution prediction. Figure 4.9a shows the damage predictions for 1 *cm* Mg vs. 1 *cm* MS in $w = 0.1$ *cm* of 1.6% NaCl solution through 8 hours, and Figure 4.9b shows the results for the same system with $w = 0.05$ *cm*. For each case the damage evolution results, as predicted by the smoothed polarization curve, are compared to those from the actual polarization curve. Clearly, the 1D approach is much less polarization sensitive for thin films, as the results show similar total anodic area loss for both curves. The thin film allows the potential to change only in the horizontal direction, therefore imposing similar IR drops for each system. All in all, the smoothed curves are appropriate for thin film electrolytes and therefore will be considered for the remainder of the proposed results.

Figure 4.9: (a) 1D damage evolution for smooth vs. actual polarization data through 8 hours in $w = .1 \text{ cm}$ electrolyte.; (b) 1D damage evolution for smooth vs. actual polarization data through 8 hours in $w = .05 \text{ cm}$ electrolyte. The anode zone is from $0 \leq x \leq 1 \text{ cm}$ and the cathode zone is from $1 \leq x \leq 2 \text{ cm}$.

4.3 Capturing Physical Phenomena

GalvanicMaster initially calculates potential and current density that is valid for short time in systems exhibiting mild and relatively small IR drops. For longer times, in aggressive systems, the potential across the surface increases due to an increase in cathode/anode area ratio. The higher operating potential leads to a larger current density that increases the corrosion rate across the anode. The continuous updating mechanism is required to obtain the full long-term damage evolution. The GalvanicMaster method for corrosion rate prediction is not as accurate as calculating the true damage with Faraday's Law and a time dependent current density. Decreasing the electrolyte thickness to $w = 0.1 \text{ cm}$ for the Mg/MS smoothed system increases the IR drop through the electrolyte, allowing for more severe interface corrosion damage. Thus, the corrosion rate at the interface, as predicted by the 1D model, quickly in-

creases beyond the initial GalvanicMaster predicted corrosion rate, as shown by the 3 day potential and current density results in Figures 4.10 and 4.11.

Figure 4.10: Mg/MS evolution of potential in $w = 0.1$ cm electrolyte. The anode zone is from $0 \leq x \leq 1$ cm and the cathode zone is from $1 \leq x \leq 2$ cm.

As described in Chapter 3, the area under the anodic and cathodic current density curves do not appear to balance through time – the anodic current density is increasing and the cathodic current density is decreasing. This is due to the fact that the integral of the cathodic current density does not appropriately compensate for the vertically exposed area of the damage. Integrating the potential equation (2.34) to obtain the current density results in

$$\kappa[(w + H(F^-))E_x(F^-)] = \int_0^{F^-} i_a(E)dx \quad (4.1)$$

Figure 4.11: Mg/MS evolution of current density in $w = 0.1 \text{ cm}$ electrolyte. The anode zone is from $0 \leq x \leq 1 \text{ cm}$ and the cathode zone is from $1 \leq x \leq 2 \text{ cm}$.

across the anode, and

$$\kappa[wE_x(F^+)] = \int_{F^+}^L -i_c(E)dx \quad (4.2)$$

across the cathode. The additional term that is added to the anodic current density is not accounted for by the cathodic current density. However, manually adding the additional term $H(F^-)E_xF^-\kappa$ to the area under the cathodic current density curve shows that the total net currents in the system do balance. For example, the total net current across the anode at 3 days is approximately $0.0047 \frac{A}{cm}$ and the total net current across the cathode is the area under the current density curve $0.0014 \frac{A}{cm}$ plus the additional term at the interface $0.0033 \frac{A}{cm}$, which equals $0.0047 \frac{A}{cm}$.

4.3.1 Varying Film Thickness

Here it is demonstrated that the 1D model indeed captures the important physical phenomena occurring in the well-mixed galvanic system. Introducing the second galvanic couple, Al/Cu in 0.1 M NaCl, the IR drop, resistance effect can be shown. Figure 4.12 plots initial potential for a 2 cm Al – 2 cm Cu system in various electrolyte thickness. Figure 4.13 plots initial current density for the same domain and changing electrolyte thickness.

Figure 4.12: Potential resistance effects for Al/Cu in various electrolyte thickness. The anode zone is from $0 \leq x \leq 2$ cm and the cathode zone is from $2 \leq x \leq 4$ cm.

Referring to the Ohm's law expression (2.49), it is clear that the prescribed current remains the same for all three cases, because the current only depends upon the current density and total domain length. Changing the electrolyte thickness

Figure 4.13: Current density resistance effects for Al/Cu in various electrolyte thickness. The anode zone is from $0 \leq x \leq 2 \text{ cm}$ and the cathode zone is from $2 \leq x \leq 4 \text{ cm}$.

alters only the resistance through the electrolyte. When $w = 0.01 \text{ cm}$ the resistance is equal to $\frac{38095}{D} \Omega$, when $w = 0.1 \text{ cm}$ the resistance is equal to $\frac{3809.5}{D} \Omega$, and when $w = 1 \text{ cm}$ the resistance is equal to $\frac{380.95}{D} \Omega$. Figure 4.12 demonstrates that the increasing electrolyte thickness and directly decreasing resistance lead to a smaller potential drop through the electrolyte domain. Figure 4.13 shows that this smaller change in potential leads to a smaller change in current density.

The current density drives the galvanic corrosion damage via Faraday's Law. Figure 4.13 shows that the larger electrolyte thickness leads to more uniform corrosion damage. It is important to note that the peak interface current density does not typically vary. However, the increased far-field current density influences a highly

increased total damage area of the aluminum anode. Figure 4.12 clearly shows that the change in concavity of potential is not affected by the resistance and occurs at the 2 cm interface with an approximate potential of -0.55 V.

Figure 4.14: Potential resistance effects for Mg/MS in various electrolyte thickness. The anode zone is from $0 \leq x \leq 1$ cm and the cathode zone is from $1 \leq x \leq 2$ cm.

Figures 4.14 and 4.15 show the effects of changing the electrolyte thickness for a 1 : 1 cm Mg vs. MS system in 1.6% NaCl. Increasing the electrolyte thickness directly decreases the resistance through the electrolyte, as it did in the Al/Cu system. The decreased resistance leads to a smaller IR drop. The decreased change in potential influences a larger current density across the metals away from the interface. The increased far-field current density leads to more total area damage of magnesium. Figure 4.14 shows that the 1 cm interface has, as predicted, a galvanic corrosion potential of approximately -1.35 V. The higher current in the Mg/MS system, as

Figure 4.15: Current density resistance effects for Mg/MS in various electrolyte thickness. The anode zone is from $0 \leq x \leq 1$ cm and the cathode zone is from $1 \leq x \leq 2$ cm.

compared to the Al/Cu system, naturally inflicts a larger IR drop. This reasoning justifies the steeper current density profiles shown in Figure 4.15.

4.3.2 Area Ratio Effects

Similarly, the area ratio effect is shown for each galvanic couple. Ohm's law implies that systems with smaller IR drops will show more of an anode/cathode area ratio effect than those with larger IR drops. Figures 4.16 and 4.17 show the initial potential and current density predictions for a 10 cm Al/Cu system in a 0.1 cm electrolyte. Various anode/cathode area ratios are overlaid on a single curve to capture the true effect. For this system the IR drop is fairly large due to the large domain and small w . A large voltage drop restricts the amount of area ratio effect for the system.

Figure 4.16: Al/Cu potential effects for various area ratios in $w = 0.1 \text{ cm}$ electrolyte.

Figure 4.17: Al/Cu current density for various area ratios in $w = 0.1 \text{ cm}$ electrolyte.

The base 1:1 scenario is modeled by a 5 *cm* Al and a 5 *cm* Cu couple. For this system, the interface location imposes the galvanic corrosion potential of -0.55 V. Figure 4.16 shows that increasing the anode/cathode area ratio to 2:8 increases the galvanic corrosion potential at the interface to -0.52 V. This transition influences a larger current density and corrosion rate across the anode, as shown in Figure 4.17. Conversely, decreasing the anode/cathode area ratio to 8:2 decreases the galvanic corrosion potential to -0.57 V. The corresponding current density is thus less than those of the 1:1 geometry. The amount of shift is directly related to the shape of the Al/Cu polarization curve, and changing the area ratio shifts the cathodic curve of copper to higher current density values along the stationary aluminum anodic curve.

The Mg/MS area ratio results are shown in Figures 4.18 and 4.19. The domain length for these results is 0.2 *cm*, the electrolyte thickness is 0.01 *cm*, and the potential and current density results are for initial time. Clearly the very small domain length drives the resistance through the electrolyte to be small. However, the large current density of the Mg/MS couple inflicts a larger total current. The larger current automatically creates a larger IR drop for this small domain.

The Mg/MS area ratio results closely resemble those from the Al/Cu system. Increasing the area ratio increases the potential, thus increasing the current density. Decreasing the area ratio decreases the potential, thus decreasing the current density. The large difference in domain lengths imply that the Mg/MS system is far more resistive than the Al/Cu system. A 50 times smaller Mg/MS domain length is required to imitate the same Al/Cu corrosive behavior. Increasing the electrolyte thickness to

Figure 4.18: Mg/MS potential effects for various area ratios in $w = 0.01 \text{ cm}$ electrolyte.

Figure 4.19: Mg/MS current density for various area ratios in $w = 0.01 \text{ cm}$ electrolyte.

the upper bound value of 0.1 *cm* allows for a smaller IR drop and a larger area ratio effect for the Mg/MS system.

4.3.3 Limiting Cathodic Influence

Fixing the anode length and increasing the cathode length leads to a saturation effect where the lengthening of the cathode does not affect the anode. For all points beyond that critical cathode length the anode corrodes as a single electrochemical metal forming its own cathode and anode via oxidation and reduction. Recognizing this critical point is important as the numerical solution cannot currently simulate systems beyond the critical cathode length. The current numerical procedure would not properly balance the currents occurring on the far-field cathode. Introducing this concept would require using the individual cathode curve to balance anodic and cathodic currents beyond the critical far-field point. Figure 4.20 shows that the critical point for the smoothed Al/Cu system in a $w = 0.01$ *cm* 0.1 M NaCl electrolyte with a fixed aluminum length of 1 *cm* occurs when copper reaches a length of 44 *cm*. Likewise, Figure 4.21 shows that the critical point for the smoothed Mg/MS system in a $w = 0.01$ *cm* 1.6% NaCl electrolyte with a fixed Mg length of 1 *cm* occurs when MS reaches a length of 10 *cm*. The less aggressive Al/Cu system imposes a smaller IR drop through the electrolyte, forcing the cathode critical point to occur much farther away from the anode/cathode interface.

Figure 4.20: Critical cathode length for Al/Cu in $w = 0.01$ cm electrolyte. The anode zone is from $0 \leq x \leq 1$ cm and the cathode zone is from $1 \leq x \leq 45$ cm.

Figure 4.21: Critical cathode length for Mg/MS in $w = 0.01$ cm electrolyte. The anode zone is from $0 \leq x \leq 1$ cm and the cathode zone is from $1 \leq x \leq 11$ cm.

4.4 Results in a Radial Geometry

The results in a radial geometry are shown in Figures 4.22, 4.23, and 4.24. The system is simulated for Mg/MS beneath a uniform 0.1 *cm* 1.6% NaCl electrolyte, with a 0.5 *cm* plug head height and a 3 *cm* total domain length. The results are compared with GalvanicMaster's initial results and are simulated through 7 days.

Figure 4.22: Potential results for a 2 *cm* Mg vs. 1 *cm* MS cylindrical plug in 0.1 *cm* electrolyte through 7 days.

Figure 4.22 shows the matching of the initial galvanic corrosion potential at the 2 *cm* Mg/MS interface of -1.35 V as illustrated by the polarization curve. The 1D potential increases dramatically through 7 days, implying that the corresponding current density is increasing as well. Figure 4.23 shows this increase in current density from approximately $0.01 \frac{\text{A}}{\text{cm}^2}$ to $0.024 \frac{\text{A}}{\text{cm}^2}$. GalvanicMaster predicts a similar initial

Figure 4.23: Current density results for a 2 *cm* Mg vs. 1 *cm* MS cylindrical plug in 0.1 *cm* electrolyte through 7 days.

Figure 4.24: Damage results for a 2 *cm* Mg vs. 1 *cm* MS cylindrical plug in 0.1 *cm* electrolyte through 7 days.

current density. The 0.1 *mm* thin film thickness leads to severe damage near the interface with negligible damage away from the interface. The damage evolution predicted by GalvanicMaster is only valid for short time. The 1D model's corrosion rate continually increases, leading to far more damage through 7 days as shown in Figure 4.24. The damage evolution of the cylindrical plug configuration will be larger than the cartesian configuration because of the increased cathode surface area. However, for this severe Mg/MS system a failure would be defined much earlier in time than 7 days.

The interpretation of results for the cylindrical model imitate those presented for the cartesian model. It is important to understand that the only adjustment occurs in the derivation procedure and the understanding of the limitations. All 1D models have strictly one-dimensional etching of corrosion and must abide by the assumptions that are used. The 1D models that are proposed in Appendix B follow the same numerical procedure as described in Chapter 3.

4.5 Simulation Limitations

For an acceptable numerical solution, the model assumptions must be valid. Verifying that the thin film assumption and the Wagner relationship are satisfied can help to guarantee that the solution obtained is accurate. The region of validity for the thin film assumption is defined as $\frac{w}{L} < \frac{1}{2}$. Analytically the thin film can be as small as desired. However, a small $\frac{w}{L}$ leads to a large resistance through the electrolyte. This large IR drop corresponds to a large potential drop through the electrolyte,

allowing for the system to follow the polarization curve from the galvanic couple further back toward the open-circuit potentials. Systems with this behavior, that have shallow 1:1 anodic curves, exhibit severe galvanic damage near the interface and minimal electrochemical corrosion of a single metal far away from the interface. Numerical simulations face issues when attempting to solve solution domains with sharp corners. To resolve this issue numerically, the user can run the simulation for an abbreviated domain length that still captures the entire anodic metal's curve back to its open-circuit potential. Then for the rest of the domain, across the anode, define the corrosion, manually, to be that of the standard electrochemical reaction that is not impacted by the galvanic couple. At some point in the domain the anode is not impacted by the cathode. From that point and forever beyond, the anode will corrode as a single metal immersed in an electrolyte.

Similar to the issue of a large resistance, the Wagner relationship also introduces a numerical concern. Its inequality, $w \ll \frac{\Delta E}{\Delta i} \kappa$, applies to the anode's anodic curve from the galvanic couple back to its open circuit potential. Understanding that the polarization curve is typically plotted on a logarithmic scale it is easily seen that the change in current density is minimal near the open circuit potential and large away from the open circuit potential. Therefore near the anodic open circuit potential the Wagner relationship is nearly always satisfied. However, away from the open circuit potential the large change in current density inflicts a much more restrictive Wagner relationship. Figure 4.25a shows an example of a steep anodic polarization curve and Figure 4.25b shows an example of a shallow anodic polarization curve.

Figure 4.25: (a) Steep anodic curve to demonstrate minimally restrictive Wagner representation; (b) Shallow anodic curve to demonstrate highly restrictive Wagner representation.

If Figures 4.25a and 4.25b were for the same metal in a typical salt water electrolyte the electrolyte's conductivity would be approximately $4.5 \frac{S}{m}$. For this conductivity a comparison can be made analyzing the Wagner relationship requirements for the two sample curves. The Wagner relationships for Figures 4.25a and 4.25b are

$$w \ll \frac{(-1.12 + 1.25)V}{(0.1 - 0.005)\frac{A}{m^2}} \left(4.5 \frac{S}{m} \right) = 6.16 \text{ m}, \quad (4.3)$$

$$w \ll \frac{(-0.90 + 1.0)V}{(10 - 1)\frac{A}{m^2}} \left(4.5 \frac{S}{m} \right) = 0.05 \text{ m}, \quad (4.4)$$

$$w \ll \frac{(-1.22 + 1.25)V}{(0.1 - 0.001)\frac{A}{m^2}} \left(4.5 \frac{S}{m} \right) = 1.36 \text{ m}, \text{ and} \quad (4.5)$$

$$w \ll \frac{(-1.13 + 1.15)V}{(10 - 1)\frac{A}{m^2}} \left(4.5 \frac{S}{m} \right) = 0.01 \text{ m}. \quad (4.6)$$

Equation (4.3) describes the Wagner relationship for the steep curve near its corrosion potential (large circles on the plot) and equation (4.4) for the steep curve away from

its corrosion potential (small circles on the plot). Equation (4.5) shows the Wagner relationship for the shallow curve near its corrosion potential and equation (4.6) for the shallow curve away from its corrosion potential. The Wagner relationship is much less restrictive near the corrosion potential requiring w to be much less than approximately 1.25 m for both the shallow and steep curves. Moving away from the corrosion potential shows that the much larger change in current density requires a much more restrictive w for each curve. The Al/Cu and Mg/MS systems used in this thesis satisfy the Wagner relationship for all presented cases.

The mathematical approach followed in Chapter 2 non-dimensionalizes the height of the damage H with the electrolyte thickness w . This implies that the results are only valid for cases where the depth of the damage is on the same order of magnitude as the electrolyte thickness. As shown for the thin film assumption, there is no sharp cut-off for this typical value. Almost all systems will undergo a small enough corrosion depth through long time, as required by the 1D approach. It must be clear, however, that the solution is not valid when the damage goes well beyond the thickness of the electrolyte. For example, if the electrolyte thickness is 1 cm and the domain length is 10 cm , the model cannot predict damage accurately beyond 4 or 5 cm in depth. It would be assumed that at a point much earlier in time, the system would be considered a failure. For the cylindrical model the height of the plug head is scaled with the electrolyte thickness parameter w . Therefore a large plug head height can not be simulated under the proposed approach. Most real life fastener applications have small bolt heads that can be handled by this model.

For the Al/Cu couple in 0.1 M NaCl it is clear that there is a smaller current density and smaller IR drop on nearly all systems. Small domain Al/Cu systems, in both thin film and bulk environments, will show uniform corrosion as a result of the small change in potential in the electrolyte. To notice more severe corrosion at the Al/Cu interface, a domain larger than $L = 2 \text{ cm}$ with a thin electrolyte must be used. The small galvanic current density restricts a large IR drop. The less severe corrosion behavior of the Al/Cu system allows it to be more easily modeled. Systems exhibiting uniform corrosion require short simulation time, while systems with sharp corrosion require larger simulation times.

The large galvanic current density of the Mg/MS system implies that almost all Mg/MS systems will have a large IR drop. For all systems larger than $L = 2 \text{ cm}$ the corrosion damage will be localized at the interface in both immersed and thin film environments. Large Mg/MS domains impose numerical difficulties, but by understanding the science, the domain length could be properly abbreviated to capture the entire galvanic reaction. To get uniform corrosion of magnesium the domain length must be shrunk sufficiently small to allow minimal change in potential across its surface.

Additionally, it was shown that polarization curves are much more sensitive in bulk electrolytes for the 1D numerical approach and GalvanicMaster. A large vertical change in potential causes the vertical potential averaging of the 1D approach to use potentials different than those directly located on the metal/electrolyte interface.

CHAPTER V

REVIEW AND FUTURE WORK

5.1 Conclusion

The work presented in this thesis includes the derivation of a one-dimensional model describing the damage evolution of various galvanic geometries. Results are presented for both a rectangular cartesian system and a concentric plug, cylindrical system. The results are for two different galvanic couples, magnesium coupled with mild steel in 1.6% NaCl and aluminum coupled with copper in 0.1M NaCl. The diversity between these couples demonstrates the capabilities of the 1D model.

The Nernst-Planck equation is reduced to the Laplace equation for the potential in the electrolyte, under a well-mixed assumption. Applying no flux boundary conditions to the insulated boundaries of the electrolyte and an Ohm's law condition along the metal/electrolyte interface, the system is defined. The equation for the potential in the electrolyte is reduced to a single dimension via an asymptotic approach. The thin film assumption of the electrolyte thickness is used to integrate out the upward direction of the electrolyte. Prescribing the Wagner relationship as a small parameter allows the final governing equation for the potential to be defined. The solution procedure remains constant for both configurations. The potential equation

(2.33) for the cartesian system is written as

$$[(w + H)E_x]_x = \frac{i(E)}{\kappa},$$

while the potential equation (2.60) for the cylindrical system is written as

$$\frac{1}{r}[rE_r]_r(w + f - S) - E_r S_r = \frac{i(E)}{\kappa}.$$

Using Faraday's law, equation (2.44), representing the rate of change of corrosion for the anode,

$$H_t = \frac{i_a(E)M_w}{eF_a\rho},$$

is derived. Coupled with the potential equation an iterative approach is followed solving for the damage evolution of the anode. The iterative approach uses Matlab's BVP solver, `bvp4c`, to simulate results. The main advantage of the one-dimensional approach is efficiency. For cases satisfying the key assumptions, this approach is fast, effective, and appropriate.

Summary of Major Assumptions:

- Well-mixed electrolyte: no concentration of species in the electrolyte
- No flux through the exterior boundaries: no change in potential through the outside 3 electrolyte surfaces
- Thin film electrolyte: electrolyte thickness w must be much smaller than the electrolyte total length L , implying $w \ll L$ or $\frac{w}{L} < \frac{1}{2}$

- Wagner relationship: electrolyte thickness w must be much smaller than the slope of the anodic polarization curve $\frac{\Delta E}{\Delta i}$ multiplied by the conductivity of the electrolyte κ , implying $w \ll \frac{\Delta E}{\Delta i} \kappa$ or $\frac{w \Delta i}{\Delta E \kappa} < \frac{1}{2}$

The model's results are verified using a software package, GalvanicMaster, for initial results, and literature [1, 6, 20], for damage evolution results. Thin film initial time results show great agreement with those predicted by GalvanicMaster for all configurations and materials. Pushing the limitations of the 1D model, attempting to model bulk electrolyte systems, shows that understanding the electrochemical science behind each system is important. For systems such as Mg/MS immersed in 1.6% NaCl, the 1D model matches the 2D model at the cathode/anode interface, but the large vertical change in potential forces the 1D averaging potential to over predict the far-field damage.

The sensitivity of polarization curve variations to the damage predictions by the 1D model is shown in the results. The curves are extremely sensitive for bulk electrolytes where large vertical changes in potential are apparent. For electrolytes with vertically uniform potential the effect of polarization curve variation is minimal. For these situations the experimental polarization curve can be smoothed and simplified to increase numerical performance.

The 1D model is also verified by showing its ability to capture known physical phenomena such as resistance and area ratio effects. Using Ohm's Law many scenarios are shown to additionally verify the 1D model. For most cases an increasing cathode/anode area ratio drives the potential to a corresponding larger current

density, and hence more damage. The cylindrical plug model is presented to show the capabilities of the asymptotic procedure for an alternate coordinate system. After the 1D model is fully verified the model's limitations are addressed. These limitations include discussing the upper and lower bounds of the electrolyte thickness, the impact of the Wagner relationship, and the necessity to abide by the sizes chosen during the non-dimensionalization process. While all constraints are affected by one another, a complete understanding of the process can allow the user to push their limitations quite far. The results section of this thesis clearly demonstrates that the one-dimensional approach to modeling the damage evolution of basic galvanic systems is effective. Many real-life applications can be visualized as simplified galvanic geometries. Making this initial transition to simplicity designates the 1D modeling approach as a key tool for understanding the damage evolution of galvanic corrosion.

Summary of Contributions/Findings:

- 1D potential and unidirectional damage evolution iterative numerical approach: fast and effective approach to simulating various galvanic systems that properly satisfy the key assumptions
- IR drop and current driven model: shape of the corrosion damage is influenced by the IR drop through the electrolyte and the severity of the galvanic operating current density
- Properly accounts for changing anode/cathode area ratios: corrosion rates properly reflect the increasing or decreasing anode/cathode relationship and the

restricting electrolyte resistance

- 1D approach can be developed for many configurations: a cylindrical plug configuration is proposed in this thesis and additional cylindrical configurations are briefly proposed in Appendix B
- Limitations of Wagner relationship: nearly always satisfied near the open circuit potential of the anode; is much more restrictive near the higher current density of the galvanic potential

5.2 Future Work

The development of galvanic corrosion modeling is currently focused on adapting higher dimensional models that can handle a larger variety of galvanic configurations. First, introducing an additional dimension through the height of the electrolyte imposes solving the full Laplace equation for the potential in the electrolyte. This process will remove the thin film restriction on the electrolyte width. For a 2D potential model, a two-dimensional damage equation will also be introduced accounting for the etching of the corrosion damage in the normal direction. This aspect will be especially important for modeling real life applications of fastener assemblies where undercutting of corrosion occurs. It will also be important for cases where the potential changes vertically through the electrolyte.

Separately, introducing an additional dimension in the horizontal direction implies accounting for the spread of corrosion damage across the surface of the metals.

This configuration requires solutions of a simplified Laplace equation, as used in this thesis, and does not require the implementation of a 2D damage equation. The final step in future work includes adding a full tracking of the species in the electrolyte. This component also includes tracking the corrosion products that develop in the electrolyte. Adding the concentration of chemical species in the electrolyte to the 1D model provides a base starting point, while a full transition into a species capable higher dimensional model provides a more accurate representation of real life galvanic corrosion applications.

5.2.1 2D Damage

Analyzing the following galvanic systems establishes the necessity of implementing a two-dimensional damage equation. The two fastener assemblies in Figure 5.1 do not

Figure 5.1: (a) Counter-sinked bolt-head; (b) Standard bolt-head configuration.

have galvanic corrosion damage solely in the vertical direction. In Figure 5.1a the etching of corrosion will follow the angle of the bolt-head, and in Figure 5.1b will

undercut the bolt head. With the current one-dimensional model neither phenomena is properly accounted for. The model is an IR driven model. This implies that a 2D damage equation requires the coupling with a 2D potential equation. The 2D potential will thus properly account for the change in potential through the vertical component of the electrolyte. Any system that does not allow for 1D damage must fully adapt the two-dimensional damage and potential equations.

5.2.2 Tracking Species

In some systems, the assumption of the uniform concentration of chemical species is not justified. There are gradients in the concentrations, allowing for the free transport of ions in the electrolyte. Here it is necessary to track each species that plays a role in the galvanic corrosion process. An expression for each ion can be written guaranteeing that the net sum of ions satisfies electro-neutrality (2.6). Each expression introduces a Nernst-Planck equation for its ion that must be solved. Without a uniform concentration of species in the electrolyte the Nernst-Planck equation (2.1) does not reduce to the Laplace equation. A system of Nernst-Planck equations must then be solved to fully track each species. It is also important to note that the electrical conductivity in the electrolyte is not constant in a species driven model and therefore varies in time and space. Similarly a changing PH alters the polarization data as the anode corrodes and the electrolyte evolves.

BIBLIOGRAPHY

- [1] K.B. Deshpande. Validated numerical modelling of galvanic corrosion for couples: Magnesium alloy (ae44) mild steel and ae44 aluminum alloy (aa6063) in brine solution. *Corrosion Science*, 52(10):3514 – 3522, 2010.
- [2] A. Rosendo. Corrosion comes in different forms. *Power Engineering*, Mar:14–20, 2011.
- [3] J.X. Jia, G. Song, and A. Atrens. Experimental measurement and computer simulation of galvanic corrosion of magnesium coupled to steel. *Advanced Engineering Materials*, 9(1-2):65–74, 2007.
- [4] J.X. Jia, G. Song, and A. Atrens. Influence of geometry on galvanic corrosion of az91d coupled to steel. *Corrosion Science*, 48(8):2133 – 2153, 2006.
- [5] J. X. Jia, G. Song, and A. Atrens. Boundary element method predictions of the influence of the electrolyte on the galvanic corrosion of az91d coupled to steel. *Materials and Corrosion*, 56(4), 2005.
- [6] K.B. Deshpande. Numerical modeling of micro-galvanic corrosion. *Electrochimica Acta*, 56(4):1737 – 1745, 2011.
- [7] G.L. Song. Potential and current distributions of one-dimensional galvanic corrosion systems. *Corrosion Science*, 52(2):455 – 480, 2010.
- [8] G. Song. Recent progress in corrosion and protection of magnesium alloys. *Advanced Engineering Materials*, 7(7):563–586, 2005.
- [9] G. Song, B. Johannesson, S. Hapugoda, and D.S. John. Galvanic corrosion of magnesium alloy az91d in contact with an aluminum alloy, steel and zinc. *Corrosion Science*, 46(4):955 – 977, 2004.
- [10] K.R. Hebert and B. Tribollet. Topics in the mathematical modeling of localized corrosion. In *Modern Aspects of Electrochemistry*, volume 44 of *Modern Aspects of Electrochemistry*, pages 289–340. Springer New York, 2009.

- [11] C. Blanc, Pebere N, B. Tribollet, and V. Vivier. Galvanic coupling between copper and aluminum in a thin-layer cell. *Corrosion Science*, 52(3):991 – 995, 2010.
- [12] Comsol. Comsol multiphysics. <http://www.comsol.com/>.
- [13] J.B. Jorcin, C. Blanc, N. Pebere, B. Tribollet, and V. Vivier. Galvanic coupling between pure copper and pure aluminum. *Journal of the Electrochemical Society*, 155(1):C46–C51, 2008.
- [14] S. Aoki and K. Kishimoto. Prediction of galvanic corrosion rates by the boundary element method. *Mathematical and Computer Modelling*, 15(35):11 – 22, 1991.
- [15] N. Okada, M. Matsumoto, K. Nishihara, M. Kimoto, T. Kudo, and S. Fujimoto. Numerical analysis model of galvanic corrosion with ion movement and reactions. *ISIJ International*, 50(5):743–751, 2010.
- [16] J. Warkus, M. Raupach, and J. Gulikers. Numerical modelling of corrosion theoretical backgrounds. *Materials and Corrosion*, 57(8):614–617, 2006.
- [17] C. Wagner. Theoretical analysis of the current density distribution in electrolytic cells. *Journal of the Electrochemical Society*, 98:116–128, 1951.
- [18] R.G. Kelly. *Electrochemical Techniques in Corrosion Science and Engineering*. Corrosion Technology. Marcel Dekker, 2003.
- [19] H.P. Hack and ASTM Committee G-1 on Corrosion of Metals. *Galvanic Corrosion*. Number 978 in ASTM Special Technical Publication. ASTM, 1988.
- [20] K.B. Deshpande. Experimental investigation of galvanic corrosion: Comparison between svet and immersion techniques. *Corrosion Science*, 52(9):2819 – 2826, 2010.
- [21] The University of Akron. Corrosion Squad. <http://www.uakron.edu>.
- [22] Elsyca. Galvanicmaster. <http://www.elsyca.com/>, 2012.
- [23] Matlab. Mathworks. <https://www.mathworks.com/>.

APPENDICES

APPENDIX A

ONE-DIMENSIONAL NUMERICAL CODE

```

1  % Cartesian Numerical Procedure
2  % Galvanic Couple #1: Mild Steel and Magnesium
3  % Galvanic Couple #2: Copper and Aluminum
4
5  $ Governing Equation and conditions:
6  %  $\kappa \cdot [(w+H) \cdot E_x]_x = +ia(E)$  or  $-ic(E)$  domain (0,F)U(F,L)
7
8  % BC: x=0, centerline of anode,  $E_x = 0$ 
9  %      x=F, continuity of E and  $E_x$ 
10 %      x=L,  $E_x = 0$  (insulated boundary at edge of cathode)
11
12 % dimensional model: lengths in cm, current in A, potential in V
13 %-----
14 function Cartesian
15 clear all
16
17 z1 = cputime;
18
19 Faraday = 96485.3365; % Faraday's constant (C/mol)
20
21 % Specify Geometry and Materials
22 icafe = 1;
23 if (icafe==1)
24     cflag = 'a';
25     w = .1; % Gap Width (cm)
26     kappa = .0105; % Conductivity of .1M of NaCl (amp/volt*cm)
27     F = 10; % Length of Aluminum (cm)
28     L = 20; % Length of Copper (cm)
29     xinit = [0 2 4 6 8 10 10 12 14 16 18 20]; % interval initial guess
30     yinit = [-.55;0]; % potential and current initial guess
31     % Aluminum Material Properties - Cmetal
32     Cmetal = 2.8/26.98; % Density (gr/cm3) over Molecular Weight (gr/mole)
33 elseif (icafe==2)
34     cflag = 'c';
35     w = .01;
36     kappa = .0271; Conductivity of 1.6% NaCl (amp/volt*cm)

```

```

37     F = 2; % Length of Magnesium
38     L = 4; % Length of Mild Steel
39     xinit = [0 .5 1 1.5 2 2 2.5 3 3.5 4];
40     yinit = [-1.35; 0];
41     % Magnesium Material Properties - Cmetal
42     Cmetal = 1.820/26.82; % Density (gr/cm^3) over Molecular Weight (gr/mole)
43 end
44
45 dx = 1e-3; % x grid spacing
46 x1 = 0:dx:F; N1 = length(x1); % Length of left material
47 x2 = F:dx:L; N2 = length(x2); % Length of right material
48 xtot = [x1(1:N1-1) x2];
49 xplot=0:dx:L;
50
51 dt = 2000; % Length of time spacing
52 nmax = 86400/dt+1; % 24 hours is 86400
53 np = 2; % print output every 2 iterations
54
55 %-----
56 % damage at time t=0
57 Hvec = zeros(1,length(xtot));
58 Hpvec = zeros(1,length(xtot));
59
60 % Specify size of polarization curve
61 EE = -2.0:.001:0.5;
62 for i=1:length(EE)
63     sa(i) = ia(EE(i));
64     sc(i) = ic(EE(i));
65 end
66
67 % Plot polarization curve (Potential vs. Current Density)
68 figure(1)
69 plot(sa,EE,sc,EE)
70 xlabel('current density')
71 ylabel('potential')
72 legend('anodic','cathodic')
73 title('Polarization Curves - Cartesian')
74
75 % Plot polarization curve (Potential vs. Log Current Density)
76 figure(2)
77 semilogx(sa,EE,sc,EE)
78 xlabel('current density')
79 ylabel('potential')
80 legend('anodic','cathodic')
81 title('Polarization Curves - Semilog')
82

```

```

83 % find initial potential
84 options = bvpset('RelTol',1e-12);
85 solint = bvpinit(xinit,yinit); %initial guess
86 y1 = bvp4c(@bvpode,@bvpbc,solint,options); %runs BVP
87 Yint = deval(y1,xplot); %BVP output
88 E = Yint(1,:); %Selects only E from the output
89 Ex = Yint(2,:); %Selects only Ex from the output
90
91 % Creating Output filenames for each case's parameters
92 filename1 = [ 'parameters.' cflag ];
93 fid1 = fopen(filename1,'w');
94 fprintf(fid1,'%f dx\n',dx);
95 fprintf(fid1,'%d nmax\n',nmax);
96 fprintf(fid1,'%d np\n',np);
97 fprintf(fid1,'%f dt\n',dt);
98 fprintf(fid1,'%f w\n',w);
99 fprintf(fid1,'%f k\n',kappa);
100 fprintf(fid1,'%d F\n',F);
101 fprintf(fid1,'%d L\n',L);
102 fprintf(fid1,'%d Cmetal\n',Cmetal);
103 fclose(fid1);
104
105 % Create file for the initial potential using cflag
106 filename1 = [ 'pot' cflag '000' ];
107 fid1 = fopen(filename1,'w');
108 for i=1:length(xplot)
109     fprintf(fid1,'%e %e\n',xplot(i),E(i));
110 end
111 fclose(fid1);
112
113 % Plot potential on figure 3 and current on figure 4
114 figure(3)
115 plot(xplot,E)
116 title('Potential')
117 hold on
118 figure(4)
119 plot(xplot,Ex)
120 title('Current')
121 hold on
122
123 % Plot current density in figure 5, s is a dummy variable
124 figure(5)
125 for i=1:length(xplot)
126     if (xplot(i)<F)
127         s(i) = ia(E(i));
128     else

```



```

129         s(i) = -ic(E(i));
130     end
131 end
132 plot(xplot,s)
133 title('Current Density')
134 hold on
135
136 %-----
137 for n=1:nmax-1
138     % update H and Hx
139     % Damage Evolution for H using Eulers Method
140     % Print the maximum value of H along with time step n
141     % Below is Damage discretization for Magnesium
142     for i=1:N1
143         Hvec(i) = Hvec(i) + dt*ia(E(i))/(2*Faraday*Cmetal);
144     end
145     % Below is Damage discretization for Aluminum
146     for i=1:N1
147         Hvec(i) = Hvec(i) + dt*ia(E(i))/(3*Faraday*Cmetal);
148     end
149     fprintf('%d %e max H\n',n,max(Hvec))
150
151     % Build Hz using 341 on boundaries and CD inside
152     Hpvec(1) = (-3*Hvec(1)+4*Hvec(2)-Hvec(3))/(2*dx);
153     for i=2:N1-1
154         Hpvec(i) = (Hvec(i+1)-Hvec(i-1))/(2*dx);
155     end
156     i = N1;
157     Hpvec(i) = (3*Hvec(i)-4*Hvec(i-1)+Hvec(i-2))/(2*dx);
158
159     % update potential
160     options = bvpset('RelTol',1e-12);
161     solint = bvpinit(xinit,yinit);
162     y1 = bvp4c(@bvpode,@bvpbc,solint,options);
163     Yint = deval(y1,xplot);
164     E = Yint(1,:);
165     Ex = Yint(2,:);
166
167     % output filenames and then plot
168     if (mod(n,np)==0)
169         rr = num2str(n/np);
170         if (length(rr)==1)
171             rr = ['00' rr];
172         end
173         if (length(rr)==2)
174             rr = ['0' rr];

```

```

175     end
176     filename1 = [ 'pot' cflag rr ];
177     filename2 = [ 'dam' cflag rr ];
178     filename3 = [ 'cur' cflag rr ];
179     filename4 = [ 'cde' cflag rr ];
180     fid1 = fopen(filename1,'w');
181     fid2 = fopen(filename2,'w');
182     fid3 = fopen(filename3,'w');
183     fid4 = fopen(filename4,'w');
184     for i=1:length(xplot)
185         fprintf(fid1,'%e %e\n',xplot(i),E(i));
186     end
187     for i=1:N1
188         fprintf(fid2,'%e %e\n',x1(i),-Hvec(i));
189     end
190     for i=1:N2
191         fprintf(fid2,'%e %e\n',x2(i),0);
192     end
193     for i=1:length(xplot)
194         fprintf(fid3,'%e %e\n',xplot(i),Ex(i));
195     end
196     for i=1:length(xplot)
197         fprintf(fid4,'%e %e\n',xplot(i),s(i));
198     end
199     fclose(fid1);
200     fclose(fid2);
201     fclose(fid3);
202     fclose(fid4);
203
204     figure(3)
205     title('Potential through 50 hours')
206     xlabel('cm')
207     ylabel('V')
208     hold on
209     plot(xplot,E)
210
211     figure(4)
212     title('Current') %xlabel('cm'),ylabel('cm')
213     hold on
214     plot(xplot,Ex)
215
216     for i=1:length(xplot)
217         if (xplot(i)<F)
218             s(i) = ia(E(i));
219         else
220             s(i) = -ic(E(i));

```

```

221         end
222     end
223     figure(5)
224     hold on
225     plot(xplot,s)
226     title('Current Density')
227
228     figure(6)
229     plot(xplot,-Hvec),title('Damage')
230     xlabel('cm')
231     ylabel('cm')
232     hold on
233     drawnow
234 end
235
236 end
237 z2 = cputime;
238 fprintf('CPU time: %f minutes\n',(z2-z1)/60)
239
240 %-----
241 function y = bvpguess(x)
242     HH = interp1q(xtot',Hvec',x);
243     HHp = interp1q(xtot',Hpvec',x);
244     y = [HH; HHp];
245 end
246
247 % BC's l - Left Endpoint, r - Right Endpoint
248 % (1) - function value, (2) - fn derivative value
249 % set = 0 on Left and Right - Insulated
250 % must set equal to each other at interface - Continuity
251 function r = bvpbc(yl,yr)
252     r = [ yl(2,1)-0
253           yr(1,1)-yl(1,2)
254           yr(2,1)-yl(2,2)
255           yr(2,end)-0];
256 end
257 %-----
258 % Differential Equations
259 % interpolate H and Hz so can evaluate at any point
260 % Region 1 - Left Anode, Region 2 - Right Cathode
261 function dzdx = bvpode(x,z,region)
262     dzdx = zeros(2,1);
263     dzdx(1) = z(2);
264     HH = interp1q(xtot',Hvec',x);
265     HHp = interp1q(xtot',Hpvec',x);
266     switch region

```

```

267         case 1
268             dzdx(2) = (ia(z(1))-HHp*kappa*z(2))/(kappa*(w+HH));
269         case 2
270             dzdx(2) = (-ic(z(1))-HHp*kappa*z(2))/(kappa*(w+HH));
271     end
272 end
273 %-----
274 % Polarization Curves for each system
275 % Anode Curves
276 function r = ia(E)
277 % Aluminum Curve
278     if (E>-.8)
279         r = -9 + ((E+.8)^(1/3))/0.1465;
280     else
281         r = -9 + ((-(E+.8))^(0.5))/0.15;
282     end
283     r = 10^r;
284 % Magnesium Curve
285     if (E>-1.55)
286         r = (E+1.55)^(1/3)/0.1982 - 5;
287     else
288         r = -5 - (3/0.45)*(E+1.55);
289     end
290     r = 10^r;
291 end
292
293 % Cathode Curves
294 function r = ic(E)
295 % Copper Curve
296     if (E<-0.1)
297         r = -4.5 + ((-(E+.8))^3)/0.07622;
298     else
299         r = -9 + (4/0.2)*(E+.1);
300     end
301     r = 10^r;
302 % Mild Steel Curve
303     if (E<-0.6)
304         r = -6 - 3.95/0.75*(E+.6);
305     else
306         r = -6 + 5/0.25*(E+.6);
307     end
308     r = 10^r;
309 end
310 %-----
311 end

```

APPENDIX B

OTHER CONFIGURATIONS AND EQUATIONS

Three additional configurations and their derived potential equations are proposed. The first geometry, shown in Figure B.1, is a cylindrical pipe/wire model with the electrolyte radially surrounding the exterior.

Figure B.1: Exterior pipe configuration.

The damage equation remains the same as previously defined by 2.44. The potential equation for the configuration in Figure B.1 is

$$E_z H_z + E_{zz} \alpha R = \frac{i(E)}{\kappa}, \quad (\text{B.1})$$

where $\alpha = \left(\frac{2RH - H^2 + 2Rw + w^2}{2R(R - H)} \right)$ and R is the radius of the pipe. For this system the thin film assumption and Wagner relationship must both be satisfied, but an additional constraint that $R \ll L$ must also be satisfied.

The second geometry, shown in Figure B.2, is a similar cylindrical pipe model with the electrolyte on the interior.

Figure B.2: Interior pipe configuration.

The potential equation for the interior pipe is

$$\frac{E_{zz}(w + H)}{2} + E_z H_z = \frac{i(E)}{\kappa}. \quad (\text{B.2})$$

The same thin film and Wagner constraints are required for this configuration. Combining the interior and exterior pipe configurations and running their simulations simultaneously, a complete pipe damage evolution model can be built. A study could also be completed analyzing the effects of insulating portions of the pipe, both internally and externally.

The third geometry, shown in Figure B.3, is a base fastener cylindrical model, as proposed in this thesis, except for a non-uniform electrolyte thickness. The potential equation for this cylindrical geometry is

$$\frac{1}{r} [(r E_r)(w + H - f)]_r = \frac{i(E)}{\kappa}. \quad (\text{B.3})$$

Figure B.3: Interior pipe configuration.

It is clear that to implement the same solution procedure the thickness of the electrolyte $w(r) = w - f(r)$ must be greater than zero. This implies that the height of the bolt-head must be smaller than the thickness in the electrolyte. The entire system must be covered by electrolyte. Non-atmospheric and bulk electrolyte configurations are optimal scenarios for the model shown in Figure B.3.