INFORMATION TO USERS

This was produced from a copy of a document sent to us for microfilming. While the most advanced technological means to photograph and reproduce this document have been used, the quality is heavily dependent upon the quality of the material submitted.

The following explanation of techniques is provided to help you understand markings or notations which may appear on this reproduction.

1. The sign or "target" for pages apparently lacking from the document photographed is "Missing Page(s)". If it was possible to obtain the missing page(s) or section, they are spliced into the film along with adjacent pages. This may have necessitated cutting through an image and duplicating adjacent pages to assure you of complete continuity.
2. When an image on the film is obliterated with a round black mark it is an indication that the film inspector noticed either blurred copy because of movement during exposure, or duplicate copy. Unless we meant to delete copyrighted materials that should not have been filmed, you will find a good image of the page in the adjacent frame.
3. When a map, drawing or chart, etc., is part of the material being photographed the photographer has followed a definite method in "sectioning" the material. It is customary to begin filming at the upper left hand corner of a large sheet and to continue from left to right in equal sections with small overlaps. If necessary, sectioning is continued again—beginning below the first row and continuing on until complete.
4. For any illustrations that cannot be reproduced satisfactorily by xerography, photographic prints can be purchased at additional cost and tipped into your xerographic copy. Requests can be made to our Dissertations Customer Services Department.
5. Some pages in any document may have indistinct print. In all cases we have filmed the best available copy.

University
Microfilms
International

300 N. ZEEB ROAD, ANN ARBOR, MI 48106
18 BEDFORD ROW, LONDON WC1R 4EJ, ENGLAND

8022323

PARKER, ALAN ANDREW

DOMAIN WALL RESONANCE IN MAGNETIC BUBBLE FILMS

The Ohio State University

PH.D.

1980

University
Microfilms
International

300 N. Zeeb Road, Ann Arbor, MI 48106

18 Bedford Row, London WC1R 4EJ, England

PLEASE NOTE:

In all cases this material has been filmed in the best possible way from the available copy. Problems encountered with this document have been identified here with a check mark ✓.

1. Glossy photographs _____
2. Colored illustrations _____
3. Photographs with dark background ✓ _____
4. Illustrations are poor copy _____
5. Print shows through as there is text on both sides of page _____
6. Indistinct, broken or small print on several pages _____ throughout

7. Tightly bound copy with print lost in spine _____
8. Computer printout pages with indistinct print _____
9. Page(s) _____ lacking when material received, and not available
from school or author _____
10. Page(s) _____ seem to be missing in numbering only as text
follows _____
11. Poor carbon copy _____
12. Not original copy, several pages with blurred type _____
13. Appendix pages are poor copy _____
14. Original copy with light type _____
15. Curling and wrinkled pages _____
16. Other _____

DOMAIN WALL RESONANCE
IN MAGNETIC BUBBLE FILMS

DISSERTATION

Presented in Partial Fulfillment of the Requirements for
the Degree Doctor of Philosophy in the Graduate
School of The Ohio State University

By

Alan A. Parker, B.S., M.S.

* * * * *

The Ohio State University

1980

Reading Committee:

Prof. Philip Wigen

Prof. J. Morkowski

Prof. David Stroud

Prof. James Tough

Approved By

Adviser
Department of Physics

ACKNOWLEDGMENTS

I would like to thank my advisor, Professor Philip Wigen, for his encouragement and support during my stay at The Ohio State University. I would also like to thank Dr. Horst Dötsch of Philips Laboratories for supplying the sample used in this study and for supplying an RF structure when we were having difficulty constructing one here at Ohio State. The assistance of Mr. Chuck Rush and the staff of the Physics Department Electronics Shop in constructing equipment and providing freely of their time to solve problems with the spectrometer was invaluable. Finally, I would like to thank my wife, Mary Ann. Her knowledge of mathematics and computer programming were very important in this work, as was her assistance in getting the experiment going and in taking the data. Her encouragement and moral support were vital; without her, this work could not have been completed.

VITA

July 16, 1951 Born - Fort Wayne, Indiana
1973 B.S., Michigan State University,
East Lansing, Michigan
1973-1976 Graduate Teaching Associate,
Department of Physics, The Ohio
State University, Columbus, Ohio
1976 M.S., The Ohio State University,
Columbus, Ohio
1977-1980 Graduate Research Associate,
Department of Physics, The Ohio
State University, Columbus, Ohio

PUBLICATIONS

"Low Field Microwave Excitations of Magnetic Domain Walls",
P.S. Limaye, A.A. Parker, D.G. Stroud, and P.E. Wigen, J.
Appl. Phys. 50, 2027 (1979).

"Measurement of the Damping Parameter from Low Field
Microwave Excitations of Domain Walls", P.S. Limaye,
A.A. Parker, and P.E. Wigen, IEEE Trans. On Mag., MAG15,
1726 (1979).

TABLE OF CONTENTS

	<u>Page</u>
ACKNOWLEDGMENTS	ii
VITA	iii
LIST OF TABLES	vi
LIST OF FIGURES	vii
 <u>CHAPTER</u>	
I. INTRODUCTION	1
II. THEORY OF DOMAIN WALL MOTION	9
1. Introduction	9
2. Basic Theory	9
3. Calculation of the Restoring Force Constant	29
4. Effect of Surface Charges on the Wall Mass	36
5. Domain Wall Mass With a Large In- Plane Field	47
6. The Theory of O'Dell	52
7. Morkowski's Solution for the Wall Mass .	56
III. EXPERIMENTAL	64
IV. EXPERIMENTAL RESULTS AND ANALYSIS OF DATA .	78
1. H_p Applied Parallel to the Domain Walls	82
2. Angular Dependence	94
V. CONCLUSIONS	107
LIST OF REFERENCES	110

TABLE OF CONTENTS (Continued)

	<u>Page</u>
APPENDIX A. CALCULATION OF THE DEMAGNETIZATION ENERGY IN THE STATIC CASE	113
APPENDIX B. CALCULATION OF THE STATIC WALL ENERGY WITH AN IN-PLANE FIELD APPLIED ALONG THE PLANE OF THE WALL	116
APPENDIX C. PROGRAM FOR CALCULATING $L_1 + L_2$ AND E_{xx} .	120
APPENDIX D. PROGRAM TO CALCULATE DOMAIN WALL STRUCTURE	123
APPENDIX E. SYSTEM PROGRAM	127

LIST OF TABLES

	<u>Page</u>
<u>TABLE</u>	
1 MATERIAL PARAMETERS FOR THE SAMPLE USED . . .	77
2 LEAST SQUARES FIT PARAMETERS FOR FITTING $\frac{1}{m}$ TO $a_0 + a_1 \cos 2\xi$	106
3 LEAST SQUARES FIT OF a_0 AND a_1 TO $b + c H_p$. .	106

LIST OF FIGURES

<u>FIGURE</u>	<u>Page</u>
1.1 An array of stripe domains. The arrows indicate the direction of the magnetization in each domain	2
1.2 Bubble domains. The arrows indicate the direction of the magnetization in each domain	3
2.2.1 Coordinate system used to derive the equations of motion for a domain wall. $\vec{m}$ points along the direction of the magnetization $\vec{M}$	11
2.2.2 Solution of equation 2.2.17 for the domain wall profile. Note that the magnetization can rotate in two opposite directions, giving rise to two separate solutions	16
2.3.1 An array of parallel strip domains. The arrows at the edge indicate the direction of magnetization. $L_1 + L_2$ is the stripe period and t is the film thickness	31
2.4.1 Wall structure vs. position across the film thickness for zero in-plane field. Wall velocity is $.05 V_W$	43
2.4.2 Wall structure vs. position across the film thickness for $H_p = .1 H_u \approx 8M$. Wall velocity is $.05 V_W$	44
2.4.3 Wall mass vs. velocity for zero in-plane field. Wall mass is obtained by calculating the wall structure and averaging ψ , as described in the text. The sharp increase in the mass at $V/V_W = .3$ is due to the nucleation of a horizontal Bloch line	45
2.4.4 Wall mass vs. in-plane field. The solid curve is the mass obtained by taking the wall structure into account. The dashed curve is the Bloch wall mass obtained in section 2.2	46

<u>FIGURE</u>	<u>Page</u>
2.5.1 Inverse wall mass vs. in-plane field. The solid curve is the model of Wigen and Dötsch. The dashed curve is the Bloch wall model	51
2.6.1 Inverse wall mass vs. in-plane field. The solid curve is the model of O'Dell. The Dashed curve is the Bloch wall model	55
2.7.1 Inverse wall mass vs. in-plane field. The solid curve is Morkowski's expression. The dashed curve is the Bloch wall mass	63
3.1 Layout of the RF structure. The light areas are gold. In the dark areas, the gold has been etched away, forming a short circuited slot line on the right side and a short circuited coaxial transmission line on the left side	65
3.2 RF fields in the slot line. The E field runs from one side of the slot to the other, the H field is normal to the plane of the structure	67
3.3 RF fields in the coaxial line. The E field runs from the center conductor to the outer (ground plane) conductors. The H field runs around the center conductor and out of the insulating gaps normal to the plane of the structure	68
3.4 RF currents around the short circuited ends of the slot line and the coaxial line	69
3.5 The RF structure with a sample in place	70
3.6 System block diagram	71
4.1 Domain wall resonance signal for $H_p = 80$ Oe. The signal is superimposed on a baseline which is due to standing waves in the spectrometer cables	79
4.2 Domain wall resonance signal for $H_p = 80$ Oe. Here, the baseline has been subtracted, leaving only the wall resonance signal	80

<u>FIGURE</u>		<u>Page</u>
4.3	Domain wall resonance signal for $H_p = 10$ Oe. The center frequency of the signal is 12.86 MHz	81
4.4	Domain wall resonance signal for $H_p = 210$ Oe. The narrow resonances superimposed on the main resonance are magnetoelastic modes	83
4.5	Domain wall resonance frequency vs. in-plane field. The crosses indicate increasing H_p the circles indicate decreasing H_p	84
4.6	$L_1 + L_2$ vs. H_p . The solid curve is for H_p increasing, the dashed curve is for H_p decreasing	85
4.7	Reduced resonance frequency vs. reduced in-plane field	87
4.8	Reduced resonance frequency vs. reduced in-plane field. The solid curve is the theoretical prediction for the Bloch wall model of the effective mass	88
4.9	Reduced resonance frequency vs. reduced in- plane field. The solid curve is the theore- tical prediction for a Bloch wall which takes the effects of surface changes on the wall structure into account	89
4.10	Reduced resonance frequency vs. reduced in- plane field. The solid curve is the theore- tical prediction based on the model of Wigen and Dötsch, as discussed in section 2.5	91
4.11	Reduced resonance frequency vs. reduced in- plane field. The solid curve is the theore- tical prediction of O'Dell's model	92
4.12	Reduced resonance frequency vs. reduced in- plane field. The solid curve is the theore- tical prediction based on O'Dell's model, modified by setting the zero field mass to $2m_D$, as discussed in the text	93
4.13	Reduced resonance frequency vs. reduced in- plane field. The solid curve is the theore- tical prediction based on Morkowski's expression for the wall mass	95

<u>FIGURE</u>	<u>Page</u>
4.14 Reduced resonance frequency vs. reduced in-plane field. The solid curve is the theoretical prediction based on Morkowski's model of the wall mass modified by doubling the zero field mass, as discussed in the text. .	96
4.15 Effective wall mass vs. reduced in-plane field. The solid curve is Morkowski's expression for the wall mass modified to take the effects of surface changes into account	97
4.16 $1/m$ vs. ξ the angle between H_p and the plane of the wall, for $H_p = 30$ Oe. The solid curve is the least squares fit of a Legendre polynomial in $\cos 2\xi$ to the data	100
4.17 $1/m$ vs. ξ for $H_p = 60$ Oe. The solid curve is the least squares fit of a Legendre polynomial in $\cos 2\xi$ to the data	101
4.18 a_0 vs. H_p . The solid line is a least squares fit through the first 4 points	102
4.19 a_1 vs. H_p . The solid line is a least squares fit to the data.	103
4.20 Reduced effective mass vs. in-plane field . . .	104

CHAPTER 1

INTRODUCTION

An unmagnetized sample of ferromagnetic material is divided into domains--regions (usually very small in size) where the material is completely magnetized. The orientations of the magnetization of the domains is usually random and thus the total magnetization of a sample of macroscopic size is zero. Kooy and Enz¹ reported the observation by means of the Faraday effect of the domain patterns in thin platelets of barium hexaferrite. This material has a strong uniaxial anisotropy normal to the plane of the platelet, and thus the magnetization of the domains is constrained to lie in the two directions parallel to the easy axis of the anisotropy. They reported the existence of two major types of domain configurations: long, usually serpentine, domains now called stripe domains and cylindrical domains, which have since come to be called bubble domains. These two types of domain configurations are illustrated in Figures 1 and 2, respectively. Bobeck² suggested that bubble domains could be used as the

Figure 1.1. An array of stripe domains. The arrows indicate the direction of the magnetization in each domain.

Figure 1.2. Bubble domains. The arrows indicate the direction of the magnetization in each domain.

primitive elements in a memory device and there now exists a relatively large and growing branch of the semiconductor industry devoted to the development and production of magnetic bubble memories. For an introductory discussion of the construction, operation and advantages of bubble memories, see reference 3. References 4 and 5 provide a more complete discussion of the details of operation of bubble devices and of the magnetic properties required to construct practical bubble devices.

Because of the interest in bubble technology, there has been a great deal of work both experimental and theoretical done on domain dynamics and domain wall dynamics in bubble type materials, which are usually thin films of rare earth iron garnet grown epitaxially on non-magnetic garnet substrates. Most such work has been concerned with domain wall mobility, how the wall velocity depends on drive field, and comparatively little interest has existed in the investigation of inertial effects.

Döring⁶ showed that a moving domain wall has an energy which is larger than that of a wall at rest. This additional energy is proportional to the square of the wall velocity and thus can be considered to be a kinetic energy, and the proportionality coefficient associated

with the $\frac{v^2}{2}$ term can be taken to be the effective mass of the domain wall. For a Bloch wall, the Döring mass is given by

$$m_D = (2\pi\gamma^2\Delta)^{-1} \quad (1.1)$$

where γ is the gyromagnetic ratio for the material and Δ is the wall width parameter.

Döring predicted that the existence of a restoring force acting on domain walls would imply the possibility of exciting domain wall resonance with an AC magnetic field of suitable frequency. Such an effect was subsequently observed in Mn Mg ferrite,⁷ barium hexaferrite,⁸ and cobalt ferrite.⁹ In garnets, wall resonance has been observed by Vella-Coleiro, et.al.¹⁰

When a magnetic field is applied in the plane of the film, the wall mass is expected to decrease. The effective mass as a function of in-plane magnetic field, H_p , is given by¹⁴

$$m_{eff} = m_D(1 + H_p/8M)^{-1} \quad (1.2)$$

where M is the saturation magnetization of the material.

When the in-plane field, H_p , reaches the uniaxial anisotropy field, H_u , the film will be saturated in the plane of the film and no domains will be present. Since

the wall can be considered to be a simple harmonic oscillator, the resonance frequency will be given by

$$\omega = \sqrt{k/m} = \sqrt{\frac{k}{m_D} (1 + H_p/8M)} \quad (1.3)$$

where k is the restoring force constant. For stripe domains the restoring force is due to a field gradient, produced either by the adjacent stripe domains or by an applied external field. In an array of stripe domains the restoring force depends on the in-plane magnetic field but for small fields can be assumed to be constant.

Several techniques have been used to study the resonance frequency and thus the effective mass of domain walls in magnetic bubble type films. In most cases, the Faraday effect is used to observe the domain walls and the wall position is monitored electronically using a photomultiplier as the walls are excited by either a step change in the bias field^{11,12} or by sinusoidal¹¹ oscillations in the bias field. In some cases, time delay photography is used to record the actual details of the wall motion by repetitively pulsing the bias field and varying the time delay between the pulse and a laser pulse used to illuminate the domain wall exposing one frame with each light pulse.¹³

Argyle and Malozemoff¹⁴ observed wall oscillations using both pulsed and sinusoidal excitation. Their results were obtained with an in-plane field very small compared to the uniaxial anisotropy field, H_u . Reasonable (50 percent) agreement with equation 1.2 was reported. Shaw, Moody and Sandfort¹⁵ studied the response of domain walls to a step change in the bias field for H_p/H_u up to approximately .3. They reported that the zero field wall mass was on the order of 2 to 3 times the Döring mass and that the field dependence of the mass was stronger than predicted by equation 1.2. Their results indicated that the coefficient of H_p in equation 2 should be on the order of $\frac{1}{2M}$ rather than $\frac{1}{8M}$. de Leeuw and Robertson¹⁶ observed oscillations of a single wall in response to a pulse in the bias field. For in-plane fields up to approximately .12 H_u , they reported good agreement with equation 2. MacNeal and Humphrey,¹⁷ using the time delay photography technique, observed the response of domain walls to a pulse in the bias field. For H_p/H_u up to approximately .14, they report good agreement with equation 2, although in some cases, they had large uncertainties in their determination of the wall resonance frequency. Wigen and Dötsch, using a non-optical technique,¹⁸ measured the resonance frequency of domain walls excited by a sinusoidally varying bias field

for H_p/H_u up to approximately .75.¹⁹ They observed that the mass dependence given by equation 2 is in serious disagreement with their results, especially for large H_p . The resonance frequency was observed to rise nearly linearly with H_p , rather than as $H_p^{1/2}$ as predicted by equation 3. That this effect has not been observed previously is not surprising considering the relatively small values of H_p that had been used in previous work.

This dissertation extends the work of Wigen and Dötsch by taking additional data for large and small in-plane fields and by measuring the resonance frequency and thus the effective wall mass as a function of angle between the applied in-plane field and the domain wall. Various models for the wall mass which attempt to account for the effect of large in-plane fields on the mass will be examined and compared with the experimental data.

CHAPTER 2

THEORY OF DOMAIN WALL MOTION

Section 2.1 - Introduction

The dynamics of magnetic domain walls have been studied extensively. This chapter will present a derivation based on the Landau-Lifshitz equations of the equation of motion of a domain wall in a thin magnetic film which experiences a restoring force due to the presence of a periodic array of domains in the film. A method of calculating the magnitude of the force constant will be given. Several models for the wall mass for large in plane fields will then be examined and comparisons made between them. These models will then be evaluated by comparing them with experimental data in a later chapter.

Section 2.2 - Basic Theory

This section will derive the equations of motion for a domain wall in a thin magnetic garnet film, following closely the work of Slonczewski.¹

This development has the restriction that it applies only to a 180° Block wall. The effect of an applied in plane magnetic field on the static spin configuration is ignored, even though in actuality an applied in plane field changes the static spin configuration. This effect will be addressed in later sections of this chapter.

The fundamental equation of motion for the magnetization in a magnetic medium is the Landau-Lifshitz² equation. In this development, a damping term of the Gilbert form³ is included. If the magnetization $\vec{M}$ is assumed to be of constant magnitude and along the direction of unit vector $\vec{m}$, then the LLG (Landau-Lifshitz-Gilbert) equation is

$$\dot{\vec{m}} = - \left(\frac{\gamma}{M} \right) \vec{T} + \alpha (\vec{m} \times \dot{\vec{m}}) \quad (2.2.1)$$

where the dot denotes differentiation with respect to time, γ is the gyromagnetic ratio, $\vec{T}$ is the torque, derived from the potential energy W , and α is the Gilbert damping parameter.

The coordinate system to be used is illustrated in Figure 2.2.1. The torque $\vec{T}$ is given by

$$\vec{T} = - \vec{m} \times \nabla W \quad (2.2.2)$$

Figure 2.2.1. Coordinate system used to derive the equations of motion for a domain wall. $\vec{m}$ points along the direction of the magnetization $\vec{M}$.

so in this coordinate system, the polar components of the torque are

$$\begin{aligned} T_{\theta} &= \frac{1}{\sin\theta} \frac{\delta W}{\delta \psi} \\ T_{\phi} &= - \frac{\delta W}{\delta \theta} \end{aligned} \quad (2.2.3)$$

where W is the volume energy density and the functional derivative $\frac{\delta W}{\delta \theta}$ is defined by

$$\frac{\delta W}{\delta \theta} = \frac{\partial W}{\partial \theta} - \nabla \cdot \frac{\partial W}{\partial \nabla \theta} \quad (2.2.4)$$

Writing equation (1) in polar form and making use of equation (3) gives

$$\begin{aligned} \dot{\theta} &= - \frac{\gamma}{M \sin\theta} \frac{\delta W}{\delta \psi} - \alpha \dot{\psi} \sin\theta \\ \dot{\psi} \sin\theta &= \frac{\gamma}{M} \frac{\delta W}{\delta \theta} + \alpha \dot{\theta} \end{aligned} \quad (2.2.5)$$

The energy density W can be considered to be composed of two terms--a short-range term and a long-range term. The short-range term is given by

$$W_S = A(\nabla m)^2 + K \sin^2\theta \quad (2.2.6)$$

here the first term is due to exchange and the second term is due to the uniaxial anisotropy. All other anisotropies (i.e. crystal anisotropy) are ignored. This term is only important near the domain wall.

The long-range term consists of all components of the energy density which are significant far away from as well as near to the wall. These are due to the effects of the applied magnetic and the demagnetization field. This is given by⁴

$$W = \frac{1}{2} \int_V \rho_m \phi dV \quad (2.2.7)$$

where W is the total magnetic energy, ρ_m is the magnetic pole density given by $\rho_m = -\nabla \cdot \vec{M}$ and ϕ is the magnetic potential given by

$$\phi = \int_V \frac{\rho_m}{4\pi\mu_0 r} dV \quad (2.2.8)$$

Note that the integrand in equation (8) is singular at $r=0$. For this reason, it is more convenient to consider the variation in the energy density directly which is given by

$$\delta W_m = - \vec{H} \cdot \delta \vec{M} \quad (2.2.9)$$

where $\vec{H}$ consists of the applied field $\vec{H}_a$ and the demagnetization field $\vec{H}_d$.

In order to derive equations of motion of a domain wall, the effects of wall motion on the energy are treated as a perturbation of the energy of a stationary Bloch wall. The variation of the energy is then

$$\delta W = \delta W_0 + \delta W_1 \quad (2.2.10)$$

where δW_0 contains the terms which describe a straight Bloch wall lying in the x-z plane. In this case W_0 is given by

$$W_0 = K \sin^2 \theta + A \left[\left(\frac{\partial \theta}{\partial y} \right)^2 + \left(\frac{\partial \psi}{\partial y} \right)^2 \sin^2 \theta \right] \quad (2.2.11)$$

In the static case, $\dot{\theta} = \dot{\psi} = 0$ and equation (5) reduces to

$$\frac{\gamma}{M \sin \theta} \frac{\delta W_0}{\delta \psi} = 0$$

$$\frac{\gamma}{M} \frac{\partial W_0}{\partial \theta} = 0 \quad (2.2.12)$$

Carrying out the functional derivatives gives from the first part of equation (12)

$$\frac{\partial^2 \psi}{\partial y^2} \sin^2 \theta + \frac{\partial \psi}{\partial y} \frac{\partial \theta}{\partial y} \sin 2\theta = 0 \quad (2.2.13)$$

and from the second part of equation (12)

$$2A\left(\frac{\partial^2 \theta}{\partial y^2}\right) - [K + A\left(\frac{\partial \psi}{\partial y}\right)^2] \sin 2\theta = 0 \quad (2.2.14)$$

The solution to equation (13) is

$$\psi = \psi_0(x, z, t) \quad (2.2.15)$$

and the solution to equation (14) is

$$\theta = \theta_0(y - q(x, z, t)) \quad (2.2.16)$$

where ψ_0 and q are arbitrary functions of x, z and t and

$$\tan \theta_0/2 = e^{(y-q)/\Delta} \quad (2.2.17)$$

where $\Delta = (A/K)^{1/2}$ is the wall width parameter.

A graph of equation (17) is shown in Figure 2.2.2.

Notice that

$$\frac{\partial \theta_0}{\partial y} = \frac{\sin \theta_0}{\Delta} \quad (2.2.18)$$

Figure 2.2.2. Solution of equation 2.2.17 for the domain wall profile. Note that the magnetization can rotate in two opposite directions, giving rise to two separate solutions.

The energy density per unit wall area σ defined as

$$\sigma = \int_{y^-}^{y^+} W dy \quad (2.2.19)$$

where $y_{\pm}$ satisfy the condition $\Delta \ll |y_{\pm}| \ll D$ when D is the width of the domain. Since, according to equation (12) W_0 does not vary with respect to variations in θ or ψ , the variation of the wall energy is

$$\delta\sigma = \int_{-\infty}^{\infty} \delta W_1 dy \quad (2.2.20)$$

The variation of the wall energy, $\delta\sigma$, will be given correctly to first order if the zero order ψ , θ , $\delta\psi$, and $\delta\theta$ are used in evaluating the integral. Also, a variation in θ can be written in terms of q , the wall position, by using equations (17) and (18) to give

$$\delta\theta_0 = - \frac{\partial\theta_0}{\partial y} \delta q = - \frac{\sin\theta_0}{\Delta} \delta q \quad (2.2.21)$$

Using equation (20), the variation of wall energy with respect to ψ is

$$\frac{\delta\sigma}{\delta\psi_0} = \int_{-\infty}^{\infty} \frac{\delta W_1}{\delta\psi_0} dy = \int_0^{\pi} \frac{\delta W_1}{\delta\psi_0} \left(\frac{\partial\theta_0}{\partial y} \right)^{-1} d\theta_0 \quad (2.2.22)$$

Using equations (5), (12), (18) and (21) in equation (22) and integrating gives

$$\frac{\delta \sigma}{\delta \psi_0} = \frac{2M}{\gamma} (\dot{q} - \alpha \Delta \dot{\psi}_0) \quad (2.2.23)$$

Similarly,

$$\frac{\delta \sigma}{\delta q} = \int_{-\infty}^{\infty} \frac{\delta W_1}{\delta \theta_0} \frac{\delta \theta_0}{\delta q} dy = \int_0^{\pi} \frac{\delta W_1}{\delta \theta_0} d\theta_0 \quad (2.2.24)$$

Substituting equations (5), (12) and (21) in equation (24) and integrating gives

$$\frac{\delta \sigma}{\delta q} = - \frac{2M}{\gamma} (\dot{\psi}_0 + \alpha \Delta^{-1} \dot{q}) \quad (2.2.25)$$

Equations (23) and (25) are the equations of motion for a Bloch wall. In the absence of damping, they reduce to

$$\begin{aligned} \dot{q} &= \frac{\gamma}{2M} \frac{\delta \sigma}{\delta \psi_0} \\ - \frac{2M}{\gamma} \dot{\psi}_0 &= + \frac{\delta \sigma}{\delta q} \end{aligned} \quad (2.2.26)$$

These are Hamilton's equations with $P = \frac{2M}{\gamma} \psi_0$ being the momentum canonically conjugate to q .

In order to obtain explicit equations of motion it is necessary to evaluate $\delta\sigma$, the variation in the wall energy. Using equation (20), $\delta\sigma$ can be found from δW_1 . δW_1 can be decomposed into two parts: δW_s , a short-range term due to exchange and uniaxial anisotropy, and δW_m , a long-range term due to magnetostatic effects. Considering the short-range term first

$$\delta W_s = \delta (A(\nabla \vec{m})^2 + K \sin^2 \theta) \quad (2.2.27)$$

since

$$\vec{m} = \sin \theta \cos \psi \hat{x} + \sin \theta \sin \psi \hat{y} + \cos \theta \hat{z} \quad (2.2.28)$$

the gradient term is

$$\begin{aligned} \nabla \vec{m} = & [\cos \theta \cos \psi \nabla \theta - \sin \theta \sin \psi \nabla \psi] \hat{x} + \\ & [\cos \theta \sin \psi \nabla \theta + \sin \theta \cos \psi \nabla \psi] \hat{y} + \\ & [-\sin \theta \nabla \theta] \hat{z} \end{aligned} \quad (2.2.29)$$

and $(\nabla \vec{m})^2$ is

$$\begin{aligned} (\nabla \vec{m})^2 &= (\nabla \vec{m}) \cdot (\nabla \vec{m}) \\ &= \nabla^2 \theta + \sin^2 \theta \nabla^2 \psi \end{aligned}$$

$$\begin{aligned}
&= \left(\frac{\partial \theta}{\partial x}\right)^2 + \left(\frac{\partial \theta}{\partial z}\right)^2 + \sin^2 \theta_0 \left[\left(\frac{\partial \psi}{\partial x}\right)^2 + \left(\frac{\partial \psi}{\partial z}\right)^2\right] \\
&\quad + \left(\frac{\partial \theta}{\partial y}\right)^2 + \sin^2 \theta_0 \left(\frac{\partial \psi}{\partial y}\right)^2 \quad (2.2.30)
\end{aligned}$$

Thus equation (27) becomes

$$\begin{aligned}
\delta W_s &= \delta \left(A (\nabla \theta)^2 + A \sin^2 \theta_0 (\nabla \psi)^2 \right) + \delta \left(A \left(\frac{\delta \theta}{\delta y} \right)^2 \right. \\
&\quad \left. + A \sin^2 \theta_0 \left(\frac{\partial \psi}{\partial y} \right)^2 + K \sin^2 \theta \right) \quad (2.2.31)
\end{aligned}$$

where the gradient is now understood to be along the x and z directions only.

Note that according to equation (11) this is just

$$\delta W_s = \delta \left(A ((\nabla \theta)^2 + \sin^2 \theta_0 (\nabla \psi)^2) \right) + \delta W_0 \quad (2.2.32)$$

If the wall satisfies equations (15) and (16) then

$\delta W_0 = 0$ and

$$\delta W_s = A \delta \left((\nabla \theta)^2 + \sin^2 \theta_0 (\nabla \psi)^2 \right) \quad (2.2.33)$$

The long-range term is given by

$$\delta W_m = - \vec{H} \cdot \delta \vec{M} \quad (2.2.34)$$

Where $\vec{H} = \vec{H}_a + \vec{H}_d$ and $\vec{H}_a$ is the applied magnetic field and $\vec{H}_d$ is the demagnetization field, given by

$$\vec{H}_d = - 4\pi M_y \quad (2.2.35)$$

thus

$$\begin{aligned} - \vec{H}_d \cdot \delta \vec{M} &= 4\pi M_y \delta M_y \\ &= 2\pi \delta (M_y)^2 \\ &= 2\pi M^2 \delta (\sin^2 \theta_0 \sin^2 \psi_0) \end{aligned} \quad (2.2.36)$$

also

$$\begin{aligned} \delta \vec{M} &= M \delta \vec{m} \\ &= M(-\sin \theta \sin \psi \delta \psi \hat{x} + \sin \theta \cos \psi \delta \psi \hat{y} - \sin \theta \delta \theta \hat{z}) \end{aligned} \quad (2.2.37)$$

Using equation (21)

$$\begin{aligned} \vec{H}_a \cdot \delta \vec{M} &= M \sin \theta_0 (H_x \sin \psi - H_y \cos \psi) \delta \psi \\ &\quad - M H_z \Delta^{-1} \sin^2 \theta \delta q \end{aligned} \quad (2.2.38)$$

Using the fact that $(\nabla \theta)^2 = \frac{\sin^2 \theta}{\Delta^2} (\nabla q)^2$ and that since $\delta \psi$ and δq are independent of y , they can be taken

out of the integral, substituting equations (33), (36) and (38) into equation (20) gives

$$\begin{aligned}
 \delta \sigma = & \delta \left[\frac{A}{\Delta^2} (\nabla q)^2 + A (\nabla \psi)^2 + 2\pi M^2 \sin^2 \psi \right] \int_{-\infty}^{\infty} \sin^2 \theta_0 dy \\
 & + M (H_x \sin \psi - H_y \cos \psi) \delta \psi \int_{-\infty}^{\infty} \sin \theta_0 dy \\
 & - \frac{MH_z}{\Delta} \delta q \int_{-\infty}^{\infty} \sin^2 \theta_0 dy
 \end{aligned} \tag{2.2.39}$$

Equation (18) implies that $dy = \frac{\Delta}{\sin \theta} d\theta$, enabling the integrals to be evaluated and giving

$$\begin{aligned}
 \delta \sigma = & \delta \left\{ \frac{2A}{\Delta} (\nabla q)^2 + 2A\Delta (\nabla \psi)^2 + 4\pi M^2 \Delta \sin^2 \psi \right\} + \\
 & \pi M \Delta (H_x \sin \psi - H_y \cos \psi) \delta \psi - 2MH_z \delta q
 \end{aligned} \tag{2.2.40}$$

The derivation thus far has ignored the presence of other domains and in particular ignored the fact that due to the surface charges of other domains, the domain wall experiences a restoring force when it is displaced from its equilibrium position. This restoring force can be included in this model by adding to the wall energy density a term proportional to q^2 , giving

$$\delta \sigma = \delta \left(\frac{2A}{\Delta} (\nabla q)^2 + 2A\Delta (\nabla \psi)^2 + 4\pi M^2 \Delta \sin^2 \psi + \frac{1}{2} k q^2 \right) +$$

$$\pi M \Delta (H_x \sin \psi - H_y \cos \psi) \delta \psi - 2M H_z \delta q \quad (2.2.41)$$

Substituting equation (41) into equation (25) and performing the functional derivative gives

$$\dot{\psi} = \gamma H_z - \gamma 2\pi M \Delta \frac{\partial}{\partial x} (\sin 2\psi) + \frac{2A\gamma}{M\Delta} \nabla^2 q - \frac{\alpha}{\Delta} \dot{q} - \frac{\gamma k}{2M} q$$

$$(2.2.42)$$

Similarly, equation (23) gives

$$\Delta^{-1} \dot{q} = 2\pi \gamma M \sin 2\psi + \frac{\pi \gamma}{2} (H_x \sin \psi - H_y \cos \psi) - \frac{2\gamma A}{M} \nabla^2 \psi + \alpha \dot{\psi}$$

$$(2.2.43)$$

If q and ψ are assumed to be uniform in the x - z plane, then the spacial derivatives in equations (42) and (43) are zero and the equations of motion reduce to

$$\dot{\psi} = \gamma H_z - \frac{\alpha}{\Delta} \dot{q} - \frac{\gamma k}{2M} q \quad (2.2.44)$$

and

$$\Delta^{-1} \dot{q} = 2\pi \gamma M \sin 2\psi + \frac{\pi \gamma}{2} (H_x \sin \psi - H_y \cos \psi) + \alpha \dot{\psi} \quad (2.2.45)$$

If ψ is assumed to consist of a static part ψ_s (due to an applied in-plane magnetic field) and a time dependent part ψ_t which is small, then

$$\begin{aligned}\cos\psi &= \cos\psi_s - \psi_t \sin\psi_s \\ \sin\psi &= \sin\psi_s + \psi_t \cos\psi_s\end{aligned}\tag{2.2.46}$$

and

$$\sin 2\psi = \sin 2\psi_s + 2\psi_t \cos 2\psi_s\tag{2.2.47}$$

Substituting equation (46) and (47) into equation (45) gives

$$\begin{aligned}\Delta^{-1} \ddot{q} &= 2\pi\gamma M(\sin 2\psi_s + 2\psi_t \cos 2\psi_s) + \frac{\pi\gamma}{2}(H_x(\sin\psi_s + \psi_t \cos\psi_s) - \\ &\quad H_y(\cos\psi_s - \psi_t \sin\psi_s)) + \alpha\dot{\psi}\end{aligned}\tag{2.2.48}$$

Noting that $\dot{\psi} = \dot{\psi}_t$, differentiating equations (44) and (48) gives (assuming that H_z can vary in time and that H_x and H_y do not)

$$\ddot{\psi} = \gamma\dot{H}_z - \frac{\alpha}{\Delta} \ddot{q} - \frac{\gamma k}{4M} \dot{q}\tag{2.2.49}$$

and

$$\Delta^{-1} \ddot{q} = 4\pi\gamma M \cos 2\psi_s \dot{\psi} + \frac{\pi\gamma}{2} H_x \cos \psi_s \dot{\psi} + H_y \sin \psi_s \dot{\psi} + \alpha \ddot{\psi} \quad (2.2.50)$$

Here the subscript t has been dropped from all derivatives of ψ as there is no ambiguity. Substituting equation (44) and (49) into equation (50) and collecting terms gives

$$\frac{1+\alpha^2}{\Delta} \ddot{q} + \frac{\alpha\gamma\mu}{\Delta} \dot{q} + \frac{\alpha\gamma k}{2M} \dot{q} + \frac{\gamma^2}{2M} \mu k q = \mu \gamma^2 H_z + \alpha \gamma \dot{H}_z \quad (2.2.51)$$

where

$$\mu = 4\pi M \cos 2\psi_s + \frac{\pi}{2} (H_x \cos \psi_s + H_y \sin \psi_s) \quad (2.2.52)$$

Multiplying through by $\frac{2M}{\gamma^2 \mu}$ gives

$$\frac{(1+\alpha^2) 2M}{\Delta \gamma^2 \mu} \ddot{q} + \alpha \left(\frac{2M}{\gamma \Delta} + \frac{k}{\gamma} \right) \dot{q} + k q = 2M H_z + \frac{2\alpha}{\gamma} \frac{M}{\mu} \dot{H}_z \quad (2.2.53)$$

This is recognized as the equation of a damped, driven simple harmonic oscillator.

The mass in this equation is

$$m^{-1} = \frac{\Delta \gamma^2 \mu}{(1+\alpha^2) 2M}$$

$$= \frac{m_D^{-1}}{1+\alpha} \left(\cos 2\psi_s + \frac{H_x \cos \psi_s + H_y \sin \psi_s}{8M} \right) \quad (2.2.54)$$

where m_D is the Döring mass given by $(2\pi\gamma^2\Delta)^{-1}$.

Noting that $H_x = H_p \cos \xi$ and $H_y = H_p \sin \xi$ where ξ is the angle between the applied in-plane field and the x axis and that $\tan \psi_s = \frac{H_y}{H_x} = \tan \xi$, equation (54) becomes

$$m^{-1} = \frac{m_D^{-1}}{1+\alpha} \left(\cos 2\xi + \frac{H_p}{8M} \right) \quad (H_p > 8M) \quad (2.2.55)$$

For small damping $Q \approx \frac{\omega}{\Delta\omega}$ and $Q = \frac{m\omega}{b}$ where b is the coefficient of the $\dot{q}$ term in equation (53). Thus, the line width of the domain wall resonance is

$$\Delta\omega = \frac{\alpha}{1+\alpha} \left[(4\pi M\gamma + 2\pi\Delta k) \cos 2\xi + \left(\frac{\pi\gamma}{2} + \frac{\pi\gamma\Delta k}{4M} \right) H_p \right] \quad (2.2.56)$$

In order to take into account the effect of an applied in plane field on the wall dynamics, it is first necessary to find the static spin configuration of the wall with an applied in-plane field. This can be done by solving

$$\frac{\delta W}{\delta \psi} = 0$$

$$\frac{\delta W}{\delta \theta} = 0 \quad (2.2.57)$$

with an energy density w which includes the effect of the in-plane field. This energy density can be found by subtracting the energy density of a uniformly magnetized volume of film

$$w_m = K_u \sin^2 \theta_0 - H_p M_0 \sin \theta_0 \quad (2.2.58)$$

from the energy density of similar volume of film containing a domain wall

$$\begin{aligned} w_D = & A\theta_Y^2 + A\psi_Y^2 \sin^2 \theta + K_u \sin^2 \theta - \\ & 2\pi M_0^2 (\sin \theta_0 \sin \theta \sin \psi_0 \sin \psi - \sin^2 \theta \sin^2 \psi) + \\ & - H_p M_0 \sin \theta \cos(\psi - \psi_0) \end{aligned} \quad (2.2.59)$$

giving

$$\begin{aligned} w = & w_D - w_m \\ = & A\theta_Y^2 + A\psi_Y^2 \sin^2 \theta - K_u (\sin^2 \theta - \sin^2 \theta_0) + \\ & 2\pi M_0^2 (\sin \theta_0 \sin \theta \sin \psi_0 \sin \psi - \sin^2 \theta \sin^2 \psi) + \\ & - H_p M_0 (\sin \theta \cos(\psi - \psi_0) - \sin \theta_0) \end{aligned} \quad (2.2.60)$$

Here the first two terms are due to exchange, the last term is due to the applied in-plane field, the third term is due to the demagnetization energy $\vec{H}_D \cdot \vec{M}$ where

$$\vec{H}_D = 4\pi(M_{yO} - M_y)\hat{y} \quad (2.2.61)$$

as shown in Appendix A. A subscript o indicates the value of the quantity far from the wall. $\theta_o = \tan^{-1} \frac{H_p}{H_u - 4\pi M}$ and $\psi_o = \tan^{-1} \frac{H_y}{H_x}$.

Substituting equation (60) into equation (57) and assuming that ψ and θ are uniform in the x-z plane gives

$$\begin{aligned} & - 2\pi M_o^2 (\sin\theta_o \sin\theta \sin\psi_o \cos\psi - \sin^2\theta \sin 2\psi) + \\ & + H_p M_o \sin\theta \sin(\psi - \psi_o) + \\ & - 2A \sin^2\theta \psi_{yy} - 2A \sin 2\theta \psi_y \theta_y = 0 \end{aligned} \quad (2.2.62)$$

and

$$\begin{aligned} & A \psi_y^2 \sin 2\theta + K_u \sin 2\theta - 2\pi M_o^2 (\sin\theta_o \sin\psi_o \sin\psi \cos\theta - \sin^2\psi \sin 2\theta) \\ & - H_p M_o \cos\theta \cos(\psi - \psi_o) + \\ & - 2A \theta_{yy} = 0 \end{aligned} \quad (2.2.63)$$

Note that if $H_p=0$, $\theta_o=\psi_o=0$ and equations (62) and (63) reduce to equations (13) and (14) respectively, except for the demagnetization term $2\pi M_o^2 \sin^2 \psi \sin^2 \theta$. However, equations (13) and (14) are intended to describe a Bloch wall and in this case $\psi=0$ for a static wall, so that under this restriction, equations (62) and (63) reduce to equations (13) and (14) exactly. Note too that for $\psi \neq 0$, equation (62) requires that ψ be a function of y , thus breaking the assumption made earlier that $\frac{\partial \psi}{\partial y} = 0$.

In order to exactly solve for the dynamics of the wall with an in-plane magnetic field, it would be necessary to solve equation (62) for the static wall structure, obtain a relationship between θ and q as was done before, and then use equation (5) to find the time dependence of ψ and q . Thus far, this complete solution has not been obtained.

Section 2.3 - Calculation of the Restoring Force Constant

In the previous section, the restoring force acting on the domain wall when it is displaced from its equilibrium position was introduced. In this section, the explicit form of the force constant will be derived and a numerical method for calculating the value of the force constant will be presented.

In general, the force constant of a simple harmonic oscillator is just the second derivative of the energy with respect to the displacement. Thus, in order to find the force constant, it is necessary to first find the energy density per unit wall area of the magnetic material. Consider an array of parallel stripe domains, as illustrated in Figure 2.3.1. If E is the energy density per unit surface area of the film, then the total energy of the volume of the film contained in the dashed box in Figure 1 is

$$\epsilon = E(L_1 + L_2)L \quad (2.3.1)$$

the total amount of domain wall area enclosed in the same volume is

$$a = 2Lt \quad (2.3.2)$$

and thus, the energy per unit wall area is

$$\epsilon/a = E(L_1 + L_2)/2t \quad (2.3.3)$$

The calculation of the energy density E can be accomplished if several restrictions are met.⁵ These are that: 1) the material quality factor Q be greater than unity; 2) the geometry of the domain structure is uniform through the film thickness; 3) the domain wall

Figure 2.3.1. An array of parallel stripe domains. The arrows at the edge indicate the direction of magnetization. $L_1 + L_2$ is the stripe period and t is the film thickness.

is very thin compared to the domain width and contribute an energy σ_w per unit wall area to the domain; 4) the film is uniform in thickness and of infinite extent so that edge effects may be neglected and; 5) the film has no defects which cause domain wall pinning.

If these restrictions are met, then only three terms contribute to the magnetic energy of a domain. They are: wall energy, the energy due to the interaction of the magnetic material with an applied magnetic field, and the demagnetizing energy of the material.

In order to calculate the equilibrium dimensions of a domain pattern and thus obtain the equilibrium energy, it is necessary to minimize the energy with respect to the dimensions of the domain pattern. In the case where the pattern is characterized by two independent dimensions, for example, x and y , then the conditions

$$\frac{\partial E}{\partial x} = \frac{\partial E}{\partial y} = 0$$

$$\frac{\partial^2 E}{\partial x^2} > 0$$

$$\left(\frac{\partial^2 E}{\partial x^2} \frac{\partial^2 E}{\partial y^2} - \left(\frac{\partial^2 E}{\partial x \partial y} \right)^2 \right) > 0 \quad (2.3.4)$$

must be satisfied. These conditions provide a way of obtaining expressions for the equilibrium values of the coordinates and of the energy density.

In the case of an array of parallel strip domains as illustrated in Figure 1, the energy is given by⁵

$$E = \frac{Y}{\pi} \sigma_w + t(1-x)H M_s + 2\pi t M_s^2(x^2-1) + \frac{16t M_s^2}{\pi Y} \sum_{n=1}^{\infty} \frac{\sin^2[\frac{n\pi}{2}(1+x)]}{n^3} (1-e^{-ny}) \quad (2.3.5)$$

where σ_w is the energy density per unit wall area, H is the applied magnetic field normal to the plane of the film and

$$x = \frac{L_1 - L_2}{L_1 + L_2}$$

$$Y = \frac{2\pi t}{L_1 + L_2} \quad (2.3.6)$$

The equilibrium conditions in equation (4) give

$$\frac{H}{4\pi M_s} = x + \frac{2}{\pi Y} \sum_{n=1}^{\infty} \frac{\sin n\pi(1+x)}{n^2} (1-e^{-ny}) \quad (2.3.7)$$

and

$$\frac{\sigma_w}{16t M_s^2} = \frac{1}{y^2} \sum_{n=1}^{\infty} \frac{\sin^2 \frac{n\pi}{2}(1+x)}{n^3} (1 - e^{-ny}(1+ny)) \quad (2.3.8)$$

The remaining parts of the stability condition are satisfied for all possible values of x and y .

If the effect of an in-plane field along the direction of the domain walls is to be included, it is necessary to make the appropriate modifications to equation (5). The presence of an in-plane magnetic field will cause the magnetization to cant; thus the M_s^2 terms in equation (5), which are due to demagnetization energy, must be replaced by M_z^2 . Also, the wall energy density σ_w will vary with in-plane field and this effect must also be taken into account. As shown in Appendix B, the wall energy density for an in-plane field along the wall is

$$\sigma_w = 2K_u \Delta_O (2 \cos \theta_O - (\pi - 2\theta_O) \sin \theta_O) \quad (2.3.9)$$

where

$$\sin \theta_O = H_p / H_u \quad (2.3.10)$$

If no bias field (H_z) is present, then $x=0$ and the equilibrium equations now reduce to

$$\frac{\sigma_w}{16t M_z^2} = \frac{1}{y^2} \sum_{n \text{ odd}} \left(\frac{1}{n^3} - \frac{e^{-ny}(1+ny)}{n^3} \right) \quad (2.3.11)$$

This equation can be solved numerically for a given value of M_z to find the corresponding value of y and thus

$$L_1 + L_2 = \frac{2\pi t}{y} \quad (2.3.12)$$

In order to calculate the force constant, it is necessary to twice differentiate the total energy given in equation (3) with respect to the wall displacement q . Noting that for a stripe pattern initially at equilibrium ($x=0$), a displacement q of a single wall results in a change in x equal to $2q/(L_1+L_2)$. Thus

$$\frac{d}{dq} = \frac{2}{L_1+L_2} \frac{d}{dx} \quad (2.3.13)$$

and the force constant is

$$k = \varepsilon_{qq} = \frac{4}{(L_1+L_2)^2} \left(\frac{L_1+L_2}{2t} \right) E_{xx} = \frac{2E_{xx}}{(L_1+L_2)t} \quad (2.3.14)$$

where $E_{xx} = \frac{\partial^2 E}{\partial x^2}$. Differentiating equation (5) and evaluating at $x=0$ gives

$$E_{xx} = 4\pi M_z^2 t \left(1 + \frac{2}{Y} \sum_{n=1}^{\infty} \frac{(-1)^n}{n} (1 - e^{-ny}) \right) \quad (2.3.15)$$

A computer program has been written⁶ to increment the in-plane field between user specified limits, calculating at each value of H_p the value of y using equation (11) and the value of E_{xx} using equation (14). The results of these calculations are then stored on magnetic tape for further use in calculating the domain wall resonance frequency of domain wall motion. A listing of this program is included in Appendix C.

Section 2.4 - Effect of Surface Charges on the Wall Mass

The development of the wall mass in Section 2.2 ignored the effects of magnetic surface charges on the structure of the wall and on the wall mass. Such an assumption would appear to be questionable and several workers^{7,8} have suggested that the structure of the wall along the z axis will have a strong influence on the wall mass. In this section, a method of calculating the structure of the wall along the z axis will be given and typical results will be shown.

As was shown in Section 2.2, the wall momentum and thus the wall mass is directly proportional to ψ . Thus, a calculation of the average value of ψ across the film thickness will give the wall momentum and, if the velocity is known, the wall mass can be evaluated.

According to equation (2.2.23)

$$\frac{\delta \sigma}{\delta \psi} = \frac{2M}{\gamma} (\dot{q} - \alpha \Delta \dot{\psi}) \quad (2.4.1)$$

and from (2.2.40)

$$\begin{aligned} \delta \sigma = \delta \left\{ \frac{2A}{\Delta} (\nabla q)^2 + 2A\Delta (\nabla \psi)^2 + 4\pi M^2 \Delta \sin^2 \psi + \frac{1}{2} k q^2 \right\} + \\ \pi M \Delta (H_x \sin \psi - (H_y + H_y^D) \cos \psi) \delta \psi - 2M H_x \delta q \end{aligned} \quad (2.4.2)$$

where H_y^D is the y (and only) component of the demagnetization field due to the surface charges resulting from the adjacent domains.

This is given by⁷

$$H_y^D(z) = -4M_z \ln \left[\frac{\tanh(\frac{\pi}{2L}(\tilde{z} + \frac{t}{2}))}{-\tanh(\frac{\pi}{2L}(\tilde{z} - \frac{t}{2}))} \right] \quad (2.4.3)$$

where L is the domain width, equal to $\frac{1}{2}(L_1 + L_2)$ if there is no bias field present, and

$$\tilde{z} = z - 2\Delta \sinh\left(\frac{z}{2\Delta_0}\right) / \cosh\left(\frac{t}{4\Delta_0}\right) \quad (2.4.4)$$

If ψ is assumed to be uniform in the x direction so that $\nabla\psi = \frac{\partial\psi}{\partial z}$, then equation (1) becomes

$$\begin{aligned} \dot{q} = & 2\pi M\gamma\Delta \sin 2\psi + \frac{\pi\gamma\Delta}{2}(H_x \sin\psi - H_y^{\text{tot}} \cos\psi) + \alpha\Delta\dot{\psi} + \\ & - \frac{2A\Delta\gamma}{M} \psi_{zz} \end{aligned} \quad (2.4.5)$$

where $H_y^{\text{tot}} = H_y + H_y^D$ and $\psi_{zz} = \frac{\partial^2\psi}{\partial z^2}$.

Noting that $\dot{q}=V$, the wall velocity, and assuming that the wall structure ψ is independent of time gives

$$\begin{aligned} & 2\pi M\gamma\Delta \sin 2\psi + \frac{\pi\gamma\Delta}{2}(H_x \sin\psi - H_y^{\text{tot}} \cos\psi) - \frac{A\Delta\gamma}{M} \psi_{zz} - V \\ & = 0 = g(\psi) \end{aligned} \quad (2.4.6)$$

This differential equation can be solved numerically for $\psi(z)$ and the resulting solution can then be averaged to obtain the wall momentum and thus its mass.

The equation (6) is solved numerically in the following manner. The function $\psi(z)$ is replaced by the discrete function ψ_i where i is now a position index and ranges from 0 at one surface of the film to 100 at the

other surface. Equation (6) can now be written as

$$\begin{aligned}
 g(\psi_{i-1}, \psi_i, \psi_{i+1}) = & 2\pi M\gamma\Delta \sin 2\psi_i + \\
 & \frac{\pi\gamma\Delta}{2}(H_x \sin\psi_i - H_{Y,i}^{\text{tot}} \cos\psi_i) + \\
 & - \frac{2\gamma\Delta A}{M} \frac{\psi_{i+1} - 2\psi_i + \psi_{i-1}}{4\left(\frac{t}{100}\right)^2} - V = 0 \quad (2.4.7)
 \end{aligned}$$

where the derivative ψ_{ZZ} has been replaced with its difference expression equivalent $\frac{\psi_{i+1} - 2\psi_i + \psi_{i-1}}{4\left(\frac{t}{100}\right)^2}$ and the i dependence of $H_{Y,i}^{\text{tot}}$ is due to the z dependence of the demagnetization field H_Y^D . $g(\psi)$ can now be expressed in terms of a Taylor expansion about some trial function ψ^T as follows

$$\begin{aligned}
 g(\psi_{i-1}, \psi_i, \psi_{i+1}) = & g(\psi_{i-1}^T, \psi_i^T, \psi_{i+1}^T) + \left. \frac{\partial g}{\partial \psi_i} \right|_{\psi_i^T} D_i + \\
 & \left. \frac{\partial g}{\partial \psi_{i+1}} \right|_{\psi_{i+1}^T} D_{i+1} + \left. \frac{\partial g}{\partial \psi_{i-1}} \right|_{\psi_{i-1}^T} D_{i-1} \quad (2.4.8)
 \end{aligned}$$

where $D_i = \psi_i - \psi_i^T$. Since $g(\psi_{i-1}, \psi_i, \psi_{i+1}) = 0$, equation

(8) is an equation for the difference between the trial function ψ^T and the actual solution ψ . This can be written in the form

$$a_i D_{i-1} + d_i D_i + c_i D_{i+1} = b_i \quad (2.4.9)$$

Performing the partial derivatives gives

$$a_i = \left. \frac{\partial g}{\partial \psi_{i-1}} \right|_{\psi_{i-1}^T} = \frac{2\gamma \Delta A}{4M(\frac{t}{100})^2} \quad (2.4.10a)$$

$$d_i = \left. \frac{\partial g}{\partial \psi_i} \right|_{\psi_i^T} = 2\pi\gamma M\Delta (2\cos 2\psi_i^T) +$$

$$\frac{\pi\gamma\Delta}{2} (H_x \cos \psi_i^T + H_{y,i}^{\text{tot}} \sin \psi_i^T) +$$

$$- \frac{4\gamma \Delta A}{4M(\frac{t}{100})^2} \quad (2.4.10d)$$

$$c_i = \left. \frac{\partial g}{\partial \psi_{i+1}} \right|_{\psi_{i+1}^T} = \frac{2\gamma \Delta A}{4M(\frac{t}{100})^2} = a_i \quad (2.4.10c)$$

$$b_i = g(\psi_{i-1}^T, \psi_i^T, \psi_{i+1}^T) =$$

$$\begin{aligned} & 2\pi M \gamma \Delta \sin 2\psi_i^T + \frac{\pi \gamma \Delta}{2} (H_x \sin \psi_i^T - H_{Y,i}^{\text{tot}} \cos \psi_i^T) + \\ & - \frac{2\gamma \Delta A}{M} \frac{\psi_{i+1}^T - 2\psi_i^T + \psi_{i-1}^T}{4 \left(\frac{t}{100}\right)^2} - V \end{aligned} \quad (2.4.10b)$$

Multiplying equation (9) by $\frac{4\pi M^2 \left(\frac{t}{100}\right)^2}{A V_w}$, where

$V_w = 2\pi \gamma \Delta M$ is the Walker velocity, gives

$$D_{i-1} + d_i D_i + D_{i+1} = b_i \quad (2.4.11)$$

and

$$d_i = \frac{4\pi M^2 \left(\frac{t}{100}\right)^2}{A} \left\{ 2\cos 2\psi_i^T + \frac{1}{4M} (H_x \cos \psi_i^T + H_{Y,i}^{\text{tot}} \sin \psi_i^T) \right\} - 2 \quad (2.4.12a)$$

$$\begin{aligned} b_i = \frac{4\pi M^2 \left(\frac{t}{100}\right)^2}{A} & \left\{ \sin 2\psi_i^T + \frac{1}{4M} (H_x \sin \psi_i^T - H_{Y,i}^{\text{tot}} \cos \psi_i^T) - \frac{V}{V_w} + \right. \\ & \left. - \frac{A}{\pi M^2} \frac{\psi_{i+1}^T - 2\psi_i^T + \psi_{i-1}^T}{\left(\frac{t}{100}\right)^2} \right\} \end{aligned} \quad (2.4.12b)$$

A computer program⁹ is included in Appendix D which calculates the function ψ by starting with a trial function

ψ^T , solving equation (11) to get the difference between the trial function and the solution function, and adding the difference to the trial function. This procedure is iterated until the sum of the D_i is less than 10^{-6} . This resulting ψ function is then plotted. Alternatively, ψ can be averaged and multiplied by $\frac{2M}{\gamma V}$ to obtain the wall mass.

Figure 2.4.1 shows $\psi(z)$ for a moving domain wall with no in-plane field applied. Figure 2.4.2 shows the same wall moving at the same velocity but with an in-plane field $H_p \sim .1 H_u$ applied along the wall. Note that the effect of the in-plane field is to "straighten" the ψ profile, tending to minimize the effect of the surface charges and make the wall more like a Bloch wall. Figure 2.4.3 shows the wall mass vs. velocity. Note that for low velocities the mass is constant. The sharp increase in the mass at $V \sim .3V_w$ is due to the velocity nucleation of a horizontal Bloch line⁷ in the wall. Figure 2.4.4 shows the mass obtained with this model as a function of H_p (H_p applied along the wall) along with the mass predicted in Section 2.2.

Figure 2.4.1. Wall structure vs. position across the film thickness for zero in-plane field. Wall velocity is .05 V_w .

Figure 2.4.2. Wall structure vs. position across the film thickness for $H_p = .1 H_u \approx 8M$. Wall velocity is $.05 V_w$.

Figure 2.4.3. Wall mass vs. velocity for zero in-plane field. Wall mass is obtained by calculating the wall structure and averaging ψ , as described in the text. The sharp increase in the mass at $V/V_w = .3$ is due to the nucleation of a horizontal Bloch line.

Figure 2.4.4. Wall mass vs. in-plane field. The solid curve is the mass obtained by taking the wall structure into account. The dashed curve is the Bloch wall mass obtained in section 2.2.

Section 2.5 - Domain Wall Mass With a Large In-Plane Field

It is possible to calculate the wall mass directly without calculating the explicit equation of motion, as was done in Section 2.2. In this section, this calculation will be done for a Bloch wall in both small and large in-plane magnetic fields.

The energy density of a domain wall is

$$\sigma_w = \int_{-\infty}^{\infty} w \, dy \quad (2.5.1)$$

where w is given in equation (2.2.60). If the in-plane field is along the plane of the wall, $\psi_0=0$ and equation (1) becomes

$$\begin{aligned} \sigma_w = \int_{-\infty}^{\infty} & A\theta_y^2 + A\psi_y^2 \sin^2 \theta + K_u (\sin^2 \theta - \sin^2 \theta_0) \\ & - 2\pi M_0^2 \sin^2 \theta \sin^2 \psi + \\ & H_p M_0 (\sin \theta \cos \psi - \sin \theta_0) \, dy \quad (2.5.2) \end{aligned}$$

Substituting equation (2) into equation (2.2.23) and ignoring damping gives

$$\dot{q} = \frac{\gamma}{2M} \int_{-\infty}^{\infty} \{ 2\pi M_O^2 \sin^2 \theta \sin 2\psi + H_p M_O \sin \theta \sin \psi \} dy \quad (2.5.3)$$

where the terms ψ_y and ψ_{yy} have been ignored because for a simple moving Bloch wall ψ is uniform everywhere. As was shown in Section 2.2, the momentum of the moving wall is

$$P = m \dot{q} = \frac{2M}{\gamma} \psi \quad (2.5.4)$$

Equation (3) can be rewritten as

$$\dot{q} = \frac{\gamma}{2M} \{ 2\pi M_O^2 \sin 2\psi \ a + H_p M_O \sin \psi \ b \} \quad (2.5.5)$$

where

$$a = \int_{-\infty}^{\infty} \sin^2 \theta dy \text{ and } b = \int_{-\infty}^{\infty} \sin \theta dy$$

Assuming that ψ is small and substituting equation (5) into equation (4) gives for the wall mass

$$\frac{1}{m} = \pi \gamma^2 \left(a + \frac{H_p}{4\pi M} b \right) \quad (2.5.6)$$

This expression can be evaluated if the integrals a and b can be evaluated. Consider first the case for

small in-plane fields. Here the wall structure can be assumed to be the Bloch wall structure, thus $\theta_0=0$ and

$\frac{dy}{d\theta} = \frac{\Delta}{\sin\theta}$. The integrals become

$$a = \int_{-\infty}^{\infty} \sin^2\theta dy = \int_0^{\pi} \sin^2\theta \frac{\Delta_0}{\sin\theta} d\theta = 2\Delta_0 \quad (2.5.7)$$

and

$$b = \int_{-\infty}^{\infty} \sin\theta dy = \int_0^{\pi} \sin\theta \frac{\Delta_0}{\sin\theta} d\theta = \pi\Delta_0 \quad (2.5.8)$$

and thus

$$\frac{1}{m} = 2\pi\gamma^2\Delta_0\left(1 + \frac{H_p}{8M}\right) = m_D^{-1}\left(1 + \frac{H_p}{8M}\right) \quad (2.5.9)$$

as was obtained in Section 2.2.

The case of large in-plane fields, however, is not as simple. In this case, θ approaches $\theta_0 = \sin^{-1} \frac{H_p}{H_u}$ as y approaches $\pm\infty$ and the integrals a and b diverge. Wigen and Dötsch¹⁰ have argued that, since the integral a is due to demagnetization energy, which goes to zero far away from the wall, it is not physically reasonable that a should diverge. They therefore propose that $a=2\Delta$ where Δ is the in-plane field dependent wall width given by

$$\Delta = \frac{\Delta_o (1 - \frac{2\theta_o}{\pi})}{1 - \sin\theta_o} \quad (2.5.10)$$

They also argue that since the b integral is due to the additional field energy due to the presence of the wall, b should be rewritten as

$$b = \int_{-\infty}^{\infty} (\sin\theta - \sin\theta_o) dy \quad (2.5.11)$$

Taking $\frac{dy}{d\theta} = \frac{\Delta_o}{\sin\theta - \sin\theta_o}$ gives $b = \pi\Delta(1 - \frac{2\theta_o}{\pi})$ and

gives for the mass

$$\frac{1}{m} = m_D^{-1} (1 - \frac{2\theta_o}{\pi}) \left(\frac{1}{1 - \sin\theta_o} + \frac{H_p}{8M} \right) \quad (2.5.12)$$

The dependence of this expression as a function of H_p is shown in Figure 2.5.1. A major difficulty of this model is the fact that for an actual moving domain wall with an applied in-plane field, ψ_y and ψ_{yy} are not zero and therefore cannot be ignored, as was done in obtaining equation (3).

Figure 2.5.1. Inverse wall mass vs. in-plane field. The solid curve is the model of Wigen and Dötsch. The dashed curve is the Bloch wall model.

Section 2.6 - The Theory of O'Dell

O'Dell¹¹ has developed a theory for the mass of a domain wall which takes into account the change in the wall structure as an in-plane field is applied, using an approach which is very different from the one used in previous sections.

The Landau-Lifshitz equation with damping is

$$\frac{-1}{\gamma} \frac{d\vec{M}}{dt} = (\vec{M} \times \vec{F}) - \lambda (\vec{F} - (\vec{F} \cdot \vec{M}) \frac{\vec{M}}{M_s^2}) \quad (2.6.1)$$

here λ is the Landau-Lifshitz damping parameter equal to $M_s \alpha$, and $\vec{F}$ is the total effective magnetic field, given by

$$\begin{aligned} F_x &= \frac{2A}{M_s^2} \frac{\partial^2 M_x}{\partial y^2} + 4\pi M_x + H_x \\ F_y &= \frac{2A}{M_s^2} \frac{\partial^2 M_y}{\partial y^2} \\ F_z &= \frac{2A}{M_s^2} \frac{\partial^2 M_z}{\partial y^2} + \frac{M_z}{M_s} H_u + 4\pi M_z + H_z \end{aligned} \quad (2.6.2)$$

The components of the magnetization $\vec{M}$ are written as

$$M_x = M_s \sin \theta \cos \psi$$

$$M_y = M_s \sin \theta \sin \psi$$

$$M_z = M_s \cos \theta \quad (2.6.3)$$

where the angle θ is defined by¹²

$$\frac{y'}{\Delta} = [\cos \theta_o]^{-1} \ln \left[\frac{(1 - \sin \theta_o - \cos \theta_o) + (1 - \sin \theta_o + \cos \theta_o) \tan \frac{\theta}{2}}{(1 - \sin \theta_o + \cos \theta_o) + (1 - \sin \theta_o - \cos \theta_o) \tan \frac{\theta}{2}} \right] \quad (2.6.4)$$

where $\sin \theta_o = \frac{H_x}{H_u}$ and $y' = y - vt$

Equations (3) and (2) can be substituted into equation (1) to obtain the equation of motion for the magnetization.

Since the wall is assumed to be rigid, equation (1) can be evaluated at any point in the wall and the resulting equation of motion will be the equation of motion for the whole wall. In particular, equation (1) is evaluated at $y = vt$, giving from the x and y components

$$\frac{1}{\gamma} \frac{d\psi}{dt} = H_z - 4\pi\lambda \left[\cos(\psi) + \frac{H_x}{4\pi M_s} \right] \sin(\psi) \quad (2.6.5)$$

and from the z component

$$v = \frac{\gamma \Delta}{M_s (1 - \sin \theta_o)} (2\pi M_s^2 \sin 2\psi + M_s H_x \sin \psi + \lambda H_z) \quad (2.6.6)$$

Assuming ψ is small (i.e. that the wall momentum is small) and combining equations (5) and (6) gives

$$\frac{2(1 - \sin \theta_o)}{4\pi \gamma^2 \Delta (1 + \frac{H_x}{4\pi M})} \frac{dv}{dt} + \frac{2\lambda (1 - \sin \theta_o)}{\gamma \Delta} v = 2M_s H_z \quad (2.6.7)$$

where terms proportional to $\frac{\lambda^2}{M_s^2} = \alpha^2$ and $\frac{dB_z}{dt}$ have been neglected because they are small compared to the other terms in the equation. Inspection of equation (7) shows that the mass is now

$$m^{-1} = m_D^{-1} \frac{1 + \frac{H_x}{4\pi M}}{1 - \sin \theta_o} \quad (2.6.8)$$

This result is shown graphically in Figure 2.6.1.

The assumption that the Landau-Lifshitz equation can be evaluated at any point seems to be suspect, however. This is saying, in effect, that the average torque acting on the spins in the wall is equal to the torque acting on the center spin of the wall. Since the energy density in the wall varies strongly, it would seem more appropriate

Figure 2.6.1. Inverse wall mass vs. in-plane field. The solid curve is the model of O'Dell. The dashed curve is the Bloch wall model.

to integrate across the wall to obtain the torque, rather than directly applying the LL equation at the center. Wigen¹³ has shown that if this is done the results obtained are the same as given by equation (2.5.12).

Section 2.7 - Morkowski's Solution for the Wall Mass

As was noted at the end of Section 2.2, in order to properly find the domain wall mass, it is necessary to solve for the static spin configuration with an applied in-plane field. Morkowski¹⁴ has calculated this in the case where H_p is applied along the plane of the domain walls and has obtained an expression for the wall mass which differs markedly in its dependence on H_p from the expressions discussed in the previous section.

The wall mass is obtained by assuming that the change in the wall energy $\delta\sigma$ of the moving wall is equal to the changes in the kinetic energy $\delta(\frac{1}{2}mv^2)$. Here, as in Section 2.2,

$$\delta\sigma = \int_{-\infty}^{\infty} (\delta w_s - \vec{H} \cdot \delta\vec{M}) dy \quad (2.7.1)$$

where now

$$w_s = A\theta_Y^2 + A \sin^2\theta \psi_Y^2 + K \sin^2\theta \quad (2.7.2)$$

and

$$-\vec{H} \cdot \delta\vec{M} = \delta(2\pi M^2 \sin^2\theta \sin^2\psi - M H_p \sin\theta \cos\psi) \quad (2.7.3)$$

The equations correspond to those given in Section 2.2 with the addition of terms reflecting the presence of the in-plane field. Also, ψ_0 is assumed to be zero since the in-plane field is along the x direction. Using this form of the energy, the Landau-Lifshitz-Gilbert equations become

$$\begin{aligned} \frac{M}{\gamma} \sin\theta (\dot{\theta} + \alpha \dot{\psi} \sin\theta) = - \frac{\delta w}{\delta \psi} = 2A(\sin^2\theta \psi_{YY} + \sin 2\theta \psi_Y \theta_Y) + \\ - M H_p \sin\theta \sin\psi - 2\pi M^2 \sin^2\theta \sin 2\psi \end{aligned} \quad (2.7.4)$$

and

$$\begin{aligned} \frac{M}{\gamma} \sin\theta (\dot{\psi} \sin\theta - \alpha \dot{\theta}) = \frac{\delta w}{\delta \theta} = -2A\theta_{YY} + K \sin 2\theta + A \sin 2\theta \psi_Y^2 + \\ 2\pi M^2 \sin 2\theta \sin^2\psi - M H_p \cos\theta \cos\psi \end{aligned} \quad (2.7.5)$$

In the static case, $\dot{\theta}=\dot{\psi}=0$ and the solution to equation (4) is $\psi=0$. Equation (5) then becomes

$$- 2A\theta_{yy} + K \sin 2\theta - M H_p \cos \theta = 0 \quad (2.7.6)$$

Using the boundary conditions $\theta_y \rightarrow 0$ as $y \rightarrow \pm\infty$ and $\theta \rightarrow \theta_0$ as $y \rightarrow \pm\infty$, the solutions to equation (6) is

$$\Delta^2 \theta_y^2 = \sin^2 \theta - \sin^2 \theta_0 - 2\mu (\sin \theta - \sin \theta_0) \quad (2.7.7)$$

where $\Delta^2 = \frac{A}{K}$ as before and $\mu = \frac{H_p}{H_u} = \frac{MH_p}{2K}$

Taking into account the demagnetization field for a flat domain far away from the wall

$$\sin \theta_0 = \frac{H_p}{H_u - 4\pi M} = \frac{H_p}{H_u} \left(\frac{Q}{Q-1} \right) = \mu_1 \quad (2.7.8)$$

and, assuming that $\mu - \mu_1$ is small

$$\begin{aligned} \Delta \theta_y &= (\sin^2 \theta - 2\mu \sin \theta + 2\mu \mu_1 - \mu_1^2)^{\frac{1}{2}} \\ &\approx \sin \theta - \mu \end{aligned} \quad (2.7.9)$$

In order to consider the dynamic properties of the domain wall, it is necessary to assume that the wall structure of the moving wall is the same as for a stationary wall, i.e.

$$\theta(y,t) = \theta(y-vt) = \theta(y-q) \quad (2.7.10)$$

and that the wall displacement q is small. From the first assumption

$$\dot{\theta} = -\dot{q} \frac{d\theta}{dy} = -v\theta_y \quad (2.7.11)$$

and from the second assumption

$$\theta(y-q) = \theta(y) - q \frac{d\theta}{dy} = \theta(y) - q\theta_y \quad (2.7.12)$$

Substituting equation (11) into equation (4) gives, if ψ is assumed to be small and damping is ignored,

$$\frac{1}{\gamma} \theta_y v = (H_p + 4\pi M \sin\theta)\psi - \frac{2A}{M} \frac{1}{\sin\theta} \frac{\partial}{\partial y} (\sin^2\theta \psi_y) \quad (2.7.13)$$

This equation, together with equation (5) modified with an additional term describing the driving term, can be solved to obtain a complete equation of motion for the wall, similar to what was done in Section 2.2. Equation (13) alone, however, is sufficient to obtain the wall mass, since equation (13) provides the relationship between the velocity and ψ .

The mass is obtained by equating the changes in the wall energy as the wall moves to the change in the wall's kinetic energy

$$\delta \left(\frac{1}{2} m v^2 \right) = \delta \sigma = \int_{-\infty}^{\infty} dy \delta w \quad (2.7.14)$$

Noting that $\delta w = \frac{\delta w}{\delta \psi} \delta \psi$ this becomes, if ψ is assumed to be small.

$$m v \delta v = \int_{-\infty}^{\infty} dy \left\{ (4\pi M^2 \sin^2 \theta + H_p M \sin \theta) - 2A \frac{\partial}{\partial y} \left(\sin^2 \theta \frac{\partial \psi}{\partial y} \right) \right\} \delta \psi \quad (2.7.15)$$

Assuming

$$\psi = f(y) v \quad (2.7.16)$$

and that the static wall structure is independent of v so that

$$\delta \psi = f(y) \delta v \quad (2.7.17)$$

then equation (13) can be substituted for the integrand in equation (15) to give

$$m \, v \delta v = \frac{M}{\gamma} \int_{-\infty}^{\infty} dy \sin \theta \, \theta_Y \, v f(y) \delta v \quad (2.7.18)$$

giving for the mass

$$\begin{aligned} m &= \frac{M}{\gamma} \int_{-\infty}^{\infty} dy \sin \theta \, \theta_Y \, f(y) \\ &= \frac{M}{\gamma} \int_{\theta_0}^{\pi - \theta_0} \sin \theta \, f(\theta) d\theta \end{aligned} \quad (2.7.19)$$

If the term $\frac{\partial}{\partial y} (\sin^2 \theta \, \psi_Y)$ can be ignored then equation (13) can be solved for $f(\theta)$ giving

$$\begin{aligned} f(\theta) &= \frac{\frac{1}{\gamma} \theta_Y}{H_p + 4\pi M \sin \theta} \\ &= \frac{1}{\gamma \Delta} \frac{\sin \theta - \mu}{4\pi M (\sin \theta + h)} \end{aligned} \quad (2.7.20)$$

where $h = \frac{H_p}{4\pi M}$

The mass is now given by

$$m = \frac{m_D}{2} \int_{\theta_0}^{\pi - \theta_0} \frac{\sin \theta (\sin \theta - \mu)}{\sin \theta + h} d\theta \quad (2.7.21)$$

A graph of equation (21) vs. H_p is shown in Figure 2.7.1.

The chief difference of this derivation of the wall mass is that, unlike the previously discussed models, it explicitly allows ψ to be a function of y for a moving wall. To not allow ψ to be a function of y is equivalent to ignoring the terms μ and h in equation (20). For this to be physically reasonable requires that $H_p \ll H_u$ and $H_p \ll 4\pi M = \frac{H_u}{Q}$ so that the previously discussed models, in Sections 2.2 and 2.5, will only be valid for very small in-plane fields.

Figure 2.7.1. Inverse wall mass vs. in-plane field. The solid curve is Morkowski's expression. The dashed curve is the Bloch wall mass.

CHAPTER 3

EXPERIMENTAL

The frequency response of domain wall motion is measured using an RF spectrometer. This is a frequency swept, transmission type system similar to the system used in previous measurements^{1,2} of domain wall resonance.

The central part of this system is the RF structure used to couple an RF magnetic field into the sample to excite domain wall motion and to pick up a signal from the oscillating domain walls. The basis of this device is a glass substrate with a thin film of gold evaporated onto one surface. Into this gold film is etched a coplanar transmission line and a slot line, to form the RF input and output sides, respectively. Each is short circuited at the end and the two parts are separated by a thin line etched between them to improve the low frequency isolation. This pattern is illustrated in Figure 1. The RF magnetic field in both the slot line and the coplanar transmission line is elliptically polarized so that it may excite domain wall motion in the magnetic material placed on top of the structure.

Figure 3.1. Layout of the RF structure. The light areas are gold. In the dark areas, the gold has been etched away, forming a short circuited slot line on the right side and a short circuited coaxial transmission line on the left side.

Diagrams of the RF fields in cross section are shown in Figure 2 for the slot line and in Figure 3 for the coaxial line. Because of the geometry of the device, when no magnetic material is present, no coupling exists between the slot line and the coaxial line. This is because the pattern of RF current distribution around the end of the coaxial line is not the same as the current distribution around the end of the slot line. These current distributions are shown in Figure 4. However, if a piece of magnetic material is placed on top of the structure and domains are present, then the RF magnetic field of the coaxial line can drive the domain walls into motion. The oscillating magnetic dipole moment associated with the moving walls will then induce a current in the slot line, effectively coupling the two parts of the structure. The normal isolation for a typical structure is 70-90 dB, and the change in the isolation due to domain wall motion is almost always 10 dB or less. Figure 5 shows the structure with a sample in place.

A block diagram of the entire spectrometer is shown in Figure 6. The RF source is a synthesized signal generator (Wavetek model 3000) whose output frequency is controlled by the computer. Frequency "sweeps" are generated by having the computer step the frequency in

Figure 3.2. RF fields in the slot line. The E field runs from one side of the slot to the other, the H field is normal to the plane of the structure.

Figure 3.3. RF fields in the coaxial line. The E field runs from the center conductor to the outer (ground plane) conductors. The H field runs around the center conductor and out of the insulating gaps normal to the plane of the structure.

Figure 3.4. RF currents around the short circuited ends of the slot line and the coaxial line.

Figure 3.5. The RF structure with a sample in place.

Figure 3.6. System block diagram

250 steps between the desired start and stop frequencies. The frequency range of this unit is 1 MHz to 520 MHz. The output of the structure is amplified (one or two SCI 1040 low noise, 40 dB gain amplifiers) and then detected with a crystal detector (HP 8472B). The output of the detector is a voltage proportional to the RF power at its input. This signal is then fed to two different DC amplifiers. The logarithmic amplifier (HP 7563) log compresses the detector voltage so that the display of the signal on the storage scope will be in dB units. The instrumentation amplifier (designed and constructed by the Physics Department electronic shop) provides additional gain under computer control as needed so that the signal can be measured by the digital voltmeter (HP 3437). The DVM digitizes the detector voltage and outputs it to the computer for storage in the computer's memory after conversion of the voltage into the corresponding power level using a look-up table stored in the computer.

The in-plane magnetic field is provided by a 4" Varian electromagnet and a 20A power supply (Kepco BOP 15-20). Fields up to 1200 Oe. with a 4" gap can be attained. The field is controlled by the computer via a HP 59501 power supply programmer and can be monitored using a Hall probe gaussmeter (F.W. Bell 640).

This arrangement allows the computer to set and monitor the in-plane magnetic field, compensating for probe placement away from the center of the gap and for hysteresis in the magnet. Bias fields are supplied by an air core, water-cooled coil made in the laboratory. Bias fields up to 350 Oe. can be attained with this coil. The field is measured by monitoring the current and using a calibration table to determine the value of the bias field. Bias field current is measured by measuring the voltage drop across a 1Ω sense resistor in series with the bias field coil. Current for the bias field coil is supplied by a manually controlled 5A constant current power supply (Kepco BOP 36-5).

A visual display of the scan is provided by a storage oscilloscope whose horizontal axis is driven by a digital-to-analog convertor. The DAC's output is stepped each time the frequency is stepped, providing a scan proportional to frequency on the scope. The vertical drive for the display comes from the logarithmic amplifier, thus the scope displays power in dB vs. frequency.

Much of the versatility of the system is due to the fact that the experiment is interfaced to the computer. Use of the computer allows greater accuracy of measurement. For example, 60 Hz noise was found to be a problem with the experiment, probably due to ground

loops. After conventional methods of dealing with this failed to sufficiently reduce the noise, a solution was developed which would be impossible without the computer. A subroutine was written to program the voltmeter to take 34 readings in $1/60$ th of a second. These readings are sent to the computer and averaged. Since there are 34 readings averaged, the 60 Hz fundamental and the next 16 harmonics are effectively removed from the reading, leaving only the desired DC level.

In addition to enhancing the accuracy of measurement by averaging many readings, complete calibration tables can be stored in the memory and used to give a more accurate reading of the quantity being measured, as is done, for example, in measuring the in-plane magnetic field. Here, two gaussmeters were used to measure the actual field at the center of the magnet air gap and at the location of the probe used in the experiment, near the pole face. The resulting table is used to convert field readings taken near the pole face to field values at the center of the gap where the sample is located. To set the field, the computer first calculates the approximate current needed and sets this value. It then measures the field, using the stored calibration table to obtain the field at the center of the gap, and adjusts the current. This measure-adjust cycle is repeated until the desired field is reached,

usually in a few seconds. Using this method, field accuracy is one percent or better. The only flaw to this scheme is that if the position of the Hall probe is changed, a new calibration table will have to be made because the magnetic field varies strongly with position near the pole face. A similar method is used with the conversion of voltage readings on the detector to power levels, extending the usable range of the detector by 25 dB.

All of the functions of the system are implemented in the master system program. Functions presently provided include taking a data scan, signal averaging, baseline storage and subtraction, plotting the data, and storing the data on magnetic tape for retrieval and use later. As new functions become desirable, they are easy to add by adding to the system program. A listing of the complete system program is provided in Appendix E.

The sample used in this study was obtained from Philips Laboratories, Hamburg, Germany. The composition is $\text{Y}_{2.96}\text{La}_{.14}\text{Fe}_{3.75}\text{Ga}_{1.25}\text{O}_{12}$ and the material parameters are listed in Table 1. The saturation magnetization, uniaxial anisotropy field, and Gilbert damping parameter were measured at OSU using a vibrating sample magnetometer and ferromagnetic resonance. The thickness and characteristic length

were measured using infrared interference and bubble collapse measurements, respectively, by Philips. Stripe period measurements as a function of in-plane field were made using an optical microscope at both locations, and the two sets of measurement, were found to be in reasonable agreement with each other. For a more complete discussion on measuring the material parameters of magnetic films, see Reference 3.

Table 1. Material Parameters for the Sample Used

h (film thickness)	4.5 μm
$4\pi M$ (saturation magnetization)	57 G
H_u (uniaxial anisotropy field)	351 Oe.
ℓ (characteristic length)	1.125 μm
α (Gilbert damping parameter)	1.98×10^{-3}
γ (gyromagnetic ratio)	$1.886 \times 10^7 \text{ Oe}^{-1} \text{ sec}^{-1}$

CHAPTER 4

EXPERIMENTAL RESULTS AND ANALYSIS OF DATA

Data was taken on the domain wall resonance frequency of an array of parallel stripe domains as a function of in-plane magnetic field H_p and as a function of ξ , the angle between H_p and the domain walls, using the RF spectrometer described in Chapter 3. A typical scan of power at the output of the structure vs. frequency is shown in Figure 4.1. The wall resonance signal is at the center of the scan and the broad peak in the frequency response is due to standing waves in the spectrometer cables. This baseline can be acquired with the sample saturated by a large in-plane field and then subtracted from a scan to enhance the wall resonance signal, as shown in Figure 4.2. As the in-plane magnetic field is decreased, the intensity of the domain wall resonance signal decreases, going to nearly zero at zero in-plane magnetic field. Figure 4.3 shows the wall resonance signal for a very low in-plane field. At large in-plane magnetic fields, domain wall motion can excite elastic¹ modes in the substrate. These appear as very narrow

Figure 4.1. Domain wall resonance signal for $H_p = 80$ Oe. The signal is superimposed on a baseline which H_p is due to standing waves in the spectrometer cables.

Figure 4.2. Domain wall resonance signal for $H_p = 80$ Oe. Here, the baseline has been subtracted, leaving only the wall resonance signal.

Figure 4.3. Domain wall resonance signal for $H_p = 10$ Oe. The center frequency of the signal is 12.86 MHz.

line width resonances superimposed on the domain wall signal, as is shown in Figure 4.4.

Domain wall resonance frequency was measured directly from the computer plots of the data. The overall accuracy of the measured resonance frequency, taking into account the accuracy of measuring the frequency from the plot, the uncertainty in the setting of H_p , and the reproducibility of the resonance signal, is estimated to be about one percent.

Section 4.1 - H_p Applied Parallel to the Domain Walls

Figure 4.5 shows the domain wall resonance frequency as a function of in-plane field. The hysteresis in the resonance frequency is due to hysteresis in the stripe period, $L_1 + L_2$, as shown in Figure 4.6.²

In comparing the wall mass to the data for the wall resonance frequency, it is more convenient to plot the ratio of the resonance frequency to the resonance frequency at zero in-plane magnetic field, obtained by extrapolating the f vs. H_p curve to $H_p = 0$. This is due to the fact that inaccuracies in the measured values of the material parameters of the sample make it difficult to calculate reliable values of the Döring mass and the restoring force constant. Thus the calculated resonance

Figure 4.4. Domain wall resonance signal for $H_p = 210$ Oe. The narrow resonances superimposed on the main resonance are magneto-elastic modes.

Figure 4.5. Domain wall resonance frequency vs. in-plane field. The crosses indicate increasing H_p ; the circles indicate decreasing H_p .

Figure 4.6. $L_1 + L_2$ vs. H_p . The solid curve is for H_p increasing, the dashed curve is for H_p decreasing.

frequency does not generally agree with the experimental data. By scaling the resonance frequencies to the frequency at $H_p=0$, the differences in the absolute values of the Döring mass and the force constant are removed and all that remains is the dependence of these quantities on H_p , which is easy to calculate. Figure 4.7 shows the reduced resonance frequency, f/f_0 , vs. the reduced in-plane magnetic field, H_p/H_u . Figure 4.8 shows the same data, along with the theoretical curve calculated using the model for the effective mass for a Bloch wall, reviewed in section 2.2. The agreement of theory with experiment is very poor, in as much as the two curves have different shapes and are going in opposite directions for large H_p .

Figure 4.9 shows the data along with a theoretical curve based on taking into account the effect on the mass of the variation of the wall's internal structure through the film thickness as discussed in section 2.4. In this model the effective mass at zero H_p is double the value of the Döring mass but very quickly approaches the mass given by equation 1 as H_p approaches $8M=.1H_u$. This model is expected to be valid only for low H_p and the model's agreement with the data for small fields is better. However, the overall shape of the theory curve remains unchanged, and overall the fit is still very poor.

Figure 4.7. Reduced resonance frequency vs. reduced in-plane field.

Figure 4.8. Reduced resonance frequency vs. reduced in-plane field. The solid curve is the theoretical prediction for the Bloch wall model of the effective mass.

Figure 4.9. Reduced resonance frequency vs. reduced in-plane field. The solid curve is the theoretical prediction for a Bloch wall which takes the effects of surface charges on the wall structure into account.

Figure 4.10 shows the data along with the theory curve calculated using the model of Wigen and Dötsch, in which the field dependence of the wall width is included, as described in section 2.5. The fit here is the poorest of all the models examined.

Figure 4.11 shows the data and a theory curve calculated using O'Dell's expression for the effective mass, equation 2.6.7. The agreement between theory and experiment is much better in this case, as the frequency increases for large H_p instead of decreasing, as it does for the models previously examined. However, the agreement still seems to be qualitative at best. The results of section 2.4 suggest that, due to the variation of the wall structure induced by the surface demagnetization fields, the zero field mass should be $2m_D$. Figure 4.12 shows the same theoretical curve as in Figure 4.11 except that the mass at zero in-plane field is doubled. This significantly improved the fit between theory and data. This improvement suggests that for $H_p \ll 4\pi M$, it is important to consider the effect of surface fields on the effective mass of the wall. The overall qualitative agreement between O'Dell's model and the experimental data indicates that the change in the static wall structure as an in-plane magnetic field is applied is the major contribution to the dependence of the wall mass on in-plane magnetic field.

Figure 4.10. Reduced resonance frequency vs. reduced in-plane field. The solid curve is the theoretical prediction based on the model of Wigen and Dötsch, as discussed in section 2.5.

Figure 4.11. Reduced resonance frequency vs. reduced in-plane field. The solid curve is the theoretical prediction of O'Dell's model.

Figure 4.12. Reduced resonance frequency vs. reduced in-plane field. The solid curve is the theoretical prediction based on O'Dell's model, modified by setting the zero field mass to $2m_D$, as discussed in the text.

Figure 4.13 shows the dependence of the wall resonance frequency on in-plane field obtained using Morkowski's model of the domain wall mass, where the y dependence of ψ is explicitly included in the calculation of the effective mass of the domain wall. Here, as with O'Dell's model, qualitative agreement between experiment and theory is obtained. Figure 4.14 shows the same curve only assuming $m_0 = 2m_D$, as was done with Figure 4.12. Here there seems to be reasonable agreement between theory and data--certainly much better than obtained with any other model proposed for the effective wall mass. Instead of plotting f/f_0 , it is possible to convert resonance frequencies to masses, using the calculated values for y and E_{xx} . Figure 4.15 shows such a plot, along with Morkowski's model for the wall mass modified to take into account the effects of wall structure at low fields. Morkowski³ indicates that taking into account higher order terms in H_p will cause the theoretical curve to bend over for large H_p , further improving the fit between theory and experiment.

Section 4.2 - Angular Dependence

Of the various models for the wall mass, only the simplest model, the Bloch wall model discussed in

Figure 4.13. Reduced resonance frequency vs. reduced in-plane field. The solid curve is the theoretical prediction based on Morkowski's expression for the wall mass.

Figure 4.14. Reduced resonance frequency vs. reduced in-plane field. The solid curve is the theoretical prediction based on Morkowski's model of the wall mass modified by doubling the zero field mass, as discussed in the text.

Figure 4.15. Effective wall mass vs. reduced in-plane field. The solid curve is Morkowski's expression for the wall mass modified to take the effects of surface charges into account.

section 2.2. provides a model for the mass as a function of angle between H_p and the wall.

The expression for the wall mass obtained in section 2.2 is

$$\frac{1}{m} = \frac{1}{m_D} (\cos 2\xi + H_p/8M) \quad (4.1)$$

$(H_p > 8M)$

This indicates that $1/m$ should depend on ξ , the angle between H_p and the domain wall, as $\cos 2\xi$. Wall resonance frequency as a function of angle was measured at several values of H_p . From the measured resonance frequencies, the values of $1/m$ were obtained using E_{xx} and $L_1 + L_2$ calculated as outlined in section 2.3. A least squares fitting program⁴ was then used to fit the data to a series of Legendre polynomials of the form $\sum_{n=0}^{\infty} a_n P_n (\cos 2\xi)$ to obtain the angular dependence of $1/m$. It was not possible to obtain data at all angles for all values of H_p used, particularly for large values of H_p , because of the difficulty of maintaining an array of parallel stripes with H_p applied at an angle to the walls. The domains have a tendency to reorient themselves parallel to H_p or buckle, leaving a zig-zag pattern of stripes.

Typical angular dependence of $1/m$ is shown in Figure 4.16 for $H_p=30$ Oe and in Figure 4.17 for $H_p=60$ Oe. The results of the least squares fitting procedure are listed in Table 2. In no case was it necessary to use any term of higher order than $\cos 2\xi$ in the analysis to obtain a good fit to the data, so that the prediction of equation 1 for the angle dependence of the mass is confirmed. As can be seen from Table 2 both of the coefficients a_0 and a_1 depend on in-plane field and are graphed in Figure 4.18 for a_0 and in Figure 4.19 for a_1 . These coefficients were fit to H_p using a linear least squares fit. The results of this fit are shown in Table 3. Labeling the intercept for a_0 as b_0 and the slope as c_0 and similarly labeling the intercept and slope for a_1 as b_1 and c_1 , equation 1 predicts that $b_0=c_1=0$ and that $b_1 = \frac{1}{m_D}$ and $c_0 = \frac{1}{8Mm_D}$. A comparison of these values, shown in the "predicted" section of Table 3, with the experimental values of these coefficients indicates that the data does not agree in any quantitative manner with equation 1. The effective wall mass as a function of the in-plane field H_p and at $\xi=0^\circ$ normalized to the mass at $H_p=0$ is shown in Figure 4.20. The solid line is a least square fit to the lowest 4 data points, and has a slope of $.140 \text{ Oe}^{-1}$. Using the values of c_0 and c_1 given for the experimental data in Table III gives a slope of m_0/m vs. H_p at $\theta=0^\circ$

Figure 4.16. $1/m$ vs. ξ the angle between H_p and the plane of the wall, for $H_p = 30 \text{ Oe}$. The solid curve is the least squares fit of a Legendre polynomial in $\cos^2 \xi$ to the data.

Figure 4.17. $1/m$ vs. ξ for $H_p = 60 \text{ Oe}$. The solid curve is the least squares fit of a Legendre polynomial in $\cos 2\xi$ to the data.

Figure 4.18. a_0 vs. H_p . The solid line is a least squares fit through the first 4 points.

Figure 4.19. a_1 vs. H_p the solid line is a least squares fit to the data.

Figure 4.20. Reduced effective mass vs. in-plane field.

of $.175 \text{ Oe}^{-1}$, indicating that the field dependence of the angular fit coefficients are consistent with the experimental data, even though inconsistent with the simple theory.

Table 2. Least Squares Fit Parameters for
Fitting $\frac{1}{m}$ to $a_0 + a_1 \cos 2\xi$

H_p (Oe)	a_0 ($10^{11} \text{cm}^2/\text{g}$)	a_1 ($10^{11} \text{cm}^2/\text{g}$)	χ^2	Confidence Level
30	$.93 \pm .023$	$.16 \pm .031$	1.01	91%
40	$1.188 \pm .035$	$.275 \pm .047$	1.74	93%
50	$1.47 \pm .09$	$.26 \pm .13$	11.5	52%
60	$1.756 \pm .045$	$.261 \pm .058$	.805	83%
100	$3.425 \pm .04$	$.424 \pm .06$	1.13	96%

Table 3. Least squares fit of
 a_0 and a_1 to $b + c H_p$

	b ($10^{11} \text{cm}^2/\text{g}$)	c ($10^{11} \text{cm}^2/\text{g-Oe}$)
Experimental		
a_0	$.1042 \pm .004$	$.0274 \pm 3 \times 10^{-6}$
a_1	$(7.248 \pm .231) \times 10^{-2}$	$(3.55 \pm .0009) \times 10^{-3}$
Predicted		
a_0	0	.0049
a_1	.178	0

CHAPTER 5

CONCLUSIONS

Domain wall resonance frequency has been measured for parallel stripe domains as a function of in-plane magnetic field H_p and as a function of the angle ξ between H_p and the domain walls. The data have been compared to theoretical predictions based on various models of the wall mass. The simplest model, the Bloch wall model, has been found to be inadequate to explain the field dependence of the wall's effective mass. This finding is not surprising, however, as the Bloch wall model does not take into account the change in the wall profile as an in-plane field is applied. Those models which do explicitly take this change into account do much better at fitting the experimental data. Morkowski's model, which in addition to taking the change in the wall profile into account explicitly allows ψ to vary across the wall, seems to best fit the experimental data.

Even with the best fit model, the fit of the data to the theory is still less than exact. This may be

due to inadequacies in the model or, as seems more likely, to inadequacies in the method of calculating the restoring force constant, $\frac{\gamma E_{xx}}{\pi t^2}$. It may be possible to obtain reliable experimental measurements of this quantity, and such measurements would probably improve the fit of theory to experiment.

Also a factor is the hysteresis in $L_1 + L_2$, which will cause an uncertainty in the measured resonance frequency. This hysteresis can be reduced if not completely eliminated by applying a modulation to the in-plane field.

In all cases, it has been found that the variation of ψ in the wall as a function of position in the film thickness has an important effect on the wall mass. This effect essentially disappears, however, when H_p becomes larger than $8M$, so that it is significant only at very small values of the in-plane field.

The angular dependence of the effective domain wall mass has been found to be of the form

$$\frac{1}{m} = a_0(H_p) + a_1(H_p) \cos 2\xi \quad (5.1)$$

The coefficient a_0 was found to rise with H_p , linearly for small H_p and faster than linearly for larger values of H_p . The angle dependent coefficient a_1 was found to vary linearly with H_p , although the uncertainties in the

values of a_1 for various values of H_p make the quality of the fit to H_p somewhat poor.

Further studies in this area could include efforts to experimentally determine the restoring force constant, attempting to improve the measurement of the angle dependence, evaluate relaxation processes by measuring the line width of the domain wall resonance as a function of in-plane field and angle, and studying the magneto-elastic modes seen at high in-plane fields.

LIST OF REFERENCES

Chapter 1

1. C. Kooy and U. Enz, Philips Res. Repts. 15, 7 (1960).
2. A.H. Bobeck, Bell Syst. Tech. J. 46, 1901 (1967).
3. A.H. Bobeck and H.E.D. Scovil, Scientific American 224, 78 (June 1971).
4. A.H. Bobeck and E. Della Torre, Magnetic Bubbles (Amsterdam, New York, North Holland, American Elsevier, 1975).
5. T.H. O'Dell, Magnetic Bubbles (New York, John Wiley & Sons, 1974).
6. W. Döring, Z. Naturforsch A3, 373 (1948).
7. G.T. Rado, R.W. Wright and W.H. Emerson, Phys. Rev. 80, 273 (1950).
8. H.P.J. Wijn, Physica 19, 555 (1953).
9. T.M. Perekalina, A.A. Askochinski and D.G. Sannikov, Sov. Phys. Sol. St. (JETP) 13, 303 (1961).
10. G.P. Vella-Coleiro, D.H. Smith and L.G. Van Uitert, J. Appl. Phys. 43, 2428 (1972).
11. B.E. Argyle and A. Halperin, IEEE Trans. Mag. MAG9, 238 (1973).
12. F.H. de Leeuw, J. Appl. Phys. 45, 3106 (1974).
13. F.B. Humphrey, IEEE Trans. Mag. MAG11, 1679 (1975).
14. B.E. Argyle and A.P. Malozemoff, AIP Conf. Proc. 10, 344 (1972).
15. R.W. Shaw, J.W. Moody and R.M. Sandfort, J. Appl. Phys. 45, 2672 (1974).

16. F.H. de Leeuw and J.M. Robertson, J. Appl. Phys. 46, 3182 (1975).
17. B.E. MacNeal and F.B. Humphrey, J. Appl. Phys. 50, 1010 (1979).
18. H. Dötsch, H.J. Schmitt and J. Müller, Appl. Phys. Lett. 23, 639 (1973).
19. P.E. Wigen and H. Dötsch, Phys. Stat. Sol., to be published.

Chapter 2

1. J.C. Slonczewski, Intern. J. Magnetism 2, 85 (1972).
2. L. Landau and E. Lifshitz, Physik A. Soviet Union 8, 153 (1935).
3. T. Gilbert, Armour Research Foundation Report #11 (1955) (unpublished).
4. S. Chikazumi, Physics of Magnetism (John Wiley & Sons, New York, 1964).
5. F. de Jonge and W. Druyvesteyn, Festkörperprobleme XII, 531 (1972).
6. P. Limaye, private communication.
7. A. Hubert, J. Appl. Phys. 46, 2276 (1975).
8. F.B. Humphrey, private communication.
9. T.J. Gallagher and F.B. Humphrey, private communication (modified extensively by A. Parker).
10. P.E. Wigen and H. Dötsch, Phys. Stat. Soli., submitted for publication.
11. T.H. O'Dell, Phys. Stat. Sol. (a) 54, 429 (1979).
12. T.H. O'Dell, Phys. Stat. Sol. (a) 48, 59 (1978).
13. P.E. Wigen, private communication.
14. J. Morkowski, to be published.

Chapter 3

1. H. Dötsch and P.E. Wigen, Solid St. Comm 30, 611 (1979).
2. H. Dötsch, H.J. Schmitt and J. Müller, Appl. Phys. Lett. 23, 639 (1973).
3. R.M. Josephs, AIP Conf. Proc. 10, 286 (1972).

Chapter 4

1. H. Dötsch, H.J. Schmitt and J. Müller, Appl. Phys. Lett. 23, 639 (1973).
2. R.J. Yeh, private communication.
3. J. Morkowski, private communication and to be published.
4. P.R. Bevington, Data Reduction and Error Analysis for the Physical Sciences (McGraw Hill, New York, 1969).

APPENDIX A

CALCULATION OF THE
DEMAGNETIZATION ENERGY IN THE STATIC CASE

According to Maxwell's equations,

$$\nabla \cdot \vec{B} = 0 \quad (\text{A.1})$$

so that, if $\vec{H}^D$ is the demagnetization field,

$$\nabla \cdot \vec{H}^D = -4\pi \nabla \cdot \vec{M} \quad (\text{A.2})$$

If $\vec{M}$ is uniform in the x-z plane, then

$$\nabla \cdot \vec{M} = \frac{\partial M_Y}{\partial Y} \quad (\text{A.3})$$

so

$$\frac{\partial H_Y^D}{\partial Y} = -4\pi \frac{\partial M_Y}{\partial Y} \quad (\text{A.4})$$

and thus

$$H_Y^D = -4\pi M_Y + C \quad (\text{A.5})$$

The integration constant C is determined by the boundary condition that $H^D \rightarrow 0$ and $y \rightarrow \pm \infty$ so

$$C = 4\pi M_Y^0 \quad (A.6)$$

and

$$= 4\pi (M_Y^0 - M_Y) \quad (A.7)$$

The demagnetization energy is

$$\begin{aligned} w_D &= \frac{1}{2} \vec{H}^D \cdot \vec{M} \\ &= 2\pi H_Y^D M_Y \\ &= 2\pi (M_Y (M_Y^0 - M_Y)) \end{aligned} \quad (A.8)$$

Since

$$M_Y = M \sin\theta \sin\psi \quad (A.9)$$

and

$$M_Y^0 = M \sin\theta_0 \sin\psi_0 \quad (A.10)$$

so

$$w_D = 4\pi M^2 (\sin\theta \sin\theta_0 \sin\psi \sin\psi_0 - \sin^2\theta \sin^2\psi) \quad (A.11)$$

APPENDIX B

CALCULATION OF THE STATIC WALL ENERGY
WITH AN IN-PLANE FIELD APPLIED ALONG
THE PLANE OF THE WALL

The wall energy density is

$$\begin{aligned}
 \sigma = & \int_{-\infty}^{\infty} \{ A\theta_Y^2 + A\psi_Y^2 \sin^2 \theta + K_u (\sin^2 \theta - \sin^2 \theta_O) \\
 & + 2\pi M_O^2 (\sin^2 \psi \sin^2 \theta - \sin \theta \sin \theta_O \sin \psi \sin \psi_O) \\
 & - H_p M_O (\sin \theta \cos(\psi - \psi_O) - \sin \theta_O) \} dy
 \end{aligned} \tag{B.1}$$

If $\psi=0$ everywhere (i.e. $H_Y=0$) then this reduces to

$$\sigma = \int_{-\infty}^{\infty} \{ A\theta_Y^2 + K_u (\sin^2 \theta - \sin^2 \theta_O) - H_p M_O (\sin \theta - \sin \theta_O) \} dy \tag{B.2}$$

In order to evaluate this integral it is necessary to evaluate θ_Y . This can be obtained from the Euler equation

$$\frac{\delta \sigma}{\delta \theta} = 0 \tag{B.3}$$

Performing the functional derivative and rearranging gives

$$\frac{\partial f}{\partial Y} = \theta_Y \frac{\partial}{\partial Y} \frac{\partial f}{\partial \theta_Y} \tag{B.4}$$

where

$$f = A\theta_Y^2 + A\psi_Y^2 \sin^2 \theta + K_u (\sin^2 \theta - \sin^2 \theta_O)$$

$$\begin{aligned}
& + 2 M_O^2 (\sin^2 \psi \sin^2 \theta - \sin \theta \sin \theta_O \sin \psi \sin \psi_O) \\
& - H_p M_O (\sin \theta \cos(\psi - \psi_O) - \sin \theta_O)
\end{aligned} \tag{B.5}$$

Integrating equation 4 gives

$$c + f = 2A\theta_Y^2 \tag{B.6}$$

where c is a constant of integration, which can be evaluated by examining the boundary conditions. Far away from the wall, $\theta_Y = \psi_Y = 0$ and $\theta = \theta_O$, $\psi = \psi_O$. Thus, $f = 0$ and the value of the integration constant is $c = 0$.

If $\psi_Y = \psi = 0$ then equation 6 reduces to

$$A\theta_Y^2 = K_u (\sin^2 \theta - \sin^2 \theta_O) - H_p M_O (\sin \theta - \sin \theta_O) \tag{B.7}$$

and equation 2 becomes

$$\sigma = 2 \int_{-\infty}^{\infty} \{K_u (\sin^2 \theta - \sin^2 \theta_O) - H_p M_O (\sin \theta - \sin \theta_O)\} dy \tag{B.8}$$

Changing the variable of integration to θ and taking note of the fact that $dy = \frac{dy}{d\theta} d\theta$, and making use of equation 7, equation 8 becomes

$$\begin{aligned}
\sigma = 2 \int_{\theta_O}^{\pi - \theta_O} & \frac{1}{A^2} \{K_u (\sin^2 \theta - \sin^2 \theta_O) \\
& - H_p M_O (\sin \theta - \sin \theta_O)\}^{\frac{1}{2}} d\theta
\end{aligned} \tag{B.9}$$

Since $\sin\theta_o = \frac{H_p}{H_u}$, $H_p = H_u \sin\theta_o = \frac{2K_u}{M_o} \sin\theta_o$ and the

second term in the integrand becomes

$$\begin{aligned} H_p M_o (\sin\theta - \sin\theta_o) &= 2K_u \sin\theta_o (\sin\theta - \sin\theta_o) \\ &= -2K_u \sin^2\theta_o + 2K_u \sin\theta_o \sin\theta \end{aligned} \quad (B.10)$$

Substituting equation 10 into equation 9 gives

$$\begin{aligned} \sigma &= 2K_u \Delta_o \int_{\theta_o}^{\pi-\theta_o} (\sin^2\theta - 2\sin\theta \sin\theta_o + \sin^2\theta_o)^{\frac{1}{2}} d\theta \\ &= 2K_u \Delta_o \int_{\theta_o}^{\pi-\theta_o} (\sin\theta - \sin\theta_o) d\theta \end{aligned} \quad (B.11)$$

where $\Delta_o = (A/K_u)^{\frac{1}{2}}$

Performing the integral gives the result

$$\sigma = 2K_u \Delta_o (2\cos\theta_o - (\pi - 2\theta_o) \sin\theta_o) . \quad (B.12)$$

APPENDIX C

PROGRAM FOR
CALCULATING $L_1 + L_2$ AND E_{xx}/t

```

0 : "finds Exx, X, and stores them":
1 : dim S[50], X[50]; 1→U; rad
2 : ent "lower limit of Hip", r4, "upper limit of Hip", r5, "interval", r6; r4→P
3 : ent "4πM", M, "Hk", H, "thickness", T, "1/t", J
4 : "4πM→M, Hip→P, Hu→H, 1/t→J, Thick→T, Delta0→W":
5 : M/4π→M; 1.051799778→Q; 2πJTM/H→W; HM/2→G
6 : dim E[2]; 1→A
7 : "N": Mf (1-PP/HH)→Z; 0→S→N→C; asn (P/H)→V
8 : .09901→D; 1e-10→E; A→X; gsb "Eval"
9 : if abs(Y)<E; sfg 2; gto "0"
10: Y→F
11: "E": A+D→A→X; gsb "Eval"; if A>=20; dsp "No Root"; stp
12: if abs(Y)<E; sfg 2; gto "0"
13: if YF<0; gto "A"
14: Y→F; gto "E"
15: "A": A-D→L; A→R
16: "D": if (C+1→C)>16; sfg 1; gto "0"
17: (L+R)/2→X; gsb "Eval"
18: if abs(Y)<E; sfg 2; gto "0"
19: if FY<0; X→R; gto "D"
20: X→L; Y→F; gto "D"
21: "0": if flg1; prt "Y eq", X, "Accuracy", R-L; spc 2
22: if flg2; prt "Y eq", X, "Error <1e-9"; spc 2
23: for I=1 to 21; (-1)I→I*exp(-IX)/I+S→S
24: 2I-1→K; (-2+2KX+KKXX)*exp(-KX)/KKK+N→N
25: next I
26: 4πZZ(1+2/X*(-ln(2)-S))→E[1]
27: 16ZZ/πXXX*(2Q-N)→E[2]
28: prt "Hip", P, "Exx", E[1], "Eyy", E[2]; spc ; prt "-----"; spc
29: E[1]→S[U]; X→X[U]; U+1→U
30: if (P+r6→P)<r5+r6; X→A; cfg 1; cfg 2; gto "N"
31: trk 1; ref 2, X[*]
32: ref 3, S[*]
33: end
34: "Eval": 0→B
35: for I=1 to 31 by 2; exp(-IX)*(1+IX)/III+B→B; next I

```

```
36: 2GW(2cos(V)-(pi-2V)sin(V))/16TZZ-(1/XX*(Q-B)+r2)+Y  
37: ret
```

APPENDIX D

PROGRAM TO
CALCULATE DOMAIN WALL STRUCTURE


```

0 : "wall structure(Gallagher)2-16-80":
1 : wrt 705, "IP2192, 2047, 9018, 5932"
2 : dim X$(10), M(0:100, 0:3)
3 : dim D(0:100), S(0:100)
4 : rad; scl 0, 1, -pi, pi; cfg 2
5 : ent "track with data?", T; trk T
6 : ent "file to load?", F; ldf F, D[*]
7 : ldf F, S[*]
8 : ent "file to store? (not files 0-4)", F
9 : ent "4piM", M, "Hk", K, "angle(rad)", A, "thickness", S, "1/t", L
10: ent "in-plane field", B; ent V
11: ent "2pi t/(L1+L2)", W; W/2->W
12: Bpi/M->B; 8e-4*K/MLL->C; asin(BM/piK)->Q; cos(Q)->Q
13: ent "free=0, B=1, T=2", T
14: ina M
15: "test": 0->M(0, 0)->M(100, 2)->M(0, 3)->M(100, 3)
16: if T=0; 1->M(0, 1)->M(100, 0); -1->M(0, 2)->M(100, 1)
17: if T=1; 1->M(0, 1)->M(100, 0); -1->M(100, 1); 0->M(0, 3)
18: if T=2; 1->M(0, 1)->M(100, 1); -1->M(0, 3); 0->M(100, 0)
19: for I=1 to 99
20: 1->M(I, 2)
21: I/100->X
22: if flg2; goto "start"
23: L*S*M/K->D; exp(S/2D)+exp(-S/2D)->Y
24: X-.5->X; X-D/(S*Y)*(exp(XS/D)-exp(-XS/D))->r0
25: W(r0+.5)->r1
26: (exp(2r1)-1)/(exp(2r1)+1)->r2
27: W(.5-r0)->r3
28: (exp(2r3)-1)/(exp(2r3)+1)->r4
29: Qln(r2/r4)->M(I, 0); X+.5->X
30: "start":
31: Bcos(A)sin(D[I])- (M(I, 0)-Bsin(A))cos(D[I])+sin(2D[I])-V->Z
32: Z-(D[I+1]+D[I-1]-2D[I])/C->Z
33: C*Z->M(I, 3)
34: Bcos(A)cos(D[I])+ (M(I, 0)-Bsin(A))sin(D[I])+2cos(2D[I])->R
35: -C*R-2->M(I, 1)

```

```

36: next I
37: if flg2=0; sfg 2
38: for I=1 to 100
39: if M[I-1,1]=0; prt "fail"; stp
40: 1/M[I-1,1]→r5; if I=100; M[100,0]/M[I-1,1]→r5
41: M[I,1]→r5*M[I-1,2]→M[I,1]
42: M[I,3]→r5*M[I-1,3]→M[I,3]
43: next I
44: if M[100,1]=0; prt "fail"; stp
45: M[100,3]/M[100,1]→D[100]
46: 0→r6
47: for I=99 to 0 by -1
48: (M[I,3]-M[I,2]*D[I+1])/M[I,1]→D[I]
49: abs(D[I])→r6→r6
50: next I
51: ara D+S→D; ara D→S
52: if r6<=1e-6; gto "ave"
53: gto "test"
54: "ave": 0→P
55: for I=1 to 99
56: D[I]/100→P→P
57: next I
58: (D[0]+D[100])/200→P→P; fxd 3
59: prt V; fxd 7; prt P; spc 1
60: fdf F; mrk 1,900
61: rcf F, D[*]
62: pen# 1; fxd 1; csiz 2.2,2
63: xax 0,.1,0,1; xax 3.14,.1; xax -3.14,.1; yax 0,.314,-π,π,2; yax 1,.314; pen
64: for X=.1 to .9 by .2
65: str(X)→X$
66: if X$[1,1]=" "; X$[2]→X$
67: plt X,0,0
68: cplt -.5len(X$),-1.25
69: lbl X$
70: pen
71: next X

```

```

72: pen; plt .5, 4, 0; fxd 4; csiz 2, 2
73: cplt -31, 0; lbl "V = ", V; pen; cplt 3, 0
74: fxd 1; lbl "Hk = ", K; pen; cplt 3, 0; lbl "in-plane field = ", BM/ $\pi$ ; pen
75: cplt 3, 0; wrt 705, "CA1"; wrt 705, "SA"; lbl "4 $\pi$ M = ", M; pen; plt .5, 3.6, 0
76: cplt -35, 0;  $\Lambda * 180 / \pi \rightarrow \Lambda$ ; lbl "in-plane field angle = ",  $\Lambda$ , " deg"; pen; cplt 3, 0
77: flt 3; lbl "thickness = ", S; pen; cplt 3, 0; fxd 3
78: lbl "1/t = ", L
79: plt .5, 3.3, 0; fxd 5
80: cplt -26, 0; lbl "average azimuthal angle = ",  $P * 180 / \pi \rightarrow P$ ; lbl P, " deg"
81: pen; cplt 3, 0; fxd 0; lbl "file no. = ", F
82: for I=0 to 100
83: plt I/100, DIII
84: next I
85: pen# 0
86: stp
87: end

```

APPENDIX E

SYSTEM PROGRAM

```

0 : "RF spectrometer v. 2.3 10/18/79":
1 : dim A[250]
2 : dim S$[12], D$[8]
3 : dim A, B, C
4 : dim H[2]
5 : dim B[250], C[250]; dim A$[6]
6 : ldk 1
7 : wrt 705, "IP1312, 952, 9733, 6966"; csiz 2, 2
8 : cll 'init DAS'
9 : cll 'new'
10: cll 'det cal'
11: cll 'CB';stp
12: "1":cll 'save';cll 'CB';stp
13: "2":cll 'retrieve';cll 'CB';stp
14: "3":cll 'set in plane field';cll 'CB';stp
15: "4":cll 'set bias field';cll 'CB';stp
16: "5":cll 'take data';cll 'CB';stp
17: "6":cll 'plot';cll 'CB';stp
18: "7":cll 'lable';cll 'CB';stp
19: "8":cll 'axes';cll 'CB';stp
20: "9":cll 'new';cll 'CB';stp
21: "10":cll 'prt status';cll 'CB';stp
22: "11":cll 'baseline';cll 'CB';stp
23: "12":ent "frequency [MHz]="; J; cll 'set freq'(J); cll 'CB';stp
24: "13":ent "attenuation [dB]="; J; cll 'set att'(J); cll 'CB';stp
25: "14":cll 'fast scan';cll 'CB';stp
26: "15":cll 'signal average';cll 'CB';stp
27: "CB":dep "COMMAND";beep;ret
28: "prt status":
29: fmt "samples:",/,c12;wrt 16,S$
30: fmt "dates:",c8;wrt 16,D$
31: fmt "start frequency:",/,2x,f7.3," MHz";wrt 16,A
32: fmt "stop frequency:",/,2x,f7.3," MHz";wrt 16,B
33: fmt 5,"in plane field",/,4x,f6.1," Oe";wrt 16.5,'Hp'→H[1]
34: fmt 5,"bias field",/,4x,f5.1," Oe";wrt 16.5,'Hb'→H[2]
35: fmt c1,"=",f4.0," degrees";wrt 16,char(16),T

```

```

36: fmt ;opc 2;ret
37: "new":
38: ent "sample",S$
39: ent "date",D$
40: ent "theta",T
41: ret
42: "baseline":
43: cll 'set in plane field'
44: cll 'signal average'
45: ara A→B
46: ret
47: "plot":
48: csiz 2,2
49: max(A[*])→D
50: min(A[*])→E
51: D+sgn(D)*.5D→D
52: E-sgn(E)*.5E→E
53: scl A,B,E,D
54: l→p1;pen# 3
55: plt A+p1C,A[p1]
56: jmp -1+2((p1+1→p1)=250)
57: pen
58: ret
59: "axes":
60: xax E,25C,A,B
61: yax A,(D-E)/10,E,D
62: cll 'lable'
63: ret
64: "lable":
65: fxd 1
66: 0→p1
67: str(A+25Cp1)→A$
68: plt A+25Cp1,E,0
69: cplt -.5len(A$),-1.5;lbl A$
70: jmp -3+4((p1+1→p1)=11)
71: l→p1;(D-E)/10→p2;fxd 2

```

```

72: str(E+p1p2)→A$
73: plt A,E+p1p2,0
74: cplt -(len(A$)+2),-.5
75: lbl A$
76: jmp -4+5((p1+1→p1)=11)
77: plt A+125C,D,0
78: cplt -(8.5+.5len(S$)+.5len(D$)→p1),3
79: lbl "SAMPLE: ",S$,"    DATE: ",D$
80: cplt -p1-14,-1
81: fxd 1;lbl "Hp = ",H[1]," 0e    Hb = ",H[2]," 0e"
82: cplt -p1-10,-1;lbl "0";cplt -1,0;lbl "- =",T," DEGREES"
83: if flg1;plt B,D,0;cplt -21,0;lbl "RECORDED ON FILE # ",F
84: pen# 0
85: ret
86: "retrieve":
87: ent "load data from file # ?",F
88: trk 1;ldf F,A[*],S$,D$,A,B,C,H[*],T
89: sfg 1
90: ret
91: "save":
92: ent "record on file # ?",F
93: fdf F;idf L,M,N,0
94: if M#0;dep "file already used";beep;wait 3000;gto -2
95: if 0=0;mrk 1,2100
96: rcf F,A[*],S$,D$,A,B,C,H[*],T
97: sfg 1
98: ret
99: "set in plane field":
100: ent "Hp?",X
101: cll 'set Hp'(X)
102: 'Hp'→H[1]
103: ret
104: "set bias field":
105: cfg 2
106: dep "manually adjust bias field";wait 3000
107: dep "then hit ""Hb set"" ";wait 3000

```

```

108: dep "Hb = ", 'Hb'; jmp flg2
109: dep ; 'Hb'→H[2]
110: ret
111: "signal average":
112: ent "number of scans?", N
113: ina C
114: for O=1 to N
115: cll 'take data'
116: ara A+C→C
117: next O
118: 1/N→N; empty N→C→A; Ø→O
119: ret
120: "take data": lkd
121: (B-A)/250→C
122: if C=Ø; dep "set start and stop freq. 'e'; beep; jmp Ø
123: prnd(A, -3)→G; prnd(B, -3)→H; prnd(C, -3)→C
124: G+250C→H
125: cll 'set gain' (Ø)
126: fxd Ø; cll 'set ch' (4)
127: fmt 1, "ch. ", f3. Ø, 1x, f7.3, " MHz", 3x, "scan #", f2. Ø
128: for J=1 to 250
129: wrt .1, J, G+JC, Ø
130: cll 'set freq' (G+JC)
131: cll 'set DAC' (.Ø4J)
132: 'power'→A[J]
133: next J
134: cfg 1; cfg 4
135: cll 'set gain' (Ø)
136: lke ; ret
137: "fast scan":
138: (B-A)/100→C
139: prnd(A, -3)→G; prnd(B, -3)→H; prnd(C, -3)→C
140: G+100C→H
141: for J=1 to 100
142: cll 'set freq' (G+JC)
143: cll 'set DAC' (.1J)

```



```

144: next J
145: ret
146: "set Hp":
147: ((p1+3.9)/.9139-1366.2)/-2.7→p2; int(2000+p2)→p2
148: fmt f4.0,z; wrt 706,p2; wait 200
149: 'Hp'→p3
150: if abs(p3-p1)>1.5; p2+sgn(p3-p1)→p2; gto -2
151: fmt ; ret
152: "Hp":
153: cll 'set ch'(2)
154: 'volts'→p1
155: p1*3000→p1; -3.9+.9139p1→p1; ret p1
156: "init DAS":
157: buf "buffer",250,3
158: dim Q$(12); dim V(34)
159: "000000001000"→Q$
160: fmt 9,c12
161: wrt 720,9,Q$
162: ret
163: "set freq":
164: 1000p1→p2; 6→p4
165: int(10frc(p2/10→p2))→p3
166: char(p3+48)→Q$(p4+6,p4+6)
167: jmp -2+3((p4-1→p4)=0)
168: fmt c12; wrt 720,Q$
169: ret
170: "set gain":
171: p1/10→p2; if p2>6 or p1<0; gto +2
172: char(p2+48)→Q$(6,6)
173: fmt c12; wrt 720,Q$
174: ret
175: "set att":
176: p1/10→p2; 0→p3; if p2>12; gto +7
177: if p2>=6; 8+p3→p3; p2-6→p2
178: if p2>=3; 4+p3→p3; p2-3→p2
179: if p2>=2; 2+p3→p3; p2-2→p2

```

```

180: if p2>=1; 1+p3→p3
181: if p3<=9; char(p3+48)→Q$[4, 4]; gto +2
182: char(p3+55)→Q$[4, 4]
183: fmt c12; wrt 720, Q$
184: ret
185: "set ch":
186: p1←1→p2
187: if p2<0 or p2>7; gto +2
188: char(p2+48)→Q$[5, 5]
189: fmt 9, c12; wrt 720, 9, Q$
190: ret
191: "set DAC":
192: 100p1→p2; 3→p3
193: if p2<0 or p2>999; gto +4
194: int(10frc(p2/10→p2))→p4
195: char(p4+48)→Q$[p3, p3]
196: jmp -2+3((p3-1→p3)=0)
197: fmt 9, c12; wrt 720, 9, Q$
198: ret
199: "freq": ret val(Q$[7, 121])/1000
200: "gain": ret 10val(Q$[6, 61])
201: "DAC": ret val(Q$[1, 31])
202: "ch": ret val(Q$[5, 5])+1
203: "att":
204: num(Q$[4, 4])→p1; 9(p1>64)+band(15, p1)→p1
205: 60bit("1XXX", p1)+30bit("X1XX", p1)+20bit("XX1X", p1)+10bit("XXX1", p1)→p1
206: ret p1
207: "power":
208: "p": 'volts'→p1; 'gain'→p2
209: if abs(p1)<.02 and p2<60; cll 'set gain'(min(p2+40, 60)); gto "p"
210: if abs(p1)>9.99; cll 'set gain'(p2-10); gto "p"
211: p1/tn↑(p2/20)→p1
212: 16→L→M
213: if abs(Q[L])>abs(p1); L+M/2→L; gto +2
214: L-M/2→L
215: M/2→M; jmp -2+3(M<=1)

```

```

216: if L>=31; 60→p4; gto +5
217: if abs(Q[L])<abs(p1); L-1→L
218: if L=0; dep "power too high!! reset!!!"; beep; jmp 0
219: Q[L]-p1→p2; Q[L]-Q[L+1]→p3
220: 2(L-1)+2(p2/p3)→p4
221: ret 10-p4-'att'
222: "det cal":
223: dim Q[55]; " "→A$
224: ent "new calibration ?", A$
225: if cap(A$)="NO"; ldf 2, Q[*]; ret
226: dep "set up det. cal hookup"; beep; beep; stp
227: cll 'set freq'(50); cll 'set ch'(4)
228: "det cal a": dep "set +10 dBm power"; beep; beep; stp
229: for J=0 to 4
230: for K=0 to 10
231: cll 'set att'(100); wait 500
232: 'volts'→p1; 'gain'→p2; tn↑(p2/20)→p3
233: if flg3; ofg 3; gto +2
234: if abs(p1)<.02; min(p2+4, 6)→p2; cll 'set gain'(10p2); ofg 3; gto -2
235: p1/p3→Q[J+1+5K]
236: next K
237: cll 'set gain'(0)
238: if J=4; gto +2
239: dep "reset power -2 dB"; beep; beep; stp
240: next J
241: cll 'set att'(0)
242: dep "reset +10dBm power"; beep; beep; stp
243: "cal": ent "calibration plot ?", A$
244: if cap(A$)≠"YES"; gto "save cal"
245: "NO"→A$
246: scl -110, 0, -4, 0
247: pen# 3
248: fxd 0; xax -4, 10, -110, 0; yax -110, 1, -4, 0, 1; pen
249: for Q=-110 to 0 by 10
250: str(Q)→A$
251: if A$[1, 1]=" "; A$[2]→A$

```

```

252: plt Q, -4, 0
253: cplt -.5len(A$), -1
254: lbl A$; pen
255: next Q
256: for Q=55 to 1 by -1
257: plt -2(Q-1), log(-Q[Q])
258: next Q
259: pen
260: plt -55, 0, 0
261: cplt -13, 3
262: lbl "detector calibration curve"
263: pen
264: plt -55, 0, 0
265: cplt -.5len(D$), 1.5
266: lbl D$; pen# 0
267: "save cal":ent "save calibration ?", A$
268: if cap(A$)#"YES"; gto +2
269: rcf 2, Q[2]
270: "NO"→A$; ent "new cal?", A$; if cap(A$)="YES"; gto "det cal a"
271: dep "Restore experimental hook up"; beep; etp
272: ret
273: "Hb":
274: cll 'eat ch' (1)
275: 'volts'/1.0006→p1
276: 58.35p1→p1
277: ret p1
278: "volts":cfg 10; fmt
279: wrt 725, "N34S, D. 0004902S, T1, R3"
280: "t":buf "buffer"
281: tfr 725, "buffer", 239, 10
282: if rde("buffer")=-1; gto +0
283: 0→p1; fmt
284: for Q=1 to 34; red "buffer", V[Q]; next Q
285: if max(V[*])=.9999; wrt 725, "R2"; efg 10; gto "t"
286: if max(V[*])=9.999; wrt 725, "R3"; efg 10; gto "t"
287: for Q=1 to 34; p1+V[Q]→p1; next Q

```

```
288: p1/34→p1
289: if flg10=1; goto +2
290: if abs(p1)<1.5; wrt 725, "R2"; sfg 10; goto "t"; if abs(p1)<.15; wrt 725, "R1"
291: ret drnd(p1, 4)
```