U·M·I

MICROCOPY RESOLUTION TEST CHART
NATIONAL BUREAU OF STANDARDS
STANDARD REFERENCE MATERIAL 1010a
(ANSI and ISO TEST CHART No. 2)

University Microfilms International
A Bell & Howell Information Company
300 N. Zeeb Road, Ann Arbor, Michigan 48106

INFORMATION TO USERS

This reproduction was made from a copy of a manuscript sent to us for publication and microfilming. While the most advanced technology has been used to photograph and reproduce this manuscript, the quality of the reproduction is heavily dependent upon the quality of the material submitted. Pages in any manuscript may have indistinct print. In all cases the best available copy has been filmed.

The following explanation of techniques is provided to help clarify notations which may appear on this reproduction.

1. Manuscripts may not always be complete. When it is not possible to obtain missing pages, a note appears to indicate this.
2. When copyrighted materials are removed from the manuscript, a note appears to indicate this.
3. Oversize materials (maps, drawings, and charts) are photographed by sectioning the original, beginning at the upper left hand corner and continuing from left to right in equal sections with small overlaps. Each oversize page is also filmed as one exposure and is available, for an additional charge, as a standard 35mm slide or in black and white paper format.*
4. Most photographs reproduce acceptably on positive microfilm or microfiche but lack clarity on xerographic copies made from the microfilm. For an additional charge, all photographs are available in black and white standard 35mm slide format.*

*For more information about black and white slides or enlarged paper reproductions, please contact the Dissertations Customer Services Department.

U·M·I Dissertation
Information Service

University Microfilms International
A Bell & Howell Information Company
300 N. Zeeb Road, Ann Arbor, Michigan 48106

8625311

Tsai, Yusheng T.

**A STRICTLY CONVERGENT, REAL-TIME SOLUTION FOR INVERSE
KINEMATICS FOR ROBOT MANIPULATORS**

The Ohio State University

PH.D. 1986

**University
Microfilms
International** 300 N. Zeeb Road, Ann Arbor, MI 48106

Copyright 1986

by

Tsai, Yusheng T.

All Rights Reserved

PLEASE NOTE:

In all cases this material has been filmed in the best possible way from the available copy. Problems encountered with this document have been identified here with a check mark ✓.

1. Glossy photographs or pages _____
2. Colored illustrations, paper or print _____
3. Photographs with dark background _____
4. Illustrations are poor copy _____
5. Pages with black marks, not original copy _____
6. Print shows through as there is text on both sides of page _____
7. Indistinct, broken or small print on several pages ✓
8. Print exceeds margin requirements _____
9. Tightly bound copy with print lost in spine _____
10. Computer printout pages with indistinct print _____
11. Page(s) _____ lacking when material received, and not available from school or author.
12. Page(s) _____ seem to be missing in numbering only as text follows.
13. Two pages numbered _____. Text follows.
14. Curling and wrinkled pages _____
15. Dissertation contains pages with print at a slant, filmed as received _____
16. Other _____

University
Microfilms
International

**A Strictly Convergent, Real-Time Solution
for Inverse Kinematics for Robot Manipulators**

DISSERTATION

**Presented in Partial Fulfillment of the Requirements for
the Degree Doctor of Philosophy in the Graduate School
of The Ohio State University**

by

Yusheng T. Tsai, B.S., M.S.

★ ★ ★ ★ ★

**The Ohio State University
1986**

Reading Committee:

David E. Orin

Karl W. Olson

Fusun Özgüner

Approved by

Advisor
Department of Electrical Engineering

Copyright by
Yusheng Timothy Tsai
1986

To my family

ACKNOWLEDGEMENT

I would like to thank Dr. David E. Orin for suggesting this topic and advising me throughout this research. I would also like to thank Professor Fusun Ozguner and Professor Karl W. Olson for their reading and suggestions.

I wish to thank my parents and brothers for their continuous support and encouragement. I am especially grateful to my wife Polly for her assistance, patience and spiritual encouragement.

Appreciation is also due to Ms. Debi Britton for her excellent work in preparing this manuscript. Discussions with Kathryn Lilly and Calvin Ling were very helpful and I want to thank both of them.

This research was supported by the National Science Foundation Computer Engineering Grant No. DMC-8312677.

Yusheng Timothy Tsai

VITA

- January 11, 1955 Born -- Taipei, Taiwan, R.O.C.**
- June, 1977 B.S., Electrical Engineering
National Cheng-Kung University
Tainan, Taiwan, R.O.C.**
- June, 1979 M.S., Electrical Engineering
National Taiwan University
Taipei, Taiwan, R.O.C.**
- 1979-1981 Electronic Engineer
Metastate Technology Corporation
Taipei, Taiwan, R.O.C.**
- 1981-1982 Instructor
National Taiwan Institute of Technology
Taipei, Taiwan, R.O.C.**
- 1983-1985 Graduate Teaching Associate
Department of Electrical Engineering
The Ohio State University
Columbus, Ohio**
- 1983-1986 Graduate Research Associate
Digital Systems Laboratory
The Ohio State University
Columbus, Ohio**

VITA -- Continued

FIELDS OF STUDY

Major Field: Electrical Engineering

Studies in Computer Engineering: Professors D.E. Orin,
K.W. Olson, F. Ozguner, C.A. Klein,
R.B. McGhee, K.J. Breeding

Studies in Control Engineering: Professors R.J. Mayhan,
R.E. Fenton, U. Ozguner

Studies in Communications: Professors D.T. Davis,
R.T. Compton

**Studies in Computer and
Information Science:** Professors M.T. Liu,
T.Y. Feng

PUBLICATIONS

"A Real-Time Computer Architecture for Inverse Kinematics," Proc. of
1986 IEEE International Conference on Robotics and Automation, San
Francisco, California, April, 1986, pp. 843-850.

Programming with PASCAL, Scholars Book Co., Ltd. Taiwan, 1982.

Wide-Band Video Amplifier Design, M.S. Thesis, National Taiwan
University, Taipei, Taiwan, R.O.C., June 1979.

TABLE OF CONTENTS

ACKNOWLEDGEMENT.....	111
VITA.....	1v
LIST OF TABLES.....	1x
LIST OF FIGURES.....	xi
<u>Chapter</u>	<u>Page</u>
1. INTRODUCTION.....	1
1.1 Introduction.....	1
1.2 Organization.....	7
2. SURVEY OF PREVIOUS WORK.....	10
2.1 Introduction.....	10
2.2 Algorithms for Inverse Kinematics.....	11
2.2.1 Closed-Form Analytical Approaches.....	11
2.2.2 Numerical Approaches.....	14
2.2.3 Singularities in Manipulator Kinematics.....	19
2.3 Special-Purpose Architectures for Robotic Control...	23
2.3.1 VLSI Robotics Processors.....	23
2.3.2 Systolic Architectures.....	27
2.3.3 Multiprocessor Architectures.....	30
2.4 Summary.....	35
3. PROBLEM FORMULATION.....	37
3.1 Introduction.....	37
3.2 Manipulator Kinematics.....	39
3.2.1 Kinematic Notation for Manipulators.....	39
3.2.2 Direct Kinematics.....	45
3.2.3 Jacobian.....	46
3.2.4 Inverse Jacobian.....	50
3.3 Numerical Integration.....	52
3.4 Requirements for Real-Time Inverse Kinematics.....	53
3.5 Summary.....	56

4.	NUMERICAL ALGORITHM FOR INVERSE KINEMATICS.....	57
4.1	Introduction.....	57
4.2	Predictor-Corrector Integration Algorithm.....	58
4.3	Error Estimation.....	60
4.4	Strictly Convergent Inverse Kinematics Algorithm....	63
4.5	Summary.....	70
5.	REAL-TIME ARCHITECTURE FOR INVERSE KINEMATICS PROCESSOR...	73
5.1	Introduction.....	73
5.2	Computation Requirements of the Algorithm.....	74
5.2.1	Matrix-Vector Operations.....	74
5.2.2	Sine/Cosine Generation.....	76
5.2.3	Reciprocal Generation.....	79
5.3	High Speed Floating-Point Architecture.....	83
5.4	Computation Times.....	91
5.5	Size of Register Files.....	95
5.6	Summary.....	97
6.	SIMULATION RESULTS.....	100
6.1	Introduction.....	100
6.2	Robot Models for Simulation.....	102
6.2.1	Mitsubishi RM-501.....	102
6.2.2	GMF S-400 Offset Wrist.....	105
6.3	Task Models.....	105
6.3.1	RM-501 Drawing a Circle.....	105
6.3.2	RM-501 Reaching Out.....	111
6.3.3	S-400 Offset Wrist Moving in a Straight Line.	114
6.4	Simulation Results and Performance Evalaution.....	122
6.4.1	Results for Three Tasks.....	123
6.4.2	Results for High Speed Movements.....	128
6.4.3	Effects of Position Feedback.....	132
6.5	Summary.....	144
7.	CONCLUSIONS.....	146
7.1	Research Contributions.....	146
7.2	Research Extensions.....	148
	REFERENCES.....	151

APPENDICES.....	157
A. Computer Programs.....	157
A.1 Contents of Appendix A.....	157
A.2 Programs for Simulations of Inverse Kinematics	
Algorithm.....	160
A.2.1 Programs for Computational Modules.....	161
A.2.2 Programs for Tasks.....	189
A.2.3 Programs for Simulations.....	199
A.3 Programs for Simulations of Inverse Kinematics	
Processor.....	212
A.3.1 Programs for Architecture and Function	
Mapping.....	213
A.3.2 Programs for Computational Modules.....	230
A.3.3 Programs for Tasks.....	290
A.3.4 Main Programs for Simulations.....	300

LIST OF TABLES

TABLE		PAGE
2.1	Comparison of Closed-Form and Numerical Approaches for Inverse Kinematics.....	22
5.1	Reservation Table for a Dot Operation of Two 6x1 Vectors on the Inverse Kinematics Processor.....	87
5.2	Results of Simulation to Determine the Number of Terms Needed in the Taylor Series for Sine and Cosine...	92
5.3	Simulation Results for the Reciprocal Showing the Seed Table Size and Number of Computation Cycles Required....	94
5.4	Computation Cycles Needed by Executing the Inverse Kinematics Algorithm on the Proposed Architecture.....	96
5.5	Size of Register Files Required for Inverse Kinematics Algorithm.....	98
6.1	Link Parameters and Operation Range of the Mitsubishi RM-501 Robot.....	104
6.2	Link Parameters of GMF S-400 Offset Wrist Robot.....	107
6.3	Results of Pascal Simulations for Three Different Tasks on the VAX-11/785.....	124
6.4	Results of Pascal Simulations for Three Different Step Sizes (GMF S-400 line move task).....	126
6.5	Results of Simulations on the Inverse Kinematics Processor (Processor Cycle Time = 150 ns).....	127
6.6	Results of Pascal Simulations of High Speed Motion with Single Precision (32-bit floating point).....	129
6.7	Results of Pascal Simulations of High Speed Motion with Double Precision (64-bit floating point).....	130
6.8	Results of Inverse Kinematics Simulation on the Proposed Architecture for a Task with High Speed Motion.....	131

6.9	Results of Simulations for a Task with Very High Speed Motion.....	133
-----	---	-----

LIST OF FIGURES

FIGURE		PAGE
1.1	Multiprocessor System Block Diagram for Robot Manipulator Control.....	5
3.1	Link Parameters Associated with Link i	41
3.2	Depiction of Vectors p_j , r_j , p_i^* , k_{tj} and Transform ${}^{i-1}U_i$ for a Manipulator.....	44
4.1	Functional Block Diagram Showing the Use of Inverse Kinematics in a Robot Control System.....	64
4.2	Flow Chart of the Inverse Kinematics Algorithm.....	67
4.3	Flow Chart of Simulation Program.....	71
5.1	DEC Single Precision Floating-Point Format.....	80
5.2	Architecture for Inverse Kinematics Processor.....	84
5.3	Control Circuit of the Inverse Kinematics Processor Showing a Possible Critical Path.....	89
5.4	Two Possible Critical Data Paths of the Inverse Kinematics Processor.....	90
6.1	Mitsubishi RM-501 Robot in Zero Configuration.....	103
6.2	Illustration of GMF S-400 Offset Wrist Robot.....	106
6.3	GMF S-400 Offset Wrist Robot in Zero Configuration.....	108
6.4	Task I: RM-501 Drawing a Circle.....	109
6.5	Illustration of RM-501 Reaching Out.....	112
6.6	Velocity Trajectory of the End-Effector for GMF S-400, Subtask 1.....	117
6.7	Velocity Trajectory of the End-Effector for GMF S-400, Subtask 2.....	119

6.8	RM-501 Continuously Drawing a Circle with a Speed of 90 deg/sec (Step Size is 0.01 sec and No Position Feedback is Added).....	136
6.9	RM-501 Continuously Drawing a Circle with a Speed of 90 deg/sec (Step Size is 0.001 sec. and No Position Feedback is Added).....	137
6.10	Rm-501 Continuously Drawing a Circle with a Speed of 90 deg/sec (Step Size is 0.01 sec and a Feedback Gain of 2 is Added).....	138
6.11	RM-501 Continuously Drawing a Circle with a Speed of 90 deg/sec (Step Size is 0.01 sec and a Feedback Gain of 50 is Added).....	139
6.12	The Relationship Between Maximum Error and the Feedback Gain for a Step Size of 0.01 sec.....	140
6.13	RM-501 Continuously Drawing a Circle with a Speed of 90/deg/sec (Step Size is 0.001 sec and a Feedback Gain of 5 is Added).....	141
6.14	RM-501 Continuously Drawing a Circle with a Speed of 90 deg/sec (Step Size is 0.001 sec and a Feedback Gain of 50 is Added).....	142
6.15	The Relationship Between Maximum Error and Feedback Gain for a Step Size of 0.001 sec.....	143
6.16	The Position Error with an Initial Error of 3 mm and Feedback Gain of 600.....	145

Chapter 1

INTRODUCTION

1.1 Introduction

Inverse Kinematics for a robot manipulator is the transformation of position from Cartesian coordinates to joint coordinates. Since motion trajectories of robots are naturally described in Cartesian coordinates while physical motion is controlled by actuators located at each joint, Inverse Kinematics is a very important transformation in the robot's control algorithm.

A real-time solution for Inverse Kinematics is required when the motion trajectory is not completely specified beforehand. For example, the motion commands for a sensor-based robot will not be generated until it receives new environmental information from its sensors and this must take place on line in real time. Since the servo rate relates loosely to the structural resonant frequency of the manipulator [1], for most industrial robot manipulators, the feedback controller for each joint actuator must receive the joint commands at a minimum rate in order to obtain smooth and predictable tracking. This minimum rate is typically between 160 Hz and 640 Hz [1], twenty times the natural frequency of the manipulator.

Since the Inverse Kinematics transformation is nonlinear and configuration dependent, there is no universal closed-form solution. On

the other hand, a general numerical solution may be found. The advantage of a closed-form solution is that its computation time is almost always smaller than the computation time for a numerical method, and a closed-form solution usually gives greater insight into the kinematic relationships describing the manipulator (useful in mechanical design). However, a closed-form solution has been obtained for only certain classes of robots, such as the PUMA 600 [2] and Stanford Manipulator [3]. These simple manipulators are configured in such a way that some joint axes intersect or consecutive axes are perpendicular or parallel. Paul [3] showed a common approach for solving these simple manipulators. Pieper and Roth [4] found that the sufficient condition for a closed-form solution is to have any three adjacent joint axes intersecting at a common point or three adjacent joint axes parallel to one another.

Although many industrial manipulators have a simple kinematic configuration and have closed-form solutions, there are examples, especially in cases in which there is an offset at the wrist, where closed-form analytical solutions are not available. Also, from a practical point of view, manufacturing errors in machining and assembly of robots lead to discrepancies between the physical structure and the designed parameters of the model [5]. If accurate kinematic models are used for off-line programming purposes or for better positioning performance, all parameters are nonzero and no configuration is considered truly simple. Furthermore, for a newly designed robot, it is tedious to find a closed-form solution if such a solution exists at all.

Therefore, a numerical solution for Inverse Kinematics which is applicable for the general configuration is needed.

The problem with previous numerical methods is that they have difficulty with convergence, especially near a singularity configuration. In the neighborhood of a singularity point there is at least one eigenvalue of the Jacobian matrix that is very small and will result in a very large component of joint rate when the equations are inverted. Also, most algorithms involve extensive computation and are difficult to implement in real time.

This dissertation will develop a strictly convergent, numerical algorithm which is robot independent and also applicable to redundant robots. This algorithm is based on numerical integration of joint rates. A weighted sum of the component differences between the estimated position/orientation and desired position/orientation of the end effector will be used as the convergence criterion. The value of this function must be reduced in each numerical step (strict convergence), and this is important so as to avoid difficulty near singularity points. A feedback mechanism based on this difference is especially designed to eliminate problems with long-term drift in numerical integration or problems with initial errors in the solution. This is also expected to result in better positioning performance.

The pseudoinverse technique will be applied so that this algorithm is applicable to robots with any number of degrees of freedom, even redundant robots. The pseudoinverse which minimizes the energy spent on the movement is selected to provide a solution which is naturally on a continuous trajectory and thus avoids the degeneracy problem. Other

types of pseudoinverse are also widely used in redundant robots. For example, the pseudoinverse which includes a constraint for maximizing the distance between obstacles and the manipulator may be used to obtain an Inverse Kinematics solution which avoids obstacles in the space of the manipulator [6]. To increase the efficiency of the algorithm, a predictor-corrector method is selected for numerical integration to reduce the number of evaluations of necessary joint rates, which are the most time-consuming processes in the Inverse Kinematics algorithm.

Although the algorithm as developed is expected to be faster than many previous numerical algorithms, the computation time on a VAX-11/785 is still expected to be much longer than real time. The concept of implementing an algorithm through the use of a special-purpose computer architecture in order to reduce the computation time has been successfully applied in many applications. Toward this end, a second objective of this dissertation is to develop a special-purpose architecture, in particular an Inverse Kinematics Processor, to solve Inverse Kinematics for a general robot manipulator in real time.

From the system point of view, the Inverse Kinematics Processor is a special-purpose processor which is connected through an interface to other parts of a multiprocessor control system. The system block diagram for this concept is shown in Fig. 1.1. The input to the Inverse Kinematics Processor is the desired position and velocity of the end effector and the output is the corresponding joint variables of the manipulator. Fig. 1.1 indicates that the entire system has many functional blocks. Each block may contain more than one processor to

Figure 1.1 Multiprocessor System Block Diagram for Robot Manipulator Control.

complete control of one function, such as Inverse Dynamics or Trajectory Generation, as shown in the figure.

In general, the architecture of the proposed Inverse Kinematics Processor will include a high-speed floating-point processor and a register file for storing link parameters and other frequently used information. Its corresponding controller will be microprogrammed. The floating-point processor should be able to execute a floating-point multiplication, addition, or subtraction (nominally 32-bit) in at most a few clock cycles. The architecture of this processor should be very efficient for matrix-vector operations because these are the most of the total operations in the Inverse Kinematics algorithm. The architecture of the Inverse Kinematics Processor will be discussed in this dissertation and a more detailed circuit block diagram will also be provided.

The complete algorithm and architecture will be simulated on the VAX-11/785 computer. Two complete simulations will be programmed to show the strict-convergence property and accuracy of the Inverse Kinematics algorithm. The first is a general Pascal simulation program while the second simulates the complete algorithm on the proposed architecture and is essentially a microprogram. Simulation results will be used to evaluate the strict-convergence property and the position precision of the developed algorithm. Also, through the proposed architecture, the solution may be obtained in real time. The execution time of simulations of two industrial robots will be examined in detail.

In summary, the concept of developing a strictly convergent

algorithm to solve the Inverse Kinematics problem for general robot manipulators and implementing it on a special-purpose architecture for real time operation will be fully explored in this dissertation. Both the algorithm and the architecture will be investigated and extensive simulation results for evaluation of performance will be discussed.

1.2 Organization

Chapter 2 provides a survey of previous work in the area of real-time solutions for Inverse Kinematics. The survey contains two basic parts: algorithms and architectures. Two different approaches to algorithm development, the closed-form analytical approach and the numerical approach, are compared and the problems of each are pointed out. The problems associated with a manipulator singularity and the work directed toward these problems will also be summarized in the chapter. The second part of the chapter presents a survey of special-purpose architectures for robotic control.

In Chapter 3, the Inverse Kinematics problem is formulated. The basic methods used to solve manipulator kinematics and perform numerical integration are described. A common notation which is used for robot manipulator kinematics is first presented and followed by solutions to several generic robotic computations required in Inverse Kinematics -- Direct Kinematics, the Jacobian, and Inverse Jacobian. An efficient numerical integration method, the predictor-corrector approach, is presented next. Finally, the specifications for real-time Inverse Kinematics are introduced.

Chapter 4 presents a numerical algorithm to solve Inverse Kinematics for general robot manipulators. It is basically a velocity

integration approach with predictor-corrector numerical integration. With absolute error checking in the integration and with the use of position feedback, the algorithm developed is strictly convergent. With the pseudoinverse which minimizes energy spent on movement, the algorithm is nondegenerant. A flow chart is used in the chapter to clearly present the algorithm.

Chapter 5 presents the development of a special-purpose architecture for Inverse Kinematics. Based on the required computations in the Inverse Kinematics algorithm, a three-bus structure processor with two feedback data paths is selected to facilitate the most frequently used matrix-vector operations. The complete architecture for the Inverse Kinematics Processor also includes a register file, seed look-up table, and a microprogrammed controller and associated program memory. The total computation cycles required and the size of register file needed for Inverse Kinematics are also given in this chapter.

In Chapter 6, simulations of Inverse Kinematics for two industrial robot manipulators are given. The design of tasks for selected robot models are first presented and followed by the simulation results. The simulation results include an evaluation of the algorithm near a kinematic singularity as well as the accuracy and the time of computation. Also, the effects of long-term drift and initial error are examined. For a seven degree-of-freedom manipulator, the computation time for Inverse Kinematics is less than $600\ \mu\text{s}$ if a processor cycle time of $150\ \text{ns}$ is used.

The last chapter summarizes the contributions of this research and presents a discussion of possible further research. An appendix is included in this dissertation and contains a listing of the important computer programs written.

CHAPTER 2

SURVEY OF PREVIOUS WORK

2.1 Introduction

Techniques for obtaining the joint displacements of a robot manipulator from the position and orientation specifications for the end effector in Cartesian coordinates have been studied extensively and especially during the past five years [1-23]. However, it is still difficult to obtain the solution in real time for any type of manipulator with any number of degrees of freedom. This chapter presents a brief survey of the previous work directed to determine a real-time solution for Inverse Kinematics and the special-purpose architectures that have been considered for this purpose.

The various approaches to the problem of Inverse Kinematics show different limitations. Some algorithms are only applicable to a very special class of robots while other algorithms are generic to many different types. Some algorithms may be executed very fast but involve extensive derivation of the equations prior to computer implementation while others require much computation and are thus slow. In the next section, both analytical and numerical approaches to Inverse Kinematics will be reviewed. Also, the problems near singularity points are important in Inverse Kinematics and will be discussed. Finally, a comparison of the different methods, with respect to their computation speed and generality, will be presented.

The other major part of this chapter reviews contributions made in special-purpose architectures for robot control. The most important design criteria for these architectures was to decrease the computation time for the control. Since a major thrust of this dissertation is to provide a special-purpose processor for Inverse Kinematics in order to reduce the computation time, these architectures are surveyed in the third section of this chapter to provide background in this area.

2.2 Algorithms for Inverse Kinematics

The algorithms for Inverse Kinematics are divided into two basic categories: analytical approaches and numerical approaches. The analytical approaches provide closed-form solutions, and generally require the least computation and also provide good insight into the kinematic structure of the manipulator. On the other hand, numerical approaches are more general but usually require more computation time and provide little understanding of the kinematics of the manipulator. The next two subsections will describe the corresponding algorithms respectively.

When a singularity is encountered, the robot manipulator loses degrees of freedom of movement. Inverse Kinematics cannot generally be solved near these positions. The third subsection will investigate this topic.

2.2.1 Closed-Form Analytical Approaches

To reduce the computation time, a closed-form solution for Inverse Kinematics is always better than a numerical solution if both of them exist. When the geometry of a robot manipulator is rather simple, such as a manipulator with two or three links and successive links parallel

or perpendicular, a closed-form solution may be obtained through simple trigonometric operations. However, if the number of links is larger than three or if there is an offset between two successive links, the direct trigonometric approach is often too difficult to apply.

Paul [3,7] pointed out that the direct trigonometric approach is difficult because of the following reasons: the equations are transcendental; both the sine and cosine are needed in order to determine an angle uniquely and accurately; the manipulator may exhibit more than one solution for a given position; and twelve equations in N unknowns (where N is the number of links of the manipulator) are given. He also concluded that there is no algorithm by which the closed-form solution can be obtained for the general robot manipulator and geometric intuition is required to direct the solution. However, once a solution is conceived, he outlined methods to produce the equations in a direct and unambiguous manner.

In his method, homogeneous transforms are used to provide equations for all the sines and cosines of all angles. For each transform equation, 12 non-trivial equations may be obtained and it is these equations which will yield the required solution. These equations are then combined with the exclusive use of the arc tangent function of two arguments in order to avoid problems of angle quadrant ambiguity inherent in trigonometry. The solution is obtained in a sequential manner, isolating each variable by premultiplication by a number of the transforms in each equation. For kinematically simple robot manipulators, the solution to the kinematic equations may be obtained in a very straightforward, error-free manner.

Since a generic algorithm to obtain the closed-form solution for any type of robot manipulator is very difficult, researchers have

considered special arrangements of joint axes for which closed-form solutions do exist. Examples may be found in Featherstone's [8], Hollerbach's [9], and Elgazzar's [10] papers. Most of their research is only applicable to a six-degree-of-freedom robot manipulator.

Featherstone [8] was the first to develop algorithms for the transformation of Cartesian position and velocity of the end effector to joint angles and rates for a six-degree-of-freedom manipulator with three revolute axes intersecting at the wrist. Robot manipulators with this joint arrangement have the property that the position of the wrist may be calculated directly from the position and orientation of the end effector, without knowledge of any of the joint variables. Therefore, Inverse Kinematics may be divided into two subproblems: the first three joints serve to position the wrist and the remaining joints serve to orient the end effector. Applying spherical trigonometry [6], all the joint variable values may be determined.

In Featherstone's algorithms, equations for the Inverse Kinematic positions and velocities for a coplanar manipulator were derived. Hollerbach [9] extended this technique to compute the accelerations for the same manipulator. Elgazzar [10] also successfully applied Featherstone's approach to the PUMA 560 manipulator, which is different from a coplanar manipulator in that it has offsets at the shoulder and elbow joints and an asymmetry in the forearm link.

The case of more general analytical (closed-form) algorithms for a manipulator with six degrees of freedom has been studied by Takano [11]. He also separated the problem into two subproblems and solved it iteratively. In his method, the first three joint variables may be solved analytically through position synthesis based on the assumption that the last three joint variables are constants. Then orientation

synthesis is used to obtain the solution for the last three joint variables assuming that the first three obtained through position synthesis are constants. Since the position and orientation of the end effector cannot be independently determined by the first three joints nor the last three joints except for very specially designed manipulators, iterative procedures are required. In Takano's paper [11], he also derived the solutions for all eight possible joint arrangements of the first three joints in case that the last three joints are all rotational.

Since a closed-form solution does not always exist, Pieper and Roth [4] found that a sufficient condition for a closed-form solution is to have any three adjacent joint axes intersecting at a common point. For each given position and orientation of the end effector, Roth et al. [12] also concluded by deductive reasoning that there are at most 32 solutions. Because of the complexity of the equations and non-existence of a general closed-form solution, Inverse Kinematics analysis for general manipulators can only be solved through numerical techniques.

2.2.2 Numerical Approaches

Because of the lack of a general closed-form solution for Inverse Kinematics, and since considerable time may be spent in deriving the equations for each manipulator when they exist, the numerical approach is preferred when a general-purpose program is needed.

At present, there are three basic methods for solving Inverse Kinematics numerically: Newton-Raphson methods [13-17], velocity integration methods [4,13,18,20], and continuation methods [21].

Newton-Raphson methods assume the existence of an approximate solution. The equations are then linearized and an increment to this approximation is computed. Hopefully, the computed increment will lead to a more accurate approximation. Repeating this process until the difference between two successive approximations is smaller than an allowed small value results in the final solution.

Uicker, et al. [17] were the first to use this method to do displacement analysis of spatial mechanisms. Based on matrix algebra, they derived the Newton-Raphson equations for a general solution of a serial-linked manipulator. The advantages of their method are its generality and that all calculations may be performed on a digital computer. The disadvantages are that it requires initial estimates for the values of the variables, and that the iteration process will not converge at a "deadpoint" in the mechanism's operation.

Pieper [13] used a similar approach, based on Newton-Raphson methods, with homogeneous transforms. He found that if the final state is considerably different from the initial state, the solution would not yield small corrections and the method would not converge.

To eliminate this convergence problem, Hansen, Gupta, and Kazerounian [16,19] developed a modified Newton-Raphson method. They refined the algorithm by introducing the concepts of control of step size and of a variable convergence criterion. The step size is controlled to ensure that the intermediate iteration steps always move the end effector closer to its target position in some sense. With step size control, the algorithm is stabilized to be strict-descent with respect to certain measures of deviation from the target position. A variable convergence criterion is used to improve the execution speed of

the algorithm and to improve its accuracy in the determination of limiting configurations. They also found that this method is reliable, stable and also leads to highly accurate results. However, it is not very time efficient [19].

For six-degree-of-freedom manipulators, Goldenberg and Lawrence [14] also presented a method for providing a generalized Inverse Kinematics solution. They reduced the matrix equation defining the position and orientation of the end effector in terms of the six joint variables to a system of six nonlinear equations. The solution is then obtained by either least squares optimization or by a method treating the system as a set of simultaneous nonlinear equations. This algorithm converges faster than that of Hansen, Gupta, and Kazerounian.

For the redundant robot, which contains more than six degrees of freedom, Oh, Orin, and Bach [15] developed another Newton-Raphson numerical procedure based on a composite Jacobian which included rows for additional constraints other than those on the end effector. They developed a more efficient formulation of Pieper's numerical approach, and extended it to include the case of a redundant manipulator. This numerical algorithm deals with all the aspects of an Inverse Kinematic analysis: positions, rates, and accelerations, and it is able to solve Inverse Kinematics for redundant or nonredundant manipulators. However, their paper did not discuss the convergence problem nor the real-time computational requirements.

The velocity integration methods are based on the relationship between joint velocities and end effector velocity, which is known as the Jacobian. Numerical integration may be used to integrate the joint velocities and along with the initial joint positions, to obtain the current joint positions. Pieper [13] found that velocity integration

methods have better convergence characteristics than Newton-Raphson methods.

Because of enhanced accuracy, better convergence characteristics, and time efficiency, most recent work [15,18,20,22] has been based on velocity integration methods.

Whitney [23] first presented a paper to use the inverse of the Jacobian to obtain the joint rates given the end effector velocity for a robot manipulator with N degrees of freedom, where N may be smaller than, equal to, or larger than six. By using Euler integration, the joint positions may be computed if the initial values are given and the step size is small enough. This method may be refined by using more sophisticated integration formula. However, since the computation of the Jacobian is based on estimated joint position values, the computational error has a cumulative nature. Pure integration of velocity is not guaranteed to be convergent.

For six-degree-of-freedom robot manipulators, Lenarcic [22] applied the conjugate gradient technique to iteratively solve the nonlinear kinematic equations. The Inverse Jacobian is still used as a relationship between the gradient in Cartesian coordinates and the gradient in joint coordinates. Since convergence of the conjugate gradient technique has been proven, Lenarcic claimed that his method has no convergence problems. To further decrease the total computation time, he also computed the Inverse Jacobian through a linear interpolation method. For most industrial robots when continuous path control is used, the convergence problem does not appear. Lenarcic's algorithm has only been tested on a six-degree-of-freedom robot, and the best average execution time is 11 ms on a VAX-11/750 computer. The maximum error is 1 mm.

For robot manipulators with any arbitrary number of degrees of freedom, Goldenberg, Benhabib, and Fenton [20] presented another iterative solution which is also based on velocity integration methods. They used a residue vector to measure the difference between the estimated and desired end effector position and orientation. This residue is then compared with a specified threshold value to check convergence. Since the generalized inverse has been applied to obtain the inverse of the Jacobian, this method is suitable for any class of robots including redundant manipulators. Furthermore, step size control is included to provide more reliable convergence properties.

Recently, Angeles [18] also introduced a robot independent algorithm. His algorithm is based on invariants in the rotational parts of the kinematic equations, which produces a formally overdetermined nonlinear algebraic system. The Inverse Jacobian is obtained by the application of a sequence of Household reflections to both sides of the kinematic equations. This can reduce the convergence problems when the manipulator is near singular configurations. For translation, a recursive scheme for polynomial evaluation is introduced. This leads to a reduced number of computations, resulting in an efficient numerical solution. He also included Inverse Kinematics for velocity and acceleration in his paper. The number of operations required per iteration to solve the displacement equations is 513 multiplications and additions plus 6 square roots.

To improve the reliability, stability, and time efficiency of numerical algorithms, Gupta and Kazerounian [19] developed a modified predictor-corrector method. They included step size control and a variable convergence criterion into their algorithm such that it can always converge if a physically realizable robot configuration exists.

They are also able to numerically determine singular positions of the robot with any desired numerical precision. It has been shown that this modified predictor-corrector algorithm is 5-15 times faster than the modified Newton-Raphson algorithm they had also presented [19].

In this dissertation, Gupta and Kazerounian's algorithm will be modified so that it may be used for robot manipulators with any arbitrary number of degrees of freedom. Different methods for obtaining the Jacobian and the errors will be used to increase the efficiency. Also, position feedback will be included to eliminate any problems with long-term drift or errors in the initial estimation.

For general five and six degree-of-freedom manipulators, Tsai and Morgan [21] also proposed a method to solve the kinematics based on continuation methods. They reduced the kinematic equations to a system of eight second-degree polynomial equations, and demonstrated that this second-degree system may be routinely solved by using a continuation algorithm. This algorithm is guaranteed to find all solutions of the system instead of just one solution. The numerical stability of continuation on small second-degree systems is proven. Therefore, this algorithm is good for routine use in off-line robot programming applications. However, the computational requirements of this method have not been thoroughly evaluated.

2.2.3 Singularities in Manipulator Kinematics

Singularities are manipulator configurations where the degrees of freedom of the manipulator are reduced below six [35]. In these configurations, there are directions along which, or about which, the manipulator cannot move or exert force or torque. Any of these configurations is called a singularity point since the Jacobian matrix

is singular. Two kinds of singularities may occur: boundary singularities and internal singularities.

Boundary singularities occur when the end effector moves to its workspace boundary. For a serial-link manipulator, links are successively connected together by joints. Each joint can provide a degree of freedom. Joints generally have limited motion ranges so that when a joint reaches its motion limit, the manipulator loses a degree of freedom. For N link manipulators, if one or more links have reached their motion limits, and the degrees of freedom of the manipulator have been reduced below six, then the manipulator is in a singular configuration. Likewise, since the link lengths of the manipulator are finite, the degrees of freedom of the manipulator will be reduced below six at its maximum extension. All of these cases are boundary singularities.

Internal singularities, which are inside the workspace boundary, arise from certain kinematic alignments of joint axes. A manipulator will lose a degree of freedom inside its workspace whenever two revolute joint axes become colinear, the axes of two prismatic joints are parallel, or the axes of three revolute joints become coplanar. Other situations may also cause the loss of degrees of freedom.

When two joint axes are colinear in space, a rotation about one axis produces identical motions of the end effector for equivalent motions of the joints. The manipulator loses one degree of freedom in this configuration.

If two rotational joints are parallel and the end effector is located in the plane formed by these two axes, the rotation of either joint will cause the same effect on the end effector. The manipulator also loses a degree of freedom in this configuration.

Paul [24] also concluded that any three revolute-joint orienting system (wrist) will lose one degree of freedom when the second wrist variable approaches 0 or 180 degrees.

Singularities will present problems for Inverse Kinematics since it is desired to find joint rates that correspond to the desired end effector velocities. Since the Jacobian is noninvertible at kinematic singularities, desired Cartesian motions at the singular configuration become impossible to realize. Near singularities the movements are also ill-conditioned because at least one eigenvalue of the Jacobian matrix is very small.

Singularity problems have long been recognized [23,25] and the properties of singularity have been studied [25]. One of these properties, very large joint velocities will be computed when the movement is close to a singularity, can be used for singularity detection. This property will also be indirectly used in the present algorithm.

Possible solutions for singularities have also been suggested [23,26]. The first approach is to avoid singularities and their associated ill-conditioned regions by planning trajectories away from them. The second approach is to switch the motion from Cartesian trajectories to joint-interpolated motion when near any singularity point [26]. The third approach is to provide extra joints. This is the most promising approach and results in redundant manipulators. The analysis and control of robot manipulators with redundancy has been studied by Yoshikawa [27]. One of the important utilizations of the redundant manipulator is singularity avoidance.

Finally, a simple comparison of analytical and numerical approaches to Inverse Kinematics is given in Table 2.1. The comparison shows that the numerical approach is the better choice if problems with computation

Table 2.1 Comparison of Closed-Form and Numerical Approaches for Inverse Kinematics.

<div> <div>Issue</div> <div>Approach</div> </div>	Closed-Form	Numerical
1. Computation speed	Fast	Slow
2. Manipulator Independence	No	Yes
3. Degrees of freedom	Fixed	Any
4. Generic solution	No	Yes
5. Accuracy	Excellent	Acceptable
6. Singularity detection	Yes	Possible
7. Convergence problem	No	Solvable

speed can be managed. The work of this dissertation is to develop a complete algorithm and a special-purpose architecture for Inverse Kinematics, and the results indicate real-time capability.

2.3 Special-Purpose Architectures for Robot Control

An intelligent robot manipulator must be able to detect recent information from its environment and with intelligent decision-making, adjust the control of the next movement, all in real time. Because of their considerable adaptability, many intelligent algorithms, which usually imply extensive computation time, will be developed and applied to future robot manipulators. One of the difficulties will be the real-time implementation of these algorithms on the control computer of the associated robot system. One possible approach that holds excellent promise is that of implementing these algorithms on special-purpose computer architectures. Since some algorithms, such as the Jacobian, Inverse Jacobian, Direct Kinematics, Inverse Kinematics, and Inverse Dynamics, are often used in robot manipulator control and may thus be considered to be generic in some sense, several investigators [28-33] have considered special-purpose architectures for these algorithms. The purpose of this section is to review these architectures. Three kinds of architectures will be discussed: VLSI robotics processors, systolic architectures, and multiprocessor architectures.

2.3.1 VLSI Robotics Processors

Investigations concerned with VLSI robotics processors deal with the chip-level implementation issues of robotics algorithms. The basic idea for reducing the computation time is to attach a special-purpose numerical processor to a general-purpose system that is directed toward

performing certain computations very efficiently. An example is that of adding a high-speed, floating-point coprocessor to a general-purpose microprocessor to increase the system performance for floating point computations. In this subsection, three different VLSI chips that are specialized for robotics computations will be reviewed.

A single chip numerical processor (NP) suitable for real-time control of a robot manipulator has been introduced by Turney and Mudge [29]. This processor is designed to be an attached processor to enhance the computation capability for robotic control algorithms. The main components of this numerical processor include a floating point adder, a floating point multiplier, input/output register files, and a program memory with a length of one thousand words. The total number of devices was estimated to be 150K, and would be implemented in nMOS technology.

The on chip program memory plays an important role in the implementation of those control algorithms, where the algorithm requires a very large number of high-precision, arithmetic operations for every input/output transaction. Programming this processor is essentially done at the microcode level.

The architecture of this processor includes two floating-point, arithmetic units connected in parallel: an adder and a multiplier. Both of them have a three-stage pipeline with a cycle time of 500 ns, and are connected to a 256 word register file through a two-bus interconnection structure. The three stages of the floating point adder perform alignment, fraction addition, and normalization, respectively. For the floating point multiplier, the first stage performs partial product generation and carry-save addition, the second stage implements carry propagation addition, and the third stage performs normalization. The critical paths for both the adder and multiplier are in the first

stage. Two types of instructions are provided: instructions to control the adder and multiplier for arithmetic computation, and instructions to control the data transfers and branching.

The design philosophy of Turney and Mudge's NP was oriented toward dedicated numerically intensive applications. A practical application is the real-time control of a robot manipulator. Analysis of the control algorithms concluded that five basic stages are involved in the overall control strategy: path planning, orientation matrix calculation, trajectory transformation, gross motion control, and fine motion adjustment. Gross motion control involves the computation of the actuator torques given the present state of the manipulator and the desired joint accelerations. This stage represents a potential computational bottleneck. Using the computation time of the equations of the gross motion control stage as a benchmark, a functional simulation was performed on the NP to test the performance of this processor. Simulation results showed that this processor can operate at an average of 2.93 MFLOPS for this benchmark, which is approximately 73% of its maximum rate.

Chao [30] also designed a single chip robotics processor (RP) to be used in computing arrays for manipulator control. His design considers the communications problems which are possible computing bottlenecks in the implementation of the control algorithm. The main components of Chao's RP include a 32-bit floating point adder, a 32-bit floating point multiplier, a 128 word register file, four unidirectional ports, and an on-chip control RAM for microprograms. The total number of transistors on the RP is estimated to be 60K. Using 3 micron nMOS technology, the die size is evaluated to be 8.2mm x 8.2mm.

The architecture of the RP also includes two floating point arithmetic units connected in parallel: a floating point adder/subtractor and a floating point multiplier. Both are internally pipelined with three-stages, and are operated in parallel in a three-bus interconnection structure. Four unidirectional ports provide buffered input/output with format conversion from the 32-bit format on the internal bus to the 16-bits format on the external bus. The register files and floating point arithmetic units are operated at a one Mhz rate while the system clock rate is 16 Mhz.

Chao's design philosophy for the RP is to create a VLSI chip which can be connected in parallel or in a pipeline to perform the necessary robotics computations at high speed. Three applications have been studied in detail: the Jacobian, Inverse Jacobian, and Inverse Dynamics algorithms. Chao concluded that all of them may be computed in 1 ms or less. For each application, Chao considered several possible configurations, then he determined the optimal configuration based on the following performance criteria: execution time, CPU utilization, total memory size, and speedup.

Since manipulator control involves a large number of vector and matrix operations, it may greatly reduce the total computation time if a special-purpose chip is developed which is able to perform general matrix-vector operations very efficiently. Lathrop [33] proposed a data path element as a primitive module and connected three of the primitive modules to give a matrix-vector processor.

Lathrop's primitive module contains two multipliers and one adder/subtractor. Each of them is accompanied with two registers for storing operands. Two buses interconnect all arithmetic units and registers in such a way that each element can communicate with adjacent

elements. Based on this structure, a vector dot product may be computed in three floating-point steps. By grouping three such primitive modules together, along with the necessary control, a matrix-vector multiplication may be implemented as three vector dot products and executed in parallel in three steps.

The control of Lathrop's matrix-vector processor is synchronized in such a way that respective dump and load operations between the source and destination processors allow intermediate results to be passed to successive operators. Also the control must specify when the operands are read and when the result is computed and written. This processor is the basic computing module in his dynamics algorithm, which will be discussed in the next subsection.

2.3.2 Systolic Architectures

Systolic architectures are concerned with task level issues of implementation. A systolic architecture has a regular structure with local communication usually in linear or mesh arrays. The task is finely partitioned into elementary operations that are closely synchronized. At this level, the mapping of the algorithm onto a suitable architecture is one of the most important issues to study. The mapping is not only concerned the execution of the algorithm on the architecture but also its computational efficiency and performance. Three systolic architectures for robotic control will be reviewed here.

Architectures for computation of the Jacobian have been studied by Orin [31] and others [34]. Based on efficient serial algorithms for the Jacobian [36], Orin developed pipeline and parallel algorithms which are suitable for implementation on a systolic array of processors. He

evaluated several configurations of processors and determined the best configurations in terms of computation time, initiation rate, and CPU utilization.

Based on Orin's parallel algorithm, the computation delay of the Jacobian is reduced to the order of $\log_2 N$, where N is the number of degrees of freedom of the manipulator. For a seven-degree-of-freedom manipulator, only three levels of computation are required to obtain the Jacobian. However, the communication between processors is not all local, and this causes implementation on the systolic architecture to be more difficult. Orin was able to map this algorithm onto a hypercube architecture with the addition of a some redundant computation and still resulted in a computation time on the order of $\log_2(N+1)$.

The results of Orin's pipelined algorithms showed that two processors could exploit all parallelism in the Jacobian computation, and the computation time would not significantly decrease with the use of additional processors because of the effects of communications delay. The computation time may be further reduced if the parallel algorithm is used. The implementation on the hypercube architecture showed that $N+1$ processors is the best choice. The computation time for the case of a seven-degree-of-freedom manipulator is 239 μ s for a 500 ns clock cycle. Because of I/O bandwidth limitations, the speedup for seven processors for a seven degree-of-freedom manipulator was only 1.52 in a pipeline configuration and 2.35 in the parallel configuration [43]. In order to reduce the execution time significantly, the computations must be further broken down to matrix-vector operations. However, the limited communications bandwidth would restrict the utility of this approach and the utilization of each processor might be low.

In order to find a cost-effective architecture using current available hardware to perform real-time dynamic control of a manipulator, algorithms and architectures for Inverse Dynamics have also been studied. Nigam and Lee [37] functionally decomposed the manipulator's dynamic model into several computational modules and proposed an appropriate computational architecture using available microprocessors to optimize its computation time.

They found that the Lagrange-Euler and Newton-Euler formulations for solving the dynamics of manipulators had a certain amount of parallelism and a large amount of sequentialism in the flow of computation. Based on the data dependencies and the parallelism in the computation flow of the algorithm, they concluded that the parallelism in the computation of the gravitational, coupling and inertial terms may be exploited by having multiple processing elements calculating these terms in parallel. The sequential nature of the remainder of the terms may be exploited through use of a pipelined architecture. Both aid in increasing the computational throughput.

Using the natural frequency of the PUMA as an example, they determined that the control should be updated every 3 ms, a rate which is 20 times the natural frequency of the robot arm. They reserved half of this time for other calculations and determined that the joint torques should be computed in 1.5 ms. With six processors as the computational modules and one processor as a system supervisor, this architecture could provide a set of torques every 0.6 ms if 16.7 Mhz Motorola 68020's were used as processing units.

Lathrop [33] also presented two Inverse Dynamics algorithms suited to high speed, highly parallel implementations using VLSI devices. He analyzed the Newton-Euler algorithm in great detail down to the

matrix-vector operation level, and proposed a matrix-vector processor. One algorithm is a parallel version of the familiar linear recursive Newton-Euler equations. The time required to perform the computation increases linearly with the number of degrees of freedom, but this new algorithm reduces the real-time coefficients by two orders of magnitude. The other algorithm is a logarithmic recursive parallel algorithm. The time cost only increases logarithmically with the number of degrees of freedom. Lathrop demonstrates that both algorithms are suitable for systolic architectures and a complete set of joint torques may be generated every four floating point operations. These are the fastest algorithms developed to date. However, both of his approaches require a large number of matrix-vector processors, 180 and 637 respectively. Also, he does not consider problems with I/O, and this may be a limiting factor.

2.3.3 Multiprocessor Architectures

Multiprocessor architectures are concerned with system level issues of implementation. Possible parallelism among tasks should be exploited. Various issues such as task partitioning and scheduling, synchronization of the control and communications, and memory management, should be considered. Further discussion of general multiprocessor systems and applications are given in [38,39]. Five multiprocessor architectures for control of robotic systems will be reviewed here.

Based on the potential advantages of multiprocessor systems -- real-time computation, high reliability, and modularity -- Klein and Wahawisan [40] designed a multiprocessor system for control of the OSU hexapod vehicle. With an eight-channel parallel line unit, they linked

five LSI-11 processors in a fully-connected configuration such that various system structures, the tree, star, and loop, may be tested by simply ignoring links that were not needed. A tree structure was implemented with the consideration of minimizing the interprocessor communication. A hierarchical design divided the control software into four levels: rate servo control, rate command generation, foot motion planning, and body motion generation. For real-time force optimization, five processors were used: one processor was used for body motion planning and rate command generation, one for execution of force optimization, and one processor for each pair of foot motion planning and corresponding rate servo control. The use of a multiprocessor to reduce the execution time from that of a uniprocessor was demonstrated.

To improve the system reliability, they also used a ring structure to add fault-tolerance so that decentralized control could automatically isolate the faulty unit. A central processor was designed to detect the faults. In their design, the fault-tolerant feature included two policies: if spare parts were available, the failed units would be automatically replaced by spare units, and if all units are in use, the necessary task would be covered by the central processor with a decrease in servoing frequency. In their experiment, the system was only tolerant of faults in the leg processors.

McGhee, Orin, Pugh, and Patterson [41] proposed a hierarchically structured control for the ASV-84 walking machine. They decomposed the entire control scheme hierarchically such that different levels of control may be implemented by modules. One advantage of the hierarchical approach is that higher levels of sensing and control, such as the use of computer vision in motion planning and remote control, may be modularly added without changing the operating hardware and software.

The on-board computer architecture for the ASV-84 vehicle is composed of a guidance computer, a coordination computer, a cockpit computer and one leg control computer for each leg. Each is an Intel iSBC 86/30 single-board computer, containing an Intel 8086 microprocessor and an 8087 floating-point coprocessor. Different data rates between computers have been designed in such a way that low data rates are used for parallel data ports and high data rates for serially arranged leg control signals.

Klein and Barrientos [42] used a top-down design approach to develop a multimicroprocessor-based controller for a monopod vehicle. The monopod leg has three degrees of freedom. Jacobian control was chosen as the main control algorithm for two reasons. First, this kind of control needs no Inverse Kinematics analysis, which is very time consuming. Second, the commanded positions and velocities for the controller may be specified in Cartesian coordinates avoiding many of the complications of dealing with joint coordinate systems.

Based on the data-flow design method, Klein and Barrientos decomposed the task into a series of sequentially related modules. Then a modular structure was developed such that each node in the data-flow graph corresponds to a single module. The controller was finally composed of a monitoring/test computer, a serial iSBX 351 programmable multimodule board, an iSBX 351 programmable parallel I/O board, an interface to the joystick command input, and a custom-built pulse width modulation control board to link to the vehicle motor electronics. The control kernel function includes four sequential modules: position estimation, motion planning, Jacobian control calculation, and servo level control. Coupling with the data acquisition and monitoring technique, they also considered the system testability in their design.

Results showed good performance for velocity and position tracking.

Ozguner and Kao [43] designed a fault-detectable and reconfigurable multiprocessor system, the Selectively Redundant Multiprocessor (SRMP), for real-time control of a six legged robot. The architecture of SRMP consists of four processing units (each unit consists of an Intel 86/30 microcomputer and an interprocessor buffer module for dynamic match) connected through four buses and a fifth unit simulates the hexapod. Each microcomputer can connect to any of the four buffers through any of four buses such that the data inside each buffer is open to all microprocessors. The SRMP allows two or three processors to execute tasks in redundant configurations. Both software and hardware methods are combined to do the fault detection and correction. Comparisons and voting on the results of redundant processors are controlled by software, but hardware comparators are used to speed up the operations. This architecture emphasizes the reliability instead of the time efficiency of the control.

Finally, multiprocessor implementation of a real-time control system for robot manipulators has been investigated by Lilly [32]. Orin [44] has divided the Inverse Plant Plus Jacobian Control algorithm into eleven computational modules for multiprocessor implementation. Lilly followed with a more detailed investigation of possible multiprocessor configurations and used a system of Intel 86/30 boards with a specially designed operating system to implement this control scheme.

First of all, Lilly scheduled each module of the system on a single processor board and measured the computation time. From these measurements, the communication time was found to be significant relative to the overall computation time of the individual processes and should be considered when scheduling the entire system.

Lilly then developed an optimal parallel schedule based on the individual process computation times. She implemented this schedule on two processors and obtained a speed up of 1.37. Because the computation time of the critical path was long relative to the overall computation time, it was determined that the two-processor configuration achieved the maximum performance in this specific application.

The third implementation was designed to test multirate control. For any multiloop control system, closing of the various loops may be at different rates while still achieving good system stability. There are three basic loops in the Inverse Plant Plus Jacobian Control scheme. The inner loop of Jacobian Control must be controlled at high speed in order to maintain stability while the other loops may run at lower rates. Lilly used 4 processors to implement this control scheme with three different feedback rates. The results showed that this multirate approach has increased the sampling rate of the inner loop significantly over the single-processor and met the real-time requirements. This is an impressive improvement in performance with only a small increase in the number of processors. She also concluded that division of a single module into multiple parallel subtasks would enable parallel algorithms to be implemented. Such parallel computation could greatly improve system computation time. Also, with a different grouping of the computational modules, multirate scheduling may result in significant improvement in system performance.

2.4 Summary

This chapter has presented a brief overview of the previous work in the areas of algorithms for Inverse Kinematics and special-purpose

architectures for robotic control. Several important issues may be summarized as follows:

For algorithms:

- (1) Since analytical approaches for an Inverse kinematics solution are robot dependent, a numerical approach will be used in this work to obtain a general solution.
- (2) Three numerical approaches have been reviewed in this chapter. Since the continuation method has a problem with degeneracy and the Newton-Raphson approach is not efficient, the third approach, integration of joint rates, will be used in this dissertation.
- (3) Most previous algorithms based on the integration of joint rates have numerical difficulty near singularity points. Much of the work of this dissertation will be directed to this problem.
- (4) All previous numerical solutions for Inverse Kinematics based on the velocity integration approach are open-loop. Numerical errors will generally accumulate and the solution will have problems with drift.
- (5) A strictly convergent algorithm which is applicable to redundant robots and has no problems with long-term drift is needed.

For architectures:

- (1) Three different types of architectures have been reviewed in this chapter. From the system point of view, a multiprocessor architecture may be used to implement a complex set of tasks and improve the overall performance if concurrency can be exploited. Since Inverse Kinematics involves relatively few

tasks, another level of implementation may be more appropriate. Systolic architectures are only good for algorithms with a regular structure. Custom VLSI robotics chips require a long design time and cannot be used in all applications since they are special-purpose.

- (2) To solve the Inverse Kinematics problem, a systolic architecture is somewhat inappropriate because of the irregular nature of the numerical Inverse Kinematics algorithms. To reduce the data communications overhead, an architecture based on a single high-speed processor may be the best choice.
- (3) Floating point is needed for the multiplication and addition/subtraction operations in order to provide the required accuracy. The design of a special-purpose architecture based on an off-the-shelf high-speed floating-point chip, which may be used efficiently for the common matrix-vector operations in robotic control, holds much promise.

With this background, a complete algorithm will be developed and a special-purpose architecture will be designed to facilitate the computations of the algorithm such that a real-time solution may be obtained for any kind of robot manipulator with any number of degrees of freedom. The next chapter will formulate the problem to be solved.

CHAPTER 3

PROBLEM FORMULATION

3.1 Introduction

Four problems must be addressed in order to obtain a viable solution for Inverse Kinematics. First of all, a generic solution is preferred. Manipulators with different kinematic configurations have different closed-form analytical solutions. As such, obtaining the closed-form equations for a newly designed manipulator may take considerable effort, if a solution is available at all. Therefore, a manipulator-independent solution, which may be used on any kind of robot manipulator with any number of degrees of freedom, is important for both off-line programming and on-line control.

Second, the degeneracy problem should be solved. Degeneracy occurs when more than one solution to the inverse transform exists. A degeneracy occurs when more than one configuration of the robot manipulator places the end effector in the same position and orientation. A manipulator with more than six joints (redundant) may have an infinite number of possible combinations of joint variables which result in the same end-effector configuration. Special techniques should be applied to handle this problem.

The third problem is the singularity problem which has been discussed in Section 2.2.3. Finally, the Inverse Kinematic solution should be furnished in real time. For any control scheme, which uses joint positions as its (or part of its) inputs, the joint positions should be

provided at a rate which is high enough to keep the system stable. In other words, the computation time for Inverse Kinematics should be smaller than the allowed delay, which is generally a few milliseconds.

Since a generic solution for Inverse Kinematics could not be obtained through an analytical approach, a numerical approach will be used. Furthermore, an algorithm based on the integration of velocity will be used since it has better convergence properties than the direct use of the positions in the Newton-Raphson method (See Chapter 2). The basic algorithm is expressed through the following equations:

$$\dot{\underline{q}} = J^{-1}(\underline{q}) \dot{\underline{x}} \quad (3.1)$$

$$\underline{q} = \int \dot{\underline{q}} dt \quad (3.2)$$

where $\dot{\underline{x}}$ is the velocity vector of the end effector as it moves along the constrained trajectory. The vector $\dot{\underline{x}}$ includes three angular and three translational components and is of dimensions 6×1 . The quantities, $\underline{q}$ and $\dot{\underline{q}}$ are vectors of joint position and rate, respectively, and are of dimensions $N \times 1$. (N is the number of degrees of freedom of the robot manipulator.)

Equations (3.1) and (3.2) use the Inverse Jacobian to transform the end-effector velocity to joint coordinates from which the rates are integrated to obtain the joint positions. To compute the Inverse Jacobian, the Jacobian for the manipulator is first obtained through the use of a set of estimated joint positions. The computation of the Inverse Jacobian could be obtained through Gaussian elimination or any other suitable method. In fact, the Inverse Jacobian is not explicitly obtained; instead, Eq. (3.1) is directly solved for $\dot{\underline{q}}$. If the Jacobian is not a square matrix, special techniques must be applied. Also, the degeneracy and singularity problems should be solved. The algorithms

for the Jacobian and Inverse Jacobian that are used in this work will be presented in the next section. Further discussion on the overall numerical algorithm developed for Inverse Kinematics is given in the next chapter.

Equation (3.2) indicates that the joint positions are obtained from the corresponding rates through numerical integration. When using any numerical method, special attention must be paid to its convergence, accuracy, and time efficiency. The third section of this chapter will introduce the basic integration algorithm used in this work and its associated problems.

Finally, the fourth section of this chapter will examine the real-time requirements for an Inverse Kinematics solution.

3.2 Manipulator Kinematics

According to Sandor's definition [45], the term manipulator kinematics deals with the geometry and the time-dependent aspects of manipulator motion without considering the forces causing the motion. The relationships of interest in this dissertation include Direct Kinematics, Inverse Kinematics, the Jacobian and Inverse Jacobian. Direct Kinematics and Inverse Kinematics transform displacements in joint space to positions of the end effector in Cartesian space and vice versa, respectively. The Jacobian and Inverse Jacobian transform rates in joint space to velocities of the end effector in Cartesian space and vice versa, respectively.

3.2.1 Kinematic Notation for Manipulators

The most widely used parameters for describing the kinematics of linked manipulators were first introduced by Denavit and Hartenberg [32]. Paul fully developed these parameters and systematically

introduced them in [7]. A similar description was also given in Lilly's thesis [32]. These parameters and some of their properties will be briefly presented in this subsection and will be used as a basis for the kinematics described in the following sections.

A manipulator may be considered as a series of links which are connected at joints. A set of N links connected by N joints form a manipulator with N degrees of freedom. The links are numbered from 1, attached to the base, to N at the last link. An end effector is connected to the last link of the manipulator and may be considered as link $(N+1)$. Similarly, the base of the manipulator may be considered as link 0. Joints are numbered so that link i is connected to link $(i-1)$ by joint i . There is no joint between the end effector and the last link.

In order to describe the relationship between links, a coordinate system is associated with each link of the manipulator. The origin of link coordinate system i is located on the axis of joint $(i+1)$, with $\underline{z}_i$ pointing along this axis. The unit vector $\underline{x}_i$ is chosen to be normal to joint axis i and joint axis $(i+1)$ and is directed outward. The y-axis of coordinate system i may be determined from $\underline{x}_i$ and $\underline{z}_i$ through the right-hand rule.

Four parameters may be used to completely describe the geometric relationship between two consecutive link coordinate systems. Fig. 3.1 shows these parameters for link i . The first parameter, θ_i , is the angle of rotation about the axis of joint i . It is measured from the x-axis of link $(i-1)$ to the x-axis of link i . The second parameter, d_i , is the offset distance between the two link normals along the z-axis of joint i , $\underline{z}_{i-1}$. These two parameters describe the geometric relationship between two successively connected links. The third

Figure 3.1 Link Parameters Associated with Link 1.

parameter, a_i , is called the length of the link. It is the common normal distance between the two joints, joint i and joint $(i+1)$. The last parameter, α_i , is the twist of link i , and is defined as the angle between the two joint axes, joint i and $(i+1)$, and is measured in a plane perpendicular to the link common normal. The last two parameters characterize the link itself.

From these four parameters, a 4x4 homogeneous transformation, ${}^{i-1}T_i$, which relates points in coordinate system i to those in coordinate system $(i+1)$, may be computed through the following rotations and translations:

- (1) rotate about $\underline{z}_{i-1}$ with an angle of θ_i ;
- (2) translate along $\underline{z}_{i-1}$ with a distance of d_i ;
- (3) translate along $\underline{x}_i$ with a distance of a_i ;
- (4) rotate about $\underline{x}_i$ with a twist angle of α_i .

For either a revolute or a prismatic joint the result is:

$${}^{i-1}T_i = \begin{bmatrix} c\theta_i & -s\theta_i c\alpha_i & s\theta_i s\alpha_i & a_i c\theta_i \\ s\theta_i & c\theta_i c\alpha_i & -c\theta_i s\alpha_i & a_i s\theta_i \\ 0 & s\alpha_i & c\alpha_i & d_i \\ \hline 0 & 0 & 0 & 1 \end{bmatrix} \quad (3.3)$$

where $c\theta_i$ and $s\theta_i$ indicate the cosine and sine of the angle, respectively.

The matrix ${}^{i-1}T_i$ contains two parts. The top-left part is a 3x3 orientation matrix which gives all orientation information and is expressed as ${}^{i-1}U_i$. The first three components of the fourth column of

${}^{i-1}T_i$ form a 3×1 translation vector which contains all the relative position information and will be denoted as ${}^{i-1}\underline{p}_i^*$.

It is often useful to have the components of $\underline{p}_i^*$ in the i th coordinate system. Transforming ${}^{i-1}\underline{p}_i^*$ to coordinate system i gives:

$${}^i\underline{p}_i^* = {}^{i-1}U_i^T {}^{i-1}\underline{p}_i^* = \begin{bmatrix} a_i \\ d_i s\alpha_i \\ d_i c\alpha_i \end{bmatrix}. \quad (3.4)$$

The component vector ${}^i\underline{p}_i^*$ gives the origin of coordinate system i with respect to the origin of coordinate system $(i-1)$ in terms of coordinate system i . Since ${}^i\underline{p}_i^*$ contains no variable elements (for a revolute joint), it may usually be computed off-line.

The general transformation from the coordinate system of link j to the coordinate system of link k may be expressed by a homogeneous matrix kT_j . The matrix kT_j may be obtained through multiplication of the intermediate homogeneous matrices. Similarly, the rotational part of this matrix may be expressed as kU_j . The translational vector, ${}^k\underline{t}_j$, represents the position of the origin of coordinate system j with respect to the origin of coordinate system k expressed in terms of coordinate system k . If $k = 0$, a position vector $\underline{p}_j$ is used and it extends from the origin of the base coordinate system to the origin of coordinate system j . Similarly, if $k = N+1$, $\underline{r}_j$ is used to express a vector from the end effector to joint j . All of these are shown in Fig. 3.2.

Figure 3.2 Depiction of Vectors $\underline{p}_j$, $\underline{r}_j$, $\underline{p}_i^*$, $\underline{k}_{tj}$ and Transform ${}^{i-1}U_i$ for a Manipulator.

3.2.2 Direct Kinematics

Direct Kinematics computes the position and orientation of the end effector from the corresponding joint displacements and other link parameters. The orientation and position of the end effector with respect to an inertial reference frame may be described by a 4x4 homogeneous transformation matrix, X . For an N -degree-of-freedom manipulator, the transformation relating the coordinate system of the last link to the base coordinate system may be computed by:

$${}^0T_N = {}^0T_1 {}^1T_2 {}^2T_3 \dots {}^{N-2}T_{N-1} {}^{N-1}T_N \quad (3.5)$$

Usually, the base coordinate system is related to the inertial reference frame by a transformation Z . Also, the transformation that relates the coordinate system of the end effector to the last link, link N , is described by E . Both of these are usually fixed transformations. Using these transformations, the matrix X may be obtained as follows:

$$X = Z {}^0T_N E \quad (3.6)$$

Since the last row of the homogeneous transform is always $[0 \ 0 \ 0 \ 1]$, the computation of Direct Kinematics may be more time efficient using U and $\underline{t}$ instead of T . Consider the following multiplication of two homogeneous matrices:

$$\begin{aligned} {}^i T_N &= {}^i T_{i+1} {}^{i+1} T_N \\ &= \begin{bmatrix} {}^i U_{i+1} & {}^i \underline{t}_{i+1} \\ \hline 0 & 1 \end{bmatrix} \begin{bmatrix} {}^{i+1} U_N & {}^{i+1} \underline{t}_N \\ \hline 0 & 1 \end{bmatrix} \end{aligned}$$

$$= \begin{bmatrix} {}^i U_N & {}^i t_N \\ \hline 0 & 1 \end{bmatrix} . \quad (3.7)$$

A more efficient implementation is given through the following equations:

$${}^i U_N = {}^i U_{i+1} {}^{i+1} U_N \quad (3.8)$$

$${}^i t_N = {}^i U_{i+1} {}^{i+1} t_N + {}^i t_{i+1} . \quad (3.9)$$

Therefore, the computation is operated on only 3x3 matrices and 3x1 vectors instead of 4x4 matrices. For 4x4 matrix multiplication 64 scalar multiplications and 48 scalar additions are required, while the second approach with 3x3 matrices and 3x1 vectors needs only 36 multiplications and 27 additions. The speedup is 1.78.

Furthermore, since the rotational matrix U is a 3x3 orthogonal matrix, any column of this matrix may be obtained from the cross product of the other two columns. Through this approach, to complete the last column only 6 multiplications and 3 additions are required instead of 9 multiplications and 6 additions. The total computation will be 33 multiplications and 24 additions. The speedup is then 1.97. One more advantage of this approach is that the final matrix is guaranteed to be orthogonal. Some amount of normalization, though, may be necessary.

3.2.3 Jacobian

The Jacobian matrix, $J(\underline{q})$, relates the joint rates, $\dot{\underline{q}}$, to the end effector velocity, $\dot{\underline{x}}$ and is of dimensions $6 \times N$ where N is the number of

degrees of freedom of the manipulator. The end effector velocity consists of two portions: $\underline{\omega}$ and $\underline{v}$. Both are 3x1 vectors. The vector $\underline{\omega}$ is the angular velocity and the vector $\underline{v}$ is the translational velocity of the end effector. Orin and Schrader's results [36] show that one of the most efficient algorithms for computing the Jacobian may be obtained if the velocity is expressed in the coordinate system of the end effector. The relationship which defines the Jacobian may be expressed through the following equation:

$$\begin{bmatrix} {}^{N+1}\underline{\omega} \\ {}^{N+1}\underline{v} \end{bmatrix} = {}^{N+1}J(\underline{q}) \dot{\underline{q}} \quad (3.10)$$

where

$${}^{N+1}J(\underline{q}) = \begin{bmatrix} {}^{N+1}x_{Y_1} & {}^{N+1}x_{Y_2} & \cdots & {}^{N+1}x_{Y_N} \\ {}^{N+1}y_{Y_1} & {}^{N+1}y_{Y_2} & \cdot & {}^{N+1}y_{Y_N} \\ {}^{N+1}z_{Y_1} & \cdot & \cdot & {}^{N+1}z_{Y_N} \\ {}^{N+1}x_{\beta_1} & \cdot & \cdot & {}^{N+1}x_{\beta_N} \\ {}^{N+1}y_{\beta_1} & \cdot & \cdot & {}^{N+1}y_{\beta_N} \\ {}^{N+1}z_{\beta_1} & \cdot & \cdot & {}^{N+1}z_{\beta_N} \end{bmatrix} \quad (3.11)$$

The components of the Jacobian and the end effector velocity are expressed in end-effector coordinates, as indicated by the leading superscript. Although they may be expressed in other coordinate systems, the form shown above is especially efficient and useful in our

application for manipulator control [47].

In Eq. (3.11), the values of ${}^{N+1}\underline{y}_i$ and ${}^{N+1}\underline{p}_i$ may be derived as follows [36]:

$${}^{N+1}\underline{U}_{N+1} = I \quad (3.12)$$

$${}^{N+1}\underline{U}_{i-1} = {}^{N+1}\underline{U}_i {}^{i-1}\underline{U}_i^T \quad i = (N+1), \dots, 2, 1 \quad (3.13)$$

$${}^{N+1}\underline{y}_i = {}^{N+1}\underline{U}_{i-1} \begin{bmatrix} 0 \\ 0 \\ 1 \end{bmatrix} \quad i = 1, 2, \dots, N \text{ revolute joint} \quad (3.14)$$

$${}^{N+1}\underline{y}_i = \underline{0} \quad i = 1, 2, \dots, N \text{ sliding joint} \quad (3.15)$$

$${}^{N+1}\underline{r}_{N+1} = \underline{0} \quad (3.16)$$

$${}^{N+1}\underline{r}_{i-1} = {}^{N+1}\underline{r}_i - {}^{N+1}\underline{U}_i {}^i \underline{p}_i^* \quad i = (N+1), \dots, 2, 1 \quad (3.17)$$

$${}^{N+1}\underline{p}_i = {}^{N+1}\underline{y}_i \times (-{}^{N+1}\underline{r}_{i-1}) \quad i = 1, 2, \dots, N \text{ revolute joint} \quad (3.18)$$

$${}^{N+1}\underline{p}_i = {}^{N+1}\underline{U}_{i-1} \begin{bmatrix} 0 \\ 0 \\ 1 \end{bmatrix} \quad i = 1, 2, \dots, N \text{ sliding joint.} \quad (3.19)$$

The above method is a serial algorithm which involves a set of recursive equations executed from the end effector to the base. This algorithm needs $(30N-25)$ multiplications and $(15N-25)$ additions to compute the Jacobian matrix. Another method which takes a few more computations, $(30N-18)$ multiplications and $(14N-15)$ additions, was used by Paul [3]. His method was expressed in [36] as follows:

$${}^{N+1}T_{N+1} = I \quad (3.20)$$

$${}^{i-1}T_{N+1} = {}^{i-1}T_i {}^iT_{N+1} \quad i = (N+1), \dots, 2, 1 \quad (3.21)$$

$${}^{N+1}y_i = {}^{i-1}U_{N+1}^T \begin{bmatrix} 0 \\ 0 \\ 1 \end{bmatrix} \quad i = 1, 2, \dots, N \text{ revolute joint} \quad (3.22)$$

$${}^{N+1}y_i = 0 \quad i = 1, 2, \dots, N \text{ sliding joint} \quad (3.23)$$

$${}^{N+1}\beta_i^j = - \left[{}^{i-1}U_{N+1}^j \times {}^{i-1}r_{i-1} \right]^T \begin{bmatrix} 0 \\ 0 \\ 1 \end{bmatrix} \quad \begin{matrix} j = 1, 2, 3 \\ i = 1, 2, \dots, N \text{ revolute joint} \end{matrix} \quad (3.24)$$

$${}^{N+1}\beta_i = {}^{i-1}U_{N+1}^T \begin{bmatrix} 0 \\ 0 \\ 1 \end{bmatrix} \quad i = 1, 2, \dots, N \text{ sliding joint.} \quad (3.25)$$

In Eq. (3.24), ${}^{N+1}\beta_i^j$ is the j th component of the vector ${}^{N+1}\beta_i$; vector ${}^{i-1}U_{N+1}^j$ is column j of the 3×3 orientation part of ${}^{i-1}T_{N+1}$; and vector ${}^{i-1}r_{i-1}$ is the first three elements of the fourth column of ${}^{i-1}T_{N+1}$.

Combining Eqs. (3.5) and (3.6) and since E is the same as ${}^NT_{N+1}$, Direct Kinematics may be expressed as:

$$X = Z {}^0T_1 {}^1T_2 \dots {}^{N-2}T_{N-1} {}^{N-1}T_N {}^NT_{N+1} \quad (3.26)$$

The fact that the computation of ${}^0T_{N+1}$ is included in the computation of both Direct Kinematics and the Jacobian may be used to

increase the computation speed. After the computation of the Jacobian, ${}^0T_{N+1}$ is available. To obtain the results for Direct Kinematics, only a matrix multiplication need be executed:

$$X = Z {}^0T_{N+1} . \quad (3.27)$$

In many applications, such as Inverse Plant Plus Jacobian Control [44], Gupta's numerical algorithm for solving Inverse Kinematics [19], etc., computation of both Direct Kinematics and the Jacobian are required. The duplicate computation of ${}^0T_{N+1}$ may be eliminated by combining them in a common computation module. This is the most efficient method for computing both Direct Kinematics and the Jacobian and will be applied in this dissertation.

Based on the fact that the position, ${}^{N+1}r_{i-1}$ and orientation, ${}^{N+1}u_{i-1}$ of the $(i-1)^{th}$ link may be computed as soon as the position and orientation of the i^{th} link is available and then the i^{th} column of the Jacobian matrix may be computed accordingly, Orin [31] derived a pipelined algorithm and described a possible implementation with systolic arrays. Also, a parallel algorithm with a computation time which varies as $\log_2 N$ has been developed such that the implementation on a hypercube-connected systolic array is possible. While neither of these algorithms are used in the present work, greater speedup, if needed, may be obtained by using such a parallel or pipelining approach. The details of these algorithms are given in [31].

3.2.4 Inverse Jacobian

Given the end effector velocity vector (6×1) , the Inverse Jacobian is used to obtain the corresponding joint rates. The algorithm to compute the Inverse Jacobian is different for manipulators with

different numbers of degrees of freedom. If $N=6$, the Jacobian matrix is square and its inverse may be solved by simply applying Gaussian Elimination to the six equations. For cases in which N is not equal to six, a pseudo-inverse is employed. The criterion used when N is greater than six is to minimize the energy spent on the movement (introduced by Whitney [23]). Other criteria may be used and examples may be found in [48,49].

The algorithm which considers different cases of number of degrees of freedom has been derived in the following manner [32]:

Case 1: For $N=6$, the following relationship holds:

$$\underline{\dot{q}} = J^{-1} \underline{\dot{x}} . \quad (3.28)$$

In this case, computation of $\underline{\dot{q}}$ includes one simple step:

Given the equation $\underline{\dot{x}} = J \underline{\dot{q}}$, apply Gaussian Elimination to obtain $\underline{\dot{q}}$.

Case 2: For $N<6$, the following relationship holds:

$$\underline{\dot{q}} = [J^T J]^{-1} J^T \underline{\dot{x}} . \quad (3.29)$$

In this case, computation of $\underline{\dot{q}}$ includes three steps:

a) $J^T J = A;$

b) $J^T \underline{\dot{x}} = \underline{b};$

c) Given the equation $A \underline{\dot{q}} = \underline{b}$, apply Gaussian Elimination to obtain $\underline{\dot{q}}$.

Case 3: For $N>6$, The following relationship holds:

$$\underline{\dot{q}} = J^T [J J^T]^{-1} \underline{\dot{x}} . \quad (3.30)$$

In this case, computation of $\underline{\dot{q}}$ also includes three steps:

a) $J J^T = R ;$

b) Given the equation $R \underline{s} = \underline{\dot{x}}$, apply Gaussian Elimination to obtain $\underline{s}$;

c) $\underline{\dot{q}} = J^T \underline{s}$.

It should be noted that in no case is the Inverse Jacobian explicitly determined. Rather, it is implicitly used to obtain the joint rates.

3.3 Numerical Integration

In order to solve Eq. (3.2), a numerical integration method should be used. Various numerical integration methods were introduced and examined in [50-52]. Considering problems with accuracy and stability, the most popular and widely used methods are of fourth order. Methods of lower order are not highly accurate because of truncation errors, while higher-order methods suffer from serious limitations on the step size.

The two best known fourth-order methods are Runge-Kutta methods and predictor-corrector methods. For the same degree of accuracy, the predictor-corrector methods prove to be better than the Runge-Kutta methods since they are faster by a factor of between two and four [50]. This advantage in speed is mainly due to the fact that for a fourth-order Runge-Kutta method, the derivative function has to be evaluated four times per iteration while two evaluations of the derivative function is enough for the predictor-corrector methods. A disadvantage of predictor-corrector methods is that they are not self-starting, and usually the Euler method or Runge-Kutta method should be used to start the integration.

Among various fourth-order predictor-corrector methods, the combination of the Crane-Klopfenstein predictor and Adams-Bashforth corrector has the largest maximum allowable step size [53]. The

detailed derivation of these equations are given in [50,53]. A large allowable step size improves the efficiency of the algorithm. Therefore, based on the considerations of stability, accuracy, and computational costs, the following equations will be used in this dissertation [19]:

Predictor:

$$\begin{aligned} y(t+\Delta t) = & 1.547652 y(t) - 1.867503 y(t-\Delta t) \\ & + 2.017204 y(t-2\Delta t) - 0.697353 y(t-3\Delta t) \\ & + \Delta t[2.002247 y'(t) - 2.03169 y'(t-\Delta t) \\ & + 1.818609 y'(t-2\Delta t) - 0.74320 y'(t-3\Delta t)] \end{aligned} \quad (3.31)$$

Corrector:

$$\begin{aligned} y(t+\Delta t) = & y(t) + \Delta t[0.375 y'(t+\Delta t) + 0.791667 y'(t) \\ & - 0.208333 y'(t-\Delta t) + 0.041667 y'(t-2\Delta t)] \end{aligned} \quad (3.32)$$

where $y(t)$ is a state variable at time t and $y'(t)$ is its derivative.

3.4 Requirements for Real-Time Inverse Kinematics

In this section, the specifications for a real-time solution to Inverse Kinematics will be investigated. Three key issues must be considered for a real-time solution: accuracy, robustness near singularities, and real-time computation.

Two aspects of accuracy are of concern in robot manipulators: joint position accuracy and end-effector position accuracy. The possible errors in each joint of the manipulator may accumulate and convert to position error of the end effector. Most industrial robot manipulators have a specification for only the position accuracy of the end effector. Position repeatability is defined as the maximum possible error that the manipulator may have if it is repeatedly commanded to go

to the same position. Depending on its size, maximum velocity, and application, the nominal standard value for position repeatability varies from 0.5 mm to 0.02 mm (1 mil). Due to the size of the manipulator, the corresponding joint accuracy may vary over a large range. A simple but useful relationship between joint and end effector position errors may be expressed as follows:

$$\rho = l_{\max} \phi \quad (3.33)$$

where ϕ is the joint angle error expressed in radians, $l_{\max}$ is the maximum reach of the manipulator, and ρ is the position repeatability.

For the case that a small manipulator has a maximum reach of 500 mm and a position repeatability of 0.02 mm, the corresponding maximum joint error may be computed as:

$$\phi = (0.02/500) * 180^\circ / \pi = 0.0023 \text{ deg.} \quad (3.34)$$

On the other hand, for a large robot with a maximum arm extension of 3000 mm and a position repeatability of 0.5mm, the maximum allowable error on the shoulder joint is approximately 0.01 degrees.

Since Inverse Kinematics has difficulties in singular configurations, it is impossible to obtain the solution exactly at these points. However, a stable algorithm should still be able to find the solution when the manipulator is located near these positions. To determine how close a distance is required, the maximum speed of the end effector and the control update time should be considered. The relationship between these quantities is expressed as follows:

$$e_{\max} = v_{\max} \Delta t \quad (3.35)$$

where e_{MAX} is the position error, v_{MAX} is the maximum velocity of the end effector, and Δt is the control update time. For example, if a manipulator has a maximum end effector speed of 500 mm/sec and the minimum step size used for control is 0.01 second, the Inverse Kinematics algorithm should still give correct results when the end effector is more than 5 mm away from any singularity position. If the minimum step size is set to 0.001 second, then the solution should still converge even when the end effector is only 0.5 mm away from a singular position. Therefore, for higher velocity ranges, the requirement is very strict and difficult to satisfy. An algorithm with such capability will be called robust.

The real-time requirement is determined by the mechanical structure of the manipulator. Usually a stable system needs a control update at a rate of 20 times the natural frequency of the robot manipulator. The natural frequencies of most manipulators are below 50 Hz. For example, the natural frequency of the Stanford arm is 16 Hz, 32 Hz for the MIT arm [18], and only 15Hz for the PUMA [47]. Therefore, a minimum update frequency for the control may be several hundred hertz. Of course, Inverse Kinematic solutions should also be updated with a similar rate. In other words, the computation time for solving Inverse Kinematics should be smaller than a few milliseconds.

The purpose of this research then is to find a solution of Inverse Kinematics which can meet all the following requirements:

- 1) The maximum position error of the end effector should be smaller than the repeatability error of most industrial robots, i.e., 0.5 mm for large robots with high speed motion and 0.02 mm for high accuracy assembly robots;

- 2) The solution should be computed in real time; i.e. in our case, at least 1000 solutions per second;
- 3) The solution should be robust even near singularity points.

3.5 Summary

This chapter has pointed out the problems that must be addressed in order to solve Inverse Kinematics in real time. One possible approach to obtaining a viable solution is based on the application of the numerical velocity integration algorithm and a real-time architecture. This approach includes three main parts:

- (1) Find a generic algorithm for Inverse Kinematics,
- (2) Create a special-purpose architecture to facilitate the matrix-vector operations required, and
- (3) Map the algorithm onto the designed architecture efficiently, such that the solution may be obtained in real time.

This chapter has formulated the approach to be taken to providing a real-time solution to Inverse Kinematics. Specific criteria for the solution have also been presented in the previous section. The following chapters will give details of the approach taken. First of all, the exact numerical algorithm used for Inverse Kinematics will be presented in the next chapter.

Chapter 4

NUMERICAL ALGORITHM FOR INVERSE KINEMATICS

4.1 Introduction

This chapter will present the complete algorithm for Inverse Kinematics. As discussed in the previous two chapters, a complete Inverse Kinematics algorithm should be generic, robust even near singularities, and time efficient. Only a numerical approach has the capability of solving Inverse Kinematics for any robot manipulator with any number of degrees of freedom and arbitrary kinematic configuration, and thus will be used in this work. However, the basic numerical method which is based on the Jacobian matrix involves considerable computation and has numerical difficulties near singular configurations. These issues will be addressed in this chapter.

The inefficiency of most numerical methods is due to the complex computation of the Inverse Jacobian and the convergence rate of integration. An efficient algorithm for the Jacobian has been presented in the previous chapter. Also, an efficient algorithm for numerical integration was introduced (predictor-corrector integration method). In the next section, this integration algorithm will be expressed in vector form and the convergence problem will be pointed out.

In the third section of the chapter, an error evaluation method will be presented for Inverse Kinematics, and it will be used as a check criterion to result in an algorithm which is strictly convergent. This error function is based on the computation of the norm of the deviation matrix which is the difference between the designed end effector position/orientation and its estimated values.

The complete algorithm with position feedback will be presented in the fourth section through the use of a flowchart and associated explanation. The method of using the absolute error for the convergence criterion will also be presented. With this algorithm the number of evaluations of the joint rates may be reduced to a minimum. Also, this algorithm is applicable to the general N degree-of-freedom manipulator. The developed algorithm has no degeneracy problem, no singularity problem, and is strictly convergent even with an initial offset of position.

4.2 Predictor-Corrector Integration Algorithm

A predictor-corrector algorithm with large maximum allowable step size has been introduced in Section 3.3. In this application, the state variables are the joint position vector, $\underline{q}$, and its derivative the joint rate vector, $\dot{\underline{q}}$. To present the complete Inverse Kinematics algorithm more clearly, the predictor-corrector integration algorithm may be rewritten in vector form as follows:

Predictor:

$$\underline{q}(t+\Delta t) = \underline{q}(t) + \Delta t \dot{\underline{q}}(t) \quad (4.1)$$

Corrector:

$$\underline{q}(t+\Delta t) = \underline{q}(t) + \Delta t \dot{\underline{q}}(t+\Delta t) \quad (4.2)$$

where $\underline{a}$, $\underline{b}$, and $\underline{c}$ are 4x1 constant vectors:

$$\underline{a} = [1.547652 \quad -1.867503 \quad 2.017204 \quad -0.697353]^T \quad (4.3)$$

$$\underline{b} = [2.002247 \quad -2.031690 \quad 1.818609 \quad -0.743200]^T \quad (4.4)$$

$$\underline{c} = [0.375000 \quad 0.791667 \quad -0.208333 \quad 0.041667]^T \quad (4.5)$$

and Q and $\dot{Q}$ are matrices used to store the last four values of the joint position or rate vectors, respectively:

$$Q(t+\Delta t) = [\underline{q}(t) \quad \underline{q}(t-\Delta t) \quad \underline{q}(t-2\Delta t) \quad \underline{q}(t-3\Delta t)] \quad (4.6)$$

$$\dot{Q}(t+\Delta t) = [\underline{\dot{q}}(t+\Delta t) \quad \underline{\dot{q}}(t) \quad \underline{\dot{q}}(t-\Delta t) \quad \underline{\dot{q}}(t-2\Delta t)]. \quad (4.7)$$

In usual applications of the predictor-corrector method, the predictor is used once and the corrector is used as many times as is necessary to achieve convergence, that is, until the successive positions are close enough to meet the convergence criteria. Gupta and Kazerounian [19] pointed out that this type of basic predictor-corrector algorithm has poor stability in robot kinematics problems. When the manipulator moves close to any singular configuration, this convergence criterion, the difference between two successive estimated positions, cannot guarantee a convergent solution. Their simulation results showed that the basic algorithm would diverge if accurate results were required near singularities.

To solve this problem, two possible approaches [19,49] have been proposed. For redundant robots, Wampler [49] reformulated the exact pseudoinverse equation as a damped least-squares problem and eliminated the discontinuity at singularities by introducing a small damping factor to keep the condition number of the Jacobian matrix under a predefined maximum value. The disadvantage of this approach is that

the value of this damping factor is dependent on the particular robot mechanism and should be adjusted according to actual accuracy requirements through experimentation. The second approach, which was first proposed by Gupta and Kazerounian [19], has no such kind of problem and is applicable to any general robot manipulator. Their method changed the criterion in the algorithm from the relative difference between two successive computed positions to an absolute error between the desired position and the estimated position. However, their algorithm still has a long-term drift problem and might not converge for any initial position error. The equations for computing the absolute error will be presented in the next section and a complete algorithm with none of these problems will be developed and explained later.

4.3 Error Estimation

The accuracy of the estimated joint positions may be judged by comparing the corresponding end effector position with the specified task position in Cartesian space. If the estimated end effector position can be directly monitored and controlled, the adverse influence of the nonlinearities in the transformation between joint space and Cartesian space may be overcome.

In Cartesian space, the end effector position may be expressed through a homogeneous matrix X , which includes a translational position vector, $\underline{p}$ and a rotation matrix, R :

$$X = \left[\begin{array}{c|c} R & \underline{p} \\ \hline 0 & 1 \end{array} \right]. \quad (4.8)$$

The rotation matrix R is a 3×3 matrix, and may be expressed as three orthogonal unit vectors $\underline{a}$, $\underline{o}$, and $\underline{n}$, with $\underline{a} = \underline{n} \times \underline{o}$:

$$R = [\underline{n} \ \underline{o} \ \underline{a}] . \quad (4.9)$$

Comparison of the estimated end effector position and the desired task position may be accomplished by using the deviation matrix, D , which is computed as follows:

$$D = X^{-1}(X_d - X), \quad (4.10)$$

or

$$D = X^{-1}X_d - I, \quad (4.11)$$

where

$$\begin{aligned} X^{-1}X_d &= \begin{bmatrix} \underline{n} & \underline{o} & \underline{a} & \underline{p} \\ 0 & 0 & 0 & 1 \end{bmatrix}^{-1} \begin{bmatrix} \underline{n}_d & \underline{o}_d & \underline{a}_d & \underline{p}_d \\ 0 & 0 & 0 & 1 \end{bmatrix} \\ &= \begin{bmatrix} \underline{n}^T & \underline{n} \cdot (-\underline{p}) \\ \underline{o}^T & \underline{o} \cdot (-\underline{p}) \\ \underline{a}^T & \underline{a} \cdot (-\underline{p}) \\ 0 & 0 & 0 & 1 \end{bmatrix} \begin{bmatrix} \underline{n}_d & \underline{o}_d & \underline{a}_d & \underline{p}_d \\ 0 & 0 & 0 & 1 \end{bmatrix} \\ &= \begin{bmatrix} \underline{n} \cdot \underline{n}_d & \underline{n} \cdot \underline{o}_d & \underline{n} \cdot \underline{a}_d & \underline{n} \cdot (\underline{p}_d - \underline{p}) \\ \underline{o} \cdot \underline{n}_d & \underline{o} \cdot \underline{o}_d & \underline{o} \cdot \underline{a}_d & \underline{o} \cdot (\underline{p}_d - \underline{p}) \\ \underline{a} \cdot \underline{n}_d & \underline{a} \cdot \underline{o}_d & \underline{a} \cdot \underline{a}_d & \underline{a} \cdot (\underline{p}_d - \underline{p}) \\ 0 & 0 & 0 & 1 \end{bmatrix} . \quad (4.12) \end{aligned}$$

Combining Eq. (4.11) and (4.12) gives:

$$\begin{aligned}
 D &= \left[\begin{array}{ccc|c} \underline{n} \cdot \underline{n}_d - 1 & \underline{n} \cdot \underline{o}_d & \underline{n} \cdot \underline{a}_d & \underline{n} \cdot (\underline{p}_d - \underline{p}) \\ \underline{o} \cdot \underline{n}_d & \underline{o} \cdot \underline{o}_d - 1 & \underline{o} \cdot \underline{a}_d & \underline{o} \cdot (\underline{p}_d - \underline{p}) \\ \underline{a} \cdot \underline{n}_d & \underline{a} \cdot \underline{o}_d & \underline{a} \cdot \underline{a}_d - 1 & \underline{a} \cdot (\underline{p}_d - \underline{p}) \\ \hline 0 & 0 & 0 & 0 \end{array} \right] \\
 &= \left[\begin{array}{c|c} \Delta R & \Delta \underline{p} \\ \hline 0 \ 0 \ 0 & 0 \end{array} \right] . \tag{4.13}
 \end{aligned}$$

For small position and orientation errors, the diagonal terms of D are nominally zero and the off-diagonal terms are directly related to the orientation and translation errors. These error terms may be reduced to a single variable, δ , which is defined as:

$$\delta = |\Delta \underline{p}|^2 + k_e |\Delta R|^2 , \tag{4.14}$$

where

$$\begin{aligned}
 |\Delta R|^2 &= (\underline{n} \cdot \underline{o}_d)^2 + (\underline{n} \cdot \underline{a}_d)^2 + (\underline{o} \cdot \underline{n}_d)^2 \\
 &\quad + (\underline{o} \cdot \underline{a}_d)^2 + (\underline{a} \cdot \underline{n}_d)^2 + (\underline{a} \cdot \underline{o}_d)^2 , \tag{4.15}
 \end{aligned}$$

and

$$\begin{aligned}
 |\Delta \underline{p}|^2 &= [\underline{n} \cdot (\underline{p}_d - \underline{p})]^2 + [\underline{o} \cdot (\underline{p}_d - \underline{p})]^2 \\
 &\quad + [\underline{a} \cdot (\underline{p}_d - \underline{p})]^2 . \tag{4.16}
 \end{aligned}$$

The constant k_e is a weighting factor and accounts for the differences between angular and linear units.

In typical industrial robots, a reasonable correspondence between an orientation error of 0.03 degree is a position error of about 0.05 mm. Then k_e is computed based on the assumption that the orientation error, $|\Delta R|^2$ have similar effects as the translation error, $|\Delta p|^2$. It is reasonable to assume that each of six off-diagonal elements of ΔR has the same average value of 0.03° and each of three elements of Δp is 0.05 mm. The constant 0.03° may be expressed in radians as follows:

$$\Delta\theta = 0.03 * \pi / 180 = 0.000524 \text{ rad.} \quad (4.17)$$

The constant k_e may be derived through the following equation:

$$k_e * 6 * (0.000524) = 3 * (0.05) \quad (4.18)$$

$$k_e = 4552.47 \text{ mm/deg} . \quad (4.19)$$

Therefore, Eq. (4.14) may be rewritten as:

$$\delta = |\Delta p|^2 + 4552.47 * |\Delta R|^2 . \quad (4.20)$$

4.4 Strictly Convergent Inverse Kinematics Algorithm

The functional block diagram showing the use of Inverse Kinematics in a robot control system is given in Fig. 4.1. The motion planning module provides the desired end effector position x_d and the desired end effector velocity $\dot{x}_d$, and furnishes these to the Inverse Kinematics module. Inverse Kinematics transforms the desired position into

Figure 4.1 Functional Block Diagram Showing the Use of Inverse Kinematics in a Robot Control System.

the corresponding joint angles. Then the joint controllers use the joint angles as set points to drive the manipulator. Therefore, the inputs to Inverse Kinematics are the Cartesian position and velocity vectors of the end effector, and the output is the vector of joint angles.

The principle of using velocity integration as the basis for a solution to Inverse Kinematics is expressed through the following relations:

$$\dot{\underline{q}} = J^{-1}(\underline{q}) \left[\dot{\underline{x}}_d + K_p \underline{\lambda} (\underline{x}_d - \underline{x}(\underline{q})) \right] \quad (4.21)$$

$$\underline{q} = \int \dot{\underline{q}} \, dt \quad . \quad (4.22)$$

In Eq. (4.21), the difference between the desired and estimated values of the end effector position/orientation is computed and transformed into a 6x1 vector, $\underline{\lambda}$. This vector, containing small differences of orientation and position, is then multiplied by a diagonal gain matrix K_p and is used to provide position feedback. It is added to the joint rates to avoid any problem with drift resulting from numerical integration. The detailed equations for obtaining vector $\underline{\lambda}$ are given in Section 6.4.3. Also, the effects of this position feedback on the performance of the algorithm will be discussed there.

To compute the Inverse Jacobian of a manipulator with N degrees of freedom, the pseudoinverse [48,54] will be used for $N \neq 6$, and Gaussian Elimination with partial pivoting will be used to directly obtain the joint rates. By minimizing the Euclidean norm of $\dot{\underline{q}}$, this approach will result in a continuous solution when more than one solution exists as is the case for $N > 6$. The detailed equations have been given in Section 3.2.4.

In the selection of the integration method for computing the joint position, stability, accuracy, and time efficiency should be considered. For the same degree of accuracy, since the predictor-corrector algorithm needs only two joint rate evaluations for each iteration while a fourth-order Runge-Kutta algorithm needs four rate evaluations, the predictor-corrector approach is more efficient. Also, the Crane-Klopfenstein predictor [53] and the Adams-Moulton corrector [1,19,50-52] will be used give the maximum range of absolute stability.

The flow chart for the Inverse Kinematics algorithm is shown in Fig. 4.2. Several different values of the error variable, δ , are used in the algorithm, and are defined as follows:

$$\delta_1 = f [X_d(t+\Delta t), X(t)] \quad (4.23)$$

$$\delta_2 = f [X_d(t+\Delta t), X_p(t+\Delta t)] \quad (4.24)$$

$$\delta_3 = f [X_d(t+\Delta t), X_c(t+\Delta t)] \quad (4.25)$$

where X_p and X_c are the values of the end effector position that are computed through the use of Direct Kinematics after a new set of joint angles are computed by either prediction or correction, respectively. The error function has been defined in the previous section. The use of this absolute error instead of the relative error, as is the case in the general predictor-corrector algorithm, resolves the difficulties near singularities.

This algorithm may be explained in a step-by-step fashion as follows:

Step 1. Compute δ_1 , the deviation between the current estimated end effector position, $X(t)$ and the next specified task position, $X_d(t+\Delta t)$.

Figure 4.2 Flow Chart of the Inverse Kinematics Algorithm.

- Step 2. Use the predictor equation to predict the next set of joint positions, $q_p(t+\Delta t)$.
- Step 3. Compute the predicted end effector position, $x_p(t+\Delta t)$, based on the predicted joint positions, $q_p(t+\Delta t)$.
- Step 4. Compute δ_2 , the deviation between the predicted end effector position, $x_p(t+\Delta t)$, and the specified task position, $x_d(t+\Delta t)$.
- Step 5. If $\delta_2 > \delta_1$, then the predicted value is well out of range. This occurs when a large change occurs along the trajectory or a discontinuity (or singularity position) is encountered. If the abrupt change is due to the selection of a time step size which is too large, the step size may be decreased (divided by two) before restarting the execution of this algorithm by going back to step 1. Otherwise, if the step size has been initially selected to be small (the case in this research), this situation indicate a singularity point. If $\delta_2 < \delta_1$, the predictor has improved the estimate for the joint positions, and the algorithm goes on to the next step. This check guarantees that the next iteration step will always move the end effector closer to the desired position and thus the algorithm is strictly convergent.
- Step 6. If $\delta_2 < \epsilon$, the deviation is smaller than the convergence criterion, and no steps of correction are required. Go to step 7. On the other hand, if $\delta_2 > \epsilon$, correction is necessary (step 8).

- Step 7. Evaluate the new joint rates, $\dot{\underline{q}}(t+\Delta t)$, and use the predicted joint position vector, $\underline{q}_p$ for the output, $\underline{q}$. Go to step 13.
- Step 8. Evaluate the joint rates, $\dot{\underline{q}}$, and compute the corrected joint positions $\underline{q}_c(t+\Delta t)$.
- Step 9. Use the corrected joint positions $\underline{q}_c(t+\Delta t)$ to compute the corresponding end effector position $\underline{x}_c(t+\Delta t)$.
- Step 10. Compute δ_3 , the deviation between the corrected end effector position, $\underline{x}_c(t+\Delta t)$, and the specified task position, $\underline{x}_d(t+\Delta t)$.
- Step 11. If $\delta_3 > \delta_2$, the corrected joint positions, $\underline{q}_c$, is worse than the predicted $\underline{q}_p$. This occurs when the end effector has been moved near a singularity point. The algorithm indicates that a singularity configuration has been detected.
- Step 12. Repeat steps 8, 9, 10, and 11 until $\delta_3 < \epsilon$ or the number of iterations is larger than a maximum allowed number. If $\delta_3 < \epsilon$, the corrected estimates are sufficiently accurate. Otherwise, correction should be repeated. If successive correction improves the solution, it will converge and the deviation δ_3 will be smaller than ϵ . On the other hand, if correction does not result in a better solution after several iterations, a singularity point has been detected. A maximum allowable repetition number, $M_{\max}$ is used to detect this

situation. If $\delta_3 < \epsilon$, the corrected joint positions $\underline{q}_c$ are used as the output, $\underline{q}$.

- Step 13. Update the most recent joint position matrix, Q , and joint rate matrix, $\dot{Q}$, by using the last four sets of joint positions and rates.
- Step 14. At the end of this algorithm the estimated joint positions are the outputs. The main control program should update the timing and call this algorithm to compute the next set of joint positions. If a singularity point is detected, a time step with half the original size is used as a flag and the higher level controller should take the responsibility for further decision making.

Based on this algorithm, a main program used to generate the motion planning output and manage other control timing is required. A proposed flow chart for simulation is shown in Fig. 4.3. Simulation programs used for this algorithm are given in Appendix A and will be discussed in Chapter 6.

4.5 Summary

This chapter has presented a strictly convergent numerical algorithm for Inverse Kinematics. The use of the absolute error between desired and estimated values of the end effector position/orientation instead of the relative difference between two successive estimated end-effector positions in the predictor-corrector integration algorithm solves the problem of convergence especially near a singularity point.

Figure 4.3 Flow Chart of Simulation Program.

The addition of position feedback in the algorithm avoids problems of possible drift caused by the numerical integration.

This algorithm can provide a generic solution for any type of robot manipulator with any number of degrees of freedom. The computation time of this algorithm has been shown to be 5 to 15 times faster than the corresponding Newton-Raphson algorithm [19]. The next chapter will introduce a special-purpose architecture to implement this algorithm such that the computation time may be improved by at least one or two orders of magnitude over that of general-purpose computers. The performance of this algorithm will be presented in Chapter 6.

Chapter 5

REAL-TIME ARCHITECTURE FOR INVERSE KINEMATICS PROCESSOR

5.1 Introduction

For a special-purpose processor to solve Inverse Kinematics in real time, it must be able to efficiently handle all the computations required by the proposed algorithm. Also, this processor should have the necessary interface with the robot control system so that input and output data may be transferred at the required rates.

This chapter will present a real-time architecture for an Inverse Kinematics Processor which is based on a high speed floating-point processor, Am29325 [55]. The basic architecture is determined based on the required computations needed in the algorithm.

In the second section of this chapter, an analysis of the Inverse Kinematics algorithm (introduced in the previous chapter) will be made to determine the basic operations needed. Also, methods for executing those basic operations will be examined. The third section will show the complete architecture for the Inverse Kinematics Processor. The cycle time will be determined by finding the critical path of the microprogrammed architecture. Section four will give the computation times for all modules when the algorithm is mapped onto this architecture. Finally, number of registers required for this application is given in Section 5.5.

5.2 Computation Requirements of the Algorithm

The operations required in the Inverse Kinematics algorithm as discussed in the previous chapter include the computation of Direct Kinematics, the Jacobian, Inverse Jacobian (evaluation of joint rates), prediction of the next joint position vector, and correction.

An analysis of the algorithm indicates that a special-purpose processor for Inverse Kinematics should be able to efficiently implement four basic sets of operations. First of all, the sine and cosine of each of the joint angles must be computed at least 2 times for each time step so that Direct Kinematics may be computed for error checking. If no more than one step of correction is required, as is the case in most iterations, then $2N$ sets of sines and cosines have to be computed per iteration. Second, a number of reciprocals are needed in solving the Inverse Jacobian. Gaussian Elimination, used in the Inverse Jacobian needs at most 6 reciprocals each time step. Third, most of the computation involves standard matrix-vector operations. The implementation of Direct Kinematics and the Jacobian involve many of these operations including 3×3 matrix multiplication, 3×1 matrix and 3×1 vector multiplication, 3×1 vector cross product, and 3×1 vector dot product. The computations of predictor and corrector need 4×1 vector dot products. Finally, a number of scalar adds, subtracts, and multiplications are required.

5.2.1 Matrix-Vector Operation

Among these four sets of operations, the most frequently used are matrix-vector operations. And since these may be synthesized through the more elementary operation of multiplication and accumulation, one

major goal of this research is to develop the most efficient architecture for multiplication and accumulation.

The general form of the multiplication and accumulation operation is:

$$s_{i+1} = s_i + a_i b_i \quad (5.1)$$

All of the matrix-vector operations may be considered as the combination of this operation and a multiplication or addition. For example, the correction operation in our algorithm is given as:

$$\begin{aligned} \theta_1(t+\Delta t) = \theta_1(t) + \Delta t [\dot{\theta}_1(t+\Delta t) \dot{\theta}_1(t) \dot{\theta}_1(t-\Delta t) \dot{\theta}_1(t-2\Delta t)] \\ \cdot [c_1 \ c_2 \ c_3 \ c_4]^T. \end{aligned} \quad (5.2)$$

It may be rewritten as follows:

$$\begin{aligned} \theta_1(t+\Delta t) = \theta_1(t) + \Delta t [\dot{\theta}_1(t+\Delta t)c_1 + \dot{\theta}_1(t)c_2 \\ + \dot{\theta}_1(t-\Delta t)c_3 + \dot{\theta}_1(t-2\Delta t)c_4] \end{aligned} \quad (5.3)$$

To compute a new angle, 5 multiplications and 4 additions must be completed, and this is equal to 4 multiplication and accumulation operations and one multiplication operation. The step-by-step execution may be expressed as follows:

$$s_1 = \dot{\theta}_1(t-2\Delta t)c_4 \quad (5.4)$$

$$s_2 = s_1 + \dot{\theta}_1(t-\Delta t)c_3 \quad (5.5)$$

$$s_3 = s_2 + \dot{\theta}_1(t)c_2 \quad (5.6)$$

$$s_4 = s_3 + \dot{\theta}_1(t+\Delta t)c_1 \quad (5.7)$$

$$\theta_1(t+\Delta t) = \theta_1(t) + \Delta t s_4 . \quad (5.8)$$

5.2.2 Sine/Cosine Generation

To generate the sine/cosine values of the joint angles, three possible approaches are compared in this section and the best one is chosen for implementation. The first approach is to use a set of function generation chips such as AMD's Am29526/27/28/29 [55] high speed sine/cosine generator. Since the function generation time for these chips is smaller than 50 ns, the sine/cosine values are available almost immediately, and the conversion from an angle to its sine/cosine is completed in the same access cycle. However, the functional accuracy is fixed. For example, the Am29526/27 and the Am29528/29 provide high speed generation of the sine and cosine functions over the range $0 < \text{angle} < \pi$ in increments of $\pi/2048$ (.00153 rad). The angle is set by an 11-bit input word. The maximum possible error for the cosine function is for an angle of $\pi/2$:

$$\begin{aligned} \delta_{\cos} &= \max [\text{abs} (\cos(\pi/2) - \cos(\pi/2 + \pi/2048)), \\ &\quad \text{abs} (\cos(\pi/2) - \cos(\pi/2 - \pi/2048))] \\ &= 0.00153398 . \end{aligned} \quad (5.9)$$

The maximum error for the sine function is for an angle of 0 or π :

$$\begin{aligned} \delta_{\sin} &= \max [\text{abs} (\sin(0) - \sin(\pi/2048)), \\ &\quad \text{abs} (\sin(\pi) - \sin(\pi - \pi/2048))] \\ &= 0.00153398 . \end{aligned} \quad (5.10)$$

The accuracy obtained by using 11 bits may not be sufficient for our application. Furthermore, the angle and its sine/cosine must be in

fixed-point form. This would require hardware for converting the values from floating point to/from fixed point.

The second approach to sine/cosine generation involves the development of special-purpose hardware. This approach may be as simple as using a large ROM to do the table look-up, or to use a smaller ROM as a seed look-up table with additional hardware to obtain better accuracy [28]. This approach is hardware intensive and may be used to obtain any required accuracy and needs only a very small computation time. However, the need to develop considerable additional hardware may minimize the effectiveness of this approach.

The third approach to sine/cosine generation is a software-style one. Applying Taylor's theorem, the sine/cosine functions may be expressed as a infinite series. However, in any digital computer implementation, only a finite number of terms will be used. Therefore, the following expression should be used [56]:

$$\begin{aligned} \sin x = & x - x^3(1/3!) + x^5(1/5!) - x^7(1/7!) + \dots \\ & + (-1)^{[(r-1)/2]} x^r(1/r!) + R(\sin) \end{aligned} \quad (5.11)$$

$$\begin{aligned} \cos x = & 1 - x^2(1/2!) + x^4(1/4!) - x^6(1/6!) + \dots \\ & + (-1)^{[(r-1)/2]} x^{r-1}(1/(r-1)!) + R(\cos) \end{aligned} \quad (5.12)$$

where r is an odd number and $R(\sin)$ and $R(\cos)$ are residual errors, and

$$|R(\sin)| < x^{r+1}/(r+1)! \quad (5.13)$$

$$|R(\cos)| < x^r/r! \quad (5.14)$$

The accuracy of the sine/cosine function is dependent on the number of terms chosen in the formula. For example, to obtain 16 bits of

accuracy for the sine function, eight terms are required for $|R(\sin)| < 2^{-16}$. Simulation may be used to determine the number of terms required in the Taylor Series for the sine and cosine for a specific amount of accuracy. The relationships between the various quantities may be expressed through the following two equations:

$$|R(\sin)| < x^{r+1}/(r+1)! < 2^{-s} \quad (5.15)$$

$$|R(\cos)| < x^r/r! < 2^{-s} \quad (5.16)$$

$\underbrace{\hspace{1.5cm}}$ Actual Accuracy	$\underbrace{\hspace{1.5cm}}$ Required # of terms	$\underbrace{\hspace{1.5cm}}$ Desired Accuracy
---	---	--

where s gives the number of bits of accuracy desired and the other variables are as defined previously.

Due to problems with accuracy, the first approach will not be used to implement our Inverse Kinematics algorithm. Since the second and the third approaches can both give the desired accuracy, the decision will be based on the trade-off between computation time and additional hardware required. Analysis of the complete algorithm (see later sections) shows that 10 percent of the total computation time will be spent on the generation of the sine and cosine functions for all the links if the third approach is used. In other words, the second approach will save 10 percent of the computation time with the burden of developing additional hardware. Since the results also show that the total computation time of the algorithm presented in Chapter 4 is much faster than real time, the third approach will be used to save the hardware development and cost.

5.2.3 Reciprocal Generation

Finding the Inverse Jacobian is a very time consuming process in our Inverse Kinematics algorithm. Therefore, the Gaussian Elimination method is used to directly find the joint rates. No matter what method is used to obtain the joint rates, division is a necessary basic operation. Research on division algorithms [57-60] show that the best approach is to generate the reciprocal of the denominator then multiply the numerator to obtain the result. Ribble [28] also shows that the use of this approach in Gaussian Elimination has two advantages. First of all, Gaussian Elimination requires repeated calculation of N_i/D for $i = 1 \dots 12$, where D remains fixed. Once $1/D$ is computed, the ratios of N_i/D may be obtained by multiplication. Second, the computation of $1/D$ requires less hardware than the computation of N/D . Therefore, it is more appropriate to compute the reciprocal rather than compute a full division.

Of course, the objective is to obtain the reciprocal as quickly as possible with the hardware requirement as small as possible. To find the reciprocal of a floating-point number, the exponent and mantissa should be manipulated separately.

Since the data in floating-point format has been normalized, finding the exponent of the reciprocal is very easy. For example, the DEC single-precision floating-point word is thirty-two bits wide, and is arranged in the format shown in Fig. 5.1. The floating-point word is divided into three fields: a single-bit sign, an eight-bit biased exponent, and a 23-bit mantissa.

$$\text{Value} = (-1)^s (2^{e-128})(.1m)$$

Figure 5.1 DEC Single Precision Floating-Point Format.

The biased exponent is an eight-bit unsigned integer field representing a multiplicative factor of some power of two. The bias value is 128. If, for example, the multiplicative factor for a floating-point number is 2^a , the value of the biased exponent would be $(a + 128)$; a is called the true exponent. If a number x is expressed as:

$$x = (-1)^s (0.1m) * (2^{e-128}) \quad (5.17)$$

where s is the sign bit, e is the biased exponent, and m is the mantissa. Its reciprocal may be expressed as:

$$\begin{aligned} 1/x &= (-1)^s (1/((0.1m) * (2^{e-128}))) \\ &= (-1)^s (1.c) * (2^{(-e+128)}) \\ &= (-1)^s (0.1c) * (2^{-e+(1+128)}) \\ &= (-1)^s (0.1c) * (2^{(257-e)-128}), \end{aligned} \quad (5.18)$$

where $1.c = 1/(0.1m)$. Therefore, the biased exponent of the reciprocal is equal to $(257 - \text{input biased exponent})$.

To find the reciprocal of the mantissa, three possible approaches are given as follows [60]:

1. Multiplicative series expansion

$$1/m = \prod_{n=1}^k (1 + x^{2^{(n-1)}}) \quad (5.19)$$

$$= (1+x)(1+x^2)(1+x^4)(1+x^8)\dots \quad (5.20)$$

where $x = 1 - m$, $0.5 < m < 1.0$, and k is the order of the expansion;

2. Additive series expansion

$$1/m = \sum_{n=0}^k (1 - m)^n \quad (5.21)$$

$$= 1 + (1 - m) + (1 - m)^2 + (1 - m)^3 + \dots \quad (5.22)$$

3. Newton-Raphson iteration

$$f(x) = 1/x - m \quad (5.23)$$

$$x_{i+1} = x_i [1 + (1 - mx_i) + (1 - mx_i)^2 + \dots + (1 - mx_i)^k] \quad (5.24)$$

In order for this iterative equation to converge, the seed value x_0 must fall in the range:

$$0 < x_0 < 2/m, \quad \text{if } m > 0; \quad (5.25)$$

$$2/m < x_0 < 0, \quad \text{if } m < 0. \quad (5.26)$$

For n -bit accuracy, the first approach needs $\log_2(n)$ terms, while the second approach needs n terms. Both of them may be used to find the reciprocal using a software approach. However, the efficiency is poor. The first approach is more efficient than the second approach if n is larger than 2.

The third approach is more general. The convergence rate [31] of this iterative algorithm is:

$$e_{i+1} = m e_i^{k+1}, \quad (5.27)$$

where k is the order of the iteration.

For $k=1$ the error of x_i reduces quadratically. The number of bits of accuracy in the result, then, roughly doubles after every iteration. To obtain a reciprocal of 24-bit accuracy in one iteration, a 12-bit

accurate initial guess is required. For $k=2$, an initial guess with 8-bit accuracy is required to obtain a reciprocal with 24-bit accuracy in one iteration. With higher order (larger k), the requirements of the accuracy of the initial guess may be reduced, but the computation time will be longer.

The disadvantage of Newton-Raphson approach is that an initial guess is required. And this initial guess value x_0 must fall in the range given in Eq. (5.25) and Eq.(5.26) for convergence. Usually, this initial guess is generated through a look-up table, a PROM or ROM. The input mantissa addresses the table while the output is called the seed mantissa. This approach then requires additional hardware. The size of the seed table and the computation time required may be traded-off when determining the best algorithm.

5.3 High Speed Floating-Point Architecture

Because of the accuracy requirements and large data variation range, a floating-point processor is selected as the central processing unit (PU). The PU should be able to perform floating-point multiplication, addition, and subtraction. Advanced Micro Devices' 32-bit floating-point processor, the Am29325 is selected because this device executes these operations very fast. Also, three internal registers and two internal data feedback paths provide an efficient structure to perform the required matrix-vector operations.

The complete architecture for the Inverse Kinematics Processor is given in Fig. 5.2. A four-port, dual-access register file, Am29334's, is used as a local fast memory to store frequently used data, such as

Figure 5.2 Architecture for Inverse Kinematics Processor.

link parameters, and intermediate results. Three of these ports are used with the three buses of the PU. The fourth port is used for input data from other sections of the control system. A seed look-up table is inserted between the register file and PU to provide an initial estimate for reciprocal generation with the Newton-Raphson algorithm. A data path is also added to provide movement of information from one location in the register file to another all in parallel with operation of the PU.

This data path is only used when the PU needs at most one operand from register file for the next operation (at least one operand is already inside the PU). This situation happens quite often, especially in matrix-vector operations. The advantage of this data path is not only on the reduction of execution time but also on the savings in register file space. For example, in computing Direct Kinematics and the Jacobian, the most important operation is:

$${}^{k+1}B = A {}^k B, \quad (5.28)$$

where A and B are 3x3 matrices. the register storing ${}^k B$ should be updated to ${}^{k+1}B$ before performing the next step of recursion. Since elements of ${}^k B$ are still needed when some elements of ${}^{k+1}B$ have been computed, these results should be temporarily stored and the corresponding elements of ${}^k B$ will not be updated until they are no longer useful. The following equation gives a better description:

$$\begin{bmatrix} k+1b_{11} & k+1b_{12} & k+1b_{13} \\ k+1b_{21} & k+1b_{22} & k+1b_{23} \\ k+1b_{31} & k+1b_{32} & k+1b_{33} \end{bmatrix} = \begin{bmatrix} a_{11} & a_{12} & a_{13} \\ a_{21} & a_{22} & a_{23} \\ a_{31} & a_{32} & a_{33} \end{bmatrix} \begin{bmatrix} kb_{11} & kb_{12} & kb_{13} \\ kb_{21} & kb_{22} & kb_{23} \\ kb_{31} & kb_{32} & kb_{33} \end{bmatrix} . \quad (5.29)$$

The first few steps of execution are given as:

$$k+1b_{11} = a_{11}kb_{11} + a_{12}kb_{21} + a_{13}kb_{31} \quad (5.30)$$

$$k+1b_{21} = a_{21}kb_{11} + a_{22}kb_{21} + a_{23}kb_{31} \quad (5.31)$$

$$k+1b_{31} = a_{31}kb_{11} + a_{32}kb_{21} + a_{33}kb_{31} . \quad (5.32)$$

$k+1b_{11}$ is available after Eq. 5.32 has been executed but cannot be used to update kb_{11} until the execution of the first addition of Eq. 5.34. Without the special data path from register file to register file, the updating process is time consuming and usually needs more register file space to temporarily store the intermediate results.

The internal block of Fig. 5.2 shows the architecture of the Am29325. Three internal registers are labeled: Reg A, Reg B, and Reg C and two multiplexers are also labeled accordingly. This PU, with its two input registers and one output register, is especially efficient for matrix-vector operations. Table 5.1 gives an example for a dot

Table 5.1 Reservation Table for a Dot Operation of Two 6x1 Vectors on the Inverse Kinematics Processor.

Operation: $s = ab + cd + ef + gh + ij + kl;$

where: $s1 = ab + cd, \quad s2 = s1 + ef,$

$s3 = s2 + gh, \quad s4 = s3 + ij,$

$s = s4 + kl.$

Cycle	1	2	3	4	5	6	7	8	9	10	11	12	13	14
Mux B	0	0	1	0	1	0	1	0	1	0	1	0	0	0
Reg B		a	c	cd	e	ef	g	gh	i	ij	k	kl		
Reg A		b	d		f		h		j		l			
Mux A	0	0	0	1	0	1	0	1	0	1	0	1	0	0
Reg C			ab	ab	s1	s1	s2	s2	s3	s3	s4	s4	s	
ALU		*	*	+	*	+	*	+	*	+	*	+		
Memory														s

operation of two 6×1 vectors. One of the most important results indicated by this reservation table is that the PU will be used on each cycle during the intermediate steps of processing. This is true for each of the matrix-vector operations commonly used in Inverse Kinematics, and thus shows the appropriateness of the proposed architecture. Generalizing the results to a dot product of $N \times 1$ vectors, the total number of cycles needed would be $2N+2$. The utilization of the PU would be $(2N-1)/(2N+2)$ which approaches 1.0 as the size of the vectors increases.

Another part of this processor shown in Fig. 5.2 is the control sequencer which is based on a microprogrammed approach. The Inverse Kinematics algorithm is implemented as a microprogram and stored in the microprogram memory which is also shown in Fig. 5.2.

To obtain a reasonable cycle time, state-of-the-art components will be used to implement the Inverse Kinematics Processor. While a complete design of the processor will be left to future work, basic elements of the design are given in Figs. 5.3 and 5.4. Also the three longest path delay are given so that a reasonable value for the cycle time may be computed.

Fig. 5.3 shows a circuit block diagram for the control part of the Inverse Kinematics Processor. All delay values are from the appropriate data books [55,61,62]. The critical path in this circuit is also shown and the minimum cycle time required includes: a register access time of 10.5 ns, a multiplexer delay from the time it is selected to the time its output data is available, 19.5 ns, a sequencer delay from the time when the condition code is available to the time when the next address

- Width of microcode is 68-bit.
- Path delay = 97 ns.

Figure 5.3 Control Circuit of the Inverse Kinematics Processor Showing a Possible Critical Path.

Figure 5.4 Two Possible Critical Data Paths of the Inverse Kinematics Processor.

is available, 30 ns, a memory access time of 35 ns, and a setup time for the pipeline register, 2 ns, for a total of 97 ns.

Fig. 5.4 shows two possible critical paths in the arithmetic and memory part of the processor. One is the execution time of arithmetic operations on the selected floating-point processor, 135 ns. Another is the path to obtain a seed for reciprocal computation, and it includes a register access time of 13 ns, a decoder delay of 12 ns, an access time for the register file, 24 ns, a table look-up time of 35 ns, a multiplexer delay of 13 ns, and a register setup time of 15 ns, for a total of 112 ns. From the above discussion, a cycle time of 150 ns is quite reasonable and is chosen for further evaluation of the algorithm.

5.4 Computation Times

A program was written to simulate the Inverse Kinematics algorithm on the proposed architecture. It is essentially a microprogram for Inverse Kinematics and simulates all the control signals and data flow at machine language level. The special algorithms for sine/cosine and the reciprocal used are as given in Sections 5.2.2 and 5.2.3. The results of simulations for sine/cosine generation are given in Table 5.2, where s , r , and R are given in Eqs. 5.15 and 5.16. The table indicates that 10 terms are needed for 24-bit accuracy and the associated computation time of both the sine and cosine is less than 60 clock cycles. Since relatively few sine/cosine computations are needed in the Inverse Kinematics algorithm, this result is acceptable especially if no additional hardware is required.

Table 5.2 Results of Simulation to Determine the Number of Terms Needed in the Taylor Series for Sine and Cosine.

Function	Desired Accuracy Binary (a)	Desired Accuracy Decimal	Number of terms Required [(r+1)/2]	Actual Accuracy (R)	Computation Time (cycles)
Sine	24 bits	5.96E-8	10	5.40E-10	57
Cosine	24 bits	5.96E-8	10	3.60E-9	

For reciprocal generation, the Newton-Raphson approach is selected. The optimal order of this algorithm, in Eq. 5.23, will be decided through simulation.

The algorithms used to do the comparison are listed as follows:

$$x^0 = \left(\frac{1}{m_T} \right)_T \quad \text{zeroth order} \quad (5.33)$$

$$x_{i+1}^1 = x_i^1 (1 + t_i) \quad \text{first order} \quad (5.34)$$

$$x_{i+1}^2 = x_i^2 (1 + t_i + t_i^2) \quad \text{second order} \quad (5.35)$$

$$x_{i+1}^3 = x_i^3 (1 + t_i)(1 + t_i^2) \quad \text{third order} \quad (5.36)$$

where

$$x_0^1 = x_0^2 = x_0^3 = x^0 \quad (5.37)$$

$$t_{n-1} = [1 - m x_i] \quad (5.38)$$

and $\left(\frac{1}{m_T} \right)_T$ means that the truncated output from the seed look-up table with a truncated input of m_T .

Extensive simulation results have been obtained for the reciprocal. The size of the seed table and number of computation cycles required, order of the Newton-Raphson iteration, and number of iterations in the algorithm have been determined and are shown in Table 5.3. The two lines in the table headed with an asterisk are the best results. Since at most 6 reciprocals are required in every computation of an Inverse Kinematics solution, the second order Newton-Raphson algorithm is

Table 5.3 Simulation Results for the Reciprocal Showing the Seed Table Size and Number of Computation Cycles Required.

Order (k)	Desired Accuracy	Seed Table size I/O bits	Size	Number of Iterations	Computation Time(cycles)
0	24 bits	23	8M*23	0	0
* 1	24 bits	11	2K*11	1	6
1	24 bits	9	512*9	2	9
* 2	24 bits	7	128*7	1	9
2	24 bits	5	32*5	2	15
3	24 bits	6	64*6	1	11

selected. A table size of 128x7 bits is used to generate the seed mantissa of the reciprocal and 9 clock cycles are required to generate a reciprocal with 24-bit accuracy. It should also be noted that in addition to the mantissa, another ROM is needed for the exponent (a size of 256 x 8).

The total number of clock cycles required by the algorithm have been determined as a function of the number of degrees of freedom of the manipulator. In Table 5.4, the computation of Direct Kinematics and the Jacobian are programmed together to reduce the total computation time by eliminating the duplicate matrix multiplications. The total cycles are the sum of all computations for each function plus an extra evaluation of the Jacobian and two extra evaluations of the error. This is necessary because Direct Kinematics/Jacobian is computed an average of twice in each time step. The greatest amount of computation is associated with the Inverse Jacobian, Direct Kinematics, and the Jacobian of the manipulator. The results show that an Inverse Kinematics solution may be computed in less than 520 μ s for a manipulator with 7 degrees of freedom if the cycle time is 150 ns. In other words, Inverse Kinematics may be computed at an approximate 2 khz rate.

5.5 Size of Register File

To speed up the computation of Inverse Kinematics, a small local memory is needed in the Inverse Kinematics Processor. This local memory is first of all used to store the link parameters. However, if commonly used constants and some partial results are also stored locally, the computational speed of the entire algorithm will be higher.

Table 5.4 Computation Cycles Needed by Executing the Inverse Kinematics Algorithm on the Proposed Architecture.

Function	Computation time (In cycles)	N=5	N=6	N=7
1. Jacobian	$130N + 78$	1452	1712	1972
2. Inverse Jacobian	$N^3 + 14.5N^2 + 35.5N - 12$, $N < 6$ 471, $N = 6$ $83N + 438$, $N > 6$	653	471	1019
3. Prediction	$16N + 3$	83	99	115
4. Correction	$9N + 3$	48	57	66
5. Error Evaluation	46	138	138	138
6. Control	56	56	56	56
7. Position Feedback	66	66	66	66
8. I/O	$N + 18$	23	24	25
Total	$N^3 + 14.5N^2 + 321.5N + 424$ $N < 6$	2519		
	2623 $N = 6$		2623	
	$369N + 874$ $N > 6$			3457

Furthermore, the speed of local memory access should match with the execution speed of the processor itself. Based on these considerations, a register file has been designed into the Inverse Kinematics Processor. The size of the register file increases linearly with the number of degrees of freedom of the manipulator. Table 5.5 indicates the required size of the register file. A register file with 320 words, 32 bits each, will be used and is adequate for manipulators with fewer than 9 degrees of freedom.

5.6 Summary

The mapping of the developed Inverse Kinematics algorithm onto a special-purpose architecture has been presented in this chapter. The architecture, given in Fig. 5.2, includes a triple-bus structure, a high speed floating-point processor with two internal data feedback paths and three internal registers, the Am29325 [55], a seed look-up table for reciprocal generation, a four-port register file with a feedback data path, and a controller which contains a sequencer, a memory for storing the microprogram for Inverse Kinematics, and a pipeline register.

With the architecture as given, the computation of matrix-vector operations is very efficient. Results of mapping the complete algorithm onto the architecture indicate that the total computation time for an Inverse kinematics solution is less than 520 ns if a clock cycle time of 150 ns is used. Also, a register file of 320 words is enough for most robot manipulators.

Table 5.5 Size of Register Files Required for Inverse Kinematics Algorithm.

Variables or Constants	Space (In words)
1. Constants <u>a</u> , <u>b</u> , <u>c</u>	$3 \times 4 = 12$
2. $\underline{Q}_n, \dot{\underline{Q}}_n$	$2 \times N \times 4$
3. $\underline{q}_p, \underline{q}_c, \dot{\underline{q}}$	$3 \times N$
4. Δt , Recip, Singu	3
5. sine/cosine constants	18
6. $\underline{Q}_{rad}$, Sine/cosine of $\underline{q}$	$3 \times (N+1)$
7. Link parameters	$4 \times (N+1)$
8. X, X_d, E , Temp	$4 \times 12 = 48$
9. Jacobian Matrix	$6 \times N$
10. Square Matrix	$6 \times 6 = 36$
11. Reciprocal	N
12. $\dot{\underline{X}}$	6
13. $\delta_1, \delta_2, \delta_3$	3
Total = $25N + 133$	

In the next chapter, extensive simulation of the algorithm on the proposed architecture will be presented. Several industrial robot models and tasks will be used to examine the accuracy, robustness, and real time effects of the algorithm on the architecture.

Chapter 6

SIMULATION RESULTS

6.1 Introduction

The purpose of this chapter is to provide results of simulation work to evaluate the Inverse Kinematics algorithm and the proposed Inverse Kinematics Processor. It is expected that the results reported in this chapter will be close to those which would be obtained in practice on an industrial robot control system since the algorithm has been programmed at the microcode-level for the proposed floating-point arithmetic unit. Also, since the Inverse Kinematics Processor is a part of the trajectory planning and transformation section of the control, and thus does not use joint-sensed information, the accuracy of the algorithm does not depend upon measurement resolution, etc.

The specific purposes of the simulations are to show:

- a) The capability of performing the Inverse Kinematics computations in real time,
- b) The strict-convergence properties of the algorithm even near singular configurations,
- c) The accuracy of computed joint positions even with high-speed motion, and
- d) The capability of convergence even with an initial offset of position.

To demonstrate the above capabilities, a Pascal program is first written to simulate the operation of the Inverse Kinematics algorithm. Then a microcode-level simulation is also written (in Pascal) to test the algorithm on the proposed architecture.

The next section of this chapter will describe the two robot models used in the simulations. The first is the Mitsubishi RM-501 robot with 5 degrees of freedom. Since the kinematics of this robot are relatively simple (consecutive axes are perpendicular or parallel with no joint offsets), a closed-form solution for Inverse Kinematics does exist. It is especially selected to demonstrate the computational accuracy and the convergence property of the algorithm. The second model is for the GMF S-400 Offset Wrist, industrial robot (6 degrees of freedom). Because of an offset at the wrist, a closed-form solution to its kinematics is yet to be found. This model is selected to show the advantages and capabilities of using a numerical method for the Inverse Kinematics solution. Both of the models are also used to demonstrate the capability of avoiding long-term drift problems and robustness even with an initial offset of position.

The third section of this chapter introduces three different tasks to be performed. The first task is to use the Mitsubishi RM-501 robot to draw a circle on a horizontal plane which is parallel with the surface of the workstation. The direction of the end effector approach vector is always into the surface. The second task sets the approach vector of the end effector of the Mitsubishi to be horizontal and then moves the end effector outward toward full arm extension. This task is designed to test the convergence characteristics of the algorithm as the hand is moved toward a singularity point. The third task is to move the

GMF S-400 Offset Wrist robot in a straight line. The trajectory is purposefully designed to pass through at least one singularity point.

The fourth section of this chapter presents all of the simulation results. It includes the maximum errors and the execution time of both the Pascal simulation and the simulation on the Inverse Kinematics Processor. The effects of position feedback will also be presented.

6.2 Robot Models for Simulation

To test the performance of the Inverse Kinematics algorithm and the proposed Inverse Kinematics Processor, it is necessary to select some generally-used industrial robots as models and design specific tasks for them for simulation. Models for two industrial robots will be described in the following subsections. The designed tasks will be detailed in the section following.

6.2.1 Mitsubishi RM-501

In order to position and orient the end effector arbitrarily in three-dimensional space, six degrees of freedom are required. However, robot arms with fewer degrees of freedom are adequate to do many useful industrial tasks such as arc welding, spray painting, and assembly because it is not always necessary to arbitrarily orient the end effector of the arm. The Mitsubishi RM-501 is a small, light-weight industrial robot with five degrees of freedom. This arm is selected as a test model because a closed-form solution to its kinematics exists and is available for comparison. An illustration of this robot in the zero configuration (as defined by Paul in [3]) is given in Fig. 6.1. Its link parameters are given in Table 6.1. Note that E and Z (as defined by Paul [3]) are simple homogeneous transforms in this case representing an offset along the z-axis only.

Figure 6.1 Mitsubishi RM-501 Robot in Zero Configuration.

Table 6.1 Link Parameters and Operation Range of the Mitsubishi RM-501 Robot.

Link	Twist	Length	Offset	Joint Operation Range
1	-90	0	0	$-150 < \theta_1 < 150$
2	0	220	0	$-100 < \theta_2 < 30$
3	0	160	0	$0 < \theta_3 < 90$
4	90	0	0	$0 < \theta_4 < 180$
5	0	0	0	$-180 < \theta_5 < 180$
E	0	0	196.1	
Z	0	0	250.0	

6.2.2 GMF S-400 Offset Wrist

The second model selected is a GMF special-purpose robot arm, the GMF S-400 Offset Wrist. This manipulator has six degrees of freedom and has an offset along the middle of the wrist joint axes. An illustration of this manipulator is given in Fig. 6.2. Its link parameters are listed in Table 6.2. Also, the zero configuration of the S-400 is shown in Fig. 6.3.

6.3 Task Models

Three different tasks are designed to demonstrate the capabilities of the proposed Inverse Kinematics Processor and the corresponding algorithm. The first two tasks are designed for the Mitsubishi RM-501 robot and the third task is designed for the GMF S-400 Offset Wrist robot. Through these three tasks, simulation results will be obtained to show the capabilities of real-time computation, the strict convergence property, and the position accuracy of the proposed approach to Inverse Kinematics.

6.3.1 RM-501 Drawing a Circle

Controlling a serial link manipulator to draw a circle on the ground is a non-trivial task because all links must move simultaneously in such a way that the corresponding trajectory of the end effector is a circle. Since the input command to the manipulator is the joint position vector, an Inverse Kinematics transformation is necessary for motion planned in Cartesian coordinates. The first task is designed to demonstrate the capabilities of the algorithm while giving results for the computational accuracy and computation time.

Fig. 6.4 shows the task. The z-axis of the end effector is directed downward, and the x-axis is always directed radially outward

Table 6.2 Link Parameters of GMF S-400 Offset Wrist Robot.

Link	Twist	Length	Offset	Joint Operation Range
1	-90	0	0	$-150 < \theta_1 < 150$
2	0	1150	0	$-135 < \theta_2 < -30$
3	-90	95	0	$-30 < \theta_3 < 90$ $\theta_2 + 30 < \theta_3 < \theta_2 + 135$
4	-90	0	1400	$-270 < \theta_4 < 90$
5	90	0	225	$-180 < \theta_5 < 180$
6	0	0	0	$-180 < \theta_6 < 180$
E	0	0	150

Figure 6.3 GMF S-400 Offset Wrist Robot in Zero Configuration.

Figure 6.4 Task I: RM-501 Drawing a Circle.

from the center of the circle. The radius of the circle is 50 mm and the motion is counterclockwise from above and begins at the outside point on the circle.

In Cartesian coordinates, the position trajectory of the task may be expressed as a time variant vector as follows:

$$\underline{p}(t) = \begin{bmatrix} 320 + 50 \cos(\phi) \\ 50 \sin(\phi) \\ 18.5 \end{bmatrix}, \quad (6.1)$$

where the units are in millimeters and

$$\phi = \omega t, \quad (6.2)$$

and ω is the angular speed.

Both the position and orientation of the trajectory of the end effector may be expressed through a time variant homogeneous transformation given as follows:

$$\underline{x}_d(t) = \begin{bmatrix} \cos(\phi) & \sin(\phi) & 0 & 320 + 50 \cos(\phi) \\ \sin(\phi) & -\cos(\phi) & 0 & 50 \sin(\phi) \\ 0 & 0 & -1 & 18.5 \\ 6 & 0 & 6 & 1 \end{bmatrix}, \quad (6.3)$$

where

$$\phi = \omega t, \quad (6.4)$$

$$\omega = 10 \text{ deg/sec}, \quad (6.5)$$

$$\text{for } 0 \leq t \leq 36 \text{ sec.} \quad (6.6)$$

The velocity of the end effector may be expressed as:

$$\dot{\underline{x}}_d = \begin{bmatrix} 0 \\ 0 \\ -10 \text{ deg/sec} \\ 0 \\ -8.73 \text{ mm/sec} \\ 0 \end{bmatrix} \quad (6.7)$$

Based on the designed speed, 10 degrees per second, drawing a circle takes 36 seconds. In other words, to meet the real-time requirement, the execution time of the Inverse Kinematics algorithm for the complete trajectory should be smaller than or equal to 36 seconds. This will be checked in the next section.

6.3.2 RM-501 Reaching Out

To show the strict-convergence characteristics of the Inverse Kinematics algorithm, a task is purposefully designed to move the end effector to one of its singular configurations. The algorithm should still be convergent up to one integration step away from the singularity point.

Since the link lengths of the manipulator are finite, at maximum extension the manipulator loses a degree of freedom since it cannot move outward at that point. Fig. 6.5 illustrates the task which moves the end effector of the RM-501 to its maximum extension.

The position and orientation trajectory of the end effector may be expressed through a time variant homogeneous transformation as follows:

Figure 6.5 Illustration of RM-501 Reaching Out.

$$\bar{x}_d(t) = \begin{bmatrix} 0 & 0 & 1 & \bar{x}_d(t) \\ 0 & 1 & 0 & 0 \\ -1 & 0 & 0 & 250 \\ 0 & 0 & 0 & 1 \end{bmatrix} , \quad (6.8)$$

where the orientation of the end effector is constant, the altitude remains constant at the shoulder level, and the entire arm remains in the same vertical plane. The only variable is $x_d(t)$. For convenience, assume that the second joint angle (θ_2) is initially set to be 30 degrees (upper arm above the horizontal). Then the initial value for $x_d(t)$ may be calculated as:

$$\begin{aligned} x_d &= 220 \cos(30) + 160 \sin(\cos^{-1}((220 \sin(30))/160)) + 196.1 \\ &= 502.8 \text{ mm} . \end{aligned} \quad (6.9)$$

The maximum value of $x_d(t)$ is reached when θ_2 is rotated to zero:

$$x_d = 220 + 160 + 196.1 = 576.1 \text{ mm} . \quad (6.10)$$

With an end effector translational velocity of 10 mm/sec and with the upper arm rotating from 30 degrees to 0 degrees, the trajectory of $x_d(t)$ may be expressed as:

$$x_d(t) = 502.8 + 10 t , \quad (6.11)$$

where t is the time variable.

The velocity of the end effector is given in vector form as:

$$\dot{\underline{x}}_d = \begin{bmatrix} 0 \\ 0 \\ 0 \\ 0 \\ 0 \\ 10 \text{ mm/sec} \end{bmatrix} \quad (6.12)$$

Based on this designed velocity, 10 mm/sec, the MITSUBISHI RM-501 should be able to detect the singular configuration, $x_d=576.1$, when time is at 7.33 second. In other words, to satisfy the real-time requirement, the execution time of the Inverse Kinematics algorithm for the complete task should be smaller than or equal to 7.33 seconds. This will be examined in the next major section.

6.3.3 GMF S-400 Offset Wrist Moving in a Straight Line

Two points are enough to specify a straight line. This task arbitrarily selects a starting point, which is not a singular point, and a singular point to form a straight line such that the robot may detect this singularity when it moves toward it.

To clearly describe the task, three different poses (position/orientation) are selected and the task is divided into two subtasks. The first subtask rotates the end effector from POS_1 to POS_2 such that the translational position of the end effector is unchanged, and the orientation of the end effector has been changed from that at POS_1 to that at POS_3 . The second subtask moves the end effector from POS_2 to POS_3 on a straight line without changing the orientation.

For the initial pose (POS₁), the end effector is parallel with the ground and $\theta_1 = -30^\circ$, $\theta_2 = -60^\circ$, $\theta_3 = 30^\circ$, $\theta_4 = 0^\circ$, $\theta_5 = 60^\circ$, and $\theta_6 = 0^\circ$. The corresponding homogeneous transformation is:

$$X_{d1} = \begin{bmatrix} 0 & -0.5 & 0.866 & 1192.836 \\ 0 & -0.866 & -0.5 & -948.49 \\ 1 & 0 & 0 & -169 \\ 0 & 0 & 0 & 1 \end{bmatrix}. \quad (6.13)$$

The singular pose (POS₃) is selected in such a way that $\theta_1 = 0^\circ$, $\theta_2 = -90^\circ$, $\theta_3 = 0^\circ$, $\theta_4 = 0^\circ$, $\theta_5 = 0^\circ$, and $\theta_6 = 0^\circ$. Its corresponding homogeneous transformation is:

$$X_{d3} = \begin{bmatrix} 0 & 0 & 1 & 1550 \\ 0 & -1 & 0 & -225 \\ 1 & 0 & 0 & 1245 \\ 0 & 0 & 0 & 1 \end{bmatrix}. \quad (6.14)$$

For POS₂, the joint positions are unknown. However, the homogeneous transformation may be obtained by including the rotational part of X_{d3} and the translational part of X_{d1} and is given as follows:

$$X_{d2} = \begin{bmatrix} 0 & 0 & 1 & 1192.836 \\ 0 & -1 & 0 & -948.49 \\ 1 & 0 & 0 & -169 \\ 0 & 0 & 0 & 1 \end{bmatrix} = \begin{bmatrix} \underline{n} & \underline{o} & \underline{a} & \underline{p}_2 \\ 0 & 0 & 0 & 1 \end{bmatrix}. \quad (6.15)$$

To produce a smooth movement, the velocity of the end effector should start from and end with a zero value when going from pose to pose. For the first subtask, since the end effector is always parallel to the ground, the movement is equivalent to rotating the end effector

with respect to its x-axis such that the orientation of the end effector is changed from that at POS₁ to that at POS₃. The end effector velocity function may be expressed as a vector with respect to end effector coordinates as follows:

$$\dot{\underline{x}}_D = \begin{bmatrix} \omega_x \text{ deg/sec} \\ 0 \\ 0 \\ 0 \\ 0 \\ 0 \end{bmatrix} \quad (6.16)$$

The velocity trajectory implemented is given in Fig. 6.6.

The desired position function may be derived as follows:

$$\underline{X}(t) = \underline{X}_1 D(\phi)$$

$$= \begin{bmatrix} 0 & -0.5 & 0.866 & 1192.836 \\ 0 & -0.866 & -0.5 & -948.49 \\ 1 & 0 & 0 & -169 \\ 0 & 0 & 0 & 1 \end{bmatrix} \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & \cos(\phi) & -\sin(\phi) & 0 \\ 0 & \sin(\phi) & \cos(\phi) & 0 \\ 0 & 0 & 0 & 1 \end{bmatrix} \\ = \begin{bmatrix} 0 & -0.5 C(\phi) + 0.866 S(\phi) & 0.5 S(\phi) + 0.866 C(\phi) & 1192.836 \\ 0 & -0.866 C(\phi) - 0.5 S(\phi) & 0.866 S(\phi) - 0.5 C(\phi) & -948.49 \\ 1 & 0 & 0 & -169 \\ 0 & 0 & 0 & 1 \end{bmatrix} \quad (6.17)$$

where $C(\phi) = \cos(\phi)$, $S(\phi) = \sin(\phi)$, and ϕ may be computed as follows:

Figure 6.6 Velocity Trajectory of the End-Effector for GMF S-400, Subtask 1.

$$\phi = \begin{cases} 0.5 \frac{\omega_{\max}}{t_{\text{acc}}} t^2, & \text{for } t \leq t_{\text{acc}} \\ \omega_{\max} (t - 0.5 t_{\text{acc}}), & \text{for } t_{\text{acc}} \leq t \leq T - t_{\text{acc}} \\ \omega_{\max} (t - 0.5 t_{\text{acc}}) - 0.5 \frac{\omega_{\max}}{t_{\text{acc}}} [t - (T - t_{\text{acc}})]^2, & \text{for } T - t_{\text{acc}} \leq t \leq T \\ 0, & \text{elsewhere} \end{cases}$$

In this subtask,

$$\omega_{\max} = 30 \text{ deg/sec}, \quad (6.19)$$

$$t_{\text{acc}} = 0.5 \text{ second}, \quad (6.20)$$

and

$$T = 1.5 \text{ seconds}. \quad (6.21)$$

For the second subtask, a straight line movement with no change of the end effector orientation is implemented. The end effector velocity trajectory is given in Fig. 6.7 where

$$V_{\max} = 100 \text{ mm/sec}, \quad (6.22)$$

and

$$t_{\text{acc}} = 0.5 \text{ second}. \quad (6.23)$$

The end effector velocity vector may be expressed as:

Figure 6.7 Velocity Trajectory of the End-Effector for GMF S-400, Subtask 2.

$$\dot{\underline{x}}_d = \begin{bmatrix} 0 \\ 0 \\ 0 \\ v_x \\ v_y \\ v_z \end{bmatrix}, \quad (6.24)$$

where v_x , v_y , and v_z will be derived in the following paragraph.

The distance between the singularity point and the starting point may be computed as follows:

$$D = POS_2^{-1} POS_3$$

$$= \begin{bmatrix} 1 & 0 & 0 & \underline{n} \cdot \underline{\Delta p} \\ 0 & 1 & 0 & \underline{o} \cdot \underline{\Delta p} \\ 0 & 0 & 1 & \underline{a} \cdot \underline{\Delta p} \\ 0 & 0 & 0 & 1 \end{bmatrix} \quad (6.25)$$

where

$$\underline{\Delta p} = \underline{p}_3 - \underline{p}_2$$

$$= \begin{bmatrix} 1550 - 1192.836 \\ -225 - (-948.49) \\ 1245 - (-169) \end{bmatrix} = \begin{bmatrix} 357.164 \\ 723.49 \\ 1414 \end{bmatrix} = \begin{bmatrix} \Delta p_x \\ \Delta p_y \\ \Delta p_z \end{bmatrix}, \quad (6.26)$$

and the distance, d , is defined as

$$d = \sqrt{\Delta p_x^2 + \Delta p_y^2 + \Delta p_z^2}. \quad (6.27)$$

From the velocity profile shown above, the velocity function may be derived as:

$$V(t) = \begin{cases} \frac{V_{\max}}{t_{\text{acc}}} t, & \text{for } t < t_{\text{acc}} \\ V_{\max}, & \text{for } t_{\text{acc}} < t \end{cases} \quad (6.28)$$

so that

$$V_x = \frac{\Delta p_z}{d} V(t), \quad (6.29)$$

$$V_y = \frac{\Delta p_y}{d} V(t), \quad (6.30)$$

$$V_z = \frac{\Delta p_x}{d} V(t). \quad (6.31)$$

The position and orientation of the end effector may be expressed as follows:

$$X(t) = \begin{bmatrix} 0 & 0 & 1 & p_{2x} + z(t) \\ 0 & -1 & 0 & p_{2y} - y(t) \\ 1 & 0 & 0 & p_{2z} + x(t) \\ 0 & 0 & 0 & 1 \end{bmatrix}, \quad (6.32)$$

where $x(t)$, $y(t)$, and $z(t)$ are expressed as follows:

for $t < t_{\text{acc}}$

$$x(t) = 0.5 \frac{\Delta p_z}{d} \frac{V_{\max}}{t_{\text{acc}}} t^2, \quad (6.33)$$

$$y(t) = 0.5 \frac{-\Delta p_y}{d} \frac{V_{\max}}{t_{\text{acc}}} t^2, \quad (6.34)$$

$$z(t) = 0.5 \frac{\Delta p_x}{d} \frac{V_{\max}}{t_{\text{acc}}} t^2, \quad (6.35)$$

and for $t \geq t_{acc}$

$$x(t) = 0.5 \frac{\Delta p_z}{d} \frac{v_{max}}{t_{acc}} (t - 0.5 t_{acc}), \quad (6.33)$$

$$y(t) = 0.5 \frac{-\Delta p_y}{d} \frac{v_{max}}{t_{acc}} (t - 0.5 t_{acc}), \quad (6.34)$$

$$z(t) = 0.5 \frac{\Delta p_x}{d} \frac{v_{max}}{t_{acc}} (t - 0.5 t_{acc}). \quad (6.35)$$

Based on the designed maximum velocity, 100 mm/sec, and the acceleration interval, 0.5 second, the time required for the end effector to move from POS₂ to POS₃ is:

$$T = \frac{d}{v_{max}} + 0.5 t_{acc} = 16.53 \text{ sec.} \quad (6.36)$$

In other words, the execution time of this subtask should be smaller than 16.53 seconds to meet the real-time requirement. The total real-time requirement for the overall task is then 18.03 seconds.

6.4 Simulation Results and Performance Evaluation

In this section, simulation results concerned with execution time, accuracy, and the effects of position feedback for the Inverse Kinematics algorithm will be presented. Also, investigations of movement at high speed and long-term stability of the algorithm are described and evaluated.

First of all, results of the simulations of the three tasks described in the previous section are shown in the first subsection. The second subsection presents the variation of accuracy for several levels of precision of the processor when the end effector is moving at high speed. Finally, the long-term stability of the algorithm is evaluated by introducing a long-term task with a reasonable speed and by

adding position feedback. All the results shown in this section were simulated on a VAX-11/785 computer.

6.4.1 Results for Three Different Tasks

Two complete simulations of the Inverse Kinematics algorithm have been programmed. A Pascal simulation is developed to show the robustness and accuracy of the algorithm even near singularities. A second simulation uses the special algorithms given in Chapter 5 to simulate the detailed operation of the algorithm on the proposed special-purpose architecture.

The basic results of the Pascal simulation are given in Table 6.3. The inverse of step size indicates the rate for updating data (integration rate). The real-time requirement denotes the maximum allowable execution time for the CPU to complete the task (for real-time operation). The execution time indicates the actual time required by the processor. For the Pascal simulations, the execution time is measured by extracting the CPU time spent in the simulation. For the simulations on the Inverse Kinematics Processor, the execution time is equal to the product of the number of cycles which the Inverse Kinematics Processor spends to execute the algorithm and the system cycle time, 150 ns. The last column of the table shows the maximum deviation between the estimated and the desired positions of the end effector. The step size for this simulation was selected to be 0.01 second, and the results indicate that this step size is adequate to give a maximum error of less than 0.1 mm. As expected, the execution time on a VAX-11/785 for any of three tasks is much slower than real time.

As indicated in the previous results, the maximum error occurs during the third task, GMF S-400 straight line movement. Using this task as a benchmark, the relationship among step size, execution time,

Table 6.3 Results of Pascal Simulations for Three Different Tasks on the VAX-11/785.

Task	Step size (sec)	Real-time requirement (sec)	Execution time (sec)	Maximum error (mm)
RM-501 circle	0.01	36	255.32	0.0069
RM-501 reaching out	0.01	7.3	42.18	0.016
GMF S-400 line move	0.01	18.03	116.71	0.046

and accuracy may be determined and is given in Tables 6.4 and 6.5 for the Pascal and detailed Inverse Kinematics Processor simulations, respectively. Note that the processor cycle time in the second case is assumed to be 150 ns. The maximum error for both simulations as shown in the tables are exactly the same. This results because the same precision for sine/cosine, reciprocal, and all arithmetic operations is used (32-bit, single precision floating point) and all computations are executed in the same sequence in both cases.

Because of roundoff errors and truncation errors, results with different maximum error may be obtained if the computation sequence is different. For example, the joint angles are expressed in degrees but have to be converted to radians for the computation of sine/cosine through Taylor's series expansion and converted back to units of degrees. Two computing sequences are possible:

$$(1) \quad \theta / 180.0 * \pi * 180.0 / \pi$$

$$(2) \quad \theta * \pi / 180.0 * 180.0 / \pi$$

The only difference between these two expressions are the computing sequence. Through the VAX-11/785 computer, the expression $\text{abs}(\theta - \theta / 180.0 * \pi * 180.0 / \pi)$ is not equal to $\text{abs}(\theta - \theta * \pi / 180.0 * 180.0 / \pi)$, and the second approach has smaller errors. Therefore, the computation sequence should be optimized at the microcode level.

However, the improvement of the execution time of the algorithm from implementation on a VAX-11/785 computer to a special-purpose Inverse Kinematics Processor is by a speed-up factor of about 170. Results in Table 6.5 indicate that a maximum error of less than 0.01 mm may be obtained in real time if the step size is 1 ms.

Results also show the robustness of this algorithm even near points of singularity. In task three, the program actually stops at a singular

Table 6.4 Results of Pascal Simulations for Three Different Step Sizes (GMF S-400 line move task).

Maximum Velocity (mm/sec)	Maximum Acceleration (mm/sec²)	Real-Time Requirement (sec)	Step Size (sec)	Maximum Error (mm)	Execution Time (sec)
100	200	16.53	0.01	0.046	106.48
100	200	16.53	0.005	0.0208	210.8
100	200	16.53	0.001	0.0079	1047.81

Table 6.5 Results of Simulations on the Inverse Kinematics Processor (Processor Cycle Time = 150 ns).

Maximum Velocity (mm/sec)	Maximum Acceleration (mm/sec²)	Real-Time Requirement (sec)	Step Size (sec)	Maximum Error (mm)	Execution Time (sec)
100	200	16.53	0.01	0.046	0.62
100	200	16.53	0.005	0.0208	1.23
100	200	16.53	0.001	0.0079	6.14

configuration although the task has been designed to pass through that point and continue to move in a straight line.

The tasks simulated in this subsection are all designed to drive the manipulator moving at low speeds: task 1 is 10 deg/sec, task 2 is 10 mm/sec, and task 3 is only 100 mm/sec. Results in the above tables indicate that the proposed Inverse Kinematics Processor is adequate to solve the Inverse Kinematics problem in real time if the manipulator is moving at low speed. For high speed movements, the error may be amplified since there is a larger increment of motion during each time step. A task with high speed motion and its associated simulation results will be presented in the next subsection.

6.4.2 High Speed Movement

Using the same task, moving the GMF S-400 in a straight line, as a benchmark, the maximum speed of the end effector may be increased from 100 mm/sec to 1500 mm/sec with an associated acceleration of 5000 mm/sec/sec. With such an acceleration, the end effector may accelerate from 0 to 1500 mm/sec within 0.3 second, which is near the greatest requirement for most industrial robots.

Pascal simulations with both single and double precision are shown in Tables 6.6 and 6.7. The results in these two tables indicate that accurate tracking, with an error of less than 0.04 mm for single precision and 0.025 mm for double precision, may be obtained. As expected, the execution time for each case is much longer than real time.

Table 6.8 shows results of the simulations of the Inverse Kinematics Processor. The maximum error for this high speed task is less than 0.04 mm as with the Pascal simulations, but the execution time is smaller than real time.

Table 6.6 Results of Pascal Simulations of High Speed Motion with Single Precision (32-bit floating point).

Maximum Velocity (mm/sec)	Maximum Acceleration (mm/sec²)	Real-Time Requirement (sec)	Step Size (sec)	Maximum Error (mm)	Execution Time (sec)
1500	5000	1.235	0.01	> 1.0	--
1500	5000	1.235	0.005	0.4914	16.33
1500	5000	1.235	0.001	0.0452	78.30
1500	5000	1.235	0.0005	0.0385	155.26

Table 6.7 Results of Pascal Simulations of High Speed Motion with Double Precision (64-bit floating point).

Maximum Velocity (mm/sec)	Maximum Acceleration (mm/sec²)	Real-Time Requirement (sec)	Step Size (sec)	Maximum Error (mm)	Execution Time (sec)
1500	5000	1.235	0.01	0.425	10.83
1500	5000	1.235	0.005	0.243	20.87
1500	5000	1.235	0.001	0.0449	100.20
1500	5000	1.235	0.0005	0.0211	195.61

Table 6.8 Results of Inverse Kinematics Simulation on the Proposed Architecture for a Task with High Speed Motion.

Maximum Velocity (mm/sec)	Maximum Acceleration (mm/sec²)	Real-Time Requirement (sec)	Step Size (sec)	Maximum Error (mm)	Execution Time (sec)
1500	5000	1.235	0.01	> 1.0	—
1500	5000	1.235	0.005	0.4914	0.095
1500	5000	1.235	0.001	0.0452	0.471
1500	5000	1.235	0.0005	0.0385	0.942

For very high speed motion of the end effector, the error may increase. Table 6.9 shows results for simulations on the same task with a maximum velocity of 3000 mm/sec and an acceleration of 6000 mm/sec/sec. Results indicate that an error of less than 0.1 mm may still be obtained in real time for such a high speed motion.

To obtain the best result and yet be within the requirement of real time operation, a step size of 0.5 ms has been used. Simulation result indicates that the maximum error is less than 0.06 mm and the execution time on the Inverse Kinematics Processor using 32-bit precision is only 0.6 sec, which is smaller than the real time requirement of 0.793 seconds.

6.4.3 Effects of Position Feedback

All previous results were obtained without any position feedback control. In other words, the diagonal gain matrix, K_p , in Eq. (4.21) was assigned to be a zero matrix. Although results seem adequate for most applications, it is anticipated that long-term drift problems associated with numerical integration may occur without this feedback. Furthermore, it is expected that position feedback may reduce the position error and give better performance in terms of accuracy of the algorithm since it provides closed-loop control of position.

The equations for the position feedback term are given as follows [20,32,47]:

Table 6.9 Results of Simulations for a Task with Very High Speed Motion.

Simulation Method	Real-Time Requirement (sec)	Step Size (sec)	Maximum Error (mm)	Execution Time (sec)
PASCAL Simulation with Single Precision	0.793	0.001	0.067	50.65
PASCAL Simulation with Double Precision	0.793	0.001	0.067	62.87
Inverse Kinematics Processor Simulation with 32-bit precision	0.793	0.001	0.067	0.303

$$\underline{\lambda}[X_d - X(q)] = \begin{bmatrix} \frac{1}{2} [(\underline{a} \cdot \underline{o}_d) - (\underline{o} \cdot \underline{a}_d)] \\ \frac{1}{2} [(\underline{n} \cdot \underline{a}_d) - (\underline{a} \cdot \underline{n}_d)] \\ \frac{1}{2} [(\underline{o} \cdot \underline{n}_d) - (\underline{n} \cdot \underline{o}_d)] \\ \underline{n} \cdot (\underline{p}_d - \underline{p}) \\ \underline{o} \cdot (\underline{p}_d - \underline{p}) \\ \underline{a} \cdot (\underline{p}_d - \underline{p}) \end{bmatrix} \quad (6.37)$$

and

$$K_p = \begin{bmatrix} K_1 & 0 & 0 & 0 & 0 & 0 \\ 0 & K_2 & 0 & 0 & 0 & 0 \\ 0 & 0 & K_3 & 0 & 0 & 0 \\ 0 & 0 & 0 & K_4 & 0 & 0 \\ 0 & 0 & 0 & 0 & K_5 & 0 \\ 0 & 0 & 0 & 0 & 0 & K_6 \end{bmatrix}, \quad (6.38)$$

where $\underline{n}_d$, $\underline{o}_d$, $\underline{a}_d$, $\underline{p}_d$ and $\underline{n}$, $\underline{o}$, $\underline{a}$, $\underline{p}$ are the first three elements of the columns of X_d or X , respectively. This computation requires 36 multiplications and 30 additions, and has been included in Table 5.4.

One of the tasks for the MITSUBISHI RM-501 which was designed in Section 6.3.1 was to draw a circle. A long-term task may be obtained by making two modifications to this task: 1) the motion speed is changed from 10 deg/sec to 90 deg/sec, and 2) the designed circle is drawn 18 times instead of only once.

Figs. 6.8 and 6.9 show the results of this simulation for a step size of 0.01 sec and 0.001 sec, respectively. Deviation between the estimated position and the desired position is recorded every second. Results indicate that long-term drift does exist if there is no position feedback control. Note that the maximum error after 18 cycles for a step size of 0.001 second, 2.084 mm, is larger than that of 0.01 step size, 1.18 mm. This results because there are 10 times more integration steps and subsequently greater accumulation of errors with a step size of 0.001 sec. This problem with drift will lead to divergence of the algorithm for any long-term task.

With position feedback, the drift problem is eliminated. Figs. 6.10 and 6.11 give results for two different feedback gains with a step size of 0.01 second. With the larger feedback gain, the system has the smaller maximum error and faster response time. Fig. 6.12 shows the relationship between feedback gain and maximum error. When the feedback gain is 100, the maximum error is only 0.043 mm which is adequate for most robot applications.

For the case of a 0.001 second step size, similar results have been obtained. Figs. 6.13 and 6.14 show the effects of position feedback. Fig. 6.15 gives the relationship between feedback gain and maximum error. The maximum error for the case that the feedback gain is 200 is only 0.0182 mm, that is 0.72 mil.

The best results for this task have also been obtained by using a step size of 0.5 ms and a feedback gain of 400. The maximum error for this case is only 0.0129 mm (0.51 mil), smaller than the requirement for any industrial robot manipulator. Also, the execution time is 53.9 sec, which is still smaller than the real time requirement of 72 seconds.

Figure 6.8 RM-501 Continuously Drawing a Circle with a Speed of 90 deg/sec (Step Size is 0.01 sec and No Position Feedback is Added).

Figure 6.9 RM-501 Continuously Drawing a Circle with a Speed of 90 deg/sec (Step Size is 0.001 sec. and No Position Feedback is Added).

Figure 6.10 Rm-501 Continuously Drawing a Circle with a Speed of 90 deg/sec (Step Size is 0.01 sec and a Feedback Gain of 2 is Added).

Figure 6.11 RM-501 Continuously Drawing a Circle with a Speed of 90 deg/sec (Step Size is 0.01 sec and a Feedback Gain of 50 is Added).

Figure 6.12 The Relationship Between Maximum Error and the Feedback Gain for a Step Size of 0.01 sec.

Figure 6.13 RM-501 Continuously Drawing a Circle with a Speed of 90/deg/sec (Step Size is 0.001 sec and a Feedback Gain of 5 is Added).

Figure 6.14 RM-501 Continuously Drawing a Circle with a Speed of 90 deg/sec (Step Size is 0.001 sec and a Feedback Gain of 50 is Added).

Figure 6.15 The Relationship Between Maximum Error and Feedback Gain for a Step Size of 0.001 sec.

With an offset at the initial position, the algorithm will diverge if the feedback term in Eq. (4.21) is not included. The second subtask for the GMF S-400 has been used and an initial position offset of 3 mm has been set. Fig. 6.16 shows the results when the position feedback term is added and a feedback gain of 600 is selected. This result indicates that the error will be reduced through an approximate exponential curve with a time constant of about 0.1 sec. Other results have indicated that the time constant will increase as the feedback gain decreases which is as expected. Simulation also shows that the system will become unstable when the feedback gain has been increased to 1000.

6.5 Summary

Through the simulations for two industrial robots on three different tasks, the results indicate that the approach suggested in this dissertation, a strict-convergence algorithm and a special-purpose architecture developed in Chapters 4 and 5, may provide a good solution for Inverse Kinematics in real time. The simulation results shown in this chapter indicate that the developed algorithm can converge even at a position which is only one time step away from singularity points. With such a special-purpose Inverse Kinematics Processor, a speed-up factor of over 150 in the execution time may be obtained (Table 6.9). Also, with a position feedback term, the algorithm converges even for a long-term task and the performance in positional precision may be 4-5 times better, Figs. 6.10 and 6.11. The best result of simulations shows that the execution time is in real time and the maximum position error is smaller than 0.01 mm, which is better than the requirement of many industrial robot manipulators.

Figure 6.16 The Position Error with an Initial Error of 3 mm and Feedback Gain of 600.

Chapter 7

SUMMARY AND CONCLUSIONS

7.1 Research Contributions

In this dissertation, a strictly convergent numerical algorithm for Inverse Kinematics has been developed such that its derived solution has no degeneracy problem, no convergence problem even near a singularity configuration or with initial errors, no problems for long-term drift associated with the integration, and is also applicable to redundant robots. Furthermore, mapping the numerical algorithm developed onto a special-purpose architecture to obtain a solution in real time has been simulated for several different models and tasks of industrial robots.

The complete algorithm is based on numerical integration of joint rates which are obtained from Cartesian rates through the Inverse Jacobian. To avoid difficulty near singularity points, a deviation function, which is a weighted sum of the squares of the component differences between the desired and estimated position/orientation of the end effector, has been used as the convergence criterion. The property of strict convergence has been reached by reducing the value of this function each time step and by introducing a feedback mechanism. With this position feedback, the algorithm forms a closed-loop system and compensation has been made for problems with long-term drift in

numerical integration and with initial errors in the solution. The positioning performance of this algorithm has also been dramatically upgraded by including this feedback mechanism.

The algorithm developed applies a pseudoinverse technique, which minimizes the energy of movement, to provide a solution which is applicable to robots with any number of degrees of freedom. By using numerical integration and this pseudoinverse, the solution generated by the algorithm naturally provides a continuous trajectory and thus has no degeneracy problem. Finally, because of the use of a predictor-corrector integration method, this algorithm is more efficient than other methods which are based on Newton-Raphson iteration.

In order to obtain an Inverse Kinematics solution in real time, the concept of implementing the algorithm through a special-purpose computer architecture has been investigated and an Inverse Kinematics Processor has been proposed for this purpose. This architecture includes a 32-bit, high-speed floating-point chip, the Am29325, a register file with a self-looping data path, a seed look-up table for reciprocal generation, and a microprogrammed controller. The internal structure of the floating-point chip contains three registers and two data paths which are very useful for efficient matrix-vector operations. With such a chip, a 32-bit, floating-point multiplication, subtraction or addition may be executed in one clock cycle. The data path associated with the register file provides a specific route for updating matrices efficiently.

Through simulation, the complete algorithm developed in this

dissertation has been mapped onto the proposed Inverse Kinematics Processor. Results shown in this dissertation indicate that the algorithm developed is strictly convergent and the solution for a six degree-of-freedom industrial robot (for which no closed-form solution exists) may be obtained at an approximate 2 KHz rate. The maximum position error is smaller than 0.01 mm for a numerical step size of 1 ms. With position feedback, long-term drift has been eliminated and the position accuracy of the end effector is much better.

In conclusion, a strictly convergent Inverse Kinematics algorithm has been fully developed and evaluations of detailed simulations of its implementation on a special-purpose architecture have shown excellent performance. Through this approach, a complete Inverse Kinematics solution for general robot manipulators may be obtained in real time.

7.2 Research Extensions

This dissertation assumed that the desired Cartesian rate, $\dot{\underline{x}}_d$, provided by the motion planning module was an exact derivative of the desired position/orientation. If the trajectory is complex, the rates will probably not be exact for all points. It is expected that the position feedback term in the algorithm will compensate for this inaccuracy. However, since the values of joint rates, $\dot{\underline{q}}$, are directly effected, the maximum error of the joint positions may increase. The effects of inaccurate Cartesian rates on position accuracy is still unknown and more research is needed.

The results in this dissertation show that a large speed-up factor (up to 150) is obtained through the use of special-purpose hardware for

Inverse Kinematics. The same approach may be applied to other complex robotics computations such as Inverse Dynamics and will hopefully lead to a real time solution. More work should be done in this area.

All results shown in this dissertation came from simulations on a VAX-11/785 computer. Since some of the simulations were done at the microcode level, it is expected that no major problem will be encountered with actual hardware implementation. However, the actual processor remains to be developed and an I/O interface for a multiprocessor needs to be designed. Also, only three tasks have been used to complete the evaluation. Other tasks with a wider range of trajectories may be designed to further evaluate the performance of the algorithm.

The number of bits in the floating-point arithmetic unit in the Inverse Kinematics Processor need not necessarily be 32. For manipulators with ultra high speed and a large maximum extension, a 32-bit processing unit may not be accurate enough, and a larger number of bits may be required. Considering the possibility of future implementations with custom VLSI, the optimal number of bits of the processing unit should be studied further. The relationship between number of bits in the processor and the position accuracy needs further investigation.

This dissertation has provided the algorithm and architecture for a real-time solution for Inverse Kinematics which is applicable to the general robot manipulator. With the algorithm developed and the proposed architecture, it is hoped that the results obtained and the

research extensions proposed will lead to a valuable Inverse Kinematics Processor for industry which will be applicable to a wide range of manipulators and tasks.

REFERENCES

- [1] Paul, R.P., "Manipulator Cartesian Path Control," IEEE Transactions on Systems, Man, and Cybernetics, SMC-9, No. 11, 1979, pp. 702-711.
- [2] Bazerghi, A. and Goldenberg, A.A., "An Exact Kinematic Model of the PUMA 600 Manipulator," IEEE Transactions on Systems, Man, and Cybernetics, Vol. SMC-14, No. 3, May/June 1984, pp. 483-487.
- [3] Paul, R.P., Robot Manipulators: Mathematics, Programming, and Control, MIT Press, Cambridge, Mass., 1981.
- [4] Pieper, D.L. and Roth, B., "The Kinematics of Manipulators Under Computer Control," Proceedings II -- International Congress on the Theory of Machines and Mechanisms, Vol. 2, 1969, pp. 159-168.
- [5] Stone, H.W., Sanderson, A.C., and Newman, C.P., "Arm Signature Identification," Proceedings 1986 IEEE International Conference on Robotics and Automation, San Francisco, CA, pp. 44-48.
- [6] Maciejewski, A.A. and Klein, C.A., "Obstacle Avoidance for Kinematically Redundant Manipulators in Dynamically Varying Environments," The International Journal of Robotics Research, Vol. 4, No. 3, Fall 1985, pp 109-117.
- [7] Paul, R.P., Shimano, B., and Mayer, G.E., "Kinematic Control Equations for Simple Manipulators," IEEE Trans. on Systems, Man, and Cybernetics, Vol. SMC-11, No. 6, June 1981, pp. 449-455.
- [8] Featherstone, R., "Position and Velocity Transformations Between Robot End-Effector Coordinates and Joint Angles," The International Journal of Robotics Research, Vol. 2, No. 2, Summer 1983, pp. 35-45.
- [9] Hollerbach, J.M. and Sahar G., "Wrist-Partitioned, Inverse Kinematic Accelerations and Manipulator Dynamics," The International Journal of Robotics Research, Vol. 2, No. 4, Winter 1983, pp. 61-76.
- [10] Elgazzar, Shadia, "Efficient Kinematic Transformations for the PUMA 560 Robot," IEEE Journal of Robotics and Automation, Vol. RA-1, No. 3, September 1985, pp. 142-151.

- [11] Takano, M., "A New Effective Solution for Inverse Kinematics Problem (Synthesis) of a Robot with Any Type of Configuration," Journal of the Faculty of Engineering, The University of Tokyo, Vol. 38, No. 2, 1985, pp. 107-135.
- [12] Roth, B., Rastegar, J., and Scheinman, V., "On the Design of Computer Controlled Manipulators," Proc. of Symposium on the Theory and Practice of Robots and Manipulators, Vol. 1, Sept. 1973, pp. 93-113.
- [13] Pieper, D.L., The Kinematics of Manipulators Under Computer Control, Ph.D. dissertation, Stanford University, CA, 1969.
- [14] Goldenberg, A.A. and Lawrence, D.L., "A Generalized Solution to the Inverse Kinematics of Robotic Manipulators," ASME Journal of Dynamic Systems, Measurement, and Control, Vol. 107, March 1985, pp. 103-106.
- [15] Oh, S.Y., Orin, D.E., and Bach, M., "An Inverse Kinematic Solution for Kinematically Redundant Robot Manipulators," Journal of Robotic Systems, 1(3), 1984, pp. 235-249.
- [16] Hansen, J.A., Gupta, K.C., and Kazerounian, S.M.K., "Generation and Evaluation of the Workspace of a Manipulator," International Journal of Robotics Research, Vol. 2, No. 3, Fall 1983, pp. 22-30.
- [17] Uicker, J.J., Denavit, J., and Hartenberg, R.S., "An Iterative Method for Displacement Analysis of Spatial Mechanisms," Journal of Applied Mechanics, June 1964, pp. 309-314.
- [18] Angeles, J., "On the Numerical Solution of the Inverse Kinematic Problem," The International Journal of Robotics Research, Vol. 4, No. 2, Summer 1985, pp. 21-37.
- [19] Gupta, K.C. and Kazerounian, K., "Improved Numerical Solutions of Inverse Kinematics of Robots," Proceedings of 1985 International Conference on Robotics and Automation, St. Louis, MO, March 1985, pp. 743-748.
- [20] Goldenberg, A.A., Benhabib, B., and Fenton, R.G., "A Complete Generalized Solution to the Inverse Kinematics of Robots," IEEE Journal of Robotics and Automation, Vol. RA-1, No. 1, March 1985, pp. 14-20.
- [21] Tsai, L.W. and Morgan, A.P., "Solving the Kinematics of the Most General Six-and Five-Degree-of-Freedom Manipulator by Continuation Methods," ASME Journal of Mechanisms, Transmissions, and Automation Design, Vol. 107, June 1985, pp. 189-200.

- [22] Lenarcic, J., "An Efficient Numerical Approach for Calculating the Inverse Kinematics for Robot Manipulators," Robotica, Vol. 1, 1983, pp. 1-6.
- [23] Whitney, D.E., "The Mathematics of Coordinate Control of Prosthetic Arms and Manipulators," Journal of Dynamic Systems, Measurement, and Control, December 1972, pp. 303-309.
- [24] Paul, R.P. and Stevenson, C.N., "Kinematics of Robot Wrists," The International Journal of Robotics Research, Vol. 2, No. 1, Spring 1983, pp. 31-38.
- [25] Uchiyama, M., "A Study of Computer Control of Motion of a Mechanical Arm," Bulletin of JSME, Vol. 22, No. 173, Nov. 1979, pp. 1640-1647.
- [26] Taylor, R.H., "Planning and Execution of Straight-Line Manipulator Trajectories," IBM Journal of Research and Development, Vol. 23, 1979, pp. 424-436.
- [27] Yoshikawa, T., "Analysis and Control of Robot Manipulators with Redundancy," Proceedings of First International Symposium of Robotics Research, Bretton Woods, N.H. Aug. 28-Sept. 2, 1983, pp. 735-747.
- [28] Ribble, E.A., Synthesis of Human Skeletal Motion and the Design of a Special-Purpose Processor for Real-Time Animation of Human and Animal Figure Motion, M.S. thesis, The Ohio State University, Columbus, Ohio, June 1982.
- [29] Turney, J.L. and Mudge, T.N., "VLSI Implementation of a Numerical Processor for Robotics," Proc. of the 27th International Instrumentation Symposium, Indianapolis, Indiana, April 1981, pp. 169-175.
- [30] Chao, H.H., Parallel/Pipeline VLSI Computing Structures for Robotics Applications, Ph.D dissertation, The Ohio State University, Columbus, Ohio, June 1985.
- [31] Orin, D.E., "Systolic Architectures for Computation of the Jacobian for Robot Manipulators," Specialized Computer Architectures for Robotics and Automation, Edited by James Graham, Gordon and Breach Publishers, New York, to appear.
- [32] Lilly, K.W., Multiprocessor Implementation of Real-Time Control Schemes For Robot Manipulators, M.S. thesis, The Ohio State University, Columbus, Ohio, August 1985.
- [33] Lathrop, R.H., "Parallelism in Manipulator Dynamics," The International Journal of Robotics Research, Vol. 4, No. 2, Summer 1985, pp. 82-102.

- [34] Orin, D.E., Chao, H.H., Olson, K.W., and Schrader, W.W., "Pipeline/Parallel Algorithms for the Jacobian and Inverse Dynamics Computations," IEEE International Conference on Robotics and Automation, St. Louis, Missouri, March 1985, pp. 785-789.
- [35] Hollerbach, J.M., "Optimum Kinematic Design for a Seven Degree of Freedom Manipulator," Robotics Research: The Second International Symposium, edited by Hanafusa H. and Inoue H., MIT Press, Cambridge, Mass. 1985, pp. 215-222.
- [36] Orin, D.E. and Schrader, W.W., "Efficient Jacobian Determination for Robot Manipulators," International Journal of Robotics Research, Vol. 3, No. 4, Winter 1984, pp. 66-75.
- [37] Nigam, R. and Lee, C.S.G., "A Multiprocessor-Based Controller for the Control of Mechanical Manipulators," IEEE Journal of Robotics and Automation, Vol. RA-1, No. 4, December 1985, pp. 173-182.
- [38] Gajski, D.D. and Peir J.K., "Essential Issues in Multiprocessor Systems," IEEE Computer Magazine, June 1985, pp. 9-27.
- [39] Patton, P.C., "Multiprocessors: Architecture and Application," IEEE Computer Magazine, June 1985, pp. 29-40.
- [40] Klein, C.A. and Wahawisan, W., "Use of a Multiprocessor for Control of a Robot System," International Journal of Robotics Research, Vol. 1, No. 2, Summer 1982, pp. 45-59.
- [41] McGhee, R.B., Orin, D.E., Pugh, D.R., and Patterson, M.R., "A Hierarchically-Structured System for Computer Control of a Hexapod Walking Machine," Proceedings of IFToMM Symposium on Robots and Manipulator Systems, Udine, Italy, June 1984.
- [42] Klein, C.A. and Barrientos, C., "Design of a Multimicroprocessor-Based Controller Using a Structured Design Approach," IEEE Transactions on Industrial Electronics, Vol. IE-31, No. 4, November 1984, pp. 292-298.
- [43] Ozguner, F. and Kao, M.L., "A Reconfigurable Multiprocessor Architecture for Reliable Control of Robotic Systems," Proceedings of the 1985 IEEE International Conference on Robotics and Automation, St. Louis, Missouri, March 1985, pp. 802-806.
- [44] Orin, D.E., "Pipelined Approach to Inverse Plant Plus Jacobian Control of Robot Manipulators," IEEE International Conference on Robotics, Atlanta, Georgia, March 1984.
- [45] Sandor, B.I., Engineering Machines: Design, Prentice Hall, Englewood Cliffs, N.J., 1983, pp. 498.

- [46] Denavit, J. and Hartenberg, R. S., "A Kinematic Notation for Lower-Pair Mechanisms based on Matrices," ASME Journal of Applied Mechanics, Vol. 23(2), June 1955, pp. 215-221.
- [47] Wu, C.H. and Paul, R.P., "Resolved Motion Force Control of Robot Manipulators," IEEE Transactions on Systems, Man, and Cybernetics, Vol. SMC-12, No. 3, May/June 1982, pp. 266-275.
- [48] Klein, C.A. and Huang, C.H., "Review of Pseudoinverse Control for Use with Kinematically Redundant Manipulators," IEEE Transactions on Systems, Man, and Cybernetics, Vol. SMC-13(2), 1983, pp. 245-250.
- [49] Wampler, C.W., "Manipulator Inverse Kinematic Solutions Based on Vector Formulations and Damped Least-Squares Methods," IEEE Transactions on Systems, Man, and Cybernetics, Vol. SMC-16, No. 1, January/February 1986, pp. 93-101.
- [50] Cohen, A.M., Numerical Analysis, Halsted Press, New York, 1973.
- [51] Ralston, A., A First Course in Numerical Analysis, McGraw-Hill Book Co. Ltd., New York, 1965.
- [52] Fox, L.(ed.), Numerical Solution of Ordinary and Partial Differential Equations, Pergamon Press, Oxford, 1962.
- [53] Crane, R.L. and Klopfenstein, R.W., "A Predictor-Corrector Algorithm with an Increased Range of Absolute Stability," Journal of Associ. Comput. Mach., 12, 1965, pp. 227-241.
- [54] Fletcher, R., "Generalized Inverse Methods for the Best Least Squares Solution of Systems on Non-Linear Equations," Computer Journal, No. 10, 1968, pp. 392-399.
- [55] AMD 1985 Data Book: Bipolar Microprocessor Logic and Interface, Advanced Micro Devices, Inc., Sunnyvale, CA, pp. 7.64 - 68.
- [56] Tuma, J.J., Engineering Mathematics Handbook, McGraw-Hill Book Company, 1970, pp. 100-101.
- [57] Wallace, C.S., "A Suggestion for A Fast Multiplier," IEEE Transactions on Electronic Computers, Vol. EC-13, Feb. 1964, pp. 14-17.
- [58] Ferrari, D., "A Division Method Using A Parallel Multiplier," IEEE Transactions on Electronic Computers, Vol. EC-16, April 1967, pp. 224-226.

- [59] Krishnamurthy, E.V., "On Optimal Iterative Schemes for High-Speed Division," IEEE Transactions on Computers, Vol. C-19, March 1970, pp. 227-231.
- [60] Flynn, M.J., "On Division by Functional Iteration," IEEE Trans. on Computers, Vol. C-19, No. 8, August 1970, pp 702-706.
- [61] Fairchild TTL Data Book, Fairchild Camera and Instrument Corporation, Mountain View, CA, 1978.
- [62] AMD 1984 Data Book: Bipolar/MOS Memories, Advanced Micro Devices, Inc., Sunnyvale, CA, 1984.
- [63] Orin, D.E. and Tsai, Y.T., "A Real-Time Computer Architecture For Inverse Kinematics," Proc. of 1986 IEEE International Conference on Robotics and Automation, San Francisco, CA. April 7-10, 1986.

APPENDIX A

Computer Programs

A.1 Contents of Appendix A

This appendix contains all programs used in the simulations of both Inverse Kinematics algorithm and Inverse Kinematics Processor. Programs are thus divided into two parts.

A.2 Contains all Pascal programs which simulate the algorithm itself and show the robustness and accuracy of the algorithm even near points of singularity. The generic computational modules are shown in Appendix A.2.1. A.2.2 contains programs of three designed tasks, and A.2.3 lists the main programs for the simulations.

A.2.1 includes 13 computational modules for the Inverse Kinematics algorithm. First of all, an announcement of all global variables is listed in file IKGLB.PAS. Three generic computational modules for robot manipulators: Direct Kinematics (DIRKIN.PAS), Jacobian (JAC.PAS), and Pseudo Inverse (PSEUDO.PAS), are listed next. Listed third are six computational modules for Inverse Kinematics: PREDICTION.PAS, CORRECTION.PAS, ERROR.PAS, EVALUATION.PAS, INTERPOLATION.PAS, and ADJUST.PAS. Finally, a position feedback module, POSBK.PAS, and an initialization module, INITIQL.PAS, are listed. All parameters of manipulators, constants for numerical integration, and initialization data are included in the initialization modules.

A.2.2 contains programs for three tasks. TASK1.PAS lists the task designed for the RM-501 to draw a circle on the ground. TASK2.PAS shows the designed trajectory for RM-501 to extend its arm to the maximum extension. TASK31.PAS is the program to rotate the S-400 manipulator around the x-axis of its end effector such that the direction of the end effector, z-axis, is changed as desired. TASK32.PAS is the program for moving the S-400 on a straight line.

A.2.3 shows the main programs for the simulations of Inverse Kinematics algorithm. INVKIV.PAS is the program to obtain the analytical solution for Inverse Kinematics of the Mitsubishi robot RM-501, which is used to provide a reference solution for comparison. Finally, LTSTP.PAS shows the complete program for the Inverse Kinematics algorithm with position feedback.

A.3 contains all programs which simulate the Inverse Kinematics algorithm on the proposed architecture. All programs are written in Pascal but are essentially microprograms. The basic architecture of the proposed Inverse Kinematics Processor is simulated through programs listed in Appendix A.3.1. A.3.2 presents computational modules for the algorithm itself, A.3.3 shows tasks, and A.3.4 lists the main programs for the simulations.

A.3.1 includes four programs. AM325.PAS simulates the arithmetic processing unit with its two feedback data paths. All control signals, arithmetic operations, and data transmissions are simulated step by step. SEEDTABLE.PAS is the program to generate the seeds for the reciprocal in software. The accuracy is 32-bit although it can be any number of bits.

SINE/COSINE.PAS simulates Taylor Series expansion of the sine/cosine function. The accuracy of both the input and output are designed to be 32 bits. SUB_REC.PAS uses the Newton-Raphson iteration equations and result from SEED_TABLE.PAS to generate the reciprocal.

A.3.2 contains 8 programs which simulate the computational modules of the Inverse Kinematics algorithm and one file of global variables. GLOBAL.PAS contains all variables. INITIQ1.PAS and INIT_XN1.PAS include all initialization parameters. KIN_JAC.PAS and PSEUDO_INV.PAS are generic modules for the computation of Direct Kinematics, the Jacobian, and the Inverse Jacobian. SUB_ADJ.PAS, SUB_COR.PAS, SUB_PRE.PAS, and SUB_ERR.PAS are four computational modules for the algorithm.

A.3.3 gives programs for the tasks. TASK1.PAS is the program which computes the designed hand positions for drawing circles by the RM-501. TASK3.PAS generates the corresponding homogeneous matrices for the RM-501 to move its arm to the maximum extension. TASK71.PAS and TASK72.PAS are programs for generating designed hand positions for the task in which the S-400 moves its end effector on a straight line.

A.3.4 contains three programs for simulations. TEST.PAS is the program used to test all computational modules and simulation programs for the proposed architecture. PIPK1.PAS and GMF.PAS simulates the Inverse Kinematics algorithm on the proposed Inverse Kinematics Processor for the RM-501 and S-400 manipulators, respectively.

A.2 Programs for Simulations of Inverse Kinematics Algorithm

A.2 Contains all Pascal programs which simulate the algorithm itself and show the robustness and accuracy of the algorithm even near points of singularity. The generic computational modules are shown in Appendix A.2.1. A.2.2 contains programs of three designed tasks, and A.2.3 lists the main programs for the simulations.

A.2.1 Programs for Computational Modules

A.2.1 includes 13 computational modules for the Inverse Kinematics algorithm. First of all, an announcement of all global variables is listed in file IKGLB.PAS. Three generic computational modules for robot manipulators: Direct Kinematics (DIRKIN.PAS), Jacobian (JAC.PAS), AND Pseudo Inverse (PSEUDO.PAS), are listed next. Thirdly listed are six computational modules for Inverse Kinematics: PREDICTION.PAS, CORRECTION.PAS, ERROR.PAS, EVALUATION.PAS, INTERPOLATION.PAS, and ADJUST.PAS. Finally, a position feedback module, POSBK.PAS, and an initialization module, INITIQ1.PAS, are listed. All parameters of manipulators, constants for numerical integration, and initialization data are included in the initialization modules.

{***** FILE: IKGLB.PAS in directory: [ee.tsai.1k2] *****}

```
{*****}
{
{ VERSION:      1.0
{
{ PROGRAMMER:   Yusheng Tsai
{
{ DATE:        MARCH 31, 1986
{
{ FUNCTION:     This file provides the global variables which
{               can be compiled with other Inverse Kinematics
{               programs.
{
{ USER GUIDE:   Put
{               %INCLUDE 'IKGLB.PAS'
{               in the first line of all programs.
{
{*****}
```

TYPE

```
  ARRAY3 = ARRAY [1..3] OF real;
  ARRAY4 = ARRAY [1..4] OF real;
  ARRAY5 = ARRAY [1..5] OF real;
  ARRAY6 = ARRAY [1..6] OF real;
  ARRAY10= ARRAY [1..10] OF real;
  MATX33 = ARRAY [1..3, 1..3] OF real;
  MATX34 = ARRAY [1..3, 1..4] OF real;
  MATX44 = ARRAY [1..4, 1..4] OF real;
  MATX55 = ARRAY [1..5, 1..5] OF real;
  MATX104 = ARRAY [1..10, 1..4] OF real;
  MATX107 = ARRAY [1..10, 1..7] OF real;
  MATX610 = ARRAY [1..6, 1..10] OF real;
  MATX310 = ARRAY [1..3, 1..10] OF real;
  JOINT_SET = (ROTATIONAL, SLIDING);
  OPTION_SET= (LEFT_UP, RIGHT_UP, LEFT_DOWN, RIGHT_DOWN);
  STATUS_SET= (VALID_SOLUTION, REACH_EXCEEDED, LIMITS_EXCEEDED);
```

```

VAR
  GRAVITY: ARRAY3;           ( Gravity vector )

  X_D, X, TOOL, COORD, E, Z: MATX44;

  LXN,DLXN : MATX107;

  Xn4,DXn4 : ARRAY10;
  A,B,C : ARRAY4;

  KINMC_VARS: ARRAY [1..10] OF
    RECORD
      JOINT_TYPE: JOINT_SET; (ROTATIONAL for a rotational joint
                             and SLIDING for sliding joint )
      ANGLE: real;           ( Joint rotation in degrees )
      TWIST: real;           ( Link twist in degrees )
      LENGTH: real;         ( Length of link )
      OFFSET: real;         ( Offset distance between adjacent
                             links )
    END;

  TIME, DELTA_TIME : real;   ( Elapsed time and delay time )

  N: INTEGER;                ( Degrees-of-freedom )

  JACOB_MAT: MATX610;        ( Jacobian matrix )

  OPTION: OPTION_SET;

```

```

[overlaid] module dirkin(INPUT,OUTPUT);

(***** FILE DIRKIN.PAS *****)

(*****)
(  PROCEDURE DIRKIN  )
(*****)

(*****)
(  VERSION:      1.0                                )
(  )                                                 )
(  PROGRAMMER:   Yusheng Tsai                       )
(  DATE:         March 31, 1986                     )
(  )                                                 )
(  FUNCTION:     Calculates product of all transformation )
(                matrices and supplies the location of  )
(                the end effector in reference         )
(                coordinates.                          )
(  )                                                 )
(  USER GUIDE:   The calling format is:              )
(                DIRKIN(DN,XX)                       )
(  )                                                 )
(  INPUT:        N : Degrees of freedom              )
(  OUTPUT:       X : Homogeneous matrix for the location of )
(                end effector in reference coordinates )
(  )                                                 )
(  PROCEDURES CALLED:  MULT4X4, CALC_A               )
(  )                                                 )
(  GLOBAL VARIABLES )
(    REFERENCED:      KINMC_VARS, Z, E                )
(  )                                                 )
(    MODIFIED:        -None-                          )
(  )                                                 )
(*****)

%INCLUDE 'IKGLB.PAS'
VAR
  I, J, K: INTEGER;

```

```

PROCEDURE MULT4X4(A, B: MATX44;
                  VAR C: MATX44);
VAR
    TEMPM : MATX44;
BEGIN (MULT4X4)
    FOR I := 1 TO 4 DO
        BEGIN
            FOR J := 1 TO 4 DO
                BEGIN
                    TEMPM[I, J] := 0.0;
                    FOR K := 1 TO 4 DO
                        TEMPM[I, J] := TEMPM[I, J] + A[I, K] * B[K, J];
                    END;
                END;
            END;
        FOR I := 1 TO 4 DO
            FOR J := 1 TO 4 DO
                C[I, J] := TEMPM[I, J];
            END; (MULT4X4)
        END;

PROCEDURE CALC_A(I1: INTEGER;
                 VAR AA: MATX44);
CONST
    PI = 3.14159;
VAR
    CT, ST, CA, SA, RAD: real;
BEGIN (CALC_A)
    WITH KINMC_VARS[I1] DO
        BEGIN (1)
            RAD := PI / 180.0;
            CT := COS(ANGLE * RAD);
            ST := SIN(ANGLE * RAD);
            CA := COS(TWIST * RAD);
            SA := SIN(TWIST * RAD);
            AA[1, 1] := CT;
            AA[1, 2] := 0.0-ST * CA;
            AA[1, 3] := ST * SA;
            AA[1, 4] := LENGTH * CT;
            AA[2, 1] := ST;
            AA[2, 2] := CT * CA;
            AA[2, 3] := 0.0-CT * SA;
            AA[2, 4] := LENGTH * ST;
            AA[3, 1] := 0.0;
            AA[3, 2] := SA;
            AA[3, 3] := CA;
            AA[3, 4] := OFFSET;
            AA[4, 1] := 0.0;
            AA[4, 2] := 0.0;
            AA[4, 3] := 0.0;
            AA[4, 4] := 1.0;
        END; (1)
    END; (CALC_A)

```

```

[GLOBAL]PROCEDURE DIRKIN(DN: INTEGER;
VAR XX: MATX44);

```

```

VAR
    T, DA: MATX44;

```

```

BEGIN (DIRKIN)
    FOR I := 1 TO 4 DO
        FOR J := 1 TO 4 DO
            IF I = J THEN
                T[I, J] := 1.0
            ELSE
                T[I, J] := 0.0;
        K := 0;

        FOR K := DN DOWNT0 1 DO
            BEGIN {1}
                CALC_A(K, DA);
                MULT4X4(DA, T, T);
            END; {1}
            MULT4X4(Z, T, T);
            MULT4X4(T, E, XX);

```

```

        END; (DIRKIN)
    end.

```

```

[OVERLAID] MODULE JACOBN ( INPUT,OUTPUT);

(***** FILE: JAC.PAS *****)

(*****)
(  PROCEDURE  JACOBN.PAS  )
(*****)

(*****)
(*  VERSION:      1.0                      *)
(*                                                       *)
(*  PROGRAMMER:   Yusheng Tsai             *)
(*                                                       *)
(*  DATE:         March 31, 1986           *)
(*                                                       *)
(*  FUNCTION:     Calculate the Jacobian based upon joint *)
(*                parameters.              *)
(*                                                       *)
(*  USER GUIDE:  The calling format is:   *)
(*                JACOBN                   *)
(*                                                       *)
(*  TO COMPILE:   $ PAS JAC                *)
(*                                                       *)
(*  PROCEDURES CALLED:  None                *)
(*  GLOBAL VARIABLES  *)
(*                REFERENCED:  KINMC_VARS, N, E *)
(*                                                       *)
(*                MODIFIED:    JACOB_MAT      *)
(*                                                       *)
(*****)

$INCLUDE 'IKGLB.PAS'

PROCEDURE CALC_UT_AND_P(I: INTEGER;
                        VAR UT: MATX33;
                        VAR P: ARRAY3);
{ CALCULATES AND BUILDS A 3X3 UT MATRIX AND A 3X1 P MATRIX }
{ FROM THE LINK PARAMETERS }

CONST
  PI = 3.14159;

VAR
  COS_THETA, SIN_THETA, COS_ALPHA, SIN_ALPHA: real;

```



```

BEGIN( CALC_UT_AND_P )
  WITH KINMC_VARS[I] DO
    BEGIN( 2 )
      COS_THETA := COS(ANGLE * PI / 180.0);
      SIN_THETA := SIN(ANGLE * PI / 180.0);
      COS_ALPHA := COS(TWIST * PI / 180.0);
      SIN_ALPHA := SIN(TWIST * PI / 180.0);
      UT[1, 1] := COS_THETA;
      UT[1, 2] := SIN_THETA;
      UT[1, 3] := 0.0;
      UT[2, 1] := - SIN_THETA * COS_ALPHA;
      UT[2, 2] := COS_THETA * COS_ALPHA;
      UT[2, 3] := SIN_ALPHA;
      UT[3, 1] := SIN_THETA * SIN_ALPHA;
      UT[3, 2] := - COS_THETA * SIN_ALPHA;
      UT[3, 3] := COS_ALPHA;
      P[1] := LENGTH;
      P[2] := OFFSET * SIN_ALPHA;
      P[3] := OFFSET * COS_ALPHA;
    END;( 2 )
  END;( CALC_UT_AND_P )

PROCEDURE MULT3X3(A, B: MATX33; VAR C: MATX33);

  ( MULTIPLIES TWO 3X3 MATRICES TO PRODUCE A 3X3 MATRIX )
  (           A X B = C           )

VAR
  I, J, K: INTEGER;
  D: MATX33;

BEGIN( MULT3X3 )
  FOR I := 1 TO 3 DO
    BEGIN( 5 )
      FOR J := 1 TO 3 DO
        BEGIN( 4 )
          D[I, J] := 0.0;
          FOR K := 1 TO 3 DO
            D[I, J] := A[I, K] * B[K, J] + D[I, J];
          END;( 4 )
        END;( 5 )
      C := D;
    END;( MULT3X3 )

```

```
PROCEDURE CALC_RN(A, P: ARRAY3; UX: MATX33; VAR RN: ARRAY3);
```

```
VAR
```

```
  Q: ARRAY3;  
  I, K: INTEGER;
```

```
BEGIN( CALC_RN )
```

```
  FOR I := 1 TO 3 DO
```

```
    BEGIN( 3 )
```

```
      Q[I] := 0.0;
```

```
      FOR K := 1 TO 3 DO
```

```
        BEGIN( 9 )
```

```
          Q[I] := UX[I, K] * P[K] + Q[I];
```

```
        END; ( 9 )
```

```
      RN[I] := A[I] - Q[I];
```

```
    END; ( 3 )
```

```
END; ( CALC_RN )
```

```
[GLOBAL]PROCEDURE CALJAC(UN: MATX33; I: INTEGER; RN: ARRAY3;  
  VAR JACOB_MAT: MATX610);
```

```
  { BUILDS JACOBIAN MATRIX }
```

```
VAR
```

```
  J : INTEGER;
```

```
BEGIN( CALJAC )
```

```
  WITH KINMC_VARS[I] DO
```

```
    BEGIN( 4 )
```

```
      IF JOINT_TYPE = ROTATIONAL
```

```
      THEN
```

```
        BEGIN( 5 )
```

```
          JACOB_MAT[1, I] := UN[1, 3];
```

```
          JACOB_MAT[2, I] := UN[2, 3];
```

```
          JACOB_MAT[3, I] := UN[3, 3];
```

```
          JACOB_MAT[4, I] := - JACOB_MAT[2, I] * RN[3] +  
                                JACOB_MAT[3, I] * RN[2];
```

```
          JACOB_MAT[5, I] := - JACOB_MAT[3, I] * RN[1] +  
                                JACOB_MAT[1, I] * RN[3];
```

```
          JACOB_MAT[6, I] := - JACOB_MAT[1, I] * RN[2] +  
                                JACOB_MAT[2, I] * RN[1];
```

```
        END( 5 )
```

```
      ELSE ( JOINT_TYPE = SLIDING )
```

```
        BEGIN( 6 )
```

```
          JACOB_MAT[1, I] := 0.0;
```

```
          JACOB_MAT[2, I] := 0.0;
```

```
          JACOB_MAT[3, I] := 0.0;
```

```
          JACOB_MAT[4, I] := UN[1, 3];
```

```
          JACOB_MAT[5, I] := UN[2, 3];
```

```
          JACOB_MAT[6, I] := UN[3, 3];
```

```
        END( 6 )
```

```
      END; ( 4 )
```

```
END; ( CALJAC )
```

```
[GLOBAL]PROCEDURE JACOBN;
```

```
VAR
```

```
  I, J, M, S: INTEGER;
```

```
  RN, P: ARRAY3;
```

```
  UN, UX, UT: MATX33;
```

```
BEGIN( JACOBN )
```

```
  FOR I := 1 TO 3 DO
```

```
    BEGIN( 8 )
```

```
      RN[I] := - E[I, 4];
```

```
      FOR S := 1 TO 3 DO
```

```
        UN[I, S] := E[S, I];
```

```
      END;( 8 )
```

```
  FOR I := N DOWNT0 1 DO
```

```
    BEGIN( 1 )
```

```
      CALC_UT_AND_P(I, UT, P);
```

```
      FOR M := 1 TO 3 DO
```

```
        FOR S := 1 TO 3 DO
```

```
          UX[M, S] := UN[M, S];
```

```
        MULT3X3(UX, UT, UN);
```

```
        CALC_RN(RN, P, UX, RN);
```

```
        CALJAC(UN, I, RN, JACOB_MAT);
```

```
      END;( 1 )
```

```
  END;( JACOBN )
```

```
END.
```

```

[OVERLAID]MODULE PSEUDO(INPUT,OUTPUT);

{***** FILE PSEUDO.PAS *****)

{*****}
{      PROCEDURE PSEUDO      }
{*****}

{*****}
{      }
{ PROGRAMMERS:  Yusheng Tsai, Eric Ribble, Ed Schiebel, }
{              and Kathy Lilly                          }
{      }
{ DATE          :  MARCH 31, 1986                        }
{      }
{ CALLING      }
{ FORMAT:      PSEUDO(Xdot,                             }
{              NumberOfRows, NumberOfColumns,           }
{              Singularity,                             }
{              Result)                                   }
{      }
{ VARIABLES:    Xdot      - INCOMING 6x1 VELOCITY VECTOR }
{              NumberOfRows - NO OF ROWS IN THE JACOBIAN }
{              NumberOfColumns - NO OF COLUMNS IN THE JACOBIAN }
{              Singularity  - SINGULARITY FLAG           }
{              Result       - OUTGOING JOINT RATES       }
{      }
{ TO COMPILE: $ PAS PSEUDO                               }
{      }
{ GLOBAL VARIABLE                                       }
{      REFERENCED: JACOB_MAT                           }
{      }
{*****}
$INCLUDE 'IKGLB.PAS'
Procedure GaussianElimination
  (MS: integer;
   var AJ: MATX55;
   var bG: ARRAY5;
   var Result: ARRAY5;
   var Singularity: boolean);
CONST
  Epsilon1 = 1.0E-25;
VAR
  I,J:      integer;
  RowCounter: integer; { row counter }
  IX:       array [1..6] of integer;
  Recip:    array [1..6] of real;
  Ratio:    array [1..6] of real;
  MSP1:     integer;
  Xdot:     array [1..6] of real;
  II,JJ:    integer;
  AG:       ARRAY [1..5,1..6] OF real;

```

```

Procedure PivotRowSearch;

var
  I:integer;{ current row number }
  Temporary: integer;
  LargestElement: real;
  CompareElement: real;
  LR: integer;{ largest row number }

begin

  LR := RowCounter;
  LargestElement := 0.0;

  { search }
  For I := RowCounter to MS do
    begin
      CompareElement := abs(AG[IX[I], RowCounter]);
      If (LargestElement < CompareElement) then
        begin
          LR := I;
          LargestElement := CompareElement;
        end;
      end;

  { Swap }
  If (LR <> RowCounter) then
    begin
      Temporary := IX [LR];
      IX [LR] := IX [RowCounter];
      IX [RowCounter] := Temporary;
    end;

  { Check For Singularity }
  If (abs (AG[IX[RowCounter], RowCounter]) < Epsilon1)
    then Singularity := true
    else Singularity := false;

end; { procedure PivotRowSearch }

```

Procedure Reduce;

```
var
I,J: integer;
Temporary: real;

begin

  ( Find Reciprocal of Pivot Row Element )
  Recip[RowCounter]:=1.0/AG[IX[RowCounter],RowCounter];

  ( Find all ratios )
  For I := (RowCounter + 1) to MS do
    Ratio [I] := AG[IX[I],RowCounter] * Recip [RowCounter];

  ( Reduce one column at a time )
  For J := (RowCounter + 1) to MSP1 do
    Begin
      Temporary := AG[IX[RowCounter],J];
      For I := (RowCounter + 1) to MS do
        AG[IX[I],J] := AG[IX[I],J] - Ratio [I] * Temporary;
      end;
    end;
end; ( procedure Reduce )
```

Procedure BackSubstitute;

```
var I,J: integer;

begin

  For J := (MS - 1) Downto 1 do
    begin
      For I := 1 to J do
        Xdot [I] := Xdot[I]-AG[IX[I],J+1]*Result[J+1];
      Result [J] := Xdot [J] * Recip [J];
    end;
  end; ( procedure BackSubstitute )
```

```

Begin { procedure GaussianElimination }
{ Initialize matrix size plus one }
MSP1 := MS + 1;
FOR I := 1 TO 5 DO
  FOR J := 1 TO 5 DO
    AG[I,J] := AJ[I,J];
  { Copy b into last column of A }
  For I := 1 to MS do AG[I,MSP1] := bG [I];
  { Initialize Index Array IX : }
  For I := 1 to MS do IX[I] := I;
  { Initialize Row Counter }
  RowCounter := 1;
  Repeat
    PivotRowSearch;
    If Not Singularity then Reduce;
    RowCounter := RowCounter + 1;
  Until ((RowCounter = MS) or Singularity);
  If Not Singularity then
    If (abs (AG[IX[MS],MS]) < Epsilon1)
    then Singularity := True
  else
    begin
      For I := 1 to MS do Xdot [I] := AG[IX[I],MSP1];
      Recip [MS] := 1.0 / AG[IX[MS],MS];
      Result [MS] := Xdot [MS] * Recip [MS];
      BackSubstitute;
    end;
end; { procedure GaussianElimination }

Procedure JtransposeTimesJ
  (var J: MATX610;
   NumberOfRows,NumberOfColumns: integer;
   var JTJ: MATX55);

var I,K,L: integer;
    temp: real;
begin
  For I := 1 to NumberOfColumns do
    For K := 1 to I do
      begin
        temp := 0.0;
        For L := 1 to NumberOfRows do
          temp := temp + J [L,I] * J [L,K];
        JTJ [I,K] := temp;
      end;
  For I := 1 to NumberOfColumns do
    For K := (I+1) to NumberOfColumns do
      JTJ [I,K] := JTJ [K,I];
  end; { Procedure JtransposeTimesJ }

```

```

Procedure JtransposeTimesVector
  (var J: MATX610;
   var B: ARRAY6;
   NumberOfRows, NumberOfColumns: integer;
   var JTB: ARRAY5);

var I,K: integer;
    temp: real;

begin

For I := 1 to NumberOfColumns do
  begin
temp := 0.0;
For K := 1 to NumberofRows do
  temp := temp + J[K,I] * B[K];
JTB [I] := temp;
  end;

end; ( Procedure JtransposeTimesVector )

[GLOBAL]Procedure PSEUDO(var Xdot: ARRAY6;
                          NumberOfRows,NumberOfColumns: integer;
                          var Singularity: boolean;
                          var Result: ARRAY5);

var I,K: integer;
    JTJ: MATX55;
    N: integer;
    B: ARRAY5;
    J: MATX610;

begin

  J:=JACOB_MAT;

  JtransposeTimesJ (J,NumberOfRows,NumberOfColumns,JTJ);

  JtransposeTimesVector (J,Xdot,NumberOfRows,NumberOfColumns,B);

  GaussianElimination (NumberOfColumns,JTJ,B,Result,Singularity);

end; ( Procedure PseudoInverseOverspecifiedNoSecondaryGoals )

END.

```



```

[overlaid]MODULE PREDICTION(INPUT,OUTPUT);

(***** FILE PREDICTION.PAS *****)

(*****)
{  PROCEDURE PREDICTION  }
(*****)

(*****)
{ VERSION:      1.0      }
{
{ PROGRAMMER:   Yusheng Tsai,
{ DATE:        March 31, 1986
{
{ FUNCTION:     CALCULATE THE PREDICTED JONIT VARIABLES
{
{ USER GUIDE:  $ PAS PREDICTION
{ PROCEDURES CALLED: NONE
{ GLOBAL VARIABLES
{   REFERENCED:      -None-
{   MODIFIED:        KINMC_VARS
{
(*****)

%INCLUDE 'IKGLB.PAS'

[GLOBAL]PROCEDURE PREDICTION(PTIME:real; VAR PQP:ARRAY10);

{ A = [ 1.547652  -1.867503  2.017204  -0.697353 ] TRANSPOSE }
{ B = [ 2.002247  -2.03169   1.818609  -0.74320   ] TRANSPOSE }
{ ARE THE GLOBAL CONSTANT ARRAYS                               }
{ LXN AND DLXN ARE TWO N BY 4 GLOBAL MATRIXES                  }
{
{  $X = LXN * A + DELTA\_TIME * DLXN * B$ 
{   n+4
{
VAR
  I,J: INTEGER;
BEGIN { 1 }
  FOR I := 1 TO N DO
    BEGIN
      Xn4[I] := 0.0;
      FOR J := 1 TO 4 DO
        Xn4[I] := Xn4[I] + DLXN[I,J] * B[J];
      Xn4[I] := DELTA_TIME * Xn4[I];
      FOR J := 1 TO 4 DO
        Xn4[I] := Xn4[I] + LXN[I,J] * A[J];
      WITH KINMC_VARS[I] DO
        ANGLE := Xn4[I];
        PQP[I] := Xn4[I];
      END;
    END; { 1 }
END. { MODULE }

```

```

[overlaid]MODULE CORRECTION(INPUT,OUTPUT);
(***** FILE CORRECTION.PAS *****)

(*****)
(  PROCEDURE CORRECTION  )
(*****)

(*****)
{ VERSION:      1.0 }
{ }
{ PROGRAMMER:   Yusheng Tsai, }
{ DATE:        March 31, 1986 }
{ }
{ FUNCTION:     CALCULATE THE CORRECTED JONIT VARIABLES }
{ }
{ USER GUIDE:   $ PAS CORRECTION }
{ PROCEDURES CALLED: NONE }
{ GLOBAL VARIABLES }
{ REFERENCED:   -None- }
{ MODIFIED:     NONE }
(*****)

%INCLUDE 'IKGLB.PAS'

VAR
  I,J: INTEGER;

[GLOBAL]PROCEDURE CORRECTION(CTIME:real; VAR CQC:ARRAY10);
(-----)
{ C = [ 0.375      0.791667  -0.208333  0.041667 ] TRANSPOSE }
{ IS A GLOBAL CONSTANT ARRAY }
{ LXN AND DLXN ARE TWO N BY 4 GLOBAL MATRICES }
{ }

$$\bar{X}_{n+4} = \bar{LXN}[ ,1] + \Delta\_TIME * \bar{DLXN} * C$$

{ }
{ }
{ }
(-----)
BEGIN { 1 }
  FOR I := 1 TO N DO
    BEGIN
      Xn4[I] := 0.0;
      FOR J := 1 TO 3 DO
        Xn4[I] := Xn4[I] + DLXN[I,J] * C[J + 1];
      Xn4[I] := Xn4[I] + DXn4[I] * C[1];
      Xn4[I] := DELTA_TIME * Xn4[I];
      Xn4[I] := LXN[I,1] + Xn4[I];
      WITH KINMC_VARS[I] DO
        ANGLE := Xn4[I];
        CQC[I] := Xn4[I];
      END;
    END; { 1 }
END. { MODULE }

```

```

[overlaid]MODULE ERROR(INPUT,OUTPUT);

(***** FILE ERROR.PAS *****)

(*****)
{   PROCEDURE ERROR   }
(*****)

(*****)
{
{ VERSION:      1.0
{
{ PROGRAMMER:   Yusheng Tsai,
{ DATE:        March 31, 1986
{
{ FUNCTION:     Compute the error between actual and
{               desired positions of end effector.
{
{ USER GUIDE:  >pas ERROR
{
{ PROCEDURES CALLED: NONE
{
{ GLOBAL VARIABLES
{   REFERENCED:      -None-
{
{   MODIFIED:        NONE
{
(*****)

$INCLUDE 'IKGLB.PAS'

[GLOBAL]PROCEDURE ERROR(EX_D,EX:MATX44; VAR DELTA_ERR:real);

VAR MI : INTEGER ;
    ESQR: real;
    DI : real;
    I,J : INTEGER;

BEGIN { 1 }
DELTA_ERR := 0.0;
FOR I := 1 TO 3 DO
  FOR J := 1 TO 3 DO
    BEGIN
      ESQR := DI * DI;
      DELTA_ERR := DELTA_ERR + ESQR;
    END;
  FOR I := 1 TO 3 DO
    BEGIN
      ESQR:= ( EX_D[I,4] - EX[I,4]) * ( EX_D[I,4] - EX[I,4]);
      DELTA_ERR := DELTA_ERR + ESQR;
    END;
  END; { 1 }
END. { MODULE }

```

```

[overlaid]MODULE EVALUATION(INPUT,OUTPUT);

{***** FILE EVALUATION.PAS *****)

{*****}
{  PROCEDURE EVALUATION  }
{*****}

{*****}
{
{  VERSION:      1.0
{
{  PROGRAMMER:   Yusheng Tsai,
{  DATE:        March 31, 1986
{
{  FUNCTION:     Evaluate new DXn4
{
{  USER GUIDE:  $ PAS EVALUATION
{
{  PROCEDURES CALLED: JACOBN,PSEUDO
{
{  GLOBAL VARIABLES
{    REFERENCED:    JACOB_MAT,XDOT
{
{    MODIFIED:      DXn4
{
{*****}

$INCLUDE 'IKGLB.PAS'

[EXTERNAL]PROCEDURE JACOBN; EXTERN;
[EXTERNAL]PROCEDURE PSEUDO( VAR VEL6: ARRAY6;
                           NO_OF_ROWS, NO_OF_COLUMNS: INTEGER;
                           VAR SINGULARITY: BOOLEAN;
                           VAR PDXn4: ARRAY10); EXTERN;

[GLOBAL]PROCEDURE EVALUATION( VAR VEL6: ARRAY6);
CONST
  PI = 3.14159;
VAR
  VEL_TEST      : ARRAY6;
  TP1           : real;
  IE,JE         : INTEGER;
  SINGULARITY    : BOOLEAN;

BEGIN { 1 }
  { VEL      = J      * DXN4      }
  {    6x1    6x5      5x1    }
  { THE COMPUTATION OF VELOCITY OF HAND WAS DONE IN THE MAIN PROGR
  JACOBN;
  PSEUDO(VEL6, 6,5, SINGULARITY, DXn4);
END; { 1 }
END. { MODULE }

```

```

[overlaid]MODULE INTERPOLATION(INPUT,OUTPUT);

(***** FILE INTERPOLATION.PAS *****)

(*****)
{   PROCEDURE INTERPOLATION   }
(*****)

(*****)
{
{ VERSION:      1.0
{
{ PROGRAMMER:   Yusheng Tsai,
{ DATE:        March 31, 1986
{
{ FUNCTION:     CALCULATE NEW LXN AND DLXN FOR 0.5 DELTA_T
{
{ USER GUIDE:   $ PAS INTERPOLATION
{
{ PROCEDURES CALLED: NONE
{
{ GLOBAL VARIABLES
{   REFERENCED:      LXN,DLXN
{   MODIFIED:        LXN,DLXN
{
{ *****}
$INCLUDE 'IKGLB.PAS'
[GLOBAL]PROCEDURE INTERPOLATION;
{ USING THE BESSEL'S FORMULA }
VAR
  II,JI: INTEGER;
  TEMP1,TEMP2:real;
BEGIN { 1 }
  FOR II := 1 TO N DO
    BEGIN {II}
      { LXN[II,1] := LXN[II,1];}
      TEMP1 := (LXN[II,1]-LXN[II,2]-LXN[II,3]+LXN[II,4]);
      TEMP2 := 0.5*(LXN[II,2]-LXN[II,3]);
      LXN[II,4] := LXN[II,2] - TEMP2 ;
      TEMP2 := 0.5*(LXN[II,1]-LXN[II,2]);
      LXN[II,3] := LXN[II,2];
      LXN[II,2] := LXN[II,1] - TEMP2 ;
      { DLXN[II,1] := DLXN[II,1];}
      TEMP1 := (DLXN[II,1]-DLXN[II,2]-DLXN[II,3]+DLXN[II,4]);
      TEMP2 := 0.5*(DLXN[II,2]-DLXN[II,3]);
      DLXN[II,4] := DLXN[II,2] - TEMP2 ;
      TEMP2 := 0.5*(DLXN[II,1]-DLXN[II,2]);
      DLXN[II,3] := DLXN[II,2];
      DLXN[II,2] := DLXN[II,1] - TEMP2;
      END; {II}
    END; { 1 }
  END. { MODULE }

```

```

[overlaid]MODULE ADJUST(INPUT,OUTPUT);
{***** FILE ADJUST.PAS *****)

{*****}
{  PROCEDURE ADJUST  }
{*****}

{*****}
{
{  VERSION:      1.0
{
{  PROGRAMMER:   Yusheng Tsai,
{  DATE:         March 31, 1986
{
{  FUNCTION:     UPDATE LXN, AND DLXN
{
{  USER GUIDE:   $ PAS ADJUST
{
{  PROCEDURES CALLED: NONE
{
{  GLOBAL VARIABLES
{    REFERENCED:    LXN,DLXN,FGA
{
{    MODIFIED:      LXN,DLXN
{
{
{*****}

$INCLUDE 'IKGLB.PAS'

VAR
  IA,JA : INTEGER;

```

```

[GLOBAL]PROCEDURE ADJUST(FGA:BOOLEAN);

BEGIN { 1 }
  IF ( FGA = FALSE ) THEN
    FOR IA := 1 TO N DO
      FOR JA := 6 DOWNT0 1 DO
        BEGIN {JA}
          LXN[IA,JA + 1] := LXN[IA,JA];
          DLXN[IA,JA + 1] := DLXN[IA,JA];
        END {JA}
      ELSE
        FOR IA := 1 TO N DO
          BEGIN {IA}
            {LXN[IA,2] := LXN[IA,2];}
            LXN[IA,3] := LXN[IA,4];
            LXN[IA,4] := LXN[IA,6];
            DLXN[IA,3] := DLXN[IA,4];
            DLXN[IA,4] := DLXN[IA,6];
          END; {IA}
          FOR IA := 1 TO N DO
            BEGIN {IA}
              LXN[IA,1] := Xn4[IA];
              DLXN[IA,1] := DXn4[IA];
            END; {IA}
          END; { 1 }
        END. { MODULE }

```

```

[overlaid]MODULE POSBK(INPUT,OUTPUT);
{***** FILE POSBK.PAS *****)

{*****}
{  PROCEDURE POSBK  }
{*****}

{*****}
{ VERSION:      1.0                                }
{              }
{ PROGRAMMER:   Yusheng Tsai,                      }
{ DATE:        March 31, 1986                      }
{              }
{ FUNCTION:     Xc_dot = Xd_dot + K Function(Xd,X)  }
{              }
{ USER GUIDE:  $ PAS POSBK                        }
{              }
{ PROCEDURES CALLED: None                          }
{              }
{ GLOBAL VARIABLES                                     }
{   REFERENCED:      Xd, Xd-dot, X                  }
{   MODIFIED:        VEL6                           }
{*****}

%INCLUDE 'IKGLB.PAS'

[GLOBAL]PROCEDURE POSBK( VAR VEL6: ARRAY6);
VAR
  VEL_TEST: ARRAY6;
  TP1: ARRAY3;
  KP : ARRAY6;
  IP,JP: INTEGER;
BEGIN { 1 }
  { SELECT GAINS OF POSITION FEEDBACK }
  FOR IP := 1 TO 6 DO
    BEGIN {IP}
      KP[IP] := 50;
    END; {IP}
  VEL_TEST[1] := 0.5*(X[1,3]*X_D[1,2]+X[2,3]*X_D[2,2]+X[3,3]*X_D[
    -(X[1,2]*X_D[1,3]+X[2,2]*X_D[2,3]+X[3,2]*X_D[3,3])
  VEL_TEST[2] := 0.5*(X[1,1]*X_D[1,3]+X[2,1]*X_D[2,3]+X[3,1]*X_D[
    -(X[1,3]*X_D[1,1]+X[2,3]*X_D[2,1]+X[3,3]*X_D[3,1])
  VEL_TEST[3] := 0.5*(X[1,2]*X_D[1,1]+X[2,2]*X_D[2,1]+X[3,2]*X_D[
    -(X[1,1]*X_D[1,2]+X[2,1]*X_D[2,2]+X[3,1]*X_D[3,2])
  TP1[1] := X_D[1,4] - X[1,4];
  TP1[2] := X_D[2,4] - X[2,4];
  TP1[3] := X_D[3,4] - X[3,4];
  VEL_TEST[4] := X[1,1]*TP1[1] + X[2,1]*TP1[2] + X[3,1]*TP1[3];
  VEL_TEST[5] := X[1,2]*TP1[1] + X[2,2]*TP1[2] + X[3,2]*TP1[3];
  VEL_TEST[6] := X[1,3]*TP1[1] + X[2,3]*TP1[2] + X[3,3]*TP1[3];
END; { 1 }
END. { MODULE }

```



```

[overlaid]MODULE EXTRAPOLATION(INPUT,OUTPUT);
{***** FILE EXTRAPOLATION.PAS *****}

{*****}
{  PROCEDURE EXTRAPOLATION  }
{*****}

{*****}
{
{  VERSION:      1.0
{
{  PROGRAMMER:   Yusheng Tsai
{  DATE:        March 31, 1986
{
{  FUNCTION:     CALCULATE NEW JOINT POSITION THROUGH
{                AITKEN'S EXTRAPOLATION FORMULAR.
{
{  USER GUIDE:   $ PAS EXTRAPOLATION
{
{  PROCEDURES CALLED: NONE
{
{  GLOBAL VARIABLES
{    REFERENCED:      LXN
{
{    MODIFIED:        NONE
{
{
{*****}

%INCLUDE 'IKGLB.PAS'

VAR
  I,J: INTEGER;
  TEMP1,TEMP2:real;

[GLOBAL]PROCEDURE EXTRAPOLATION (VAR PQP:ARRAY10);
{ USING THE AITKEN'S FORMULA }
BEGIN { 1 }
  FOR I := 1 TO N DO
    BEGIN
      Xn4[I] := LXN[I,1]-( SQR(LXN[I,1]-LXN[I,2])/
        (LXN[I,1]- 2*LXN[I,2] +LXN[I,3]) );
      DXn4[i] := (Xn4[i] - LXN[i,1]) / DELTA_TIME;
      WITH KINMC_VARS[I] DO
        ANGLE := Xn4[I];
        PQP[I] :=Xn4[I];
      END;
    END; { 1 }
END. ( MODULE )

```

```

[overlaid]MODULE INITIQ1(INPUT,OUTPUT,PARA);

(***** FILE INITIQ1.PAS *****)

(*****)
{  PROCEDURE INITIQ1  }
(*****)

(*****)
{
{  VERSION:      1.0
{
{  PROGRAMMER:   Yusheng Tsai,
{  DATE:        MARCH 31, 1986
{
{  FUNCTION:     Initialize the MMitsubishi robot parameters
{
{  USER GUIDE:   >pas INITIQ1
{
{  PROCEDURES CALLED: INIT80
{
{  GLOBAL VARIABLES
{    REFERENCED:      -None-
{
{    MODIFIED:       KINMC_VARS, 2, E, N
{
{
{  (*****)

$INCLUDE 'IKGLB.PAS'

VAR
  II: INTEGER;
  VARCH, COMMAND: CHAR;
  PARA : TEXT ;

[EXTERNAL]PROCEDURE DIRKIN(NN:INTEGER;var XX:MATX44);EXTERN;

PROCEDURE INIT80 (VAR A: MATX44);

VAR
  I, J: INTEGER; ( SUBSCRIPTS )

BEGIN
  FOR I := 1 TO 4 DO
    FOR J := 1 TO 4 DO
      IF I = J THEN
        A[I, J] := 1
      ELSE
        A[I, J] := 0
END; { INIT80 }

```

```

[GLOBAL]PROCEDURE INITIQ1;
VAR
  JUNK: INTEGER;
  MMI:INTEGER ;
  ACE:real;
BEGIN { 1 }
  N :=5 ;
  {0. Initialize LXN and DLXN matrix by using Lagrange integration }
  {USE EULER METHOD }
  DLXN[1,3]:= 1.35135; DLXN[1,4] := 1.35135;
  DLXN[2,3]:= - 0.01177; DLXN[2,4] := - 0.00392;
  DLXN[3,3]:= 0.02890; DLXN[3,4] := 0.00963;
  DLXN[4,3]:= - 0.01712; DLXN[4,4] := - 0.00571;
  DLXN[5,3]:= - 8.64866; DLXN[5,4] := - 8.64866;
  LXN[1,4] := 0.0;
  LXN[2,4] := - 4.74582;
  LXN[3,4] := 24.31906;
  LXN[4,4] := 160.42691;
  LXN[5,4] := 0.0;
  WRITELN(OUTPUT,'DELTA_TIME= ',DELTA_TIME);
  { STARTING POINT IS SET AT TIME = 0.0 }
  FOR MMI := 1 TO N DO
    BEGIN
      ACE := (DLXN[MMI,3]-DLXN[MMI,4])/ 0.01;
      DLXN[MMI,1] := DLXN[MMI,4];
      DLXN[MMI,2] := DLXN[MMI,1] - ACE * DELTA_TIME;
      DLXN[MMI,3] := DLXN[MMI,2] - ACE * DELTA_TIME;
      DLXN[MMI,4] := DLXN[MMI,3] - ACE * DELTA_TIME;
      LXN[MMI,1] := LXN[MMI,4];
      LXN[MMI,2] := LXN[MMI,1] - DLXN[MMI,4] * DELTA_TIME;
      LXN[MMI,3] := LXN[MMI,2] - DLXN[MMI,3] * DELTA_TIME;
      LXN[MMI,4] := LXN[MMI,3] - DLXN[MMI,2] * DELTA_TIME;
    END;

  {1. Initialize the A, B, and C constant arrays }
  A[1] := 1.547652; A[2] := -1.867503;
  A[3] := 2.017204; A[4] := -0.697353;
  B[1] := 2.002247; B[2] := -2.03169 ;
  B[3] := 1.818609; B[4] := -0.74320 ;
  C[1] := 0.37500000; C[2] := 0.7916666667 ;
  C[3] := - 0.2083333333; C[4] := 0.041666667 ;

```

```

(2. Initialize Mitsubishi robot parameters )
INIT80(Z);
INIT80(E);
FOR II := 1 TO 10 DO
  WITH KINMC_VARS[II] DO
    BEGIN ( 11 )
      JOINT_TYPE := ROTATIONAL;
      ANGLE := 0.0;
      TWIST := 0.0;
      LENGTH := 0.0;
      OFFSET := 0.0;
    END; ( 11 )
  OPEN ( PARA,
    FILE_NAME := 'MITSU3.PAR',

    HISTORY := READONLY );

    RESET (PARA) ;
  REPEAT
    BEGIN (2)
      READLN(PARA,MMI);
      WITH KINMC_VARS[MMI] DO
        BEGIN ( 3 )
          VARCH := ' ';
          WHILE NOT ((VARCH = 'A') OR (VARCH = 'O')) DO
            BEGIN ( 4 )
              READLN(PARA,VARCH);
              CASE VARCH OF
                'A':
                  JOINT_TYPE := ROTATIONAL;
                'O':
                  JOINT_TYPE := SLIDING;
              END; ( CASE )
            END; ( 4 )
          READ(PARA,ANGLE);
          READ(PARA,TWIST);
          READ(PARA,LENGTH);
          READLN(PARA,OFFSET);
        END ; ( 3 )

        END ; ( 2 )

      UNTIL ( MMI = 9 ) ;
      CLOSE ( PARA ) ;
      E[3,4]:=196.1;
      Z[3,4]:=250 ;
      N := 5 ;

```

```

( WRITE OUT THE LINK PARAMETERS AT THE STARTING POINT )
BEGIN { 10 }
  WRITELN(OUTPUT,'  LINK    ANGLE    TWIST    LENGTH(A)    OFFSET(
  FOR II :=1 TO N DO
    WITH KINMC_VARS{II} DO
WRITELN(OUTPUT,'    ',II:4,'    ',ANGLE:5:1,'    ',TWIST:5:1,'    '
          LENGTH:6:2,'    ',OFFSET:6:2);
WRITELN(OUTPUT); WRITELN(OUTPUT);
( WRITE OUT THE X MATRIX AT THE STARTING POINT )
  DIRKIN(N, X);
  WRITELN (OUTPUT,'N= ',N );
  WRITELN(OUTPUT,'X MATRIX:');
  FOR II := 1 TO 3 DO
    WRITELN(OUTPUT,X[II,1]:8:4,X[II,2]:8:4,X[II,3]:8:4,X[II,4]:8
    WRITELN(OUTPUT);
  END; { 10 }

END; { 1 }
END. { MODULE }

```

A.2.2 Programs for Tasks

A.2.2 contains programs for three tasks. TASK1.PAS lists the task designed for the RM-501 to draw a circle on the ground. TASK2.PAS shows the designed trajectory for the RM-501 to extend its arm to the maximum extension. TASK31.PAS is the program to rotate the S-400 manipulator around the x-axis of its end effector such that the direction of the end effector, z-axis, is changed as desired. TASK32.PAS is the program for moving the S-400 on a straight line.

```

[OVERLAID]MODULE TASK1( INPUT, OUTPUT );
(***** FILE: TASK1.PAS *****)

(*****)
(*      PROGRAM: TASK1.PAS      *)
(*****)

(*****)
{ *
{ * PROGRAMMER: Yusheng Tsai
{ * DATE:      March 31, 1986
{ *
{ * FUNCTION:   Generate the task desired position and rotation
{ *             X_D.   The task was designed to rotate the
{ *             Motion_Angle from -180 to +180 degrees.
{ *
{ * USER GUIDE: THE CALLING FORMAT IS:
{ *             TASK1(X_D, TIME_TASK);
{ *
{ * PROGRAMMER
{ * GUIDE:      $ PAS TASK1
{ *             *** It is not a main program. ***
{ *
{ * PROCEDURES
{ * CALLED:     NONE
{ *
{ * FUNCTIONS
{ * CALLED:     NONE
{ *
{ * GLOBAL VARIABLES
{ * REFERENCED:      NONE
{ *
{ * GLOBAL VARIABLES
{ * MODIFIED:      NONE
{ *****}

%INCLUDE 'IKGLB.PAS'
[GLOBAL]PROCEDURE TASK1(VAR TX_D: MATX44;
                        TTIME_TASK: real    );
{ Procedure for generating the task desired position and orientatio
{
{             X_D
CONST
  PI = 3.141592653589793;

VAR
  MOTION_ANGLE : real;
  ANGULAR_SPEED : real;
  ANGLE        : real;
  SI,CO        : real;

```

```

BEGIN
  ANGULAR_SPEED := 10.0;  ( SPEED = 10 DEGREE/SECOND )
  ANGLE := ANGULAR_SPEED * TTIME_TASK * PI / 180.0 ; ( IN RAD )
  SI := SIN ( ANGLE );
  CO := COS ( ANGLE );
  TX_D[1,1] := - CO;
  TX_D[1,2] := - SI;
  TX_D[1,3] := 0.0;
  TX_D[2,1] := - SI;
  TX_D[2,2] :=  CO;
  TX_D[2,3] := 0.0;
  TX_D[3,1] := 0.0;
  TX_D[3,2] := 0.0;
  TX_D[3,3] := -1.0;
  TX_D[1,4] := 320.0 + 50.0 * CO; ( IN mm )
  TX_D[2,4] := 50.0 * SI;
  TX_D[3,4] := 18.5;
  TX_D[4,4] := 1.0;
  (TX_D[4,1]:=0.0; TX_D[4,2]:=0.0; TX_D[4,3]:=0.0;)
END;
END.

```



```

[OVERLAID]MODULE task2( INPUT, OUTPUT );
[***** FILE: task2.PAS *****]

[*****]
[*      PROGRAM: task2.PAS      *]
[*****]

[*****]
[*]
[* PROGRAMMER: Yusheng Tsai      *]
[* DATE:      March 31,1986     *]
[*]
[* FUNCTION:      Generate the task desired position and rotation *]
[*      X_D.      The task was designed to stretch out the *]
[*      robot arm to its maximum extension. *]
[*]
[* USER GUIDE:    THE CALLING FORMAT IS: *]
[*      task2(X_D, TIME_TASK); *]
[*]
[* PROGRAMMER *]
[* GUIDE:      $ PAS task2 *]
[*      *** It is not a main program. *** *]
[*]
[* PROCEDURES *]
[* CALLED:      NONE *]
[*]
[* FUNCTIONS *]
[* CALLED:      NONE *]
[*]
[* GLOBAL VARIABLES *]
[* REFERENCED:      None *]
[*]
[* GLOBAL VARIABLES *]
[* MODIFIED:      None *]
[*****]

%INCLUDE 'IKGLB.PAS'
[GLOBAL]PROCEDURE task2(VAR TX D: MATX44;
                        TTIME_TASK: real );
{ Procedure for generating the task desired position and orientatio
{      X_D
CONST
  PI = 3.141592653589793;

VAR
  MOTION_ANGLE : real;
  ANGULAR_SPEED : real;
  ANGLE : real;
  SI,CO : real;

```

```

BEGIN
  TX_D[1,1] := 0.0;
  TX_D[1,2] := 0.0;
  TX_D[1,3] := 1.0;
  TX_D[2,1] := 0.0;
  TX_D[2,2] := 1.0;
  TX_D[2,3] := 0.0;
  TX_D[3,1] := -1.0;
  TX_D[3,2] := 0.0;
  TX_D[3,3] := 0.0;
  TX_D[1,4] := 503.1 + 10.0 * TTIME_TASK;
  TX_D[2,4] := 0.0;
  TX_D[3,4] := 250.0;
  TX_D[4,4] := 1.0;
  (TX_D[4,1]:=0.0; TX_D[4,2]:=0.0; TX_D[4,3]:=0.0;)
END;
END.

```

```

[OVERLAID]MODULE task5( INPUT, OUTPUT );
[***** FILE: task31.PAS *****]

[*****]
[*      PROGRAM: task5.PAS      *]
[*****]

[*****]
[*      *]
[* PROGRAMMER: Yusheng Tsai      *]
[* DATE:      March 31, 1986    *]
[*      *]
[* FUNCTION:   Generate the task desired position and rotation *]
[*      X_D.   The task was designed to draw a line      *]
[*      by GMF robot. This is the first part.            *]
[*      *]
[* USER GUIDE: THE CALLING FORMAT IS:                    *]
[*      task5(X_D, TIME_TASK);                               *]
[*      *]
[* PROGRAMMER      *]
[* GUIDE:          $ PAS TASK31                             *]
[*      *** It is not a main program. ***                  *]
[*      *]
[* PROCEDURES      *]
[* CALLED:         NONE                                     *]
[*      *]
[* FUNCTIONS       *]
[* CALLED:         NONE                                     *]
[*      *]
[* GLOBAL VARIABLES *]
[* REFERENCED:     None                                     *]
[*      *]
[* GLOBAL VARIABLES *]
[* MODIFIED:       None                                     *]
[*****]

$INCLUDE 'IKGLB.PAS'
[GLOBAL]PROCEDURE task5(VAR TX_D: MATX44;
                        TTIME_TASK: real;
                        VAR VEL_HD :ARRAY6);
( Procedure for generating the task desired position and orientatio
{      X_D
CONST
  PI = 3.141592653589793;

VAR
  angle : real;
  i_t : integer;
  SA,CA,SB,CB : REAL;
  TMP_TASK : REAL;
  VEL_HAND_X,VEL_HAND_Y : REAL;
  DT : REAL;

```

```

BEGIN
  IF (TTIME_TASK < 0.5) AND ( TTIME_TASK >= 0.0 ) THEN
    angle := (30.0 * TTIME_TASK * ttime_task) * pi / 180.0;
  IF (TTIME_TASK > 0.5) AND ( TTIME_TASK <= 1.0 ) THEN
    angle := (30.0 * (TTIME_TASK - 0.25)) * pi / 180.0;
  IF (TTIME_TASK > 1.0) AND ( TTIME_TASK <= 1.5 ) THEN
    angle := (30.0 * (TTIME_TASK - 0.25)
      - 30.0*(TTIME_TASK-1.0)*(TTIME_TASK-1.0)) * pi / 180.0;
  IF (TTIME_TASK > 1.5 ) THEN ANGLE := 30.0;
  CA := cos ( angle );
  SA := sin ( angle );
  CB := COS ( 60.0 / 180.0 * PI );
  SB := SIN ( 60.0 / 180.0 * PI );
  TX_D[1,1] := 0.0;
  TX_D[1,2] := - CB * CA + SB * SA;
  TX_D[1,3] := CB * SA + SB * CA;
  TX_D[2,1] := 0.0;
  TX_D[2,2] := -SB * CA - CB * SA;
  TX_D[2,3] := SB * SA - CB * CA;
  TX_D[3,1] := 1.0;
  TX_D[3,2] := 0.0;
  TX_D[3,3] := 0.0;
  TX_D[1,4] := 1192.836; ( IN mm )
  TX_D[2,4] := -948.49;
  TX_D[3,4] := -169;
  TX_D[4,4] := 1.0;
  (TX_D[4,1]:=0.0; TX_D[4,2]:=0.0; TX_D[4,3]:=0.0;)
  (***** HAND VELOCITY *****)
  FOR I_T := 2 TO 6 DO VEL_HD[I_T] := 0.0;
  IF (TTIME_TASK < 0.5) AND ( TTIME_TASK >= 0.0 ) THEN
    VEL_HD[1] := 60.0 * TTIME_TASK;
  IF (TTIME_TASK > 0.5) AND ( TTIME_TASK <= 1.0 ) THEN
    VEL_HD[1] := 30.0;
  IF (TTIME_TASK > 1.0) AND ( TTIME_TASK <= 1.5 ) THEN
    VEL_HD[1] := (30.0 - 60.0*(TTIME_TASK-1.0));
  IF (TTIME_TASK > 1.5 ) THEN VEL_HD[1] := 0.0;
  { X_DOT[4] = VEL_HD [x] - VEL_BASE[Y] }
END;
END.

```

```

[OVERLAID]MODULE task5( INPUT, OUTPUT );
{***** FILE: task32.PAS *****}

{*****}
{*      PROGRAM: task5.PAS      *}
{*****}

{*****}
{*
{* PROGRAMMER: Yusheng Tsai
{* DATE:      March 31, 1986
{*
{* FUNCTION:   Generate the task desired position and rotation
{*             X_D. The task was designed to draw a line
{*             by GMF robot. This is the second part.
{*
{* USER GUIDE: THE CALLING FORMAT IS:
{*             task5(X_D, TIME_TASK);
{*
{* PROGRAMMER
{* GUIDE:      $ PAS TASK32
{*             *** It is not a main program. ***
{*
{* PROCEDURES
{* CALLED:     NONE
{*
{* FUNCTIONS
{* CALLED:     NONE
{*
{* GLOBAL VARIABLES
{* REFERENCED:      None
{*
{* GLOBAL VARIABLES
{* MODIFIED:        None
{*****}

%INCLUDE 'IKGLB.PAS'
[GLOBAL]PROCEDURE task5(VAR TX_D: MATX44;
                        TIME_TASK: real;
                        VAR VEL_HD :ARRAY6);
{ Procedure for generating the task desired position and orientatio
{
{             X_D
CONST
  PI = 3.141592653589793;

VAR
  I_T : INTEGER;
  angle : real;
  SA,CA,SB,CB : REAL;
  TMP_TASK : REAL;
  VEL_HAND_X,VEL_HAND_Y : REAL;
  T61,T62,TACC,VMAX,VI,ACC,VX_MAX,VY_MAX,VZ_MAX : REAL;
  DX,DY,DZ, TMP1 : REAL;
  DT : REAL;

```

```

BEGIN
  {Low speed }
  VMAX := 100.0; TACC := 0.5; T61 := 0.0; T62 := 17.0;
  {Very high speed}
  VMAX := 3000.0; TACC := 0.5; T61 := 0.0; T62 := 15;
  VMAX := 2000.0; TACC := 0.5; T61 := 0.0; T62 := 2;
  {High speed}
  VMAX := 1500.0; TACC := 0.3; T61 := 0.0; T62 := 1.085; T62 := 1.6;
  ACC := VMAX/TACC;
  {***** HAND VELOCITY *****}
  FOR I_T := 1 TO 3 DO VEL_HD[I_T] := 0.0;
  IF (TTIME_TASK < (TACC + T61)) AND ( TTIME_TASK >= T61 ) THEN
    VI := ACC * TTIME_TASK;
  IF (TTIME_TASK >= (T61 + TACC)) AND ( TTIME_TASK <= (T62 - TACC) )
    VI := VMAX;
  IF (TTIME_TASK > (T62 - TACC)) AND ( TTIME_TASK <= T62 ) THEN
    VI := VMAX - ACC * (TTIME_TASK - T62 + TACC);
  IF (TTIME_TASK > T62 ) THEN VI := 0.0;
  TMP1 := 180.0/PI;
  VEL_HD[4] := 0.86855 * VI * TMP1;
  VEL_HD[5] := - 0.4444 * VI * TMP1;
  VEL_HD[6] := 0.2194 * VI * TMP1;
  VX_MAX := 0.86855 * VMAX;
  VY_MAX := - 0.4444 * VMAX;
  VZ_MAX := 0.2194 * VMAX;
  {***** HAND POSITION *****}
  IF (TTIME_TASK < (TACC + T61)) AND ( TTIME_TASK >= T61 ) THEN
    BEGIN
      TMP_TASK := 0.5 * TTIME_TASK * TTIME_TASK / TACC;
      DX := VX_MAX * TMP_TASK;
      DY := VY_MAX * TMP_TASK;
      DZ := VZ_MAX * TMP_TASK;
    END;
  IF (TTIME_TASK > (T61 + TACC)) AND ( TTIME_TASK <= (T62 - TACC) )
    BEGIN
      TMP_TASK := TTIME_TASK - (0.5 * TACC);
      DX := VX_MAX * TMP_TASK;
      DY := VY_MAX * TMP_TASK;
      DZ := VZ_MAX * TMP_TASK;
    END;
  IF (TTIME_TASK > (T62 - TACC)) AND ( TTIME_TASK <= T62 ) THEN
    BEGIN
      TMP_TASK := TTIME_TASK - (0.5 * TACC)
        - (0.5 * (TTIME_TASK - (T62-TACC)));
      DX := VX_MAX * TMP_TASK;
      DY := VY_MAX * TMP_TASK;
      DZ := VZ_MAX * TMP_TASK;
    END;
END;

```

```

IF (TTIME_TASK > T62 ) THEN
  BEGIN
    TMP_TASK := T62 - TACC;
    DX := VX_MAX * TMP_TASK;
    DY := VY_MAX * TMP_TASK;
    DZ := VZ_MAX * TMP_TASK;
    END;
    TX_D[1,1] := 0.0;
    TX_D[1,2] := 0.0;
    TX_D[1,3] := 1.0;
    TX_D[2,1] := 0.0;
    TX_D[2,2] := -1.0;
    TX_D[2,3] := 0.0;
    TX_D[3,1] := 1.0;
    TX_D[3,2] := 0.0;
    TX_D[3,3] := 0.0;
    TX_D[1,4] := 1192.836 + DZ; ( IN mm )
    TX_D[2,4] := -948.49 - DY;
    TX_D[3,4] := -169 + DX;
    TX_D[4,4] := 1.0;
    (TX_D[4,1]:=0.0; TX_D[4,2]:=0.0; TX_D[4,3]:=0.0;)
  END;
END.

```

A.2.3 Programs for Simulations

A.2.3 shows the main programs for the simulations of Inverse Kinematics algorithm. INVKIV.PAS is the program to obtain the analytical solution for Inverse Kinematics of the Mitsubishi robot RM-501, which is used to provide a reference solution for comparison. Finally, LTSTP.PAS shows the complete program for the Inverse Kinematics algorithm with position feedback.


```

[OVERLAID]MODULE INVKIN( INPUT, OUTPUT );

(***** FILE: INVKIN.PAS *****)

(*****)
(*      PROGRAM: INVKIN.PAS      *)
(*****)

(*****)
{*                                     *}
{* PROGRAMMER: Yusheng Tsai          *}
{* DATE:      March 31, 1986        *}
{*                                     *}
{* FUNCTION:      Inverse Kinematics -- compute the joint angles *}
{*               (ANGLE_D) for RM-501 given the position/ *}
{*               orientation of the end effector(X_D)      *}
{*               *}
{* USER GUIDE:    THE CALLING FORMAT IS:                    *}
{*               INVKIN(X_D, OPTION, STATUS, ANGLE_D)      *}
{*               *}
{* VARIABLES :    OPTION = LEFT_UP....arm left, elbow up  *}
{*               RIGHT_UP...arm right, elbow up           *}
{*               LEFT_DOWN..arm left, elbow down          *}
{*               RIGHT_DOWN.arm right, elbow down         *}
{*               STATUS = VALID_SOLUTION                  *}
{*               REACH_EXCEEDED                            *}
{*               LIMITS_EXCEEDED                          *}
{*               *}
{* PROGRAMMER                                           *}
{* GUIDE:      $ PAS INVKIN                            *}
{*               *}
{* PROCEDURES                                           *}
{* CALLED:      MATPRD                                  *}
{*               *}
{* FUNCTIONS                                           *}
{* CALLED:      ACTAN2                                  *}
{*               *}
{* GLOBAL VARIABLES                                     *}
{* REFERENCED:   KINMC_VARS,Z,E                        *}
{*               *}
{* GLOBAL VARIABLES                                     *}
{* MODIFIED:     ANGLE_D                                *}
(*****)

$INCLUDE 'IKGLB.PAS'

```

```

FUNCTION ACTAN2(Y, X: REAL): REAL;

  CONST
    PI = 3.141592653589793;

  VAR
    SIGN: REAL;

  BEGIN
    IF Y >= 0.0 THEN
      SIGN := 1.0
    ELSE
      SIGN := - 1.0;
    IF ABS(X) > 0.00001 THEN { X IS NON-ZERO }
      IF X > 0.0 THEN
        ACTAN2 := ARCTAN(Y / X)
      ELSE
        ACTAN2 := ARCTAN(Y / X) + PI * SIGN
      { END IF X }
    ELSE
      ACTAN2 := PI / 2.0 * SIGN;
    END;

PROCEDURE MATPRD(INMA, INMB: MATX44;
  VAR OUTM: MATX44);

  VAR
    WORKM: MATX44; { MATRIX USED TO HOLD PARTIAL ANSWER }
    { UNTIL READY TO RETURN }
    I, J, K: INTEGER;

  BEGIN
    FOR I := 1 TO 4 DO
      FOR J := 1 TO 4 DO
        WORKM[I, J] := 0.0;
      FOR I := 1 TO 4 DO
        FOR J := 1 TO 4 DO
          FOR K := 1 TO 4 DO
            BEGIN
              WORKM[I, J] := INMA[I, K] * INMB[K, J] + WORKM[I, J];
            END;
          OUTM := WORKM;
        END;
      END;
    END;
  END;

```

```

[GLOBAL]PROCEDURE INVKIN(X_D: MATX44;
    VAR OPTION: OPTION_SET;
    VAR STATUS: STATUS_SET;
    VAR ANGLE_D: ARRAY5);

CONST
    PI = 3.14159;

VAR
    I, J, K: INTEGER;
    TEMP, T5: MATX44;
    W, C1, S1, C3, S3, SEC3, R: REAL;

BEGIN
    STATUS := VALID_SOLUTION;
    (* COMPUTE ELEMENTS OF T5 MATRIX *)
    (* INVERT E *)
    TEMP := E;
    FOR I := 1 TO 3 DO
        TEMP[I, 4] := - TEMP[I, 4];
    (* LET T5 = X x E INVERSE *)
    MATPRD(X_D, TEMP, T5);
    (* INVERT Z *)
    TEMP := Z;
    FOR I := 1 TO 3 DO
        TEMP[I, 4] := - TEMP[I, 4];
    (* T5 = Z INVERSE x X x E INVERSE *)
    MATPRD(TEMP, T5, T5);
    (* COMPUTE JOINT ANGLES *)
    WITH KINMC_VARS[1] DO
        BEGIN
            ANGLE_D[1] := ACTAN2(T5[2, 4], T5[1, 4]);
            IF ((OPTION = LEFT_UP) OR (OPTION = LEFT_DOWN)) THEN
                BEGIN
                    IF (ANGLE_D[1] < 0) THEN
                        ANGLE_D[1] := ANGLE_D[1] + PI
                    END
                ELSE IF (ANGLE_D[1] > 0) THEN
                    ANGLE_D[1] := ANGLE_D[1] - PI;
                IF ((ANGLE_D[1] >= - 2 * PI) AND
                    (ANGLE_D[1] <= - 240.0 * PI / 180.0)) THEN
                    ANGLE_D[1] := 2 * PI + ANGLE_D[1];
                IF ((ANGLE_D[1] >= 240.0 * PI / 180.0) AND (ANGLE_D[1] <= 2 *
                    ANGLE_D[1] := - 2 * PI + ANGLE_D[1];
                C1 := COS(ANGLE_D[1]);
                S1 := SIN(ANGLE_D[1]);
            END; (WITH)

```

```

WITH KINMC_VARS[5] DO
  BEGIN
    ANGLE_D[5] := ACTAN2(((C1 * T5[2, 1]) - (S1 * T5[1, 1])),
                        ((C1 * T5[2, 2]) - (S1 * T5[1, 2])));
  END;

WITH KINMC_VARS[3] DO
  BEGIN
    R := C1*T5[1, 4] + (S1*T5[2, 4]);
    C3 := (SQR(R)+SQR(T5[3,4])-SQR(160.0)-SQR(220.0))/2.0/160.0/2
    IF (1 - SQR(C3) < 0) THEN
      STATUS := REACH_EXCEEDED
    ELSE
      ANGLE_D[3] := ACTAN2(SQRT(1 - SQR(C3)), C3);
      IF ((OPTION = LEFT_UP) OR (OPTION = RIGHT_UP)) THEN
        BEGIN
          IF (ANGLE_D[3] < 0) THEN
            ANGLE_D[3] := - ANGLE_D[3]
          END
        ELSE IF (ANGLE_D[3] > 0) THEN
          ANGLE_D[3] := - ANGLE_D[3];
        IF ((ANGLE_D[3] >= - 2 * PI) AND
            (ANGLE_D[3] <= - 90.0 * PI / 180.0)) THEN
          ANGLE_D[3] := 2 * PI + ANGLE_D[3];
        IF ((ANGLE_D[3] >= 180.0 * PI / 180.0) AND (ANGLE_D[3] <= 2 *
            ANGLE_D[3] := - 2 * PI + ANGLE_D[3];
        C3 := COS(ANGLE_D[3]);
        S3 := SIN(ANGLE_D[3]);
      END;

WITH KINMC_VARS[2] DO
  BEGIN
    W := C1 * T5[1, 4] + S1 * T5[2, 4];
    ANGLE_D[2] := ACTAN2( - (160.0*C3 + 220.0) * T5[3, 4]-160.
                        ((160.0*C3 + 220.0) * W - 160.0*(S3 * T5[
    IF ((ANGLE_D[2] >= - 2 * PI) AND
        (ANGLE_D[2] <= - 330.0 * PI / 180.0)) THEN
      ANGLE_D[2] := 2 * PI + ANGLE_D[2];
    IF ((ANGLE_D[2] >= 260.0 * PI / 180.0) AND (ANGLE_D[2] <= 2
        ANGLE_D[2] := - 2 * PI + ANGLE_D[2];
    END;

WITH KINMC_VARS[4] DO
  BEGIN
    ANGLE_D[4] := ACTAN2(((C1 * T5[1, 3]) + (S1 * T5[2, 3])),
                        T5[3, 3]) - ANGLE_D[2] - ANGLE_D[3];
    IF ((ANGLE_D[4] > 180.0 * PI / 180.0) AND (ANGLE_D[4] <= 2 *
        ANGLE_D[4] := - 2 * PI + ANGLE_D[4];
    IF ((ANGLE_D[4] >= - 2 * PI) AND
        (ANGLE_D[4] < - 180 * PI / 180.0)) THEN
      ANGLE_D[4] := 2 * PI + ANGLE_D[4];
    END;

```

```

      FOR I := 1 TO 5 DO
        WITH KINMC_VARS[I] DO
        BEGIN

          ANGLE_D[I] := ANGLE_D[I] * 180.0 / PI;
        ANGLE := ANGLE_D[I];

        END;

      IF STATUS = VALID_SOLUTION THEN
        IF ((ANGLE_D[1] > 150) OR (ANGLE_D[1] < - 150) OR (ANGLE_D[2]
          (ANGLE_D[2] < - 100) OR (ANGLE_D[3] > 90) OR
          (ANGLE_D[3] < - 0 ) OR (ANGLE_D[4] > 180) OR
          (ANGLE_D[4] < - 0)) THEN
          STATUS := LIMITS_EXCEEDED;
        END;
      END.

```

```

[OVERLAID]program LTSTP( INPUT, OUTPUT );

[***** FILE: LTSTP.PAS *****]

[*****]
[*      PROGRAM: LTSTP.PAS      *]
[*****]

[*****]
[*]
[* PROGRAMMER: Yusheng Tsai      *]
[* DATE:      MARCH 31, 1986    *]
[*]
[* FUNCTION:    Simulates numerical approach for Inverse      *]
[*              Kinematics algorithm with position feedback.  *]
[*]
[* USER GUIDE:  THE CALLING FORMAT IS:                          *]
[*              LTSTP                                           *]
[*]
[* PROGRAMMER                                       *]
[* GUIDE:      $ PAS LTSTP                          *]
[*]
[* PROCEDURES                                       *]
[* CALLED      INITQ1,ERROR,PREDITION,EVALUATION,DIRKIN,JAC   *]
[*              CORRECTION, ADJUST,PSEUDO,INTERPOLATION,POSBK  *]
[*              TASK                                           *]
[* FUNCTIONS                                       *]
[* CALLED:      ACTAN2                                         *]
[*]
[* GLOBAL VARIABLES                                       *]
[* REFERENCED:  ALL                                           *]
[*]
[* GLOBAL VARIABLES                                       *]
[* MODIFIED:    ALL                                           *]
[*****]

TYPE
  FG = ( PREDICT, CORRECT);
  MATX54 = ARRAY [1..5,1..4] OF real;

%INCLUDE 'IKGLB.PAS'

LABEL 9,10,20,30,50,100,200;

[EXTERNAL]PROCEDURE TASK1(VAR X_D: MATX44;
                          TIME_TASK1: real    );
  EXTERN;

[EXTERNAL]PROCEDURE DIRKIN(NN : INTEGER; VAR XX : MATX44); EXTERN;

```

```

[EXTERNAL]PROCEDURE PREDICTION (PTIME : real; VAR PQP : ARRAY10);
    EXTERN;
[EXTERNAL]PROCEDURE CORRECTION (CTIME : real; VAR CQC : ARRAY10);
    EXTERN;
[EXTERNAL]PROCEDURE POSBK(VAR VEL_HAND:ARRAY6); EXTERN;
[EXTERNAL]PROCEDURE EVALUATION(VEL_HAND:ARRAY6); EXTERN;
[EXTERNAL]PROCEDURE ADJUST(FG2T:BOOLEAN); EXTERN;
[EXTERNAL]PROCEDURE INTERPOLATION; EXTERN;
[EXTERNAL]PROCEDURE ERROR( EX_D,EX: MATX44; VAR DELTA_ERR: real);
    EXTERN;
[EXTERNAL]PROCEDURE INITIQL; EXTERN;

```

```

CONST

```

```

    PI = 3.141592653589793;

```

```

VAR

```

```

    MMX :MATX44;
    MAX_STEP : real; { MAXIMUM STEP SIZE }
    MAX_ERR : real; { MAXIMUM ERROR in mm square}
    mxerr : real; { maximum error in mm}
    TTIME : real;
    JAC_NO:integer;
    PRE_NO:integer;
    COR_NO1:integer;
    COR_NO:integer;
    ite_NO:integer;
    MX_TEMP : MATX44;
    FG2T:BOOLEAN;
    I,J : INTEGER;
    TIME_TASK1 : real;
    QP,OC : ARRAY10;{ PREDICTED AND CORRECTED JOINT ANGLED }
    QTASK1 : ARRAY10;{ DESIRED TASK1 JOINT ANGLES }
    MIN_DELTA_TIME : real; { MINIMUM STEP }
    NSTORE : INTEGER;
    DELTA1,DELTA2,DELTA3 : real;
    EPSER1 : real; { MAXIMUM ALLOWED ERROR }
    EPSER2 : real; { MAXIMUM ALLOWED ERROR }
    ETA : INTEGER ; { FOR realing STEPS }
    NMAX : INTEGER ; { FOR CORRECTION LOOP }
    FLAG : FG;
    VEL_HAND: ARRAY6;
    vel_test: array6;
    TEND : real; { TIME FOR ENDING THE PROGRAM }
    NO : INTEGER;

```

```

PROCEDURE INITP;
( Initialize all the parameters used in this simulation )
BEGIN ( INITP )
  ITE_NO :=0; JAC_NO := 0; PRE_NO := 0; COR_NO := 0; COR_NO1:=0;
  FOR I := 1 TO 6 DO
    VEL_HAND[I] := 0.0000;
    VEL_HAND[3] := - 90.000000000;          { DEG/SEC }
    VEL_HAND[5] := 8.730 * 9;                { mm * /SEC }
    VEL_HAND[5] := - 4500.0;                 { mm * rad/deg/SEC }
    TTTIME := 1.0000000000;    { DISPLAY OUTPUT PER SECOND }
    TEND := 72.00000; { ASSUME THE SPEED IS 90 DEG/SEC AND 18 CIRCL
    DELTA_TIME := 1.0000000000000000000E-3; { Delta_t = 0.001 sec
    MAX_STEP := DELTA_TIME;
    MAX_ERR := 0.0;
    MIN_DELTA_TIME := 0.00000100000000000;
    TIME := 0.0;
    EPSER1 :=0.000001000000000;
    EPSER2 :=0.25000000000;
    ETA := 5000;
    NMAX := 3;
    FG2T := FALSE;
    NSTORE := 4;
  END; ( INITP )

PROCEDURE WRITEOUT;
VAR
  I : INTEGER;
BEGIN ( WRITEOUT )
  WRITELN ( OUTPUT, 'TIME= ',TIME:14:8);
  WRITE ( OUTPUT, 'QP= ');
  FOR I := 1 TO N DO
    WRITE ( OUTPUT, QP[I]:12:6,' ');
  WRITELN;
  WRITE ( OUTPUT, 'QC= ');
  FOR I := 1 TO N DO
    WRITE ( OUTPUT, QC[I]:12:6,' ');
  WRITELN;
  {WRITE OUT X, X_D }
  WRITELN (OUTPUT,'***** X ***** ');
  FOR I := 1 TO 4 DO
    BEGIN
      FOR J := 1 TO 4 DO
        WRITE(OUTPUT,X[I,J]:12:6);
        WRITELN(OUTPUT);
      END;
    WRITELN (OUTPUT,'***** X_D ***** ');
    FOR I := 1 TO 4 DO
      BEGIN
        FOR J := 1 TO 4 DO
          WRITE(OUTPUT,X_D[I,J]:12:6);
          WRITELN(OUTPUT);
        END;
      END;
    END; ( WRITEOUT )

```



```

PROCEDURE INIT80(VAR A: MATX44);

  VAR
    I, J: INTEGER; { SUBSCRIPTS }

  BEGIN
    FOR I := 1 TO 4 DO
      FOR J := 1 TO 4 DO
        IF I = J THEN
          A[I, J] := 1
        ELSE
          A[I, J] := 0
        END; { INIT80 }

  PROCEDURE CAL_VEL(TIME:real);
  { COMPUTE THE HAND VELOCITY VECTOR ON TIME }
  BEGIN { CAL_HAND }
  END; { CAL_HAND }

  { MAIN PROGRAM BEGINS }
  BEGIN { MAIN }
    INITP; { Initialize SIMULATION parameters }
    INITQ1; { Initialize the starting angles }
    TIME := 0.0;
  FOR I := 1 TO 6 DO
    WITH KINMC_VARS[I] DO
      ANGLE := LXN[I,1];
      DIRKIN(N,X);
      POSBK(VEL_HAND);
      EVALUATION(VEL_TEST);
    9:
      ITE_NO := ITE_NO + 1;
      DIRKIN(N,X);
      MX_TEMP := X;
    10:
      TIME := TIME + DELTA_TIME;
      IF ( TIME > TEND + 0.0005 ) THEN
        BEGIN
          DELTA_TIME := DELTA_TIME - (TIME - TEND);
          TIME := TEND;
        END;
      TASK1(X_D,TIME); { Find the desired position and orientation }
      ERROR(X_D,MX_TEMP,DELTA1);
      PREDICTION(TIME,QP);
      PRE_NO := PRE_NO + 1;
      DIRKIN(N,X); { Find X for predicted angles QP }
      ERROR(X_D,X,DELTA2);
      IF ( DELTA2 > ( DELTA1 + 5 ) ) THEN
        GOTO 20

```

```

ELSE
BEGIN ( ELSE 10 )
IF ( DELTA2 < EPSER1 ) THEN
BEGIN
IF ( MAX_ERR < DELTA2 ) THEN MAX_ERR := DELTA2;
POSBK(VEL_HAND);
EVALUATION(VEL_HAND);
JAC_NO := JAC_NO + 1;
FLAG := PREDICT;
GOTO 50;
END
ELSE
BEGIN ( ELSE 30 )
COR_NO1 := COR_NO1 + 1;
NO := 1;
CAL_VEL(TIME);
30: POSBK(VEL_HAND);
EVALUATION(VEL_HAND);

JAC_NO := JAC_NO + 1;
CORRECTION(TIME, QC);
COR_NO := COR_NO + 1;
DIRKIN(N,X); { Find X for CORRECTed angles QC }
ERROR(X_D,X,DELTA3);
IF ( DELTA3 > DELTA2 + 5 ) THEN GOTO 20
ELSE
IF ( DELTA3 > EPSER2 ) THEN
BEGIN
NO := NO + 1;
IF ( NO > NMAX ) THEN GOTO 20
ELSE GOTO 30;
END
ELSE
BEGIN
IF ( MAX_ERR < DELTA3 ) THEN MAX_ERR := DELTA3;
FLAG := CORRECT;
GOTO 50;
END;
END; ( ELSE 30 )
END; ( ELSE 10 )
20: IF ( DELTA3 > DELTA2 ) OR ( DELTA2 > DELTA1 ) THEN
BEGIN
WRITELN (OUTPUT, 'DELTA1 = ', DELTA1:12:6);
WRITELN (OUTPUT, 'DELTA2 = ', DELTA2:12:6);
WRITELN (OUTPUT, 'DELTA3 = ', DELTA3:12:6);
END;
BEGIN ( HALF STEP )
TIME := TIME - DELTA_TIME;
DELTA_TIME := 0.5 * DELTA_TIME;

```

```

        IF ( DELTA_TIME < MIN_DELTA_TIME ) THEN
            BEGIN
                GOTO 100;
            END
        ELSE
            BEGIN
                INTERPOLATION;
                nstore := 4;
                GOTO 10;
            END;
        END; { HALF STEP }
50:      BEGIN { 50 }
        IF ( TIME > TTIME - 0.000045 ) THEN
            BEGIN
                TTIME := TTIME + 1.00000000;
                mxerr := sqrt(max_err);
                WRITELN(OUTPUT,TIME, ' ', mxerr);
            END;
        { Update angles }
        BEGIN { angle }
        FOR I := 1 TO N DO
            WITH KINMC_VARS[I] DO
                IF ( FLAG = CORRECT ) THEN
                    ANGLE := QC[I]
                ELSE
                    ANGLE := QP[I];
            END; { ANGLE }
        NSTORE := NSTORE + 1;
        IF ( TIME < TEND ) THEN
            BEGIN { 90 }
            IF ( NSTORE < 7 ) THEN FG2T := FALSE
            ELSE
                IF ( DELTA2 < EPSER1/ETA )
                    OR ( DELTA3 < EPSER1/ETA )
                THEN
                    BEGIN
                        NSTORE := 4;
                        FG2T := TRUE;
                        DELTA_TIME := DELTA_TIME + DELTA_TIME;
                        IF ( MAX_STEP < DELTA_TIME ) THEN
                            MAX_STEP := DELTA_TIME;
                        END
                    ELSE FG2T :=FALSE;
                    { Adjust Xn and dot Xn }
                    ADJUST(FG2T);
                    GOTO 9;
                END
            ELSE GOTO 200;
        END; { 50 }

```

```

100:
    { Singularity process }
    WRITELN ( OUTPUT, ' THE SINGULARITY POINT IS HERE: ');
    WRITEOUT;
200:
    WRITEOUT;
    WRITELN(OUTPUT,'NSTORE= ',NSTORE);
    WRITELN(OUTPUT,'delta_TIME= ',DELTA_TIME:14:8);
    WRITELN(OUTPUT,'TIME = ',TIME:14:8);
    WRITELN (OUTPUT,'DELTA1 = ', DELTA1:12:6);
    WRITELN (OUTPUT,'DELTA2 = ', DELTA2:12:6);
    WRITELN (OUTPUT,'DELTA3 = ', DELTA3:12:6);
    WRITELN (OUTPUT,'FINAL DELTA_TIME = ',DELTA_TIME:14:8);
    WRITELN (OUTPUT,'MAXIMUM STEP SIZE= ',MAX_STEP:14:8);
    WRITELN (OUTPUT,'MAXIMUM ERROR      = ',MAX_ERR:14:8);
    WRITELN (OUTPUT,'ETA                = ',ETA:5);
    WRITELN (OUTPUT,'CONVERGENCE         = ',EPSE2:14:8);
    WRITELN (OUTPUT,'ITERATION_NUMBER = ',ITE_NO:5);
    WRITELN (OUTPUT,'PREDICTION_NUMBER= ',PRE_NO:5);
    WRITELN (OUTPUT,'COR_LOOP_NUMBER   = ',COR_NO1:5);
    WRITELN (OUTPUT,'CORRECTION_NUMBER= ',COR_NO:5);
    WRITELN (OUTPUT,'JACOBN_NUMBER     = ',JAC_NO:5);
END. ( MAIN )

```

A.3 Programs for Simulations of Inverse Kinematics Processor

A.3 contains all programs which simulate the Inverse Kinematics algorithm on the proposed architecture. All programs are written in Pascal but are essentially microprograms. The basic architecture of the proposed Inverse Kinematics Processor is simulated through programs listed in Appendix A.3.1. A.3.2 presents computational modules for the algorithm itself, A.3.3 shows the tasks, and A.3.4 lists the main programs for the simulations.

A.3.1 Programs for Architecture and Function Mapping

A.3.1 includes four programs. AM325.PAS simulates the arithmetic processing unit with its two feedback data paths. All control signals, arithmetic operations, and data transmissions are simulated step by step. SEEDTABLE.PAS is the program to generate the seeds for the reciprocal in software. The accuracy is 32 bits although it can be any number of bits. SINE/COSINE.PAS simulates Taylor Series expansion of the sine/cosine function. The accuracy of both the input and output are designed to be 32 bits. SUB_REC.PAS uses the Newton-Raphson iteration equations and results from SEED_TABLE.PAS to generate the reciprocal. Registers S, R, and F inside the simulation programs are corresponding to registers A, B, and C in figure 5.7, respectively.

```

[OVERLAID]MODULE AM325( INPUT, OUTPUT );
{***** FILE: AM325.PAS *****)

{*****}
{ *      PROGRAM: AM325.PAS      *}
{*****}

{*****}
{ * }
{ * PROGRAMMER: Yusheng Tsai      *}
{ * DATE:      August 19, 1985   *}
{ * }
{ * FUNCTION:   Simulate the operation of the 32-bit floating   *}
{ *             point processor: AM29325                       *}
{ * }
{ * USER GUIDE: THE CALLING FORMAT IS:                          *}
{ *             AM325;                                          *}
{ * NOTE :      Change the CONTROL variables before the call.  *}
{ * }
{ * PROGRAMMER }
{ * GUIDE:      $ PAS AM325                                     *}
{ *             *** It is not a main program. ***             *}
{ * }
{ * PROCEDURES }
{ * CALLED:      NONE                                          *}
{ * }
{ * FUNCTIONS   }
{ * CALLED:      NONE                                          *}
{ * }
{ * GLOBAL VARIABLES      CONTROL, BUS_R, BUS_S               *}
{ * REFERENCED:           }
{ * }
{ * GLOBAL VARIABLES      BUS_F                                *}
{ * MODIFIED:              }
{*****}

%INCLUDE 'GLOBAL.PAS'

[EXTERNAL]PROCEDURE SEED_TABLE; EXTERNAL;

PROCEDURE SUB_INT_TO_FP;
  BEGIN { SUB_INT_TO_FP }
  END; { SUB_INT_TO_FP }

PROCEDURE SUB_FP_TO_INT;
  BEGIN { SUB_FP_TO_INT }
  END; { SUB_FP_TO_INT }

PROCEDURE SUB_IEEE_TO_DEC;
  BEGIN { SUB_IEEE_TO_DEC }
  END; { SUB_IEEE_TO_DEC }

```

```

PROCEDURE SUB_DEC_TO_IEEE;
  BEGIN ( SUB_DEC_TO_IEEE )
  END; ( SUB_DEC_TO_IEEE )

[GLOBAL]PROCEDURE AM325;

BEGIN (AM325)
  ( Please check the initialization of CONTROL: FT0,FT1 )
  { If input registers are feedthrough then FT0 := HIGH }
  { If OUTPUT register is feedthrough then FT1 := HIGH }
  WITH CONTROL DO
    BEGIN ( CONTROL )
      IF ( FT0 = LOW ) THEN
        BEGIN
          IF ( ENR_BAR = LOW ) THEN REG_R := MUX_R;
          IF ( ENS_BAR = LOW ) THEN REG_S := BUS_S_END;
        END;
      IF ( FT1 = LOW ) THEN
        IF ( ENF_BAR = LOW ) THEN REG_F := ALU_F;
        (*****)
        BUS_S_END := BUS_S_SEND;
        SEED_IN := BUS_R;
        SEED_TABLE;
        IF ( MUX_A_SELECT = TRUE ) THEN MUX_A := SEED_OUT
          ELSE MUX_A := BUS_R;
        IF ( MUX_S_SELECT = TRUE )
          THEN
            IF ( FT1 = LOW ) THEN MUX_S := REG_F
              ELSE MUX_S := ALU_F
            ELSE
              IF ( FT0 = LOW ) THEN MUX_S := REG_S
                ELSE MUX_S := BUS_S_END;
            (***** ALU ***** )
            IF ( FT0 = LOW ) THEN ALU_R := REG_R
              ELSE ALU_R := MUX_R;
            ALU_S := MUX_S;
            (***** ALU_OPERATION ***** )
            CASE INS_ALU OF
              R_PLUS_S:
                BEGIN
                  ALU_F := ALU_R + ALU_S;
                  ADD_CNTR := ADD_CNTR + 1;
                END;
              R_MINUS_S:
                BEGIN
                  ALU_F := ALU_R - ALU_S;
                  ADD_CNTR := ADD_CNTR + 1;
                END;
            END;
          END;
        END;
      END;
    END;
  END;

```



```

R_TIMES_S:
BEGIN
    ALU_F := ALU_R * ALU_S;
    MUL_CNTR := MUL_CNTR + 1;
END;
TWO_MINUS_S:
BEGIN
    ALU_F := 2 - ALU_S;
    ADD_CNTR := ADD_CNTR + 1;
END;
(* NOT AVAILABLE *)
INT_TO_FP:    SUB_INT_TO_FP;
FP_TO_INT:    SUB_FP_TO_INT;
IEEE_TO_DEC:  SUB_IEEE_TO_DEC;
DEC_TO_IEEE:  SUB_DEC_TO_IEEE;
(* JUST FOR CYCLE COUNTER *)
NOP : BEGIN END;
END; {CASE}
IF ( MUX_R_SELECT = TRUE ) THEN MUX_R := ALU_F
                                ELSE MUX_R := MUX_A;
{*****      OUTPUT      *****}
IF ( OUT_EN = HIGH ) THEN
    IF ( FT1 = HIGH ) THEN BUS_F := ALU_F
                          ELSE BUS_F := REG_F;
END; { CONTROL }
AMD_CNTR := AMD_CNTR + 1;
END; {AM325}
END. { MODULE AM325 .}

```

```

[OVERLAID]MODULE SEED_TABLE( INPUT, OUTPUT );

{***** FILE: SEED_TABLE.PAS *****)

{*****}
{ *      PROGRAM: SEED_TABLE.PAS      *}
{*****}

{*****}
{ *                                     *}
{ * PROGRAMMER: Yusheng Tsai          *}
{ * DATE:      August 19, 1985        *}
{ *                                     *}
{ * FUNCTION:   Simulate the operation of the 32-bit floating *}
{ *             point SEED_TABLE to generate the seed for sine *}
{ *             cosin, and reciprocal operation.              *}
{ *                                     *}
{ * USER GUIDE: THE CALLING FORMAT IS: *}
{ *             SEED_TABLE              *}
{ * NOTE :      Change the SEED_SELECT before the call.       *}
{ *                                     *}
{ * PROGRAMMER                                     *}
{ * GUIDE:      $ PAS SEED_TABLE              *}
{ *             *** It is not a main program. ***             *}
{ *                                     *}
{ * PROCEDURES                                     *}
{ * CALLED:     NONE                               *}
{ *                                     *}
{ * FUNCTIONS                                     *}
{ * CALLED:     NONE                               *}
{ *                                     *}
{ * GLOBAL VARIABLES      CONTROL, BUS_R, SEED_IN *}
{ * REFERENCED:                                     *}
{ *                                     *}
{ * GLOBAL VARIABLES      SEED_OUT                *}
{ * MODIFIED:                                     *}
{*****}

%INCLUDE 'GLOBAL.PAS'

```

```

PROCEDURE IN_EX(VAR EX : INTEGER);
(***) FIND THE EXPONENT OF SEED_IN (***)
VAR
    K_SUB : REAL;
BEGIN
    EX := 0;
    K_SUB := ABS(SEED_IN);
    REPEAT
        IF K_SUB >= 2.0 THEN
            BEGIN
                EX := EX + 1;
                K_SUB := K_SUB/2.0;
            END;
        IF K_SUB < 1.0 THEN
            BEGIN
                EX := EX - 1;
                K_SUB := K_SUB * 2.0;
            END;
        UNTIL ((1.0 < K_SUB) AND (K_SUB < 2.0)) OR (K_SUB = 1.0));
    END;

PROCEDURE SUB_SIN_TAB;
VAR
    EX : INTEGER;
    TM1 : REAL;
    FRAC_NUM, BIT_NUM_OUT, POWER, I_S:INTEGER;
BEGIN
    (
        { X IS EXPRESSED IN RADIANS, IN +/- ***.***...*** BINARY FORMAT }
        { SIN(X) = SIN( a+b ) }
        { USE 12-BIT AS a = +/- ***.***...*** }
        { b = X - a }
        { OUTPUT IS SIN(a) IN SIGN + 8_BIT EXPONENT + 11_BIT FRACTION }
    )
    FRAC_NUM := 8;
    BIT_NUM_OUT := 11;
    ( IN_EX(EX);
      FRAC_NUM := FRAC_NUM - EX;
      BIT_NUM_OUT := BIT_NUM_OUT + EX + 1;
    ) POWER := 1;
    FOR I_S := 1 TO FRAC_NUM DO
        POWER := POWER * 2;
    TM1 := TRUNC( SEED_IN * POWER ) / POWER;
    POWER := 1;
    FOR I_S := 1 TO BIT_NUM_OUT DO
        POWER := POWER * 2;
    SEED_OUT := TRUNC( SIN(TM1) * POWER ) / POWER;
END;

```

```

PROCEDURE SUB_COS_TAB;
VAR
  EX : INTEGER;
  TM1: REAL;
  FRAC_NUM, BIT_NUM_OUT, POWER, I_S:INTEGER;
BEGIN
  (
    { X IS EXPRESSED IN RADIANS, IN +/- ***.***...*** BINARY FORMAT }
    { COS(X) = COS( a+b ) }
    { USE 12-BIT AS a = +/- ***.***** }
    { b = X - a }
    { OUTPUT IS COS(a) IN SIGN + 8_BIT EXPONENT + 11_BIT FRACTION }
    -----
    FRAC_NUM := 8;
    BIT_NUM_OUT := 11;
    POWER := 1;
    FOR I_S := 1 TO FRAC_NUM DO
      POWER := POWER * 2;
    TM1 := TRUNC( SEED_IN * POWER ) / POWER;
    POWER := 1;
    FOR I_S := 1 TO BIT_NUM_OUT DO
      POWER := POWER * 2;
    SEED_OUT := TRUNC( COS(TM1) * POWER ) / POWER;
  END;

PROCEDURE SUB_REC1;
VAR
  EX : INTEGER;
  TM1: REAL;
  FRAC_NUM, BIT_NUM_OUT, POWER, I_S:INTEGER;
BEGIN
  (WRITELN(OUTPUT, ' TEST IN THE BEGINNING OF SUB_REC1 '));)
  FRAC_NUM := 12;
  BIT_NUM_OUT := 12;
  IN_EX(EX);
  FRAC_NUM := FRAC_NUM - EX;
  BIT_NUM_OUT := BIT_NUM_OUT + EX + 1;
  POWER := 1;
  FOR I_S := 1 TO FRAC_NUM DO
    POWER := POWER * 2;
  TM1 := TRUNC( SEED_IN * POWER ) / POWER;
  POWER := 1;
  FOR I_S := 1 TO BIT_NUM_OUT DO
    POWER := POWER * 2;
  SEED_OUT := TRUNC( 1.0/(TM1) * POWER ) / POWER;
  END;

```

```
[GLOBAL]PROCEDURE SEED_TABLE ;  
BEGIN  
  WITH CONTROL DO  
    CASE SEED_SELECT OF  
      SIN_TAB      : SUB_SIN_TAB;  
      COS_TAB      : SUB_COS_TAB;  
      RECIPROCAL: SUB_REC1;  
    END;  
  END;  
END.
```

```

[OVERLAID]MODULE SIN_COS( INPUT, OUTPUT );
{***** FILE: SIN_COS.PAS *****)

{*****}
{*      PROGRAM: SIN_COS.PAS      *}
{*****}

{*****}
{*
{* PROGRAMMER: Yusheng Tsai
{* DATE:      August 27, 1985
{*
{* FUNCTION:   Simulate the operation of SINE/COSINE FUNCTION
{*             on the 32-bit floating point processor: AM29325
{*
{* USER GUIDE: THE CALLING FORMAT IS:
{*             SIN_COS (      THETA      : REAL
{*                     VAR SIN_OUT : REAL
{*                     VAR COS_OUT : REAL);
{*
{* PROGRAMMER
{* GUIDE:      $ PAS SIN_COS
{*             *** It is not a main program. ***
{*
{* PROCEDURES
{* CALLED:     AM325
{*
{* FUNCTIONS
{* CALLED:     NONE
{*
{* GLOBAL VARIABLES      CONTROL, BUS_R, BUS_S
{* REFERENCED:
{*
{* GLOBAL VARIABLES      BUS_F
{* MODIFIED:
{*****}

%INCLUDE 'GLOBAL.PAS'

[EXTERNAL]PROCEDURE AM325; EXTERNAL;

PROCEDURE WR_STATUS(CYCLE:INTEGER);
BEGIN
    WRITELN(OUTPUT,'SINE/COSINE CYCLE  ',CYCLE:4,' :');
    WRITELN(OUTPUT,'REG_R= ',REG_R:14:8,' REG_S= ',REG_S:14:8,
              ' REG_F= ',REG_F:14:8);
    WRITELN(OUTPUT,'MUX_A= ',MUX_A:14:8,' MUX_R= ',
              MUX_R:14:8,' MUX_S= ',MUX_S:14:8);
    WRITELN(OUTPUT,'ALU_R= ',ALU_R:14:8,' ALU_S= ',
              ALU_S:14:8,' ALU_F= ',ALU_F:14:8);
    WRITELN(OUTPUT,'BUS_R= ',BUS_R:14:8,' BUS_S= ',
              BUS_S_END:14:8,' BUS_F= ',BUS_F:14:8);
END;

```

```

[GLOBAL]PROCEDURE SIN_COS(      THETA_RAD : REAL;
                               VAR SIN_OUT  : REAL;
                               VAR COS_OUT  : REAL );

VAR
  I_SIN : INTEGER;

BEGIN {SUB_SIN}
{WRITELN(OUTPUT,'BEGIN SIN_COS CYCLE_CNTR= ', CYCLE_CNTR);}
  WITH CONTROL DO
    BEGIN { CONTROL }
      {-----}
      ENR_BAR := LOW; ENS_BAR := LOW; ENF_BAR := LOW;
      FT0 := LOW; FT1 := LOW; OUT_EN := LOW;
      MUX_A_SELECT := FALSE; MUX_R_SELECT := FALSE;
      MUX_S_SELECT := FALSE; SEED_SELECT := NONE;
      BUS_R := THETA_RAD; BUS_S_SEND := THETA_RAD;
      INS_ALU := NOP;
      (1) AM325;
      ( WR_STATUS(CYCLE_CNTR); )
      CYCLE_CNTR := CYCLE_CNTR + 1;
      {-----}
      BUS_S_SEND := THETA_RAD;
      MUX_R_SELECT := TRUE;
      INS_ALU := R_TIMES_S;
      (2) AM325;
      ( WR_STATUS(CYCLE_CNTR); )

      CYCLE_CNTR := CYCLE_CNTR + 1;
      {-----}
      OUT_EN := HIGH;
      MUX_S_SELECT := FALSE;
      (3) AM325;
      ( WR_STATUS(CYCLE_CNTR); )
      CYCLE_CNTR := CYCLE_CNTR + 1;
      WITH R_FILE DO
        TEMP[1] := BUS_F;
      {-----}
      ENR_BAR := HIGH;
      OUT_EN := HIGH;
      MUX_S_SELECT := TRUE;
      INS_ALU := R_TIMES_S;
      FOR I_SIN := 2 TO 6 DO
        BEGIN
          (4) AM325;
          ( WR_STATUS(CYCLE_CNTR); )
          WITH R_FILE DO
            TEMP[I_SIN] := BUS_F;
            CYCLE_CNTR := CYCLE_CNTR + 1;
          END;
        END;
      END;
    END;
  END;

```

```

(-----)
  WITH R_FILE DO
    BUS_S_SEND := SIN_REG_CONST[7];
    MUX_R_SELECT := TRUE;
(4) AM325;
  ( WR_STATUS(CYCLE_CNTR); )
    WITH R_FILE DO
      TEMP[7] := BUS_F;
      CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  MUX_R_SELECT := FALSE;
  OUT_EN := LOW;
  ENR_BAR := LOW;
  INS_ALU := R_TIMES_S;
  MUX_S_SELECT := FALSE;
  WITH R_FILE DO
    BUS_S_SEND := SIN_REG_CONST[6];
    MUX_R_SELECT := FALSE;
    WITH R_FILE DO
      BUS_R := TEMP[7];
(5) AM325;
  ( WR_STATUS(CYCLE_CNTR); )
    CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  OUT_EN := HIGH;
  FOR I_SIN := 6 DOWNT0 2 DO
  BEGIN
    WITH R_FILE DO
      BUS_R := TEMP[I_SIN];
    WITH R_FILE DO
      BUS_S_SEND := SIN_REG_CONST[I_SIN - 1];
(5) AM325;
  ( WR_STATUS(CYCLE_CNTR); )
    WITH R_FILE DO
      TEMP[I_SIN + 1] := BUS_F;
      CYCLE_CNTR := CYCLE_CNTR + 1;
  END;
(-----)
  BUS_R := THETA_RAD;
(5) AM325;
  ( WR_STATUS(CYCLE_CNTR); )
    WITH R_FILE DO
      TEMP[2] := BUS_F;
      CYCLE_CNTR := CYCLE_CNTR + 1;

```



```

(-----)
    ENS_BAR := HIGH;
    OUT_EN := LOW;
    MUX_S_SELECT := TRUE;
    INS_ALU := R_PLUS_S;
    FOR I_SIN := 2 TO 7 DO
    BEGIN
        WITH R_FILE DO
            BUS_R := TEMP[I_SIN];
(6) AM325;
        ( WR_STATUS(CYCLE_CNTR); )
          CYCLE_CNTR := CYCLE_CNTR + 1;
        END;
(-----)
        WITH R_FILE DO
            BUS_R := TEMP[1];
        WITH R_FILE DO
            BUS_S_SEND := TEMP[1];
(6) AM325;
        ( WR_STATUS(CYCLE_CNTR); )
          CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
        INS_ALU := R_TIMES_S;
        ENS_BAR := LOW;
        MUX_S_SELECT := FALSE;
        OUT_EN := HIGH;
(7) AM325;
        ( WR_STATUS(CYCLE_CNTR); )
          CYCLE_CNTR := CYCLE_CNTR + 1;
          SIN_OUT := BUS_F;
(-----)
        ENR_BAR := HIGH;
        MUX_S_SELECT := TRUE;
        FOR I_SIN := 2 TO 5 DO
        BEGIN
(8) AM325;
            ( WR_STATUS(CYCLE_CNTR); )
              CYCLE_CNTR := CYCLE_CNTR + 1;
            WITH R_FILE DO
                TEMP[I_SIN] := BUS_F;
            END;
(-----)
            WITH R_FILE DO
                BUS_R := COS_REG_CONST[7];
                MUX_R_SELECT := FALSE;
(8) AM325;
            ( WR_STATUS(CYCLE_CNTR); )
              WITH R_FILE DO
                  TEMP[6] := BUS_F;
                  CYCLE_CNTR := CYCLE_CNTR + 1;

```

```

(-----)
    ENR_BAR := LOW;
    OUT_EN := LOW;
    WITH R_FILE DO
        BUS_R := TEMP[5];
    WITH R_FILE DO
        BUS_S_SEND := COS_REG_CONST[5];
(8) AM325;
(    WR_STATUS(CYCLE_CNTR);)
    CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
    MUX_S_SELECT := FALSE;
    OUT_EN := HIGH;
    FOR I_SIN := 4 DOWNTO 1 DO
        BEGIN
            WITH R_FILE DO
                BUS_R := TEMP[I_SIN];
            WITH R_FILE DO
                BUS_S_SEND := COS_REG_CONST[I_SIN];
(9) AM325;
(    WR_STATUS(CYCLE_CNTR);)
            WITH R_FILE DO
                TEMP[I_SIN + 1] := BUS_F;
            CYCLE_CNTR := CYCLE_CNTR + 1;
        END;
(-----)
        WITH R_FILE DO
            BUS_R := TEMP[6];
        WITH R_FILE DO
            BUS_S_SEND := COS_REG_CONST[6];
(9) AM325;
(    WR_STATUS(CYCLE_CNTR);)
            WITH R_FILE DO
                TEMP[1] := BUS_F;
            CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
        BUS_R := ONE;
(9) AM325;
(    WR_STATUS(CYCLE_CNTR);)
        WITH R_FILE DO
            TEMP[6] := BUS_F;
        CYCLE_CNTR := CYCLE_CNTR + 1;

```

```

(-----)
    OUT_EN := LOW;
    MUX_S_SELECT := TRUE;
    INS_ALU := R_PLUS_S;
    FOR I_SIN := 1 TO 6 DO
    BEGIN
        WITH R_FILE DO
            BUS_R := TEMP[I_SIN];
{10} AM325;
        ( WR_STATUS(CYCLE_CNTR); )
          CYCLE_CNTR := CYCLE_CNTR + 1;
        END;
(-----)
        BUS_R := 0.0;
        BUS_S_SEND := 0.0;
        AM325;
        ( WR_STATUS(CYCLE_CNTR); )
          CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
        MUX_S_SELECT := FALSE;
        OUT_EN := HIGH;
        AM325;
        CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)

        ( WR_STATUS(CYCLE_CNTR); )
        WITH R_FILE DO
            COS_OUT := BUS_F;
            CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
        END; ( CONTROL )
(WRITELN(OUTPUT,'END OF SIN_COS CYCLE_CNTR= ',CYCLE_CNTR);)
(WRITELN(OUTPUT,'THETA_RAD= ',THETA_RAD);)
WRITELN(OUTPUT,'COS_OUT= ', COS_OUT,'SIN_OUT= ',SIN_OUT);
    }
END; (SUB_SIN)
END.( MODULE SUB_SIN )

```

```

[OVERLAID]MODULE SUB_REC( INPUT, OUTPUT );

(***** FILE: SUB_REC.PAS *****)

(*****)
(*      PROGRAM: SUB_REC.PAS      *)
(*****)

(*****)
(*                                     *)
(* PROGRAMMER: Yusheng Tsai          *)
(* DATE:      August 26, 1985        *)
(*                                     *)
(* FUNCTION:   Simulate the operation of RECIPROCAL ON *)
(*             the 32-bit floating point processor: AM29325 *)
(*                                     *)
(* USER GUIDE: THE CALLING FORMAT IS: *)
(*             SUB_REC                *)
(* NOTE :      Change the CONTROL variables before the call. *)
(*                                     *)
(* PROGRAMMER                                     *)
(* GUIDE:      $ PAS SUB_REC                    *)
(*             *** It is not a main program. *** *)
(*                                     *)
(* PROCEDURES                                     *)
(* CALLED:      NONE                            *)
(*                                     *)
(* FUNCTIONS                                         *)
(* CALLED:      NONE                            *)
(*                                     *)
(* GLOBAL VARIABLES      CONTROL, BUS_R, BUS_S *)
(* REFERENCED:                                     *)
(*                                     *)
(* GLOBAL VARIABLES      BUS_F *)
(* MODIFIED:                                     *)
(*****)

%INCLUDE 'GLOBAL.PAS'

[EXTERNAL]PROCEDURE AM325; EXTERNAL;

PROCEDURE WR_STATUS(cycle_cntrl:INTEGER);
BEGIN
    WRITELN(OUTPUT,'RECIPROCAL CYCLE',cycle_cntrl:2,' :');
    WRITELN(OUTPUT,'REG_R= ',REG_R:14:8,' REG_S= ',REG_S:14:8,
        ' REG_F= ',REG_F:14:8);
    WRITELN(OUTPUT,'MUX_A= ',MUX_A:14:8,' MUX_R= ',
        MUX_R:14:8,' MUX_S= ',MUX_S:14:8);
    WRITELN(OUTPUT,'ALU_R= ',ALU_R:14:8,' ALU_S= ',
        ALU_S:14:8,' ALU_F= ',ALU_F:14:8);
END;

```

```

[GLOBAL]PROCEDURE SUB_REC(REC_VAR : REAL);

BEGIN (SUB_REC)
  WITH CONTROL DO
    BEGIN ( CONTROL )
      (-----)
      FT0 := LOW; FT1 := LOW; OUT_EN := LOW;
      MUX_A_SELECT := TRUE; MUX_R_SELECT := FALSE;
      MUX_S_SELECT := FALSE; SEED_SELECT := RECIPROCAL;
      BUS_R := REC_VAR; BUS_S_SEND := REC_VAR;
      INS_ALU := NOP;
      (1) AM325;
      (WR_STATUS(cycle_cntr);)
      cycle_cntr := cycle_cntr + 1;
      (-----)
      INS_ALU := R_TIMES_S;
      MUX_S_SELECT := FALSE;
      (2) AM325;
      (WR_STATUS(cycle_cntr);)
      cycle_cntr := cycle_cntr + 1;
      (-----)
      (REPEAT)
      ENR_BAR := HIGH;
      MUX_S_SELECT := TRUE;
      INS_ALU := TWO_MINUS_S;
      BUS_R := REC_VAR;
      (3) AM325;
      (WR_STATUS(cycle_cntr);)
      cycle_cntr := cycle_cntr + 1;
      (-----)
      BUS_S_SEND := REC_VAR;
      MUX_R_SELECT := TRUE;
      INS_ALU := R_TIMES_S;
      (4) AM325;
      (WR_STATUS(cycle_cntr);)
      cycle_cntr := cycle_cntr + 1;
      (-----)
      INS_ALU := R_TIMES_S;
      MUX_S_SELECT := false;
      OUT_EN := HIGH;
      ENR_BAR := LOW;
      (5) AM325;
      (WR_STATUS(cycle_cntr);)
      cycle_cntr := cycle_cntr + 1;
    END ( CONTROL )
  END (SUB_REC)

```

```

(-----)
(WRITELN(OUTPUT,'REC_VAR= ',REC_VAR);)
(WRITELN(OUTPUT,'REG_F= ',REG_F);)
[ UNTIL( ABS( reg_f - 1.0/REC_VAR) < 0.000002 );]
  WITH R_FILE DO
    REC := BUS_F;
  END; { CONTROL }
{ACTUALLY, NO R_TIMES_S OP IN STEP 5 }
  MUL_CNTR := MUL_CNTR - 1;
{ FOR SEND OUTPUT TO R_FILE }
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
END; {SUB_REC}
END.{ MODULE SUB_REC }

```

A.3.2 Programs for Computational Modules

A.3.2 contains 8 programs which simulate the computational modules of the Inverse Kinematics algorithm and one file of global variables. GLOBAL.PAS contains all variables. INITIQ1.PAS and INIT_XN1.PAS include all initialization parameters. KIN_JAC.PAS and PSEUDO_INV.PAS are generic modules for the computation of Direct Kinematics, the Jacobian, and the Inverse Jacobian. SUB_ADJ.PAS, SUB_COR.PAS, SUB_PRE.PAS, and SUB_ERR.PAS are four computational modules for the algorithm.

```

(***** FILE: GLOBAL.PAS in directory: [EE.TSAI.AMD] *****)

(*****)
{
{ VERSION:      1.0
{
{ PROGRAMMER:   Yusheng Tsai
{
{ DATE:        AUGUST 19, 1985
{
{ FUNCTION:     This file provides the global variables which
{               can be compiled with other Inverse Kinematics
{               programs for AMD simulation
{
{ USER GUIDE:   Put
{               %INCLUDE 'GLOBAL.PAS'
{               in the first line of all programs.
{
{
{ *****)

```

TYPE

```

INSTRUCTION = ( R_PLUS_S, R_MINUS_S, R_TIMES_S, TWO_MINUS_S,
               NOP,INT_TO_FP,FP_TO_INT,IEEE_TO_DEC,DEC_TO_IEEE);
LOGIC       = ( HIGH, LOW );
FG          = ( PREDICT,CORRECT );
SQUARE_MAT_66 = ARRAY [1..6,1..7] OF REAL;
SEED_TYPE   = ( SIN_TAB, COS_TAB, RECIPROCAL, NONE );
ARRAY4      = ARRAY [1..4] OF REAL;
ARRAY6      = ARRAY [1..6] OF REAL;
ARRAY7      = ARRAY [1..7] OF REAL;
ARRAY8      = ARRAY [1..8] OF REAL;
ARRAY9      = ARRAY [1..9] OF REAL;
ARRAY12     = ARRAY [1..12] OF REAL;
ARRAY34     = ARRAY [1..3,1..4] OF REAL;
ARRAY67     = ARRAY [1..6,1..7] OF REAL;
ARRAY74     = ARRAY [1..7,1..4] OF REAL;
LINK_TYP    = ( SLIDING, REVOLUTE );
IN_CHR_TYPE = ( A,P,D,T,R,S,C,E,K,J,I,Y,O,M,G );

```

CONST

```

PI = 3.1415927;
( PI = 3.141592653589793; )
ONE = 1.0;

```

VAR

```

MUX_A, MUX_R, MUX_S : REAL;
REG_R, REG_S, REG_F : REAL;
ALU_R, ALU_S, ALU_F : REAL;

```



```

CONTROL :
  RECORD
    ENR_BAR : LOGIC ; ( Register R is enabled if LOW )
    ENS_BAR, ENF_BAR : LOGIC;
    MUX_A_Select, MUX_R_Select, MUX_S_Select : Boolean;
    INS_ALU : INSTRUCTION;
    FT0, FT1 : LOGIC;
    OUT_EN : LOGIC; ( OUTPUT ENABLE )
    SEED_SELECT : SEED_TYPE;
  END;
R_FILE :
  RECORD
    A_CONST,B_CONST,C_CONST : ARRAY4;
    X_N,X_N_DOT : ARRAY74;
    X4_P,X4_C,X4_DOT : ARRAY7;
    DELTA_T,REC : REAL;
    SIN_REG_CONST : ARRAY7;
    COS_REG_CONST : ARRAY7;
    ANGLE_RAD,SIN_THETA,COS_THETA : ARRAY8;
    LINK_PARM_A,LINK_PARM_D,LINK_PARM_SA,LINK_PARM_CA:ARRAY9;
    X,X_D,E : ARRAY34;
    TEMP : ARRAY12;
    JACOBN_MAT : ARRAY67;
    LINK_TYPE : LINK_TYP;
    S : SQUARE_MAT_66;
    V61,X_DOT : ARRAY7;
    VN1,Q_DOT : ARRAY7;
    SINGULARITY : BOOLEAN;
    RECIP : ARRAY7;
  END;

N : INTEGER;

BUS_R, BUS_S_SEND,BUS_S_END, BUS_F : REAL;

SEED_IN, SEED_OUT: REAL; ( NOT FINAL )

AMD_CNTR,CYCLE_CNTR, ADD_CNTR, MUL_CNTR : INTEGER;

I_KIN,I_TST : INTEGER;

M_REC_VAR,ANGLE_S,ANGLE_RAD,SIN_OUT2,COS_OUT2 : REAL;

IN_CHR : IN_CHR_TYPE;

(MAIN PROGRAM VARIABLES)
TIME,TEND : REAL;
FLAG : FG;
ETA, EPSER : REAL;
JAC_NO,PRE_NO,NO_COR_NO,COR_NO,COR_LP_NO,ITE_NO : INTEGER;
MAX_ERR,MAX_TIM,DELTA1,DELTA2,DELTA3 : REAL;

```

```

[overlaid]MODULE INITIQ1(INPUT,OUTPUT);

(***** FILE INITIQ1.PAS *****)

(*****)
(  PROCEDURE INITIQ1  )
(*****)

(*****)
(
(  VERSION:      1.0
(
(  PROGRAMMER:   Yusheng Tsai,
(  DATE:         SEP.16, 1985
(
(  FUNCTION:     Initialize the Mitsubishi robot parameters
(
(  USER GUIDE:   >pas INITIQ1
(
(  PROCEDURES CALLED: INIT80
(
(  GLOBAL VARIABLES
(    REFERENCED:    -None-
(
(    MODIFIED:      KINMC_VARS, Z, E, N
(
(
(*****)

%INCLUDE 'GLOBAL.PAS'

[EXTERNAL]PROCEDURE INIT_XN1; EXTERN;
[EXTERNAL]PROCEDURE SIN_COS(  THETA_RAD : REAL;
                             VAR SIN_OUT : REAL;
                             VAR COS_OUT : REAL); EXTERN;
[EXTERNAL]PROCEDURE kin_jac; EXTERN;
[EXTERNAL]PROCEDURE WRITE_ANGLE; EXTERN;

```

```

[GLOBAL]PROCEDURE INIT;
VAR
  K_I,J_I : INTEGER;
BEGIN ( INIT )
  {*****}
  { SINE/COSINE REGISTERS" INITILIZATION }
  WITH R_FILE DO
    BEGIN
      N := 5;
      COS_REG_CONST[1] := - 1/2;
      FOR K_I := 1 TO 6 DO
        BEGIN
          J_I := 2 * K_I + 1;
          SIN_REG_CONST[K_I] := COS_REG_CONST[K_I]/J_I;
          COS_REG_CONST[K_I+1] := - SIN_REG_CONST[K_I]/(J_I + 1);
        END;
      SIN_REG_CONST[7] := COS_REG_CONST[7]/15;
    END;
  {*****}
  { AM29325 INITILIZATION }
  BUS_R :=0.0; BUS_S_SEND :=0.0; BUS_S_END := 0.0; BUS_R := 0.0;
  WITH CONTROL DO
    BEGIN
      ENR_BAR := LOW; ENS_BAR := LOW; ENF_BAR := LOW;
      MUX_A_SELECT := FALSE; MUX_R_SELECT := FALSE;
      MUX_S_SELECT := FALSE; INS_ALU := R_PLUS_S;
      FT0 := LOW; FT1 := LOW;
      OUT_EN :=LOW; SEED_SELECT := NONE;
    END;
  {*****}
END; ( INIT )

[GLOBAL]PROCEDURE INIT_LINK;
{ASSIGN THE MITSUBISHI ROBOT}
BEGIN (INIT_LINK)
  { E MATRIX }
  WITH R_FILE DO
    BEGIN
      E[1,1] := 1.0; E[2,2] := 1.0; E[3,3] := 1.0;
      E[3,4] := 196.1;
    END;

```

```

WITH R_FILE DO
  BEGIN
    LINK_TYPE := REVOLUTE;
    LINK_PARM_A[1] := 0.0; LINK_PARM_D[1] := 250.0;
    LINK_PARM_SA[1] := 0.0; LINK_PARM_CA[1] := 1.0;
    LINK_PARM_A[2] := 0.0; LINK_PARM_D[2] := 0.0;
    LINK_PARM_SA[2] := -1.0; LINK_PARM_CA[2] := 0.0;
    LINK_PARM_A[3] := 220.0; LINK_PARM_D[3] := 0.0;
    LINK_PARM_SA[3] := 0.0; LINK_PARM_CA[3] := 1.0;
    LINK_PARM_A[4] := 160.0; LINK_PARM_D[4] := 0.0;
    LINK_PARM_SA[4] := 0.0; LINK_PARM_CA[4] := 1.0;
    LINK_PARM_A[5] := 0.0; LINK_PARM_D[5] := 0.0;
    LINK_PARM_SA[5] := 1.0; LINK_PARM_CA[5] := 0.0;
    LINK_PARM_A[6] := 0.0; LINK_PARM_D[6] := 0.0;
    LINK_PARM_SA[6] := 0.0; LINK_PARM_CA[6] := 1.0;
    SIN_COS (ANGLE_RAD[1], SIN_THETA[1], COS_THETA[1]);
  END;
END; (INIT_LINK)

[GLOBAL]PROCEDURE INITIQL;
VAR
  JUNK: INTEGER;
  MMI,MMJ:INTEGER ;
  ACE: real;
BEGIN { 1 }
  (WRITELN(OUTPUT,' START OF THE INITIALIZATION PROCESS ' ));
  INIT;
  INIT_LINK;
  WITH CONTROL DO BEGIN
  WITH R_FILE DO BEGIN
    N := 5;
    DELTA_T := 0.01;
    {1. Initialize the A, B, and C constant arrays }
    A_CONST[1] := 1.547652; A_CONST[2] := -1.867503;
    A_CONST[3] := 2.017204; A_CONST[4] := -0.697353;
    B_CONST[1] := 2.002247; B_CONST[2] := -2.03169 ;
    B_CONST[3] := 1.818609; B_CONST[4] := -0.74320 ;
    C_CONST[1] := 0.37500000; C_CONST[2] := 0.7916666667 ;
    C_CONST[3] := - 0.2083333333; C_CONST[4] := 0.041666667 ;
    {2. Initialize X_N and X_N_DOT matrix by using Lagrange integration
    {USE EULER METHOD }
    { FOR TASK # 2 }
    X_N_DOT[1,3] := 0.0; X_N_DOT[1,4] := 0.0;
    X_N_DOT[2,3] := 1.97945; X_N_DOT[2,4] := 1.97828;
    X_N_DOT[3,3] := -5.22102; X_N_DOT[3,4] := - 5.21873;
    X_N_DOT[4,3] := 3.24157; X_N_DOT[4,4] := 3.24045;
    X_N_DOT[5,3] := 0.0; X_N_DOT[5,4] := 0.0;
    X_N[1,4] := 0.0;
    X_N[2,4] := -29.94374;
    X_N[3,4] := 73.28407;
    X_N[4,4] := 46.65975;
    X_N[5,4] := 0.0;

```

```

( STARTING POINT IS SET AT TIME = 0.0 )
FOR MMI := 1 TO N DO
  BEGIN
    ACE := (X_N_DOT[MMI,3]-X_N_DOT[MMI,4])/ 0.0073;
    X_N_DOT[MMI,1] := X_N_DOT[MMI,4];
    X_N_DOT[MMI,2] := X_N_DOT[MMI,1] - ACE * DELTA_t;
    X_N_DOT[MMI,3] := X_N_DOT[MMI,2] - ACE * DELTA_t;
    X_N_DOT[MMI,4] := X_N_DOT[MMI,3] - ACE * DELTA_t;
    X_N[MMI,1] := X_N[MMI,4];
    X_N[MMI,2] := X_N[MMI,1] - X_N_DOT[MMI,4] * DELTA_t;
    X_N[MMI,3] := X_N[MMI,2] - X_N_DOT[MMI,3] * DELTA_t;
    X_N[MMI,4] := X_N[MMI,3] - X_N_DOT[MMI,2] * DELTA_t;
  END;
( FOR TASK #1 )
INIT_XN1;
(*****)
FOR MMI := 1 TO N DO
  BEGIN
    WITH R_FILE DO
      ANGLE_RAD[MMI +1] := X_N[MMI,1]/ 180.0 * PI;
    END;
    WRITELN(OUTPUT, '***** STARTING POINT *****');
    WRITE_ANGLE;
    WRITELN (OUTPUT, 'N= ', N );
    kin_jac;
    WRITELN(OUTPUT, 'X MATRIX:');
    FOR MMI := 1 TO 3 DO
      WRITELN(OUTPUT, X[MMI,1]:10:5, X[MMI,2]:10:5, X[MMI,3]:10:5,
        X[MMI,4]:10:5);
    WRITELN(OUTPUT, '***** TEST IN INITIQL *****');
  END;
(*****)
( INITIALIZE X_DOT )
( FOR TASK #1 )
  X_DOT[1] := 0.0; { IN DEG/SEC }
  X_DOT[2] := 0.0; { IN DEG/SEC }
  X_DOT[3] := -10.0; { IN DEG/SEC }
  X_DOT[4] := 0.0; { IN MM/SEC }
  X_DOT[5] := - 500.0; { IN MM/SEC }
  X_DOT[6] := 0.0; { IN MM/SEC }
  WRITELN(OUTPUT, 'DEFAULT X_DOT ARE:');
  FOR I_TST := 1 TO 6 DO
    WRITE(OUTPUT, X_DOT[I_TST]:12:6);
  WRITELN(OUTPUT);
(*****)
END; (R_FILE)
END; (CONTROL)
END; { 1 }
END. ( MODULE )

```

```

[overlaid]MODULE INIT_XN1(INPUT,OUTPUT);

{***** FILE INIT_XN1.PAS *****)

{*****}
{  PROCEDURE INIT_XN1  }
{*****}

{*****}
{
{  VERSION:      1.0
{
{  PROGRAMMER:  Yusheng Tsai,
{  DATE:        September 12, 1985
{
{  FUNCTION:    Initialize the INITIAL parameters
{
{  USER GUIDE:  >pas INIT_XN1
{
{  PROCEDURES CALLED: NONE
{
{  GLOBAL VARIABLES
{    REFERENCED:      -None-
{
{    MODIFIED:        X_N,X_N_DOT,A_CONST,B_CONST,C_CONST
{
{
{*****}

%INCLUDE 'global.PAS'

[GLOBAL]PROCEDURE INIT_XN1;
VAR
  MMI,MMJ : INTEGER;
  ACE      : REAL;

BEGIN ( 1 )
  WITH CONTROL DO BEGIN
  WITH R_FILE DO BEGIN
  N := 5;
  DELTA_T := 0.01;

```

```

(0. Initialize X_N and X_N_DOT matrix by
    using Lagrange integration )
    (USE EULER METHOD )
    X_N_DOT[1,3]:= 1.35135; X_N_DOT[1,4] := 1.35135;
  ( X_N_DOT[1,3]:= 1.35134; X_N_DOT[1,4] := 1.35135;)
    X_N_DOT[2,3]:= - 0.01177; X_N_DOT[2,4] := - 0.00392;
    X_N_DOT[3,3]:= 0.02890; X_N_DOT[3,4] := 0.00963;
    X_N_DOT[4,3]:= - 0.01712; X_N_DOT[4,4] := - 0.00571;
    X_N_DOT[5,3]:= - 8.64866; X_N_DOT[5,4] := - 8.64866;
  ( X_N_DOT[5,3]:= - 8.64867; X_N_DOT[5,4] := - 8.64866;)
X_N[1,4] := 0.0;
X_N[2,4] := - 4.74582;
X_N[3,4] := 24.31906;
X_N[4,4] := 160.42691;
X_N[5,4] := 180.0;
( STARTING POINT IS SET AT TIME = 0.0 )
FOR MMI := 1 TO N DO
  BEGIN
    ACE := (X_N_DOT[MMI,3]-X_N_DOT[MMI,4])/ 0.01;
    X_N_DOT[MMI,1] := X_N_DOT[MMI,4];
    X_N_DOT[MMI,2] := X_N_DOT[MMI,1] - ACE * DELTA_T;
    X_N_DOT[MMI,3] := X_N_DOT[MMI,2] - ACE * DELTA_T;
    X_N_DOT[MMI,4] := X_N_DOT[MMI,3] - ACE * DELTA_T;
    X_N[MMI,1] := X_N[MMI,4];
    X_N[MMI,2] := X_N[MMI,1] - X_N_DOT[MMI,4] * DELTA_T;
    X_N[MMI,3] := X_N[MMI,2] - X_N_DOT[MMI,3] * DELTA_T;
    X_N[MMI,4] := X_N[MMI,3] - X_N_DOT[MMI,2] * DELTA_T;
  END;

(1. Initialize the A, B, and C constant arrays )
A_CONST[1] := 1.547652; A_CONST[2] := -1.867503;
A_CONST[3] := 2.017204; A_CONST[4] := -0.697353;
B_CONST[1] := 2.002247; B_CONST[2] := -2.03169 ;
B_CONST[3] := 1.818609; B_CONST[4] := -0.74320 ;
C_CONST[1] := 0.37500000; C_CONST[2] := 0.7916666667 ;
C_CONST[3] := - 0.2083333333; C_CONST[4] := 0.0416666667 ;

END; (R_FILE)
END; (CONTROL)

END; ( 1 )
END. ( MODULE )

```

```

[OVERLAID]MODULE KIN_JAC( INPUT, OUTPUT );

(***** FILE: KIN_JAC.PAS *****)

(*****)
(*      PROGRAM: KIN_JAC.PAS      *)
(*****)

(*****)
(*                                                                           *)
(* PROGRAMMER: Yusheng Tsai                                               *)
(* DATE:      August 27, 1985                                           *)
(*                                                                           *)
(* FUNCTION:   Simulate the operation of DIRKIN $ JACOBIAN              *)
(*             on the 32-bit floating point processor: AM29325          *)
(*                                                                           *)
(* USER GUIDE: THE CALLING FORMAT IS:                                    *)
(*             KIN_JAC;                                                  *)
(*                                                                           *)
(* PROGRAMMER  *)
(* GUIDE:      $ PAS KIN_JAC                                             *)
(*             *** It is not a main program. ***                         *)
(*                                                                           *)
(* PROCEDURES  *)
(* CALLED:     AM325                                                      *)
(*                                                                           *)
(* FUNCTIONS   *)
(* CALLED:     NONE                                                       *)
(*                                                                           *)
(* GLOBAL VARIABLES      CONTROL, BUS_R, BUS_S                          *)
(* REFERENCED:                                                    *)
(*                                                                           *)
(* GLOBAL VARIABLES      BUS_F                                           *)
(* MODIFIED:                                                      *)
(*****)

$INCLUDE 'GLOBAL.PAS'

[EXTERNAL]PROCEDURE AM325; EXTERNAL;

[EXTERNAL]PROCEDURE WRITE_X; EXTERNAL;
[EXTERNAL]PROCEDURE WRITE_JAC; EXTERNAL;

[EXTERNAL]PROCEDURE SIN_COS(      THETA_RAD : REAL;
                                VAR  SIN_OUT  : REAL;
                                VAR  COS_OUT  : REAL );
    EXTERNAL;

```



```

PROCEDURE WR_STATUS (CYCLE: INTEGER);
BEGIN
    WRITELN(OUTPUT, 'SINE/COSINE CYCLE ', CYCLE:4, ' :');
    WRITELN(OUTPUT, 'REG_R= ', REG_R:14:8, ' REG_S= ', REG_S:14:8,
        ' REG_F= ', REG_F:14:8);
    WRITELN(OUTPUT, 'MUX_A= ', MUX_A:14:8, ' MUX_R= ',
        MUX_R:14:8, ' MUX_S= ', MUX_S:14:8);
    WRITELN(OUTPUT, 'ALU_R= ', ALU_R:14:8, ' ALU_S= ',
        ALU_S:14:8, ' ALU_F= ', ALU_F:14:8);
    WRITELN(OUTPUT, 'BUS_R= ', BUS_R:14:8, ' BUS_S= ',
        BUS_S_END:14:8, ' BUS_F= ', BUS_F:14:8);
END;

PROCEDURE T34_TIMES_T34 (I_T34 : INTEGER);
VAR
    I_II : INTEGER;
BEGIN ( T34 )
    WITH CONTROL DO
        BEGIN ( CONTROL )
            WITH R_FILE DO
                BEGIN ( R_FILE )
                    ( WRITE LINK PARAMETERS )
                    ( WRITE (OUTPUT, ' LINK_PARM_A LINK_PARM_D LINK_PARM_SA');
                    WRITELN(OUTPUT, ' LINK_PARM_CA');
                    FOR I_II := 1 TO N+1 DO
                        BEGIN
                            WRITE(OUTPUT, LINK_PARM_A[I_II]:13:5);
                            WRITE(OUTPUT, LINK_PARM_D[I_II]:13:5);
                            WRITE(OUTPUT, LINK_PARM_SA[I_II]:13:5);
                            WRITE(OUTPUT, LINK_PARM_CA[I_II]:13:5);
                            WRITELN(OUTPUT);
                        END;
                    ) (-----)
                    ENR_BAR := LOW; ENS_BAR := LOW; ENF_BAR := LOW;
                    FTO := LOW; FT1 := LOW; OUT_EN := HIGH;
                    MUX_A_SELECT := FALSE; MUX_R_SELECT := FALSE;
                    MUX_S_SELECT := FALSE; SEED_SELECT := NONE;
                    BUS_R := SIN_THETA[I_T34];
                    BUS_S_SEND := LINK_PARM_CA[I_T34];
                    INS_ALU := NOP;
                (1) AM325;
                {WR_STATUS(CYCLE_CNTR);}
                CYCLE_CNTR := CYCLE_CNTR + 1;
                (-----)
                INS_ALU := R_TIMES_S;
                BUS_R := SIN_THETA[I_T34];
                BUS_S_SEND := LINK_PARM_SA[I_T34];
                (2) AM325;
                {WR_STATUS(CYCLE_CNTR);}
                CYCLE_CNTR := CYCLE_CNTR + 1;

```

```

    INS_ALU := R_TIMES_S;
    BUS_R := COS_THETA[I_T34];
    BUS_S_SEND := LINK_PARM_CA[I_T34];
    WRITELN(OUTPUT, 'FOR LINK ', I_T34, '-1 SIN= ', SIN_THETA[I_T34],
            ' COS= ', COS_THETA[I_T34]);
(3) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
    (-----)
    TEMP[1] := BUS_F;
    INS_ALU := R_TIMES_S;
    BUS_R := COS_THETA[I_T34];
    BUS_S_SEND := LINK_PARM_SA[I_T34];
(4) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
    (-----)
    TEMP[2] := BUS_F;
    INS_ALU := R_TIMES_S;
    BUS_R := TEMP[1];
    BUS_S_SEND := X[2,1];
(5) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
    (-----)
    ENF_BAR := LOW;
    TEMP[3] := BUS_F;
    INS_ALU := R_TIMES_S;
    BUS_R := COS_THETA[I_T34];
    BUS_S_SEND := X[1,1];
(6) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
    (-----)
    TEMP[4] := BUS_F;
    INS_ALU := R_TIMES_S;
    MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(7) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
    (-----)
    ENF_BAR := HIGH;
    INS_ALU := R_MINUS_S;
    BUS_R := TEMP[2];
    BUS_S_SEND := X[3,1];
    MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(8) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;

```

```

(-----)
  ENF_BAR := LOW;
  INS_ALU := R_TIMES_S;
  MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(9) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  ENF_BAR := HIGH;
  INS_ALU := R_PLUS_S;
  BUS_R := TEMP[1];
  BUS_S_SEND := X[2,2];
  MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(10) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  ENF_BAR := LOW;
  MUX_R_SELECT := FALSE; MUX_S_SELECT := FALSE;
  INS_ALU := R_TIMES_S;
  BUS_R := COS_THETA[I_T34];
  BUS_S_SEND := X[1,2];
(11) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  TEMP[5] := BUS_F;
  INS_ALU := R_TIMES_S;
  MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(12) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  ENF_BAR := HIGH;
  INS_ALU := R_MINUS_S;
  BUS_R := TEMP[2];
  BUS_S_SEND := X[3,2];
  MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(13) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  ENF_BAR := LOW;
  INS_ALU := R_TIMES_S;
  MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(14) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;

```

```

(-----)
  ENF_BAR := HIGH;
  INS_ALU := R_PLUS_S;
  BUS_R := TEMP[1];
  BUS_S_SEND := X[2,3];
  MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(15) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  ENF_BAR := LOW;
  MUX_R_SELECT := FALSE; MUX_S_SELECT := FALSE;
  INS_ALU := R_TIMES_S;
  BUS_R := COS_THETA[I_T34];
  BUS_S_SEND := X[1,3];
(16) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  TEMP[6] := BUS_F;
  INS_ALU := R_TIMES_S;
  MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(17) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  ENF_BAR := HIGH;
  INS_ALU := R_MINUS_S;
  BUS_R := TEMP[2];
  BUS_S_SEND := X[3,3];
  MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(18) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  ENF_BAR := LOW;
  INS_ALU := R_TIMES_S;
  MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(19) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  ENF_BAR := HIGH;
  INS_ALU := R_PLUS_S;
  BUS_R := TEMP[4];
  BUS_S_SEND := X[3,1];
  MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(20) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;

```

```

(-----)
ENF_BAR := LOW;
MUX_R_SELECT := FALSE; MUX_S_SELECT := FALSE;
INS_ALU := R_TIMES_S;
BUS_R := SIN_THETA[I_T34];
BUS_S_SEND := X[1,1];
(21) AM325;
(WR_STATUS(CYCLE_CNTR);)
CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
TEMP[7] := BUS_F;
INS_ALU := R_TIMES_S;
MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(22) AM325;
(WR_STATUS(CYCLE_CNTR);)
CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
ENF_BAR := HIGH;
INS_ALU := R_MINUS_S;
BUS_R := TEMP[3];
BUS_S_SEND := X[2,1];
MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(23) AM325;
(WR_STATUS(CYCLE_CNTR);)
CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
ENF_BAR := LOW;
INS_ALU := R_TIMES_S;
MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(24) AM325;
(WR_STATUS(CYCLE_CNTR);)
CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
ENF_BAR := HIGH;
INS_ALU := R_PLUS_S;
BUS_R := TEMP[4];
BUS_S_SEND := X[3,2];
MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(25) AM325;
(WR_STATUS(CYCLE_CNTR);)
CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
ENF_BAR := LOW;
MUX_R_SELECT := FALSE; MUX_S_SELECT := FALSE;
INS_ALU := R_TIMES_S;
BUS_R := SIN_THETA[I_T34];
BUS_S_SEND := X[1,2];
(26) AM325;
(WR_STATUS(CYCLE_CNTR);)
CYCLE_CNTR := CYCLE_CNTR + 1;

```

```

(-----)
TEMP[8] := BUS_F;
INS_ALU := R_TIMES_S;
MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(27) AM325;
(WR_STATUS(CYCLE_CNTR);)
CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
(OUTSIDE) X[1,1] := TEMP[5];
ENF_BAR := HIGH;
INS_ALU := R_MINUS_S;
BUS_R := TEMP[3];
BUS_S_SEND := X[2,2];
MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(28) AM325;
(WR_STATUS(CYCLE_CNTR);)
CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
ENF_BAR := LOW;
INS_ALU := R_TIMES_S;
MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(29) AM325;
(WR_STATUS(CYCLE_CNTR);)
CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
ENF_BAR := HIGH;
INS_ALU := R_PLUS_S;
BUS_R := TEMP[4];
BUS_S_SEND := X[3,3];
MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(30) AM325;
(WR_STATUS(CYCLE_CNTR);)
CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
ENF_BAR := LOW;
MUX_R_SELECT := FALSE; MUX_S_SELECT := FALSE;
INS_ALU := R_TIMES_S;
BUS_R := SIN_THETA[I_T34];
BUS_S_SEND := X[1,3];
(31) AM325;
(WR_STATUS(CYCLE_CNTR);)
CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
TEMP[9] := BUS_F;
INS_ALU := R_TIMES_S;
MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(32) AM325;
(WR_STATUS(CYCLE_CNTR);)
CYCLE_CNTR := CYCLE_CNTR + 1;

```

```

(-----)
{OUTSIDE} X[1,2] := TEMP[6];
  ENF_BAR := HIGH;
  INS_ALU := R_MINUS_S;
  BUS_R := TEMP[3];
  BUS_S_SEND := X[2,3];
  MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
{33} AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  ENF_BAR := LOW;
  INS_ALU := R_TIMES_S;
  MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
{34} AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  ENF_BAR := HIGH;
  INS_ALU := R_PLUS_S;
  BUS_R := LINK_PARM_SA[I_T34];
  BUS_S_SEND := X[2,1];
  MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
{35} AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  ENF_BAR := LOW;
  MUX_R_SELECT := FALSE; MUX_S_SELECT := FALSE;
  INS_ALU := R_TIMES_S;
  BUS_R := LINK_PARM_CA[I_T34];
  BUS_S_SEND := X[3,1];
{36} AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  TEMP[10] := BUS_F;
  INS_ALU := R_TIMES_S;
  MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
{37} AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
{OUTSIDE} X[1,3] := TEMP[7];
  ENF_BAR := HIGH;
  INS_ALU := R_PLUS_S;
  BUS_R := LINK_PARM_SA[I_T34];
  BUS_S_SEND := X[2,2];
  MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
{38} AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;

```

```

{-----}
    ENF_BAR := LOW;
    MUX_R_SELECT := FALSE; MUX_S_SELECT := FALSE;
    INS_ALU := R_TIMES_S;
    BUS_R := LINK_PARM_CA[I_T34];
    BUS_S_SEND := X[3,2];
(39) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
{-----}
    X[3,1] := BUS_F;
    INS_ALU := R_TIMES_S;
    MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(40) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
{-----}
(OUTSIDE) X[2,1] := TEMP[8];
    ENF_BAR := HIGH;
    INS_ALU := R_PLUS_S;
    BUS_R := LINK_PARM_SA[I_T34];
    BUS_S_SEND := X[2,3];
    MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(41) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
{-----}
(OUTSIDE)
    IF ( I_T34 > 1) THEN
        IF (LINK_TYPE = REVOLUTE) THEN
            JACOBN_MAT[1,I_T34 - 1] := X[3,1]
        ELSE
            JACOBN_MAT[4,I_T34 - 1] := X[3,1];
    ENF_BAR := LOW;
    MUX_R_SELECT := FALSE; MUX_S_SELECT := FALSE;
    INS_ALU := R_TIMES_S;
    BUS_R := LINK_PARM_CA[I_T34];
    BUS_S_SEND := X[3,3];
(42) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
{-----}
    X[3,2] := BUS_F;
    INS_ALU := R_TIMES_S;
    MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(43) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;

```



```

{-----}
(OUTSIDE) X[2,2] := TEMP[9];
    ENF_BAR := HIGH;
    INS_ALU := R_PLUS_S;
    BUS_R := TEMP[1];
    BUS_S_SEND := X[2,4];
    MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(44) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
{-----}
(OUTSIDE)
    IF ( I_T34 > 1) THEN
        IF (LINK_TYPE = REVOLUTE) THEN
            JACOBN_MAT[2,I_T34 - 1] := X[3,2]
        ELSE
            JACOBN_MAT[5,I_T34 - 1] := X[3,2];
        ENF_BAR := LOW;
        BUS_R := COS_THETA[I_T34];
        BUS_S_SEND := X[1,4];
        MUX_R_SELECT := FALSE; MUX_S_SELECT := FALSE;
        INS_ALU := R_TIMES_S;
(45) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
{-----}
    X[3,3] := BUS_F;
    INS_ALU := R_TIMES_S;
    MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(46) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
{-----}
(OUTSIDE) X[2,3] := TEMP[10];
    ENF_BAR := HIGH;
    INS_ALU := R_MINUS_S;
    BUS_R := TEMP[2];
    BUS_S_SEND := X[3,4];
    MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(47) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;

```

```

(-----)
{OUTSIDE}
  IF ( I_T34 > 1) THEN
    IF (LINK_TYPE = REVOLUTE) THEN
      JACOBN_MAT[3,I_T34 - 1] := X[3,3]
    ELSE
      JACOBN_MAT[6,I_T34 - 1] := X[3,3];
    ENF_BAR := LOW;
    INS_ALU := R_TIMES_S;
    MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(48) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
    ENF_BAR := HIGH;
    INS_ALU := R_PLUS_S;
    BUS_R := COS_THETA[I_T34];
    BUS_S_SEND := LINK_PARM_A[I_T34];
    MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(49) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
    ENF_BAR := LOW;
    INS_ALU := R_TIMES_S;
    MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(50) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
    ENF_BAR := HIGH;
    INS_ALU := R_PLUS_S;
    BUS_R := TEMP[4];
    BUS_S_SEND := X[3,4];
    MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(51) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
    ENF_BAR := LOW;
    MUX_R_SELECT := FALSE; MUX_S_SELECT := FALSE;
    INS_ALU := R_TIMES_S;
    BUS_R := SIN_THETA[I_T34];
    BUS_S_SEND := LINK_PARM_A[I_T34];
(52) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;

```

```

{-----}
    TEMP[1] := BUS_F;
    INS_ALU := R_TIMES_S;
    MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(53) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
{-----}
    ENF_BAR := HIGH;
    INS_ALU := R_MINUS_S;
    BUS_R := SIN_THETA[I_T34];
    BUS_S_SEND := X[1,4];
    MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(54) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
{-----}
    ENF_BAR := LOW;
    INS_ALU := R_TIMES_S;
    MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(55) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
{-----}
    ENF_BAR := HIGH;
    INS_ALU := R_PLUS_S;
    BUS_R := TEMP[3];
    BUS_S_SEND := X[2,4];
    MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(56) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
{-----}
    ENF_BAR := LOW;
    INS_ALU := R_TIMES_S;
    MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(57) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
{-----}
    ENF_BAR := HIGH;
    INS_ALU := R_PLUS_S;
    BUS_R := LINK_PARM_SA[I_T34];
    BUS_S_SEND := X[2,4];
    MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(58) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;

```

```

(-----)
  ENF_BAR := LOW;
  MUX_R_SELECT := FALSE; MUX_S_SELECT := FALSE;
  INS_ALU := R_TIMES_S;
  BUS_R := LINK_PARM_CA[I_T34];
  BUS_S_SEND := X[3,4];
(59) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  X[2,4] := BUS_F;
  INS_ALU := R_TIMES_S;
  MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(60) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
(OUTSIDE) X[1,4] := TEMP[1];
  ENF_BAR := HIGH;
  INS_ALU := R_PLUS_S;
  BUS_R := LINK_PARM_D[I_T34];
  MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(61) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  ENF_BAR := LOW;
  INS_ALU := R_PLUS_S;
  BUS_R := X[2,4];
  BUS_S_SEND := X[1,1];
  MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(62) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  ENF_BAR := LOW;
  MUX_R_SELECT := FALSE; MUX_S_SELECT := FALSE;
  INS_ALU := R_TIMES_S;
  BUS_R := X[1,4];
  BUS_S_SEND := X[2,1];
(63) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  X[3,4] := BUS_F;
  INS_ALU := R_TIMES_S;
  MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(64) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;

```

```

{-----}
{ FOR LINK_0, JUST STOP }
IF ( I_T34 > 1 ) THEN
  BEGIN ( CYCLE_65_73 )
    ENF_BAR := HIGH;
    INS_ALU := R_MINUS_S;
    BUS_R := X[2,4];
    BUS_S_SEND := X[1,2];
    MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(65) AM325;
    (WR_STATUS(CYCLE_CNTR);)
    CYCLE_CNTR := CYCLE_CNTR + 1;
  {-----}
    ENF_BAR := LOW;
    MUX_R_SELECT := FALSE; MUX_S_SELECT := FALSE;
    INS_ALU := R_TIMES_S;
    BUS_R := X[1,4];
    BUS_S_SEND := X[2,2];
(66) AM325;
    (WR_STATUS(CYCLE_CNTR);)
    CYCLE_CNTR := CYCLE_CNTR + 1;
  {-----}
    JACOBN_MAT[4,I_T34 - 1] := BUS_F;
    INS_ALU := R_TIMES_S;
    MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(67) AM325;
    (WR_STATUS(CYCLE_CNTR);)
    CYCLE_CNTR := CYCLE_CNTR + 1;
  {-----}
    ENF_BAR := HIGH;
    INS_ALU := R_MINUS_S;
    BUS_R := X[2,4];
    BUS_S_SEND := X[1,3];
    MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(68) AM325;
    (WR_STATUS(CYCLE_CNTR);)
    CYCLE_CNTR := CYCLE_CNTR + 1;
  {-----}
    ENF_BAR := LOW;
    MUX_R_SELECT := FALSE; MUX_S_SELECT := FALSE;
    INS_ALU := R_TIMES_S;
    BUS_R := X[1,4];
    BUS_S_SEND := X[2,3];
(69) AM325;
    (WR_STATUS(CYCLE_CNTR);)
    CYCLE_CNTR := CYCLE_CNTR + 1;

```

```

(-----)
  JACOBN_MAT[5,I_T34 - 1] := BUS_F;
  INS_ALU := R_TIMES_S;
  MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(70) AM325;
  (WR_STATUS(CYCLE_CNTR);)
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  ENF_BAR := HIGH;
  INS_ALU := R_MINUS_S;
  BUS_R := 0.0;
  BUS_S_SEND := 0.0;
  MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(71) AM325;
  (WR_STATUS(CYCLE_CNTR);)
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  ENF_BAR := LOW;
  MUX_R_SELECT := FALSE; MUX_S_SELECT := FALSE;
  INS_ALU := NOP;
(72) AM325;
  (WR_STATUS(CYCLE_CNTR);)
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  JACOBN_MAT[6,I_T34 - 1] := BUS_F;
(73)
  (WR_STATUS(CYCLE_CNTR);)
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  END; { CYCLE_65_73 }
  END; { R_FILE }
  END; { CONTROL }
END; { T34 }

[GLOBAL]PROCEDURE KIN_JAC;
VAR
  TST: REAL;
BEGIN
  { X := E; }
  WITH R_FILE DO
    X := E;
    CYCLE_CNTR := CYCLE_CNTR + 12;
  { IF IT CAN BE DONE IN PARALLEL WITH AM325 IN ANOTHER }
  { PROCEDURE THAN CYCLE_CNTR SHOULD BE INITIALISED TO 0 }
  (WRITELN(OUTPUT,'N= ',N);)

```

```

( FOR LINK #0 SIN_COS SHOULD BE DONE IN THE INITIALIZATION )
FOR I_KIN := 2 TO N+1 DO
  BEGIN
    WITH R_FILE DO
      BEGIN
        SIN_COS (ANGLE_RAD[I_KIN], SIN_THETA[I_KIN], COS_THETA[I_KIN]);
      END;
    END;
  FOR I_KIN := N + 1 DOWNT0 1 DO
    BEGIN
      {WRITELN(OUTPUT, ' CYCLE_CNTR = ', CYCLE_CNTR);}
      T34_TIMES_T34(I_KIN);
      {WRITE_X;}
      {WRITE_JAC;}
    END;
  END;
END.

```

```

[OVERLAID]MODULE PSEUDO_INV( INPUT, OUTPUT );

(***** FILE: PSEUDO_INV.PAS *****)

(*****)
(*      PROGRAM: PSEUDO_INV.PAS      *)
(*****)

(*****)
(*                                     *)
(* PROGRAMMER: Yusheng Tsai           *)
(* DATE:      September 4, 1985       *)
(*                                     *)
(* FUNCTION:   Simulate the operation of PSEUDO INVERSE *)
(*             on the 32-bit floating point processor: AM29325 *)
(*                                     *)
(* USER GUIDE: THE CALLING FORMAT IS: *)
(*             PSEUDO_INV;             *)
(*                                     *)
(* PROGRAMMER *)
(* GUIDE:      $ PAS PSEUDO_INV        *)
(*             *** It is not a main program. *** *)
(*                                     *)
(* PROCEDURES *)
(* CALLED:     AM325,SUB_REC            *)
(*                                     *)
(* FUNCTIONS  *)
(* CALLED:     NONE                    *)
(*                                     *)
(* GLOBAL VARIABLES      CONTROL, BUS_R, BUS_S *)
(* REFERENCED:           *)
(*                                     *)
(* GLOBAL VARIABLES      BUS_F *)
(* MODIFIED:             *)
(*****)

%INCLUDE 'GLOBAL.PAS'

[EXTERNAL]PROCEDURE AM325; EXTERNAL;
[EXTERNAL]PROCEDURE SUB_REC(IN_DATA:REAL); EXTERNAL;
[EXTERNAL]PROCEDURE WRITE_JAC; EXTERNAL;

```



```

PROCEDURE WRITE_S(IN_MAT66 : SQUARE_MAT_66);
VAR
  I_S, J_S : INTEGER;
BEGIN
  WRITELN(OUTPUT, ' MATRIX IS:');
  FOR I_S := 1 TO 6 DO
    BEGIN
      FOR J_S := 1 TO 6 DO
        WITH R_FILE DO
          WRITE(OUTPUT, S[I_S, J_S]);
          WRITELN(OUTPUT);
        END;
      END;
    END;

[GLOBAL]PROCEDURE WRITE_VEC(VECTOR : ARRAY7; NO : INTEGER);
VAR
  I_S, J_S : INTEGER;
BEGIN
  FOR I_S := 1 TO NO DO
    WRITE(OUTPUT, VECTOR[I_S]);
    WRITELN(OUTPUT);
  END;

PROCEDURE WR_STATUS(CYCLE:INTEGER);
BEGIN
  WRITELN(OUTPUT, ' CYCLE ', CYCLE:4, ' :');
  WRITELN(OUTPUT, ' REG_R= ', REG_R:14:8, ' REG_S= ', REG_S:14:8,
    ' REG_F= ', REG_F:14:8);
  WRITELN(OUTPUT, ' MUX_A= ', MUX_A:14:8, ' MUX_R= ',
    MUX_R:14:8, ' MUX_S= ', MUX_S:14:8);
  WRITELN(OUTPUT, ' ALU_R= ', ALU_R:14:8, ' ALU_S= ',
    ALU_S:14:8, ' ALU_F= ', ALU_F:14:8);
  WRITELN(OUTPUT, ' BUS_R= ', BUS_R:14:8, ' BUS_S= ',
    BUS_S_END:14:8, ' BUS_F= ', BUS_F:14:8);
END;

[GLOBAL]PROCEDURE JT_MUL_J( VAR SS : SQUARE_MAT_66 );
VAR
  I_JT, J_JT, K_JT : INTEGER;
BEGIN { JT_MUL_J }
  WITH CONTROL DO
    BEGIN { CONTROL }
    WITH R_FILE DO
      BEGIN { R_FILE }

```

```

(-----)
  ENR_BAR := LOW; ENS_BAR := LOW; ENF_BAR := LOW;
  FT0 := LOW; FT1 := LOW; OUT_EN := HIGH;
  MUX_A_SELECT := FALSE; MUX_R_SELECT := FALSE;
  MUX_S_SELECT := FALSE; SEED_SELECT := NONE;
  BUS_R := JACOBN_MAT[1,1];
  BUS_S_SEND := JACOBN_MAT[1,1];
  INS_ALU := NOP;
(1) AM325;
  (WR_STATUS(CYCLE_CNTR);)
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  FOR I_JT := 1 TO N DO
  BEGIN ( I_JT )
(-----)
    FOR J_JT := 1 TO 1 DO
    BEGIN ( J_JT )
(-----)
      ENF_BAR := LOW;
      MUX_R_SELECT := FALSE; MUX_S_SELECT := FALSE;
      INS_ALU := R_TIMES_S;
      BUS_R := JACOBN_MAT[2,I_JT];
      BUS_S_SEND := JACOBN_MAT[2,J_JT];
(2) AM325;
      (WR_STATUS(CYCLE_CNTR);)
      CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
      FOR K_JT := 3 TO 6 DO
      BEGIN ( K_JT )
(-----)
        ENF_BAR := LOW;
(OUTSIDE) IF (( I_JT <> 1 ) AND ( K_JT = 3 )) THEN
        BEGIN
          S[I_JT-1,N] := BUS_F;
        END;
        INS_ALU := R_TIMES_S;
        MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(3) AM325;
        (WR_STATUS(CYCLE_CNTR);)
        CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
        ENF_BAR := HIGH;
        INS_ALU := R_PLUS_S;
        BUS_R := JACOBN_MAT[K_JT,I_JT];
        BUS_S_SEND := JACOBN_MAT[K_JT,J_JT];
        MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(4) AM325;
        (WR_STATUS(CYCLE_CNTR);)
        CYCLE_CNTR := CYCLE_CNTR + 1;

```

```

(-----)
END; { K_JT }
(-----)
ENF_BAR := LOW;
INS_ALU := R_TIMES_S;
MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(5) AM325;
{WR_STATUS(CYCLE_CNTR);}
CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
ENF_BAR := HIGH;
INS_ALU := R_PLUS_S;
BUS_R := JACOBN_MAT[1,I_JT];
BUS_S_SEND := JACOBN_MAT[1,J_JT + 1];
MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(6) AM325;
{WR_STATUS(CYCLE_CNTR);}
CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
END; { J_JT }
(-----)
FOR J_JT := 2 TO N DO
BEGIN { J_JT }
(-----)
ENF_BAR := LOW;
MUX_R_SELECT := FALSE; MUX_S_SELECT := FALSE;
INS_ALU := R_TIMES_S;
BUS_R := JACOBN_MAT[2,I_JT];
BUS_S_SEND := JACOBN_MAT[2,J_JT];
(7) AM325;
{WR_STATUS(CYCLE_CNTR);}
CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
FOR K_JT := 3 TO 6 DO
BEGIN { K_JT }
(-----)
(OUTSIDE) IF ( K_JT = 3 ) THEN
BEGIN
S[I_JT,J_JT-1] := BUS_F;

END;
ENF_BAR := LOW;
INS_ALU := R_TIMES_S;
MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(8) AM325;
{WR_STATUS(CYCLE_CNTR);}
CYCLE_CNTR := CYCLE_CNTR + 1;

```

```

(-----)
  ENF_BAR := HIGH;
  INS_ALU := R_PLUS_S;
  BUS_R := JACOBN_MAT[K_JT,I_JT];
  BUS_S_SEND := JACOBN_MAT[K_JT,J_JT];
  MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(9) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
END; ( K_JT )
(-----)
  ENF_BAR := LOW;
  INS_ALU := R_TIMES_S;
  MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(5) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  ENF_BAR := HIGH;
  INS_ALU := R_PLUS_S;
  IF ( J_JT = N ) THEN
  BEGIN
    IF ( I_JT < N ) THEN
      begin
        BUS_R := JACOBN_MAT[1,I_JT+1];
        BUS_S_SEND := JACOBN_MAT[1,1]
      END
    ELSE
      BEGIN
        BUS_R := 0.0; BUS_S_SEND := 0.0;
      END;
    END
  ELSE
    BEGIN
      BUS_R := JACOBN_MAT[1,I_JT];
      BUS_S_SEND := JACOBN_MAT[1,J_JT+1];
    END;
  MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(6) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
END; ( J_JT )

```

```

(-----)
END; ( I_JT )
MUX_R_SELECT := FALSE; MUX_S_SELECT := FALSE;
BUS_R := 0.0; BUS_S_SEND := 0.0;
ENF_BAR := LOW;
OUT_EN := HIGH;
INS_ALU := NOP;
AM325;
(WR_STATUS(CYCLE_CNTR);)
CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
(OUTSIDE) S[N,N] := BUS_F;
(WR_STATUS(CYCLE_CNTR);)
CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
(TEST) (WRITELN(OUTPUT, '----- END OF JT_MUL_J -----')));
END; ( R_FILE )
END; ( CONTROL )
END; ( JT_MUL_J )

[GLOBAL]PROCEDURE J_MUL_JT( VAR SS : SQUARE_MAT_66 );
VAR
  I_JT, J_JT, K_JT : INTEGER;
BEGIN ( J_MUL_JT )
  WITH CONTROL DO
    BEGIN ( CONTROL )
      WITH R_FILE DO
        BEGIN ( R_FILE )
          (-----)
          ENR_BAR := LOW; ENS_BAR := LOW; ENF_BAR := LOW;
          FT0 := LOW; FT1 := LOW; OUT_EN := HIGH;
          MUX_A_SELECT := FALSE; MUX_R_SELECT := FALSE;
          MUX_S_SELECT := FALSE; SEED_SELECT := NONE;
          BUS_R := JACOBN_MAT[1,1];
          BUS_S_SEND := JACOBN_MAT[1,1];
          INS_ALU := NOP;
        (1) AM325;
          (WR_STATUS(CYCLE_CNTR);)
          CYCLE_CNTR := CYCLE_CNTR + 1;
        (-----)
        FOR I_JT := 1 TO N DO
          BEGIN ( I_JT )
            (-----)
            FOR J_JT := 1 TO 1 DO
              BEGIN ( J_JT )

```

```

(-----)
    ENF_BAR := LOW;
    MUX_R_SELECT := FALSE; MUX_S_SELECT := FALSE;
    INS_ALU := R_TIMES_S;
    BUS_R := JACOBN_MAT[I_JT,2];
    BUS_S_SEND := JACOBN_MAT[J_JT,2];
(2) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
    FOR K_JT := 3 TO 6 DO
        BEGIN ( K_JT )
(-----)
            ENF_BAR := LOW;
(OUTSIDE) IF (( I_JT <> 1 ) AND ( K_JT = 3 )) THEN
                S[I_JT-1,N] := BUS_F;
            INS_ALU := R_TIMES_S;
            MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(3) AM325;
            {WR_STATUS(CYCLE_CNTR);}
            CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
            ENF_BAR := HIGH;
            INS_ALU := R_PLUS_S;
            BUS_R := JACOBN_MAT[I_JT,K_JT];
            BUS_S_SEND := JACOBN_MAT[J_JT,K_JT];
            MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(4)AM325;
            {WR_STATUS(CYCLE_CNTR);}
            CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
            END; ( K_JT )
(-----)
            ENF_BAR := LOW;
            INS_ALU := R_TIMES_S;
            MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(5) AM325;
            {WR_STATUS(CYCLE_CNTR);}
            CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
            ENF_BAR := HIGH;
            INS_ALU := R_PLUS_S;
            BUS_R := JACOBN_MAT[I_JT,1];
            BUS_S_SEND := JACOBN_MAT[J_JT+1,1];
            MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(6) AM325;
            {WR_STATUS(CYCLE_CNTR);}
            CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
            END; ( J_JT )

```

```

(-----)
FOR J_JT := 2 TO 6 DO
  BEGIN { J_JT }
(-----)
  ENF_BAR := LOW;
  MUX_R_SELECT := FALSE; MUX_S_SELECT := FALSE;
  INS_ALU := R_TIMES_S;
  BUS_R := JACOBN_MAT[I_JT,2];
  BUS_S_SEND := JACOBN_MAT[J_JT,2];
(7) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  FOR K_JT := 3 TO 6 DO
    BEGIN { K_JT }
(-----)
    {OUTSIDE} IF ( K_JT = 3 ) THEN S[J_JT-1,I_JT] := BUS_F;
    ENF_BAR := LOW;
    INS_ALU := R_TIMES_S;
    MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(8) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
    ENF_BAR := HIGH;
    INS_ALU := R_PLUS_S;
    BUS_R := JACOBN_MAT[I_JT,K_JT];
    BUS_S_SEND := JACOBN_MAT[J_JT,K_JT];
    MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(9)AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
    END; { K_JT }
(-----)
    ENF_BAR := LOW;
    INS_ALU := R_TIMES_S;
    MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(5) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;

```

```

(-----)
ENF_BAR := HIGH;
INS_ALU := R_PLUS_S;
IF ( J_JT = N ) THEN
BEGIN
    IF ( I_JT < N ) THEN
        begin
            BUS_R := JACOBN_MAT[I_JT+1,1];
            BUS_S_SEND := JACOBN_MAT[1,1]
        END
    ELSE
    BEGIN
        BUS_R := 0.0; BUS_S_SEND := 0.0;
    END;
END
ELSE
BEGIN
    BUS_R := JACOBN_MAT[I_JT,1];
    BUS_S_SEND := JACOBN_MAT[J_JT+1,1];
END;
MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(6) AM325;
{WR_STATUS(CYCLE_CNTR);}
CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
END; ( J_JT )
(-----)
END; ( I_JT )
MUX_R_SELECT := FALSE; MUX_S_SELECT := FALSE;
BUS_R := 0.0; BUS_S_SEND := 0.0;
ENF_BAR := LOW;
OUT_EN := HIGH;
INS_ALU := NOP;
AM325;
{WR_STATUS(CYCLE_CNTR);}
CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
(OUTSIDE) S[N,N] := BUS_F;
{WR_STATUS(CYCLE_CNTR);}
CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)

END; ( R_FILE )
END; ( CONTROL )
END; ( JT_MUL_J )

```



```

[GLOBAL]PROCEDURE JT_MUL_V61(      VECT61 : ARRAY7;
                                VAR  VECTN1 : ARRAY7) ;

VAR
  I_JT,K_JT : INTEGER;
BEGIN { V61 }
  WITH CONTROL DO
    BEGIN { CONTROL }
    WITH R_FILE DO
      BEGIN { R_FILE }
      (-----)
      ENR_BAR := LOW; ENS_BAR := LOW; ENF_BAR := LOW;
      FTO := LOW; FT1 := LOW; OUT_EN := HIGH;
      MUX_A_SELECT := FALSE; MUX_R_SELECT := FALSE;
      MUX_S_SELECT := FALSE; SEED_SELECT := NONE;
      BUS_R := JACOBN_MAT[1,1];
      BUS_S_SEND := VECT61[1];
      INS_ALU := NOP;
(1) AM325;
      {WR_STATUS(CYCLE_CNTR);}
      CYCLE_CNTR := CYCLE_CNTR + 1;
      (-----)
      FOR I_JT := 1 TO N DO
      BEGIN { I_JT }
      (-----)
        ENF_BAR := LOW;
        MUX_R_SELECT := FALSE; MUX_S_SELECT := FALSE;
        INS_ALU := R_TIMES_S;
        BUS_R := JACOBN_MAT[2,I_JT];
        BUS_S_SEND := VECT61[2];
(2) AM325;
        {WR_STATUS(CYCLE_CNTR);}
        CYCLE_CNTR := CYCLE_CNTR + 1;
      (-----)
      FOR K_JT := 2 TO 6 DO
      BEGIN { K_JT }
      (-----)
      (OUTSIDE) IF ( I_JT <> 1 ) AND ( K_JT = 2 )
        THEN VECTN1[I_JT-1] := BUS_F;
        ENF_BAR := LOW;
        INS_ALU := R_TIMES_S;
        MUX_R_SELECT := TRUE; MUX_S_SELECT := FALSE;
(3) AM325;
        {WR_STATUS(CYCLE_CNTR);}
        CYCLE_CNTR := CYCLE_CNTR + 1;

```

```

(-----)
    ENF_BAR := HIGH;
    INS_ALU := R_PLUS_S;
    IF ( K_JT < 6 ) THEN
    BEGIN
        BUS_R := JACOBN_MAT[K_JT+1,I_JT];
        BUS_S_SEND := VECT61[K_JT+1];
    END
    ELSE
    BEGIN
        BUS_R := JACOBN_MAT[1,I_JT+1];
        BUS_S_SEND := VECT61[1];
    END;
    MUX_R_SELECT := FALSE; MUX_S_SELECT := TRUE;
(4)AM325;
    (WR_STATUS(CYCLE_CNTR));
    CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
    END; { K_JT }
(-----)
    END; { I_JT }
(-----)
    ENF_BAR := LOW;
    INS_ALU := NOP;
    MUX_R_SELECT := FALSE; MUX_S_SELECT := FALSE;
(5) AM325;
    (WR_STATUS(CYCLE_CNTR));
    CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
(OUTSIDE)    VECTN1[N] := BUS_F;
(6)
    CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
    END; { R_FILE }
    END; { CONTROL }
END; { V61 }

[GLOBAL]PROCEDURE GAUSSIAN_ELI(VAR R_G : SQUARE_MAT_66;
                                VAR RESULT : ARRAY7;
                                VAR B_G : ARRAY7;
                                VAR SINGULARITY_G : BOOLEAN );
CONST
    EPSILON = 1.0E-6;
VAR
    TEMPO: REAL;
    I_TEMPO:INTEGER;
    I_TEMP : ARRAY [1..9] OF INTEGER;
    I,J,ROW_CNTR,NO_OF_COLUMN : INTEGER;
    I_REAL,ROW_CNTR_REAL,DIFFERENCE : REAL;

```

```

PROCEDURE PIVOT_ROW_SEARCH_SWAP;
BEGIN
  WITH CONTROL DO
    BEGIN ( CONTROL )
      WITH R_FILE DO
        BEGIN ( R_FILE )
          (OUTSIDE)
            TEMP[8] := R_G[ROW_CNTR,ROW_CNTR]; { LARGEST NUMBER }
            {WR_STATUS(CYCLE_CNTR);}
            CYCLE_CNTR := CYCLE_CNTR + 1;
            {-----}
            ROW_CNTR_REAL := ROW_CNTR;
          (OUTSIDE) TEMP[9] := ROW_CNTR_REAL; { LARGEST ROW NUMBER }
            I_TEMP[9] := ROW_CNTR;
            {WR_STATUS(CYCLE_CNTR);}
            CYCLE_CNTR := CYCLE_CNTR + 1;
            {-----}
            {PIVOT_ROW_SEARCH_SWAP BEGIN}
            FOR I := ROW_CNTR+1 TO NO_OF_COLUMN DO
              (SEARCH)BEGIN
                ENR_BAR := LOW; ENS_BAR := LOW; ENF_BAR := LOW;
                FTO := LOW; FT1 := LOW; OUT_EN := HIGH;
                MUX_A_SELECT := FALSE; MUX_R_SELECT := FALSE;
                MUX_S_SELECT := FALSE; SEED_SELECT := NONE;
                { HARDWARE SUPPORT TO GET THE ABSOLUTE VALUES BY INSERTING }
                { ZERO - LOW TO THE SIGN BIT }
                BUS_R := ABS(TEMP[8]);
                BUS_S_SEND := ABS(R_G[I_TEMP[I],ROW_CNTR]);
                INS_ALU := NOP;
              (1) AM325;
                {WR_STATUS(CYCLE_CNTR);}
                CYCLE_CNTR := CYCLE_CNTR + 1;
                {-----}
                INS_ALU := R_MINUS_S;
              (2) AM325;
                {WR_STATUS(CYCLE_CNTR);}
                CYCLE_CNTR := CYCLE_CNTR + 1;
                {-----}
                INS_ALU := NOP;
              (3) AM325;
                {WR_STATUS(CYCLE_CNTR);}
                CYCLE_CNTR := CYCLE_CNTR + 1;
              { GET THE DIFFERENCE }
              {-----}
              { CHECK THE SIGN BIT OF REG_F OR BUS_F }
              (4) IF ( REG_F < 0 ) THEN
                (OUTSIDE) BEGIN I_TEMP[9] := I; TEMP[9] := I; END;
              { WR_STATUS(CYCLE_CNTR);}
              CYCLE_CNTR := CYCLE_CNTR + 1;
            END;
          END;
        END;
      END;
    END;
  END;

```

```

(-----)
(5) IF ( REG_F < 0 ) THEN
  (OUTSIDE) TEMP[8] := R_G[I_TEMP[I],ROW_CNTR];
  (WR_STATUS(CYCLE_CNTR);)
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
(SEARCH)END;
(SWAP BEGIN)
  ROW_CNTR_REAL := ROW_CNTR; (ACTURALLY SAME)
  ENR_BAR := LOW; ENS_BAR := LOW; ENF_BAR := LOW;
  FT0 := LOW; FT1 := LOW; OUT_EN := HIGH;
  MUX_A_SELECT := FALSE; MUX_R_SELECT := FALSE;
  MUX_S_SELECT := FALSE; SEED_SELECT := NONE;
  BUS_R := TEMP[9];
  BUS_S_SEND := ROW_CNTR_REAL;
  INS_ALU := NOP;
(1) AM325;
  (WR_STATUS(CYCLE_CNTR);)
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  INS_ALU := R_MINUS_S;
(2) AM325;
  (WR_STATUS(CYCLE_CNTR);)
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  INS_ALU := NOP;
(3) AM325;
  (WR_STATUS(CYCLE_CNTR);)
  CYCLE_CNTR := CYCLE_CNTR + 1;
( GET THE DIFFERENCE )
(-----)
( CHECK THE ZERO STATUS OF THE OUTPUT DIFFERENCE )
(4) IF ( REG_F <> 0 ) THEN
  BEGIN
    (OUTSIDE) I_TEMPO := I_TEMP[I_TEMP[9]];
    (OUTSIDE) TEMPO := TEMP[I_TEMP[9]];
    END;
    (WR_STATUS(CYCLE_CNTR);)
    CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
(5) IF ( REG_F <> 0 ) THEN
  BEGIN
    (OUTSIDE) I_TEMP[I_TEMP[9]] := I_TEMP[ROW_CNTR];
    (OUTSIDE) TEMP[I_TEMP[9]] := TEMP[ROW_CNTR];
    END;
    (WR_STATUS(CYCLE_CNTR);)
    CYCLE_CNTR := CYCLE_CNTR + 1;

```

```

(-----)
(6) IF ( REG_F <> 0 ) THEN
    BEGIN
        {OUTSIDE} I_TEMP[ROW_CNTR] := I_TEMPO;
        {OUTSIDE} TEMP[ROW_CNTR] := TEMPO;
        END;
        {WR_STATUS(CYCLE_CNTR);}
        CYCLE_CNTR := CYCLE_CNTR + 1;
    (-----)

    ( CHECK FOR SINGULARITY )
        ENR_BAR := LOW; ENS_BAR := LOW; ENF_BAR := LOW;
        FTO := LOW; FT1 := LOW; OUT_EN := HIGH;
        MUX_A_SELECT := FALSE; MUX_R_SELECT := FALSE;
        MUX_S_SELECT := FALSE; SEED_SELECT := NONE;
    { HARDWARE SUPPORT TO GET THE ABSOLUTE VALUES BY INSERTING }
    { ZERO - LOW TO THE SIGN BIT }
        BUS_R := ABS(R_G[I_TEMP[ROW_CNTR],ROW_CNTR]);
        BUS_S_SEND := EPSILON;
        INS_ALU := NOP;
    (1) AM325;
        {WR_STATUS(CYCLE_CNTR);}
        CYCLE_CNTR := CYCLE_CNTR + 1;
    (-----)
        INS_ALU := R_MINUS_S;
    (2) AM325;
        {WR_STATUS(CYCLE_CNTR);}
        CYCLE_CNTR := CYCLE_CNTR + 1;
    (-----)
        INS_ALU := NOP;
    (3) AM325;
        {WR_STATUS(CYCLE_CNTR);}
        CYCLE_CNTR := CYCLE_CNTR + 1;
    { GET THE DIFFERENCE }
    (-----)
    { CHECK THE SIGN BIT OF REG_F OR BUS_F }
    (4) IF ( REG_F < 0 ) THEN
        {OUTSIDE} SINGULARITY_G := TRUE
        ELSE SINGULARITY_G := FALSE;
        {WR_STATUS(CYCLE_CNTR);}
        CYCLE_CNTR := CYCLE_CNTR + 1;
    (-----)
        END; ( R_FILE )
        END; ( CONTROL )
    END;
    {PIVOT_ROW_SEARCH_SWAP END}
    {*****}

```

```

PROCEDURE REDUCE;
BEGIN
  WITH CONTROL DO
    BEGIN { CONTROL }
    WITH R_FILE DO
      BEGIN { R_FILE }
      {FIND RECIPROCAL OF PIVOT ROW ELEMENT}
      SUB_REC(R_G[I_TEMP[ROW_CNTR],ROW_CNTR]);
      { WR_STATUS(CYCLE_CNTR); }
      {-----}
      RECIP[ROW_CNTR] := REC;
      {FIND ALL THE RATIOS}
      ENR_BAR := LOW; ENS_BAR := LOW; ENF_BAR := LOW;
      FT0 := LOW; FT1 := LOW; OUT_EN := HIGH;
      MUX_A_SELECT := FALSE; SEED_SELECT := NONE;
      MUX_S_SELECT := FALSE; MUX_R_SELECT := FALSE;
      BUS_R := R_G[I_TEMP[ROW_CNTR+1],ROW_CNTR];
      BUS_S_SEND := RECIP[ROW_CNTR];
      INS_ALU := NOP;
      (1) AM325;
      {WR_STATUS(CYCLE_CNTR); }
      CYCLE_CNTR := CYCLE_CNTR + 1;
      {-----}
      FOR J := (ROW_CNTR + 1) TO NO_OF_COLUMN DO
      (J) BEGIN
        I := ROW_CNTR + 1;
        WHILE ( I <= NO_OF_COLUMN ) DO
          BEGIN
            {-----}
            MUX_S_SELECT := FALSE; MUX_R_SELECT := FALSE;
            INS_ALU := R_TIMES_S;
            BUS_R := R_G[I_TEMP[ROW_CNTR],J];
            (2) AM325;
            {WR_STATUS(CYCLE_CNTR); }
            CYCLE_CNTR := CYCLE_CNTR + 1;
            {-----}
            IF ( I > ROW_CNTR + 1)
              THEN R_G[I_TEMP[I-1],J] := BUS_F;
            IF ((I = ROW_CNTR + 1) AND ( J > (ROW_CNTR+1)))
              THEN R_G[I_TEMP[NO_OF_COLUMN],J-1] := BUS_F;
            INS_ALU := R_TIMES_S;
            BUS_R := R_G[I_TEMP[I],J];
            MUX_S_SELECT := TRUE; MUX_R_SELECT := FALSE;
            (3) AM325;
            {WR_STATUS(CYCLE_CNTR); }
            CYCLE_CNTR := CYCLE_CNTR + 1;

```

```

{-----}
  I := I + 1;
  MUX_S_SELECT := TRUE; MUX_R_SELECT := FALSE;
  INS_ALU := R_MINUS_S;
  IF ( I <= NO_OF_COLUMN ) THEN
    BUS_R := R_G[I_TEMP[I],ROW_CNTR]
  ELSE
    BUS_R := R_G[I_TEMP[ROW_CNTR+1],ROW_CNTR];
  BUS_S_SEND := RECIP[ROW_CNTR];
(4) AM325;
  ( WR_STATUS(CYCLE_CNTR); )
  CYCLE_CNTR := CYCLE_CNTR + 1;
  END; (WHILE)
{-----}
(J) END;
{-----}
  I := ROW_CNTR + 1;
  WHILE ( I <= NO_OF_COLUMN ) DO
  BEGIN
    {-----}
    MUX_S_SELECT := FALSE; MUX_R_SELECT := FALSE;
    INS_ALU := R_TIMES_S;
    BUS_R := B_G[I_TEMP[ROW_CNTR]];
(5) AM325;
    (WR_STATUS(CYCLE_CNTR); )
    CYCLE_CNTR := CYCLE_CNTR + 1;
    {-----}
    IF ( I = ROW_CNTR + 1 ) THEN
      R_G[NO_OF_COLUMN,NO_OF_COLUMN] := BUS_F;
    IF ( I > ROW_CNTR + 1 )
      THEN B_G[I_TEMP[I-1]] := BUS_F;
    INS_ALU := R_TIMES_S;
    BUS_R := B_G[I_TEMP[I]];
    MUX_S_SELECT := TRUE; MUX_R_SELECT := FALSE;
(6) AM325;
    (WR_STATUS(CYCLE_CNTR); )
    CYCLE_CNTR := CYCLE_CNTR + 1;
    {-----}
    I := I + 1;
    MUX_S_SELECT := TRUE; MUX_R_SELECT := FALSE;
    INS_ALU := R_MINUS_S;
    IF ( I <= NO_OF_COLUMN ) THEN
      BUS_R := R_G[I_TEMP[I],ROW_CNTR]
    ELSE
      BUS_R := 0.0;
    BUS_S_SEND := RECIP[ROW_CNTR];
(7) AM325;
    (WR_STATUS(CYCLE_CNTR); )
    CYCLE_CNTR := CYCLE_CNTR + 1;

```

```

(-----)
END; (WHILE)
(-----)
MUX_S_SELECT := FALSE; MUX_R_SELECT := FALSE;
BUS_S_SEND := 0.0;
INS_ALU := NOP;
(8) AM325;
{WR_STATUS(CYCLE_CNTR);}
CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
B_G[I_TEMP[NO_OF_COLUMN]] := BUS_F;
(9)
{WR_STATUS(CYCLE_CNTR);}
CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
{WRITELN(OUTPUT, ' B_G = ');
WRITE_VEC(B_G,N);}
(TEST) {WRITE_S(R_G);}
END; { R_FILE }
END; { CONTROL }
END;
(*****
PROCEDURE BACK_SUBSTITUTE;
BEGIN
WITH R_FILE DO
BEGIN { R_FILE }
(-----)
{RESULT[NO_OF_COLUMN] := RESULT[NO_OF_COLUMN]*RECIP}
(FIND RECIPROCAL)
{WRITELN(OUTPUT, 'NO_OF_COLUMN= ',NO_OF_COLUMN);}
SUB_REC(R_G[I_TEMP[NO_OF_COLUMN],NO_OF_COLUMN]);
END; { R_FILE }
{WR_STATUS(CYCLE_CNTR);}
(-----)
WITH CONTROL DO
BEGIN { CONTROL }
WITH R_FILE DO
BEGIN { R_FILE }
ENR_BAR := LOW; ENS_BAR := LOW; ENF_BAR := LOW;
FT0 := LOW; FT1 := LOW; OUT_EN := HIGH;
MUX_A_SELECT := FALSE; SEED_SELECT := NONE;
MUX_S_SELECT := FALSE; MUX_R_SELECT := FALSE;
BUS_R := B_G[I_TEMP[NO_OF_COLUMN]];
BUS_S_SEND := REC;
INS_ALU := NOP;
(1) AM325;
{WR_STATUS(CYCLE_CNTR);}
CYCLE_CNTR := CYCLE_CNTR + 1;

```



```

{-----}
  INS_ALU := R_TIMES_S;
(2) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
{-----}
  INS_ALU := NOP;
(3) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
{-----}
  RESULT[NO_OF_COLUMN] := BUS_F;
(4)
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
{-----}
  FOR J := (NO_OF_COLUMN - 1) DOWNT0 1 DO
  (J)BEGIN
    ENR_BAR := LOW; ENS_BAR := LOW; ENF_BAR := LOW;
    FTO := LOW; FT1 := LOW; OUT_EN := HIGH;
    MUX_A_SELECT := FALSE; SEED_SELECT := NONE;
    MUX_S_SELECT := FALSE; MUX_R_SELECT := FALSE;
    BUS_R := R_G[I_TEMP[J],J+1];
    BUS_S_SEND := RESULT[J+1];
    INS_ALU := NOP;
  (1) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
  {-----}
  FOR I := J DOWNT0 1 DO
  BEGIN(I)
    MUX_S_SELECT := FALSE; MUX_R_SELECT := FALSE;
    BUS_R := B_G[I_TEMP[I]];
    INS_ALU := R_TIMES_S;
  (2) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
  {-----}
    IF ( I<J ) THEN B_G[i_temp[I+1]] := BUS_F;
    BUS_R := RECIP[J];
    INS_ALU := R_MINUS_S;
    MUX_S_SELECT := TRUE; MUX_R_SELECT := FALSE;
    IF (I>1) THEN BEGIN
      BUS_R := R_G[I_TEMP[I-1],J+1];
      BUS_S_SEND := RESULT[J+1];
    END ELSE BEGIN
      BUS_R := 0.0;
      BUS_S_SEND := 0.0; END;
  (3) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;

```

```

(-----)
END; {I}
(-----)
    MUX_S_SELECT := FALSE; MUX_R_SELECT := FALSE;
    INS_ALU := NOP;
(4) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
    B_G[i_temp[1]] := BUS_F;
    MUX_S_SELECT := FALSE; MUX_R_SELECT := FALSE;
(5)
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
    MUX_S_SELECT := FALSE; MUX_R_SELECT := FALSE;
    BUS_R := B_G[i_temp[J]];
    BUS_S_SEND := RECIP[J];
    INS_ALU := NOP;
(6) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
    INS_ALU := R_TIMES_S;
(7) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
    INS_ALU := NOP;
(8) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
    RESULT[J] := BUS_F;
(9)
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
(J)END;
    END; { R_FILE }
    END; { CONTROL }
END;
{*****}
BEGIN(GAUSS)
    WITH CONTROL DO
        BEGIN { CONTROL }
    WITH R_FILE DO
        BEGIN { R_FILE }

```

```

(-----)
{ CAN BE DONE IN THE INITIALIZATION }
IF (N < 6) THEN NO_OF_COLUMN := N
      ELSE NO_OF_COLUMN := 6;
{ CAN BE DONE IN THE INITIALIZATION }
(-----)
{ INITIALIZE THE INDEX ARRAY }
FOR I := 1 TO N DO
  BEGIN I_TEMP[I] := I; TEMP[I] := I; END;
  {WR_STATUS(CYCLE_CNTR);}
  ROW_CNTR := 1;
(-----)
Repeat
  WRITELN(OUTPUT,'BEGIN SEARCH CYCLE_CNTR= ',CYCLE_CNTR);
  PIVOT_ROW_SEARCH_SWAP;
  WRITELN(OUTPUT,'END ROW_SWAPS CYCLE_CNTR= ',CYCLE_CNTR);
  IF (NOT SINGULARITY_G) THEN
    BEGIN
      WRITELN(OUTPUT,'BEGIN REDUCE CYCLE_CNTR= ',CYCLE_CNTR);
      REDUCE;
      WRITELN(OUTPUT,'END REDUCE CYCLE_CNTR= ',CYCLE_CNTR);
      END;
      ROW_CNTR := ROW_CNTR + 1;
    Until ( ( ROW_CNTR = (NO_OF_COLUMN) ) OR SINGULARITY_G);
    IF (NOT SINGULARITY_G) THEN
      IF (ABS(R_G[NO_OF_COLUMN,NO_OF_COLUMN]) < EPSILON)
        THEN SINGULARITY_G := TRUE
        ELSE
          BEGIN
            WRITELN(OUTPUT,'BEGIN BACK_SUB CYCLE_CNTR= ',CYCLE_CNTR);
            BACK_SUBSTITUTE;
            WRITELN(OUTPUT,'END BACK_SUB CYCLE_CNTR= ',CYCLE_CNTR);
            END;
            END; ( R_FILE )
            END; ( CONTROL )
            END; (GAUSS)

```

```

[GLOBAL]PROCEDURE PSEUDO_INV;
BEGIN
{ JACOBN_MAT SHOULD BE COMPUTED BEFORE CALL THIS PROCEDURE }
{WRITE_JAC;}
{*****}
WITH R_FILE DO
BEGIN {R_FILE}
  IF ( N = 6 ) THEN
    GAUSSIAN_ELI(JACOBN_MAT,Q_DOT,X_DOT,SINGULARITY);
  IF ( N < 6 ) THEN
    BEGIN
      JT_MUL_J(S);
      JT_MUL_V61(X_DOT,VN1);
      GAUSSIAN_ELI(S,Q_DOT,VN1,SINGULARITY);
      WRITELN(OUTPUT,' THETA_DOT IS: ');
      WRITE_VEC(Q_DOT,N);
    END;
  IF ( N > 6 ) THEN
    BEGIN
      J_MUL_JT(S);
      GAUSSIAN_ELI(S,V61,X_DOT,SINGULARITY);
      JT_MUL_V61(VN1,Q_DOT);
    END;
  IF SINGULARITY THEN
    WRITELN(OUTPUT,' THIS IS THE SINGULARITY POINT. ');
END; {R_FILE}

END;
END.

```

```

[OVERLAID]MODULE sub_ADJ( INPUT, OUTPUT );

{***** FILE: sub_ADJ.PAS *****)

{*****}
{*      PROGRAM: sub_ADJ.PAS      *}
{*****}

{*****}
{*
{* PROGRAMMER: Yusheng Tsai
{* DATE:      September 11, 1985
{*
{* FUNCTION:   Simulate the computation of THE CORRECTOR
{*             ON the 32-bit floating point processor: AM29325
{*
{* USER GUIDE: THE CALLING FORMAT IS:
{*             SUB_ADJ(Q_IN)
{*
{* PROGRAMMER
{* GUIDE:      $ PAS SUB_ADJ
{*             *** It is not a main program. ***
{*
{* PROCEDURES
{* CALLED:     NONE
{*
{* FUNCTIONS
{* CALLED:     NONE
{*
{* GLOBAL VARIABLES      CONTROL, BUS_R, BUS_S
{* REFERENCED:
{*
{* GLOBAL VARIABLES      BUS_F
{* MODIFIED:
{*****}

%INCLUDE 'GLOBAL.PAS'

[EXTERNAL]PROCEDURE AM325; EXTERNAL;

PROCEDURE WR_STATUS(CYCLE_CNTR1:INTEGER);
BEGIN
    WRITELN(OUTPUT,'RECIPROCAL CYCLE',CYCLE_CNTR1:2,' ');
    WRITELN(OUTPUT,'REG_R= ',REG_R:14:8,' REG_S= ',REG_S:14:8,
            ' REG_F= ',REG_F:14:8);
    WRITELN(OUTPUT,'MUX_A= ',MUX_A:14:8,' MUX_R= ',
            MUX_R:14:8,' MUX_S= ',MUX_S:14:8);
    WRITELN(OUTPUT,'ALU_R= ',ALU_R:14:8,' ALU_S= ',
            ALU_S:14:8,' ALU_F= ',ALU_F:14:8);
    WRITELN(OUTPUT,'BUS_R= ',BUS_R:14:8,' BUS_S= ',
            BUS_S_SEND:14:8,' BUS_F= ',BUS_F:14:8);
END;

```

```

[GLOBAL]PROCEDURE sub_ADJ(VAR THETA_ADJ : ARRAY7);
{ THETA_ADJ CAN BE EITHER THETA_PRE OR THETA_COR }
{ 1.e.                X4_P OR      X4_C      }
VAR
  I_E,J_E,K_E :INTEGER;

BEGIN {sub_ADJ}
  WITH R_FILE DO
    BEGIN { R_FILE }
    { X4_DOT IS SAME AS Q_DOT, NO CYCLE COUNT }
    FOR I_E := 1 TO N DO
      X4_DOT[I_E] := Q_DOT[I_E];
    (-----)
    FOR I_E := 1 TO N DO
      BEGIN { I_E }
      (-----)
      X_N[I_E,4] := X_N[I_E,3];
      (1) {OUTSIDE}
      CYCLE_CNTR := CYCLE_CNTR + 1;
      (-----)
      X_N[I_E,3] := X_N[I_E,2];
      (2) {OUTSIDE}
      CYCLE_CNTR := CYCLE_CNTR + 1;
      (-----)
      X_N[I_E,2] := X_N[I_E,1];
      (3) {OUTSIDE}
      CYCLE_CNTR := CYCLE_CNTR + 1;
      (-----)
      X_N[I_E,1] := THETA_ADJ[I_E];
      (4) {OUTSIDE}
      CYCLE_CNTR := CYCLE_CNTR + 1;
      (-----)
      X_N_DOT[I_E,4] := X_N_DOT[I_E,3];
      (5) {OUTSIDE}
      CYCLE_CNTR := CYCLE_CNTR + 1;
      (-----)
      X_N_DOT[I_E,3] := X_N_DOT[I_E,2];
      (6) {OUTSIDE}
      CYCLE_CNTR := CYCLE_CNTR + 1;
      (-----)
      X_N_DOT[I_E,2] := X_N_DOT[I_E,1];
      (7) {OUTSIDE}
      CYCLE_CNTR := CYCLE_CNTR + 1;
      (-----)
      X_N_DOT[I_E,1] := X4_DOT[I_E];
      (8) {OUTSIDE}
      CYCLE_CNTR := CYCLE_CNTR + 1;
      (-----)
      END; { I_E }
    END; { R_FILE }
  END; {SUB_ADJ}
END. {MODULE}

```

```

[OVERLAID]MODULE sub_cor( INPUT, OUTPUT );

(***** FILE: sub_cor.PAS *****)

(*****)
(*      PROGRAM: sub_cor.PAS      *)
(*****)

(*****)
(*                                     *)
(* PROGRAMMER: Yusheng Tsai          *)
(* DATE:      September 11, 1985     *)
(*                                     *)
(* FUNCTION:   Simulate the computation of THE CORRECTOR *)
(*             ON the 32-bit floating point processor: AM29325 *)
(*                                     *)
(* USER GUIDE: THE CALLING FORMAT IS: *)
(*             SUB_cor(Q_C)           *)
(*                                     *)
(* PROGRAMMER                                     *)
(* GUIDE:      $ PAS SUB_cor                *)
(*             *** It is not a main program. *** *)
(*                                     *)
(* PROCEDURES                                     *)
(* CALLED:      NONE                          *)
(*                                     *)
(* FUNCTIONS                                     *)
(* CALLED:      NONE                          *)
(*                                     *)
(* GLOBAL VARIABLES      CONTROL, BUS_R, BUS_S *)
(* REFERENCED:                                     *)
(*                                     *)
(* GLOBAL VARIABLES      BUS_F *)
(* MODIFIED:                                     *)
(*****)

$INCLUDE 'GLOBAL.PAS'

[EXTERNAL]PROCEDURE AM325; EXTERNAL;

PROCEDURE WR_STATUS(CYCLE_CNTR1:INTEGER);
BEGIN
    WRITELN(OUTPUT,'RECIPROCAL CYCLE',CYCLE_CNTR1:2,' :');
    WRITELN(OUTPUT,'REG_R= ',REG_R:14:8,' REG_S= ',REG_S:14:8,
        ' REG_F= ',REG_F:14:8);
    WRITELN(OUTPUT,'MUX_A= ',MUX_A:14:8,' MUX_R= ',
        MUX_R:14:8,' MUX_S= ',MUX_S:14:8);
    WRITELN(OUTPUT,'ALU_R= ',ALU_R:14:8,' ALU_S= ',
        ALU_S:14:8,' ALU_F= ',ALU_F:14:8);
    WRITELN(OUTPUT,'BUS_R= ',BUS_R:14:8,' BUS_S= ',
        BUS_S_SEND:14:8,' BUS_F= ',BUS_F:14:8);
END;

```

```

[GLOBAL]PROCEDURE sub_cor(VAR THETA_cor : ARRAY7);
VAR
  I_E,J_E,K_E :INTEGER;

BEGIN (sub_cor)
  WITH CONTROL DO
    BEGIN ( CONTROL )
    WITH R_FILE DO
      BEGIN ( R_FILE )
        {-----}
        ENR_BAR := LOW; ENS_BAR := LOW; ENF_BAR := LOW;
        FT0 := LOW; FT1 := LOW; OUT_EN := HIGH;
        MUX_A_SELECT := FALSE; SEED_SELECT := NONE;
        MUX_S_SELECT := FALSE;MUX_R_SELECT := FALSE;
        BUS_R := X4_DOT[1]; BUS_S_SEND := C_CONST[1];
        INS_ALU := NOP;
      (1) AM325;
        {WR_STATUS(CYCLE_CNTR);}
        CYCLE_CNTR := CYCLE_CNTR + 1;
      {-----}
    FOR I_E := 1 TO N DO
      BEGIN ( I_E )
      {-----}
        ENF_BAR := LOW;
        OUT_EN := HIGH;
        INS_ALU := R_TIMES_S;
        MUX_S_SELECT := FALSE;MUX_R_SELECT := FALSE;
        BUS_R := X_N_DOT[I_E,1]; BUS_S_SEND := C_CONST[2];
      (2) AM325;
        {WR_STATUS(CYCLE_CNTR);}
        CYCLE_CNTR := CYCLE_CNTR + 1;
      {-----}
    FOR J_E := 3 TO 4 DO
      BEGIN(J_E)
      {-----}
      (OUTSIDE) IF ( (I_E > 1) AND (J_E = 3) ) THEN
        THETA_cor[I_E-1] := BUS_F;
        ENF_BAR := LOW;
        INS_ALU := R_TIMES_S;
        MUX_S_SELECT := FALSE;MUX_R_SELECT := TRUE;
      (3) AM325;
        {WR_STATUS(CYCLE_CNTR);}
        CYCLE_CNTR := CYCLE_CNTR + 1;
      {-----}
        ENF_BAR := HIGH;
        INS_ALU := R_PLUS_S;
        MUX_S_SELECT := TRUE;MUX_R_SELECT := FALSE;
        BUS_R := X_N_DOT[I_E,J_E-1]; BUS_S_SEND := C_CONST[J_E];
      (4) AM325;
        {WR_STATUS(CYCLE_CNTR);}
        CYCLE_CNTR := CYCLE_CNTR + 1;

```



```

(-----)
END; (J_E)
(-----)
    ENF_BAR := LOW;
    INS_ALU := R_TIMES_S;
    MUX_S_SELECT := FALSE; MUX_R_SELECT := TRUE;
(7) AM325;
    (WR_STATUS(CYCLE_CNTR));
    CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
    ENF_BAR := HIGH;
    INS_ALU := R_PLUS_S;
    MUX_S_SELECT := TRUE; MUX_R_SELECT := FALSE;
    BUS_R := DELTA_T;
(8) AM325;
    (WR_STATUS(CYCLE_CNTR));
    CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
    ENF_BAR := LOW;
    INS_ALU := R_TIMES_S;
    MUX_S_SELECT := TRUE; MUX_R_SELECT := FALSE;
    BUS_R := X_N[I_E,1];
(9) AM325;
    (WR_STATUS(CYCLE_CNTR));
    CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
    ENF_BAR := LOW;
    INS_ALU := R_PLUS_S;
    MUX_S_SELECT := TRUE; MUX_R_SELECT := FALSE;
    IF ( I_E < N ) THEN BEGIN
        BUS_R := X4_DOT[I_E+1]; BUS_S_SEND := C_CONST[1];
    END ELSE BEGIN
        BUS_R := 0.0; BUS_S_SEND := 0.0; END;
(10) AM325;
    (WR_STATUS(CYCLE_CNTR));
    CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
END; (I_E)
(-----)
    OUT_EN := HIGH;
    ENF_BAR := LOW;
    MUX_S_SELECT := FALSE; MUX_R_SELECT := FALSE;
    BUS_R := 0.0; BUS_S_SEND := 0.0;
    INS_ALU := NOP;
(11) AM325;
    (WR_STATUS(CYCLE_CNTR));
    CYCLE_CNTR := CYCLE_CNTR + 1;

```

```

(-----)
{OUTSIDE} THETA_cor[N] := BUS_F;
{12}
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
FOR I_E := 1 TO N DO
{WRITELN(OUTPUT,'THETA_cor[' ,I_E,']= ',THETA_cor[I_E]);
WRITELN(OUTPUT,'***** CALL sub_cor *****');
    } END;{ R_FILE }
    END;{ CONTROL }
END; {sub_cor}
END.{ MODULE sub_cor }

```

```

[OVERLAID]MODULE sub_PRE( INPUT, OUTPUT );
[***** FILE: sub_PRE.PAS *****]

[*****]
[*      PROGRAM: sub_PRE.PAS      *]
[*****]

[*****]
[*                                     *]
[* PROGRAMMER: Yusheng Tsai          *]
[* DATE:      September 11, 1985     *]
[*                                     *]
[* FUNCTION:   Simulate the computation of THE PREDICTOR          *]
[*             ON the 32-bit floating point processor: AM29325    *]
[*                                     *]
[* USER GUIDE: THE CALLING FORMAT IS: *]
[*             SUB_PRE(Q_P)         *]
[*                                     *]
[* PROGRAMMER                                     *]
[* GUIDE:      $ PAS SUB_PRE          *]
[*             *** It is not a main program. ***                 *]
[*                                     *]
[* PROCEDURES                                     *]
[* CALLED:      NONE                                     *]
[*                                     *]
[* FUNCTIONS                                     *]
[* CALLED:      NONE                                     *]
[*                                     *]
[* GLOBAL VARIABLES      CONTROL, BUS_R, BUS_S          *]
[* REFERENCED:                                     *]
[*                                     *]
[* GLOBAL VARIABLES      BUS_F                          *]
[* MODIFIED:                                     *]
[*****]

%INCLUDE 'GLOBAL.PAS'

[EXTERNAL]PROCEDURE AM325; EXTERNAL;

PROCEDURE WR_STATUS(CYCLE_CNTR1:INTEGER);
BEGIN
    WRITELN(OUTPUT,'RECIPROCAL CYCLE',CYCLE_CNTR1:2,' ');
    WRITELN(OUTPUT,'REG_R= ',REG_R:14:8,' REG_S= ',REG_S:14:8,
              ' REG_F= ',REG_F:14:8);
    WRITELN(OUTPUT,'MUX_A= ',MUX_A:14:8,' MUX_R= ',
              MUX_R:14:8,' MUX_S= ',MUX_S:14:8);
    WRITELN(OUTPUT,'ALU_R= ',ALU_R:14:8,' ALU_S= ',
              ALU_S:14:8,' ALU_F= ',ALU_F:14:8);
END;

```

```

[GLOBAL]PROCEDURE sub_PRE(VAR THETA_PRE : ARRAY7);
VAR
  I_E,J_E,K_E :INTEGER;

BEGIN (sub_PRE)
  WITH CONTROL DO
    BEGIN ( CONTROL )
    WITH R_FILE DO
      BEGIN ( R_FILE )
        (-----)
        ENR_BAR := LOW; ENS_BAR := LOW; ENF_BAR := LOW;
        FTO := LOW; FT1 := LOW; OUT_EN := HIGH;
        MUX_A_SELECT := FALSE; SEED_SELECT := NONE;
        MUX_S_SELECT := FALSE;MUX_R_SELECT := FALSE;
        BUS_R := X_n_dot[1,1]; BUS_S_SEND := B_CONST[1];
        INS_ALU := NOP;
      (1) AM325;
        {WR_STATUS(CYCLE_CNTR);}
        CYCLE_CNTR := CYCLE_CNTR + 1;
      (-----)
    FOR I_E := 1 TO N DO
      BEGIN ( I_E )
      (-----)
        ENF_BAR := LOW;
        INS_ALU := R_TIMES_S;
        MUX_S_SELECT := FALSE;MUX_R_SELECT := FALSE;
        BUS_R := X_N_DOT[I_E,2]; BUS_S_SEND := B_CONST[2];
      (2) AM325;
        {WR_STATUS(CYCLE_CNTR);}
        CYCLE_CNTR := CYCLE_CNTR + 1;
      (-----)
    FOR J_E := 3 TO 4 DO
      BEGIN(J_E)
      (-----)
      (OUTSIDE) IF ( (I_E > 1) AND (J_E = 3) ) THEN
        THETA_PRE[I_E-1] := BUS_F;
        ENF_BAR := LOW;
        INS_ALU := R_TIMES_S;
        MUX_S_SELECT := FALSE;MUX_R_SELECT := TRUE;
      (3) AM325;
        {WR_STATUS(CYCLE_CNTR);}
        CYCLE_CNTR := CYCLE_CNTR + 1;
      (-----)
        ENF_BAR := HIGH;
        INS_ALU := R_PLUS_S;
        MUX_S_SELECT := TRUE;MUX_R_SELECT := FALSE;
        BUS_R := X_N_DOT[I_E,J_E]; BUS_S_SEND := B_CONST[J_E];
      (4) AM325;
        {WR_STATUS(CYCLE_CNTR);}
        CYCLE_CNTR := CYCLE_CNTR + 1;
      (-----)
    END; (J_E)

```

```

(-----)
  ENF_BAR := LOW;
  INS_ALU := R_TIMES_S;
  MUX_S_SELECT := FALSE; MUX_R_SELECT := TRUE;
(7) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  ENF_BAR := HIGH;
  INS_ALU := R_PLUS_S;
  MUX_S_SELECT := TRUE; MUX_R_SELECT := FALSE;
  BUS_R := DELTA_T;
(8) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  ENF_BAR := LOW;
  INS_ALU := R_TIMES_S;
  MUX_S_SELECT := TRUE; MUX_R_SELECT := FALSE;
  BUS_R := X_N[I_E,1]; BUS_S_SEND := A_CONST[1];
(9) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  FOR J_E := 2 TO 4 DO
  BEGIN { J_E }
  (-----)
    ENF_BAR := LOW;
    INS_ALU := R_TIMES_S;
    MUX_S_SELECT := FALSE; MUX_R_SELECT := TRUE;
  (10) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
  (-----)
    ENF_BAR := HIGH;
    INS_ALU := R_PLUS_S;
    MUX_S_SELECT := TRUE; MUX_R_SELECT := FALSE;
    BUS_R := X_N[I_E,J_E]; BUS_S_SEND := A_CONST[J_E];
  (11) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;
  (-----)
  END; {J_E}
  (-----)
    ENF_BAR := LOW;
    INS_ALU := R_TIMES_S;
    MUX_S_SELECT := FALSE; MUX_R_SELECT := TRUE;
  (16) AM325;
    {WR_STATUS(CYCLE_CNTR);}
    CYCLE_CNTR := CYCLE_CNTR + 1;

```

```

(-----)
  ENF_BAR := HIGH;
  INS_ALU := R_PLUS_S;
  MUX_S_SELECT := TRUE; MUX_R_SELECT := FALSE;
  IF (I_E < N) THEN
    BEGIN
      BUS_R := X_N_DOT[I_E+1,1]; BUS_S_SEND := B_CONST[1];
    END
  ELSE BEGIN
    BUS_R := 0.0; BUS_S_SEND := 0.0; END;
(17)AM325;
  (WR_STATUS(CYCLE_CNTR);)
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  END; (I_E)
(-----)
  OUT_EN := HIGH;
  ENF_BAR := LOW;
  MUX_S_SELECT := FALSE; MUX_R_SELECT := FALSE;
  BUS_R := 0.0; BUS_S_SEND := 0.0;
  INS_ALU := NOP;
(18)AM325;
  (WR_STATUS(CYCLE_CNTR);)
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
(OUTSIDE) THETA_PRE[N] := BUS_F;
(19)
  (WR_STATUS(CYCLE_CNTR);)
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
FOR I_E := 1 TO N DO
  (WRITELN(OUTPUT, 'THETA_PRE[' , I_E, ']= ' , THETA_PRE[I_E]));
  WRITELN(OUTPUT, '***** CALL sub_PRE *****');
  ) END; ( R_FILE )
  END; ( CONTROL )

END; (sub_PRE)
END. ( MODULE sub_PRE )

```

```

[OVERLAID]MODULE sub_err( INPUT, OUTPUT );

(***** FILE: sub_err.PAS *****)

(*****)
(*      PROGRAM: sub_err.PAS      *)
(*****)

(*****)
(*                                     *)
(* PROGRAMMER: Yusheng Tsai          *)
(* DATE:      September 11, 1985    *)
(*                                     *)
(*                                     *)
(* FUNCTION:   Simulate the computation of ERROR ( X_D - X ) 2 *)
(*            ON the 32-bit floating point processor: AM29325 *)
(*                                     *)
(* USER GUIDE: THE CALLING FORMAT IS: *)
(*            SUB_ERR(DELTA)          *)
(*                                     *)
(* PROGRAMMER *)
(* GUIDE:      $ PAS SUB_ERR          *)
(*            *** It is not a main program. *** *)
(*                                     *)
(* PROCEDURES *)
(* CALLED:     NONE                   *)
(*                                     *)
(* FUNCTIONS  *)
(* CALLED:     NONE                   *)
(*                                     *)
(* GLOBAL VARIABLES      CONTROL, BUS_R, BUS_S *)
(* REFERENCED:           *)
(*                                     *)
(* GLOBAL VARIABLES      BUS_F *)
(* MODIFIED:             *)
(*****)

%INCLUDE 'GLOBAL.PAS'

[EXTERNAL]PROCEDURE AM325; EXTERNAL;

PROCEDURE WR_STATUS(CYCLE_CNTR1:INTEGER);
BEGIN
    WRITELN(OUTPUT,'SUB_ERROR CYCLE',CYCLE_CNTR1:2,' :');
    WRITELN(OUTPUT,'BUS_R= ',BUS_R:14:8,' BUS_S= ',
        BUS_S_SEND:14:8,' BUS_F= ',BUS_F:14:8);
    WRITELN(OUTPUT,'REG_R= ',REG_R:14:8,' REG_S= ',REG_S:14:8,
        ' REG_F= ',REG_F:14:8);
    WRITELN(OUTPUT,'MUX_A= ',MUX_A:14:8,' MUX_R= ',
        MUX_R:14:8,' MUX_S= ',MUX_S:14:8);
    WRITELN(OUTPUT,'ALU_R= ',ALU_R:14:8,' ALU_S= ',
        ALU_S:14:8,' ALU_F= ',ALU_F:14:8);
END;

```

```

[GLOBAL]PROCEDURE sub_err(VAR DELTA_OUT : REAL);
VAR
  I_E,J_E,K_E :INTEGER;

BEGIN (sub_err)
  WITH CONTROL DO
    BEGIN ( CONTROL )
      WITH R_FILE DO
        BEGIN ( R_FILE )
          (-----)
          ENR_BAR := LOW; ENS_BAR := LOW; ENF_BAR := LOW;
          FT0 := LOW; FT1 := LOW; OUT_EN := LOW;
          MUX_A_SELECT := FALSE; SEED_SELECT := NONE;
          MUX_S_SELECT := FALSE; MUX_R_SELECT := FALSE;
          BUS_R := X_D[1,1]; BUS_S_SEND := X[1,1];
          INS_ALU := NOP;
        (1) AM325;
          {WR_STATUS(CYCLE_CNTR);}
          CYCLE_CNTR := CYCLE_CNTR + 1;
        (-----)
          MUX_S_SELECT := FALSE; MUX_R_SELECT := FALSE;
          INS_ALU := R_MINUS_S;
          BUS_R := X_D[1,2]; BUS_S_SEND := X[1,2];
        (2) AM325;
          {WR_STATUS(CYCLE_CNTR);}
          CYCLE_CNTR := CYCLE_CNTR + 1;
        (-----)
          OUT_EN := HIGH;
          INS_ALU := R_MINUS_S;
          BUS_R := X_D[1,3]; BUS_S_SEND := X[1,3];
        (3) AM325;
          {WR_STATUS(CYCLE_CNTR);}
          CYCLE_CNTR := CYCLE_CNTR + 1;
        (-----)
          K_E := 1;
          FOR I_E := 2 TO 3 DO
            BEGIN ( I_E )
              FOR J_E := 1 TO 4 DO
                BEGIN ( J_E )
                  (-----)
                  {OUTSIDE} TEMP[K_E] := BUS_F;
                  K_E := K_E + 1;
                  OUT_EN := HIGH;
                  INS_ALU := R_MINUS_S;
                  BUS_R := X_D[I_E,J_E]; BUS_S_SEND := X[I_E,J_E];
                (4) AM325;
                  {WR_STATUS(CYCLE_CNTR);}
                  CYCLE_CNTR := CYCLE_CNTR + 1;
                (-----)
              END ( J_E )
            END ( I_E )
          END ( K_E )
        END ( R_FILE )
      END ( CONTROL )
    END (sub_err)
  END ( DELTA_OUT )

```



```

(-----)
END; ( J_E )
END; ( I_E )
(-----)
(OUTSIDE) TEMP[9] := BUS_F;
          OUT_EN := HIGH;
          INS_ALU := R_MINUS_S;
          BUS_R := X_D[1,4]; BUS_S_SEND := X[1,4];
(12) AM325;
      (WR_STATUS(CYCLE_CNTR);)
      CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
(OUTSIDE) TEMP[10] := BUS_F;
          OUT_EN := HIGH;
          INS_ALU := R_MINUS_S;
          BUS_R := TEMP[1]; BUS_S_SEND := TEMP[1];
(13) AM325;
      (WR_STATUS(CYCLE_CNTR);)
      CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
(OUTSIDE) TEMP[11] := BUS_F;
          OUT_EN := HIGH;
          INS_ALU := R_TIMES_S;
          BUS_R := TEMP[2]; BUS_S_SEND := TEMP[2];
(14) AM325;
      (WR_STATUS(CYCLE_CNTR);)
      CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
(OUTSIDE) TEMP[12] := BUS_F;
          OUT_EN := LOW;
          MUX_S_SELECT := FALSE; MUX_R_SELECT := TRUE;
          INS_ALU := R_TIMES_S;
(15) AM325;
      (WR_STATUS(CYCLE_CNTR);)
      CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
FOR K_E := 3 TO 12 DO
BEGIN (K_E)
    ENF_BAR := HIGH;
    MUX_S_SELECT := TRUE; MUX_R_SELECT := FALSE;
    BUS_R := TEMP[K_E]; BUS_S_SEND := TEMP[K_E];
    INS_ALU := R_PLUS_S;
(16) AM325;
      (WR_STATUS(CYCLE_CNTR);)
      CYCLE_CNTR := CYCLE_CNTR + 1;

```

```

(-----)
  ENF_BAR := LOW;
  MUX_S_SELECT := FALSE; MUX_R_SELECT := TRUE;
  INS_ALU := R_TIMES_S;
(17) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
END; (K_E)
(-----)
  ENF_BAR := HIGH;
  MUX_S_SELECT := TRUE; MUX_R_SELECT := FALSE;
  BUS_R := 0.0; BUS_S_SEND := 0.0;
  INS_ALU := R_PLUS_S;
(36) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  OUT_EN := HIGH;
  ENF_BAR := LOW;
  MUX_S_SELECT := FALSE; MUX_R_SELECT := FALSE;
  BUS_R := 0.0; BUS_S_SEND := 0.0;
  INS_ALU := NOP;
(37) AM325;
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
(OUTSIDE) DELTA_OUT := BUS_F;
(38)
  {WR_STATUS(CYCLE_CNTR);}
  CYCLE_CNTR := CYCLE_CNTR + 1;
(-----)
  END; ( R_FILE )
  END; ( CONTROL )

END; (sub_err)
END. ( MODULE sub_err )

```

A.3.3 Programs for Tasks

A.3.3 gives programs for the tasks. TASK1.PAS is the program which computes the designed hand positions for drawing circles by the RM-501. TASK3.PAS generates the corresponding homogeneous matrices for the RM-501 to move its arm to the maximum extension. TASK71.PAS and TASK72.PAS are programs for generating designed hand positions for the task in which the S-400 moves its end effector on a straight line.

```

[OVERLAID]MODULE TASK1( INPUT, OUTPUT );

{***** FILE: TASK1.PAS *****)

{*****}
{*      PROGRAM: TASK1.PAS      *}
{*****}

{*****}
{*                                     *}
{* PROGRAMMER: Yushang Tsai          *}
{* DATE:      March 31, 1986         *}
{*                                     *}
{* FUNCTION:      Generate the task desired position and rotation *}
{*               X_D.  The task was designed to rotate the      *}
{*               Motion_Angle from 180 to -180 degrees.         *}
{*                                     *}
{* USER GUIDE:    THE CALLING FORMAT IS:                          *}
{*               TASK1(X_D, TIME_TASK);                          *}
{*                                     *}
{* PROGRAMMER                                           *}
{* GUIDE:      $ PAS TASK                                *}
{*               *** It is not a main program. ***          *}
{*                                     *}
{* PROCEDURES                                           *}
{* CALLED:      NONE                                       *}
{*                                     *}
{* FUNCTIONS                                           *}
{* CALLED:      NONE                                       *}
{*                                     *}
{* GLOBAL VARIABLES                                     *}
{* REFERENCED:                                           *}
{*                                     *}
{* GLOBAL VARIABLES                                     *}
{* MODIFIED:                                             *}
{*****}

%INCLUDE 'GLOBAL.PAS'
[GLOBAL]PROCEDURE TASK1(VAR TX_D: ARRAY34;
                        TTIME_TASK: REAL      );

VAR
    MOTION_ANGLE : REAL;
    ANGULAR_SPEED : REAL;
    ANGLE        : REAL;
    SI,CO        : REAL;

```

```

BEGIN
  ANGULAR_SPEED := 10.0; { SPEED = 10 DEGREE/SECOND }
  ANGLE := ANGULAR_SPEED * TTIME_TASK * PI / 180.0 ; { IN RAD }
  SI := SIN ( ANGLE );
  CO := COS ( ANGLE );
  TX_D[1,1] := CO;
  TX_D[1,2] := SI;
  TX_D[1,3] := 0.0;
  TX_D[2,1] := SI;
  TX_D[2,2] := - CO;
  TX_D[2,3] := 0.0;
  TX_D[3,1] := 0.0;
  TX_D[3,2] := 0.0;
  TX_D[3,3] := -1.0;
  TX_D[1,4] := 320.0 + 50.0 * CO; { IN mm }
  TX_D[2,4] := 50.0 * SI;
  TX_D[3,4] := 18.5;
END;
END.

```

```

[OVERLAID]MODULE TASK3( INPUT, OUTPUT );

(***** FILE: TASK3.PAS *****)

(*****)
(*      PROGRAM: TASK3.PAS      *)
(*****)

(*****)
(*                                     *)
(* PROGRAMMER: Yusheng Tsai         *)
(* DATE:      Sep. 8, 1985         *)
(*                                     *)
(* FUNCTION:   Generate the task desired position and rotation *)
(*             X_D.  The task was designed to move the hand *)
(*             to a singularity point *)
(*                                     *)
(* USER GUIDE: THE CALLING FORMAT IS: *)
(*             TASK3(X_D, TIME_TASK); *)
(*                                     *)
(* PROGRAMMER *)
(* GUIDE:      $ PAS TASK           *)
(*             *** It is not a main program. *** *)
(*                                     *)
(* PROCEDURES *)
(* CALLED:     NONE                 *)
(*                                     *)
(* FUNCTIONS  *)
(* CALLED:     NONE                 *)
(*                                     *)
(* GLOBAL VARIABLES *)
(* REFERENCED: *)
(*                                     *)
(* GLOBAL VARIABLES *)
(* MODIFIED: *)
(*****)

%INCLUDE 'global.PAS'
[GLOBAL]PROCEDURE TASK3(VAR TX_D: array34;
                        TTIME_TASK: real );
{ Procedure for generating the task desired position and orientatio
{
X_D

```

```

BEGIN
  TX_D[1,1] := 0.0;
  TX_D[1,2] := 0.0;
  TX_D[1,3] := 1.0;
  TX_D[2,1] := 0.0;
  TX_D[2,2] := 1.0;
  TX_D[2,3] := 0.0;
  TX_D[3,1] := -1.0;
  TX_D[3,2] := 0.0;
  TX_D[3,3] := 0.0;
  TX_D[1,4] := 503.1 + 10.0 * TTIME_TASK;
  TX_D[2,4] := 0.0 ;
  TX_D[3,4] := 250.0 ;
  { TX_D[4,4] := 1.0; TX_D[4,1]:=0.0; TX_D[4,2]:=0.0; TX_D[4,3]:=0.0;}
END;
END.

```

```
[OVERLAID]MODULE TASK5( INPUT, OUTPUT );
```

```
(***** FILE: TASK5.PAS *****)
```

```
(*****)
```

```
(* PROGRAM: TASK5.PAS *)
```

```
(*****)
```

```
(*****)
```

```
(* *)
```

```
(* PROGRAMMER: Yusheng Tsai *)
```

```
(* DATE: Sep. 8, 1985 *)
```

```
(* *)
```

```
(* FUNCTION: Generate the task desired position and rotation *)
```

```
(* X_D. The task was designed to draw a line *)
```

```
(* by GMF robot. *)
```

```
(* *)
```

```
(* USER GUIDE: THE CALLING FORMAT IS: *)
```

```
(* TASK5(X_D,VEL_HD, TIME_TASK); *)
```

```
(* *)
```

```
(* PROGRAMMER *)
```

```
(* GUIDE: $ PAS TASK *)
```

```
(* *** It is not a main program. *** *)
```

```
(* *)
```

```
(* PROCEDURES *)
```

```
(* CALLED: NONE *)
```

```
(* *)
```

```
(* FUNCTIONS *)
```

```
(* CALLED: NONE *)
```

```
(* *)
```

```
(* GLOBAL VARIABLES *)
```

```
(* REFERENCED: *)
```

```
(* *)
```

```
(* GLOBAL VARIABLES *)
```

```
(* MODIFIED: *)
```

```
(*****)
```

```
%INCLUDE 'GLOBAL.PAS'
```

```
[GLOBAL]PROCEDURE TASK5(VAR TX_D: ARRAY34;
```

```
VAR VEL_HAND:ARRAY7;
```

```
TIME_TASK: REAL );
```

```
{ Procedure for generating the task desired position and orientatio
```

```
{ X_D
```

```
VAR
```

```
angle : real;
```

```
SA,CA,SB,CB : REAL;
```

```
TMP_TASK : REAL;
```

```
VEL_HAND_X,VEL_HAND_Y : REAL;
```

```
DT : REAL;
```



```

BEGIN
  WITH R_FILE DO
  BEGIN
    IF (TTIME_TASK < 0.5) AND ( TTIME_TASK >= 0.0 ) THEN
      angle := (30.0 * TTIME_TASK * ttime_task) * pi / 180.0;
    IF (TTIME_TASK > 0.5) AND ( TTIME_TASK <= 1.0 ) THEN
      angle := (30.0 * (TTIME_TASK - 0.25)) * pi / 180.0;
    IF (TTIME_TASK > 1.0) AND ( TTIME_TASK <= 1.5 ) THEN
      angle := (30.0 * (TTIME_TASK - 0.25)
        - 30.0*(TTIME_TASK-1.0)*(TTIME_TASK-1.0))* pi / 180.0;
    IF (TTIME_TASK > 1.5 ) THEN ANGLE := 30.0;
    CA := cos ( angle );
    SA := sin ( angle );
    CB := COS ( 60.0 / 180.0 * PI );
    SB := SIN ( 60.0 / 180.0 * PI );
    TX_D[1,1] := 0.0;
    TX_D[1,2] := - CB * CA + SB * SA;
    TX_D[1,3] := CB * SA + SB * CA;
    TX_D[2,1] := 0.0;
    TX_D[2,2] := -SB * CA - CB * SA;
    TX_D[2,3] := SB * SA - CB * CA;
    TX_D[3,1] := 1.0;
    TX_D[3,2] := 0.0;
    TX_D[3,3] := 0.0;
    TX_D[1,4] := 1192.836; { IN mm }
    TX_D[2,4] := -948.49;
    TX_D[3,4] := -169;
    TX_D[4,4] := 1.0;
    {TX_D[4,1]:=0.0; TX_D[4,2]:=0.0; TX_D[4,3]:=0.0;}
    {***** HAND VELOCITY *****}
    FOR I_TST := 2 TO 6 DO VEL_HAND[I_TST] := 0.0;
    IF (TTIME_TASK < 0.5) AND ( TTIME_TASK >= 0.0 ) THEN
      VEL_HAND[1] := 60.0 * TTIME_TASK;
    IF (TTIME_TASK > 0.5) AND ( TTIME_TASK <= 1.0 ) THEN
      VEL_HAND[1] := 30.0;
    IF (TTIME_TASK > 1.0) AND ( TTIME_TASK <= 1.5 ) THEN
      VEL_HAND[1] := (30.0 - 60.0*(TTIME_TASK-1.0));
    IF (TTIME_TASK > 1.5 ) THEN VEL_HAND[1] := 0.0;
    { X_DOT[4] = VEL_HAND [x] = VEL_BASE[Y] }
  END;
END;
END.

```

```

[OVERLAID]MODULE TASK5( INPUT, OUTPUT );
[***** FILE: TASK5.PAS *****]

[*****]
[*      PROGRAM: TASK5.PAS      *]
[*****]

[*****]
[*      *]
[* PROGRAMMER: Yusheng Tsai      *]
[* DATE:      March 31, 1986    *]
[*      *]
[* FUNCTION:   Generate the task desired position and rotation *]
[*      X_D.   The task was designed to draw a line          *]
[*      by GMF robot.                                              *]
[*      *]
[* USER GUIDE: THE CALLING FORMAT IS:                             *]
[*      TASK5(X_D,VEL_HD, TIME_TASK);                             *]
[*      *]
[* PROGRAMMER *]
[* GUIDE:     $ PAS TASK                                           *]
[*      *** It is not a main program. ***                          *]
[*      *]
[* PROCEDURES *]
[* CALLED:    NONE                                                 *]
[*      *]
[* FUNCTIONS  *]
[* CALLED:    NONE                                                 *]
[*      *]
[* GLOBAL VARIABLES *]
[* REFERENCED: ALL                                                 *]
[*****]

%INCLUDE 'GLOBAL.PAS'
[GLOBAL]PROCEDURE TASK5(VAR TX_D: ARRAY34;
                        VAR VEL_HAND:ARRAY7;
                        TTIME_TASK: REAL    );
{ Procedure for generating the task desired position and orientatio
{      X_D

VAR
  angle : real;
  SA,CA,SB,CB : REAL;
  TMP_TASK : REAL;
  VEL_HAND_X,VEL_HAND_Y : REAL;
  T61,T62,TACC,VMAX,VI,ACC,VX_MAX,VY_MAX,VZ_MAX : REAL;
  DX,DY,DZ, TMP1 : REAL;
  DT : REAL;

```

```

BEGIN
  ( VMAX := 100.0; TACC := 0.5; T61 := 0.0; T62 := 17.28; )
  VMAX := 1500.0; TACC := 0.3; T61 := 0.0; T62 := 1.54;
  ( VMAX := 3000.0; TACC := 0.5; T62 := 15; )
  ACC := VMAX/TACC;
  WITH R_FILE DO
  BEGIN
    (***** HAND VELOCITY *****)
    FOR I_TST := 1 TO 3 DO VEL_HAND[I_TST] := 0.0;
    IF (TTIME_TASK < (TACC + T61)) AND ( TTIME_TASK >= T61 ) THEN
      VI := ACC * TTIME_TASK;
    IF (TTIME_TASK >= (T61 + TACC)) AND ( TTIME_TASK <= (T62 - TACC) )
      VI := VMAX;
    IF (TTIME_TASK > (T62 - TACC)) AND ( TTIME_TASK <= T62 ) THEN
      VI := VMAX - ACC * (TTIME_TASK - T62 + TACC);
    IF (TTIME_TASK > T62 ) THEN VI := 0.0;
    TMP1 := 180.0/PI;
    ( TMP1 := 1.0; )
    VEL_HAND[4] := 0.86855 * VI * TMP1;
    VEL_HAND[5] := - 0.4444 * VI * TMP1;
    VEL_HAND[6] := 0.2194 * VI * TMP1;
    VX_MAX := 0.86855 * VMAX;
    VY_MAX := - 0.4444 * VMAX;
    VZ_MAX := 0.2194 * VMAX;
    (***** HAND VELOCITY *****)
    IF (TTIME_TASK < (TACC + T61)) AND ( TTIME_TASK >= T61 ) THEN
      BEGIN
        (
          DX := 0.5 * VX_MAX * TTIME_TASK * TTIME_TASK / TACC;
          DY := 0.5 * VY_MAX * TTIME_TASK * TTIME_TASK / TACC;
          DZ := 0.5 * VZ_MAX * TTIME_TASK * TTIME_TASK / TACC;
        )
        TMP_TASK := 0.5 * TTIME_TASK * TTIME_TASK / TACC;
        DX := VX_MAX * TMP_TASK;
        DY := VY_MAX * TMP_TASK;
        DZ := VZ_MAX * TMP_TASK;
      END;
    IF (TTIME_TASK > (T61 + TACC)) AND ( TTIME_TASK <= (T62 - TACC) )
      BEGIN
        TMP_TASK := TTIME_TASK - (0.5 * TACC);
        DX := VX_MAX * TMP_TASK;
        DY := VY_MAX * TMP_TASK;
        DZ := VZ_MAX * TMP_TASK;
      END;
    IF (TTIME_TASK > (T62 - TACC)) AND ( TTIME_TASK <= T62 ) THEN
      BEGIN
        TMP_TASK := TTIME_TASK - (0.5 * TACC)
          - (0.5 * (TTIME_TASK - (T62-TACC)));
        DX := VX_MAX * TMP_TASK;
        DY := VY_MAX * TMP_TASK;
        DZ := VZ_MAX * TMP_TASK;
      END;
  END;

```

```

IF (TTIME_TASK > T62 ) THEN
  BEGIN
    TMP_TASK := T62 - TACC;
    DX := VX_MAX * TMP_TASK;
    DY := VY_MAX * TMP_TASK;
    DZ := VZ_MAX * TMP_TASK;
    END;
    TX_D[1,1] := 0.0;
    TX_D[1,2] := 0.0;
    TX_D[1,3] := 1.0;
    TX_D[2,1] := 0.0;
    TX_D[2,2] := -1.0;
    TX_D[2,3] := 0.0;
    TX_D[3,1] := 1.0;
    TX_D[3,2] := 0.0;
    TX_D[3,3] := 0.0;
    TX_D[1,4] := 1192.836 + DZ; ( IN mm )
    TX_D[2,4] := -948.49 - DY;
    TX_D[3,4] := -169 + DX;
    ( TX_D[4,4] := 1.0; TX_D[4,1] := -0.0; TX_D[4,2] := -0.0; TX_D[4,3] := -0.0;
  END;
END;
END.

```

A.3.4 Main Programs for Simulations

A.3.4 contains three programs for simulations. TEST.PAS is the program used to test all computational modules and simulation programs for the proposed architecture. PIPIK1.PAS and GMF.PAS simulates the Inverse Kinematics algorithm on the proposed Inverse Kinematics Processor for the RM-501 and S-400 manipulators, respectively.

```

[OVERLAID]PROGRAM TEST( INPUT, OUTPUT );
{***** FILE: TEST.PAS *****)

{*****}
{ *          PROGRAM: TEST.PAS          *}
{*****}
{*****}
{ TEST THE OPERATION OF MODULES }
{*****}
%INCLUDE 'GLOBAL.PAS'

[EXTERNAL]PROCEDURE SEED_TABLE; EXTERN;
[EXTERNAL]PROCEDURE SUB_REC3(REC_VAR:REAL); EXTERNAL;
[EXTERNAL]PROCEDURE SUB_REC(REC_VAR:REAL); EXTERNAL;
[EXTERNAL]PROCEDURE SIN_COS(THETA_RAD1:REAL;
                           VAR SIN_OUT1: REAL;
                           VAR COS_OUT1: REAL); EXTERNAL;
{ [EXTERNAL]PROCEDURE SIN_COS3(THETA_RAD1:REAL;
                              VAR SIN_OUT1: REAL;
                              VAR COS_OUT1: REAL); EXTERNAL;
} [EXTERNAL]PROCEDURE AM325; EXTERNAL;
[EXTERNAL]PROCEDURE DIRKIN_TST; EXTERNAL;
[EXTERNAL]PROCEDURE KIN_JAC; EXTERNAL;
[EXTERNAL]PROCEDURE KIN_JAC1; EXTERNAL;
[EXTERNAL]PROCEDURE JT_MUL_J(VAR SS: SQUARE_MAT_66); EXTERN;
[EXTERNAL]PROCEDURE JT_MUL_V61( VEC61: ARRAY7;
                              VAR VECN1:ARRAY7); EXTERN;
[EXTERNAL]PROCEDURE J_MUL_JT(VAR SS: SQUARE_MAT_66); EXTERN;
[EXTERNAL]PROCEDURE PSEUDO_INV; EXTERN;
[EXTERNAL]PROCEDURE PSEUDO( VAR XDOT: ARRAY6;
                          NOR,NOC : INTEGER;
                          VAR SINGU : BOOLEAN;
                          VAR RES : ARRAY7); EXTERN;
[EXTERNAL]PROCEDURE SUB_ERR(VAR DELTA_SUB : REAL );EXTERN;
[EXTERNAL]PROCEDURE SUB_PRE(VAR THETA_P : ARRAY7); EXTERN;
[EXTERNAL]PROCEDURE SUB_COR(VAR THETA_C : ARRAY7); EXTERN;
[EXTERNAL]PROCEDURE SUB_ADJ(VAR THETA_IN : ARRAY7); EXTERN;
[EXTERNAL]PROCEDURE INIT_XN; EXTERN;
[EXTERNAL]PROCEDURE GAUSSIAN_ELI(VAR G_A: SQUARE_MAT_66;
                                VAR G_B: ARRAY7;
                                VAR G_C: ARRAY7;
                                VAR G_D: BOOLEAN);EXTERN;

PROCEDURE INIT;
VAR
  K_I,J_I : INTEGER;
BEGIN { INIT }
{*****}

```

```

{ SINE/COSINE REGISTERS" INITIALIZATION }
WITH R_FILE DO
BEGIN
  N := 5;
  COS_REG_CONST[1] := - 1/2;
  FOR K_I := 1 TO 6 DO
  BEGIN
    J_I := 2 * K_I + 1;
    SIN_REG_CONST[K_I] := COS_REG_CONST[K_I]/J_I;
    COS_REG_CONST[K_I+1] := - SIN_REG_CONST[K_I]/(J_I + 1);
  END;
  SIN_REG_CONST[7] := COS_REG_CONST[7]/15;
  FOR K_I := 1 TO 7 DO
    WRITELN(OUTPUT, 'SIN_CONST-', K_I:2, '= ', SIN_REG_CONST[K_I],
            'COS_CONST-', K_I:2, '= ', COS_REG_CONST[K_I]);
  END;
{*****}
{ AM29325 INITIALIZATION }
BUS_R := 0.0; BUS_S_SEND := 0.0; BUS_S_END := 0.0; BUS_R := 0.0;
WITH CONTROL DO
BEGIN
  ENR_BAR := LOW; ENS_BAR := LOW; ENF_BAR := LOW;
  MUX_A_SELECT := FALSE; MUX_R_SELECT := FALSE;
  MUX_S_SELECT := FALSE; INS_ALU := R_PLUS_S;
  FT0 := LOW; FT1 := LOW;
  OUT_EN := LOW; SEED_SELECT := NONE;
END;
{*****}
END; ( INIT )

procedure tst_sin;
var
  II_S : INTEGER;
  tmp_sin, tmp_cos: real;
  tmp: array [1..12] of real;

BEGIN {S}
  WITH R_FILE DO
  BEGIN {R}
    WRITE(OUTPUT, ' KEY IN THE TESTING ANGLE IN DEGREES => ');
    READLN(INPUT, ANGLE_S);
    TMP[12] := ANGLE_S * PI / 180.0;
    tmp_sin := sin(TMP[12]);
    tmp_cos := cos(TMP[12]);
    SIN_COS(TMP[12], SIN_OUT2, COS_OUT2);
    WRITELN(OUTPUT, 'FOR ANGLE= ', ANGLE_S, ' SIN(ANGLE)=',
            SIN_OUT2:16:10, ' COS(ANGLE)= ', COS_OUT2:16:10);
    writeln(output, ' true solution is:');
    WRITELN(OUTPUT, 'FOR ANGLE= ', ANGLE_S, ' SIN(ANGLE)=',
            tmp_sin:16:10, ' COS(ANGLE)= ', tmp_cos:16:10);
  END {R}
END {S}

```

```

( SIN_COS3(TMP[12],SIN_OUT2,COS_OUT2);
  writeln(output,'FOR SIN_COS3 MICRO-CODE ');
  WRITELN(OUTPUT,'FOR ANGLE= ', ANGLE_S,' SIN(ANGLE)=',
    SIN_OUT2:16:10,' COS(ANGLE)= ',COS_OUT2:16:10);
  writeln(output,' true solution is:');
  WRITELN(OUTPUT,'FOR ANGLE= ', ANGLE_S,' SIN(ANGLE)=',
    tmp_sin:16:10,' COS(ANGLE)= ',tmp_cos:16:10);
)  TMP[4] := 0.0;
   TMP[5] := 0.0;
   FOR II_S := 1 TO 1000 DO
   BEGIN
     TMP[12] := PI * II_S / 1000;
     TMP[1] := TMP[12] * 180.0 / PI;
     SIN_COS(TMP[12],SIN_OUT2,COS_OUT2);
     tmp_sin := sin(TMP[12]);
     tmp_cos := cos(TMP[12]);
     TMP[2] := ABS(TMP_SIN - SIN_OUT2);
     TMP[3] := ABS(TMP_COS - COS_OUT2);
     IF ( TMP[4] < TMP[2] ) THEN
       BEGIN
         TMP[4] := TMP[2];
         TMP[6] := TMP[1];
         TMP[8] := TMP_SIN;
         TMP[10] := SIN_OUT2;
       END;
     IF ( TMP[5] < TMP[3] ) THEN
       BEGIN
         TMP[5] := TMP[3];
         TMP[7] := TMP[1];
         TMP[9] := TMP_COS;
         TMP[11] := COS_OUT2;
       END;
     END;
     TMP[4] := 0.0;
     TMP[5] := 0.0;
     WRITELN(OUTPUT,' THE MAXIMUM ERROR FOR SINE IS: ',
       TMP[4]:16:12, ' AT ',TMP[6]:10:6);
     WRITELN(OUTPUT,' ITS TRUE SINE IS ',TMP[8]:16:12);
     WRITELN(OUTPUT,' ITS MICRO-SINE IS ',TMP[10]:16:12);
     WRITELN(OUTPUT,' THE MAXIMUM ERROR FOR COSINE IS: ',
       TMP[5]:16:12, ' AT ',TMP[7]:10:6);
     WRITELN(OUTPUT,' ITS TRUE COSINE IS ',TMP[9]:16:12);
     WRITELN(OUTPUT,' ITS MICRO-COSINE IS ',TMP[11]:16:12);
   (TEST FOR SIN_COS3)
   {  FOR II_S := 1 TO 1000 DO
   BEGIN
     TMP[12] := PI * II_S / 1000;
     TMP[1] := TMP[12] * 180.0 / PI;
     SIN_COS3(TMP[12],SIN_OUT2,COS_OUT2);
     tmp_sin := sin(TMP[12]);
     tmp_cos := cos(TMP[12]);

```



```

    TMP[2] := ABS(TMP_SIN - SIN_OUT2);
    TMP[3] := ABS(TMP_COS - COS_OUT2);
    IF ( TMP[4] < TMP[2] ) THEN
        BEGIN
            TMP[4] := TMP[2];
            TMP[6] := TMP[1];
            TMP[8] := TMP_SIN;
            TMP[10] := SIN_OUT2;
        END;
    IF ( TMP[5] < TMP[3] ) THEN
        BEGIN
            TMP[5] := TMP[3];
            TMP[7] := TMP[1];
            TMP[9] := TMP_COS;
            TMP[11] := COS_OUT2;
        END;
    END;
    WRITELN(OUTPUT, ' THE MAXIMUM ERROR FOR SINE IS: ',
            TMP[4]:16:12, ' AT ', TMP[6]:10:6);
    WRITELN(OUTPUT, ' ITS TRUE SINE IS ', TMP[8]:16:12);
    WRITELN(OUTPUT, ' ITS MICRO-SINE IS ', TMP[10]:16:12);
    WRITELN(OUTPUT, ' THE MAXIMUM ERROR FOR COSINE IS: ',
            TMP[5]:16:12, ' AT ', TMP[7]:10:6);
    WRITELN(OUTPUT, ' ITS TRUE COSINE IS ', TMP[9]:16:12);
    WRITELN(OUTPUT, ' ITS MICRO-COSINE IS ', TMP[11]:16:12);
)
( testing the sin_seed_table )
  with control do
  begin
    SEED_SELECT := SIN_TAB ;
    SEED_IN := ANGLE_S * PI /180.0;
    SEED_TABLE;
    WRITELN(OUTPUT, ' SEED_IN ( IN RAD )= ', SEED_IN:12:8,
            ' SEED_OUT FOR SINE= ', SEED_OUT:12:8);
  end;
END(R);
END; {S}

PROCEDURE WRITE_X;
VAR
  K_I, J_I : INTEGER;
BEGIN {WRITE_X}
  WRITELN(OUTPUT, '          X MATRIX IS :  ');
  WITH R_FILE DO
  BEGIN
    FOR K_I := 1 TO 3 DO
    BEGIN
      FOR J_I := 1 TO 4 DO
        WRITE(OUTPUT, X[K_I, J_I]:14:8);
        WRITELN(OUTPUT);
      END;
    END;
  END;
END; {WRITE_X}

```

```

PROCEDURE WRITE_Xd;
VAR
  K_I,J_I : INTEGER;
BEGIN {WRITE_Xd}
  WRITELN(OUTPUT,'      X_D MATRIX IS :  ');
  WITH R_FILE DO
  BEGIN
    FOR K_I := 1 TO 3 DO
    BEGIN
      FOR J_I := 1 TO 4 DO
        WRITE(OUTPUT,X_D[K_I,J_I]:14:8);
        WRITELN(OUTPUT);
      END;
    END;
  END; {WRITE_Xd}

PROCEDURE WRITE_JAC;
VAR
  K_I,J_I : INTEGER;
BEGIN {WRITE_jac}
  WRITELN(OUTPUT,'      JACOBIAN MATRIX IS :  ');
  WITH R_FILE DO
  BEGIN
    FOR K_I := 1 TO 6 DO
    BEGIN
      FOR J_I := 1 TO N DO
        WRITE(OUTPUT,JACOBN_MAT[K_I,J_I]:10:5);
        WRITELN(OUTPUT);
      END;
    END;
  END; {WRITE_JAC}

PROCEDURE WRITE_S;
VAR
  K_I,J_I : INTEGER;
BEGIN {WRITE_S}
  WRITELN(OUTPUT,'      S MATRIX IS :  ');
  WITH R_FILE DO
  BEGIN
    FOR K_I := 1 TO 6 DO
    BEGIN
      FOR J_I := 1 TO 6 DO
        WRITE(OUTPUT,S[K_I,J_I]:13:5);
        WRITELN(OUTPUT);
      END;
    END;
  END; {WRITE_S}

```

```

[GLOBAL]PROCEDURE WRITE_ANGLE;
VAR
  K_I,J_I : INTEGER;
  ANGLE_S1 : REAL;
BEGIN {WRITE_ANGLE}
  WRITELN(OUTPUT,' WITH JOINT ANGLES :');
  FOR K_I := 1 TO N DO
    BEGIN
      WITH R_FILE DO
        ANGLE_S1 := ANGLE_RAD[K_I+1] * 180.0 / PI;
        WRITE (OUTPUT,'THETA['',K_I:1,'']= ',ANGLE_S1:10:4);
      END;
    WRITELN(OUTPUT);
  END; {WRITE_ANGLE}

[GLOBAL]PROCEDURE WRITE_ANGLE1;
VAR
  K_I,J_I : INTEGER;
  ANGLE_S1 : REAL;
BEGIN {WRITE_ANGLE}
  WRITELN(OUTPUT,' WITH JOINT ANGLES :');
  FOR K_I := 1 TO N DO
    BEGIN
      WITH R_FILE DO
        ANGLE_S1 := ANGLE_RAD[K_I+1] * 180.0 / PI;
        WRITEln (OUTPUT,'THETA['',K_I:1,'']= ',ANGLE_S1:14:8);
      END;
    WRITELN(OUTPUT);
  END; {WRITE_ANGLE}

PROCEDURE WRITE_THETA_DOT;
VAR
  K_I,J_I : INTEGER;
  ANGLE_S1 : REAL;
BEGIN {WRITE_ANGLE_RATE}
  WRITELN(OUTPUT,' THE JOINT ANGLE RATES (IN DEG/SEC) ARE :');
  FOR K_I := 1 TO N DO
    BEGIN
      WITH R_FILE DO
        WRITELN (OUTPUT,'THETA_DOT['',K_I:1,'']= ',Q_DOT[K_I]:14:8);
      END;
    WRITELN(OUTPUT);
  END; {WRITE_ANGLE_RATE}

```

```

PROCEDURE INIT_LINK;
{ASSIGN THE MITSUBISHI ROBOT}
BEGIN {INIT_LINK}
  { E MATRIX }
  WITH R_FILE DO
    BEGIN
      E[1,1] := 1.0; E[2,2] := 1.0; E[3,3] := 1.0;
      E[3,4] := 196.1;
    END;
  WITH R_FILE DO
    BEGIN
      N := 5;
      LINK_TYPE := REVOLUTE;
      LINK_PARM_A[1] := 0.0; LINK_PARM_D[1] := 250.0;
      LINK_PARM_SA[1] := 0.0; LINK_PARM_CA[1] := 1.0;
      LINK_PARM_A[2] := 0.0; LINK_PARM_D[2] := 0.0;
      LINK_PARM_SA[2] := -1.0; LINK_PARM_CA[2] := 0.0;
      LINK_PARM_A[3] := 220.0; LINK_PARM_D[3] := 0.0;
      LINK_PARM_SA[3] := 0.0; LINK_PARM_CA[3] := 1.0;
      LINK_PARM_A[4] := 160.0; LINK_PARM_D[4] := 0.0;
      LINK_PARM_SA[4] := 0.0; LINK_PARM_CA[4] := 1.0;
      LINK_PARM_A[5] := 0.0; LINK_PARM_D[5] := 0.0;
      LINK_PARM_SA[5] := 1.0; LINK_PARM_CA[5] := 0.0;
      LINK_PARM_A[6] := 0.0; LINK_PARM_D[6] := 0.0;
      LINK_PARM_SA[6] := 0.0; LINK_PARM_CA[6] := 1.0;
      SIN_COS (ANGLE_RAD[1], SIN_THETA[1], COS_THETA[1]);
    END;
  END; {INIT_LINK}

PROCEDURE INIT_GMF;
{ASSIGN THE GMF ROBOT}
BEGIN {INIT_GMF}
  { E MATRIX }
  WITH R_FILE DO
    BEGIN
      E[1,1] := 1.0; E[2,2] := 1.0; E[3,3] := 1.0;
      E[3,4] := 150.0;
    END;
  WITH R_FILE DO
    BEGIN
      N := 6;
      LINK_TYPE := REVOLUTE;
      LINK_PARM_A[1] := 0.0; LINK_PARM_D[1] := 0.0;
      LINK_PARM_SA[1] := 0.0; LINK_PARM_CA[1] := 1.0;
      LINK_PARM_A[2] := 0.0; LINK_PARM_D[2] := 0.0;
      LINK_PARM_SA[2] := -1.0; LINK_PARM_CA[2] := 0.0;
      LINK_PARM_A[3] := 1150.0; LINK_PARM_D[3] := 0.0;

```

```

LINK_PARM_SA[3] := 0.0; LINK_PARM_CA[3] := 1.0;
LINK_PARM_A[4] := 95.0; LINK_PARM_D[4] := 0.0;
LINK_PARM_SA[4] := -1.0; LINK_PARM_CA[4] := 0.0;
LINK_PARM_A[5] := 0.0; LINK_PARM_D[5] := 1400.0;
LINK_PARM_SA[5] := -1.0; LINK_PARM_CA[5] := 0.0;
LINK_PARM_A[6] := 0.0; LINK_PARM_D[6] := 225.0;
LINK_PARM_SA[6] := 1.0; LINK_PARM_CA[6] := 0.0;
LINK_PARM_A[7] := 0.0; LINK_PARM_D[7] := 0.0;
LINK_PARM_SA[7] := 0.0; LINK_PARM_CA[7] := 1.0;
SIN_COS(ANGLE_RAD[1], SIN_THETA[1], COS_THETA[1]);
END;
END; {INIT_GMF}

PROCEDURE TST_KIN;

BEGIN {K}
  {1. INITIALIZE LINK PARAMETERS}
  WRITE(OUTPUT, ' TEST MISHUBISHI(M) OR GMF(G)? => ');
  READLN(INPUT, IN_CHR);
  IF (IN_CHR = G) THEN
    INIT_GMF
  ELSE
    INIT_LINK;
  {2. ASSIGN JOINT VARIABLES }
  {WRITE(OUTPUT, ' DEFAULT N= 5, KEY IN THE DEG_OF_FREDOOM=> ');
  READLN(INPUT, N);}
  WITH R_FILE DO
BEGIN
  ANGLE_RAD[2] := 40 * pi / 180.0;
  ANGLE_RAD[3] := 40 * pi / 180.0;
  ANGLE_RAD[4] := 40 * pi / 180.0;
  ANGLE_RAD[5] := 40 * pi / 180.0;
  ANGLE_RAD[6] := 40 * pi / 180.0;
END;

  WITH R_FILE DO
BEGIN
  ANGLE_RAD[2] := 8.35048 * pi / 180.0;
  ANGLE_RAD[3] := -24.47175 * pi / 180.0;
  ANGLE_RAD[4] := 76.73547 * pi / 180.0;
  ANGLE_RAD[5] := 127.73643 * pi / 180.0;
  ANGLE_RAD[6] := -111.64963 * pi / 180.0;
END;

  WITH R_FILE DO
BEGIN
  ANGLE_RAD[2] := 0.0 * pi / 180.0;
  ANGLE_RAD[3] := 0.0 * pi / 180.0;
  ANGLE_RAD[4] := 0.0 * pi / 180.0;
  ANGLE_RAD[5] := 0.0 * pi / 180.0;
  ANGLE_RAD[6] := 0.0 * pi / 180.0;
END;

```

```

WRITE_ANGLE;
  WRITE(OUTPUT, 'DEFAULT JOINT ANGLES ARE AS ABOVE, CHANGE THEM? ',
        ' (Y OR O) => ');
  READLN(INPUT, IN_CHR);
  WRITELN(OUTPUT, ' IN_CHR= ', IN_CHR);
  IF ( IN_CHR = O ) THEN
    BEGIN END;
  WHILE ( IN_CHR = Y ) DO
    BEGIN
      FOR I_TST := 1 TO N DO
        BEGIN
          WRITELN(OUTPUT, 'KEY IN ANGLE[' , I_TST, ' ] IN DEGREES =>');
          READLN(INPUT, ANGLE_S);
          writeln(output, angle_s:14:8);
          WITH R_FILE DO
            ANGLE_RAD[I_TST+1] := ANGLE_S * pi / 180.0;
          END;
          IN_CHR := O;
        END;
      {3. TEST THE PROCEDURE KIN_JAC }
      writeln(output, ' test for kin_jac -- micro sin_cos');
      WRITE_ANGLE1;
      KIN_JAC;
      WRITE_JAC;
      WRITE_X;
      writeln(output, ' test for DIRkin_TST -- PASCAL PROGRAM');
      WRITE_ANGLE1;
      DIRKIN_TST;
      WRITE_X;
      writeln(output, ' test for kin_jac -- true sine/cosine');
      WRITE_ANGLE1;
      KIN_JAC1;
      WRITE_JAC;
      WRITE_X;
    END; {K}

PROCEDURE TST_PSEUDO;
var
  i1i, j1j : integer;
  XDOT : ARRAY6;
  V6, VOUT : ARRAY7;
  RESULT5 : ARRAY7;
  RESULT : ARRAY7;
  sing : boolean;

```

```

BEGIN(PSEUDO_INV)

  TST_KIN;
  WITH R_FILE DO
  BEGIN
    X_DOT[1] := 0.0; { IN DEG/SEC }
    X_DOT[2] := 0.0; { IN DEG/SEC }
    X_DOT[3] := -10.0; { IN DEG/SEC }
    X_DOT[4] := 0.0; { IN MM/SEC }
    X_DOT[5] := 500.0; { IN MM/SEC }
    X_DOT[6] := 0.0; { IN MM/SEC }
  END;
  WRITELN(OUTPUT, 'DEFAULT X_DOT ARE:');
  FOR I_TST := 1 TO N DO
  WITH R_FILE DO
    WRITE(OUTPUT, X_DOT[I_TST]:12:6);
  WRITELN(OUTPUT);
  ( WRITE(OUTPUT, ' CHANGE THEM? (Y OR O) => ');
  READLN(INPUT, IN_CHR);
  WRITELN(OUTPUT, ' IN_CHR= ', IN_CHR);
  WHILE ( IN_CHR = Y ) DO
  BEGIN
    FOR I_TST := 1 TO 6 DO
    BEGIN
      WRITE(OUTPUT, 'KEY IN X_DOT[' , I_TST, ' ] IN DEG/SEC',
        ' OR MM/SEC =>');
      WITH R_FILE DO
      READLN(INPUT, X_DOT[I_TST]);
    END;
    WRITELN(OUTPUT, 'NEW X_DOT ARE:');
    FOR I_TST := 1 TO N DO
    WITH R_FILE DO
      WRITE(OUTPUT, X_DOT[I_TST]:12:6);
    WRITELN(OUTPUT);
    IN_CHR := O;
  END; }
  (TEST)
  FOR I_TST := 1 TO 6 DO
  WITH R_FILE DO
    XDOT[I_TST] := X_DOT[I_TST];
    FOR I_TST := 1 TO N DO
      RESULTS[I_TST] := 0.0;
    FOR I_TST := 1 TO N DO
      WRITE(OUTPUT, RESULTS[I_TST]:12:6);
  WRITELN(OUTPUT);
  WRITELN(OUTPUT, 'NEW X_DOT ARE:');

```

```

        FOR I_TST := 1 TO 6 DO
        WITH R_FILE DO
            WRITE(OUTPUT,XDOT[I_TST]);
WRITELN(OUTPUT);
        WITH R_FILE DO
PSEUDO(XDOT,6,5,SINGULARITY,RESULTS);
            WRITELN(OUTPUT,'PASCAL RESULT IS: ');
            FOR I_TST := 1 TO N DO
                WRITE(OUTPUT,RESULTS[I_TST]);
WRITELN(OUTPUT);
(TEST)
            WRITELN(OUTPUT,'NEW X_DOT ARE:');
            FOR I_TST := 1 TO N DO
                WITH R_FILE DO
                    WRITE(OUTPUT,X_DOT[I_TST]:12:6);
WRITELN(OUTPUT);
            write_jac;
            WITH R_FILE DO
                jt_mul_j(S);
            write_s;
FOR III := 1 TO 7 DO
    V6[III] := III;
JT_MUL_V61(V6,VOUT);
WRITELN(OUTPUT,' TEST FOR JT_MUL_V6 ');
WRITELN(OUTPUT,'V6 IS: ');
FOR III := 1 TO 7 DO
    WRITE(OUTPUT,V6[III]:10:5);
    WRITELN(OUTPUT);
WRITELN(OUTPUT,'VOUT IS: ');
FOR III := 1 TO 5 DO
    WRITE(OUTPUT,VOUT[III]:14:4);
    WRITELN(OUTPUT);
(TEST)
        FOR I_TST := 1 TO N DO
        WITH R_FILE DO
            Q_DOT[I_TST]:= 0.0;
            FOR I_TST := 1 TO N DO
                WITH R_FILE DO
                    WRITE(OUTPUT,Q_DOT[I_TST]:12:6);
WRITELN(OUTPUT);
            PSEUDO_INV;
WRITELN(OUTPUT,'MICRO PSEUDO HAS THE RERULT AS: ');
            FOR I_TST := 1 TO N DO
                WITH R_FILE DO
                    WRITE(OUTPUT,Q_DOT[I_TST]);
WRITELN(OUTPUT);
            WRITELN(OUTPUT,'PASCAL RESULT IS: ');
            FOR I_TST := 1 TO N DO
                WRITE(OUTPUT,RESULTS[I_TST]);

```



```

WRITELN(OUTPUT);
WRITELN(OUTPUT,'END OF PSEUDO_INV *****');
(TEST)
    WRITE_THETA_DOT;
    END;(PSEUDO_INV)

PROCEDURE TST_ERR;
VAR
    DELTA_TST : REAL;
    I_T,J_T : INTEGER;

BEGIN ( TST_ERR )
    (TEST THE ZERO CONFIGURATION)
    writeln(output,' AT ZERO CONFIGURATION ');
    WITH R_FILE DO
        BEGIN (R_FILE)
            FOR I_T := 1 TO 3 DO
                BEGIN
                    FOR J_T := 1 TO 3 DO
                        X_D[I_T,J_T] := 0.0;
                        X_D[I_T,I_T] := 1.0;
                        X_D[1,4] := 380.0;
                        X_D[2,4] := 0.0;
                        X_D[3,4] := 446.1;
                    END;
                END;(R_FILE)
                TST_KIN;
                WRITE_Xd;
                SUB_ERR(DELTA_TST);
                WRITELN(OUTPUT,'DELTA IS: ',DELTA_TST);
            END;( TST_ERR )

PROCEDURE TST_CORRECTOR;
VAR
    I_T,J_T : INTEGER;
BEGIN(TST_COR)
    INIT_XN;
    WITH R_FILE DO
        BEGIN
            SUB_COR(X4_C);
            WRITELN(OUTPUT,'X4_C IS : ');
            FOR I_T := 1 TO N DO
                WRITE(OUTPUT,X4_C[I_T]);
            WRITELN(OUTPUT);
        END;
    END;(TST_COR)

```

```

PROCEDURE TST_PREDICTOR;
VAR
  I_T, J_T : INTEGER;
BEGIN(TST_PRE)
  INIT_XN;
  WITH R_FILE DO
    BEGIN
      SUB_PRE(X4_P);
      WRITELN(OUTPUT, 'X4_P IS : ');
      FOR I_T := 1 TO N DO
        WRITE(OUTPUT, X4_P[I_T]);
      WRITELN(OUTPUT);
    END;
  END; (TST_PRE)

PROCEDURE TST_ADJUST;
VAR
  I_T, J_T : INTEGER;
BEGIN(TST_ADJ)
  INIT_XN;
  WITH R_FILE DO
    BEGIN
      SUB_PRE(X4_P);
      WRITELN(OUTPUT, 'X4_P IS : ');
      FOR I_T := 1 TO N DO
        WRITE(OUTPUT, X4_P[I_T]);
      WRITELN(OUTPUT);
      SUB_ADJ(X4_P);
    ( FOR TESTING ONLY )
    WRITELN(OUTPUT, ' X_N MATRIX = ');
    FOR I_T := 1 TO 5 DO
      BEGIN
        FOR J_T := 1 TO 4 DO
          WRITE(OUTPUT, X_N[I_T, J_T], ' ');
        WRITELN(OUTPUT);
      END;
    WRITELN(OUTPUT, ' X_N_DOT MATRIX = ');
    FOR I_T := 1 TO 5 DO
      BEGIN
        FOR J_T := 1 TO 4 DO
          WRITE(OUTPUT, X_N_DOT[I_T, J_T], ' ');
        WRITELN(OUTPUT);
      END;
    ( FOR TESTING ONLY )

    END;
  END; (TST_ADJ)

```

```

BEGIN { MAIN }
  INIT;
  WITH CONTROL DO
    BEGIN
  REPEAT
    writeln(output,'Which function are you going to test?');
    WRITELN(OUTPUT,'KIN_JAC(K),PSEUDO_INV(J),INV_KIN(I)');
    WRITELN(OUTPUT,'PREDICTOR(P),CORRECTOR(T),ERROR(D),ADJUST(A)');
    write(output,'RECIPROCAL(R), SINE(S), COSINE(C) OR END(E) => ');
    READLN(INPUT,IN_CHR);
    CASE IN_CHR OF
      J: TST_PSEUDO;
      P: BEGIN
          TST_PREDICTOR;
        END;
      T: BEGIN
          TST_CORRECTOR;
        END;
      A: BEGIN
          TST_ADJUST;
        END;
      D: BEGIN
          TST_ERR;
        END;
      K: BEGIN (K)
          TST_KIN;
        END;
      R: BEGIN (R)
          SEED_SELECT := RECIPROCAL;
          WRITE(OUTPUT,' KEY IN THE TESTING VALUE => ');
          READLN(INPUT,M_REC_VAR);
          SUB_REC(M_REC_VAR);
          WITH R_FILE DO
            BEGIN
              WRITELN(OUTPUT,'      ITS RECIPROCAL= ', REC:16:12);
              REC := 1/M_REC_VAR;
              WRITELN(OUTPUT,'      TRUE RECIPROCAL= ', REC:16:12);
              TEMP[3] :=0;
              FOR I_TST := 1 TO 1000 DO
                BEGIN
                  TEMP[1] := 0.001 * I_TST;
                  SUB_REC(TEMP[1]);
                {   WRITELN(OUTPUT,'      FOR ', TEMP[1]:16:12);
                  WRITELN(OUTPUT,'      ITS RECIPROCAL= ', REC:16:12);
                }
                  TEMP[2] := ABS (1/TEMP[1] -REC);
                  IF ( TEMP[3] < TEMP[2] ) THEN

```

```

        BEGIN
        TEMP[3] := TEMP[2];
        TEMP[4] := TEMP[1];
        TEMP[5] := REC;
        TEMP[6] := 1/TEMP[1];
        END;
    END;

    WRITELN(OUTPUT, 'FOR SUB_REC ');
    WRITELN(OUTPUT, 'THE MAXIMUM ERROR IS ', TEMP[3]:16:12);
    WRITELN(OUTPUT, '      HAPPENED AT ', TEMP[4]:16:12);
    WRITELN(OUTPUT, '      ITS RECIPROCAL= ', TEMP[5]:16:12);
    WRITELN(OUTPUT, '      TRUE RECIPROCAL= ', REC:16:12);

    TEMP[3] := 0;
    FOR I_TST := 1 TO 1000 DO
    BEGIN
        TEMP[1] := 0.001 * I_TST;
        SUB_REC3(TEMP[1]);
    {   WRITELN(OUTPUT, '      FOR ', TEMP[1]:16:12);
    WRITELN(OUTPUT, '      ITS RECIPROCAL= ', REC:16:12);
    }   TEMP[2] := ABS (1/TEMP[1] - REC);
        IF ( TEMP[3] < TEMP[2] ) THEN
        BEGIN
            TEMP[3] := TEMP[2];
            TEMP[4] := TEMP[1];
            TEMP[5] := REC;
            TEMP[6] := 1/TEMP[1];
        END;
    END;
    WRITELN(OUTPUT, 'FOR SUB_REC3 ');
    WRITELN(OUTPUT, 'THE MAXIMUM ERROR IS ', TEMP[3]:16:12);
    WRITELN(OUTPUT, '      HAPPENED AT ', TEMP[4]:16:12);
    WRITELN(OUTPUT, '      ITS RECIPROCAL= ', TEMP[5]:16:12);
    WRITELN(OUTPUT, '      TRUE RECIPROCAL= ', REC:16:12);

    END;
END; (R)
S:
BEGIN (S)
    tst_sin;
    (   WRITE(OUTPUT, ' KEY IN THE TESTING ANGLE IN DEGREES => ');
    READLN(INPUT, ANGLE_S);
    ANGLE_RAD := ANGLE_S * PI / 180.0;
    SIN_COS(ANGLE_RAD, SIN_OUT2, COS_OUT2);
    WRITELN(OUTPUT, 'FOR ANGLE= ', ANGLE_S, ' SIN(ANGLE)=',
        SIN_OUT2, ' COS(ANGLE)= ', COS_OUT2);
    )

```

```

( testing the sin_seed_table )
(   SEED_SELECT := SIN_TAB ;
    SEED_IN := ANGLE_S * PI /180.0;
    SEED_TABLE;
    WRITELN(OUTPUT,' SEED_IN ( IN RAD )= ',SEED_IN:12:8,
            'SEED_OUT FOR SINE= ', SEED_OUT:12:8);
) END; (S)
C: BEGIN (C)
    WRITE(OUTPUT,' KEY IN THE TESTING ANGLE IN DEGREES => ');
    READLN(INPUT,ANGLE_S);
    SEED_SELECT := COS_TAB ;
    SEED_IN := ANGLE_S * PI /180.0;
    SEED_TABLE;
    WRITELN(OUTPUT,' SEED_IN ( IN RAD )= ',SEED_IN:12:8,
            'SEED_OUT FOR COSINE= ', SEED_OUT:12:8);
END; (C)
END; (CASE)
UNTIL IN_CHR = E;
END; (CONTROL)
END.
( CASE SEED_SELECT OF
    SIN_TAB : SUB_SIN_TAB;
    COS_TAB : SUB_COS_TAB;
    RECIPROCAL: SUB_REC;
)

```

```

[OVERLAID]program PIPIK1( INPUT, OUTPUT );

{***** FILE: PIPIK1.PAS *****)

{*****}
{*      PROGRAM: PIPIK1.PAS      *}
{*****}

{*****}
{*                                     *}
{* PROGRAMMER: Yusheng Tsai        *}
{* DATE:      March 31, 1986      *}
{*                                     *}
{* FUNCTION:      Simulates Numerical Approach for Inverse      *}
{*               Kinematics Algorithm - compute the joint angles *}
{*               *}
{* USER GUIDE:    THE CALLING FORMAT IS:                          *}
{*               PIPIK1                                           *}
{*               *}
{* PROGRAMMER                                           *}
{* GUIDE:      $ PAS PIPIK1                                     *}
{*               $ LINK PIPIK1,INITQ1,ERROR,PREDITION,EVALUATION,*}
{*               CORRECTION,PSEUDO, TASK, DIRKIN, JAC,          *}
{*               ADJUST                                         *}
{*               OR $ @PIPIK1                                   *}
{*               *}
{* PROCEDURES                                           *}
{* CALLED:      INITQ1, ERROR, PREDICTION, EVALUATION, TASK,    *}
{*               CORRECTION, PSEUDO, DIRKIN, JAC, ADJUST        *}
{*               *}
{* FUNCTIONS                                           *}
{* CALLED:      ACTAN2                                         *}
{*               *}
{* GLOBAL VARIABLES                                           *}
{* REFERENCED:  ALL                                           *}
{*               *}
{* GLOBAL VARIABLES                                           *}
{* MODIFIED:    ALL                                           *}
{*****}

TYPE
  FG = ( PREDICT, CORRECT);
  MATX54 = ARRAY [1..5,1..4] OF real;

%INCLUDE 'IKGLB.PAS'

LABEL 9,10,20,30,50,100,200;

[EXTERNAL]PROCEDURE TASK1(VAR X_D: MATX44;
                          TIME_TASK1: real    );
  EXTERN;

```

```

[EXTERNAL]PROCEDURE DIRKIN(NN : INTEGER; VAR XX : MATX44); EXTERN;

[EXTERNAL]PROCEDURE PREDICTION (PTIME : real; VAR PQP : ARRAY10);
    EXTERN;
[EXTERNAL]PROCEDURE CORRECTION (CTIME : real; VAR CQC : ARRAY10);
    EXTERN;
[EXTERNAL]PROCEDURE EVALUATION(VEL_HAND:ARRAY6); EXTERN;
[EXTERNAL]PROCEDURE ADJUST(FG2T:BOOLEAN); EXTERN;
[EXTERNAL]PROCEDURE INTERPOLATION; EXTERNAL;
[EXTERNAL]PROCEDURE ERROR( EX_D,EX: MATX44; VAR DELTA_ERR: real);
    EXTERN;
[EXTERNAL]PROCEDURE INITIQ1; EXTERN;

CONST
    PI = 3.141592653589793;

VAR
    MMX :MATX44;
    MAX_STEP : real; ( MAXIMUM STEP SIZE )
    MAX_ERR : real; ( MAXIMUM ERROR )
    TTIME : real;
    JAC_NO:integer;
    PRE_NO:integer;
    COR_NO1:integer;
    COR_NO:integer;
    ite_NO:integer;
    MX_TEMP : MATX44;
    FG2T:BOOLEAN;
    I,J : INTEGER;
    TIME_TASK1 : real;
    QP,QC : ARRAY10;( PREDICTED AND CORRECTED JOINT ANGLED )
    QTASK1 : ARRAY10;( DESIRED TASK1 JOINT ANGLES )
    MIN_DELTA_TIME : real; ( MINIMUM STEP )
    NSTORE : INTEGER;
    DELTA1,DELTA2,DELTA3 : real;
    EPSER1 : real; ( MAXIMUM ALLOWED ERROR )
    EPSER2 : real; ( MAXIMUM ALLOWED ERROR )
    ETA : INTEGER ; ( FOR realING STEPS )
    NMAX : INTEGER ; ( FOR CORRECTION LOOP )
    FLAG : FG;
    VEL_HAND: ARRAY6;
    vel_test: array6;
    TEND : real; ( TIME FOR ENDING THE PROGRAM )
    NO : INTEGER;

```

```

PROCEDURE INITP;
( Initialize all the parameters used in this simulation )
BEGIN { INITP }
  ITE_NO :=0; JAC_NO := 0; PRE_NO := 0; COR_NO := 0; COR_NO1:=0;
  { INITIALIZE THE HAND VELOCITY }
  FOR I := 1 TO 6 DO
    VEL_HAND[I] := 0.0000;
    VEL_HAND[3] := - 10.0000000000;          { DEG/SEC }
    VEL_HAND[5] := - 500.0;                  { mm * rad/deg/SEC }
    TTIME := 1.0000000000;      { DISPLAY OUTPUT PER SECOND }
    TEND := 36.00000; { ASSUME THE SPEED IS 10 DEG/SEC }
    DELTA_TIME := 1.000000000000000000E-2; { Delta_t = 0.01 sec }
    MAX_STEP := DELTA_TIME;
    MAX_ERR := 0.0;
    MIN_DELTA_TIME := 0.0000010000000000;
    TIME := 0.0;
    EPSER1 :=0.0000010000000000;
    EPSER2 :=0.25000000000;
    ETA := 50;
    NMAX := 3;
    FG2T := FALSE;
    NSTORE := 4;
  END; { INITP }

```

```

PROCEDURE WRITEOUT;
VAR
  I : INTEGER;
BEGIN { WRITEOUT }
  WRITELN ( OUTPUT, 'TIME= ',TIME:14:8);
  WRITE   ( OUTPUT, 'QP= ');
  FOR I := 1 TO N DO
    WRITE   ( OUTPUT, QP[I]:12:6,' ');
  WRITELN;
  WRITE   ( OUTPUT, 'QC= ');
  FOR I := 1 TO N DO
    WRITE   ( OUTPUT, QC[I]:12:6,' ');
  WRITELN;
  { WRITE OUT X, X_D }
  WRITELN (OUTPUT,'***** X ***** ');
  FOR I := 1 TO 4 DO
    BEGIN
      FOR J := 1 TO 4 DO
        WRITE(OUTPUT,X[I,J]:12:6);
        WRITELN(OUTPUT);
      END;
      WRITELN (OUTPUT,'***** X_D ***** ');
      FOR I := 1 TO 4 DO
        BEGIN
          FOR J := 1 TO 4 DO
            WRITE(OUTPUT,X_D[I,J]:12:6);
            WRITELN(OUTPUT);
          END;
        END;
      END;
    END; { WRITEOUT }

```



```

PROCEDURE INIT80(VAR A: MATX44);

VAR
  I, J: INTEGER; { SUBSCRIPTS }

BEGIN
  FOR I := 1 TO 4 DO
    FOR J := 1 TO 4 DO
      IF I = J THEN
        A[I, J] := 1
      ELSE
        A[I, J] := 0
      END; { INIT80 }

PROCEDURE CAL_VEL(TIME:real);
{ COMPUTE THE HAND VELOCITY VECTOR ON TIME }
BEGIN { CAL_HAND }
END; { CAL_HAND }

{ MAIN PROGRAM BEGINS }
BEGIN { MAIN }
  INITP; { Initialize SIMULATION parameters }
  INITIQL; { Initialize the starting angles }
  TIME := 0.0;
  FOR I := 1 TO 6 DO
    WITH KINMC_VARS[I] DO
      ANGLE := LXN[I,1];
      DIRKIN(N,X);
      WRITELN (OUTPUT,'*****   X   *****' );
      FOR I := 1 TO 4 DO
        BEGIN
          FOR J := 1 TO 4 DO
            WRITE(OUTPUT,X[I,J]:12:6);
            WRITELN(OUTPUT);
          END;
          EVALUATION(VEL_HAND);
        END;
      9:
      ITE_NO := ITE_NO + 1;
      DIRKIN(N,X);
      MX_TEMP := X;

```

```

10:
  TIME := TIME + DELTA_TIME;
  IF ( TIME > TEND + 0.001 ) THEN
    BEGIN
      DELTA_TIME := DELTA_TIME - (TIME - TEND);
      TIME := TEND;
    END;
  TASK1(X_D,TIME); { Find the desired position and orientation }
  ERROR(X_D,MX_TEMP,DELTA1);
  writeln(output,'time= ', time:12:6);
  WRITELN (OUTPUT,'DELTA1 = ', DELTA1:12:6);
  PREDICTION(TIME,QP);
  PRE_NO := PRE_NO + 1;
  DIRKIN(N,X); { Find X for predicted angles QP }
  ERROR(X_D,X,DELTA2);
  IF ( DELTA2 > ( DELTA1 + 0.001 ) ) THEN
    GOTO 20
  ELSE
    BEGIN { ELSE 10 }
      IF ( DELTA2 < EPSER1 ) THEN
        BEGIN
          IF ( MAX_ERR < DELTA2 ) THEN MAX_ERR := DELTA2;
          EVALUATION(VEL_HAND);
          JAC_NO := JAC_NO + 1;
          FLAG := PREDICT;
          GOTO 50;
        END
      ELSE
        BEGIN { ELSE 30 }
          COR_NO1 := COR_NO1 + 1;
          NO := 1;
          CAL_VEL(TIME);
          EVALUATION(VEL_HAND);
          JAC_NO := JAC_NO + 1;
          CORRECTION(TIME,QC);
          COR_NO := COR_NO + 1;
          DIRKIN(N,X); { Find X for CORRECTed angles QC }
          ERROR(X_D,X,DELTA3);
          IF ( DELTA3 > DELTA2 + 0.01 ) THEN GOTO 20
          ELSE
            IF ( DELTA3 > EPSER2 ) THEN
              BEGIN
                NO := NO + 1;
                IF ( NO > NMAX ) THEN GOTO 20
                ELSE GOTO 30;
              END
            ELSE
              BEGIN
                IF ( MAX_ERR < DELTA3 ) THEN MAX_ERR := DELTA3;
                FLAG := CORRECT;
                GOTO 50;
              END;
            END; { ELSE 30 }
          END; { ELSE 10 }
        30:
        END; { ELSE 10 }

```

```

20:
  IF ( DELTA3 > DELTA2 ) OR ( DELTA2 > DELTA1 ) THEN
    BEGIN
      WRITELN (OUTPUT,'DELTA1 = ', DELTA1:12:6);
      WRITELN (OUTPUT,'DELTA2 = ', DELTA2:12:6);
      WRITELN (OUTPUT,'DELTA3 = ', DELTA3:12:6);
    END;
    BEGIN ( HALF STEP )
      TIME := TIME - DELTA_TIME;
      DELTA_TIME := 0.5 * DELTA_TIME;
      IF ( DELTA_TIME < MIN_DELTA_TIME ) THEN
        BEGIN
          WRITELN(OUTPUT,'DELTA_TIME = ',DELTA_TIME:12:6);
          GOTO 100;
        END
      ELSE
        BEGIN
          INTERPOLATION;
          nstore := 4;
          GOTO 10;
        END;
      END; ( HALF STEP )
50: BEGIN ( 50 )
      IF ( TIME > TTIME - 0.000001 ) THEN
        BEGIN
          TTIME := TTIME + 1.00000000;
          WRITEOUT;
          WRITELN(OUTPUT,'NSTORE= ',NSTORE);
          WRITELN(OUTPUT,'delta_TIME= ',DELTA_TIME:14:8);
          WRITELN(OUTPUT,'TIME = ',TIME:14:8);
          WRITELN (OUTPUT,'DELTA1 = ', DELTA1:12:6);
          WRITELN (OUTPUT,'DELTA2 = ', DELTA2:12:6);
          WRITELN (OUTPUT,'DELTA3 = ', DELTA3:12:6);
        END;
        ( Update angles )
        BEGIN ( angle )
          FOR I := 1 TO N DO
            WITH KINMC_VARS[I] DO
              IF ( FLAG = CORRECT ) THEN
                ANGLE := QC[I]
              ELSE
                ANGLE := QP[I];
            END;( ANGLE )
          NSTORE := NSTORE + 1;
          IF ( TIME < TEND ) THEN

```

```

      BEGIN (90)
      IF (NSTORE < 7) THEN FG2T := FALSE
      ELSE
        IF ( DELTA2 < EPSER1/ETA )
          OR ( DELTA3 < EPSER1/ETA)
          THEN
            BEGIN
              NSTORE := 4;
              FG2T := TRUE;
              DELTA_TIME := DELTA_TIME + DELTA_TIME;
              IF ( MAX_STEP < DELTA_TIME ) THEN
                MAX_STEP := DELTA_TIME;
              END
            ELSE FG2T :=FALSE;
            ( Adjust Xn and dot Xn )
          ADJUST(FG2T);
          GOTO 9;
        END (90)
      ELSE GOTO 200;
      END; { 50 }

100:
  { Singularity process }
  WRITELN ( OUTPUT, ' THE SINGULARITY POINT IS HERE: ');
  WRITEOUT;

200:
  WRITEOUT;
  WRITELN(OUTPUT,'NSTORE= ',NSTORE);
  WRITELN(OUTPUT,'delta_TIME= ',DELTA_TIME:14:8);
  WRITELN(OUTPUT,'TIME = ',TIME:14:8);
  WRITELN (OUTPUT,'DELTA1 = ', DELTA1:12:6);
  WRITELN (OUTPUT,'DELTA2 = ', DELTA2:12:6);
  WRITELN (OUTPUT,'DELTA3 = ', DELTA3:12:6);
  WRITELN (OUTPUT,'FINAL DELTA_TIME = ',DELTA_TIME:14:8);
  WRITELN (OUTPUT,'MAXIMUM STEP SIZE= ',MAX_STEP:14:8);
  WRITELN (OUTPUT,'MAXIMUM ERROR    = ',MAX_ERR:14:8);
  WRITELN (OUTPUT,'ETA              = ',ETA:5);
  WRITELN (OUTPUT,'CONVERGENCE      = ',EPSER2:14:8);
  WRITELN (OUTPUT,'ITERATION_NUMBER = ',ITE_NO:5);
  WRITELN (OUTPUT,'PREDICTION_NUMBER= ',PRE_NO:5);
  WRITELN (OUTPUT,'COR_LOOP_NUMBER  = ',COR_NO1:5);
  WRITELN (OUTPUT,'CORRECTION_NUMBER= ',COR_NO:5);
  WRITELN (OUTPUT,'JACOBN_NUMBER    = ',JAC_NO:5);
END. { MAIN }

```

```

[OVERLAID]program GMF( INPUT, OUTPUT );

(***** FILE: GMF.PAS *****)

(*****)
{*      PROGRAM: GMF.PAS      *}
(*****).

(*****)
{*
{* PROGRAMMER: Yusheng Tsai
{* DATE:      SEP.16, 1985
{*
{* FUNCTION:      Simulates numerical approach for Inverse
{*                  Kinematics algorithm for the proposed
{*                  Inverse Kinematics Processor.
{*
{* USER GUIDE:    THE CALLING FORMAT IS:
{*                  GMF
{*
{* PROGRAMMER
{* GUIDE:          $ PAS GMF
{*
{* PROCEDURES
{* CALLED:         INITQ1, SUB_ERR, SUB_PRE, SUB_COR, SUB_ADJ,
{*                  TASK31, KIN_JAC, PSEUDO_INV
{*
{* FUNCTIONS
{* CALLED:         ACTAN2
{*
(*****)
$INCLUDE 'GLOBAL.PAS'

[EXTERNAL]PROCEDURE TASK5(VAR X_D: ARRAY34;
                        VAR VEL_HD1:ARRAY7;
                        TIME_TASK1: REAL    );
    EXTERN;

[EXTERNAL]PROCEDURE KIN_JAC; EXTERN;

[EXTERNAL]PROCEDURE SUB_PRE(VAR THETA_PRE1: ARRAY7);
    EXTERN;
[EXTERNAL]PROCEDURE SUB_COR(VAR THETA_COR1: ARRAY7);
    EXTERN;
[EXTERNAL]PROCEDURE SUB_ERR(VAR DELTA_OUT1: REAL);
    EXTERN;
[EXTERNAL]PROCEDURE PSEUDO_INV; EXTERN;
[EXTERNAL]PROCEDURE SUB_ADJ(VAR THETA_ADJ1: ARRAY7);
    EXTERN;
[EXTERNAL]PROCEDURE INITQ1; EXTERN;
[EXTERNAL]PROCEDURE WRITE_VEC(VECTOR:ARRAY7; NO : INTEGER);
    EXTERN;

```

```

[GLOBAL]PROCEDURE WRITE_X;
VAR
  K_I,J_I : INTEGER;
BEGIN {WRITE_X}
  WRITELN(OUTPUT,'      X MATRIX IS :  ');
  WITH R_FILE DO
    BEGIN
      FOR K_I := 1 TO 3 DO
        BEGIN
          FOR J_I := 1 TO 4 DO
            WRITE(OUTPUT,X[K_I,J_I]:14:8);
            WRITELN(OUTPUT);
          END;
        END;
      END;
    END; {WRITE_X}

[GLOBAL]PROCEDURE WRITE_Xd;
VAR
  K_I,J_I : INTEGER;
BEGIN {WRITE_Xd}
  WRITELN(OUTPUT,'      X_D MATRIX IS :  ');
  WITH R_FILE DO
    BEGIN
      FOR K_I := 1 TO 3 DO
        BEGIN
          FOR J_I := 1 TO 4 DO
            WRITE(OUTPUT,X_D[K_I,J_I]:14:8);
            WRITELN(OUTPUT);
          END;
        END;
      END;
    END; {WRITE_Xd}

[GLOBAL]PROCEDURE WRITE_JAC;
VAR
  K_I,J_I : INTEGER;
BEGIN {WRITE_X}
  WRITELN(OUTPUT,'      JACOBIAN MATRIX IS :  ');
  WITH R_FILE DO
    BEGIN
      FOR K_I := 1 TO 6 DO
        BEGIN
          FOR J_I := 1 TO N DO
            WRITE(OUTPUT,JACOBN_MAT[K_I,J_I]:14:8);
            WRITELN(OUTPUT);
          END;
        END;
      END;
    END; {WRITE_X}

```

```

[GLOBAL]PROCEDURE WRITE_ANGLE;
VAR
  K_I,J_I : INTEGER;
  ANGLE_S1 : REAL;
BEGIN {WRITE_ANGLE}
  WRITELN(OUTPUT,' WITH JOINT ANGLES :');
  FOR K_I := 1 TO N DO
    BEGIN
      WITH R_FILE DO
        ANGLE_S1 := ANGLE_RAD[K_I+1] * 180.0 / PI;
        WRITE (OUTPUT,' ',ANGLE_S1:14:8);
      END;
    WRITELN(OUTPUT);
  END; {WRITE_ANGLE}

[GLOBAL]PROCEDURE WRITE_THETA_DOT;
VAR
  K_I,J_I : INTEGER;
  ANGLE_S1 : REAL;
BEGIN {WRITE_ANGLE_RATE}
  WRITELN(OUTPUT,' THE JOINT ANGLE RATES (IN DEG/SEC) ARE :');
  FOR K_I := 1 TO N DO
    BEGIN
      WITH R_FILE DO
        WRITELN (OUTPUT,'THETA_DOT['',K_I:1,']= ',Q_DOT[K_I]:14:8);
      END;
    WRITELN(OUTPUT);
  END; {WRITE_ANGLE_RATE}

PROCEDURE WRITEOUT;
VAR
  I_W,J_W : INTEGER;

BEGIN { WRITEOUT }
  WITH R_FILE DO
    BEGIN
      WRITELN ( OUTPUT, 'TIME= ',TIME:14:8);
      WRITE ( OUTPUT, 'QP= ');
      FOR I_W := 1 TO N DO
        WRITE ( OUTPUT, X4_P[I_W]:12:6,' ');
      WRITELN;
      WRITE ( OUTPUT, 'QC= ');
      FOR I_W := 1 TO N DO
        WRITE ( OUTPUT, X4_C[I_W]:12:6,' ');
      WRITELN;
    END;
  END;

```

```

( WRITE OUT X, X_D )
  WRITELN (OUTPUT, '*****  X  *****' );
  FOR I_W := 1 TO 3 DO
    BEGIN
      FOR J_W := 1 TO 4 DO
        WRITE (OUTPUT, X[I_W, J_W]:12:6);
        WRITELN (OUTPUT);
      END;
    WRITELN (OUTPUT, '*****  X_D  *****' );
    FOR I_W := 1 TO 3 DO
      BEGIN
        FOR J_W := 1 TO 4 DO
          WRITE (OUTPUT, X_D[I_W, J_W]:12:6);
          WRITELN (OUTPUT);
        END;
      WRITELN (OUTPUT, '*****  X_N =  *****' );
      FOR I_W := 1 TO N DO
        BEGIN
          FOR J_W := 1 TO 4 DO
            WRITE (OUTPUT, X_N[I_W, J_W]:12:6);
            WRITELN (OUTPUT);
          END;
        WRITELN (OUTPUT, '*****  X_N_DOT=  *****' );
        FOR I_W := 1 TO N DO
          BEGIN
            FOR J_W := 1 TO 4 DO
              WRITE (OUTPUT, X_N_DOT[I_W, J_W]:12:6);
              WRITELN (OUTPUT);
            END;
          END; {R_FILE}
        END; { WRITEOUT }
      END;
    END;
  END;

PROCEDURE WRITE_XN;
VAR
  I_W, J_W : INTEGER;

BEGIN { WRITE_XN }
  WITH R_FILE DO
    BEGIN
      WRITELN (OUTPUT, '*****  X_N =  *****' );
      FOR I_W := 1 TO N DO
        BEGIN
          FOR J_W := 1 TO 4 DO
            WRITE (OUTPUT, X_N[I_W, J_W]:12:6);
            WRITELN (OUTPUT);
          END;
        WRITELN (OUTPUT, '*****  X_N_DOT=  *****' );
      END;
    END;
  END;

```



```

    FOR I_W := 1 TO N DO
      BEGIN
        FOR J_W := 1 TO 4 DO
          WRITE(OUTPUT,X_N_DOT[I_W,J_W]:12:6);
          WRITELN(OUTPUT);
        END;
      END; (R_FILE)
    END; { WRITE_XN }

PROCEDURE CAL_VEL(CTIME:REAL);
  { COMPUTE THE HAND VELOCITY VECTOR ON TIME }
  BEGIN { CAL_HAND }
  END; { CAL_HAND }

{*****}
PROCEDURE INV_KIN;
  LABEL 1,10,20,100;
  CONST
    { EPS_INV = 0.00001; }
    EPS_INV = 0.00001;
  VAR
    I_IN,J_IN,NO : INTEGER;

  BEGIN { INV_KIN }
    WITH R_FILE DO
      BEGIN { R_FILE }
        {WRITELN(OUTPUT,'***** START OF THE INV_KIN PROCEDURE *****');}
        {write_x; write_xd;}
        SUB_ERR(Delta1);
        {WRITELN(OUTPUT,'Delta1= ',Delta1);}
        PRE_NO := PRE_NO + 1;
        {WRITELN(OUTPUT,'BEFORE SUB_PRE **** CYCLE_CNTR= ', CYCLE_CNTR);}
        SUB_PRE(X4_P);
        {WRITELN(OUTPUT,'AFTER SUB_PRE **** CYCLE_CNTR= ', CYCLE_CNTR);}
        FOR I_IN := 1 TO N DO
          ANGLE_RAD[I_IN+1] := X4_P[I_IN] * PI / 180.0;
          { SINCE THE SCALE - PI/180 CAN BE COMPUTED WHEN SIN/COS IS
            COMPUTED, NO MORE CYCLES ARE NEEDED. }
          {WRITELN(OUTPUT,'BEFORE KIN_JAC **** CYCLE_CNTR= ', CYCLE_CNTR);}
          KIN_JAC;
          {WRITELN(OUTPUT,'AFTER KIN_JAC **** CYCLE_CNTR= ', CYCLE_CNTR);}
          WRITE_JAC;
          WRITE_X;
        }
        {write_x; write_xd;}
        SUB_ERR(Delta2);
        {WRITELN(OUTPUT,'Delta2= ',Delta2);}
      END;
    END;
  END;

```

```

        CYCLE_CNTR := CYCLE_CNTR + 4;
        ADD_CNTR := ADD_CNTR + 1;
    IF ( DELTA2 <= DELTA1 + 0.01) THEN
        BEGIN ( DELTA2 )
            CYCLE_CNTR := CYCLE_CNTR + 4;
            ADD_CNTR := ADD_CNTR + 1;
            IF ( DELTA2 >= EPS_INV ) THEN
                BEGIN ( EPS )
                    COR_LP_NO := COR_LP_NO + 1;
                    NO := 1;
                    FLAG := CORRECT;
                    GOTO 1;
                END (EPS )
            ELSE
                BEGIN
                    (WRITELN(OUTPUT, 'BEFORE PSEUDO **** CYCLE_CNTR= ', CYCLE_CNTR);)
                    PSEUDO_INV;
                    (WRITELN(OUTPUT, 'AFTER PSEUDO **** CYCLE_CNTR= ', CYCLE_CNTR);)
                    FLAG := PREDICT;
                    NO_COR_NO := NO_COR_NO + 1;
                    GOTO 20;
                END;
            END ( DELTA2 )
        ELSE
            begin
                (WRITELN(OUTPUT, ' TEST IN ITE_NO '));)
                ITE_NO := ITE_NO +1;
                GOTO 10;
            END;
1:    PSEUDO_INV;
    ( WRITELN(OUTPUT, 'NO = ', NO);)
    (WRITELN(OUTPUT, 'BEFORE SUB_COR **** CYCLE_CNTR= ', CYCLE_CNTR);)
    SUB_COR(X4_C);
    ( WRITELN(OUTPUT, 'corrected ANGLE : ');
    WRITE_VEC(X4_C,N);
    ) (WRITELN(OUTPUT, 'AFTER SUB_COR **** CYCLE_CNTR= ', CYCLE_CNTR);)
    COR_NO := COR_NO + 1;
    FOR I_IN := 1 TO N DO
        ANGLE_RAD[I_IN+1] := X4_C[I_IN] * PI / 180.0;
    (WRITELN(OUTPUT, 'BEFORE KIN_JAC **** CYCLE_CNTR= ', CYCLE_CNTR);)
    KIN_JAC;
    (WRITELN(OUTPUT, 'AFTER KIN_JAC **** CYCLE_CNTR= ', CYCLE_CNTR);)
    SUB_ERR(DELTA3);
    ( WRITELN(OUTPUT, 'DELTA3= ', DELTA3);
    WRITE_ANGLE;
    CYCLE_CNTR := CYCLE_CNTR + 4;
    ADD_CNTR := ADD_CNTR + 1;

```

```

IF ( DELTA3 > DELTA2 + 0.1 ) THEN
  GOTO 10
ELSE
  BEGIN
    CYCLE_CNTR := CYCLE_CNTR + 4;
    ADD_CNTR := ADD_CNTR + 1;
    IF ( DELTA3 < 10.0 ) THEN GOTO 20
    ELSE
      BEGIN
        NO := NO + 1;
        CYCLE_CNTR := CYCLE_CNTR + 4;
        ADD_CNTR := ADD_CNTR + 1;
        IF ( NO < 5 ) THEN GOTO 1
        ELSE GOTO 10;
      END;
    END;
10: BEGIN
  DELTA_T := DELTA_T * 0.5;
  WRITELN(OUTPUT, '***** DELTA_T HAS BEEN HALFED ***** ');
  WRITELN(OUTPUT, 'NO = ', NO);
  WRITELN(OUTPUT, 'TIME IS: ', TIME);
  WRITELN(OUTPUT, 'DELTA1= ', DELTA1);
  WRITELN(OUTPUT, 'DELTA2= ', DELTA2);
  WRITELN(OUTPUT, 'DELTA3= ', DELTA3);
  CYCLE_CNTR := CYCLE_CNTR + 4;
  MUL_CNTR := MUL_CNTR + 1;
  GOTO 100;
END;

20:
  {WRITEOUT;}
  IF ( FLAG = PREDICT ) THEN
    BEGIN
      {WRITELN(OUTPUT, 'BEFORE SUB_ADJ **** CYCLE_CNTR= ', CYCLE_CNTR);}
      SUB_ADJ(X4_P);
      {WRITELN(OUTPUT, 'AFTER SUB_ADJ **** CYCLE_CNTR= ', CYCLE_CNTR);}
    END
  ELSE SUB_ADJ(X4_C);
100: {END}
  END; { R_FILE }
  END; { INV_KIN }

{*****}
{ MAIN PROGRAM BEGINS }
  BEGIN { MAIN }
  WITH R_FILE DO
  BEGIN { R_FILE }
  CYCLE_CNTR := 0;

```

```

TIME := 0.0;
JAC_NO := 0; COR_LP_NO := 0; COR_NO := 0; ITE_NO := 0;
NO_COR_NO := 0; CYCLE_CNTR := 0; AMD_CNTR := 0;
{ Initialize SIMULATION parameters }
    INITIQL;TEND := 1.5;
    (TEST){ DELTA_T := 1.0;}
    MAX_TIM := DELTA_T;
    MAX_TIM := 0.100;
    TASK5(X_D,X_DOT,TIME);
    WRITELN(OUTPUT,'TIME IS: ',TIME);
    WRITELN(OUTPUT,'DELTA_T IS: ',DELTA_T);
    writeout;
    TIME := TIME + DELTA_T;
    WRITELN(OUTPUT,'TOTAL INITIALAZATION *** CYCLE_CNTR= ', CYCLE_CNT
    WHILE ((abs( TIME - TEND ) > 0.00001) AND ( SINGULARITY = FALSE )
    BEGIN (WHILE)
        IF ( TIME > TEND ) THEN
            BEGIN
                DELTA_T := DELTA_T - (TIME - TEND);
                TIME := TEND;
            END;
            TASK5(X_D,X_DOT,TIME);
            ( CAL_VEL(TIME);){ IN TASK5 )
            (WRITELN(OUTPUT,' BEFORE INV_KIN ');)
            INV_KIN;
            (WRITEOUT;)
        IF ( (ABS(MAX_TIM)-0.0001) < TIME)
            AND (TIME < (ABS(MAX_TIM)+ 0.0001)) THEN
            BEGIN
                ( MAX_TIM := MAX_TIM + 0.73;)
                ( WRITELN(OUTPUT,'TIME = ', TIME:14:6);)
                MAX_TIM := MAX_TIM + 0.1;
                WRITELN(OUTPUT,'DELTA1= ',DELTA1);
                WRITELN(OUTPUT,'DELTA2= ',DELTA2);
                WRITELN(OUTPUT,'DELTA3= ',DELTA3);
                WRITEOUT;
            END;
            ( I/O TIME FOR TRANSFER X_D, VEL_HAND, AND THETAS )
            CYCLE_CNTR := CYCLE_CNTR + 12 + 6 + N;
            ( IF ( DELTA_T < 0.0072 ) THEN)
            IF ( DELTA_T < 0.0072 ) and (abs(time - tend) > 0.00001)THEN
                begin
                    writeln(output,'DELTA_T HAS BEEN HALFED. ');
                    SINGULARITY := TRUE;
                END ELSE
                    TIME := TIME + DELTA_T;
            END; (WHILE)

```

```

IF ( SINGULARITY = TRUE ) THEN
  { Singularity process }
  begin
    WRITELN ( OUTPUT, ' THE SINGULARITY POINT IS HERE: ');
    WRITEOUT;
  end;

  WRITELN(OUTPUT,'DELTA1= ',DELTA1);
  WRITELN(OUTPUT,'DELTA2= ',DELTA2);
  WRITELN(OUTPUT,'DELTA3= ',DELTA3);
  WRITEOUT;

  {WRITELN (OUTPUT,'MAXIMUM ERROR      = ',MAX_ERR:14:8);
  WRITELN (OUTPUT,'MAXIMUM ERROR AT = ',MAX_TIM:14:8,' SECONDS');
  WRITELN (OUTPUT,'ETA              = ',ETA:5);
  WRITELN (OUTPUT,'CONVERGENCE       = ',EPSE:14:8);}
  WRITELN (OUTPUT,'FINAL DELTA TIME = ',DELTA_T:14:8);
    WRITELN(OUTPUT,'DELTA1= ',DELTA1);
    WRITELN(OUTPUT,'DELTA2= ',DELTA2);
    WRITELN(OUTPUT,'DELTA3= ',DELTA3);
    WRITELN(OUTPUT,'***** CYCLE_CNTR= ', CYCLE_CNTR);
    WRITELN(OUTPUT,'***** AMD_CNTR= ', AMD_CNTR);
    WRITELN(OUTPUT,'***** MUL_CNTR= ', MUL_CNTR);
    WRITELN(OUTPUT,'***** ADD_CNTR= ', ADD_CNTR);
  WRITELN (OUTPUT,'ITERATION_NUMBER = ',ITE_NO:5);
  WRITELN (OUTPUT,'PREDICTION_NUMBER= ',PRE_NO:5);
  WRITELN (OUTPUT,'no_cor_LOOP_NUMBER = ',no_COR_NO:5);
  WRITELN (OUTPUT,'COR_LOOP_NUMBER   = ',COR_LP_NO:5);
  WRITELN (OUTPUT,'CORRECTION_NUMBER= ',COR_NO:5);
  {WRITELN (OUTPUT,'JACOBN_NUMBER    = ',JAC_NO:5);}
  END; { R_FILE }
END. { MAIN }

```